

5.1.1 P-CCPCH RSCP

Definition	Received Signal Code Power, the received power on P-CCPCH of own or neighbour cell after despreading . The reference point for the RSCP is the antenna connector at the UE.
Applicable for	idle mode, connected mode (intra-frequency & inter-frequency)
Range/mapping	<p>P-CCPCH RSCP is given with a resolution of 1 dBm with the range [-115, ..., -25] dBm. P-CCPCH RSCP shall be reported in the unit P-CCPCH_RSCP_LEV where:</p> <p>P-CCPCH_RSCP_LEV_00: P-CCPCH_RSCP < -115dBm P-CCPCH_RSCP_LEV_01: -115dBm ≤ P-CCPCH_RSCP < -114dBm P-CCPCH_RSCP_LEV_02: -114dBm ≤ P-CCPCH_RSCP < -113dBm ... P-CCPCH_RSCP_LEV_89: -27dBm ≤ P-CCPCH_RSCP < -26dBm P-CCPCH_RSCP_LEV_90: -26dBm ≤ P-CCPCH_RSCP < -25dBm P-CCPCH_RSCP_LEV_91: -25dBm ≤ P-CCPCH_RSCP</p>

5.1.2 CPICH RSCP

Definition	Received Signal Code Power, the received power on the CPICH code after despreading . The reference point for the RSCP is the antenna connector at the UE.
Applicable for	idle mode, connected mode (inter-frequency)
Range/mapping	<p>CPICH RSCP is given with a resolution of 1 dBm with the range [-115, ..., -25] dBm. CPICH RSCP shall be reported in the unit CPICH_RSCP_LEV where:</p> <p>CPICH_RSCP_LEV_00: CPICH_RSCP < -115dBm CPICH_RSCP_LEV_01: -115dBm ≤ CPICH_RSCP < -114dBm CPICH_RSCP_LEV_02: -114dBm ≤ CPICH_RSCP < -113dBm ... CPICH_RSCP_LEV_89: -27dBm ≤ CPICH_RSCP < -26dBm CPICH_RSCP_LEV_90: -26dBm ≤ CPICH_RSCP < -25dBm CPICH_RSCP_LEV_91: -25dBm ≤ CPICH_RSCP</p>

5.1.3 RSCP

Definition	Received Signal Code Power, the received power on the code of a specified DPCH or PDSCH after despreading . The reference point for the RSCP is the antenna connector at the UE.
Applicable for	connected mode (intra-frequency)

Range/mapping	<p>RSCP is given with a resolution of 1 dBm with the range [-115, ..., -25] dBm. RSCP shall be reported in the unit UE_RSCP_LEV where:</p> <p>$UE_RSCP_LEV_00$: RSCP < -115dBm $UE_RSCP_LEV_01$: -115dBm ≤ RSCP < -114dBm $UE_RSCP_LEV_02$: -114dBm ≤ RSCP < -113dBm ... $UE_RSCP_LEV_89$: -27dBm ≤ RSCP < -26dBm $UE_RSCP_LEV_90$: -26dBm ≤ RSCP < -25dBm $UE_RSCP_LEV_91$: -25dBm ≤ RSCP</p>
----------------------	--

5.1.4 Timeslot ISCP

Definition	Interference Signal Code Power, the interference on the received signal in a specified timeslot after despreading. Only the non-orthogonal part of the interference shall be included in the measurement. The reference point for the ISCP is the antenna connector at the UE.
Applicable for	connected mode (intra-frequency)
Range/mapping	<p>Timeslot ISCP is given with a resolution of 1 dBm with the range [-115, ..., -25] dBm. Timeslot ISCP shall be reported in the unit $UE_TS_ISCP_LEV$ where:</p> <p>$UE_TS_ISCP_LEV_00$: Timeslot_ISCP < -115dBm $UE_TS_ISCP_LEV_01$: -115dBm ≤ Timeslot_ISCP < -114dBm $UE_TS_ISCP_LEV_02$: -114dBm ≤ Timeslot_ISCP < -113dBm ... $UE_TS_ISCP_LEV_89$: -27dBm ≤ Timeslot_ISCP < -26dBm $UE_TS_ISCP_LEV_90$: -26dBm ≤ Timeslot_ISCP < -25dBm $UE_TS_ISCP_LEV_91$: -25dBm ≤ Timeslot_ISCP</p>

5.1.5 UTRA carrier RSSI

Definition	Received Signal Strength Indicator, the wide-band received power within the relevant channel bandwidth in a specified timeslot. Measurement shall be performed on a UTRAN DL carrier. The reference point for the RSSI is the antenna connector at the UE.
Applicable for	idle mode, connected mode (intra- & inter-frequency)
Range/mapping	<p>UTRA carrier RSSI is given with a resolution of 1 dBm with the range [-94, ..., -32] dBm. UTRA carrier RSSI shall be reported in the unit $UTRA_carrier_RSSI_LEV$ where:</p> <p>$UTRA_carrier_RSSI_LEV_00$: UTRA_carrier_RSSI < -94dBm $UTRA_carrier_RSSI_LEV_01$: -94dBm ≤ UTRA_carrier_RSSI < -93dBm $UTRA_carrier_RSSI_LEV_02$: -93dBm ≤ UTRA_carrier_RSSI < -92dBm ... $UTRA_carrier_RSSI_LEV_61$: -34dBm ≤ UTRA_carrier_RSSI < -33dBm $UTRA_carrier_RSSI_LEV_62$: -33dBm ≤ UTRA_carrier_RSSI < -32dBm $UTRA_carrier_RSSI_LEV_63$: -32dBm ≤ UTRA_carrier_RSSI</p>

5.1.6 GSM carrier RSSI

Definition	Received Signal Strength Indicator, the wide-band received power within the relevant channel bandwidth in a specified timeslot. Measurement shall be performed on a GSM BCCH carrier. The reference point for the RSSI is the antenna connector at the UE.
Applicable for	idle mode, connected mode (inter-frequency)
Range/mapping	According to the definition of RXLEV in GSM 05.08.

5.1.7 SIR

Definition	<p>Signal to Interference Ratio, defined as: $(RSCP/ISCP) \times SF$. The reference point for the SIR is the antenna connector of the UE.</p> <p>where: <u>RSCP = Received Signal Code Power, the received power on the code of a specified DPCH or PDSCH.</u> <u>ISCP = Interference Signal Code Power, the interference on the received signal. Only the non-orthogonal part of the interference is included in the measurement.</u> <u>SF = The spreading factor used.</u></p> <p>Signal to Interference Ratio, defined as the RSCP of a DPCH or PDSCH divided by ISCP of the same timeslot. The reference point for the SIR is the antenna connector of the UE.</p>
Applicable for	connected mode (intra-frequency)
Range/mapping	<p>SIR is given with a resolution of 0.5 dB with the range [-11, ..., 20] dB.</p> <p>SIR shall be reported in the unit SIR where:</p> <p>SIR_00: SIR < -11.0dB SIR_01: -11.0dB ≤ SIR < -10.5dB SIR_02: -10.5dB ≤ SIR < -10.0dB SIR_61: 19.0dB ≤ SIR < 19.5dB SIR_62: 19.5dB ≤ SIR < 20.0dB SIR_63: 20.0dB ≤ SIR</p>

5.1.8 CPICH Ec/No

Definition	The received energy per chip divided by the power density in the band. The Ec/No is identical to RSCP/RSSI. The reference point for Ec/No is the antenna connector at the UE.
Applicable for	idle mode, connected mode (inter-frequency)
Range/mapping	<p>CPICH Ec/No is given with a resolution of 1 dB with the range [-24, ..., 0] dB.</p> <p>CPICH Ec/No shall be reported in the unit CPICH_Ec/No where:</p> <p>CPICH_Ec/No_00: CPICH_Ec/No < -24dB CPICH_Ec/No_01: -24dB ≤ CPICH_Ec/No < -23dB CPICH_Ec/No_02: -23dB ≤ CPICH_Ec/No < -22dB ... CPICH_Ec/No_23: -2dB ≤ CPICH_Ec/No < -1dB CPICH_Ec/No_24: -1dB ≤ CPICH_Ec/No < 0dB CPICH_Ec/No_25: 0dB ≤ CPICH_Ec/No</p>

Range/mapping	<p>UE transmitted power is given with a resolution of 1dBm with the range [-50, ..., 33] dBm. UE transmitted power shall be reported in the unit UE_TX_POWER, where:</p> <p>UE_TX_POWER_000 to UE_TX_POWER_020: reserved</p> <p>UE_TX_POWER_021: -50dBm ≤ UE_transmitted_power < -49dBm</p> <p>UE_TX_POWER_022: -49dBm ≤ UE_transmitted_power < -48dBm</p> <p>UE_TX_POWER_023: -48dBm ≤ UE_transmitted_power < -47dBm</p> <p>...</p> <p>UE_TX_POWER_102: 31dBm ≤ UE_transmitted_power < 32dBm</p> <p>UE_TX_POWER_103: 32dBm ≤ UE_transmitted_power < 33dBm</p> <p>UE_TX_POWER_104: 33dBm ≤ UE_transmitted_power < 34dBm</p>
----------------------	---

5.1.12 SFN-SFN observed time difference

Definition	<p>-</p> <p>SFN-SFN observed time difference is the time difference of the reception times of frames from two cells (serving and target) measured in the UE and expressed in chips. It is distinguished in two types: Type 2 applies if the serving and the target cell have the same frame timing and SFN numbering. Type 1 applies in all other cases.</p> <p>Type 1: SFN-SFN observed time difference = $OFF \times 38400 + T_m$ in chips, where: $T_m = T_{RxSFNk} - T_{RxSFNi}$, given in chip units with the range [0, 1, ..., 38399] chips T_{RxSFNi}: time of start of the received frame SFN_i of the serving TDD cell i. T_{RxSFNk}: time of start of the received frame SFN_k of the target UTRA cell k <u>received most recent in time before</u> the time <u>instant</u> T_{RxSFNi} in the UE. If <u>this next</u> frame SFN_k of the target UTRA cell is received <u>exactly</u> at T_{RxSFNi} then $T_{RxSFNk} = T_{RxSFNi}$ (which leads to $T_m = 0$). $OFF = (SFN_{ik} - SFN_{ki}) \bmod 256$, given in number of frames with the range [0, 1, ..., 255] frames SFN_i <u>is the</u> <u>system</u> frame number for downlink frame from serving TDD cell i in the UE at the <u>time</u> T_{RxSFNi}. SFN_k <u>is the</u> <u>system</u> frame number for downlink frame from target UTRA cell k received in the <u>UE</u> at the time T_{RxSFNk} (for FDD: the P-CCPCH frame)</p> <p>Type 2: SFN-SFN observed time difference = $T_{RxTSk} - T_{RxTSi}$, in chips, where T_{RxTSi}: time of start of a timeslot received of the serving TDD cell i. T_{RxTSk}: time of start of a timeslot received from the target UTRA cell k that is closest in time to the start of the timeslot of the serving TDD cell i.</p>
Applicable for	idle mode, connected mode (intra-frequency)
Range/mapping	<p>Type 1: SFN-SFN observed time difference is given with a resolution of 1 chip with the range [0; 9830400] chips (24 bits). SFN-SFN observed time difference shall be reported in the unit T1_SFN-SFN_TIME, where T1_SFN-SFN_TIME_N: $N * 1 \text{ chip} \leq \text{SFN-SFN observed time difference} < (N+1) * 1 \text{ chip}$ With N= 0, 1, 2, ..., 9830399</p> <p>Type 2: SFN-SFN observed time difference is given with a resolution of 0.25 chip with the range (-1280; 1280] chips (14 bits). SFN-SFN observed time difference shall be reported in the unit T2_SFN-SFN_TIME, where T2_SFN-SFN_TIME_N: $N * 0.25 \text{ chip} - 1280 \text{ chips} < \text{SFN-SFN observed time difference} \leq (N+1) * 0.25 \text{ chip} - 1280 \text{ chips}$ With N= 0, 1, 2, ..., 10239</p>

5.2.2 Timeslot ISCP

Definition	Interference Signal Code Power, the interference on the received signal in a specified timeslot <u>after despreading</u> . Only the non-orthogonal part of the interference <u>shall be</u> included in the measurement. The reference point for the ISCP shall be the antenna connector.
Range/mapping	Timeslot ISCP is given with a resolution of 0.5 dBm with the range [-120, ..., -80] dBm. Timeslot ISCP shall be reported in the unit <u>UTRAN_TS_ISCP_LEV</u> where: UTRAN_TS_ISCP_LEV_00: Timeslot_ISCP < -120.0dBm UTRAN_TS_ISCP_LEV_01: -120.0dBm ≤ Timeslot_ISCP < -119.5dBm UTRAN_TS_ISCP_LEV_02: -119.5dBm ≤ Timeslot_ISCP < -119.0dBm ... UTRAN_TS_ISCP_LEV_79: -81.0dBm ≤ Timeslot_ISCP < -80.5dBm UTRAN_TS_ISCP_LEV_80: -80.5dBm ≤ Timeslot_ISCP < -80.0dBm UTRAN_TS_ISCP_LEV_81: -80.0dBm ≤ Timeslot_ISCP

5.2.3 RSSI

Definition	Received Signal Strength Indicator, the wide-band received power within the UTRAN UL <u>carrier</u> channel bandwidth in a specified timeslot. The reference point for the RSSI shall be the antenna connector.
Range/mapping	RSSI is given with a resolution of 0.5dBm with the range [-105, ..., -74] dBm. RSSI shall be reported in the unit <u>RSSI_LEV</u> , where: RSSI_LEV_00: RSSI < -105.0dBm RSSI_LEV_01: -105.0dBm ≤ RSSI < -104.5dBm RSSI_LEV_02: -104.5dBm ≤ RSSI < -104.0dBm ... RSSI_LEV_61: -75.0dBm ≤ RSSI < -74.5dBm RSSI_LEV_62: -74.5dBm ≤ RSSI < -74.0dBm RSSI_LEV_63: -74.0dBm ≤ RSSI

5.2.4 SIR

Definition	Signal to Interference Ratio, defined as: $(RSCP/ISCP) \times SF$. The reference point for the SIR is <u>the antenna connector of the UE</u> . <u>where:</u> <u>RSCP = Received Signal Code Power, the received power on the code of a specified DPCH, PRACH or PUSCH.</u> <u>ISCP = Interference Signal Code Power, the interference on the received signal. Only the non-orthogonal part of the interference is included in the measurement.</u> <u>SF = The spreading factor used.</u> <u>Signal to Interference Ratio, defined as the RSCP of the DPCH or PUSCH divided by ISCP of the same timeslot. The reference point for the SIR shall be the antenna connector.</u>
-------------------	---

