

Fail: Error found in test case during verification
 Pass: Test case is OK
 N/A: Test case is not tested or no result available
 Green: Test cases that are ready to be verified
 Red: Test cases that are supplied for visual inspection and comment only

Test cases with problems - v140

produced on: 07/11/2002 17:50:05
 page 1 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
020028									
	tc_8_1_1_4	RRC / Paging for notification of BCCH modification in idle mode	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	tcv_MIB.mib_ValueTag is not incremented before step3 in the testcase (it should be done like in tc_8_1_1_5 or tc_8_1_1_6)	Accepted - V150 - The test case variable tcv_MIB.mib_valueTag is already incremented in the step +ts_ChangeMIB_ValueTag called (called in ts_SendSIB5). So there is no need to increment it again the test case behaviour. The test cases tc_8_1_1_5 and tc_8_1_1_6 will be corrected.	17/07/2002
	tc_8_3_3_1	RRC / UTRAN Mobility Information: Success	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	ts_CMAC_NewU_RNTI_Reconf should be started after UTRAN MOBILITY INFORMATION CONFIRM was received. Otherwise it is possible that the SRBs are suspended, and the UTRAN MOBILITY INFORMATION CONFIRM Message can not be sent on RB2	Rejected - V150 - To send the UTRAN MOBILITY INFORMATION CONFIRM message the UE shall use the new C-RNTI value in the MAC header, so SS shall be reconfigured before the reception of this message. To facilitate the reception/buffering of the message during the reconfiguration steps, ts_CMAC_NewU_RNTI_Reconf will be updated to reconfigure UL before DL. (SRBs are not suspended any more during reconfiguration)	17/07/2002

GCF priority:
 Category: D
 Package: 1

GCF priority:
 Category: D
 Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:05

page 2 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_8_3_3_1	RRC / UTRAN Mobility Information: Success	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	Line 17 in tc: parameter for the timer in ts_RRC_ReceiveCellUpdate should be 330000 instead of 33000	Accepted - V150	17/07/2002
GCF priority:									
Category: D									
Package: 1									
	tc_8_3_3_1	RRC / UTRAN Mobility Information: Success	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	t_Guard should be started with parameter (e.g. 800), because step5 and step8 takes 330s each	Accepted - V150 - The guard timer value will be updated to 2500 (30 min/line 15 + 5 min/line 17)	17/07/2002
GCF priority:									
Category: D									
Package: 1									
	tc_8_3_3_1	RRC / UTRAN Mobility Information: Success	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	line 15 in tc: timer duration is set to 33min (1980000ms = tsc_T305_Max), but it should be 5,5min (see comment in this line). Therefore SIB1 should contain the value m5 for t_305 as well;	Rejected - V150 - In line 15, the timer value shall be 30 min in accordance with the value provided in 34.108 clause 6.1 (30 min), the comment shall be updated. If it is required to change SIB1 then a CR to the prose should be proposed.	17/07/2002
GCF priority:									
Category: D									
Package: 1									

Test cases with problems - v140

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_9_2_3	Authentication rejected by the UE (MAC code failure)	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	The last 2 IEs should be 'ldType' and 'spare4' in this order according to TS 24.008 V5.3.0 ch. 9.2.10, and not vice versa, as in the ATS.	Rejected - According to TS24.008 clause 9 : "In a (maximal) sequence of consecutive information elements with half octet length, the first information element with half octet length occupies bits 1 to 4 of octet N, the second bits 5 to 8 of octet N, the third bits 1 to 4 of octet N+1 etc. - Object name: c_IdReq	16/07/2002

GCF priority:
 Category: B
 Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:06

page 4 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
020029									
	tc_7_2_2_2	UM RLC / Segmentation and reassembly / Selection of 7 or 15 bit Length Indicators	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	<p>This is a general comment on (Probably all) RLC UM and AM test cases.If we refer to 34.123-1 Clause 7.2.2.1, the RB configuration described in section 6.11.1 and 6.11.2 shall be used.In these sections of 34.108, the PS domain services are used (interactive or background).But in TTCN implementation, we can find: 1. The tcv for domain is being initialized for CS-Domain.2. The Paging is being done for Conversational call (i.e. CS Domain).3. In the Radio Bearer Setup, the Domain of the RAB is being given as CS Domain.We feel this is wrong, as the UE will not be in a position to establish a UM or AM RAB for the CS domain Conversational call.</p>	Accepted - Prose problem. Waiting for a solution from T1S	22/07/2002
	tc_8_1_2_4	RRC / RRC Connection Establishment: Reject ("wait time" is not equal to 0)	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	<p>Between rows 24 and 25, the transmission of RRC Connection Setup is missing</p>	Accepted - v150	26/07/2002

GCF priority:
 Category: C
 Package: 1

GCF priority:
 Category: P
 Package: 3

Test cases with problems - v140

produced on: 07/11/2002 17:50:06

page 5 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_8_2_3_6	RRC / Radio Bearer Release for transition from CELL_DCH to CELL_DCH: Failure (Invalid message reception and invalid configuration)	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	there should be RADIO BEARER RELEASE FAILURE Message with cause set to INVALID CONFIGURATION, at step 4 but in the ETSI test case it is RADIO BEARER SETUP FAILURE Message with cause set to INVALID CONFIGURATION	Accepted - v150	25/07/2002
	tc_9_4_2_4 Proc 2	Location updating / rejected / roaming not allowed in this location area / Procedure 2	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	The test case behaviour do not follow the prose spec, The discrepancy is starting at step 9	Accepted - v150 - No discrepancy was found, however, in line 14: tsc_CellB must be used as parameter instead of tsc_CellA.	22/07/2002
	tc_9_4_2_4 Proc 2	Location updating / rejected / roaming not allowed in this location area / Procedure 2	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	in Row 16 and 17 corresponding to step 18 in the prose. Prose says the mobile is paged with TMSI, and Mobile shall not respond to it. But in TTCN it is being paged by IMSI, and as per 24.008 sec: 4.2.2.3 , and 23.122 Table 2 in Clause 5, the UE can optionally respond when paged with IMSI. Hence the paging cannot be with IMSI.	Accepted - v150 - In rows 16 and 17 of the code IMSI is to be replaced by TMSI, twice on each row	29/07/2002

GCF priority:

Category:

Package:

GCF priority:

Category: J

Package: 2

GCF priority:

Category: J

Package: 2

Test cases with problems - v140

produced on: 07/11/2002 17:50:06

page 6 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
020030									
	tc_8_2_2_4	RRC / Radio Bearer Reconfiguration from CELL_DCH to CELL_DCH: Failure (Physical channel failure and reversion failure)	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	Cell update confirm is send on DCCH but the RB Id set to tsc_RB0, it should be tsc_RB1	Accepted - v150	06/08/2002
GCF priority:									
Category: P									
Package: 3									
	tc_8_2_3_4	RRC / Radio Bearer Release for transition from CELL_DCH to CELL_DCH: Failure (Physical channel failure and reversion failure)	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	Cell update confirm is send on DCCH but the RB Id set to tsc_RB0, it should be tsc_RB1	Accepted - v150	06/08/2002
GCF priority:									
Category: P									
Package: 3									

Test cases with problems - v140

produced on: 07/11/2002 17:50:06

page 7 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date	
020032										
	tc_12_2_1_1	PS attach / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	Line no: 27, in "It_Steps_3To7", the constraint for Attach Request has old_RAI as OMIT. However, old_RAI is a mandatory field and cannot be omitted. Reference 24008 sec: 9.4.1	Accepted - v150 - Since the old_RAI information element in the ATTACH REQUEST message is mandatory, we will replace the OMIT by '?' in the appropriate receiving constraints	22/08/2002	GCF priority: Category: B Package: 1
	tc_12_2_1_1	PS attach / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	"When the UE is a Class A Mobile, and when we are executing (either row 9 to 11 or row 13 to 15), then as the Network Mode is II, and Mobile Class A, then when we switch off and switch on, the UE will first do the MM Location update followed by a GMM attach, but not only GMM attach (some thinkg like what we have in the Idle update test step)? "	Accepted - v150	10/09/2002	GCF priority: Category: B Package: 1
	tc_12_2_1_1	PS attach / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	"In ""It_Steps_20To23"", the step to receive Attach_Complete should not be included. This is because, a new P-TMSI is not being allocated in the corresponding Attach_Accept message. Please refer to the SPEC: 24008.380 sec: 4.7.3.1.3. "	Accepted - V150	04/09/2002	GCF priority: Category: B Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:06

page 8 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_12_2_1_1	PS attach / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	The message type of Detach_Request in " cr_DetachReq " should be " 05" instead of "e8". Please refer to 24008.380 sec: 10.4 (Table 10.4) used in test step "ts_GMM_DetachOnSwitch Off" row 6)	Accepted - v150	29/08/2002
	tc_12_2_1_1	PS attach / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	In the constraint "c_MobileIdPTMSI", the iei of PTMSI should be 18 instead of 17. (used in row 30). Please refer to 24008.380 sec: 9.4.2 (Table 9.4.2) same for constraint c_MobileIdPTMSI_Def in row 39.	Accepted - v150	29/08/2002
	tc_12_2_1_1	PS attach / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	In the test step: "ts_GMM_DetachOnSwitch Off", line no:6 (Detach_Request constraint) , the PTMSI signature should be of the type TLV with 5 bytes . However, a TV constraint with 4 bytes has been used. This needs a modification to the definition 'DETACHREQUESTMO'. Please refer to 24008.380 sec: 9.4.5.2	Accepted - v150	29/08/2002

GCF priority:

Category: B

Package: 1

GCF priority:

Category: B

Package: 1

GCF priority:

Category: B

Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:06

page 9 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_12_2_1_2	PS attach / rejected / IMSI invalid / illegal UE	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	<p>"After rejection of the Attachment in CellA, and camp onto CellC, UE will perform both Location Update and Attach. This is because the MCC is 2 for cell C, OpMode for UE is Class A and update_status is Not Updated. (Since, the previous Attach was rejected). Hence, the test_step:</p> <p>""ts_RegistrationOnCS2_If OpModeA"" in line 21 should include steps to handle both Location Update and Attach, instead of just Location Update. Further, a separate trigger for Attach is not required (as it will be done in ts_RegistrationOnCS2_IfOpModeA).</p>	Accepted - v150	04/09/2002
	tc_12_7_1	General Identification	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	<p>In local tree ""It_Attach_Steps_3To5"", in constraint ""cr_AttachReq()"" expecting 'oldRAI' as OMIT. This is a general comment and has already been raised by us. As oldRAI is an Mandatory IE "</p>	Accepted - v150	05/09/2002

GCF priority:

Category: P

Package: 3

GCF priority:

Category: B

Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:06

page 10 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_12_7_1	General Identification	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	In 34.123-1, in expected sequence row [12] ""The UE is switched off or power is removed"". And in row[13], ""DETACH REQUEST"" message not sent if power is removed. ETSI scripts are coded for SWITCH OFF only.	Accepted - v150	05/09/2002
	tc_8_1_1_1	RRC / Paging for Connection in idle mode	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	in ts_IdleUpdatedSpecial, ts_GMM_IdleUpdatedSpecial, in attach accept, constraint c_MobileIdMSI, iei is given a wrong value	Accepted - v150	09/08/2002
	tc_8_1_1_6	RRC / Paging for notification of BCCH modification in connected mode (URA_PCH)	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	According to the prose, the paging type 1 in step 2 shall not include any paging record list ie	Accepted - v150	09/08/2002

GCF priority:

Category: B

Package: 1

GCF priority:

Category: D

Package: 1

GCF priority:

Category: D

Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:06

page 11 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
--------------------	---------------	-------	-------------	---------	---------------	--------------	---------	---------------------------	-----------

020033

tc_8_1_1_4	RRC / Paging for notification of BCCH modification in idle mode	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	the way tcv_BCCH_ModTime is calculated does not seem to give a SFN value, which is stated in 25.331 clause 10.3.8.1.	Accepted - v150	04/09/2002
------------	---	--	--------	---------------------	-----	--	-----------------	------------

GCF priority:

Category: D

Package: 1

020034

tc_7_2_3_21	AM RLC / Polling for status / Operation of Timer_Poll timer / Timer expiry	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	The Test Suite Constant "tsc_TTI " is declared with value "40" ms. It is described as: /* Transmission time interval in milliseconds for the transport channel supporting the RB used for RLC testing. This is used for calculations based on the TTI, for example 'Send (2 * T / TTI) RLC SDUs.' */ The TTI for the SRB used in the RLC tests is 40ms.However, the TTI used for the AM/UM RABs defined for RLC testing has the value 20ms. (see TS 34.108 section 6.11). tsc_TTI is used in calculations about the number of PDUs to transmit and in calculating timer tolerances.	Accepted - v150	04/09/2002
-------------	--	--	--------	------------------	-----	---	-----------------	------------

GCF priority:

Category: C

Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:07

page 12 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
020035									
	tc_7_2_2_tc_11	UM RLC / Segmentation / 15-bit Length Indicators / Invalid LI value	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	Error in the calculation of the data sizes in lines 7 (-1 -> -2) and 8 (-2 -> -4)	Accepted - v150	04/09/2002
GCF priority:									
Category:									
Package:									
	tc_7_2_3_3	AM RLC / Segmentation / 7-bit Length Indicators / Padding	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	The variables tcv_NumPDUsReceived and tcv_StatusReceived are not reseted in the middle of the test when counting restarts; shall be reset to 0 and FALSE	Accepted - v150	04/09/2002
GCF priority:									
Category:									
Package:									
	tc_7_2_3_4	AM RLC / Segmentation / 7-bit Length Indicators / LI = 0	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	In line 7 the PDU should be sent with tsc_P_Poll instead of tsc_P_NoPoll.	Accepted - v150	04/09/2002
GCF priority:									
Category: C									
Package: 1									

Test cases with problems - v140

produced on: 07/11/2002 17:50:07

page 13 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_7_2_3_7	AM RLC / Segmentation / 15-bit Length Indicators / Padding or Piggy-backed Status	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	Erroneous length of Status PDU sent (-5 -> -1)	Accepted - v150	04/09/2002
	tc_8_1_9	RRC / Signalling Connection Release Indication	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	line 31: incorrect construction, will always fail the test case because this line will be entered before the timeout happens.	Accepted - v150	03/09/2002

GCF priority:

Category:

Package:

GCF priority:

Category: D

Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:07

page 14 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
020036									
	tc_12_2_1_1	PS attach / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	As per sub-clause 9.4.2, 24.008 the IEI of "Allocated P-TMSI" should be 18. But, coded different value. This change is to be made in row[3] test step "It_Steps_11To16", constraint is "c_MobileIdPTMSI_Def".	Accepted - V150	09/09/2002
	tc_12_9_2	Service Request Initiated by Network Procedure	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	As per sub-clause 9.4.9, 24.008, the IEI value of "Authentication Parameter AUTN" should be 28 but, coded as 20. This problem is in the constraint "c_GMM_AuthAUTN".	Accepted - v150	09/09/2002

GCF priority:
Category: B
Package: 1

GCF priority:
Category: B
Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:07

page 15 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
020039									
	tc_7_1_1_8	DTCH or DCCH mapped to DCH / Invalid C/T Field	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	line 10 and line 14 : replace tsc_RB_DCCH_FACH_M AC by tsc_RB_DCCH_DCH_MA C	Accepted - v151	27/09/2002
GCF priority: Category: C Package: 1									
	tc_7_2_2_2	UM RLC / Segmentation and reassembly / Selection of 7 or 15 bit Length Indicators	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	The TFCS order shall be TFCS /0/2/1/3/ instead of /0/1/2/3/	Rejected - the order of TFCS is irrelevant	26/09/2002
GCF priority: Category: C Package: 1									
	tc_7_2_2_2	UM RLC / Segmentation and reassembly / Selection of 7 or 15 bit Length Indicators	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	The cellID to be used shall be tsc_CellDedicated instead of tsc_DefaultCellId.	Accepted - v151	26/09/2002
GCF priority: Category: C Package: 1									

Test cases with problems - v140

produced on: 07/11/2002 17:50:07

page 16 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_7_2_3_13	AM RLC / Control of Transmit Window	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	<p>After 8 PDUs send,SS continue to send data, but UE do not send data after UE send PDU8,because UE finish to send for Tx_windowsize. TTCN substitute data (sending SS) for tcv_AM_Data. But tcv_AM_Data is overwrite every data(PDU24). So SS sends status_ack,PDU24 is compare with PDU9,It is missmatch. tcv_AM_Data is only one,it is problem. (But other test case ""TX_window=1536"",many tcv_AM_Data is need It is not realistic.) It is need more consideration another method,Please</p>	Accepted - v151	08/10/2002
	tc_7_2_3_13	AM RLC / Control of Transmit Window	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	<p>1) SS sends PDU every 40ms,and wait to receive PDU (loopback from UE) but set the timer is t_TTI(40ms). I think it's too short for receiving data.</p>	Accepted - v151	08/10/2002

GCF priority:

Category: C

Package: 1

GCF priority:

Category: C

Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:07

page 17 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_7_2_3_15	AM RLC / Polling for status / Last PU in transmission queue	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	Line 32 replace (tcv_SUFI_Params.LB := INT_TO_BIT(0, tsc_AM_SN_Size),tcv_SU FI_Params.UB := INT_TO_BIT(3, tsc_AM_SN_Size)) by (tcv_SUFI_Params.LB := INT_TO_BIT(0, tsc_AM_SN_Size),tcv_SU FI_Params.UB := INT_TO_BIT(3, tsc_AM_SN_Size),tcv_SU FI_Params.ACK_presence := TRUE,tcv_SUFI_Params.WSN_presence := OMIT,tcv_SUFI_Params.M RW_presence := OMIT,tcv_SUFI_Params.N ack1 := OMIT,tcv_SUFI_Params.N ack2 := OMIT,tcv_SUFI_Params.N ack3 := OMIT)	Rejected - "the default values of the indicated fields is OMIT, therefore the proposed change is redundant. For tcv_SUFI_Params.ACK_presence := TRUE, I have to object because the test case does not make any assumption how the positive acknowledgements are transmitted. It is very likely this may be done using an ACK, but it is not mandated. Could be in another type of SUFI as well.	26/09/2002
	tc_7_2_3_2	AM RLC / Segmentation and reassembly / Selection of 7 or 15 bit Length Indicators	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	The field 'superFilds' shall be set to * instead of OMIT	Accepted - v150	26/09/2002

GCF priority:
Category: C
Package: 1

GCF priority:
Category: C
Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:07

page 18 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_7_2_3_2	AM RLC / Segmentation and reassembly / Selection of 7 or 15 bit Length Indicators	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	The cellID to be used shall be tsc_CellDedicated instead of tsc_DefaultCellId.	Accepted - v150	26/09/2002
									GCF priority: Category: C Package: 1
	tc_7_2_3_2	AM RLC / Segmentation and reassembly / Selection of 7 or 15 bit Length Indicators	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	In the field 'superFieldsRec' replace '?H by ?. In the field 'padding' replace '*H by *	Accepted - v151	26/09/2002
									GCF priority: Category: C Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:07

page 19 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_7_2_3_25	AM RLC / Receiver Status Triggers / Detection of missing PUs	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	Line 17 (tcv_SUFI_Params.LB := INT_TO_BIT(0, tsc_AM_SN_Size),tcv_SU FI_Params.Nack1 := INT_TO_BIT(7, tsc_AM_SN_Size),tcv_SU FI_Params.UB := INT_TO_BIT(8, tsc_AM_SN_Size) by (tcv_SUFI_Params.LB := INT_TO_BIT(0, tsc_AM_SN_Size),tcv_SU FI_Params.Nack1 := INT_TO_BIT(7, tsc_AM_SN_Size),tcv_SU FI_Params.UB := INT_TO_BIT(8, tsc_AM_SN_Size),tcv_SU FI_Params.ACK_presence := OMIT,tcv_SUFI_Params. WSN_presence := OMIT,tcv_SUFI_Params.M RW_presence := OMIT,tcv_SUFI_Params.N ack2 := OMIT,tcv_SUFI_Params.N ack3 := OMIT)	Rejected - the default values of the indicated fields is OMIT, therefore the	26/09/2002

GCF priority!

Category: C

Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:07

page 20 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_7_2_3_25	AM RLC / Receiver Status Triggers / Detection of missing PUs	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	Line 22 replace (tcv_SUFI_Params.LB := INT_TO_BIT(9, tsc_AM_SN_Size),tcv_SU FI_Params.Nack1 := INT_TO_BIT(7, tsc_AM_SN_Size), tcv_SUFI_Params.Nack2 := INT_TO_BIT(13, tsc_AM_SN_Size),tcv_SU FI_Params.Nack3 := INT_TO_BIT(14, tsc_AM_SN_Size), tcv_SUFI_Params.UB := INT_TO_BIT(15, tsc_AM_SN_Size)) by (tcv_SUFI_Params.LB := INT_TO_BIT(9, tsc_AM_SN_Size),tcv_SU FI_Params.Nack1 := INT_TO_BIT(7, tsc_AM_SN_Size), tcv_SUFI_Params.Nack2 := INT_TO_BIT(13, tsc_AM_SN_Size),tcv_SU FI_Params.Nack3 := INT_TO_BIT(14, tsc_AM_SN_Size), tcv_SUFI_Params.UB := INT_TO_BIT(15, tsc_AM_SN_Size),tcv_SU FI_Params.ACK_presence := OMIT,tcv_SUFI_Params. WSN_presence := OMIT,tcv_SUFI_Params.M RW_presence := OMIT)	Rejected - the default values of the indicated fields is OMIT, therefore the	26/02/2009

GCF priority!

Category: C

Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:07

page 21 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_8_1_1_1	RRC / Paging for Connection in idle mode	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	SS should be reconfigured just before receiving the Initial direct Transfer	Accepted - v150	16/09/2002
									GCF priority: Category: D Package: 1
	tc_8_1_3_1	RRC / RRC Connection Release in CELL_DCH state: Successful	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	The condition [tcv_K=(tcv_N308+1)) AND tcv_TimedOut] is not correct to get a PASS verdict	Accepted - v150	16/09/2002
									GCF priority: Category: D Package: 1
	tc_8_1_3_1	RRC / RRC Connection Release in CELL_DCH state: Successful	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	The usage of timer shall be reviewed	Accepted - v150	16/09/2002
									GCF priority: Category: D Package: 1
	tc_8_2_3_1	RRC / Radio Bearer Release for transition from CELL_DCH to CELL_DCH: Success	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	Line 13, tcv_RRC_RAB_type shall be used instead of cell_DCH_StandAloneSRB	Accepted - v150	16/09/2002
									GCF priority: Category: D Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:08

page 22 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_8_3_1_1	RRC / Cell Update: cell reselection in CELL_FACH	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	The indentation level shall be corrected	Accepted - v150	16/09/2002
GCF priority:									
Category: D									
Package: 1									
	tc_8_3_3_1	RRC / UTRAN Mobility Information: Success	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	As line 3 the loop condition is [tcv_k > 4], then tcv_k shall be set to 5 in line 6, otherwise the loop will not end upon receipt of the DeactivatePDPCContextAccept.	Accepted - v151	07/10/2002
GCF priority:									
Category: D									
Package: 1									
	tc_8_3_3_1	RRC / UTRAN Mobility Information: Success	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	Line 14, tsc_CellDedicated shall be used instead of tsc_cellA	Accepted - v150	16/09/2002
GCF priority:									
Category: D									
Package: 1									
	tc_8_4_1_1	Measurement Control and Report: Intra-frequency measurement for transition from idle mode to CELL_DCH state	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	SB type shall be included in the constraint - c_MIB_ModifiedMeasurement	Accepted - v150	16/09/2002
GCF priority:									
Category: D									
Package: 1									

Test cases with problems - v140

produced on: 07/11/2002 17:50:08

page 23 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_8_4_1_1	Measurement Control and Report: Intra-frequency measurement for transition from idle mode to CELL_DCH state	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	Line 24, the list reference numbers should be corrected	Accepted - v150	16/09/2002
	tc_8_4_1_1	Measurement Control and Report: Intra-frequency measurement for transition from idle mode to CELL_DCH state	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	SB type shall be included in the constraint - c_MIB_ModifiedMeasEurope	Accepted - v150	16/09/2002

GCF priority:

Category: D

Package: 1

GCF priority:

Category: D

Package: 1

Test cases with problems - v140

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
020040									
	tc_12_2_1_5a_3	PS attach / rejected / roaming not allowed in this location area / test procedure 3	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	We are doing a location update and an attach simultaneously. The attach is being rejected. Then the UE will send a signalling connection release which is not handled in the TTCN.	Open	?
<div style="float: right; border: 1px solid red; padding: 2px;"> GCF priority: Category: Package: </div>									
	tc_7_2_3_14	AM RLC / Control of Receive Window	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	line 18 , tcv_AM_Data has to be replaced by * . As line 11 calculates value of tcv_AM_Data , which we expect for first RLC PDU to be received , but this tcv_AMD PDU value is overwritten by the RLC PDU send .So if we have send 5th RLC PDU (which can be the case due to loop back delay)and then we are receiving the first RLC PDU so value in data part tcv_AM_Data will be different than expected.	Accepted - v151	16/10/2002
<div style="float: right; border: 1px solid red; padding: 2px;"> GCF priority: Category: C Package: 1 </div>									
	tc_7_2_3_16	AM RLC / Polling for status / Last PU in retransmission queue	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	In line 18 c_SNiLi(0, 0) to be replaced by c_SNiLi(0, 1)	Accepted - v151	16/10/2002
<div style="float: right; border: 1px solid red; padding: 2px;"> GCF priority: Category: C Package: 1 </div>									

Test cases with problems - v140

produced on: 07/11/2002 17:50:08

page 25 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_7_2_3_17	AM RLC / Polling for status / Poll every Poll_PU PUs	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	1. In Line 28 , [tcv_NumPDUsRx = p_P] should be changed to [tcv_NumPDUsRx = (p_P-1)] 2. In Line 30 , [tcv_NumPDUsRx = p_P] should be changed to [tcv_NumPDUsRx = (2 *p_P) - 1)] 3. In Line 32 , [tcv_NumPDUsRx = p_P] should be changed to [tcv_NumPDUsRx = ((3 *p_P) -1)]	Accepted - v151	16/10/2002
	tc_7_2_3_25	AM RLC / Receiver Status Triggers / Detection of missing PUs	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	For all the TxAMD data send tsc_P_Poll has to be replaced by tsc_P_NoPoll . Poll is not required and there is no status pdu handling for that in test case	Accepted - v151	16/10/2002

GCF priority:

Category: C

Package: 1

GCF priority:

Category: C

Package: 1

Test cases with problems - v140

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_7_2_3_26	AM RLC / Receiver Status Triggers / Operation of timer Timer_Status_Periodic	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	<p>RLC Spec 25.322 in clause 9.6 (g) section specify that This (timer_StatusPeriodic) timer shall be started when the RLC entity is created".So as soon as RAB setup message is sent and UE configures rlc entity , this timer is started. With the typical value of Activation time we use for DCH to DCH RB Setup of around 2.5 Seconds, The RLC entity for RAB may be established long before this, and the RLC layer starts sending it to MAC and hence to Physical. But Physical layer is not allowed to send it, before Activation time, but from Activation time, the Status PDU's get transmitted. RRC layer sends Radio bearer setup complete, only after all layers, including Physical Says everything is fine. In short,it is required to handle Status PDU in (may be) default handler for test step which has radiobearer setup procedure, as RLC Status PDU's on RAB will start coming much before the Radio Bearer Setup Complete."</p>	Accepted - v151	24/10/2002

GCF priority:
 Category: C
 Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:08

page 27 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_7_2_3_27	AM RLC / Receiver Status Triggers / Operation of timer Timer_Status_Prohibit	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	1. Due to Timer_statusPeriodic, enabled, The status PDU's come before Radio Bearer Setup complete. So we need to handle it in probably in default handler for the step. (explanation as given in above comment) 2. In line 34 condition changed to greater than equal to 2 . As there can be any number of STATUS PDU during the execution of test case .	Accepted - v151	24/10/2002
	tc_7_2_3_28	AM RLC / Status reporting / Abnormal conditions / Reception of LIST SUFI with Length set to zero	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	In Line 9 , tcv_AM_VTS is to be replaced by tcv_AM_VRR . Reason : For Receiving RLC PDU , AM receive state variable VR(R) should be used .	Accepted - v151	16/10/2002
	tc_8_2_1_9	RRC / Radio Bearer Establishment for transition from CELL_DCH to CELL_FACH: Success (Cell re-selection)	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	In cell update confirm, we have to OMIT max_allowed_dl_power since even that is "Physical channel information element" and hence is a case of incompatible simultaneous reconfig . Refer to 25.331 section 8.3.1.9a	Accepted - v150	12/09/2002

GCF priority:

Category: C

Package: 1

GCF priority:

Category:

Package:

GCF priority:

Category: D

Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:09

page 28 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_8_2_3_9	RRC / Radio Bearer Release for transition from CELL_FACH to CELL_DCH: Success	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	"The transport channels to be deleted is not in configured list. Pls see constraint cbs_108_RB_RelFACH_T oDCH ies ul_deletedTransChInfoList & dl_DeletedTransChInfoList. I think these 2 can be OMITed."	Accepted - v150	12/09/2002
	tc_8_3_3_1	RRC / UTRAN Mobility Information: Success	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	"The value of T305 is initially given to be half an hour. After the UMI we are making the value of T305 as 5 mins. But the next periodic cell update will not come in 5 mins, since the changed value of T305 will be in effect only after its initial expiry."	Accepted - v150	13/09/2002
	tc_8_3_3_2	RRC / UTRAN Mobility Information: Failure (Invalid message reception)	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	For each updated timer value: start using the new value next time the timer is started.	Accepted - v150	13/09/2002

GCF prioritie:

Category: D

Package: 1

GCF prioritie:

Category: D

Package: 1

GCF prioritie:

Category:

Package:

Test cases with problems - v140

produced on: 07/11/2002 17:50:09

page 29 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
020041									
	tc_12_2_1_5a_1	PS attach / rejected / roaming not allowed in this location area / test procedure 1	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	In the local tree It_Steps_14To16, the DETACH is done for P_TMSI, but it is not done for IMSI. The IMSI detach should be done because the Network is operating in mode II and the attach/detach flag is set to ON.	Rejected	10/10/2002
	tc_8_1_9	RRC / Signalling Connection Release Indication	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	In order to simplify the test case and to have a predictable behaviour without compromising the test purposes, we suggest to use paging and paging response instead of registration for this specific test case.	Accepted - v151	01/10/2002

GCF priority:
Category:
Package:

GCF priority:
Category: D
Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:09

page 30 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
020042									
	tc_12_2_2_2_1	Combined PS attach / PS only attach accepted / test procedure 1	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	Delete the fields under t3302Value	Rejected	27/09/2002
									GCF priority: Category: Package:
	tc_7_1_1_2	DTCH or DCCH mapped to RACH/FACH / Invalid TCTF	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	the fields 'SWN_presence', 'MRW_presence', 'Value', 'Nack2', 'Nack3' shall be replaced from ? by OMIT	Rejected	17/10/2002
									GCF priority: Category: C Package: 1
	tc_7_1_1_2	DTCH or DCCH mapped to RACH/FACH / Invalid TCTF	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	The field 'ACK_presence' shall be replaced from ? To TRUE	Rejected	17/09/2002
									GCF priority: Category: C Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:09

page 31 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_8_1_2_2	RRC / RRC Connection Establishment: Success after T300 timeout	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	visual inspection	n/a	Line 26, the configuration cell_DCH_StandAloneSRB is not configured, replace it by cell_FACH	Accepted - v150	17/07/2002
GCF priority:									
Category: D									
Package: 1									
	tc_8_1_2_2	RRC / RRC Connection Establishment: Success after T300 timeout	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	Lines 41, 42, tcv_K is not incremented by 1	Accepted - v150	17/04/2002
GCF priority:									
Category: D									
Package: 1									
	tc_8_1_2_2	RRC / RRC Connection Establishment: Success after T300 timeout	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	Starting line 17, the indentation levels shall be incremented by 1	Accepted - v150	17/01/2002
GCF priority:									
Category: D									
Package: 1									
	tc_8_2_3_19	RRC / Radio Bearer Release from CELL_DCH to URA_PCH: Success	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	The cell configuration is not updated after releasing the RAB, then errors are generated in the postamble	Accepted - v151 - ts_SS_ReleaseDCH_ToFACH_PS has been updated, the configuration of the cell is set to cell_FACH	17/10/2002
GCF priority:									
Category: D									
Package: 1									

Test cases with problems - v140

produced on: 07/11/2002 17:50:09

page 32 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_8_2_3_19	RRC / Radio Bearer Release from CELL_DCH to URA_PCH: Success	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	The cell configuration is not updated after releasing the RAB, then errors are generated in the postamble	Accepted - v151	17/10/2002
GCF priority:									
Category: D									
Package: 1									
	tc_8_2_3_7	RRC / Radio Bearer Release for transition from CELL_DCH to CELL_FACH: Success	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	The cell configuration is not updated after releasing the RAB, then errors are generated in the postamble	Accepted - v151 - ts_SS_ReleaseDCH_ToFACH_PS has been updated, the configuration of the cell is set to cell_FACH	17/10/2002
GCF priority:									
Category:									
Package:									
	tc_8_2_3_7	RRC / Radio Bearer Release for transition from CELL_DCH to CELL_FACH: Success	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	The cell configuration is not updated after releasing the RAB, then errors are generated in the postamble	Accepted - v151	17/10/2002
GCF priority:									
Category:									
Package:									
	tc_8_2_5_4	RRC / Transport format combination Control in CELL_DCH: Failure (Invalid message reception and invalid configuration)	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	Lines 11,14,15,18, for sending and receiving message on RB2, tsc_CellDedicated shall be used instead of tsc_CellA	Accepted - v150	17/10/2002
GCF priority:									
Category:									
Package:									

Test cases with problems - v140

produced on: 07/11/2002 17:50:09

page 33 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
020044									
	tc_12_2_2_1	Combined PS attach / PS and non-PS attach accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	Step 15, 15a and 16 (with reference to 34.123-1, June-02), the test has 2 sequences one for Switch off, where in step 16 Detach Request message is to be expected, and the other sequence for Power off, where in step 16, Detach should not be expected. TTCN implementation has only the first sequence for the Switch off, and the test flow for Power off is missing.	Accepted - v151	24/10/2002
	tc_12_4_3_1	Periodic routing area updating / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	The t_UpperBound timer shall be cancelled after the receipt of the Routing area update request, not after the end of the routing area update procedure (timer should be cancelled line 34)	Accepted - v151	23/10/2002
	tc_12_4_3_1	Periodic routing area updating / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	Line 38, the Routing area update complete shall not be sent by UE because no new PTMSi is allocated (refer to 24.008 clause 4.7.5.1.3 and to the sequence in prose)	Accepted - v151	23/10/2002

GCF priority:

Category: I

Package: 2

GCF priority:

Category: J

Package: 2

GCF priority:

Category: J

Package: 2

Test cases with problems - v140

produced on: 07/11/2002 17:50:09

page 34 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_12_4_3_1	Periodic routing area updating / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	The value of the constant tsc_PTMSI_Sig3 is having a length of 4 oCTETSTRING, but the type of the structure PTMSI_Signature is having a length restriction to OCTETSTRING[3] (refer to 24.008 clause 10.5.5.8)	Accepted - v151	23/10/2002
	tc_12_4_3_1	Periodic routing area updating / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	Line 20, indentation level shall be increased by 1	Accepted - v151	23/10/2002
	tc_12_5	P-TMSI reallocation	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	Line 31 and 31, the indentation level shall be increased by 1	Accepted - v151	23/10/2002
	tc_12_5	P-TMSI reallocation	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	Line 41, the Fail verdict is incorrect in this line as it is a START Timer action	Accepted - v151	23/10/2002

GCF priority:

Category: J

Package: 2

GCF priority:

Category: J

Package: 2

GCF priority:

Category: J

Package: 2

GCF priority:

Category: J

Package: 2

Test cases with problems - v140

produced on: 07/11/2002 17:50:10

page 35 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_8_1_3_5	RRC / RRC Connection Release in CELL_FACH state: Invalid message	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	Discrepancy between the prose and the TTCN	Accepted - v151	17/10/2002
	tc_9_2_4	Authentication rejected by the UE (SQN failure)	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	Line 27, tcv_AuthAMF should be replaced by '1111111111111111'B, or tcv_AuthAMF should be assigned to '1111111111111111'B before line 17.	Accepted - v151	23/10/2002

GCF priority:

Category: P

Package: 3

GCF priority:

Category: B

Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:10

page 36 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
020047									
	tc_12_2_1_1	PS attach / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	Steps shall not be called using tsc_CellDedicated (tsc_CellA or tsc_CellB shall be used instead)	Accepted - v151	22/10/2002
									GCF priority: Category: B Package: 1
	tc_12_2_2_1	Combined PS attach / PS only attach accepted / test procedure 1	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	cs_AttachAcc2: Delete the fields under t3302Value	Rejected	22/10/2002
									GCF priority: Category: Package:
	tc_12_3_1_1	PS detach / power off / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	Steps shall not be called using tsc_CellDedicated (tsc_CellA or tsc_CellB shall be used instead)	Accepted - v151	22/10/2002
									GCF priority: Category: B Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:10

page 37 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_12_3_1_1	PS detach / power off / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	Line 32, ts_RRC_ConnRel(tsc_Cell C, cell_Dch) shall be replaced by +ts_RRC_ConnRel(tsc_Ce IIA, cell_Dch) as the connection is established on cell A	Accepted - v151	22/10/2002
GCF priority: Category: B Package: 1									
	tc_12_3_1_2	PS detach / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	Lines 30 and 31, the cell passed as parameter to steps shall be tsc_CellA instead of tsc_CellDedicated	Accepted - v151	22/10/2002
GCF priority: Category: B Package: 1									
	tc_12_3_1_5	PS detach / power off / accepted / PS/IMSI detach	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	Line 22, ts_RRC_ConnRel(tsc_Cell C, cell_Dch) shall be replaced by +ts_RRC_ConnRel(tsc_Ce IIA, cell_Dch) as the connection is established on cell A	Accepted - v151	22/10/2002
GCF priority: Category: B Package: 1									
	tc_12_3_1_5	PS detach / power off / accepted / PS/IMSI detach	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	Steps shall not be called using tsc_CellDedicated (tsc_CellA or tsc_CellB shall be used instead)	Accepted - v151	22/10/2002
GCF priority: Category: B Package: 1									

Test cases with problems - v140

produced on: 07/11/2002 17:50:10

page 38 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_12_3_1_5	PS detach / power off / accepted / PS/IMSI detach	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	Line 17, the RAI ie in cr_Attachreq shall be of any value (?) instead of OMIT	Accepted - v150	22/10/2002
									GCF priority: Category: B Package: 1
	tc_12_3_1_6	PS detach / accepted / PS/IMSI detach	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	Line 22, the RAI ie in cr_Attachreq shall be of any value (?) instead of OMIT	Accepted - v150	22/10/2002
									GCF priority: Category: B Package: 1
	tc_12_3_1_6	PS detach / accepted / PS/IMSI detach	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	Steps shall not be called using tsc_CellDedicated (tsc_CellA or tsc_CellB shall be used instead)	Accepted - v151	22/10/2002
									GCF priority: Category: B Package: 1
	tc_12_3_1_6	PS detach / accepted / PS/IMSI detach	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	Line 27, ts_RRC_ConnRel(tsc_Cell C, cell_Dch) shall be replaced by +ts_RRC_ConnRel(tsc_CellA, cell_Dch) as the connection is established on cell A	Accepted - v151	22/10/2002
									GCF priority: Category: B Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:10

page 39 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_12_3_2_1	PS detach / re-attach not required / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	Steps shall not be called using tsc_CellDedicated (tsc_CellA or tsc_CellB shall be used instead)	Accepted - v151	22/10/2002
									GCF priority: Category: B Package: 1
	tc_12_3_2_1	PS detach / re-attach not required / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	Lines 22 and 31, the RAI ie in cr_Attachreq shall be of any value (?) instead of OMIT	Accepted - v150	22/10/2002
									GCF priority: Category: B Package: 1
	tc_12_3_2_1	PS detach / re-attach not required / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	Line 36, ts_RRC_ConnRel(tsc_Cell C, cell_Dch) shall be replaced by +ts_RRC_ConnRel(tsc_Ce lIA, cell_Dch) as the connection is established on cell A	Accepted - v150	22/10/2002
									GCF priority: Category: B Package: 1
	tc_12_4_1_1a	Routing area updating / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	Line 34, the RAI ie in cr_Attachreq shall be of any value (?) instead of OMIT	Accepted - v150	22/10/2002
									GCF priority: Category: B Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:10

page 40 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_12_4_1_1a	Routing area updating / accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	Lines 35, 36, 42, 49, 50, steps shall be called using tsc_CellDedicated instead of tsc_CellA or tsc_CellB	Accepted - v151	22/10/2002
									GCF priority: Category: B Package: 1
	tc_12_6_1_1	Authentication accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	Steps shall not be called using tsc_CellDedicated (tsc_CellA or tsc_CellB shall be used instead)	Accepted - v151	22/10/2002
									GCF priority: Category: B Package: 1
	tc_12_6_1_1	Authentication accepted	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	Line 25, the RAI ie in cr_Attachreq shall be of any value (?) instead of OMIT	Accepted - v150	22/10/2002
									GCF priority: Category: B Package: 1
	tc_12_7_1	General Identification	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	Line 26, the RAI ie in cr_Attachreq shall be of any value (?) instead of OMIT	Accepted - v150	22/10/2002
									GCF priority: Category: B Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:10

page 41 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_12_7_1	General Identification	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	c_MobileIdIMEI_lvr: the length shall be set to '09'O instead of '08'O	Accepted - v151	22/10/2002
									GCF priority: Category: B Package: 1
	tc_12_7_1	General Identification	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	Steps shall not be called using tsc_CellDedicated (tsc_CellA or tsc_CellB shall be used instead)	Accepted - v151	22/10/2002
									GCF priority: Category: B Package: 1
	tc_12_9_1	Service Request Initiated by UE Procedure	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	Steps shall not be called using tsc_CellDedicated (tsc_CellA or tsc_CellB shall be used instead)	Accepted - v151	22/10/2002
									GCF priority: Category: B Package: 1
	tc_12_9_1	Service Request Initiated by UE Procedure	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work station	n/a	Line 24, the RAI ie in cr_Attachreq shall be of any value (?) instead of OMIT	Accepted - v150	22/10/2002
									GCF priority: Category: B Package: 1

Test cases with problems - v140

produced on: 07/11/2002 17:50:11

page 42 of 43

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
	tc_12_9_2	Service Request Initiated by Network Procedure	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	Line 24, the RAI ie in cr_Attachreq shall be of any value (?) instead of OMIT	Accepted - v150	22/10/2002
GCF priority:									
Category: B									
Package: 1									
	tc_12_9_2	Service Request Initiated by Network Procedure	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	Steps shall not be called using tsc_CellDedicated (tsc_CellA or tsc_CellB shall be used instead)	Accepted - v151	22/10/2002
GCF priority:									
Category: B									
Package: 1									
	tc_12_9_3	Service Request / rejected / Illegal MS	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	Line 38, the RAI ie in cr_Attachreq shall be of any value (?) instead of OMIT	Accepted - v150	22/10/2002
GCF priority:									
Category: P									
Package: 3									
	tc_12_9_3	Service Request / rejected / Illegal MS	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	test in work static	n/a	Steps shall not be called using tsc_CellDedicated (tsc_CellA or tsc_CellB shall be used instead)	Accepted - v151	22/10/2002
GCF priority:									
Category: P									
Package: 3									

Test cases with problems - v140

Nr of error report	Test case nr.	Title	Environment	Version	Test category	Test results	Problem	Comment from MCC Task 160	Done date
--------------------	---------------	-------	-------------	---------	---------------	--------------	---------	---------------------------	-----------

020048

	tc_8_1_2_1	RRC / RRC Connection Establishment in CELL_DCH state: Success	<input checked="" type="checkbox"/> environment_n/a <input checked="" type="checkbox"/> FDD <input type="checkbox"/> TDD <input type="checkbox"/> CS <input type="checkbox"/> PS <input type="checkbox"/> with integrity <input type="checkbox"/> voice call <input type="checkbox"/> data call	v1.4.0	real environment	n/a	Single RAT UEs cannot be tested as it is an optional ie, the field shall be set to AnyOrOmit value '*' in the radio access capability.	Accepted - v151	29/10/2002
--	------------	---	--	--------	------------------	-----	--	-----------------	------------

GCF priority:
 Category: D
 Package: 1

This report contains:

Number of problems: 116

Completed problems: 115