

3GPP TSG-RAN Meeting#15
Jeju, South Korea, 5th – 8th of March 2002

Tdoc RP-020248

CR-Form-v5

CHANGE REQUEST

⌘ **25.331 CR 1330** ⌘ rev **5** ⌘ Current version: **3.9.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

Proposed change affects: ⌘ (U)SIM ME/UE Radio Access Network Core Network

Title:	⌘ Clarification to physical channel establishment criteria	
Source:	⌘ Nokia	
Work item code:	⌘	
	Date: ⌘ 18 th Feb. 2002	
Category:	⌘ F	Release: ⌘ R99
Use <u>one</u> of the following categories: F (correction) A (corresponds to a correction in an earlier release) B (addition of feature), C (functional modification of feature) D (editorial modification)		
Use <u>one</u> of the following releases: 2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) REL-4 (Release 4) REL-5 (Release 5)		
Detailed explanations of the above categories can be found in 3GPP TR 21.900 .		

Reason for change:	⌘ The current description of the physical channel establishment criteria defines that the UE shall wait for N312 successive in-sync indications from layer 1 before a physical channel is considered to be established. The term "successive" is ambiguous in this context. According to 25.214, layer 1 will send either an in-sync indication or no message for each frame during the physical channel establishment. Out-of-sync indications are not sent. This definition allows two different interpretations: 1. RRC needs to receive N312 in-sync indications during N312 consecutive frames, each frame where no in-sync indication is received resets the counter 2. RRC needs to receive N312 in-sync indications. Frames without any indication from layer 1 do not reset the counter. To avoid potential ambiguities it is proposed to remove the word "successive" from the description of N312. A similar clarification is needed for the radio link failure criteria. It seemed that the values 1, 50, ... 1000 for N312 and N315 had been introduced erroneously into ASN.1 by the very first CR on ASN.1. These values don't seem to be suitable and it is proposed that the value range is aligned with N313 (which is 1, 2, 4, 10, 20, 50, 100, 200) and that values 2, 4, 10 and 20 are added as an
---------------------------	------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

[extension.](#)

Summary of change:⌘ During physical layer establishment, the UE shall wait for layer 1 to indicate N312 "in sync" indications. The word "successive" is removed from the definition of the physical channel establishment criteria.
A similar clarification is added to the Radio link failure criteria in section 8.5.6
The values for N312 and N315 are aligned with N313 to support also values between 1 and 50.

Isolated Impact Analysis:

Corrected functionality is the physical channel establishment and radio link failure criteria.

If the network implements the change but the UE does not [\(or the other way around\)](#) then the UE will use the default values for N312 and N315 [in case values are included in the extension.](#)

[In case the UE implements the CR and the network do not implement the CR, the network will only use values according to the old IE and changes in this CR will not have any affect at all.](#) To minimise backward compatibility problems, the new ranges for N312 and N315 are implemented in a non-critical extension and the old IEs should no longer be sent. This means that in the case that either the UE or NW has not implemented this change the UE will use the default value of 1. Although the network will be unaware of this the only possible side effect is that the UE would consider the channel established earlier than expected and begin transmitting, but this is not considered to be a problem.

Consequences if not approved:⌘ The PDCH establishment criteria remains erroneous. This makes it in practice impossible for the network to configure any other value than 1, which is not seen as suitable for all cases.

Clauses affected: ⌘ 8.5.4, 8.5.6, 10.3.3.43, 10.3.3.44, 11.2, 11.3, 13.1, 13.3

Other specs affected:	⌘	Other core specifications	⌘	
	X	Test specifications		TS 34.123
		O&M Specifications		

Other comments: ⌘

8.5.4 Physical channel establishment criteria

When a physical dedicated channel establishment is initiated by the UE, the UE shall start a timer T312 and wait for layer 1 to indicate N312 ~~successive~~ "in sync" indications. On receiving N312 ~~successive~~ "in sync" indications, the physical channel is considered established and the timer T312 is stopped and reset.

If the timer T312 expires before the physical channel is established, the UE shall consider this as a "physical channel establishment failure".

8.5.6 Radio link failure criteria and actions upon radio link failure

In CELL_DCH State, after receiving N313 consecutive "out of sync" indications from layer 1 for the established DPCCH physical channel in FDD, and the DPCH associated with mapped DCCHs in TDD, the UE shall:

- start timer T313;
- upon receiving N315 successive "in sync" indications from layer 1 and upon change of UE state:
 - stop and reset timer T313.
- if T313 expires:
 - consider it as a "Radio link failure".

Periods in time where neither "in sync" nor "out of sync" is reported by layer 1 do not affect the evaluation of the number of consecutive (resp. successive) "in sync" or "out of sync" indications.

When a radio link failure occurs, the UE shall:

- clear the dedicated physical channel configuration;
- perform actions as specified for the ongoing procedure;
- if no procedure is ongoing or no actions are specified for the ongoing procedure:
 - perform a cell update procedure according to subclause 8.3.1 using the cause "radio link failure".

10.3.3.43 UE Timers and Constants in connected mode

This information element specifies timer- and constants values used by the UE in connected mode.

Information Element/Group name	Need	Multi	Type and reference	Semantics description
T301	MD		Integer(100, 200 .. 2000 by step of 200, 3000, 4000, 6000, 8000)	Value in milliseconds. Default value is 2000. This IE should not be used by the UE in this release of the protocol.
N301	MD		Integer(0..7)	Default value is 2. This IE should not be used by the UE in this release of the protocol.
T302	MD		Integer(100, 200... 2000 by step of 200, 3000, 4000, 6000, 8000)	Value in milliseconds. Default value is 4000.
N302	MD		Integer(0..7)	Default value is 3.
T304	MD		Integer(100,	Value in milliseconds. Default

Information Element/Group name	Need	Multi	Type and reference	Semantics description
			200, 400, 1000, 2000)	value is 2000. At least one spare value is needed. Note 1.
N304	MD		Integer(0..7)	Default value is 2. Note 1.
T305	MD		Integer(5, 10, 30, 60, 120, 360, 720, infinity)	Value in minutes. Default value is 30. Infinity means no update
T307	MD		Integer(5, 10, 15, 20, 30, 40, 50)	Value in seconds. Default value is 30.
T308	MD		Integer(40, 80, 160, 320)	Value in milliseconds. Default value is 160. Note 1.
T309	MD		Integer(1...8)	Value in seconds. Default value is 5. Note 1.
T310	MD		Integer(40 .. 320 by step of 40)	Value in milliseconds. Default value is 160. Note 1.
N310	MD		Integer(0 .. 7)	Default value is 4. Note 1.
T311	MD		Integer(250 .. 2000 by step of 250)	Value in milliseconds. Default value is 2000. Note 1.
T312	MD		Integer (0..15)	Value in seconds. Default value is 1. The value 0 is not used in this version of the specification.
N312	MD		Integer (1, <u>2</u> , 4, 10, 20, 50, 100, 200, 400, 600, 800, 1000)	Default value is 1.
T313	MD		Integer (0..15)	Value in seconds. Default value is 3. Note 1.
N313	MD		Integer (1, 2, 4, 10, 20, 50, 100, 200)	Default value is 20. Note 1.
T314	MD		Integer(0, 2, 4, 6, 8, 12, 16, 20)	Value in seconds. Default value is 12. Note 1.
T315	MD		Integer (0,10, 30, 60, 180, 600, 1200, 1800)	Value in seconds. Default value is 180. Note 1.
N315	MD		Integer (1, <u>2</u> , 4, 10, 20, 50, 100, 200, 400, 600, 800, 1000)	Default value is 1. Note 1.
T316	MD		Integer(0, 10, 20, 30, 40, 50, infinity)	Value in seconds. Default value is 30.
T317	MD		Integer (0,10, 30, 60, 180, 600, 1200, 1800)	Value in seconds. Default value is 180.

NOTE 1: If the value of SIB1 changes, the UE shall re-read SIB1 and use the new value of the parameter, if modified.

10.3.3.44 UE Timers and Constants in idle mode

This information element specifies timer- and constant values used by the UE in idle mode.

Information Element/Group name	Need	Multi	Type and reference	Semantics description
T300	MP		Integer(100, 200... 2000 by step of 200, 3000, 4000, 6000, 8000)	Value in milliseconds. Default value is 1000. Use of Default is described in 10.2.48.8.4 and in 10.2.48.8.16.
N300	MP		Integer(0..7)	Default value is 3. Use of Default is described in 10.2.48.8.4 and in 10.2.48.8.16.
T312	MP		Integer(0 .. 15)	Value in seconds. Default value is 1. Use of Default is described in 10.2.48.8.4 and in 10.2.48.8.16. The value 0 is not used in this version of the specification.
N312	MP		Integer (1, <u>2</u> , <u>4</u> , <u>10</u> , <u>20</u> , 50, 100, 200, 400, 600, 800, 1000)	Default value is 1. Use of Default is described in 10.2.48.8.4 and in 10.2.48.8.16.

11.2 PDU definitions

```
--*****
-- TABULAR: The message type and integrity check info are not
-- visible in this module as they are defined in the class module.
-- Also, all FDD/TDD specific choices have the FDD option first
-- and TDD second, just for consistency.
--*****
```

```
PDU-definitions DEFINITIONS AUTOMATIC TAGS ::=
```

```
BEGIN
```

```
--*****
-- IE parameter types from other modules
--*****
```

```
IMPORTS
```

```
-- Core Network IEs :
  CN-DomainIdentity,
  CN-InformationInfo,
  CN-InformationInfoFull,
  NAS-Message,
  PagingRecordTypeID,
-- UTRAN Mobility IEs :
  URA-Identity,
-- User Equipment IEs :
  ActivationTime,
  C-RNTI,
  CapabilityUpdateRequirement,
  CellUpdateCause,
  CipheringAlgorithm,
  CipheringModeInfo,
  EstablishmentCause,
  FailureCauseWithProtErr,
  FailureCauseWithProtErrTrId,
  InitialUE-Identity,
  IntegrityProtActivationInfo,
  IntegrityProtectionModeInfo,
```

```

N-308,
PagingCause,
PagingRecordList,
ProtocolErrorIndicator,
ProtocolErrorIndicatorWithMoreInfo,
Rb-timer-indicator,
RedirectionInfo,
RejectionCause,
ReleaseCause,
RRC-StateIndicator,
RRC-TransactionIdentifier,
SecurityCapability,
START-Value,
STARTList,
U-RNTI,
U-RNTI-Short,
UE-RadioAccessCapability,
UE-RadioAccessCapability-v370ext,
UE-RadioAccessCapability-v380ext,
DL-PhysChCapabilityFDD-v380ext,
UE-ConnTimersAndConstants,
UE-ConnTimersAndConstants-v3a0ext,
UE-SecurityInformation,
URA-UpdateCause,
UTRAN-DRX-CycleLengthCoefficient,
WaitTime,
-- Radio Bearer IEs :
DefaultConfigIdentity,
DefaultConfigMode,
DL-CounterSynchronisationInfo,
PredefinedConfigIdentity,
PredefinedConfigStatusList,
RAB-Info,
RAB-Info-Post,
RAB-InformationList,
RAB-InformationReconfigList,
RAB-InformationSetupList,
RB-ActivationTimeInfoList,
RB-COUNT-C-InformationList,
RB-COUNT-C-MSB-InformationList,
RB-IdentityList,
RB-InformationAffectedList,
RB-InformationReconfigList,
RB-InformationReleaseList,
SRB-InformationSetupList,
SRB-InformationSetupList2,
UL-CounterSynchronisationInfo,
-- Transport Channel IEs:
CPCH-SetID,
DL-AddReconfTransChInfo2List,
DL-AddReconfTransChInfoList,
DL-CommonTransChInfo,
DL-DeletedTransChInfoList,
DRAC-StaticInformationList,
TFC-Subset,
TFCS-Identity,
UL-AddReconfTransChInfoList,
UL-CommonTransChInfo,
UL-DeletedTransChInfoList,
-- Physical Channel IEs :
Alpha,
CCTrCH-PowerControlInfo,
ConstantValue,
CPCH-SetInfo,
DL-CommonInformation,
DL-CommonInformationPost,
DL-InformationPerRL,
DL-InformationPerRL-List,
DL-InformationPerRL-ListPostFDD,
DL-InformationPerRL-PostTDD,
DL-PDSCH-Information,
DPCH-CompressedModeStatusInfo,
FrequencyInfo,
FrequencyInfoFDD,
FrequencyInfoTDD,
MaxAllowedUL-TX-Power,
PDSCH-CapacityAllocationInfo,
PDSCH-Identity,

```

```

PrimaryCCPCH-TX-Power,
PUSCH-CapacityAllocationInfo,
PUSCH-Identity,
RL-AdditionInformationList,
RL-RemovalInformationList,
SpecialBurstScheduling,
SSDT-Information,
TFC-ControlDuration,
TimeslotList,
TX-DiversityMode,
UL-ChannelRequirement,
UL-ChannelRequirementWithCPCH-SetID,
UL-DPCH-Info,
UL-DPCH-InfoPostFDD,
UL-DPCH-InfoPostTDD,
UL-TimingAdvance,
UL-TimingAdvanceControl,
-- Measurement IEs :
AdditionalMeasurementID-List,
Frequency-Band,
EventResults,
InterRAT-TargetCellDescription,
MeasuredResults,
MeasuredResults-v390ext,
MeasuredResultsList,
MeasuredResultsOnRACH,
MeasurementCommand,
MeasurementIdentity,
MeasurementReportingMode,
PrimaryCCPCH-RSCP,
TimeslotListWithISCP,
TrafficVolumeMeasuredResultsList,
UE-Positioning-GPS-AssistanceData,
UE-Positioning-Measurement-v390ext,
UE-Positioning-OTDOA-AssistanceData,
UE-Positioning-OTDOA-AssistanceData-UEB,
-- Other IEs :
BCCH-ModificationInfo,
CDMA2000-MessageList,
GSM-MessageList,
InterRAT-ChangeFailureCause,
InterRAT-HO-FailureCause,
InterRAT-UE-RadioAccessCapabilityList,
InterRAT-UE-SecurityCapList,
IntraDomainNasNodeSelector,
ProtocolErrorMoreInformation,
Rplmn-Information,
SegCount,
SegmentIndex,
SFN-Prime,
SIB-Data-fixed,
SIB-Data-variable,
SIB-Type
FROM InformationElements

maxSIBperMsg
FROM Constant-definitions;

-- *****
-- 
-- UTRAN MOBILITY INFORMATION
-- 
-- *****

UTRANMobilityInformation ::= CHOICE {
    r3           SEQUENCE {
        utranMobilityInformation-r3      UTRANMobilityInformation-r3-IES,
        v3a0nonCriticalExtensions      SEQUENCE {
            utranMobilityInformation-v3a0ext   UTRANMobilityInformation-v3a0ext-IES,
            nonCriticalExtensions          SEQUENCE {} OPTIONAL
        },
        later-than-r3                  SEQUENCE {
            rrc-TransactionIdentifier     RRC-TransactionIdentifier,
            criticalExtensions          SEQUENCE {}
        }
    }
}

```

```

UTRANMobilityInformation-r3-IEs ::= SEQUENCE {
  -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    integrityProtectionModeInfo   IntegrityProtectionModeInfo
    cipheringModeInfo             CipheringModeInfo
    new-U-RNTI                   U-RNTI
    new-C-RNTI                   C-RNTI
    ue-ConnTimersAndConstants    UE-ConnTimersAndConstants
  -- CN information elements
    cn-InformationInfo           CN-InformationInfoFull
  -- UTRAN mobility IEs
    ura-Identity                 URA-Identity
  -- Radio bearer IEs
    dl-CounterSynchronisationInfo DL-CounterSynchronisationInfo
  -- Extension mechanism for non- release99 information
    nonCriticalExtensions        SEQUENCE {}      OPTIONAL
}

UTRANMobilityInformation-v3a0ext-IEs ::= SEQUENCE {
  ue-ConnTimersAndConstants-v3a0ext  UE-ConnTimersAndConstants-v3a0ext
}

```

11.3 Information element definitions

```

N-312 ::= ENUMERATED {
  s1, s50, s100, s200, s400,
  s600, s800, s1000 }

N-312ext ::= ENUMERATED {
  s1, s2, s4, s10, s20,
  s50, s100, s200}

N-313 ::= ENUMERATED {
  s1, s2, s4, s10, s20,
  s50, s100, s200 }

N-315 ::= ENUMERATED {
  s1, s50, s100, s200, s400,
  s600, s800, s1000 }

N-315ext ::= ENUMERATED {
  s1, s2, s4, s10, s20,
  s50, s100, s200}

```

```

UE-ConnTimersAndConstants ::= SEQUENCE {
  -- Optional is used also for parameters for which the default value is the last one read in SIB1
  -- t-301 and n-301 should not be used by the UE in this release of the protocol
    t-301                      T-301                  DEFAULT ms2000,
    n-301                      N-301                  DEFAULT 2,
    t-302                      T-302                  DEFAULT ms4000,
    n-302                      N-302                  DEFAULT 3,
    t-304                      T-304                  DEFAULT ms2000,
    n-304                      N-304                  DEFAULT 2,
    t-305                      T-305                  DEFAULT m30,
    t-307                      T-307                  DEFAULT s30,
    t-308                      T-308                  DEFAULT ms160,
    t-309                      T-309                  DEFAULT 5,
    t-310                      T-310                  DEFAULT ms160,
    n-310                      N-310                  DEFAULT 4,
    t-311                      T-311                  DEFAULT ms2000,
    t-312                      T-312                  DEFAULT 1,
  -- n-312 shall be ignored if n-312 in UE-ConnTimersAndConstants-v3a0ext is present, and the
  -- value of that element shall be used instead.
  -- dummy is not used in this version of specification, it should
  -- not be sent and if received it should be ignored. Instead the
  -- IE in UE-ConnTimersAndConstants-v3a0ext should be used for N312.
    n-312                      N-312                  DEFAULT s1,
    t-313                      T-313                  DEFAULT 3,
    n-313                      N-313                  DEFAULT s20,

```

```

t-314                               T-314                               DEFAULT s12,
t-315                               T-315                               DEFAULT s180,
-- n-315 shall be ignored if n-3125 in UE-ConnTimersAndConstants-v3a0ext is present, and the
-- value of that element shall be used instead.
-- dummy is not used in this version of specification, it should
-- not be sent and if received it should be ignored. Instead the
-- IE in UE-ConnTimersAndConstants-v3a0ext should be used for N315.
n-315                               N-315                               DEFAULT s1,
t-316                               T-316                               DEFAULT s30,
t-317                               T-317                               DEFAULT s180
}

UE-ConnTimersAndConstants-v3a0ext ::= SEQUENCE {
  n-312                           N-312ext                            DEFAULT s1 OPTIONAL,
  n-315                           N-315ext                            DEFAULT s1 OPTIONAL
}

UE-IdleTimersAndConstants ::= SEQUENCE {
  t-300                           T-300,
  n-300                           N-300,
  t-312                           T-312,
-- n-3152 shall be ignored if n-312 in UE-IdleTimersAndConstants-v3a0ext is present, and the
-- value of that element shall be used instead.
-- dummy is not used in this version of specification and it should
-- be ignored. Instead the IE in UE-IdleTimersAndConstants-v3a0ext
-- should be used for N312.
  n-312                           N-312
}

UE-IdleTimersAndConstants-v3a0ext ::= SEQUENCE {
  n-312                           N-312ext                            OPTIONAL
}

SysInfoType1 ::= SEQUENCE {
  -- Core network IEs
  cn-CommonGSM-MAP-NAS-SysInfo   NAS-SystemInformationGSM-MAP,
  cn-DomainSysInfoList           CN-DomainSysInfoList,
  -- User equipment IEs
  ue-ConnTimersAndConstants     UE-ConnTimersAndConstants    OPTIONAL,
  ue-IdleTimersAndConstants      UE-IdleTimersAndConstants    OPTIONAL,
  -- Extension mechanism for non-release99 information
  v3a0nonCriticalExtensions    SEQUENCE {
    sysInfoType1-v3a0ext          SysInfoType1-v3a0ext-IES,
    nonCriticalExtensions        SEQUENCE {} OPTIONAL
  }                                OPTIONAL
}

SysInfoType1-v3a0ext-IES ::= SEQUENCE {
  ue-ConnTimersAndConstants-v3a0ext  UE-ConnTimersAndConstants-v3a0ext  OPTIONAL,
  ue-IdleTimersAndConstants-v3a0ext  UE-IdleTimersAndConstants-v3a0ext  OPTIONAL
}

SysInfoType13 ::= SEQUENCE {
  -- Core network IEs
  cn-DomainSysInfoList           CN-DomainSysInfoList,
  -- User equipment IEs
  ue-IdleTimersAndConstants      UE-IdleTimersAndConstants    OPTIONAL,
  capabilityUpdateRequirement     CapabilityUpdateRequirement  OPTIONAL,
  -- Extension mechanism for non-release99 information
  v3a0nonCriticalExtensions    SEQUENCE {
    sysInfoType13-v3a0ext         SysInfoType13-v3a0ext-IES,
    nonCriticalExtensions        SEQUENCE {} OPTIONAL
  }                                OPTIONAL
}

SysInfoType13-v3a0ext-IES ::= SEQUENCE {
  ue-IdleTimersAndConstants-v3a0ext  UE-IdleTimersAndConstants-v3a0ext  OPTIONAL,
}

```

13.1 Timers for UE

Timer	Start	Stop	At expiry
T300	Transmission of RRC CONNECTION REQUEST	Reception of RRC CONNECTION SETUP	Retransmit RRC CONNECTION REQUEST if V300 =< N300, else go to Idle mode
T302	Transmission of CELL UPDATE/URA UPDATE	Reception of CELL UPDATE CONFIRM/URA UPDATE CONFIRM	Retransmit CELL UPDATE/URA UPDATE if V302 =< N302, else, go to Idle mode
T304	Transmission of UE CAPABILITY INFORMATION	Reception of UE CAPABILITY INFORMATION CONFIRM	Retransmit UE CAPABILITY INFORMATION if V304 =< N304, else initiate a cell update procedure
T305	Entering CELL_FACH or URA_PCH or CELL_PCH state. Reception of CELL UPDATE CONFIRM/URA UPDATE CONFIRM.	Entering another state.	Transmit CELL UPDATE if T307 is not activated and the UE detects "in service area". Otherwise, if T307 is not active, start T307.
T307	When the timer T305 has expired and the UE detects "out of service area".	When the UE detects "in service area".	Transit to idle mode
T308	Transmission of RRC CONNECTION RELEASE COMPLETE	Not stopped	Transmit RRC CONNECTION RELEASE COMPLETE if V308 <= N308, else go to idle mode.
T309	Upon reselection of a cell belonging to another radio access system from connected mode, or reception of CELL CHANGE ORDER FROM UTRAN message	Successful establishment of a connection in the new cell	Resume the connection to UTRAN
T310	Transmission of PUSCH CAPACITY REQUEST	Reception of PHYSICAL SHARED CHANNEL ALLOCATION	Transmit PUSCH CAPACITY REQUEST if V310 =< N310, else procedure stops.
T311	Reception of PHYSICAL SHARED CHANNEL ALLOCATION message with the CHOICE "PUSCH allocation" set to "PUSCH allocation pending".	Reception of PHYSICAL SHARED CHANNEL ALLOCATION message with CHOICE "PUSCH allocation" set to "PUSCH allocation assignment".	UE may initiate a PUSCH capacity request procedure.
T312	When the UE starts to establish dedicated CH	When the UE detects consecutive N312 "in sync" indication from L1.	The criteria for physical channel establishment failure is fulfilled
T313	When the UE detects consecutive N313 "out of sync" indication from L1.	When the UE detects consecutive N315 "in sync" indication from L1.	The criteria for Radio Link failure is fulfilled
T314	When the criteria for radio link failure are fulfilled. The timer is started only if radio bearer(s) that are associated with T314 exist.	When the Cell Update procedure has been completed.	See subclause 8.3.1.13
T315	When the criteria for radio link failure are fulfilled. The timer is started only if radio bearer(s) that are associated with T315 exist.	When the Cell Update procedure has been completed.	See subclause 8.3.1.14

Timer	Start	Stop	At expiry
T316	When the UE detects "out of service area" in URA_PCH or CELL_PCH state	When the UE detects "in service area".	Initiate cell update procedure if in service area is detected. Otherwise start timer T317, transit to CELL_FACH state and initiate cell update procedure when the UE detects "in service area".
T317	When the T316 expires or when in CELL_FACH state, the UE detects "out of service area".	When the UE detects "in service area".	Transit to idle mode

13.3 UE constants and parameters

Constant	Usage
N300	Maximum number of retransmissions of the RRC CONNECTION REQUEST message
N302	Maximum number of retransmissions of the CELL UPDATE / URA UPDATE message
N304	Maximum number of retransmissions of the UE CAPABILITY INFORMATION message
N308	Maximum number of retransmissions of the RRC CONNECTION RELEASE COMPLETE message
N310	Maximum number of retransmission of the PUSCH CAPACITY REQUEST message
N312	Maximum number of successive "in sync" received from L1.
N313	Maximum number of successive "out of sync" received from L1.
N315	Maximum number of successive "in sync" received from L1 during T313 is activated.