

**TSG RAN Meeting #20**  
**Hämeenlinna, Finland, 3 - 6 June, 2003**

**RP-030353**

**Title** CRs (Rel-5 only) to TS 25.423 and 25.433 linked to RAN1 (25.215 Rel-6) on Phase Reference Signalling Support  
**Source** TSG RAN WG3  
**Agenda Item** 7.3.6

	Spec	curr. Vers.	new Vers.	REL	CR	Rev	Cat	Title	Work item
	25.423	5.5.0	5.6.0	REL-5	817	2	F	Phase Reference Signalling Support	TEI5
	25.433	5.4.0	5.5.0	REL-5	836	2	F	Phase Reference Signalling Supporting	TEI5
	25.215	5.3.0	6.0.0	REL-6	138	3	F	Beamforming Enhancement related measurements	RANimp-BFE

Note: CR817 Rev.1 to TS25.423 Rel-5 and CR836 Rev.1 to TS25.433 in RP-030344 were 'conditionally agreed' by RAN3 under the condition that RAN1 has not changed the cell portion concept.

## CHANGE REQUEST

⌘ TS25.215 CR 138 ⌘ rev 3 ⌘ Current version: 5.3.0 ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

**Proposed change affects:** UICC apps ⌘ ME ⌘ Radio Access Network  Core Network ⌘

<b>Title:</b>	⌘ Beamforming Enhancement related measurements	
<b>Source:</b>	⌘ Nokia	
<b>Work item code:</b>	⌘ RANimp-BFE	<b>Date:</b> ⌘ 4/06/2003
<b>Category:</b>	⌘ <b>B</b> <i>Use one of the following categories:</i> <b>F</b> (correction) <b>A</b> (corresponds to a correction in an earlier release) <b>B</b> (addition of feature), <b>C</b> (functional modification of feature) <b>D</b> (editorial modification)	<b>Release:</b> ⌘ Rel-5 <i>Use one of the following releases:</i> 2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) Rel-4 (Release 4) Rel-5 (Release 5) Rel-6 (Release 6)
Detailed explanations of the above categories can be found in 3GPP <a href="#">TR 21.900</a> .		

<b>Reason for change:</b>	⌘ Agreed changes to UTRAN measurements from Work Item on Beamforming Enhancements are introduced.
<b>Summary of change:</b>	⌘ The Rel'6 feature of beamforming enhancement is also introduced to Rel'5 with relevant restrictions. UTRAN measurements for received total wide band power, SIR, transmitted carrier power and transmitted carrier power of all codes not used for HS-PDSCH or HS-SCCH transmission are revised to support beamforming enhancement.
<b>Consequences if not approved:</b>	⌘ Rel'5 beamforming solution is not complete in the specification.

<b>Clauses affected:</b>	⌘ 5.2.1, 5.2.2, 5.2.4												
<b>Other specs affected:</b>	<table border="1" style="display: inline-table; vertical-align: middle;"> <tr> <td style="text-align: center;">Y</td> <td style="text-align: center;">N</td> </tr> <tr> <td style="text-align: center;"><input checked="" type="checkbox"/></td> <td></td> </tr> </table> Other core specifications ⌘ CR836 TS 25.433 v5.4.0 <table border="1" style="display: inline-table; vertical-align: middle;"> <tr> <td style="text-align: center;"></td> <td style="text-align: center;">X</td> </tr> <tr> <td></td> <td></td> </tr> </table> Test specifications ⌘ CR817 TS 25.423 v5.5.0 <table border="1" style="display: inline-table; vertical-align: middle;"> <tr> <td style="text-align: center;"></td> <td style="text-align: center;">X</td> </tr> <tr> <td></td> <td></td> </tr> </table> O&M Specifications	Y	N	<input checked="" type="checkbox"/>			X				X		
Y	N												
<input checked="" type="checkbox"/>													
	X												
	X												
<b>Other comments:</b>	⌘												

### How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.

- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

---

## 1 Scope

The present document contains the description and definition of the measurements for FDD done at the UE and network in order to support operation in idle mode and connected mode.

---

## 2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TS 25.211: "Physical channels and mapping of transport channels onto physical channels (FDD)".
- [2] 3GPP TS 25.212: "Multiplexing and channel coding (FDD)".
- [3] 3GPP TS 25.213: "Spreading and modulation (FDD)".
- [4] 3GPP TS 25.214: "Physical layer procedures (FDD)".
- [5] 3GPP TS 25.215: "Physical layer - Measurements (FDD)".
- [6] 3GPP TS 25.221: "Physical channels and mapping of transport channels onto physical channels (TDD)".
- [7] 3GPP TS 25.222: "Multiplexing and channel coding (TDD)".
- [8] 3GPP TS 25.223: "Spreading and modulation (TDD)".
- [9] 3GPP TS 25.224: "Physical layer procedures (TDD)".
- [10] 3GPP TS 25.301: "Radio Interface Protocol Architecture".
- [11] 3GPP TS 25.302: "Services provided by the Physical layer".
- [12] 3GPP TS 25.303: "UE functions and interlayer procedures in connected mode".
- [13] 3GPP TS 25.304: "UE procedures in idle mode".
- [14] 3GPP TS 25.331: "RRC Protocol Specification".
- [15] 3GPP TR 25.922: "Radio Resource Management Strategies".
- [16] 3GPP TR 25.923: "Report on Location Services (LCS)".
- [17] 3GPP TR 25.401: "UTRAN Overall Description".
- [18] 3GPP TS 25.101: "UE Radio transmission and Reception (FDD)".
- [19] 3GPP TS 25.104: "UTRA (BS) FDD; Radio transmission and Reception".
- [20] 3GPP TS 25.133: " Requirements for Support of Radio Resource Management (FDD)"
- [21] 3GPP TS 25.225: " Physical layer – Measurements (TDD)".

---

## 3 Definitions and Abbreviations

### 3.1 Definitions

For the purposes of the present document, the following terms and definitions apply.

cell portion: a part of a cell that is covered by a specific beam antenna radiation pattern. Cell portions are semistatic and are not necessarily analogue to the actual beams transmitted and received at Node B.

### 3.2 Abbreviations

For the purposes of the present document, the following abbreviations apply:

BER	Bit Error Rate
BLER	Block Error Rate
Ec/No	Received energy per chip divided by the power density in the band
ISCP	Interference Signal Code Power
RL	Radio Link
RSCP	Received Signal Code Power
RSSI	Received Signal Strength Indicator
SIR	Signal to Interference Ratio

### 5.1.10 UE Rx-Tx time difference

<b>Definition</b>	The difference in time between the UE uplink DPCCH/DPDCH frame transmission and the first detected path (in time), of the downlink DPCH frame from the measured radio link. Type 1 and Type 2 are defined. For Type 1, the reference Rx path shall be the first detected path (in time) amongst the paths (from the measured radio link) used in the demodulation process. For Type 2, the reference Rx path shall be the first detected path (in time) amongst all paths (from the measured radio link) detected by the UE. The reference path used for the measurement may therefore be different for Type 1 and Type 2. The reference point for the UE Rx-Tx time difference shall be the antenna connector of the UE. Measurement shall be made for each cell included in the active set.
<b>Applicable for</b>	CELL_DCH intra

### 5.1.11 Observed time difference to GSM cell

<b>Definition</b>	<p>The Observed time difference to GSM cell is defined as: <math>T_{RxGSMj} - T_{RxSFNi}</math>, where:</p> <p><math>T_{RxSFNi}</math> is the time at the beginning of the P-CCPCH frame with SFN=0 from cell i. Cell i is an intra-frequency cell.</p> <p><math>T_{RxGSMj}</math> is the time at the beginning of the GSM BCCH 51-multiframe from GSM frequency j received closest in time after the time <math>T_{RxSFNi}</math>. If the next GSM multiframe is received exactly at <math>T_{RxSFNi}</math> then <math>T_{RxGSMj} = T_{RxSFNi}</math> (which leads to <math>T_{RxGSMj} - T_{RxSFNi} = 0</math>). The reference point for the Observed time difference to GSM cell shall be the antenna connector of the UE.</p> <p>The beginning of the GSM BCCH 51-multiframe is defined as the beginning of the first tail bit of the frequency correction burst in the first TDMA-frame of the GSM BCCH 51-multiframe, i.e. the TDMA-frame following the IDLE-frame.</p> <p>The reported time difference is calculated from the actual measurement in the UE. The actual measurement shall be based on:</p> <p><math>T_{MeasGSM,j}</math>: The start of the first tail bit of the most recently received GSM SCH on frequency j</p> <p><math>T_{MeasSFN,i}</math>: The start of the last P-CCPCH frame received from cell i before receiving the GSM SCH on frequency j</p> <p>For calculating the reported time difference, the frame lengths are always assumed to be 10 ms for UTRA and (60/13) ms for GSM.</p>
<b>Applicable for</b>	Idle, URA_PCH inter-RAT, CELL_PCH inter-RAT, CELL_DCH inter-RAT

### 5.1.12 UE GPS Timing of Cell Frames for UE positioning

<b>Definition</b>	The timing between cell j and GPS Time Of Week. $T_{UE-GPSj}$ is defined as the time of occurrence of a specified UTRAN event according to GPS time. The specified UTRAN event is the beginning of a particular frame (identified through its SFN) in the first detected path (in time) of the cell j CPICH, where cell j is a cell chosen by the UE. The reference point for $T_{UE-GPSj}$ shall be the antenna connector of the UE.
<b>Applicable for</b>	CELL_FACH intra, CELL_DCH intra

### 5.1.13 UE GPS code phase

<b>Definition</b>	The whole and fractional phase of the spreading code of the $i^{\text{th}}$ GPS satellite signal. The reference point for the GPS code phase shall be the antenna connector of the UE.
<b>Applicable for</b>	Void (this measurement is not related to UTRAN/GSM signals; its applicability is therefore independent of the UE RRC state)

## 5.2 UTRAN measurement abilities

The structure of the table defining a UTRAN measurement quantity is shown below.

Column field	Comment
Definition	Contains the definition of the measurement.

The term "antenna connector" used in this sub-clause to define the reference point for the UTRAN measurements refers to the "BS antenna connector" test port A and test port B as described in [19]. The term "antenna connector" refers to Rx or Tx antenna connector as described in the respective measurement definitions.

### 5.2.1 Received total wide band power

<b>Definition</b>	The received wide band power, including noise generated in the receiver, within the bandwidth defined by the receiver pulse shaping filter. The reference point for the measurement shall be the Rx antenna connector. In case of receiver diversity the reported value shall be linear average of the power in the diversity branches. <a href="#">When cell portions are defined in the cell the received total wide band power shall also be measured for each cell portion.</a>
-------------------	---

### 5.2.2 SIR

<b>Definition</b>	Signal to Interference Ratio, is defined as: $(\text{RSCP}/\text{ISCP}) \times \text{SF}$ . <a href="#">The M measurement shall be performed on the DPCCH of a Radio Link Set. In compressed mode the SIR shall not be measured in the transmission gap. The reference point for the SIR measurements shall be the Rx antenna connector. If the radio link set contains more than one radio link, the reported value shall be the linear summation of the SIR from each radio link of the radio link set. If Rx diversity is used in the Node B for a cell, the SIR for a radio link shall be the linear summation of the SIR from each Rx antenna for that radio link.</a> <a href="#">When cell portions are defined in the cell the SIR shall also be measured for each cell portion.</a>  where:  RSCP = Received Signal Code Power, unbiased measurement of the received power on one code. ISCP = Interference Signal Code Power, the interference on the received signal. SF=The spreading factor used on the DPCCH.
-------------------	---

### 5.2.3 SIR<sub>error</sub>

<b>Definition</b>	SIR <sub>error</sub> = SIR - SIR <sub>target_ave</sub> , where:  SIR = the SIR measured by UTRAN, defined in section 5.2, given in dB.  SIR <sub>target_ave</sub> = the SIR <sub>target</sub> averaged over the same time period as the SIR used in the SIR <sub>error</sub> calculation. In compressed mode SIR <sub>target</sub> =SIR <sub>cm_target</sub> shall be used when calculating SIR <sub>target_ave</sub> . In compressed mode the SIR <sub>target_ave</sub> shall not be calculated over the transmission gap. The averaging of SIR <sub>target</sub> shall be made in a linear scale and SIR <sub>target_ave</sub> shall be given in dB.
-------------------	--

## 5.2.4 Transmitted carrier power

<b>Definition</b>	Transmitted carrier power, is the ratio between the total transmitted power on one DL carrier from one UTRAN access point, and the maximum transmission power possible to use on that DL carrier at this moment of time. Total transmission power is the mean power [W] on one carrier from one UTRAN access point. Maximum transmission power is the mean power [W] on one carrier from one UTRAN access point when transmitting at the configured maximum power for the cell. Measurement shall be possible on any carrier transmitted from the UTRAN access point. The reference point for the transmitted carrier power measurement shall be the Tx antenna connector. In case of Tx diversity the transmitted carrier power for each branch shall be measured and the maximum of the two values shall be reported to higher layers, i.e. only one value will be reported to higher layers. <a href="#"><u>When cell portions are defined in the cell the transmitted carrier power for each cell portion shall be measured also and reported to higher layers. In that case, the maximum transmission power used in the computation shall be the same as defined above.</u></a>
-------------------	--

## 5.2.5 Transmitted code power

<b>Definition</b>	Transmitted code power, is the transmitted power on one channelisation code on one given scrambling code on one given carrier. Measurement shall be possible on the DPCCH-field of any dedicated radio link transmitted from the UTRAN access point and shall reflect the power on the pilot bits of the DPCCH-field. When measuring the transmitted code power in compressed mode all slots shall be included in the measurement, e.g. also the slots in the transmission gap shall be included in the measurement. The reference point for the transmitted code power measurement shall be the Tx antenna connector. In case of Tx diversity the transmitted code power for each branch shall be measured and summed together in [W].
-------------------	---

## 5.2.6 Transport channel BER

<b>Definition</b>	The transport channel BER is an estimation of the average bit error rate (BER) of the DPDCH data of a Radio Link Set. The transport channel (TrCH) BER is measured from the data considering only non-punctured bits at the input of the channel decoder in Node B. It shall be possible to report an estimate of the transport channel BER for a TrCH after the end of each TTI of the TrCH. The reported TrCH BER shall be an estimate of the BER during the latest TTI for that TrCH.
-------------------	--

## 5.2.7 Physical channel BER

<b>Definition</b>	The Physical channel BER is an estimation of the average bit error rate (BER) on the DPCCH of a Radio Link Set. An estimate of the Physical channel BER shall be possible to be reported after the end of each TTI of any of the transferred TrCHs. The reported physical channel BER shall be an estimate of the BER averaged over the latest TTI of the respective TrCH.
-------------------	--

## 5.2.8 Round trip time

<b>Definition</b>	Round trip time (RTT), is defined as $RTT = T_{RX} - T_{TX}, \text{ where}$ <p><math>T_{TX}</math> = The time of transmission of the beginning of a downlink DPCH frame to a UE. The reference point for <math>T_{TX}</math> shall be the Tx antenna connector.</p> <p><math>T_{RX}</math> = The time of reception of the beginning (the first detected path, in time) of the corresponding uplink DPCCH/DPDCH frame from the UE. The reference point for <math>T_{RX}</math> shall be the Rx antenna connector.</p> <p>Measurement shall be possible on DPCH for each RL transmitted from an UTRAN access point and DPDCH/DPCCH for each RL received in the same UTRAN access point.</p>
-------------------	--

## 5.2.9 UTRAN GPS Timing of Cell Frames for UE positioning

<b>Definition</b>	$T_{\text{UTRAN-GPS}}$ is defined as the time of the occurrence of a specified UTRAN event according to GPS Time Of Week. The specified UTRAN event is the beginning of the transmission of a particular frame in the cell. The reference point for $T_{\text{UTRAN-GPS}}$ shall be the Tx antenna connector.
-------------------	---

## 5.2.10 PRACH/PCPCH Propagation delay

<b>Definition</b>	Propagation delay is defined as one-way propagation delay as measured during either PRACH or PCPCH access:  <u>PRACH :</u>  Propagation delay = $(T_{\text{RX}} - T_{\text{TX}} - 2560)/2$ , where: $T_{\text{TX}}$ = The transmission time of AICH access slot (n-2-AICH transmission timing), where $0 \leq (n-2\text{-AICH Transmission Timing}) \leq 14$ and AICH_Transmission_Timing can have values 0 or 1. The reference point for $T_{\text{TX}}$ shall be the Tx antenna connector. $T_{\text{RX}}$ = The time of reception of the beginning (the first detected path, in time) of the PRACH message from the UE at PRACH access slot n. The reference point for $T_{\text{RX}}$ shall be the Rx antenna connector.  <u>PCPCH:</u>  Propagation delay = $(T_{\text{RX}} - T_{\text{TX}} - (L_{\text{pc-preamble}} + 1)*2560 - (k-1)*38400)/2$ , where $T_{\text{TX}}$ = The transmission time of CD-ICH at access slot (n-2-T <sub>cpch</sub> ), where $0 \leq (n-2-T_{\text{cpch}}) \leq 14$ and T <sub>cpch</sub> can have values 0 or 1. The reference point for $T_{\text{TX}}$ shall be the Tx antenna connector. $T_{\text{RX}}$ = The time of reception of the first chip (the first detected path, in time) of the kth frame of the PCPCH message from the UE, where $k \in \{1, 2, \dots, N_{\text{Max\_frames}}\}$ . The reference point for $T_{\text{RX}}$ shall be the Rx antenna connector. $N_{\text{max\_frames}}$ is a higher layer parameter and defines the maximum length of the PCPCH message. The PCPCH message begins at uplink access slot $(n+L_{\text{pc-preamble}}/2)$ , where $0 \leq (n + L_{\text{pc-preamble}}/2) \leq 14$ and where $L_{\text{pc-preamble}}$ can have values 0 or 8.
-------------------	--

## 5.2.11 Acknowledged PRACH preambles

<b>Definition</b>	The Acknowledged PRACH preambles measurement is defined as the total number of acknowledged PRACH preambles per access frame per PRACH. This is equivalent to the number of positive acquisition indicators transmitted per access frame per AICH.
-------------------	--

## 5.2.12 Detected PCPCH access preambles

<b>Definition</b>	The detected PCPCH access preambles measurement is defined as the total number of detected access preambles per access frame on the PCPCHs belonging to a CPCH set.
-------------------	---

## 5.2.13 Acknowledged PCPCH access preambles

<b>Definition</b>	The Acknowledged PCPCH access preambles measurement is defined as the total number of acknowledged PCPCH access preambles per access frame on the PCPCHs belonging to a SF. This is equivalent to the number of positive acquisition indicators transmitted for a SF per access frame per AP-AICH.
-------------------	--

### 5.2.14 SFN-SFN observed time difference

<b>Definition</b>	<p>The relative timing difference between cell j and cell i, defined as <math>T_{CPICHRxj} - T_{CPICHRx_i}</math>, where:</p> <p><math>T_{CPICHRxj}</math> is the time when the LMU receives the beginning of one Primary CPICH frame from cell j and</p> <p><math>T_{CPICHRx_i}</math> is the time when the LMU receives the beginning of the Primary CPICH frame from cell i that is closest in time to the beginning of Primary CPICH frame received from cell j.</p> <p>The reference point for the measurements shall be the Rx antenna connector.</p>
-------------------	---

### 5.2.15 Transmitted carrier power of all codes not used for HS-PDSCH or HS-SCCH transmission

<b>Definition</b>	<p>Transmitted carrier power of all codes not used for HS-PDSCH or HS-SCCH transmission is the ratio between the total transmitted power of all codes not used for HS-PDSCH or HS-SCCH transmission on one DL carrier from one UTRAN access point, and the maximum transmission power possible to use on that DL carrier at this moment of time. Total transmission power of all codes not used for HS-PDSCH or HS-SCCH transmission is the mean power [W] of all codes not used for HS-PDSCH or HS-SCCH transmission on one carrier from one UTRAN access point. Maximum transmission power is the mean power [W] on one carrier from one UTRAN access point when transmitting at the configured maximum power for the cell. The measurement shall be possible on any carrier transmitted from the UTRAN access point. The reference point for the transmitted carrier power measurement of all codes not used for HS-PDSCH or HS-SCCH transmission shall be the Tx antenna connector. In case of Tx diversity the transmitted carrier power of all codes not used for HS-PDSCH or HS-SCCH transmission for each branch shall be measured and the maximum of the two values shall be reported to higher layers, i.e. only one value will be reported to higher layers. <a href="#"><u>When cell portions are defined in the cell the transmitted carrier power of all codes not used for HS-PDSCH or HS-SCCH transmission for each cell portion shall be measured also and reported to higher layers. In that case the maximum transmission power used in the computation shall be the same as defined above.</u></a></p>
-------------------	--

**3GPP TSG-RAN3 Meeting #36**  
**Paris, France, 19<sup>th</sup> – 23<sup>rd</sup>, May 2003**

**Tdoc #R3-030xxx**

CR-Form-v7

## CHANGE REQUEST

# **25.423 CR 817** # rev **2** # Current version: **5.5.0** #

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the # symbols.

**Proposed change affects:** UICC apps #  ME #  Radio Access Network  Core Network #

<b>Title:</b>	# Phase Reference Signalling Support	
<b>Source:</b>	# Nokia	
<b>Work item code:</b>	# TEIX	<b>Date:</b> # 19/05/2003
<b>Category:</b>	# <b>F</b> Use <u>one</u> of the following categories: <b>F</b> (correction) <b>A</b> (corresponds to a correction in an earlier release) <b>B</b> (addition of feature), <b>C</b> (functional modification of feature) <b>D</b> (editorial modification) Detailed explanations of the above categories can be found in 3GPP <a href="#">TR 21.900</a> .	<b>Release:</b> # Rel-X Use <u>one</u> of the following releases: 2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) Rel-4 (Release 4) Rel-5 (Release 5) Rel-6 (Release 6)

<b>Reason for change:</b>	# According to the current understanding in RAN1, the Node B is not provided with knowledge over the lub of which phase reference a certain UE is using.  This problem can be avoided by introducing phase reference signalling over lub and lur. Note that the phase reference is one of <ul style="list-style-type: none"><li>▪ P-CPICH</li><li>▪ one of possibly several S-CPICHs</li><li>▪ dedicated pilot</li></ul> as specified in 25.211.  During RAN1 and RNA3 unofficial joint session, it turned out that without the measurement, in principle S-CPICH cannot be used. Thus the measurement enhancement(which has been studied under Rel-6 WI) is indeed a correction of incomplete feature. To completed Rel99 beamforming feature, Best Received Cell Portion measurement as well as other measurements for cell portion are included in this CR.
---------------------------	--

<b>Summary of change:</b>	# Rev.1 <ul style="list-style-type: none"><li>- RL Addition is removed</li><li>- Best Received Cell Portion is included in UL Signalling Transfer.</li><li>- RL Parameter Update Procedure is included to indicate to SRNC to change the reference phase.</li></ul>
---------------------------	---

Phase reference signalling is added in Radio Link Setup, Radio Link Addition and Radio Link Reconfiguration procedures.

**Consequences if not approved:**

- ⌘ RAN1 has identified the following problems if the Node B does not have knowledge of the phase reference used by a certain UE:
- Node B beam-forming is impossible without knowledge of the phase reference used by each UE.
  - Proper operation of HSDPA in Rel-5 requires the suggested signalling.

Impact Analysis:

Impact assessment towards the previous version of the specification (same release):

This CR has isolated impact with the previous version of the specification. The change is limited only to the phase reference functionality.

Impact assessment towards the previous release of the specification:

This CR has no impact on previous releases because the functionality is introduced in backward compatible way.

**Clauses affected:** ⌘ 8.2.1.2, 8.3.4.2, 8.3.7.2, 8.3.21.1, 8.3.21.2, 9.1.3.1, 9.1.4.1, 9.1.5.1, 9.1.11.1, 9.1.12.1, 9.1.16.1, 9.1.58.1, new 9.2.2.x1, new 9.2.2.x2, new 9.2.2.x3, new 9.2.2.x4, new 9.2.2.x5, new 9.2.2.x7, 9.3.3, 9.3.4, 9.3.6

<b>Other specs affected:</b>	Y	N	Other core specifications Test specifications O&M Specifications	⌘ CR836 TS 25.433 v5.4.0 CR138 TS 25.215 v5.3.0
	X			
		X		

**Other comments:** ⌘

**How to create CRs using this form:**

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/>. For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

## 8.3 DCH Procedures

### 8.3.1.2 Successful Operation

/\* partly omitted \*/

#### Physical Channels Handling:

##### [FDD - Compressed Mode]:

[FDD - If the RADIO LINK SETUP REQUEST message includes the *Transmission Gap Pattern Sequence Information IE*, the DRNS shall store the information about the Transmission Gap Pattern Sequences to be used in the Compressed Mode Configuration. This Compressed Mode Configuration shall be valid in the DRNS until the next Compressed Mode Configuration is configured in the DRNS or the last Radio Link is deleted.]

[FDD - If the RADIO LINK SETUP REQUEST message includes the *Transmission Gap Pattern Sequence Information IE* and the *Active Pattern Sequence Information IE*, the DRNS shall use the information to activate the indicated Transmission Gap Pattern Sequence(s) in the new RL. The received *CM Configuration Change CFN IE* refers to latest passed CFN with that value. The DRNS shall treat the received *TGCFN IE*s as follows:]

- [FDD - If any received *TGCFN IE* has the same value as the received *CM Configuration Change CFN IE*, the DRNS shall consider the concerned Transmission Gap Pattern Sequence as activated at that CFN.]
- [FDD - If any received *TGCFN IE* does not have the same value as the received *CM Configuration Change CFN IE* but the first CFN after the CM Configuration Change CFN with a value equal to the *TGCFN IE* has already passed, the DRNS shall consider the concerned Transmission Gap Pattern Sequence as activated at that CFN.]
- [FDD - For all other Transmission Gap Pattern Sequences included in the *Active Pattern Sequence Information IE*, the DRNS shall activate each Transmission Gap Pattern Sequence at the first CFN after the CM Configuration Change CFN with a value equal to the *TGCFN IE* for the Transmission Gap Pattern Sequence.]

[FDD- If the *Downlink Compressed Mode Method IE* in one or more Transmission Gap Pattern Sequence is set to "SF/2" in the RADIO LINK SETUP REQUEST message, the DRNS shall include the *Transmission Gap Pattern Sequence Scrambling Code Information IE* in the RADIO LINK SETUP RESPONSE message indicating for each DL Channelisation Code whether the alternative scrambling code shall be used or not.]

##### [FDD - DL Code Information]:

[FDD - When more than one DL DPDCH are assigned per RL, the segmented physical channel shall be mapped on to DL DPDCHs according to [8]. When  $p$  number of DL DPDCHs are assigned to each RL, the first pair of DL Scrambling Code and FDD DL Channelisation Code Number corresponds to "*PhCH number 1*", the second to "*PhCH number 2*", and so on until the  $p$ th to "*PhCH number  $p$* ".]

##### [FDD – Phase Reference Handling]:

[FDD – If the RADIO LINK SETUP REQUEST message includes the *UE Support Of Dedicated Pilots For Channel Estimation IE*, the DRNC shall assume that dedicated pilots may be used for channel estimation with DCH or DSCH.]

[FDD – If the RADIO LINK SETUP REQUEST message includes the *UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH IE*, the DRNC shall assume that dedicated pilots may be used for channel estimation with HS-DSCH.]

[FDD – If Primary CPICH shall not be used as a Phase Reference for this Radio Link, the DRNC shall include the *Primary CPICH Usage For Channel Estimation IE* set to the value "Primary CPICH shall not be used" in the RADIO LINK SETUP RESPONSE message.]

[FDD – If Secondary CPICH may be used as a Phase Reference for this Radio Link, the DRNC shall include the *Secondary CPICH Information IE* in the RADIO LINK SETUP RESPONSE message.]

**General:**

[FDD - If the *Propagation Delay* IE is included, the DRNS may use this information to speed up the detection of UL synchronisation on the Uu interface.]

[FDD - If the received *Limited Power Increase* IE is set to "Used", the DRNS shall, if supported, use Limited Power Increase according to ref. [10] subclause 5.2.1 for the inner loop DL power control.]

[FDD - If the RADIO LINK SETUP REQUEST message does not include the *Length of TFCI2* IE and the *Split type* IE is present with the value "Hard", then the DRNS shall assume the length of the TFCI (field 2) is 5 bits.]

[FDD - If the RADIO LINK SETUP REQUEST message includes *Split Type* IE, then the DRNS shall apply this information to the new configuration of TFCI.]

[FDD - If the RADIO LINK SETUP REQUEST message includes the *Length of TFCI2* IE, the DRNS shall apply this information to the length of TFCI(field 2).]

[TDD - If the RADIO LINK SETUP REQUEST message includes the *Maximum Number of DL Physical Channels per Timeslot* IE the DRNC shall take this value into account when allocating physical resources, otherwise the DRNC can assume that this UE capability is consistent with the other signalled UE capabilities.]

[1.28Mcps TDD - If the RADIO LINK SETUP REQUEST message includes the *Support for 8PSK* IE within the *DL Physical Channel Information IE or UL Physical Channel Information IE*, the DRNC shall take this into account in the specified direction when allocating physical resources, otherwise the DRNC can assume that this UE does not support 8PSK resource allocation.]

**Radio Link Handling:****Diversity Combination Control:**

[FDD - The *Diversity Control Field* IE indicates for each RL except for the first RL whether the DRNS shall combine the RL with any of the other RLs or not.

- If the *Diversity Control Field* IE is set to "May" (be combined with another RL), the DRNS shall decide for any of the alternatives.
- If the *Diversity Control Field* IE is set to "Must", the DRNS shall combine the RL with one of the other RL.
- If the *Diversity Control Field* IE is set to "Must not", the DRNS shall not combine the RL with any other existing RL.

When an RL is to be combined, the DRNS shall choose which RL(s) to combine it with.]

[FDD - In the RADIO LINK SETUP RESPONSE message, the DRNC shall indicate for each RL with the Diversity Indication in the *RL Information Response* IE whether the RL is combined or not.]

- [FDD - In case of not combining with a RL previously listed in the RADIO LINK SETUP RESPONSE message or for the first RL in the RADIO LINK SETUP RESPONSE message, the DRNC shall include in the *DCH Information Response* IE in the RADIO LINK SETUP RESPONSE message the *Binding ID* IE and *Transport Layer Address* IE for the transport bearer to be established for each DCH of this RL.]
- [FDD - Otherwise in case of combining, the *RL ID* IE indicates (one of) the RL(s) previously listed in this RADIO LINK SETUP RESPONSE message with which the concerned RL is combined.]

[TDD - The DRNC shall always include in the RADIO LINK SETUP RESPONSE message both the *Transport Layer Address* IE and the *Binding ID* IE for the transport bearer to be established for each DCH, DSCH and USCH of the RL.]

In the case of a set of co-ordinated DCHs requiring a new transport bearer the *Binding ID* IE and the *Transport Layer Address* IE shall be included in the RADIO LINK SETUP RESPONSE message for only one of the DCHs in the set of co-ordinated DCHs.

**[FDD-Transmit Diversity]:**

[FDD - If the cell in which the RL is being set up is capable to provide Close loop Tx diversity, the DRNC shall include the *Closed Loop Timing Adjustment Mode* IE in the RADIO LINK SETUP RESPONSE message indicating the configured Closed loop timing adjustment mode of the cell.]

[FDD - When the *Diversity Mode* IE is set to "STTD", "Closed loop mode1", or "Closed loop mode2", the DRNC shall activate/deactivate the Transmit Diversity for each Radio Link in accordance with the *Transmit Diversity Indicator* IE].

#### **DL Power Control:**

[FDD - If both the *Initial DL TX Power* IE and *Uplink SIR Target* IE are included in the message, the DRNS shall use the indicated DL TX Power and Uplink SIR Target as initial value. If the value of the *Initial DL TX Power* IE is outside the configured DL TX power range, the DRNS shall apply these constrains when setting the initial DL TX power. The DRNS shall also include the configured DL TX power range defined by *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the RADIO LINK SETUP RESPONSE message. The DRNS shall not transmit with a higher power than indicated by the *Maximum DL TX Power* IE or lower than indicated by the *Minimum DL TX Power* IE on any DL DPCH of the RL except during compressed mode, when the  $\delta P_{curr}$ , as described in ref.[10] subclause 5.2.1.3, shall be added to the maximum DL power for the associated compressed frame.]

[FDD - If both the *Initial DL TX Power* and the *Uplink SIR Target* IEs are not included in the RADIO LINK SETUP REQUEST message, then DRNC shall determine the initial Uplink SIR Target and include it in the *Uplink SIR Target* IE in the RADIO LINK SETUP RESPONSE message.]

[TDD - The DRNC shall use the *Uplink SIR Target CCTrCH* IEs in the RADIO LINK SETUP RESPONSE message to indicate for any UL CCTrCH an Uplink SIR Target value in case this is deviating from the value included in the *Uplink SIR Target* IE specified for the Radio Link. If in any [3.84Mcps TDD - *UL CCTrCH Information* IE] [1.28Mcps TDD - *UL CCTrCH Information LCR* IE] the *Uplink SIR Target CCTrCH* IE is not included, the value of the *Uplink SIR Target* IE shall apply to the respective UL CCTrCH.]

[FDD - If the *Primary CPICH Ec/No* IE is present, the DRNC should use the indicated value when deciding the Initial DL TX Power. If the *Enhanced Primary CPICH Ec/No* IE is present, the DRNC should use the indicated value when deciding the Initial DL Tx Power.]

[TDD - If the *Primary CCPCH RSCP* IE [3.84Mcps TDD -and/or the *DL Time Slot ISCP Info* IE] [1.28Mcps TDD - and/or the *DL Time Slot ISCP Info LCR* IE] are present, the DRNC should use the indicated values when deciding the Initial DL TX Power. for the Radio Link. The DRNS shall use the indicated DL Timeslot ISCP when determining the initial DL power per timeslot as specified in [22], i.e. it shall reduce the DL TX power in those downlink timeslots of the radio link where the interference is low, and increase the DL TX power in those timeslots where the interference is high, while keeping the total downlink power in the radio link unchanged.]

[3.84 Mcps TDD - The DL TX power upper and lower limit is configured in the following way: The DRNC shall include the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the RADIO LINK SETUP RESPONSE message. If the maximum or minimum power needs to be different for particular DCH type CCTrCHs, the DRNC shall include the value(s) for that CCTrCH in the *CCTrCH Maximum DL TX Power* IE and *CCTrCH Minimum DL TX Power* IE. The DRNS shall not transmit with a higher power than indicated by the appropriate *Maximum DL TX Power* IE/*CCTrCH Maximum DL TX Power* IE or lower than indicated by the appropriate *Minimum DL TX Power* IE/*CCTrCH Minimum DL TX Power* IE on any DL DPCH within each CCTrCH of the RL.]

[1.28 Mcps TDD - The DL TX power upper and lower limit is configured in the following way: The DRNC shall include the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the RADIO LINK SETUP RESPONSE message. If the maximum or minimum power needs to be different for particular timeslots within a DCH type CCTrCH, the DRNC shall include the value(s) for that timeslot in the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE within the *DL Timeslot Information LCR* IE. The DRNS shall not transmit with a higher power than indicated by the appropriate *Maximum DL TX Power* IE or lower than indicated by the appropriate *Minimum DL TX Power* IE on any DL DPCH within each timeslot of the RL.]

[1.28McpsTDD - If the *TSTD Support Indicator* IE is present, the DRNS shall apply this information when configuring the transmit diversity for the new radio link.]

[FDD - The DRNS shall start any DL transmission using the indicated DL TX power level (if received) or the decided DL TX power level on each DL channelisation code of a RL until UL synchronisation is

achieved on the Uu interface for the concerned RLS or Power Balancing is activated. No inner loop power control or power balancing shall be performed during this period. The DL power shall then vary according to the inner loop power control (see ref.[10] subclause 5.2.1.2) and the power control procedure (see 8.3.15.).]

[TDD - The DRNS shall start any DL transmission using the decided DL TX power level on each DL channelisation code and on each Time Slot of a RL until UL synchronisation is achieved on the Uu interface for the concerned RL. No inner loop power control shall be performed during this period. Then after UL synchronisation, the DL power shall vary according to the inner loop power control (see ref. [22] subclause 4.2.3.3).]

[FDD - If the received *Inner Loop DL PC Status* IE is set to "Active", the DRNS shall activate the inner loop DL power control for all RLs. If *Inner Loop DL PC Status* IE is set to "Inactive", the DRNS shall deactivate the inner loop DL power control for all RLs according to ref. [10].]

[FDD - If the *DPC Mode* IE is present in the RADIO LINK SETUP REQUEST message, the DRNC shall apply the DPC mode indicated in the message, and be prepared that the DPC mode may be changed during the life time of the RL. If the *DPC Mode* IE is not present in the RADIO LINK SETUP REQUEST message, DPC mode 0 shall be applied (see ref. [10]).]

[FDD - If the RADIO LINK SETUP REQUEST message includes the *DL Power Balancing Information* IE and the *Power Adjustment Type* IE is set to "Common" or "Individual", the DRNS shall activate the power balancing, if activation of power balancing by the RADIO LINK SETUP REQUEST message is supported, according to subclause 8.3.15, using the *DL Power Balancing Information* IE. If the DRNS starts the DL transmission and the activation of the power balancing at the same CFN, the initial power of the power balancing i.e.  $P_{init}$  shall be set to the power level indicated by the *Initial DL TX Power* IE (if received) or the decided DL TX power level on each DL channelisation code of a RL based on the *Primary CPICH Ec/No* IE or the *Enhanced Primary CPICH Ec/No* IE.]

[FDD - If activation of power balancing by the RADIO LINK SETUP REQUEST message is supported by the DRNS, the DRNC shall include the *DL Power Balancing Activation Indicator* IE in the *RL Information Response* IE in the RADIO LINK SETUP RESPONSE message.]

### Neighbouring Cell Handling:

If there are UMTS neighbouring cell(s) to the cell in which a Radio Link was established then:

- The DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Neighbouring FDD Cell Information* IE and/or *Neighbouring TDD Cell Information* IE in the *Neighbouring UMTS Cell Information* IE for each neighbouring FDD cell and/or TDD cell respectively. In addition, if the information is available, the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Frame Offset* IE, *Primary CPICH Power* IE, *Cell Individual Offset* IE, *STTD Support Indicator* IE, *Closed Loop Mode1 Support Indicator* IE, *Closed Loop Mode2 Support Indicator* IE, *Coverage Indicator* IE, *Antenna Co-location Indicator* IE and *HCS Prio* IE in the *Neighbouring FDD Cell Information* IE, and the *Frame Offset* IE, *Cell Individual Offset* IE, *DPCH Constant Value* IE, the *PCCPCH Power* IE, *Coverage Indicator* IE, *Antenna Co-location Indicator* IE and *HCS Prio* IE in the *Neighbouring TDD Cell Information* IE or the *Neighbouring TDD Cell Information LCR* IE. If the *Neighbouring TDD Cell Information* IE includes the *Sync Case* IE for the set to "Case1", the DRNC shall include the *Time Slot For SCH* IE in the *Neighbouring TDD Cell Information* IE. If the *Neighbouring TDD Cell Information* IE includes *Sync Case* IE set to "Case2", the DRNC shall include the *SCH Time Slot* IE in the *Neighbouring TDD Cell Information* IE.
- If a UMTS neighbouring cell is not controlled by the same DRNC, the DRNC shall also include in the RADIO LINK SETUP RESPONSE message the *CN PS Domain Identifier* IE and/or *CN CS Domain Identifier* IE which are the identifiers of the CN nodes connected to the RNC controlling the UMTS neighbouring cell.
- If the information is available, the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *DPC Mode Change Support Indicator* IE for each neighbour cell in the *Neighbouring FDD Cell Information* IE
- [FDD- The DRNC shall include the *Flexible Hard Split Support Indicator* IE if the DRNC is aware that the neighbouring cell supports *Flexible Hard Split* mode.]

- The DRNC shall include the *Cell Capability Container FDD IE*, the *Cell Capability Container TDD IE* and/or the *Cell Capability Container TDD LCR IE* if the DRNC is aware that the neighbouring cell supports any functionalities listed in 9.2.2.D, 9.2.3.1a and 9.2.3.1b.
- For the UMTS neighbouring cells which are controlled by the DRNC, the DRNC shall report in the RADIO LINK SETUP RESPONSE message the restriction state of those cells, otherwise the *Restriction StateIndicator IE* may be absent. The DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Restriction StateIndicator IE* for the neighbouring cells which are controlled by the DRNC in the *Neighbouring FDD Cell Information IE*, the *Neighbouring TDD Cell Information IE* and the *Neighbouring TDD Cell Information LCR IE*.
- If available, the DRNC shall include the *SNA Information IE* for the concerned neighbouring cells in the *Neighbouring FDD Cell Information IE*, the *Neighbouring TDD Cell Information IE* and the *Neighbouring TDD Cell Information LCR IE*.

If there are GSM neighbouring cells to the cell(s) where a radio link is established, the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Neighbouring GSM Cell Information IE* for each of the GSM neighbouring cells. If available the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Cell Individual Offset IE*, and if the *Cell Individual Offset IE* alone cannot represent the value of the offset, the DRNC shall also include the *Extended GSM Cell Individual Offset IE* in the *Neighbouring GSM Cell Information IE*. If available the DRNC shall also include in the RADIO LINK SETUP RESPONSE message the *Coverage Indicator IE*, *Antenna Co-location Indicator IE* and *HCS Prio IE* in the *Neighbouring GSM Cell Information IE*. If available, the DRNC shall also include the *SNA Information IE* for the concerned neighbouring cells in the *Neighbouring GSM Cell Information IE*.

When receiving the *SNA Information IE* in the RADIO LINK SETUP RESPONSE message, the SRNC should use it to restrict cell access based on SNA information. See also [40] for a broader description of the SNA access control.

If there are GERAN neighbouring cells to the cell(s) where a radio link is established, the DRNC shall include the *GERAN Cell Capability IE* in the *Neighbouring GSM Cell Information IE* that is included in the RADIO LINK SETUP RESPONSE message for each of the GERAN cells.

If there are GERAN Iu-mode neighbouring cells to the cell(s) where a radio link is established, the DRNC shall include, if available, the *GERAN Classmark IE* in the *Neighbouring GSM Cell Information IE* that is included in the RADIO LINK SETUP RESPONSE message for each of the GERAN Iu-mode neighbouring cells. Ref. [39] defines when the transmission of the *GERAN Classmark IE* will be required at the initiation of the Relocation Preparation procedure.

#### **[1.28Mcps TDD - Uplink Synchronisation Parameters LCR]:**

[If the *Uplink Synchronisation Parameters LCR IE* is present, the DRNC shall use the indicated values of *Uplink synchronisation stepsize IE* and *Uplink synchronisation frequency IE* when evaluating the timing of the UL synchronisation.]

#### **[1.28Mcps TDD - Uplink Timing Advance Control LCR]:**

[1.28Mcps TDD - The DRNC shall include the *Uplink Timing Advance Control LCR IE* in the RADIO LINK SETUP RESPONSE message.]

#### **General:**

If the RADIO LINK SETUP REQUEST message includes the *RL Specific DCH Information IE*, the DRNC may use the transport layer address and the binding identifier received from the SRNC when establishing a transport bearer for the DCH or the set of co-ordinated DCHs.

[FDD - If the RADIO LINK SETUP REQUEST message includes the *SSDT Cell Identity IE* and the *S-Field Length IE*, the DRNS shall activate SSDT, if supported, using the *SSDT Cell Identity IE*, *S-Field Length IE* and *SSDT Cell Identity Length IE*.]

[FDD - If the RADIO LINK SETUP REQUEST message includes the *Qth Parameter IE* in addition to the *SSDT Cell Identity IE*, the DRNS shall use the *Qth Parameter IE*, if Qth signalling is supported, when SSDT is activated in the concerned new RL.]

[FDD - If the RADIO LINK SETUP REQUEST message includes the *SSDT Cell Identity for EDSCHPC IE*, the DRNS shall activate enhanced DSCH power control, if supported, using the *SSDT Cell Identity for EDSCHPC IE* and *SSDT Cell Identity Length IE* as well as *Enhanced DSCH PC IE* in accordance with ref. [10] subclause 5.2.2. If the RADIO LINK SETUP REQUEST message includes both *SSDT Cell Identity IE* and *SSDT Cell Identity for EDSCHPC IE*, then the DRNS shall ignore the *SSDT Cell Identity for EDSCHPC IE*. If the enhanced DSCH power control is activated and the *TFCI PC Support Indicator IE* is set to "TFCI PC Mode 2 Supported", the primary/secondary status determination in the enhanced DSCH power control shall be applied to the TFCI power control in DSCH hard split mode.]

[FDD - If the *DRAC Control IE* is set to "requested" in the RADIO LINK SETUP REQUEST message for at least one DCH and if the DRNS supports the DRAC, the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Secondary CCPCH Info IE* for the FACH in which the DRAC information is sent, for each Radio Link established in a cell where DRAC is active. If the DRNS does not support DRAC, the DRNC shall not provide these IEs in the RADIO LINK SETUP RESPONSE message.]

If no *D-RNTI IE* was included in the RADIO LINK SETUP REQUEST message, the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *D-RNTI IE*, the *CN PS Domain Identifier IE* and/or the *CN CS Domain Identifier IE* for the CN domains (using LAC and RAC of the current cell) to which the DRNC is connected.

[FDD - If the *D-RNTI IE* was included the RADIO LINK SETUP REQUEST message the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Primary Scrambling Code IE*, the *UL UARFCN IE* and the *DL UARFCN IE*.]

[TDD - If the *D-RNTI IE* was included in the RADIO LINK SETUP REQUEST message the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *UARFCN IE*, the *Cell Parameter ID IE* and the *SCTD Indicator IE*.]

[3.84Mcps TDD - If the *D-RNTI IE* was included in the RADIO LINK SETUP REQUEST message the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Sync Case IE* and if the *Sync Case IE* is set to "Case 2", the DRNC shall also include the *SCH Time Slot IE* in the RADIO LINK SETUP RESPONSE message. If the included *Sync Case IE* is set to "Case1", the DRNC shall also include the *Time Slot For SCH IE*]

[3.84Mcps TDD - The DRNC shall include the *Secondary CCPCH Info TDD IE* in the RADIO LINK SETUP RESPONSE message if at least one *DSCH Information Response IE* or *USCH Information Response IE* is included in the message and at least one DCH is configured for the radio link. The DRNC shall also include the *Secondary CCPCH Info TDD IE* in the RADIO LINK SETUP RESPONSE message if at least one *DSCH Information Response IE* or *USCH Information Response IE* is included in the message and the SHCCH messages for this radio link will be transmitted over a different secondary CCPCH than selected by the UE from system information.]

[1.28 Mcps TDD - The DRNC shall include the *Secondary CCPCH Info TDD LCR IE* in the RADIO LINK SETUP RESPONSE message if at least one *DSCH Information Response LCR IE* or *USCH Information Response LCR IE* is included in the message and at least one DCH is configured for the radio link. The DRNC shall also include the *Secondary CCPCH Info TDD LCR IE* in the RADIO LINK SETUP RESPONSE message if at least one *DSCH Information Response LCR IE* or *USCH Information Response LCR IE* is included in the message and the SHCCH messages for this radio link will be transmitted over a different secondary CCPCH than selected by the UE from system information.]

For each Radio Link established in a cell in which at least one URA Identity is being broadcast, the DRNC shall include in the *URA Information IE* within the RADIO LINK SETUP RESPONSE message URA Information for this cell including the *URA ID IE*, the *Multiple URAs Indicator IE* indicating whether or not multiple URA Identities are being broadcast in the cell, and the *RNC-ID IE*s of all other RNCs that have at least one cell within the URA identified by the *URA ID IE*.

Depending on local configuration in the DRNS, the DRNC may include in the RADIO LINK SETUP RESPONSE message the *UTRAN Access Point Position IE* and the geographical co-ordinates of the cell, represented either by the *Cell GAI IE* or by the *Cell GA Additional Shapes IE*. If the DRNC includes the *Cell GA Additional Shapes IE* in the RADIO LINK SETUP RESPONSE message, it shall also include the *Cell GAI IE*.

If the DRNS need to limit the user rate in the uplink of a DCH due to congestion caused by the UL UTRAN Dynamic Resources (see subclause 9.2.1.79) when starting to utilise a new Radio Link, the DRNC shall

include in the RADIO LINK SETUP RESPONSE message the *Allowed UL Rate* IE in the *DCH Information Response* IE for this Radio Link.

If the DRNS need to limit the user rate in the downlink of a DCH due to congestion caused by the DL UTRAN Dynamic Resources (see subclause 9.2.1.79) when starting to utilise a new Radio Link, the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Allowed DL Rate* IE in the *DCH Information Response* IE for this Radio Link.

If the *Permanent NAS UE Identity* IE is included in the RADIO LINK SETUP REQUEST message, the DRNS shall store the information for the considered UE Context for the life-time of the UE Context.

If the RADIO LINK SETUP REQUEST message includes the *Permanent NAS UE Identity* IE and a *C-ID* IE corresponding to a cell reserved for operator use, the DRNS shall use this information to determine whether it can set up a Radio Link on this cell or not for the considered UE Context.

If the HCS priority information is available in the DRNS, it shall include the *HCS Prio* IE for each of the established RLs in the RADIO LINK SETUP RESPONSE message.

[FDD - If the accessed cell supports TFCI power control, the DRNC shall include the *TFCI PC Support Indicator* IE in the RADIO LINK SETUP RESPONSE message.]

The DRNS shall start receiving on the new RL(s) after the RLs are successfully established.

#### **[FDD - Radio Link Set Handling]:**

[FDD - The *First RLS Indicator* IE indicates if the concerned RL shall be considered part of the first RLS established towards this UE. The DRNS shall use the *First RLS Indicator* IE to determine the initial TPC pattern in the DL of the concerned RL and all RLs which are part of the same RLS, as described in [10], section 5.1.2.2.1.2.]

[FDD - For each RL not having a common generation of the TPC commands in the DL with another RL, the DRNS shall assign to the RL a unique value for the *RL Set ID* IE which uniquely identifies the RL as an RL Set within the UE Context.]

[FDD - For all RLs having a common generation of the TPC commands in the DL with another RL, the DRNS shall assign to each RL the same value for the *RL Set ID* IE which uniquely identifies these RLs as members of the same RL Set within the UE Context.]

[FDD - The UL out-of-sync algorithm defined in ref. [10] shall, for each of the established RL Set(s), use the maximum value of the parameters N\_OUTSYNC\_IND and T\_RLFAILURE that are configured in the cells supporting the radio links of the RL Set. The UL in-sync algorithm defined in [10] shall, for each of the established RL Set(s), use the minimum value of the parameters N\_INSYNC\_IND that are configured in the cells supporting the radio links of the RL Set.]

#### **Response Message:**

Upon receipt of the RADIO LINK SETUP REQUEST message, the DRNS allocates the requested type of channelisation codes and other physical channel resources for each RL and assigns a binding identifier and a transport layer address for each DCH, for each set of co-ordinated DCHs and for each DSCH [TDD - and USCH]. This information shall be sent to the SRNC in the RADIO LINK SETUP RESPONSE message when all the RLs have been successfully established.

After sending the RADIO LINK SETUP RESPONSE message the DRNS shall continuously attempt to obtain UL synchronisation on the Uu interface and start reception on the new RL.

For each RL for which the *Delayed Activation* IE is not included in the RADIO LINK SETUP REQUEST message the DRNS shall:

- [FDD - start transmission on the DL DPDCH(s) of the new RL as specified in ref. [4].]
- [TDD - start transmission on the new RL immediately as specified in ref. [4].]

For each RL for which the *Delayed Activation* IE is included in the RADIO LINK SETUP REQUEST message, the DRNS shall:

- if the *Delayed Activation* IE indicates "Separate Indication":

- not start any DL transmission for the concerned RL on the Uu interface;
- if the *Delayed Activation* IE indicates "CFN":
  - [FDD - start transmission on the DL DPDCH(s) of the new RL as specified in ref. [4], however never before the CFN indicated in the *Activation CFN* IE.]
  - [TDD - start transmission on the new RL at the CFN indicated in the *Activation CFN* IE as specified in ref. [4].]

## 8.3.2 Radio Link Addition

### 8.3.2.2 Successful Operation

*/\* partly omitted \*/*

#### Physical Channels Handling:

##### [FDD-Compressed Mode]:

[FDD - If the RADIO LINK ADDITION REQUEST message includes the *Active Pattern Sequence Information* IE, the DRNS shall use the information to activate the indicated (all ongoing) Transmission Gap Pattern Sequence(s) in the new RL. The received *CM Configuration Change CFN* IE refers to the latest passed CFN with that value. The DRNS shall treat the received *TGCFN* IEs as follows:]

- [FDD - If any received *TGCFN* IE has the same value as the received *CM Configuration Change CFN* IE, the DRNS shall consider the concerned Transmission Gap Pattern Sequence as activated at that CFN.]
- [FDD - If any received *TGCFN* IE does not have the same value as the received *CM Configuration Change CFN* IE but the first CFN after the CM Configuration Change CFN with a value equal to the *TGCFN* IE has already passed, the DRNS shall consider the concerned Transmission Gap Pattern Sequence as activated at that CFN.]
- [FDD - For all other Transmission Gap Pattern Sequences included in the *Active Pattern Sequence Information* IE, the DRNS shall activate each Transmission Gap Pattern Sequence at the first CFN after the CM Configuration Change CFN with a value equal to the *TGCFN* IE for the Transmission Gap Pattern Sequence.]

FDD - If the *Active Pattern Sequence Information* IE is not included, the DRNS shall not activate the ongoing compressed mode pattern in the new RLs, but the ongoing pattern in the existing RL shall be maintained.]

[FDD - If some Transmission Gap Pattern sequences using SF/2 method are initialised in the DRNS, the DRNC shall include the *Transmission Gap Pattern Sequence Scrambling Code Information* IE in the *DL Code Information* IE in the RADIO LINK ADDITION RESPONSE message to indicate the Scrambling code change method that it selects for each channelisation code.]

##### [FDD-DL Code Information]:

[FDD - When more than one DL DPDCH are assigned per RL, the segmented physical channel shall be mapped on to DL DPDCHs according to [8]. When  $p$  number of DL DPDCHs are assigned to each RL, the first pair of DL Scrambling Code and FDD DL Channelisation Code Number corresponds to "*PhCH number 1*", the second to "*PhCH number 2*", and so on until the  $p$ th to "*PhCH number p*".]

##### [TDD - CCTrCH Handling]:

[TDD - If the *UL CCTrCH Information* IE is present, the DRNS shall configure the new UL CCTrCH(s) according to the parameters given in the message.]

[1.28Mcps TDD - If the *UL CCTrCH Information* IE includes the *TDD TPC Uplink Step Size* IE, the DRNS shall configure the uplink TPC step size according to the parameters given in the message, otherwise it shall use the step size configured in other radio link.]

[TDD - If the *DL CCTrCH Information* IE is present, the DRNS shall configure the new DL CCTrCH(s) according to the parameters given in the message.]

[TDD - If the *DL CCTrCH Information* IE includes the *TDD TPC Downlink Step Size* IE, the DRNS shall configure the downlink TPC step size according to the parameters given in the message, otherwise it shall use the step size configured in other radio link.]

##### [FDD – Phase Reference Handling]:

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *UE Support Of Dedicated Pilots For Channel Estimation* IE the DRNC shall assume that the UE supports dedicated pilots for channel estimation with DCH or DSCH.]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH* IE the DRNC shall assume that the UE supports dedicated pilots for channel estimation with HS-DSCH.]

[FDD – If Primary CPICH shall not be used as a Phase Reference for this Radio Link, the DRNC shall include the *Primary CPICH Usage For Channel Estimation* IE set to the value "Primary CPICH shall not be used" in the RADIO LINK ADDITION RESPONSE message.]

[FDD – If Secondary CPICH may be used as a Phase Reference for this Radio Link, the DRNC shall include the *Secondary CPICH Information* IE in the RADIO LINK ADDITION RESPONSE message.]

#### **General:**

[FDD - The DRNS shall use the provided Uplink SIR Target value as the current target for the inner-loop power control.]

#### **Radio Link Handling:**

##### **Diversity Combination Control:**

The *Diversity Control Field* IE indicates for each RL whether the DRNS shall combine the new RL with existing RL(s) or not on the Iur.

- If the *Diversity Control Field* IE is set to "May" (be combined with another RL), the DRNS shall decide for any of the alternatives.
- If the *Diversity Control Field* IE is set to "Must", the DRNS shall combine the RL with one of the other RL. When a new RL is to be combined the DRNS shall choose which RL(s) to combine it with.
- If the *Diversity Control Field* IE is set to "Must not", the DRNS shall not combine the RL with any other existing RL.

In the case of not combining a RL with a RL established with a previous Radio Link Setup or Radio Link Addition Procedure or a RL previously listed in the RADIO LINK ADDITION RESPONSE message, the DRNC shall indicate with the Diversity Indication in the *RL Information Response* IE in the RADIO LINK ADDITION RESPONSE message that no combining is done. In this case the DRNC shall include in the *DCH Information Response* IE both the *Transport Layer Address* IE and the *Binding ID* IE for the transport bearer to be established for each DCH of the RL in the RADIO LINK ADDITION RESPONSE message.

In the case of combining with a RL established with a previous Radio Link Setup or Radio Link Addition Procedure or with a RL previously listed in this RADIO LINK ADDITION RESPONSE message, the DRNC shall indicate with the Diversity Indication in the *RL Information Response* IE in the RADIO LINK ADDITION RESPONSE message that the RL is combined. In this case, the *RL ID* IE indicates (one of) the previously established RL(s) or a RL previously listed in this RADIO LINK ADDITION RESPONSE message with which the new RL is combined.

[TDD - The DRNC shall always include in the RADIO LINK ADDITION RESPONSE message both the *Transport Layer Address* IE and the *Binding ID* IE for the transport bearer to be established for each DSCH and USCH of the RL.]

In the case of a set of co-ordinated DCHs, the DRNC shall include in the RADIO LINK ADDITION RESPONSE message the *Binding ID* IE and the *Transport Layer Address* IE for only one of the DCHs in the set of co-ordinated DCHs.

If the DRNS needs to limit the user rate in the uplink of a DCH due to congestion caused by the UL UTRAN Dynamic Resources (see subclause 9.2.1.79) when starting to utilise a new Radio Link, the DRNC shall include in the RADIO LINK ADDITION RESPONSE message the *Allowed UL Rate* IE in the *DCH Information Response* IE for this Radio Link.

If the DRNS needs to limit the user rate in the downlink of a DCH due to congestion caused by the DL UTRAN Dynamic Resources (see subclause 9.2.1.79) when starting to utilise a new Radio Link, the DRNC

shall include in the RADIO LINK ADDITION RESPONSE message the *Allowed DL Rate* IE in the *DCH Information Response* IE for this Radio Link.

**[FDD-Tx Diversity]:**

The DRNS shall activate any feedback mode diversity according to the received settings.

[FDD - If the cell in which the RL is being added is capable to provide Close loop Tx diversity, the DRNC shall indicate the Closed loop timing adjustment mode of the cell by includiing the *Closed Loop Timing Adjustment Mode* IE in the RADIO LINK ADDITION RESPONSE message.]

[FDD - When the *Transmit Diversity Indicator* IE is present the DRNS shall activate/deactivate the Transmit Diversity for each new Radio Link in accordance with the *Transmit Diversity Indicator* IE using the diversity mode of the existing Radio Link(s).]

/\* partly omitted \*/

## 8.3.4 Synchronised Radio Link Reconfiguration Preparation

### 8.3.4.2 Successful Operation

/\* partly omitted \*/

#### [1.28Mcps TDD - Uplink Synchronisation Parameters LCR]:

[1.28Mcps TDD -If the *Uplink Synchronisation Parameters LCR* IE is present, the DRNC shall use the indicated values of *Uplink synchronisation stepsize* IE and *Uplink synchronisation frequency* IE when evaluating the timing of the UL synchronisation.]

#### [1.28Mcps TDD - Uplink Timing Advance Control LCR]:

[1.28Mcps TDD - The DRNC shall include the *Uplink Timing Advance Control LCR* IE in the RADIO LINK RECONFIGURATION READY message, if the Uplink Timing Advance Control parameters have been changed.]

#### [TDD] DSCH RNTI Addition/Deletion

[TDD - If the RADIO LINK RECONFIGURATION PREPARE message includes the PDSCH RL ID IE, then the DRNS shall use it as the new RL identifier for PDSCH and PUSCH..]

- [TDD - If the indicated PDSCH RL ID is in the DRNS and there was no DSCH-RNTI allocated to the UE Context, the DRNC shall allocate a DSCH-RNTI to the UE Context and include the DSCH-RNTI IE in the RADIO LINK RECONFIGURATION READY message.]
- [TDD - If the indicated PDSCH RL ID is in the DRNS and there was a DSCH-RNTI allocated to the UE Context, the DRNC shall allocate a new DSCH-RNTI to the UE Context, release the old DSCH-RNTI and include the DSCH-RNTI IE in the RADIO LINK RECONFIGURATION READY message.]
- [TDD - If the indicated PDSCH RL ID is not in the DRNS and there was a DSCH-RNTI allocated to the UE Context, the DRNC shall release this DSCH-RNTI.]

[TDD - If the RADIO LINK RECONFIGURATION PREPARE message includes a DSCHs to Delete IE and/or a USCHs to Delete IE which results in the deletion of all DSCH and USCH resources for the UE Context, then the DRNC shall release the DSCH-RNTI allocated to the UE Context, if there was one.]

#### [FDD – Phase Reference Handling]:

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *UE Support Of Dedicated Pilots For Channel Estimation* IE, the DRNC shall assume that dedicated pilots may be used for channel estimation with DCH or DSCH.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH* IE, the DRNC shall assume that dedicated pilots may be used for channel estimation with HS-DSCH.]

[FDD – If Primary CPICH usage for channel estimation information has been reconfigured, the DRNC shall include the *Primary CPICH Usage For Channel Estimation* IE in the RADIO LINK RECONFIGURATION READY message.]

[FDD – If Secondary CPICH information for channel estimation has been reconfigured, the DRNC shall include the *Secondary CPICH Information Change* IE in the RADIO LINK RECONFIGURATION READY message.]

#### General

If the requested modifications are allowed by the DRNC and the DRNC has successfully reserved the required resources for the new configuration of the Radio Link(s), it shall respond to the SRNC with the RADIO LINK RECONFIGURATION READY message. When this procedure has been completed successfully there exists a Prepared Reconfiguration, as defined in subclause 3.1.

If the RADIO LINK RECONFIGURATION PREPARE message includes the *Transport Layer Address* IE and *Binding ID* IE in the *DSCHs To Modify* IE, *DSCHs To Add* IE, [TDD - *USCHs To Modify* IE, *USCHs To Add* IE], *HS-DSCH To Modify* IE, *HS-DSCH To Add* IE or in the *RL Specific DCH Information* IEs, the DRNC may use the transport layer address and the binding identifier received from the SRNC when establishing a transport bearer for any Transport

Channel or HS-DSCH MAC-d flow being added, or any Transport Channel or HS-DSCH MAC-d flow being modified for which a new transport bearer was requested with the *Transport Bearer Request Indicator* IE.

The DRNC shall include the *Transport Layer Address* IE and the *Binding ID* IE in the *DCH Information Response* IE for any Transport Channel or HS-DSCH MAC-d flow being added, or any Transport Channel or HS-DSCH MAC-d flow being modified for which a new transport bearer was requested with the *Transport Bearer Request Indicator* IE. In the case of a set of co-ordinated DCHs requiring a new transport bearer on the Iur interface, the *Transport Layer Address* IE and the *Binding ID* IE in the *DCH Information Response* IE shall be included for only one of the DCHs in the set of co-ordinated DCHs.

In the case of a Radio Link being combined with another Radio Link within the DRNS, the *Transport Layer Address* IE and the *Binding ID* IE in the *DCH Information Response* IE shall be included for only one of the combined Radio Links.

Any allowed rate for the uplink of a modified DCH provided for the old configuration will not be valid for the new configuration. If the DRNS needs to limit the user rate in the uplink of a DCH due to congestion caused by the UL UTRAN Dynamic Resources (see subclause 9.2.1.79) in the new configuration for a Radio Link, the DRNC shall include in the RADIO LINK RECONFIGURATION READY message the *Allowed UL Rate* IE in the *DCH Information Response* IE for this Radio Link.

Any allowed rate for the downlink of a modified DCH provided for the old configuration will not be valid for the new configuration. If the DRNS needs to limit the user rate in the downlink of a DCH due to congestion caused by the DL UTRAN Dynamic Resources (see subclause 9.2.1.79) in the new configuration for a Radio Link, the DRNC shall include in the RADIO LINK RECONFIGURATION READY message the *Allowed DL Rate* IE in the *DCH Information Response* IE for this Radio Link.

The DRNS decides the maximum and minimum SIR for the uplink of the Radio Link(s) and the DRNC shall include in the RADIO LINK RECONFIGURATION READY message the *Maximum Uplink SIR* IE and *Minimum Uplink SIR* IE for each Radio Link when these values are changed.

[FDD - If the DL TX power upper or lower limit has been re-configured, the DRNC shall include in the RADIO LINK RECONFIGURATION READY message the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE respectively. The DRNS shall not transmit with a higher power than indicated by the *Maximum DL TX Power* IE or lower than indicated by the *Minimum DL TX Power* IE on any DL DPCH of the RL -except during compressed mode, when the  $\delta P_{curr}$ , as described in ref.[10] subclause 5.2.1.3, shall be added to the maximum DL power for the associated compressed frame.]

[3.84 Mcps TDD - If the DL TX power upper or lower limit has been re-configured, the DRNC shall include the new value(s) in the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the RADIO LINK RECONFIGURATION READY message. If the maximum or minimum power needs to be different for particular DCH type CCTrCHs, the DRNC shall include the new value(s) for that CCTrCH in the *CCTrCH Maximum DL TX Power* IE and *CCTrCH Minimum DL TX Power*. The DRNS shall not transmit with a higher power than indicated by the appropriate *Maximum DL TX Power* IE/*CCTrCH Maximum DL TX Power* IE or lower than indicated by the appropriate *Minimum DL TX Power* IE/*CCTrCH Minimum DL TX Power* IE on any DL DPCH within each CCTrCH of the RL.]

[1.28 Mcps TDD - If the DL TX power upper or lower limit has been re-configured, the DRNC shall include the new value(s) in the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the RADIO LINK RECONFIGURATION READY message. If the maximum or minimum power needs to be different for particular timeslots within a DCH type CCTrCH, the DRNC shall include the new value(s) for that timeslot in the *Maximum DL TX Power* IE and *Minimum DL TX Power* within the *DL Timeslot Information LCR* IE. The DRNS shall not transmit with a higher power than indicated by the appropriate *Maximum DL TX Power* IE or lower than indicated by the appropriate *Minimum DL TX Power* IE on any DL DPCH within each timeslot of the RL.]

[TDD - If the *Primary CCPCH RSCP* IE and/or the [3.84Mcps TDD - *DL Time Slot ISCP Info* IE][1.28Mcps TDD - *DL Time Slot ISCP Info LCR* IE] are present, the DRNC should use the indicated values when deciding the Initial DL TX Power.]

## 8.3.7 Un同步ised Radio Link Reconfiguration

### 8.3.7.2 Successful Operation

/\* partly omitted \*/

#### **DL Power Control:**

[FDD - If the RADIO LINK RECONFIGURATION REQUEST message includes the *DL Reference Power Information* IE and the power balancing is active, the DRNS shall update the reference power of the power balancing in the indicated RL(s), if updating of power balancing parameters by the RADIO LINK RECONFIGURATION REQUEST message is supported, using the *DL Reference Power Information* IE in the RADIO LINK RECONFIGURATION REQUEST message. The updated reference power shall be used from the next adjustment period.]

[FDD - If updating of power balancing parameters by the RADIO LINK RECONFIGURATION REQUEST message is supported by the DRNS, the DRNC shall include the *DL Power Balancing Updated Indicator* IE in the *RL Information Response* IE for each affected RL in the RADIO LINK RECONFIGURATION RESPONSE message.]

#### **[1.28Mcps TDD - Uplink Synchronisation Parameters LCR]:**

[1.28Mcps TDD - If the *Uplink Synchronisation Parameters LCR* IE is present, the DRNC shall use the indicated values of *Uplink synchronisation stepsize* IE and *Uplink synchronisation frequency* IE when evaluating the timing of the UL synchronisation.]

#### **[1.28Mcps TDD - Uplink Timing Advance Control LCR]:**

[1.28Mcps TDD - The DRNC shall include the *Uplink Timing Advance Control LCR* IE in the RADIO LINK RECONFIGURATION RESPONSE message, if the Uplink Timing Advance Control parameters have been changed.]

#### **[FDD – Phase Reference Handling]:**

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *UE Support Of Dedicated Pilots For Channel Estimation* IE, the DRNC shall assume that dedicated pilots may be used for channel estimation with DCH or DSCH.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH* IE, the DRNC shall assume that dedicated pilots may be used for channel estimation with HS-DSCH.]

#### **General:**

If the requested modifications are allowed by the DRNS, and if the DRNS has successfully allocated the required resources and changed to the new configuration, the DRNC shall respond to the SRNC with the RADIO LINK RECONFIGURATION RESPONSE message.

If the RADIO LINK RECONFIGURATION REQUEST message includes the *RL Specific DCH Information* IE, the DRNC may use the transport layer address and the binding identifier received from the SRNC when establishing a transport bearer for any Transport Channel being added, or any Transport Channel being modified for which a new transport bearer was requested with the *Transport Bearer Request Indicator* IE.

The DRNC shall include the *Transport Layer Address* IE and the *Binding ID* IE in the *DCH Information Response* IE for any Transport Channel being added, or any Transport Channel being modified for which a new transport bearer was requested with the *Transport Bearer Request Indicator* IE. The detailed frame protocol handling during transport bearer replacement is described in [4], subclause 5.10.1.

In the case of a set of co-ordinated DCHs requiring a new transport bearer on the Iur interface, the DRNC shall include the *Transport Layer Address* IE and the *Binding ID* IE in the *DCH Information Response* IE only for one of the DCHs in the set of co-ordinated DCHs.

In the case of a Radio Link being combined with another Radio Link within the DRNS, the DRNC shall include the *Transport Layer Address* IE and the *Binding ID* IE in the *DCH Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message for only one of the combined Radio Links.

Any allowed rate for the uplink of a modified DCH provided for the old configuration will not be valid for the new configuration. If the DRNS needs to limit the user rate in the uplink of a DCH due to congestion caused by the UL UTRAN Dynamic Resources (see subclause 9.2.1.79) in the new configuration for a Radio Link, the DRNC shall include in the RADIO LINK RECONFIGURATION RESPONSE message the *Allowed UL Rate* IE in the *DCH Information Response* IE for this Radio Link.

Any allowed rate for the downlink of a modified DCH provided for the old configuration will not be valid for the new configuration. If the DRNS needs to limit the user rate in the downlink of a DCH due to congestion caused by the DL UTRAN Dynamic Resources (see subclause 9.2.1.79) in the new configuration for a Radio Link, the DRNC shall include in the RADIO LINK RECONFIGURATION RESPONSE message the *Allowed DL Rate* IE in the *DCH Information Response* IE for this Radio Link.

The DRNS decides the maximum and minimum SIR for the uplink of the Radio Link(s), and the DRNC shall include in the RADIO LINK RECONFIGURATION RESPONSE message the *Maximum Uplink SIR* IE and *Minimum Uplink SIR* IE for each Radio Link when these values are changed.

[FDD - If the DL TX power upper or lower limit has been re-configured, the DRNC shall include the new value(s) in the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the RADIO LINK RECONFIGURATION RESPONSE message. The DRNS shall not transmit with a higher power than indicated by the *Maximum DL TX Power* IE or lower than indicated by the *Minimum DL TX Power* IE on any DL DPCH of the RL except during compressed mode, when the  $\delta P_{curr}$ , as described in ref.[10] subclause 5.2.1.3, shall be added to the maximum DL power for the associated compressed frame.]

[3.84 Mcps TDD - If the DL TX power upper or lower limit has been re-configured, the DRNC shall include the new value(s) in the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the RADIO LINK RECONFIGURATION RESPONSE message. If the maximum or minimum power needs to be different for particular DCH type CCTrCHs, the DRNC shall include the new value(s) for that CCTrCH in the *CCTrCH Maximum DL TX Power* IE and *CCTrCH Minimum DL TX Power*. The DRNS shall not transmit with a higher power than indicated by the appropriate *Maximum DL TX Power*/CCTrCH *Maximum DL TX Power* IE or lower than indicated by the appropriate *Minimum DL TX Power* IE/CCTrCH *Minimum DL TX Power* IE on any DL DPCH within each CCTrCH of the RL.]

[1.28 Mcps TDD - If the DL TX power upper or lower limit has been re-configured, the DRNC shall include the new value(s) in the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the RADIO LINK RECONFIGURATION RESPONSE message. If the maximum or minimum power needs to be different for particular timeslots within a DCH type CCTrCH, the DRNC shall include the new value(s) for that timeslot in the *Maximum DL TX Power* IE and *Minimum DL TX Power* within the *DL Timeslot Information LCR* IE. The DRNS shall not transmit with a higher power than indicated by the appropriate *Maximum DL TX Power* IE or lower than indicated by the appropriate *Minimum DL TX Power* IE on any DL DPCH within each timeslot of the RL.]

### 8.3.21 Radio Link Parameter Update

#### 8.3.21.1 General

The Radio Link Parameter Update procedure is executed by the DRNS to update parameters related to HS-DSCH on a radio link for a UE-UTRAN connection [or to update phase reference on a list of the radio links](#).

This procedure shall use the signalling bearer connection for the relevant UE context.

The Radio Link Parameter Update procedure shall not be initiated if a Prepared Reconfiguration exists, as defined in subclause 3.1.

#### 8.3.21.2 Successful Operation



**Figure 26E: Radio Link Parameter Update Indication, Sucessful Operation**

The Radio Link Parameter Update procedure is initiated by the DRNS by sending the RADIO LINK PARAMETER UPDATE INDICATION message to the SRNC.

##### HS-DSCH related Parameter(s) Updating:

[If RADIO LINK PARAMETER UPDATE INDICATION message is used to update the parameters related to HS-DSCH, it contains](#) suggested value(s) of the HS-DSCH related parameter(s) that should be reconfigured on the radio link.

If DRNS needs to update HS-DSCH related parameters, DRNS shall initiate RADIO LINK PARAMETER UPDATE INDICATION message including [FDD - HS-DSCH FDD Update Information IE] [TDD - HS-DSCH TDD Update Information IE].

If DRNS needs to allocate new HS-SCCH Codes, DRNS shall initiate RADIO LINK PARAMETER UPDATE INDICATION message including *HS-SCCH Code Change Indicator IE*.

[FDD - If DRNS needs to update the CQI Feedback Cycle k, CQI Repetition Factor, ACK-NACK Repetition Factor, CQI Power Offset, ACK Power Offset and/or NACK Power Offset, DRNS shall initiate RADIO LINK PARAMETER UPDATE INDICATION message including *CQI Feedback Cycle k IE*, *CQI Repetition Factor IE*, *ACK-NACK Repetition Factor IE*, *CQI Power Offset IE*, *ACK Power Offset IE* and/or *NACK Power Offset IE*.]

##### FDD – Phase Reference Handling:

[\[FDD – If DRNS needs to update phase reference for the channel estimation for one or several Radio Links, the DRNC shall initiate RADIO LINK PARAMETER UPDATE INDICATION message including \*Phase Reference Update Information IE\* for the concerned RL\(s\).\]](#)

#### 8.3.21.3 Abnormal Conditions

## 9.1.3 RADIO LINK SETUP REQUEST

### 9.1.3.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		–	
SRNC-ID	M		RNC-ID 9.2.1.50		YES	reject
S-RNTI	M		9.2.1.53		YES	reject
D-RNTI	O		9.2.1.24		YES	reject
Allowed Queuing Time	O		9.2.1.2		YES	reject
<b>UL DPCCH Information</b>		1			YES	reject
>UL Scrambling Code	M		9.2.2.53		–	
>Min UL Channelisation Code Length	M		9.2.2.25		–	
>Max Number of UL DPDCHs	C – CodeLen		9.2.2.24		–	
>Puncture Limit	M		9.2.1.46	For the UL.	–	
>TFCS	M		TFCS for the UL 9.2.1.63		–	
>UL DPCCH Slot Format	M		9.2.2.52		–	
>Uplink SIR Target	O		Uplink SIR 9.2.1.69		–	
>Diversity mode	M		9.2.2.8		–	
>SSDT Cell Identity Length	O		9.2.2.41		–	
>S Field Length	O		9.2.2.36		–	
>DPC Mode	O		9.2.2.12A		YES	reject
<b>DL DPCH Information</b>		1			YES	reject
>TFCS	M		TFCS for the DL. 9.2.1.63		–	
>DL DPCH Slot Format	M		9.2.2.9		–	
>Number of DL Channelisation Codes	M		9.2.2.26A		–	
>TFCI Signalling Mode	M		9.2.2.46		–	
>TFCI Presence	C-SlotFormat		9.2.1.55		–	
>Multiplexing Position	M		9.2.2.26		–	
<b>&gt;Power Offset Information</b>		1			–	
>>PO1	M		Power Offset 9.2.2.30	Power offset for the TFCI bits.	–	
>>PO2	M		Power Offset 9.2.2.30	Power offset for the TPC bits.	–	
>>PO3	M		Power Offset 9.2.2.30	Power offset for the pilot bits.	–	
>FDD TPC Downlink Step Size	M		9.2.2.16		–	
>Limited Power Increase	M		9.2.2.21A		–	
>Inner Loop DL PC Status	M		9.2.2.21a		–	
>Split Type	O		9.2.2.39a		YES	reject
>Length of TFCI2	O		9.2.2.21C		YES	reject
DCH Information	M		DCH FDD Information 9.2.2.4A		YES	reject
DSCH Information	O		DSCH FDD Information		YES	reject

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
			9.2.2.13A			
<b>RL Information</b>		1...<maxn oofRLs>			EACH	notify
>RL ID	M		9.2.1.49		–	
>C-ID	M		9.2.1.6		–	
>First RLS Indicator	M		9.2.2.16A		–	
>Frame Offset	M		9.2.1.30		–	
>Chip Offset	M		9.2.2.1		–	
>Propagation Delay	O		9.2.2.33		–	
>Diversity Control Field	C – NotFirstRL		9.2.1.20		–	
>Initial DL TX Power	O		DL Power 9.2.1.21A		–	
>Primary CPICH Ec/No	O		9.2.2.32		–	
>SSDT Cell Identity	O		9.2.2.40		–	
>Transmit Diversity Indicator	C – Diversity mode		9.2.2.48		–	
>SSDT Cell Identity for EDSCHPC	C- EDSCHPC		9.2.2.40A		YES	ignore
>Enhanced Primary CPICH Ec/No	O		9.2.2.13I		YES	ignore
>RL Specific DCH Information	O		9.2.1.49A		YES	ignore
>Delayed Activation	O		9.2.1.19Aa		YES	reject
>Qth Parameter	O		9.2.2.34a		YES	ignore
Transmission Gap Pattern Sequence Information	O		9.2.2.47A		YES	reject
Active Pattern Sequence Information	O		9.2.2.A		YES	reject
Permanent NAS UE Identity	O		9.2.1.73		YES	ignore
DL Power Balancing Information	O		9.2.2.10A		YES	ignore
HS-DSCH Information	O		HS-DSCH FDD Information 9.2.2.19a		YES	reject
HS-PDSCH RL ID	C – InfoHSDS CH		RL ID 9.2.1.49		YES	reject
<u>UE Support Of Dedicated Pilots For Channel Estimation</u>	<u>O</u>		<u>9.2.2.x1</u>		<u>YES</u>	<u>ignore</u>
<u>UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH</u>	<u>O</u>		<u>9.2.2.x2</u>		<u>YES</u>	<u>ignore</u>

Condition	Explanation
CodeLen	The IE shall be present if <i>Min UL Channelisation Code length</i> IE equals to 4
SlotFormat	The IE shall be present if the <i>DL DPCH Slot Format</i> IE is equal to any of the values from 12 to 16.
NotFirstRL	The IE shall be present if the RL is not the first one in the <i>RL Information</i> IE.
Diversity mode	The IE shall be present if <i>Diversity Mode</i> IE in <i>UL DPCH Information</i> IE is not equal to "none".
EDSCHPC	This IE shall be present if <i>Enhanced DSCH PC</i> IE is present in the <i>DSCH Information</i> IE.
InfoHSDSCH	This IE shall be present if <i>HS-DSCH Information</i> IE is present.

Range bound	Explanation
<i>maxnoofRLs</i>	Maximum number of RLs for one UE.

## 9.1.4 RADIO LINK SETUP RESPONSE

### 9.1.4.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		–	
D-RNTI	O		9.2.1.24		YES	ignore
CN PS Domain Identifier	O		9.2.1.12		YES	ignore
CN CS Domain Identifier	O		9.2.1.11		YES	ignore
<b>RL Information Response</b>		1..<maxno ofRLs>			EACH	ignore
>RL ID	M		9.2.1.49		–	
>RL Set ID	M		9.2.2.35		–	
>URA Information	O		9.2.1.70B		–	
>SAI	M		9.2.1.52		–	
>Cell GAI	O		9.2.1.5A		–	
>UTRAN Access Point Position	O		9.2.1.70A		–	
>Received Total Wide Band Power	M		9.2.2.35A		–	
>Secondary CCPCH Info	O		9.2.2.37B		–	
>DL Code Information	M		FDD DL Code Information 9.2.2.14A		–	
>CHOICE Diversity Indication	M				–	
>>Combining					–	
>>>RL ID	M		9.2.1.49	Reference RL ID for the combining	–	
>>>DCH Information Response	O		9.2.1.16A		YES	ignore
>>Non Combining or First RL					–	
>>>DCH Information Response	M		9.2.1.16A		–	
>SSDT Support Indicator	M		9.2.2.43		–	
>Maximum Uplink SIR	M		Uplink SIR 9.2.1.69		–	
>Minimum Uplink SIR	M		Uplink SIR 9.2.1.69		–	
>Closed Loop Timing Adjustment Mode	O		9.2.2.3A		–	
>Maximum Allowed UL Tx Power	M		9.2.1.35		–	
>Maximum DL TX Power	M		DL Power 9.2.1.21A		–	
>Minimum DL TX Power	M		DL Power 9.2.1.21A		–	
>Primary Scrambling Code	O		9.2.1.45		–	
>UL UARFCN	O		UARFCN 9.2.1.66	Corresponds to Nu in ref. [6]	–	
>DL UARFCN	O		UARFCN 9.2.1.66	Corresponds to Nd in ref. [6]	–	
>Primary CPICH Power	M		9.2.1.44		–	
>DSCH Information Response	O		DSCH FDD Information		YES	ignore

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
			Response 9.2.2.13B		–	
>Neighbouring UMTS Cell Information	O		9.2.1.41A		–	
>Neighbouring GSM Cell Information	O		9.2.1.41C		–	
>PC Preamble	M		9.2.2.27a		–	
>SRB Delay	M		9.2.2.39A		–	
>Cell GA Additional Shapes	O		9.2.1.5B		YES	ignore
>DL Power Balancing Activation Indicator	O		9.2.2.10B		YES	ignore
>HS-DSCH Information Response	O		HS-DSCH FDD Information Response 9.2.2.19b		YES	ignore
>TFCI PC Support Indicator	O		9.2.2.46A		YES	ignore
>HCS Prio	O		9.2.1.30N		YES	ignore
<a href="#"><u>&gt;Primary CPICH Usage For Channel Estimation</u></a>	<a href="#"><u>O</u></a>		<a href="#"><u>9.2.2.x3</u></a>		<a href="#"><u>YES</u></a>	<a href="#"><u>ignore</u></a>
<a href="#"><u>&gt;Secondary CPICH Information</u></a>	<a href="#"><u>O</u></a>		<a href="#"><u>9.2.2.x4</u></a>		<a href="#"><u>YES</u></a>	<a href="#"><u>ignore</u></a>
Uplink SIR Target	O		Uplink SIR 9.2.1.69		YES	ignore
Criticality Diagnostics	O		9.2.1.13		YES	ignore
DSCH-RNTI	O		9.2.1.26Ba		YES	ignore
HS-DSCH-RNTI	O		9.2.1.30P		YES	reject

Range bound	Explanation
<i>maxnoofRLs</i>	Maximum number of RLs for one UE.

## 9.1.5 RADIO LINK SETUP FAILURE

### 9.1.5.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		–	
D-RNTI	O		9.2.1.24		YES	ignore
CN PS Domain Identifier	O		9.2.1.12		YES	ignore
CN CS Domain Identifier	O		9.2.1.11		YES	ignore
CHOICE Cause Level	M				YES	ignore
>General					–	
>>Cause	M		9.2.1.5		–	
>RL Specific					–	
>>Unsuccessful RL Information Response		1..<maxno ofRLs>			EACH	ignore
>>>RL ID	M		9.2.1.49		–	
>>>Cause	M		9.2.1.5		–	
>>Successful RL Information Response		0..<maxno ofRLs-1>			EACH	ignore
>>>RL ID	M		9.2.1.49		–	
>>>RL Set ID	M		9.2.2.35		–	
>>>URA Information	O		9.2.1.70B		–	
>>>SAI	M		9.2.1.52		–	
>>>Cell GAI	O		9.2.1.5A		–	
>>>UTRAN Access Point Position	O		9.2.1.70A		–	
>>>Received Total Wide Band Power	M		9.2.2.35A		–	
>>>Secondary CCPCH Info	O		9.2.2.37B		–	
>>>DL Code Information	M		FDD DL Code Information 9.2.2.14A		–	
>>>CHOICE Diversity Indication	M				–	
>>>>Combining					–	
>>>>RL ID	M		9.2.1.49	Reference RL ID for the combining	–	
>>>>DCH Information Response	O		9.2.1.16A		YES	ignore
>>>>Non Combining or First RL					–	
>>>>DCH Information Response	M		9.2.1.16A		–	
>>>SSDT Support Indicator	M		9.2.2.43		–	
>>>Maximum Uplink SIR	M		Uplink SIR 9.2.1.69		–	
>>>Minimum Uplink SIR	M		Uplink SIR 9.2.1.69		–	
>>>Closed Loop Timing Adjustment Mode	O		9.2.2.3A		–	
>>>Maximum Allowed UL Tx Power	M		9.2.1.35		–	
>>>Maximum DL TX Power	M		DL Power 9.2.1.21A		–	
>>>Minimum DL TX Power	M		DL Power 9.2.1.21A		–	
>>>Primary CPICH	M		9.2.1.44		–	

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Power					–	
>>>Primary Scrambling Code	O		9.2.1.45		–	
>>>UL UARFCN	O		UARFCN 9.2.1.66	Corresponds to Nu in ref. [6]	–	
>>>DL UARFCN	O		UARFCN 9.2.1.66	Corresponds to Nd in ref. [6]	–	
>>>DSCH Information Response	O		DSCH FDD Information Response 9.2.2.13B		YES	ignore
>>>Neighbouring UMTS Cell Information	O		9.2.1.41A		–	
>>>Neighbouring GSM Cell Information	O		9.2.1.41C		–	
>>>PC Preamble	M		9.2.2.27a		–	
>>>SRB Delay	M		9.2.2.39A		–	
>>>Cell GA Additional Shapes	O		9.2.1.5B		YES	ignore
>>>DL Power Balancing Activation Indicator	O		9.2.2.10B		YES	ignore
>>>HS-DSCH Information Response	O		HS-DSCH FDD Information Response 9.2.2.19b		YES	ignore
>>>TFCI PC Support Indicator	O		9.2.2.46A		YES	ignore
>>>HCS Prio	O		9.2.1.30N		YES	ignore
>>> <a href="#">Primary CPICH Usage For Channel Estimation</a>	<a href="#">O</a>		<a href="#">9.2.2.x3</a>		<a href="#">YES</a>	<a href="#">ignore</a>
>>> <a href="#">Secondary CPICH Information</a>	<a href="#">O</a>		<a href="#">9.2.2.x4</a>		<a href="#">YES</a>	<a href="#">ignore</a>
>>DSCH-RNTI	O		9.2.1.26Ba		YES	ignore
>>HS-DSCH-RNTI	O		9.2.1.30P		YES	reject
Uplink SIR Target	O		Uplink SIR 9.2.1.69		YES	ignore
Criticality Diagnostics	O		9.2.1.13		YES	ignore

Range bound	Explanation
<i>maxnoofRLs</i>	Maximum number of RLs for one UE.

## 9.1.6 RADIO LINK ADDITION REQUEST

### 9.1.6.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		—	
Uplink SIR Target	M		Uplink SIR 9.2.1.69		YES	reject
<b>RL Information</b>		<i>1..&lt;maxn oofRLs-1&gt;</i>			EACH	notify
>RL ID	M		9.2.1.49		—	
>C-ID	M		9.2.1.6		—	
>Frame Offset	M		9.2.1.30		—	
>Chip Offset	M		9.2.2.1		—	
>Diversity Control Field	M		9.2.1.20		—	
>Primary CPICH Ec/No	O		9.2.2.32		—	
>SSDT Cell Identity	O		9.2.2.40		—	
>Transmit Diversity Indicator	O		9.2.2.48		—	
>DL Reference Power	O		DL Power 9.2.1.21A	Power on DPCH	YES	ignore
>Enhanced Primary CPICH Ec/No	O		9.2.2.13I		YES	ignore
>RL Specific DCH Information	O		9.2.1.49A		YES	ignore
>Delayed Activation	O		9.2.1.19Aa		YES	reject
>Qth Parameter	O		9.2.2.34a		YES	ignore
Active Pattern Sequence Information	O		9.2.2A	Either all the already active Transmission Gap Sequence(s) are addressed (Transmission Gap Pattern sequence shall overlap with the existing one) or none of the transmission gap sequences is activated.	YES	reject
DPC Mode	O		9.2.2.12A		YES	reject
Permanent NAS UE Identity	O		9.2.1.73		YES	ignore
<a href="#"><u>UE Support Of Dedicated Pilots For Channel Estimation</u></a>	<a href="#"><u>O</u></a>		<a href="#"><u>9.2.2.x1</u></a>		<a href="#"><u>YES</u></a>	<a href="#"><u>ignore</u></a>
<a href="#"><u>UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH</u></a>	<a href="#"><u>O</u></a>		<a href="#"><u>9.2.2.x2</u></a>		<a href="#"><u>YES</u></a>	<a href="#"><u>ignore</u></a>

Range bound	Explanation
<i>maxnoofRLs</i>	Maximum number of radio links for one UE.

## 9.1.7 RADIO LINK ADDITION RESPONSE

### 9.1.7.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		–	
<b>RL Information Response</b>		1..<maxnoof RLS-1>			EACH	ignore
>RL ID	M		9.2.1.49		–	
>RL Set ID	M		9.2.2.35		–	
>URA Information	O		9.2.1.70B		–	
>SAI	M		9.2.1.52		–	
>Cell GAI	O		9.2.1.5A		–	
>UTRAN Access Point Position	O		9.2.1.70A		–	
>Received Total Wide Band Power	M		9.2.2.35A		–	
>Secondary CCPCH Info	O		9.2.2.37B		–	
>DL Code Information	M		FDD DL Code Information 9.2.2.14A		YES	ignore
>CHOICE Diversity Indication	M				–	
>>Combining					–	
>>>RL ID	M		9.2.1.49	Reference RL ID	–	
>>>DCH Information Response	O		9.2.1.16A		YES	ignore
>>Non Combining					–	
>>>DCH Information Response	M		9.2.1.16A		–	
>SSDT Support Indicator	M		9.2.2.43		–	
>Minimum Uplink SIR	M		Uplink SIR 9.2.1.69		–	
>Maximum Uplink SIR	M		Uplink SIR 9.2.1.69		–	
>Closed Loop Timing Adjustment Mode	O		9.2.2.3A		–	
>Maximum Allowed UL Tx Power	M		9.2.1.35		–	
>Maximum DL TX Power	M		DL Power 9.2.1.21A		–	
>Minimum DL TX Power	M		DL Power 9.2.1.21A		–	
>Neighbouring UMTS Cell Information	O		9.2.1.41A		–	
>Neighbouring GSM Cell Information	O		9.2.1.41C		–	
>PC Preamble	M		9.2.2.27a		–	
>SRB Delay	M		9.2.2.39A		–	
>Primary CPICH Power	M		9.2.1.44		–	
>Cell GA Additional Shapes	O		9.2.1.5B		YES	ignore
>DL Power Balancing Activation Indicator	O		9.2.2.10B		YES	ignore
>TFCI PC Support Indicator	O		9.2.2.46A		YES	ignore
>HCS Prio	O		9.2.1.30N		YES	ignore
> <a href="#">Primary CPICH Usage For Channel Estimation</a>	<a href="#">O</a>		<a href="#">9.2.2.x3</a>		<a href="#">YES</a>	<a href="#">ignore</a>

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
<a href="#">&gt;Secondary CPICH Information</a>	O		<a href="#">9.2.2.x4</a>		<a href="#">YES</a>	<a href="#">ignore</a>
Criticality Diagnostics	O		9.2.1.13		YES	ignore

Range bound	Explanation
<i>maxnoofRLs</i>	Maximum number of radio links for one UE.

## 9.1.8 RADIO LINK ADDITION FAILURE

### 9.1.8.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		–	
CHOICE Cause Level	M				YES	ignore
>General					–	
>>Cause	M		9.2.1.5		–	
>RL Specific					–	
>>Unsuccessful RL Information Response		1..<maxnoof RLS-1>			EACH	ignore
>>>RL ID	M		9.2.1.49		–	
>>>Cause	M		9.2.1.5		–	
>>Successful RL Information Response		0..<maxnoof RLS-2>			EACH	ignore
>>>RL ID	M		9.2.1.49		–	
>>>RL Set ID	M		9.2.2.35		–	
>>>URA Information	O		9.2.1.70B		–	
>>>SAI	M		9.2.1.52		–	
>>>Cell GAI	O		9.2.1.5A		–	
>>>UTRAN Access Point Position	O		9.2.1.70A		–	
>>>Received Total Wide Band Power	M		9.2.2.35A		–	
>>>Secondary CCPCH Info	O		9.2.2.37B		–	
>>>DL Code Information	M		FDD DL Code Information 9.2.2.14A		YES	ignore
>>>CHOICE Diversity Indication	M				–	
>>>>Combining					–	
>>>>RL ID	M		9.2.1.49	Reference RL ID	–	
>>>>DCH Information Response	O		9.2.1.16A		YES	ignore
>>>>Non Combining					–	
>>>>DCH Information Response	M		9.2.1.16A		–	
>>>SSDT Support Indicator	M		9.2.2.43		–	
>>>Minimum Uplink SIR	M		Uplink SIR 9.2.1.69		–	
>>>Maximum Uplink SIR	M		Uplink SIR 9.2.1.69		–	
>>>Closed Loop Timing Adjustment Mode	O		9.2.2.3A		–	
>>>Maximum Allowed UL Tx Power	M		9.2.1.35		–	
>>>Maximum DL TX Power	M		DL Power 9.2.1.21A		–	
>>>Minimum DL TX Power	M		DL Power 9.2.1.21A		–	
>>>Neighbouring UMTS Cell Information	O		9.2.1.41A		–	
>>>Neighbouring GSM Cell Information	O		9.2.1.41C		–	

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>>>Primary CPICH Power	M		9.2.1.44		–	
>>>PC Preamble	M		9.2.2.27a		–	
>>>SRB Delay	M		9.2.2.39A		–	
>>>Cell GA Additional Shapes	O		9.2.1.5B		YES	ignore
>>>DL Power Balancing Activation Indicator	O		9.2.2.10B		YES	ignore
>>>TFCI PC Support Indicator	O		9.2.2.46A		YES	ignore
>>>HCS Prio	O		9.2.1.30N		YES	ignore
<a href="#"><u>&gt;&gt;&gt;Primary CPICH Usage For Channel Estimation</u></a>	<a href="#"><u>O</u></a>		<a href="#"><u>9.2.2.x3</u></a>		<a href="#"><u>YES</u></a>	<a href="#"><u>ignore</u></a>
<a href="#"><u>&gt;&gt;&gt;Secondary CPICH Information</u></a>	<a href="#"><u>O</u></a>		<a href="#"><u>9.2.2.x4</u></a>		<a href="#"><u>YES</u></a>	<a href="#"><u>ignore</u></a>
Criticality Diagnostics	O		9.2.1.13		YES	ignore

Range bound	Explanation
<i>maxnoofRLs</i>	Maximum number of radio links for one UE.

## 9.1.11 RADIO LINK RECONFIGURATION PREPARE

### 9.1.11.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		–	
Allowed Queuing Time	O		9.2.1.2		YES	reject
<b>UL DPCCH Information</b>		0..1			YES	reject
>UL Scrambling Code	O		9.2.2.53		–	
>UL SIR Target	O		Uplink SIR 9.2.1.69		–	
>Min UL Channelisation Code Length	O		9.2.2.25		–	
>Max Number of UL DPDCHs	C – CodeLen		9.2.2.24		–	
>Puncture Limit	O		9.2.1.46	For the UL.	–	
>TFCS	O		9.2.1.63	TFCS for the UL.	–	
>UL DPCCH Slot Format	O		9.2.2.52		–	
>Diversity Mode	O		9.2.2.8		–	
>SSDT Cell Identity Length	O		9.2.2.41		–	
>S-Field Length	O		9.2.2.36		–	
<b>DL DPCH Information</b>		0..1			YES	reject
>TFCS	O		9.2.1.63	TFCS for the DL.	–	
>DL DPCH Slot Format	O		9.2.2.9		–	
>Number of DL Channelisation Codes	O		9.2.2.26A		–	
>TFCI Signalling Mode	O		9.2.2.46		–	
>TFCI Presence	C- SlotFormat		9.2.1.55		–	
>Multiplexing Position	O		9.2.2.26		–	
>Limited Power Increase	O		9.2.2.21A		–	
>Split Type	O		9.2.2.39a		YES	reject
>Length of TFCI2	O		9.2.2.21C		YES	reject
DCHs To Modify	O		FDD DCHs To Modify 9.2.2.13C		YES	reject
DCHs To Add	O		DCH FDD Information 9.2.2.4A		YES	reject
<b>DCHs to Delete</b>		0..<maxnoof DCHs>			GLOBAL	reject
>DCH ID	M		9.2.1.16		–	
<b>DSCHs To Modify</b>		0..1			YES	reject
>DSCH Info		0..<maxnoof DSCHs>			–	
>>DSCH ID	M		9.2.1.26A		–	
>>TrCH Source Statistics Descriptor	O		9.2.1.65		–	
>>Transport Format Set	O		9.2.1.64	For DSCH	–	
>>Allocation/ Retention Priority	O		9.2.1.1		–	
>>Scheduling	O		9.2.1.51A		–	

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Priority Indicator						
>>BLER	O		9.2.1.4		–	
>>Transport Bearer Request Indicator	M		9.2.1.61		–	
>>Traffic Class	O		9.2.1.58A		YES	ignore
>>Binding ID	O		9.2.1.3	Shall be ignored if bearer establishment with ALCAP.	YES	ignore
>>Transport Layer Address	O		9.2.1.62	Shall be ignored if bearer establishment with ALCAP.	YES	ignore
>PDSCH RL ID	O		RL ID 9.2.1.49		–	
>TFCS	O		9.2.1.63	For DSCH	–	
>Enhanced DSCH PC Indicator	O		9.2.2.13F		YES	ignore
>Enhanced DSCH PC	C-EDSCHPC On		9.2.2.13D		YES	ignore
DSCHs To Add	O		DSCH FDD Information 9.2.2.13A		YES	reject
DSCHs to Delete		0..1			YES	reject
>DSCH Info		1..<maxnoof DSCHs>			–	
>>DSCH ID	M		9.2.1.26A		–	
RL Information		0..<maxnoof RLS>			EACH	reject
>RL ID	M		9.2.1.49		–	
>SSDT Indication	O		9.2.2.42		–	
>SSDT Cell Identity	C - SSDTIndON		9.2.2.40		–	
>Transmit Diversity Indicator	C – Diversity mode		9.2.2.48		–	
>SSDT Cell Identity for EDSCHPC	C-EDSCHPC		9.2.2.40A		YES	ignore
>DL Reference Power	O		DL Power 9.2.1.21A	Power on DPCH	YES	ignore
>RL Specific DCH Information	O		9.2.1.49A		YES	ignore
>DL DPCH Timing Adjustment	O		9.2.2.9A	Required RL Timing Adjustment	YES	reject
>Qth Parameter	O		9.2.2.34a		YES	ignore
> <a href="#">Phase Reference Update Indicator</a>	<a href="#">O</a>		<a href="#">9.2.2.x7</a>		<a href="#">YES</a>	<a href="#">ignore</a>
Transmission Gap Pattern Sequence Information	O		9.2.2.47A		YES	reject
HS-DSCHs Information To Modify	O		HS-DSCH Information To modify 9.2.1.30Q		YES	reject
HS-DSCHs Information To Add	O		HS-DSCH FDD		YES	reject

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
			Information 9.2.2.19a			
<b>HS-DSCHs Information To Delete</b>		$0..<\maxnoofMACdFlows>$			GLOBAL	reject
>HS-DSCH MAC-d Flow ID	M		9.2.1.300		-	
HS-PDSCH RL ID	O		RL ID 9.2.1.49		YES	reject
<a href="#">UE Support Of Dedicated Pilots For Channel Estimation</a>	<a href="#">O</a>		<a href="#">9.2.2.x1</a>		<a href="#">YES</a>	<a href="#">ignore</a>
<a href="#">UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH</a>	<a href="#">O</a>		<a href="#">9.2.2.x2</a>		<a href="#">YES</a>	<a href="#">ignore</a>

Condition	Explanation
SSDTIndON	The IE shall be present if the <i>SSDT Indication</i> IE is set to "SSDT Active in the UE".
CodeLen	The IE shall be present only if the <i>Min UL Channelisation Code length</i> IE equals to 4.
SlotFormat	The IE shall only be present if the <i>DL DPCCH Slot Format</i> IE is equal to any of the values from 12 to 16.
Diversity mode	The IE shall be present if <i>Diversity Mode</i> IE is present in the <i>UL DPCH Information</i> IE and is not equal to "none".
EDSCHPCOn	The IE shall be present if the <i>Enhanced DSCH PC Indicator</i> IE is set to "Enhanced DSCH PC Active in the UE".
EDSCHPC	The IE shall be present if <i>Enhanced DSCH PC</i> IE is present in either the <i>DSCHs To Modify</i> IE or the <i>DSCHs To Add</i> IE.

Range bound	Explanation
<i>maxnoofDCHs</i>	Maximum number of DCHs for a UE.
<i>maxnoofDSCHs</i>	Maximum number of DSCHs for one UE.
<i>maxnoofRLs</i>	Maximum number of RLs for a UE.
<i>maxnoofMACdFlows</i>	Maximum number of HS-DSCH MAC-d flows

## 9.1.12 RADIO LINK RECONFIGURATION READY

### 9.1.12.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		—	
<b>RL Information Response</b>		<i>0..&lt;maxnoofRLs&gt;</i>			EACH	ignore
>RL ID	M		9.2.1.49		—	
>Maximum Uplink SIR	O		Uplink SIR 9.2.1.69		—	
>Minimum Uplink SIR	O		Uplink SIR 9.2.1.69		—	
>Maximum DL TX Power	O		DL Power 9.2.1.21A		—	
>Minimum DL TX Power	O		DL Power 9.2.1.21A		—	
>Secondary CCPCH Info	O		9.2.2.37B		—	
>DL Code Information	O		FDD DL Code Information 9.2.2.14A		YES	ignore
>DCH Information Response	O		9.2.1.16A		YES	ignore
>DSCHs to be Added or Modified	O		DSCH FDD Information Response 9.2.2.13B		YES	ignore
>DL Power Balancing Updated Indicator	O		9.2.2.10D		YES	ignore
>HS-DSCH Information Response	O		HS-DSCH FDD Information Response 9.2.2.19b		YES	ignore
<u>&gt;Primary CPICH Usage For Channel Estimation</u>	<u>O</u>		<u>9.2.2.x3</u>		<u>YES</u>	<u>ignore</u>
<u>&gt;Secondary CPICH Information Change</u>	<u>O</u>		<u>9.2.2.x5</u>		<u>YES</u>	<u>ignore</u>
Criticality Diagnostics	O		9.2.1.13		YES	ignore
DSCH-RNTI	O		9.2.1.26Ba		YES	ignore
HS-DSCH-RNTI	O		9.2.1.30P		YES	reject
MAC-hs Reset Indicator	O		9.2.1.34B		YES	reject

Range bound	Explanation
<i>maxnoofRLs</i>	Maximum number of RLs for a UE.

## 9.1.16 RADIO LINK RECONFIGURATION REQUEST

### 9.1.16.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		–	
Allowed Queuing Time	O		9.2.1.2		YES	reject
<b>UL DPCH Information</b>		0..1			YES	reject
>TFCS	O		9.2.1.63	TFCS for the UL.	–	
<b>DL DPCH Information</b>		0..1			YES	reject
>TFCS	O		9.2.1.63	TFCS for the DL.	–	
>TFCI Signalling Mode	O		9.2.2.46		–	
>Limited Power Increase	O		9.2.2.21A		–	
DCHs To Modify	O		FDD DCHs To Modify 9.2.2.13C		YES	reject
DCHs To Add	O		DCH FDD Information 9.2.2.4A		YES	reject
<b>DCHs to Delete</b>		0..<maxno ofDCHs>			GLOBAL	reject
>DCH ID	M		9.2.1.16		–	
Transmission Gap Pattern Sequence Information	O		9.2.2.47A		YES	reject
<b>RL Information</b>		0..<maxno ofRLs>			EACH	ignore
>RL ID	M		9.2.1.49		–	
>RL Specific DCH Information	O		9.2.1.49A		–	
DL Reference Power Information	O		9.2.2.10C		YES	ignore
<a href="#">UE Support Of Dedicated Pilots For Channel Estimation</a>	<a href="#">O</a>		<a href="#">9.2.2.x1</a>		<a href="#">YES</a>	<a href="#">ignore</a>
<a href="#">UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH</a>	<a href="#">O</a>		<a href="#">9.2.2.x2</a>		<a href="#">YES</a>	<a href="#">ignore</a>

## 9.1.58 RADIO LINK PARAMETER UPDATE INDICATION

### 9.1.58.1 FDD Message

IE/Group name	Presence	Range	IE Type and Reference	Semantic Description	Criticality	Assigned Criticality
Message type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		—	
HS-DSCH FDD Update Information	O		9.2.2.19c		YES	reject
<a href="#">RL Information</a>		<a href="#">0..&lt;maxn oofRLs&gt;</a>			<a href="#">EACH</a>	<a href="#">reject</a>
<a href="#">&gt;RL Id</a>	<a href="#">M</a>		<a href="#">9.2.1.49</a>		<a href="#">—</a>	
<a href="#">&gt;Phase Reference Update Indicator</a>	<a href="#">O</a>		<a href="#">9.2.2.x6</a>		<a href="#">—</a>	

### 9.2.2.x1 UE Support Of Dedicated Pilots For Channel Estimation

The *UE Support Of Dedicated Pilots For Channel Estimation* IE indicates whether the UE supports dedicated pilots for channel estimation or not with DCH or DSCH.

<u>IE/Group Name</u>	<u>Presence</u>	<u>Range</u>	<u>IE Type and Reference</u>	<u>Semantics Description</u>
<a href="#">UE Support Of Dedicated Pilots For Channel Estimation</a>			<a href="#">ENUMERATED (Dedicated pilots for channel estimation supported)</a>	

### 9.2.2.x2 UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH

The *UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH* IE indicates whether the UE supports dedicated pilots for channel estimation or not with HS-DSCH.

<u>IE/Group Name</u>	<u>Presence</u>	<u>Range</u>	<u>IE Type and Reference</u>	<u>Semantics Description</u>
<a href="#">UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH</a>			<a href="#">ENUMERATED (Dedicated pilots for channel estimation supported)</a>	

### 9.2.2.x3 Primary CPICH Usage For Channel Estimation

The *Primary CPICH Usage For Channel Estimation* IE indicates whether the Primary CPICH may be used for channel estimation or not.

<u>IE/Group Name</u>	<u>Presence</u>	<u>Range</u>	<u>IE Type and Reference</u>	<u>Semantics Description</u>
<a href="#">Primary CPICH Usage For Channel Estimation</a>			<a href="#">ENUMERATED (Primary CPICH may be used, Primary CPICH shall not be used)</a>	

### 9.2.2.x4 Secondary CPICH Information

The *Secondary CPICH Information* IE provides the information on the Secondary CPICH when it can be used for channel estimation.

<u>IE/Group Name</u>	<u>Presence</u>	<u>Range</u>	<u>IE Type and Reference</u>	<u>Semantics Description</u>
<a href="#">DL Scrambling Code</a>			<a href="#">9.2.2.11</a>	
<a href="#">FDD DL Channelisation Code Number</a>			<a href="#">9.2.2.14</a>	

### 9.2.2.x5 Secondary CPICH Information Change

The *Secondary CPICH Information Change* IE indicates modification of information of the Secondary CPICH for channel estimation.

<u>IE/Group Name</u>	<u>Presence</u>	<u>Range</u>	<u>IE Type and Reference</u>	<u>Semantics Description</u>
<u>CHOICE Secondary CPICH Information Change</u>				
<u>&gt;New Secondary CPICH</u>				
<u>&gt;&gt;Secondary CPICH Information</u>	<u>M</u>		<u>9.2.2.x4</u>	
<u>&gt;Secondary CPICH Shall Not Be Used</u>			<u>NULL</u>	

### 9.2.2.x7 Phase Reference Update Indicator

The *Phase Reference Update Indicator* IE indicates that the phase reference for the radio link needs to be changed.

<u>IE/Group Name</u>	<u>Presence</u>	<u>Range</u>	<u>IE Type and Reference</u>	<u>Semantics Description</u>
<u>Phase Reference Update indicator</u>			<u>ENUMERATED</u> <u>(Phase Reference needs to be changed)</u>	

### 9.3.3 PDU Definitions

```
-- ****
-- PDU definitions for RNSAP.
-- ****

RNSAP-PDU-Contents {
    itu-t (0) identified-organization (4) etsi (0) mobileDomain (0)
    umts-Access (20) modules (3) rnsap (1) version1 (1) rnsap-PDU-Contents (1) }

DEFINITIONS AUTOMATIC TAGS :=

BEGIN

-- ****
-- IE parameter types from other modules.
-- ****

IMPORTS
    Active-Pattern-Sequence-Information,
    AllocationRetentionPriority,
    AllowedQueueingTime,
    Allowed-Rate-Information,
    AlphaValue,
    AntennaColocationIndicator,
    BLER,
    SCTD-Indicator,
    BindingID,
    C-ID,
    C-RNTI,
    CCTrCH-ID,
    CFN,
    ClosedLoopMode1-SupportIndicator,
    ClosedLoopMode2-SupportIndicator,
    ClosedloopTimingadjustmentmode,
    CN-CS-DomainIdentifier,
    CN-PS-DomainIdentifier,
    CNDomainType,
    Cause,
    CellCapabilityContainer-FDD,
    CellCapabilityContainer-TDD,
    CellCapabilityContainer-TDD-LCR,
    CellParameterID,
    ChipOffset,
    CommonMeasurementAccuracy,
    CommonMeasurementType,
```

CommonMeasurementValue,  
CommonMeasurementValueInformation,  
CommonTransportChannelResourcesInitialisationNotRequired,  
CongestionCause,  
CoverageIndicator,  
CriticalityDiagnostics,  
D-RNTI,  
D-RNTI-ReleaseIndication,  
DCH-FDD-Information,  
DCH-ID,  
DCH-InformationResponse,  
DCH-TDD-Information,  
DL-DPCH-SlotFormat,  
DL-TimeslotISCP,  
DL-Power,  
DL-PowerBalancing-Information,  
DL-PowerBalancing-ActivationIndicator,  
DL-PowerBalancing-UpdatedIndicator,  
DL-ReferencePowerInformation,  
DL-ScramblingCode,  
DL-Timeslot-Information,  
DL-TimeslotLCR-Information,  
DL-TimeSlot-ISCP-Info,  
DL-TimeSlot-ISCP-LCR-Information,  
DPC-Mode,  
DPC-Mode-Change-SupportIndicator,  
DPCH-ID,  
DL-DPCH-TimingAdjustment,  
DRACControl,  
DRXCycleLengthCoefficient,  
DedicatedMeasurementType,  
DedicatedMeasurementValue,  
DedicatedMeasurementValueInformation,  
DelayedActivation,  
DelayedActivationUpdate,  
DiversityControlField,  
DiversityMode,  
DSCH-FDD-Information,  
DSCH-FDD-InformationResponse,  
DSCH-FlowControlInformation,  
DSCH-FlowControlItem,  
DSCH-TDD-Information,  
DSCH-ID,  
DSCH-RNTI,  
SchedulingPriorityIndicator,  
EnhancedDSCHPC,  
EnhancedDSCHPCCounter,  
EnhancedDSCHPCIIndicator,  
EnhancedDSCHPCWnd,  
EnhancedDSCHPowerOffset,  
Enhanced-PrimaryCPICH-EcNo,

FACH-FlowControlInformation,  
FDD-DCHs-to-Modify,  
FDD-DL-ChannelisationCodeNumber,  
FDD-DL-CodeInformation,  
FDD-S-CCPCH-Offset,  
FDD-TPC-DownlinkStepSize,  
FirstRLS-Indicator,  
FNReportingIndicator,  
FrameHandlingPriority,  
FrameOffset,  
GA-AccessPointPosition,  
GA-Cell,  
GA-CellAdditionalShapes,  
HCS-Prio,  
HSDSCH-FDD-Information,  
HSDSCH-FDD-Information-Response,  
HSDSCH-FDD-Update-Information,  
HSDSCH-TDD-Update-Information,  
HSDSCH-Information-to-Modify,  
HSDSCH-MACdFlow-ID,  
HSDSCH-RNTI,  
HSDSCH-TDD-Information,  
HSDSCH-TDD-Information-Response,  
HS-SICH-ID,  
IMSI,  
InformationExchangeID,  
InformationReportCharacteristics,  
InformationType,  
InnerLoopDLPCTStatus,  
L3-Information,  
SplitType,  
LengthOfTFCI2,  
LimitedPowerIncrease,  
MaximumAllowedULTxPower,  
MaxNrDLPhysicalchannels,  
MaxNrDLPhysicalchannelsTS,  
MaxNrOfUL-DPCHs,  
MaxNrTimeslots,  
MaxNrULPhysicalchannels,  
MeasurementFilterCoefficient,  
MeasurementID,  
MidambleAllocationMode,  
MidambleShiftAndBurstType,  
MidambleShiftLCR,  
MinimumSpreadingFactor,  
MinUL-ChannelisationCodeLength,  
MultiplexingPosition,  
NeighbouringFDDCellMeasurementInformation,  
NeighbouringTDDCellMeasurementInformation,  
Neighbouring-GSM-CellInformation,  
Neighbouring-UMTS-CellInformation,

NeighbouringTDDCellMeasurementInformationLCR,  
NrOfDLchannelisationcodes,  
PagingCause,  
PagingRecordType,  
PartialReportingIndicator,  
PDSCHCodeMapping,  
PayloadCRC-PresenceIndicator,  
PCCPCH-Power,  
PC-Preamble,  
Permanent-NAS-UE-Identity,  
Phase-Reference-Update-Indicator,  
Phase-Reference-Update-InformationList,  
PowerAdjustmentType,  
PowerOffset,  
PrimaryCCPCH-RSCP,  
PrimaryCPICH-EcNo,  
PrimaryCPICH-Power,  
Primary-CPICH-Usage-For-Channel-Estimation,  
PrimaryScramblingCode,  
PropagationDelay,  
PunctureLimit,  
QE-Selector,  
Qth-Parameter,  
RANAP-RelocationInformation,  
RB-Info,  
RL-ID,  
RL-Set-ID,  
RNC-ID,  
RepetitionLength,  
RepetitionPeriod,  
ReportCharacteristics,  
Received-total-wide-band-power,  
RequestedDataValue,  
RequestedDataValueInformation,  
RL-Specific-DCH-Info,  
RxTimingDeviationForTA,  
S-FieldLength,  
S-RNTI,  
SCH-TimeSlot,  
SAI,  
SFN,  
Secondary-CCPCH-Info,  
Secondary-CCPCH-Info-TDD,  
Secondary-CPICH-Information,  
Secondary-CPICH-Information-Change,  
Secondary-LCR-CCPCH-Info-TDD,  
SNA-Information,  
SpecialBurstScheduling,  
SSDT-CellID,  
SSDT-CellID-Length,  
SSDT-Indication,

SSDT-SupportIndicator,  
STD-Indicator,  
STD-SupportIndicator,  
AdjustmentPeriod,  
ScaledAdjustmentRatio,  
MaxAdjustmentStep,  
SecondaryCCPCH-SlotFormat,  
SRB-Delay,  
Support-8PSK,  
SyncCase,  
SynchronisationConfiguration,  
TDD-ChannelisationCode,  
TDD-DCHs-to-Modify,  
TDD-DL-Code-Information,  
TDD-DPCHOFFSET,  
TDD-PhysicalChannelOffset,  
TDD-TPC-DownlinkStepSize,  
TDD-ChannelisationCodeLCR,  
TDD-DL-Code-LCR-Information,  
TDD-UL-Code-Information,  
TDD-UL-Code-LCR-Information,  
TFCI-Coding,  
TFCI-PC-SupportIndicator,  
TFCI-Presence,  
TFCI-SignallingMode,  
TimeSlot,  
TimeSlotLCR,  
TimingAdvanceApplied,  
ToAWE,  
ToAWS,  
TrafficClass,  
TransmitDiversityIndicator,  
TransportBearerID,  
TransportBearerRequestIndicator,  
TFCS,  
Transmission-Gap-Pattern-Sequence-Information,  
TransportFormatManagement,  
TransportFormatSet,  
TransportLayerAddress,  
TrCH-SrcStatisticsDescr,  
TSTD-Indicator,  
TSTD-Support-Indicator,  
UARFCN,  
UC-ID,  
[UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation,](#)  
[UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH,](#)  
UL-DPCCH-SlotFormat,  
UL-SIR,  
UL-FP-Mode,  
UL-PhysCH-SF-Variation,  
UL-ScramblingCode,

UL-Timeslot-Information,  
UL-TimeslotLCR-Information,  
UL-TimeSlot-ISCP-Info,  
UL-TimeSlot-ISCP-LCR-Info,  
URA-ID,  
URA-Information,  
USCH-ID,  
USCH-Information,  
UL-Synchronisation-Parameters-LCR,  
TDD-DL-DPCH-TimeSlotFormat-LCR,  
TDD-UL-DPCH-TimeSlotFormat-LCR,  
MAChs-ResetIndicator,  
UL-TimingAdvanceCtrl-LCR,  
TDD-TPC-UplinkStepSize-LCR  
FROM RNSAP-IES

PrivateIE-Container{},  
ProtocolExtensionContainer{},  
ProtocolIE-ContainerList{},  
ProtocolIE-ContainerPair{},  
ProtocolIE-ContainerPairList{},  
ProtocolIE-Container{},  
ProtocolIE-Single-Container{},  
RNSAP-PRIVATE-IES,  
RNSAP-PROTOCOL-EXTENSION,  
RNSAP-PROTOCOL-IES,  
RNSAP-PROTOCOL-IES-PAIR  
FROM RNSAP-Containers

maxNoOfDSCHs,  
maxNoOfUSCHs,  
maxNrOfCCTrCHs,  
maxNrOfDCHs,  
maxNrOfTS,  
maxNrOfDPCHs,  
maxNrOfRLs,  
maxNrOfRLSets,  
maxNrOfRLSets-1,  
maxNrOfRLs-1,  
maxNrOfRLs-2,  
maxNrOfULTs,  
maxNrOfDLTs,  
maxResetContext,  
maxNoOfDSCHsLCR,  
maxNoOfUSCHsLCR,  
maxNrOfCCTrCHsLCR,  
maxNrOfTsLCR,  
maxNrOfDLTsLCR,  
maxNrOfULTsLCR,  
maxNrOfDPCHsLCR,  
maxNrOfLCRTDDNeighboursPerRNC,

maxNrOfMeasNCell,  
maxNrOfMACdFlows,  
maxNrOfHSSICHs,  
  
id-Active-Pattern-Sequence-Information,  
id-AdjustmentRatio,  
id-AllowedQueuingTime,  
id-AntennaColocationIndicator,  
id-BindingID,  
id-C-ID,  
id-C-RNTI,  
id-CFN,  
id-CFNReportingIndicator,  
id-CN-CS-DomainIdentifier,  
id-CN-PS-DomainIdentifier,  
id-Cause,  
id-CauseLevel-RL-AdditionFailureFDD,  
id-CauseLevel-RL-AdditionFailureTDD,  
id-CauseLevel-RL-ReconfFailure,  
id-CauseLevel-RL-SetupFailureFDD,  
id-CauseLevel-RL-SetupFailureTDD,  
id-CCTrCH-InformationItem-RL-FailureInd,  
id-CCTrCH-InformationItem-RL-RestoreInd,  
id-CellCapabilityContainer-FDD,  
id-CellCapabilityContainer-TDD,  
id-CellCapabilityContainer-TDD-LCR,  
id-ClosedLoopMode1-SupportIndicator,  
id-ClosedLoopMode2-SupportIndicator,  
id-CNOriginatedPage-PagingRqst,  
id-CommonMeasurementAccuracy,  
id-CommonMeasurementObjectType-CM-Rprt,  
id-CommonMeasurementObjectType-CM-Rqst,  
id-CommonMeasurementObjectType-CM-Rsp,  
id-CommonMeasurementType,  
id-CommonTransportChannelResourcesInitialisationNotRequired,  
id-CongestionCause,  
id-CoverageIndicator,  
id-CriticalityDiagnostics,  
id-D-RNTI,  
id-D-RNTI-ReleaseIndication,  
id-DCHs-to-Add-FDD,  
id-DCHs-to-Add-TDD,  
id-DCH-DeleteList-RL-ReconfPrepFDD,  
id-DCH-DeleteList-RL-ReconfPrepTDD,  
id-DCH-DeleteList-RL-ReconfRqstFDD,  
id-DCH-DeleteList-RL-ReconfRqstTDD,  
id-DCH-FDD-Information,  
id-DCH-TDD-Information,  
id-FDD-DCHs-to-Modify,  
id-TDD-DCHs-to-Modify,  
id-DCH-InformationResponse,

id-DCH-Rate-InformationItem-RL-CongestInd,  
id-DL-CCTrCH-InformationAddItem-RL-ReconfPrepTDD,  
id-DL-CCTrCH-InformationDeleteItem-RL-ReconfPrepTDD,  
id-DL-CCTrCH-InformationModifyItem-RL-ReconfPrepTDD,  
id-DL-CCTrCH-InformationListIE-RL-ReconfReadyTDD,  
id-DL-CCTrCH-InformationModifyItem-RL-ReconfRqstTDD,  
id-DL-CCTrCH-InformationDeleteItem-RL-ReconfRqstTDD,  
id-DL-CCTrCH-InformationItem-RL-SetupRqstTDD,  
id-DL-CCTrCH-InformationListIE-PhyChReconfRqstTDD,  
id-DL-CCTrCH-InformationListIE-RL-AdditionRspTDD,  
id-DL-CCTrCH-InformationListIE-RL-SetupRspTDD,  
id-DL-CCTrCH-InformationAddList-RL-ReconfPrepTDD,  
id-DL-CCTrCH-InformationDeleteList-RL-ReconfPrepTDD,  
id-DL-CCTrCH-InformationModifyList-RL-ReconfPrepTDD,  
id-DL-CCTrCH-InformationDeleteList-RL-ReconfRqstTDD,  
id-DL-CCTrCH-InformationModifyList-RL-ReconfRqstTDD,  
id-DL-CCTrCH-InformationList-RL-SetupRqstTDD,  
id-FDD-DL-CodeInformation,  
id-DL-DPCH-Information-RL-ReconfPrepFDD,  
id-DL-DPCH-Information-RL-SetupRqstFDD,  
id-DL-DPCH-Information-RL-ReconfRqstFDD,  
id-DL-DPCH-InformationItem-PhyChReconfRqstTDD,  
id-DL-DPCH-InformationItem-RL-AdditionRspTDD,  
id-DL-DPCH-InformationItem-RL-SetupRspTDD,  
id-DL-DPCH-InformationAddListIE-RL-ReconfReadyTDD,  
id-DL-DPCH-InformationDeleteListIE-RL-ReconfReadyTDD,  
id-DL-DPCH-InformationModifyListIE-RL-ReconfReadyTDD,  
id-DL-DPCH-TimingAdjustment,  
id-DL-Physical-Channel-Information-RL-SetupRqstTDD,  
id-DL-PowerBalancing-Information,  
id-DL-PowerBalancing-ActivationIndicator,  
id-DL-PowerBalancing-UpdatedIndicator,  
id-DL-ReferencePowerInformation,  
id-DLReferencePower,  
id-DLReferencePowerList-DL-PC-Rqst,  
id-DL-ReferencePowerInformation-DL-PC-Rqst,  
id-DRXCycleLengthCoefficient,  
id-DedicatedMeasurementObjectType-DM-Fail,  
id-DedicatedMeasurementObjectType-DM-Fail-Ind,  
id-DedicatedMeasurementObjectType-DM-Rprt,  
id-DedicatedMeasurementObjectType-DM-Rqst,  
id-DedicatedMeasurementObjectType-DM-Rsp,  
id-DedicatedMeasurementType,  
id-DelayedActivation,  
id-DelayedActivationList-RL-ActivationCmdFDD,  
id-DelayedActivationList-RL-ActivationCmdTDD,  
id-DelayedActivationInformation-RL-ActivationCmdFDD,  
id-DelayedActivationInformation-RL-ActivationCmdTDD,  
id-DPC-Mode,  
id-DPC-Mode-Change-SupportIndicator,  
id-DSCHs-to-Add-FDD,

id-DSCHs-to-Add-TDD,  
id-DSCH-DeleteList-RL-ReconfPrepTDD,  
id-DSCH-Delete-RL-ReconfPrepFDD,  
id-DSCH-FDD-Information,  
id-DSCH-InformationListIE-RL-AdditionRspTDD,  
id-DSCH-InformationListIEs-RL-SetupRspTDD,  
id-DSCH-TDD-Information,  
id-DSCH-FDD-InformationResponse,  
id-DSCH-ModifyList-RL-ReconfPrepTDD,  
id-DSCH-Modify-RL-ReconfPrepFDD,  
id-DSCH-RNTI,  
id-DSCHsToBeAddedOrModified-FDD,  
id-DSCHToBeAddedOrModifiedList-RL-ReconfReadyTDD,  
id-EnhancedDSCHPC,  
id-EnhancedDSCHPCIndicator,  
id-Enhanced-PrimaryCPICH-EcNo,  
id-FACH-InfoForUESelectedS-CCPCH-CTCH-ResourceRspFDD,  
id-FACH-InfoForUESelectedS-CCPCH-CTCH-ResourceRspTDD,  
id-GA-Cell,  
id-GA-CellAdditionalShapes,  
id-HCS-Prio,  
id-HSDSCH-FDD-Information,  
id-HSDSCH-FDD-Information-Response,  
id-HSDSCH-FDD-Information-to-Add,  
id-HSDSCH-FDD-Information-to-Delete,  
id-HSDSCH-FDD-Update-Information,  
id-HSDSCH-TDD-Update-Information,  
id-HSDSCH-Information-to-Modify,  
id-HSDSCH-RNTI,  
id-HSDSCH-TDD-Information,  
id-HSDSCH-TDD-Information-Response,  
id-HSDSCH-TDD-Information-Response-LCR,  
id-HSDSCH-TDD-Information-to-Add,  
id-HSDSCH-TDD-Information-to-Delete,  
id-HSPDSCH-RL-ID,  
id-HSPDSCH-Timeslot-InformationList-PhyChReconfRqstTDD,  
id-HSPDSCH-Timeslot-InformationListLCR-PhyChReconfRqstTDD,  
id-HSSICH-Info-DM-Rprt,  
id-HSSICH-Info-DM-Rqst,  
id-HSSICH-Info-DM-Rsp,  
id-IMSI,  
id-InformationExchangeID,  
id-InformationExchangeObjectType-InfEx-Rprt,  
id-InformationExchangeObjectType-InfEx-Rqst,  
id-InformationExchangeObjectType-InfEx-Rsp,  
id-InformationReportCharacteristics,  
id-InformationType,  
id-InnerLoopDLPCTStatus,  
id-SplitType,  
id-LengthOfTFCI2,  
id-L3-Information,

id-AdjustmentPeriod,  
id-MaxAdjustmentStep,  
id-MeasurementFilterCoefficient,  
id-MeasurementID,  
id-PagingArea-PagingRqst,  
id-PartialReportingIndicator,  
id-PDSCH-RL-ID,  
id-Permanent-NAS-UE-Identity,  
id-FACH-FlowControlInformation,  
id-PowerAdjustmentType,  
id-PrimCCPCH-RSCP-DL-PC-RqstTDD,  
[id-Primary-CPICH-Usage-For-Channel-Estimation,](#)  
id-PropagationDelay,  
id-Qth-Parameter,  
id-RANAP-RelocationInformation,  
id-ResetIndicator,  
id-RL-Information-PhyChReconfRqstFDD,  
id-RL-Information-PhyChReconfRqstTDD,  
id-RL-Information-RL-AdditionRqstFDD,  
id-RL-Information-RL-AdditionRqstTDD,  
id-RL-Information-RL-DeletionRqst,  
id-RL-Information-RL-FailureInd,  
id-RL-Information-RL-ReconfPrepFDD,  
id-RL-Information-RL-RestoreInd,  
id-RL-Information-RL-SetupRqstFDD,  
id-RL-Information-RL-SetupRqstTDD,  
id-RL-InformationItem-RL-CongestInd,  
id-RL-InformationItem-DM-Rprt,  
id-RL-InformationItem-DM-Rqst,  
id-RL-InformationItem-DM-Rsp,  
id-RL-InformationItem-RL-PreemptRequiredInd,  
id-RL-InformationItem-RL-SetupRqstFDD,  
id-RL-InformationList-RL-CongestInd,  
id-RL-InformationList-RL-AdditionRqstFDD,  
id-RL-InformationList-RL-DeletionRqst,  
id-RL-InformationList-RL-PreemptRequiredInd,  
id-RL-InformationList-RL-ReconfPrepFDD,  
id-RL-InformationResponse-RL-AdditionRspTDD,  
id-RL-InformationResponse-RL-ReconfReadyTDD,  
id-RL-InformationResponse-RL-ReconfRspTDD,  
id-RL-InformationResponse-RL-SetupRspTDD,  
id-RL-InformationResponseItem-RL-AdditionRspFDD,  
id-RL-InformationResponseItem-RL-ReconfReadyFDD,  
id-RL-InformationResponseItem-RL-ReconfRspFDD,  
id-RL-InformationResponseItem-RL-SetupRspFDD,  
id-RL-InformationResponseList-RL-AdditionRspFDD,  
id-RL-InformationResponseList-RL-ReconfReadyFDD,  
id-RL-InformationResponseList-RL-ReconfRspFDD,  
id-RL-InformationResponseList-RL-SetupRspFDD,  
[id-RL-ParameterUpdateIndicationFDD-RL-Information-Item,](#)  
[id-RL-ParameterUpdateIndicationFDD-RL-InformationList,](#)

id-RL-ReconfigurationFailure-RL-ReconfFail,  
id-RL-ReconfigurationReadyTDD-RL-Information,  
id-RL-ReconfigurationRequestFDD-RL-InformationList,  
id-RL-ReconfigurationRequestFDD-RL-Information-IEs,  
id-RL-ReconfigurationRequestTDD-RL-Information,  
id-RL-Specific-DCH-Info,  
id-RL-Set-InformationItem-DM-Rprt,  
id-RL-Set-InformationItem-DM-Rqst,  
id-RL-Set-InformationItem-DM-Rsp,  
id-RL-Set-Information-RL-FailureInd,  
id-RL-Set-Information-RL-RestoreInd,  
id-RL-Set-Successful-InformationItem-DM-Fail,  
id-RL-Set-Unsuccessful-InformationItem-DM-Fail,  
id-RL-Unsuccessful-InformationItem-DM-Fail-Ind,  
id-RL-Successful-InformationItem-DM-Fail,  
id-RL-Unsuccessful-InformationItem-DM-Fail,  
id-RL-Unsuccessful-InformationItem-DM-Fail-Ind,  
id-ReportCharacteristics,  
id-Reporting-Object-RL-FailureInd,  
id-Reporting-Object-RL-RestoreInd,  
id-RNC-ID,  
id-RxTimingDeviationForTA,  
id-S-RNTI,  
id-SAI,  
id-Secondary-CPICH-Information,  
id-Secondary-CPICH-Information-Change,  
id-SFN,  
id-SFNReportingIndicator,  
id-SNA-Information,  
id-SRNC-ID,  
id-SSDT-CellIDforEDSCHPC,  
id-STTD-SupportIndicator,  
id-SuccessfulRL-InformationResponse-RL-AdditionFailureFDD,  
id-SuccessfulRL-InformationResponse-RL-SetupFailureFDD,  
id-TDD-maxNrDLPhysicalchannels,  
id-TDD-Support-8PSK,  
id-TFCI-PC-SupportIndicator,  
id-timeSlot-ISCP,  
id-TimeSlot-RL-SetupRspTDD,  
id-TransportBearerID,  
id-TransportBearerRequestIndicator,  
id-TransportLayerAddress,  
id-UC-ID,  
id-ContextInfoItem-Reset,  
id-Transmission-Gap-Pattern-Sequence-Information,  
id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation,  
id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH,  
id-UL-CCTrCH-AddInformation-RL-ReconfPrepTDD,  
id-UL-CCTrCH-DeleteInformation-RL-ReconfPrepTDD,  
id-UL-CCTrCH-ModifyInformation-RL-ReconfPrepTDD,  
id-UL-CCTrCH-InformationDeleteItem-RL-ReconfRqstTDD,

id-UL-CCTrCH-InformationModifyItem-RL-ReconfRqstTDD,  
id-UL-CCTrCH-InformationAddList-RL-ReconfPrepTDD,  
id-UL-CCTrCH-InformationDeleteList-RL-ReconfPrepTDD,  
id-UL-CCTrCH-InformationModifyList-RL-ReconfPrepTDD,  
id-UL-CCTrCH-InformationDeleteList-RL-ReconfRqstTDD,  
id-UL-CCTrCH-InformationModifyList-RL-ReconfRqstTDD,  
id-UL-CCTrCH-InformationItem-RL-SetupRqstTDD,  
id-UL-CCTrCH-InformationList-RL-SetupRqstTDD,  
id-UL-CCTrCH-InformationListIE-PhyChReconfRqstTDD,  
id-UL-CCTrCH-InformationListIE-RL-AdditionRspTDD,  
id-UL-CCTrCH-InformationListIE-RL-ReconfReadyTDD,  
id-UL-CCTrCH-InformationListIE-RL-SetupRspTDD,  
id-UL-DPCH-Information-RL-ReconfPrepFDD,  
id-UL-DPCH-Information-RL-ReconfRqstFDD,  
id-UL-DPCH-Information-RL-SetupRqstFDD,  
id-UL-DPCH-InformationItem-PhyChReconfRqstTDD,  
id-UL-DPCH-InformationItem-RL-AdditionRspTDD,  
id-UL-DPCH-InformationItem-RL-SetupRspTDD,  
id-UL-DPCH-InformationAddListIE-RL-ReconfReadyTDD,  
id-UL-DPCH-InformationDeleteListIE-RL-ReconfReadyTDD,  
id-UL-DPCH-InformationModifyListIE-RL-ReconfReadyTDD,  
id-UL-Physical-Channel-Information-RL-SetupRqstTDD,  
id-UL-SIRTarget,  
id-URA-Information,  
id-UnsuccessfulRL-InformationResponse-RL-AdditionFailureFDD,  
id-UnsuccessfulRL-InformationResponse-RL-AdditionFailureTDD,  
id-UnsuccessfulRL-InformationResponse-RL-SetupFailureFDD,  
id-UnsuccessfulRL-InformationResponse-RL-SetupFailureTDD,  
id-USCHs-to-Add,  
id-USCH-DeleteList-RL-ReconfPrepTDD,  
id-USCH-InformationListIE-RL-AdditionRspTDD,  
id-USCH-InformationListIES-RL-SetupRspTDD,  
id-USCH-Information,  
id-USCH-ModifyList-RL-ReconfPrepTDD,  
id-USCHToBeAddedOrModifiedList-RL-ReconfReadyTDD,  
id-DL-Timeslot-ISCP-LCR-Information-RL-SetupRqstTDD,  
id-RL-LCR-InformationResponse-RL-SetupRspTDD,  
id-UL-CCTrCH-LCR-InformationListIE-RL-SetupRspTDD,  
id-UL-DPCH-LCR-InformationItem-RL-SetupRspTDD,  
id-DL-CCTrCH-LCR-InformationListIE-RL-SetupRspTDD,  
id-DL-DPCH-LCR-InformationItem-RL-SetupRspTDD,  
id-DSCH-LCR-InformationListIES-RL-SetupRspTDD,  
id-USCH-LCR-InformationListIES-RL-SetupRspTDD,  
id-DL-Timeslot-ISCP-LCR-Information-RL-AdditionRqstTDD,  
id-RL-LCR-InformationResponse-RL-AdditionRspTDD,  
id-UL-CCTrCH-LCR-InformationListIE-RL-AdditionRspTDD,  
id-UL-DPCH-LCR-InformationItem-RL-AdditionRspTDD,  
id-DL-CCTrCH-LCR-InformationListIE-RL-AdditionRspTDD,  
id-DL-DPCH-LCR-InformationItem-RL-AdditionRspTDD,  
id-DSCH-LCR-InformationListIES-RL-AdditionRspTDD,  
id-USCH-LCR-InformationListIES-RL-AdditionRspTDD,

```

id-UL-DPCH-LCR-InformationAddListIE-RL-ReconfReadyTDD,
id-UL-Timeslot-LCR-InformationModifyList-RL-ReconfReadyTDD,
id-DL-DPCH-LCR-InformationAddListIE-RL-ReconfReadyTDD,
id-DL-Timeslot-LCR-InformationModifyList-RL-ReconfReadyTDD,
id-UL-Timeslot-LCR-InformationList-PhyChReconfRqstTDD,
id-DL-Timeslot-LCR-InformationList-PhyChReconfRqstTDD,
id-timeSlot-ISCP-LCR-List-DL-PC-Rqst-TDD,
id-TSTD-Support-Indicator-RL-SetupRqstTDD,
id-PrimaryCCPCH-RSCP-RL-ReconfPrepTDD,
id-DL-TimeSlot-ISCP-Info-RL-ReconfPrepTDD,
id-DL-Timeslot-ISCP-LCR-Information-RL-ReconfPrepTDD,
id-neighbouringTDDCellMeasurementInformationLCR,
id-UL-SIR-Target-CCTrCH-InformationItem-RL-SetupRspTDD,
id-UL-SIR-Target-CCTrCH-LCR-InformationItem-RL-SetupRspTDD,
id-TrafficClass,
id-UL-Synchronisation-Parameters-LCR,
id-TDD-DL-DPCH-TimeSlotFormatModifyItem-LCR-RL-ReconfReadyTDD,
id-TDD-UL-DPCH-TimeSlotFormatModifyItem-LCR-RL-ReconfReadyTDD,
id-MAChs-ResetIndicator,
id-UL-TimingAdvanceCtrl-LCR,
id-CCTrCH-Maximum-DL-Power-RL-SetupRspTDD,
id-CCTrCH-Minimum-DL-Power-RL-SetupRspTDD,
id-CCTrCH-Maximum-DL-Power-RL-AdditionRspTDD,
id-CCTrCH-Minimum-DL-Power-RL-AdditionRspTDD,
id-CCTrCH-Maximum-DL-Power-RL-ReconfReadyTDD,
id-CCTrCH-Minimum-DL-Power-RL-ReconfReadyTDD,
id-Maximum-DL-Power-TimeslotLCR-InformationModifyItem-RL-ReconfReadyTDD,
id-Minimum-DL-Power-TimeslotLCR-InformationModifyItem-RL-ReconfReadyTDD,
id-DL-CCTrCH-InformationList-RL-ReconfRspTDD,
id-DL-DPCH-InformationModifyItem-LCR-RL-ReconfRspTDD,
id-TDD-TPC-UplinkStepSize-LCR-RL-SetupRqstTDD,
id-UL-CCTrCH-InformationList-RL-AdditionRqstTDD,
id-UL-CCTrCH-InformationItem-RL-AdditionRqstTDD,
id-DL-CCTrCH-InformationList-RL-AdditionRqstTDD,
id-DL-CCTrCH-InformationItem-RL-AdditionRqstTDD,
id-TDD-TPC-UplinkStepSize-InformationAdd-LCR-RL-ReconfPrepTDD,
id-TDD-TPC-UplinkStepSize-InformationModify-LCR-RL-ReconfPrepTDD,
id-TDD-TPC-DownlinkStepSize-InformationAdd-RL-ReconfPrepTDD,
id-TDD-TPC-DownlinkStepSize-InformationModify-RL-ReconfPrepTDD

FROM RNSAP-Constants;

-- ****
-- 
-- RADIO LINK SETUP REQUEST FDD
-- 
-- ****

RadioLinkSetupRequestFDD ::= SEQUENCE {
    protocolIEs          ProtocolIE-Container {{RadioLinkSetupRequestFDD-IES}},
    protocolExtensions   ProtocolExtensionContainer {{RadioLinkSetupRequestFDD-Extensions}} OPTIONAL,
}

```

```

}
...
}

RadioLinkSetupRequestFDD-IEs RNSAP-PROTOCOL-IES ::= {
{ ID id-SRNC-ID           CRITICALITY reject   TYPE RNC-ID           PRESENCE mandatory} |
{ ID id-S-RNTI            CRITICALITY reject   TYPE S-RNTI           PRESENCE mandatory } |
{ ID id-D-RNTI            CRITICALITY reject   TYPE D-RNTI           PRESENCE optional } |
{ ID id-AllowedQueuingTime CRITICALITY reject   TYPE AllowedQueuingTime PRESENCE optional } |
{ ID id-UL-DPCH-Information-RL-SetupRqstFDD CRITICALITY reject   TYPE UL-DPCH-Information-RL-SetupRqstFDD  PRESENCE mandatory } |
{ ID id-DL-DPCH-Information-RL-SetupRqstFDD CRITICALITY reject   TYPE DL-DPCH-Information-RL-SetupRqstFDD  PRESENCE mandatory } |
{ ID id-DCH-FDD-Information CRITICALITY reject   TYPE DCH-FDD-Information PRESENCE mandatory } |
{ ID id-DSCH-FDD-Information CRITICALITY reject   TYPE DSCH-FDD-Information PRESENCE optional } |
{ ID id-RL-Information-RL-SetupRqstFDD    CRITICALITY notify   TYPE RL-InformationList-RL-SetupRqstFDD  PRESENCE mandatory } |
{ ID id-Transmission-Gap-Pattern-Sequence-Information CRITICALITY reject   TYPE Transmission-Gap-Pattern-Sequence-Information PRESENCE optional } |
{ ID id-Active-Pattern-Sequence-Information CRITICALITY reject   TYPE Active-Pattern-Sequence-Information  PRESENCE optional },
...
}

UL-DPCH-Information-RL-SetupRqstFDD ::= SEQUENCE {
  ul-ScramblingCode          UL-ScramblingCode,
  minUL-ChannelisationCodeLength MinUL-ChannelisationCodeLength,
  maxNrOfUL-DPCHs             MaxNrOfUL-DPCHs      OPTIONAL
  -- This IE shall be present if minUL-ChannelisationCodeLength equals to 4 --
  ul-PunctureLimit            PunctureLimit,
  ul-TFCs                      TFCS,
  ul-DPCCH-SlotFormat         UL-DPCCH-SlotFormat,
  ul-SIR                       UL-SIR      OPTIONAL,
  diversityMode                DiversityMode,
  ssDT-CellIdLength            SSIDT-CellID-Length  OPTIONAL,
  s-FieldLength                S-FieldLength      OPTIONAL,
  iE-Extensions                ProtocolExtensionContainer { UL-DPCH-Information-RL-SetupRqstFDD-ExtIEs } OPTIONAL,
...
}

UL-DPCH-Information-RL-SetupRqstFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
{ ID id-DPC-Mode           CRITICALITY reject   EXTENSION DPC-Mode  PRESENCE optional } ,
...
}

DL-DPCH-Information-RL-SetupRqstFDD ::= SEQUENCE {
  tFCs                      TFCS,
  dl-DPCH-SlotFormat        DL-DPCH-SlotFormat,
  nrOfDLchannelisationcodes NrOfDLchannelisationcodes,
  tFCI-SignallingMode       TFCI-SignallingMode,
  tFCI-Presence              TFCI-Presence      OPTIONAL
  -- This IE shall be present if DL DPCH Slot Format IE is equal to any of the values from 12 to 16 --,
  multiplexingPosition       MultiplexingPosition,
  powerOffsetInformation     PowerOffsetInformation-RL-SetupRqstFDD,
  fdd-dl-TPC-DownlinkStepSize FDD-TPC-DownlinkStepSize,
  limitedPowerIncrease       LimitedPowerIncrease,
}

```

```

innerLoopDLPCStatus           InnerLoopDLPCStatus,
iE-Extensions                 ProtocolExtensionContainer { {DL-DPCH-Information-RL-SetupRqstFDD-ExtIEs} } OPTIONAL,
...
}

DL-DPCH-Information-RL-SetupRqstFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
{ ID id-SplitType CRITICALITY reject EXTENSION SplitType PRESENCE optional }|
{ ID id-LengthOfTFCI2 CRITICALITY reject EXTENSION LengthOfTFCI2 PRESENCE optional },
...
}

PowerOffsetInformation-RL-SetupRqstFDD ::= SEQUENCE {
    pol-ForTFCI-Bits          PowerOffset,
    po2-ForTPC-Bits           PowerOffset,
    po3-ForPilotBits          PowerOffset,
    iE-Extensions              ProtocolExtensionContainer { { PowerOffsetInformation-RL-SetupRqstFDD-ExtIEs} } OPTIONAL,
...
}

PowerOffsetInformation-RL-SetupRqstFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
...
}

RL-InformationList-RL-SetupRqstFDD      ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-InformationItemIEs-RL-SetupRqstFDD} }

RL-InformationItemIEs-RL-SetupRqstFDD RNSAP-PROTOCOL-IES ::= {
{ ID id-RL-InformationItem-RL-SetupRqstFDD CRITICALITY notify TYPE RL-InformationItem-RL-SetupRqstFDD PRESENCE mandatory }
}

RL-InformationItem-RL-SetupRqstFDD ::= SEQUENCE {
    rL-ID                      RL-ID,
    c-ID                       C-ID,
    firstRLS-indicator         FirstRLS-Indicator,
    frameOffset                FrameOffset,
    chipOffset                 ChipOffset,
    propagationDelay           PropagationDelay OPTIONAL,
    diversityControlField      DiversityControlField OPTIONAL
-- This IE shall be present if the RL is not the first one in the RL-InformationList-RL-SetupRqstFDD --,
    dl-InitialTX-Power          DL-Power OPTIONAL,
    primaryCPICH-EcNo           PrimaryCPICH-EcNo OPTIONAL,
    ssDT-CellID                 SSDT-CellID OPTIONAL,
    transmitDiversityIndicator TransmitDiversityIndicator OPTIONAL,
-- This IE shall be present unless Diversity Mode IE in UL DPCH Information group is "none"
    iE-Extensions               ProtocolExtensionContainer { {RL-InformationItem-RL-SetupRqstFDD-ExtIEs} } OPTIONAL,
...
}

RL-InformationItem-RL-SetupRqstFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
{ ID id-SSDT-CellIDforEDSCHPC CRITICALITY ignore EXTENSION SSDT-CellID PRESENCE conditional }|
-- This IE shall be present if Enhanced DSCH PC IE is present in the DSCH Information IE.
}

```

```

{ ID id-Enhanced-PrimaryCPICH-EcNo           CRITICALITY ignore      EXTENSION Enhanced-PrimaryCPICH-EcNo          PRESENCE optional }|
{ ID id-RL-Specific-DCH-Info    CRITICALITY ignore      EXTENSION RL-Specific-DCH-Info      PRESENCE optional }|
{ ID id-DelayedActivation CRITICALITY reject      EXTENSION DelayedActivation PRESENCE optional }|
{ ID id-Qth-Parameter   CRITICALITY ignore      EXTENSION Qth-Parameter      PRESENCE optional },
...
}

RadioLinkSetupRequestFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
{ ID id-Permanent-NAS-UE-Identity        CRITICALITY ignore      EXTENSION Permanent-NAS-UE-Identity      PRESENCE optional }|
{ ID id-DL-PowerBalancing-Information    CRITICALITY ignore      EXTENSION DL-PowerBalancing-Information      PRESENCE optional }|
{ ID id-HSDSCH-FDD-Information          CRITICALITY reject      EXTENSION HSDSCH-FDD-Information      PRESENCE optional }|
{ ID id-HSPDSCH-RL-ID                  CRITICALITY reject      EXTENSION RL-ID      PRESENCE conditional }|
{ ID id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation      CRITICALITY ignore      EXTENSION UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation      PRESENCE optional }|
{ ID id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH      CRITICALITY ignore      EXTENSION UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH      PRESENCE optional },
...
}

/* partly omitted */

-- ****
-- 
-- RADIO LINK SETUP RESPONSE FDD
-- 
-- ****

RadioLinkSetupResponseFDD ::= SEQUENCE {
  protocolIES          ProtocolIE-Container      {{RadioLinkSetupResponseFDD-IEs}},
  protocolExtensions    ProtocolExtensionContainer {{RadioLinkSetupResponseFDD-Extensions}}          OPTIONAL,
...
}

RadioLinkSetupResponseFDD-IEs RNSAP-PROTOCOL-IES ::= {
{ ID id-D-RNTI            CRITICALITY ignore      TYPE D-RNTI      PRESENCE optional }|
{ ID id-CN-PS-DomainIdentifier    CRITICALITY ignore      TYPE CN-PS-DomainIdentifier      PRESENCE optional }|
{ ID id-CN-CS-DomainIdentifier    CRITICALITY ignore      TYPE CN-CS-DomainIdentifier      PRESENCE optional }|
{ ID id-RL-InformationResponseList-RL-SetupRspFDD    CRITICALITY ignore      TYPE RL-InformationResponseList-RL-SetupRspFDD      PRESENCE mandatory }|
{ ID id-UL-SIRTarget          CRITICALITY ignore      TYPE UL-SIR      PRESENCE optional }|
{ ID id-CriticalityDiagnostics    CRITICALITY ignore      TYPE CriticalityDiagnostics      PRESENCE optional },
...
}

RL-InformationResponseList-RL-SetupRspFDD      ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-InformationResponseItemIEs-RL-SetupRspFDD} }

RL-InformationResponseItemIEs-RL-SetupRspFDD RNSAP-PROTOCOL-IES ::= {
{ ID id-RL-InformationResponseItem-RL-SetupRspFDD    CRITICALITY ignore      TYPE RL-InformationResponseItem-RL-SetupRspFDD      PRESENCE mandatory }
}

RL-InformationResponseItem-RL-SetupRspFDD ::= SEQUENCE {

```

```

rL-ID
rL-Set-ID
uRA-Information
SAI
gA-Cell
gA-AccessPointPosition
received-total-wide-band-power
secondary-CCPCH-Info
dl-CodeInformation
diversityIndication
-- This IE represents both the Diversity Indication IE and the choice based on the diversity indication as described in
-- the tabular message format in subclause 9.1.
sSDT-SupportIndicator
maxUL-SIR
minUL-SIR
closedloopTimingAdjustmentMode
maximumAllowedULTxPower
maximumDLTxPower
minimumDLTxPower
primaryScramblingCode
uL-UARFCN
dL-UARFCN
primaryCPICH-Power
DSCHInformationResponse
neighbouring-UMTS-CellInformation
neighbouring-GSM-CellInformation
pC-Preamble
sRB-Delay
iE-Extensions
...
}

RL-InformationResponseItem-RL-SetupRspFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
  { ID id-GA-CellAdditionalShapes CRITICALITY ignore EXTENSION GA-CellAdditionalShapes PRESENCE optional } |
  { ID id-DL-PowerBalancing-ActivationIndicator CRITICALITY ignore EXTENSION DL-PowerBalancing-ActivationIndicator PRESENCE
optional } |
  { ID id-HSDSCH-FDD-Information-Response CRITICALITY ignore EXTENSION HSDSCH-FDD-Information-Response PRESENCE optional } |
  { ID id-TFCI-PC-SupportIndicator CRITICALITY ignore EXTENSION TFCI-PC-SupportIndicator PRESENCE optional } |
  { ID id-HCS-Prio CRITICALITY ignore EXTENSION HCS-Prio PRESENCE optional } |
  { ID id-Primary-CPICH-Usage-For-Channel-Estimation CRITICALITY ignore EXTENSION Primary-CPICH-Usage-For-Channel-Estimation PRESENCE
optional } |
  { ID id-Secondary-CPICH-Information CRITICALITY ignore EXTENSION Secondary-CPICH-Information PRESENCE optional },
  ...
}

DiversityIndication-RL-SetupRspFDD ::= CHOICE {
  combining
  nonCombiningOrFirstRL
}
}

Combining-RL-SetupRspFDD ::= SEQUENCE {

```

```

rL-ID
iE-Extensions
...
}

CombiningItem-RL-SetupRspFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-DCH-InformationResponse      CRITICALITY ignore   EXTENSION DCH-InformationResponse      PRESENCE optional },
    ...
}

NonCombiningOrFirstRL-RL-SetupRspFDD ::= SEQUENCE {
    dCH-InformationResponse      DCH-InformationResponse,
    iE-Extensions                ProtocolExtensionContainer { { NonCombiningOrFirstRLItem-RL-SetupRspFDD-ExtIEs } } OPTIONAL,
    ...
}

NonCombiningOrFirstRLItem-RL-SetupRspFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

DSCH-InformationResponse-RL-SetupRspFDD ::= ProtocolIE-Single-Container {{ DSCH-InformationResponseIE-RL-SetupRspFDD } }

DSCH-InformationResponseIE-RL-SetupRspFDD RNSAP-PROTOCOL-IES ::= {
    { ID id-DSCH-FDD-InformationResponse  CRITICALITY ignore   TYPE DSCH-FDD-InformationResponse PRESENCE mandatory }
}

RadioLinkSetupResponseFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-DSCH-RNTI                  CRITICALITY ignore   EXTENSION DSCH-RNTI      PRESENCE optional } |
    { ID id-HSDSCH-RNTI                CRITICALITY reject    EXTENSION HSDSCH-RNTI     PRESENCE optional },
    ...
}

/*
 * partly omitted */
-- ****
-- 
-- RADIO LINK SETUP FAILURE FDD
-- 
-- ****

RadioLinkSetupFailureFDD ::= SEQUENCE {
    protocolIEs          ProtocolIE-Container     {{RadioLinkSetupFailureFDD-IES}},
    protocolExtensions   ProtocolExtensionContainer {{RadioLinkSetupFailureFDD-Extensions}}           OPTIONAL,
    ...
}

RadioLinkSetupFailureFDD-IES RNSAP-PROTOCOL-IES ::= {
    { ID id-D-RNTI          CRITICALITY ignore   TYPE D-RNTI          PRESENCE optional } |
    { ID id-CN-PS-DomainIdentifier  CRITICALITY ignore   TYPE CN-PS-DomainIdentifier  PRESENCE optional } |
    { ID id-CN-CS-DomainIdentifier  CRITICALITY ignore   TYPE CN-CS-DomainIdentifier  PRESENCE optional } |
    { ID id-CauseLevel-RL-SetupFailureFDD  CRITICALITY ignore   TYPE CauseLevel-RL-SetupFailureFDD  PRESENCE mandatory } |
}

```

**Release 5****3GPP TS 25.423 V5.0.0(2002-03)**

```
{ ID id-UL-SIRTarget           CRITICALITY ignore  TYPE UL-SIR           PRESENCE optional } |  
{ ID id-CriticalityDiagnostics CRITICALITY ignore  TYPE CriticalityDiagnostics  PRESENCE optional },  
...  
}  
  
CauseLevel-RL-SetupFailureFDD ::= CHOICE {  
    generalCause      GeneralCauseList-RL-SetupFailureFDD,  
    rLSpecificCause   RLSpecificCauseList-RL-SetupFailureFDD,  
    ...  
}  
  
GeneralCauseList-RL-SetupFailureFDD ::= SEQUENCE {  
    cause                  Cause,  
    iE-Extensions          ProtocolExtensionContainer { { GeneralCauseItem-RL-SetupFailureFDD-ExtIEs } } OPTIONAL,  
    ...  
}  
  
GeneralCauseItem-RL-SetupFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {  
    ...  
}  
  
RLSpecificCauseList-RL-SetupFailureFDD ::= SEQUENCE {  
    unsuccessful-RL-InformationRespList-RL-SetupFailureFDD     UnsuccessfulRL-InformationResponseList-RL-SetupFailureFDD,  
    successful-RL-InformationRespList-RL-SetupFailureFDD        SuccessfulRL-InformationResponseList-RL-SetupFailureFDD OPTIONAL,  
    iE-Extensions          ProtocolExtensionContainer { { RLSpecificCauseItem-RL-SetupFailureFDD-ExtIEs } } OPTIONAL,  
    ...  
}  
  
RLSpecificCauseItem-RL-SetupFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {  
    { ID id-DSCH-RNTI          CRITICALITY ignore      EXTENSION DSCH-RNTI           PRESENCE optional } |  
    { ID id-HSDSCH-RNTI        CRITICALITY reject      EXTENSION HSDSCH-RNTI         PRESENCE optional },  
    ...  
}  
  
UnsuccessfulRL-InformationResponseList-RL-SetupFailureFDD ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container { {UnsuccessfulRL-InformationResponse-RL-SetupFailureFDD-IEs} }  
  
UnsuccessfulRL-InformationResponse-RL-SetupFailureFDD-IEs RNSAP-PROTOCOL-IES ::= {  
    { ID id-UnsuccessfulRL-InformationResponse-RL-SetupFailureFDD      CRITICALITY ignore  TYPE UnsuccessfulRL-InformationResponse-RL-SetupFailureFDD  
    PRESENCE mandatory }  
}  
  
UnsuccessfulRL-InformationResponse-RL-SetupFailureFDD ::= SEQUENCE {  
    rL-ID                 RL-ID,  
    cause                 Cause,  
    iE-Extensions          ProtocolExtensionContainer { {UnsuccessfulRL-InformationResponse-RL-SetupFailureFDD-ExtIEs} } OPTIONAL,  
    ...  
}  
  
UnsuccessfulRL-InformationResponse-RL-SetupFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {  
    ...  
}
```

```

}

SuccessfulRL-InformationResponseList-RL-SetupFailureFDD ::= SEQUENCE (SIZE (0..maxNrOfRLs-1)) OF ProtocolIE-Single-Container { {SuccessfulRL-
InformationResponse-RL-SetupFailureFDD-IES} }

SuccessfulRL-InformationResponse-RL-SetupFailureFDD-IES RNSAP-PROTOCOL-IES ::= {
  { ID id-SuccessfulRL-InformationResponse-RL-SetupFailureFDD      CRITICALITY ignore   TYPE SuccessfulRL-InformationResponse-RL-SetupFailureFDD
    PRESENCE mandatory  }
}

SuccessfulRL-InformationResponse-RL-SetupFailureFDD ::= SEQUENCE {
  rL-ID                               RL-ID,
  rL-Set-ID                            RL-Set-ID,
  uRA-Information                      URA-Information     OPTIONAL,
  sAI                                  SAI,
  gA-Cell                             GA-Cell     OPTIONAL,
  gA-AccessPointPosition               GA-AccessPointPosition     OPTIONAL,
  received-total-wide-band-power       Received-total-wide-band-power,
  secondary-CCPCH-Info                Secondary-CCPCH-Info     OPTIONAL,
  dl-CodeInformation                   FDD-DL-CodeInformation,
  diversityIndication                 DiversityIndication-RL-SetupFailureFDD,
  -- This IE represents both the Diversity Indication IE and the choice based on the diversity indication as described in
  -- the tabular message format in subclause 9.1.
  ssDT-SupportIndicator              ssDT-SupportIndicator,
  maxUL-SIR                           UL-SIR,
  minUL-SIR                           UL-SIR,
  closedlooptimingadjustmentmode    Closedlooptimingadjustmentmode OPTIONAL,
  maximumAllowedULTxPower            MaximumAllowedULTxPower,
  maximumDLTxPower                  DL-Power,
  minimumDLTxPower                  DL-Power,
  primaryCPICH-Power                PrimaryCPICH-Power,
  primaryScramblingCode              PrimaryScramblingCode     OPTIONAL,
  uL-UARFCN                          UARFCN     OPTIONAL,
  dL-UARFCN                          UARFCN     OPTIONAL,
  dsCH-InformationResponse-RL-SetupFailureFDD DSCH-InformationResponseList-RL-SetupFailureFDD     OPTIONAL,
  neighbouring-UMTS-CellInformation Neighbouring-UMTS-CellInformation OPTIONAL,
  neighbouring-GSM-CellInformation   Neighbouring-GSM-CellInformation OPTIONAL,
  pC-Preamble                         PC-Preamble,
  sRB-Delay                           SRB-Delay,
  iE-Extensions                       ProtocolExtensionContainer { {SuccessfulRL-InformationResponse-RL-SetupFailureFDD-ExtIEs} } OPTIONAL,
  ...
}

SuccessfulRL-InformationResponse-RL-SetupFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
  { ID id-GA-CellAdditionalShapes      CRITICALITY ignore   EXTENSION  GA-CellAdditionalShapes     PRESENCE optional }|
  { ID id-DL-PowerBalancing-ActivationIndicator  CRITICALITY ignore   EXTENSION  DL-PowerBalancing-ActivationIndicator  PRESENCE
optional }|
  { ID id-HSDSCH-FDD-Information-Response      CRITICALITY ignore   EXTENSION  HSDSCH-FDD-Information-Response     PRESENCE optional }|
  { ID id-TFCI-PC-SupportIndicator          CRITICALITY ignore   EXTENSION  TFCI-PC-SupportIndicator     PRESENCE optional }|
  { ID id-HCS-Prio                          CRITICALITY ignore   EXTENSION  HCS-Prio     PRESENCE optional }|_
}

```

```

{ ID id-Primary-CPICH-Usage-For-Channel-Estimation      CRITICALITY ignore EXTENSION Primary-CPICH-Usage-For-Channel-Estimation      PRESENCE
optional }|
{ ID id-Secondary-CPICH-Information      CRITICALITY ignore EXTENSION Secondary-CPICH-Information      PRESENCE optional },
...
}

DiversityIndication-RL-SetupFailureFDD ::= CHOICE {
    combining                  Combining-RL-SetupFailureFDD,
    nonCombiningOrFirstRL     NonCombiningOrFirstRL-RL-SetupFailureFDD
}

Combining-RL-SetupFailureFDD ::= SEQUENCE {
    rL-ID                      RL-ID,
    iE-Extensions               ProtocolExtensionContainer { { CombiningItem-RL-SetupFailureFDD-ExtIEs} } OPTIONAL,
    ...
}

CombiningItem-RL-SetupFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-DCH-InformationResponse      CRITICALITY ignore EXTENSION DCH-InformationResponse      PRESENCE optional },
    ...
}

NonCombiningOrFirstRL-RL-SetupFailureFDD ::= SEQUENCE {
    dCH-InformationResponse           DCH-InformationResponse,
    iE-Extensions                   ProtocolExtensionContainer { { NonCombiningOrFirstRLItem-RL-SetupFailureFDD-ExtIEs} } OPTIONAL,
    ...
}

NonCombiningOrFirstRLItem-RL-SetupFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

DSCH-InformationResponseList-RL-SetupFailureFDD ::= ProtocolIE-Single-Container { { DSCH-InformationResponseListIEs-RL-SetupFailureFDD } }

DSCH-InformationResponseListIEs-RL-SetupFailureFDD RNSAP-PROTOCOL-IES ::= {
    { ID id-DSCH-FDD-InformationResponse      CRITICALITY ignore TYPE DSCH-FDD-InformationResponse      PRESENCE mandatory }
}

RadioLinkSetupFailureFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

/* partly omitted */

-- ****
-- 
-- RADIO LINK ADDITION REQUEST FDD
-- 
-- ****

```

```

RadioLinkAdditionRequestFDD ::= SEQUENCE {
    protocolIEs                  ProtocolIE-Container      {{RadioLinkAdditionRequestFDD-IEs}},
    protocolExtensions           ProtocolExtensionContainer {{RadioLinkAdditionRequestFDD-Extensions}}
} OPTIONAL,
...
}

RadioLinkAdditionRequestFDD-IEs RNSAP-PROTOCOL-IES ::= {
{ ID id-UL-SIRTarget          CRITICALITY reject   TYPE UL-SIR           PRESENCE mandatory } |
{ ID id-RL-InformationList-RL-AdditionRqstFDD  CRITICALITY notify    TYPE RL-InformationList-RL-AdditionRqstFDD PRESENCE mandatory } |
{ ID id-Active-Pattern-Sequence-Information CRITICALITY reject    TYPE Active-Pattern-Sequence-Information  PRESENCE optional },
...
}

RL-InformationList-RL-AdditionRqstFDD ::= SEQUENCE (SIZE (1..maxNrOfRLs-1)) OF ProtocolIE-Single-Container { {RL-Information-RL-AdditionRqstFDD-IEs} }

RL-Information-RL-AdditionRqstFDD-IEs RNSAP-PROTOCOL-IES ::= {
{ ID id-RL-Information-RL-AdditionRqstFDD  CRITICALITY notify    TYPE RL-Information-RL-AdditionRqstFDD  PRESENCE mandatory }
}

RL-Information-RL-AdditionRqstFDD ::= SEQUENCE {
    rL-ID                      RL-ID,
    c-ID                       C-ID,
    frameOffset                FrameOffset,
    chipOffset                 ChipOffset,
    diversityControlField     DiversityControlField,
    primaryCPICH-EcNo          PrimaryCPICH-EcNo      OPTIONAL,
    sSDT-CellID                SSDT-CellID        OPTIONAL,
    transmitDiversityIndicator TransmitDiversityIndicator OPTIONAL,
    iE-Extensions               ProtocolExtensionContainer { {RL-Information-RL-AdditionRqstFDD-ExtIEs} } OPTIONAL,
}
...

RL-Information-RL-AdditionRqstFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
{ ID id-DLReferencePower    CRITICALITY ignore    EXTENSION DL-Power      PRESENCE optional } |
{ ID id-Enhanced-PrimaryCPICH-EcNo      CRITICALITY ignore    EXTENSION Enhanced-PrimaryCPICH-EcNo    PRESENCE optional } |
{ ID id-RL-Specific-DCH-Info    CRITICALITY ignore    EXTENSION RL-Specific-DCH-Info  PRESENCE optional } |
{ ID id-DelayedActivation  CRITICALITY reject    EXTENSION DelayedActivation PRESENCE optional } |
{ ID id-Qth-Parameter       CRITICALITY ignore    EXTENSION Qth-Parameter  PRESENCE optional },
}
...

RadioLinkAdditionRequestFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
{ ID id-DPC-Mode            CRITICALITY reject    EXTENSION DPC-Mode      PRESENCE optional } |
{ ID id-Permanent-NAS-UE-Identity  CRITICALITY ignore    EXTENSION Permanent-NAS-UE-Identity  PRESENCE optional } |
{ ID id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation  CRITICALITY ignore    EXTENSION UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation  PRESENCE optional } |
{ ID id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH  CRITICALITY ignore    EXTENSION UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation-With-HS-DSCH  PRESENCE optional },
}
...
}

```

```

/* partly omitted */

-- ****
-- RADIO LINK ADDITION RESPONSE FDD
-- ****

RadioLinkAdditionResponseFDD ::= SEQUENCE {
    protocolIES          ProtocolIE-Container      {{RadioLinkAdditionResponseFDD-IEs}},
    protocolExtensions   ProtocolExtensionContainer {{RadioLinkAdditionResponseFDD-Extensions}}                                OPTIONAL,
    ...
}

RadioLinkAdditionResponseFDD-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-InformationResponseList-RL-AdditionRspFDD      CRITICALITY ignore   TYPE RL-InformationResponseList-RL-AdditionRspFDD      PRESENCE mandatory
    } |
    { ID id-CriticalityDiagnostics      CRITICALITY ignore   TYPE CriticalityDiagnostics      PRESENCE optional },
    ...
}

RL-InformationResponseList-RL-AdditionRspFDD      ::= SEQUENCE (SIZE (1..maxNrOfRLs-1)) OF ProtocolIE-Single-Container { {RL-
InformationResponseItemIEs-RL-AdditionRspFDD} }

RL-InformationResponseItemIEs-RL-AdditionRspFDD RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-InformationResponseItem-RL-AdditionRspFDD      CRITICALITY ignore   TYPE RL-InformationResponseItem-RL-AdditionRspFDD      PRESENCE
mandatory }
}

RL-InformationResponseItem-RL-AdditionRspFDD ::= SEQUENCE {
    rL-ID                  RL-ID,
    rL-Set-ID              RL-Set-ID,
    uRA-Information        URA-Information      OPTIONAL,
    SAI                    SAI,
    gA-Cell                GA-Cell      OPTIONAL,
    gA-AccessPointPosition GA-AccessPointPosition OPTIONAL,
    received-total-wide-band-power Received-total-wide-band-power,
    secondary-CCPCH-Info   Secondary-CCPCH-Info      OPTIONAL,
    dl-CodeInformation     DL-CodeInformationList-RL-AdditionRspFDD,
    diversityIndication   DiversityIndication-RL-AdditionRspFDD,
    -- This IE represents both the Diversity Indication IE and the choice based on the diversity indication as described in
    -- the tabular message format in subclause 9.1.
    sSDT-SupportIndicator SSDT-SupportIndicator,
    minUL-SIR               UL-SIR,
    maxUL-SIR               UL-SIR,
    closedlooptimingadjustmentmode Closedlooptimingadjustmentmode      OPTIONAL,
    maximumAllowedULTxPower MaximumAllowedULTxPower,
    maximumDLTxPower       DL-Power,
    minimumDLTxPower       DL-Power,
    neighbouring-UMTS-CellInformation Neighbouring-UMTS-CellInformation      OPTIONAL,
}

```

```

neighbouring-GSM-CellInformation    Neighbouring-GSM-CellInformation OPTIONAL,
pC-Preamble                         PC-Preamble,
sRB-Delay                           SRB-Delay,
primaryCPICH-Power                 PrimaryCPICH-Power,
iE-Extensions                        ProtocolExtensionContainer { {RL-InformationResponseItem-RL-AdditionRspFDD-ExtIEs} } OPTIONAL,
...
}

RL-InformationResponseItem-RL-AdditionRspFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
  { ID id-GA-CellAdditionalShapes      CRITICALITY ignore EXTENSION GA-CellAdditionalShapes      PRESENCE optional }|
  { ID id-DL-PowerBalancing-ActivationIndicator   CRITICALITY ignore EXTENSION DL-PowerBalancing-ActivationIndicator      PRESENCE
optional }|
  { ID id-TFCI-PC-SupportIndicator     CRITICALITY ignore EXTENSION TFCI-PC-SupportIndicator      PRESENCE optional }|
  { ID id-HCS-Prio                   CRITICALITY ignore EXTENSION HCS-Prio                  PRESENCE optional }|
  { ID id-Primary-CPICH-Usage-For-Channel-Estimation   CRITICALITY ignore EXTENSION Primary-CPICH-Usage-For-Channel-Estimation      PRESENCE
optional }|
  { ID id-Secondary-CPICH-Information     CRITICALITY ignore EXTENSION Secondary-CPICH-Information      PRESENCE optional },
...
}

DL-CodeInformationList-RL-AdditionRspFDD ::= ProtocolIE-Single-Container {{ DL-CodeInformationListIEs-RL-AdditionRspFDD }}
```

DL-CodeInformationListIEs-RL-AdditionRspFDD RNSAP-PROTOCOL-IES ::= {  
 { ID id-FDD-DL-CodeInformation CRITICALITY ignore TYPE FDD-DL-CodeInformation PRESENCE mandatory }  
}

DiversityIndication-RL-AdditionRspFDD ::= CHOICE {  
 combining Combining-RL-AdditionRspFDD,  
 nonCombining NonCombining-RL-AdditionRspFDD  
}

Combining-RL-AdditionRspFDD ::= SEQUENCE {  
 rL-ID RL-ID,  
 iE-Extensions ProtocolExtensionContainer { { CombiningItem-RL-AdditionRspFDD-ExtIEs} } OPTIONAL,
...
}

CombiningItem-RL-AdditionRspFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {  
 { ID id-DCH-InformationResponse CRITICALITY ignore EXTENSION DCH-InformationResponse PRESENCE optional } ,
...
}

NonCombining-RL-AdditionRspFDD ::= SEQUENCE {  
 dCH-InformationResponse DCH-InformationResponse,  
 iE-Extensions ProtocolExtensionContainer { { NonCombiningItem-RL-AdditionRspFDD-ExtIEs} } OPTIONAL,
...
}

NonCombiningItem-RL-AdditionRspFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {  
 ...
}

```

RadioLinkAdditionResponseFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

/* partly omitted */

-- *****
-- 
-- RADIO LINK ADDITION FAILURE FDD
-- 
-- *****

RadioLinkAdditionFailureFDD ::= SEQUENCE {
    protocolIEs          ProtocolIE-Container {{RadioLinkAdditionFailureFDD-IEs}},
    protocolExtensions   ProtocolExtensionContainer {{RadioLinkAdditionFailureFDD-Extensions}}                                OPTIONAL,
    ...
}

RadioLinkAdditionFailureFDD-IES RNSAP-PROTOCOL-IES ::= {
    { ID id-CauseLevel-RL-AdditionFailureFDD                      CRITICALITY ignore           TYPE CauseLevel-RL-AdditionFailureFDD
      PRESENCE mandatory }|
    { ID id-CriticalityDiagnostics       CRITICALITY ignore           TYPE CriticalityDiagnostics
      PRESENCE optional },
    ...
}

CauseLevel-RL-AdditionFailureFDD ::= CHOICE {
    generalCause        GeneralCauseList-RL-AdditionFailureFDD,
    rLSpecificCause     RLSpecificCauseList-RL-AdditionFailureFDD,
    ...
}

GeneralCauseList-RL-AdditionFailureFDD ::= SEQUENCE {
    cause                Cause,
    iE-Extensions        ProtocolExtensionContainer { { GeneralCauseItem-RL-AdditionFailureFDD-ExtIEs} }                                OPTIONAL,
    ...
}

GeneralCauseItem-RL-AdditionFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

RLSpecificCauseList-RL-AdditionFailureFDD ::= SEQUENCE {
    unsuccessful-RL-InformationRespList-RL-AdditionFailureFDD      UnsuccessfulRL-InformationResponseList-RL-AdditionFailureFDD,
    successful-RL-InformationRespList-RL-AdditionFailureFDD         SuccessfulRL-InformationResponseList-RL-AdditionFailureFDD OPTIONAL,
    iE-Extensions          ProtocolExtensionContainer { { RLSpecificCauseItem-RL-AdditionFailureFDD-ExtIEs} }                                OPTIONAL,
    ...
}

RLSpecificCauseItem-RL-AdditionFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

```

```

}

UnsuccessfulRL-InformationResponseList-RL-AdditionFailureFDD ::= SEQUENCE (SIZE (1..maxNrOfRLs-1)) OF ProtocolIE-Single-Container { {UnsuccessfulRL-
InformationResponse-RL-AdditionFailureFDD-IEs} }

UnsuccessfulRL-InformationResponse-RL-AdditionFailureFDD-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-UnsuccessfulRL-InformationResponse-RL-AdditionFailureFDD      CRITICALITY ignore   TYPE UnsuccessfulRL-InformationResponse-RL-
    AdditionFailureFDD          PRESENCE mandatory   }
}

UnsuccessfulRL-InformationResponse-RL-AdditionFailureFDD ::= SEQUENCE {
    rL-ID                      RL-ID,
    cause                       Cause,
    iE-Extensions               ProtocolExtensionContainer { {UnsuccessfulRL-InformationResponse-RL-AdditionFailureFDD-ExtIEs} } OPTIONAL,
    ...
}

UnsuccessfulRL-InformationResponse-RL-AdditionFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

SuccessfulRL-InformationResponseList-RL-AdditionFailureFDD ::= SEQUENCE (SIZE (0..maxNrOfRLs-2)) OF ProtocolIE-Single-Container { {SuccessfulRL-
InformationResponse-RL-AdditionFailureFDD-IEs} }

SuccessfulRL-InformationResponse-RL-AdditionFailureFDD-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-SuccessfulRL-InformationResponse-RL-AdditionFailureFDD      CRITICALITY ignore   TYPE SuccessfulRL-InformationResponse-RL-AdditionFailureFDD
    PRESENCE mandatory   }
}

SuccessfulRL-InformationResponse-RL-AdditionFailureFDD ::= SEQUENCE {
    rL-ID                      RL-ID,
    rL-Set-ID                   RL-Set-ID,
    uRA-Information              URA-Information      OPTIONAL,
    sAI                         SAI,
    gA-Cell                     GA-Cell      OPTIONAL,
    gA-AccessPointPosition       GA-AccessPointPosition      OPTIONAL,
    received-total-wide-band-power Received-total-wide-band-power,
    secondary-CCPCH-Info         Secondary-CCPCH-Info      OPTIONAL,
    dl-CodeInformation           DL-CodeInformationList-RL-AdditionFailureFDD,
    diversityIndication         DiversityIndication-RL-AdditionFailureFDD,
    -- This IE represents both the Diversity Indication IE and the choice based on the diversity indication as described in
    -- the tabular message format in subclause 9.1.
    ssDT-SupportIndicator        ssDT-SupportIndicator,
    minUL-SIR                    UL-SIR,
    maxUL-SIR                    UL-SIR,
    closedlooptimingadjustmentmode Closedlooptimingadjustmentmode  OPTIONAL,
    maximumAllowedULTxPower      MaximumAllowedULTxPower,
    maximumDLTxPower             DL-Power,
    minimumDLTxPower             DL-Power,
    neighbouring-UMTS-CellInformation Neighbouring-UMTS-CellInformation OPTIONAL,
    neighbouring-GSM-CellInformation Neighbouring-GSM-CellInformation OPTIONAL,
}

```

```

primaryCPICH-Power          PrimaryCPICH-Power,
pC-Preamble                 PC-Preamble,
sRB-Delay                   SRB-Delay,
iE-Extensions               ProtocolExtensionContainer { {SuccessfulRL-InformationResponse-RL-AdditionFailureFDD-ExtIEs} } OPTIONAL,
...
}

SuccessfulRL-InformationResponse-RL-AdditionFailureFDD-RNSAP-PROTOCOL-EXTENSION ::= {
  { ID id-GA-CellAdditionalShapes      CRITICALITY ignore EXTENSION GA-CellAdditionalShapes      PRESENCE optional }|
  { ID id-DL-PowerBalancing-ActivationIndicator   CRITICALITY ignore EXTENSION DL-PowerBalancing-ActivationIndicator      PRESENCE
optional }|
  { ID id-TFCI-PC-SupportIndicator      CRITICALITY ignore EXTENSION TFCI-PC-SupportIndicator      PRESENCE optional }|
  { ID id-HCS-Prio                  CRITICALITY ignore EXTENSION HCS-Prio      PRESENCE optional }|
  { ID id-Primary-CPICH-Usage-For-Channel-Estimation    CRITICALITY ignore EXTENSION Primary-CPICH-Usage-For-Channel-Estimation      PRESENCE
optional }|
  { ID id-Secondary-CPICH-Information     CRITICALITY ignore EXTENSION Secondary-CPICH-Information      PRESENCE optional },
...
}

DL-CodeInformationList-RL-AdditionFailureFDD ::= ProtocolIE-Single-Container { { DL-CodeInformationListIEs-RL-AdditionFailureFDD } }

DL-CodeInformationListIEs-RL-AdditionFailureFDD RNSAP-PROTOCOL-IES ::= {
  { ID id-FDD-DL-CodeInformation      CRITICALITY ignore TYPE FDD-DL-CodeInformation      PRESENCE mandatory }
}

DiversityIndication-RL-AdditionFailureFDD ::= CHOICE {
  combining                  Combining-RL-AdditionFailureFDD,
  nonCombining               NonCombining-RL-AdditionFailureFDD
}

Combining-RL-AdditionFailureFDD ::= SEQUENCE {
  rL-ID                      RL-ID,
  iE-Extensions               ProtocolExtensionContainer { { CombiningItem-RL-AdditionFailureFDD-ExtIEs} } OPTIONAL,
...
}

CombiningItem-RL-AdditionFailureFDD-RNSAP-PROTOCOL-EXTENSION ::= {
  { ID id-DCH-InformationResponse   CRITICALITY ignore EXTENSION DCH-InformationResponse      PRESENCE optional },
...
}

NonCombining-RL-AdditionFailureFDD ::= SEQUENCE {
  dCH-InformationResponse       DCH-InformationResponse,
  iE-Extensions                ProtocolExtensionContainer { { NonCombiningItem-RL-AdditionFailureFDD-ExtIEs} } OPTIONAL,
...
}

NonCombiningItem-RL-AdditionFailureFDD-RNSAP-PROTOCOL-EXTENSION ::= {
...
}

```

```

RadioLinkAdditionFailureFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

/* partly omitted */

-- *****
-- 
-- RADIO LINK RECONFIGURATION PREPARE FDD
-- 
-- *****

RadioLinkReconfigurationPrepareFDD ::= SEQUENCE {
    protocolIEs          ProtocolIE-Container      {{RadioLinkReconfigurationPrepareFDD-IEs}},
    protocolExtensions   ProtocolExtensionContainer {{RadioLinkReconfigurationPrepareFDD-Extensions}}                               OPTIONAL,
    ...
}

RadioLinkReconfigurationPrepareFDD-IES RNSAP-PROTOCOL-IES ::= {
    { ID id-AllowedQueuingTime           CRITICALITY reject   TYPE AllowedQueuingTime           PRESENCE optional } |
    { ID id-UL-DPCH-Information-RL-ReconfPrepFDD        CRITICALITY reject   TYPE UL-DPCH-Information-RL-ReconfPrepFDD        PRESENCE optional } |
    { ID id-DL-DPCH-Information-RL-ReconfPrepFDD        CRITICALITY reject   TYPE DL-DPCH-Information-RL-ReconfPrepFDD        PRESENCE optional } |
    { ID id-FDD-DCHs-to-Modify            CRITICALITY reject   TYPE FDD-DCHs-to-Modify            PRESENCE optional } |
    { ID id-DCHs-to-Add-FDD             CRITICALITY reject   TYPE DCH-FDD-Information         PRESENCE optional } |
    { ID id-DCH-DeleteList-RL-ReconfPrepFDD        CRITICALITY reject   TYPE DCH-DeleteList-RL-ReconfPrepFDD        PRESENCE optional } |
    { ID id-DSCH-Modify-RL-ReconfPrepFDD        CRITICALITY reject   TYPE DSCH-Modify-RL-ReconfPrepFDD        PRESENCE optional } |
    { ID id-DSCHs-to-Add-FDD             CRITICALITY reject   TYPE DSCH-FDD-Information         PRESENCE optional } |
    { ID id-DSCH-Delete-RL-ReconfPrepFDD        CRITICALITY reject   TYPE DSCH-Delete-RL-ReconfPrepFDD        PRESENCE optional } |
    { ID id-RL-InformationList-RL-ReconfPrepFDD        CRITICALITY reject   TYPE RL-InformationList-RL-ReconfPrepFDD        PRESENCE optional } |
    { ID id-Space-Information           CRITICALITY reject   TYPE Transmission-Gap-Pattern-Sequence-Information PRESENCE optional },
    ...
}

UL-DPCH-Information-RL-ReconfPrepFDD ::= SEQUENCE {
    ul-ScramblingCode        UL-ScramblingCode        OPTIONAL,
    ul-SIRTarget              UL-SIR                  OPTIONAL,
    minUL-ChannelisationCodeLength MinUL-ChannelisationCodeLength OPTIONAL,
    maxNrOfUL-DPDCHs         MaxNrOfUL-DPDCHs        OPTIONAL
    -- This IE shall be present if minUL-ChannelisationCodeLength equals to 4 --
    ul-PunctureLimit          PunctureLimit          OPTIONAL,
    tFCs                      TFCs                   OPTIONAL,
    ul-DPCCH-SlotFormat       UL-DPCCH-SlotFormat       OPTIONAL,
    diversityMode              DiversityMode          OPTIONAL,
    sSDT-CellIDLength         SSDT-CellID-Length     OPTIONAL,
    s-FieldLength              S-FieldLength          OPTIONAL,
    iE-Extensions              ProtocolExtensionContainer {{UL-DPCH-Information-RL-ReconfPrepFDD-ExtIEs}} OPTIONAL,
    ...
}

UL-DPCH-Information-RL-ReconfPrepFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
}

```

```

}
  ...
}

DL-DPCH-Information-RL-ReconfPrepFDD ::= SEQUENCE {
    tFCS                      OPTIONAL,
    dl-DPCH-SlotFormat        OPTIONAL,
    nrOfDLchannelisationcodes OPTIONAL,
    tFCI-SignallingMode       OPTIONAL,
    tFCI-Presence              OPTIONAL
    -- This IE shall be present if DL DPCH Slot Format IE is from 12 to 16 --,
    multiplexingPosition      OPTIONAL,
    limitedPowerIncrease       OPTIONAL,
    iE-Extensions               ProtocolExtensionContainer { {DL-DPCH-Information-RL-ReconfPrepFDD-ExtIEs} } OPTIONAL,
    ...
}

DL-DPCH-Information-RL-ReconfPrepFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-SplitType   CRITICALITY reject EXTENSION SplitType PRESENCE optional } |
    { ID id-LengthOfTFCI2  CRITICALITY reject EXTENSION LengthOfTFCI2 PRESENCE optional },
    ...
}

DCH-DeleteList-RL-ReconfPrepFDD          ::= SEQUENCE (SIZE (0..maxNrOfDCHs)) OF DCH-DeleteItem-RL-ReconfPrepFDD

DCH-DeleteItem-RL-ReconfPrepFDD ::= SEQUENCE {
    dCH-ID                  DCH-ID,
    iE-Extensions             ProtocolExtensionContainer { {DCH-DeleteItem-RL-ReconfPrepFDD-ExtIEs} } OPTIONAL,
    ...
}

DCH-DeleteItem-RL-ReconfPrepFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

DSCH-Modify-RL-ReconfPrepFDD ::= SEQUENCE {
    DSCH-Information           DSCH-ModifyInfo-RL-ReconfPrepFDD OPTIONAL,
    pdSCH-RL-ID                RL-ID OPTIONAL,
    tFCS                       TFCS OPTIONAL,
    iE-Extensions               ProtocolExtensionContainer { {DSCH-Modify-RL-ReconfPrepFDD-ExtIEs} } OPTIONAL,
    ...
}

DSCH-Modify-RL-ReconfPrepFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-EnhancedDSCHPCIndicator   CRITICALITY ignore EXTENSION EnhancedDSCHPCIndicator PRESENCE optional } |
    { ID id-EnhancedDSCHPC          CRITICALITY ignore EXTENSION EnhancedDSCHPC PRESENCE conditional },
    -- The IE shall be present if the Enhanced DSCH PC Indicator IE is set to "Enhanced DSCH PC Active in the UE".
    ...
}

DSCH-ModifyInfo-RL-ReconfPrepFDD ::= SEQUENCE (SIZE(0..maxNoOfDSCHs)) OF DSCH-ModifyInformationItem-RL-ReconfPrepFDD

```

```

DSCH-ModifyInformationItem-RL-ReconfPrepFDD ::= SEQUENCE {
    dSCH-ID                               DSCH-ID,
    trChSourceStatisticsDescriptor        TrCH-SrcStatisticsDescr OPTIONAL,
    transportFormatSet                  TransportFormatSet      OPTIONAL,
    allocationRetentionPriority       AllocationRetentionPriority  OPTIONAL,
    schedulingPriorityIndicator     SchedulingPriorityIndicator  OPTIONAL,
    bLER                                BLER                 OPTIONAL,
    transportBearerRequestIndicator   TransportBearerRequestIndicator,
    iE-Extensions                         ProtocolExtensionContainer { {DSCH-ModifyInformationItem-RL-ReconfPrepFDD-ExtIEs} } OPTIONAL,
    ...
}

DSCH-ModifyInformationItem-RL-ReconfPrepFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-TrafficClass           CRITICALITY ignore EXTENSION TrafficClass          PRESENCE optional } |
    { ID id-BindingID              CRITICALITY ignore EXTENSION BindingID            PRESENCE          optional } |
    -- Shall be ignored if bearer establishment with ALCAP.
    { ID id-TransportLayerAddress CRITICALITY ignore EXTENSION TransportLayerAddress PRESENCE optional },
    -- Shall be ignored if bearer establishment with ALCAP.
    ...
}

DSCH-Delete-RL-ReconfPrepFDD ::= SEQUENCE {
    dSCH-Information                DSCH-Info-Delete-RL-ReconfPrepFDD,
    iE-Extensions                   ProtocolExtensionContainer { {DSCH-Delete-RL-ReconfPrepFDD-ExtIEs} } OPTIONAL,
    ...
}

DSCH-Delete-RL-ReconfPrepFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

DSCH-Info-Delete-RL-ReconfPrepFDD ::= SEQUENCE (SIZE(1..maxNoOfDSCHs)) OF DSCH-DeleteInformationItem-RL-REconfPrepFDD

DSCH-DeleteInformationItem-RL-REconfPrepFDD ::= SEQUENCE {
    dSCH-ID                               DSCH-ID,
    iE-Extensions                         ProtocolExtensionContainer { {DSCH-DeleteInformationItem-RL-ReconfPrepFDD-ExtIEs} } OPTIONAL,
    ...
}

DSCH-DeleteInformationItem-RL-ReconfPrepFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

RL-InformationList-RL-ReconfPrepFDD      ::= SEQUENCE (SIZE (0..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-Information-RL-ReconfPrepFDD-IEs} }

RL-Information-RL-ReconfPrepFDD-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-Information-RL-ReconfPrepFDD   CRITICALITY reject   TYPE RL-Information-RL-ReconfPrepFDD   PRESENCE mandatory   }
}

RL-Information-RL-ReconfPrepFDD ::= SEQUENCE {

```

```

rl-ID           RL-ID,
sSDT-Indication   SSDT-Indication    OPTIONAL,
sSDT-CellIdentity  SSDT-CellID      OPTIONAL
-- The IE shall be present if the sSDT-Indication is set to 'sSDT-active-in-the-UE' --,
transmitDiversityIndicator  TransmitDiversityIndicator  OPTIONAL,
-- This IE shall be present if Diversity Mode IE is present in UL DPCH Information IE and is not equal to "none"
iE-Extensions     ProtocolExtensionContainer { { RL-Information-RL-ReconfPrepFDD-ExtIEs } } OPTIONAL,
...
}

RL-Information-RL-ReconfPrepFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
{ ID id-SSDT-CellIDforEDSCHPC CRITICALITY ignore EXTENSION SSDT-CellID      PRESENCE conditional }|
-- This IE shall be present if Enhanced DSCH PC IE is present in either the DSCHs to Modify IE or the DSCHs to Add IE.
{ ID id-DLReferencePower   CRITICALITY ignore EXTENSION DL-Power      PRESENCE optional }|
{ ID id-RL-Specific-DCH-Info  CRITICALITY ignore EXTENSION RL-Specific-DCH-Info PRESENCE optional }|
{ ID id-DL-DPCH-TimingAdjustment CRITICALITY reject EXTENSION DL-DPCH-TimingAdjustment PRESENCE optional }|
{ ID id-Qth-Parameter   CRITICALITY ignore EXTENSION Qth-Parameter  PRESENCE optional }|
{ ID id-Phase-Reference-Update-Indicator  CRITICALITY ignore EXTENSION Phase-Reference-Update-Indicator  PRESENCE optional },
...
}

RadioLinkReconfigurationPrepareFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
{ ID id-HSDSCH-Information-to-Modify   CRITICALITY reject EXTENSION HSDSCH-Information-to-Modify  PRESENCE optional }|
{ ID id-HSDSCH-FDD-Information-to-Add  CRITICALITY reject EXTENSION HSDSCH-FDD-Information  PRESENCE optional }|
{ ID id-HSDSCH-FDD-Information-to-Delete CRITICALITY reject EXTENSION HSDSCH-DeleteList-RL-ReconfPrepFDD  PRESENCE optional }|
{ ID id-HSPDSCH-RL-ID   CRITICALITY reject EXTENSION RL-ID      PRESENCE optional }|
{ ID id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation  CRITICALITY ignore EXTENSION UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation  PRESENCE optional }|
{ ID id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH  CRITICALITY ignore EXTENSION UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH  PRESENCE optional },
...
}

HSDSCH-DeleteList-RL-ReconfPrepFDD ::= SEQUENCE (SIZE (1..maxNrOfMACdFlows)) OF HSDSCH-DeleteItem-RL-ReconfPrepFDD

HSDSCH-DeleteItem-RL-ReconfPrepFDD ::= SEQUENCE {
  hSDSCH-MACdFlow-ID,          HSDSCH-MACdFlow-ID,
  iE-Extensions,               ProtocolExtensionContainer { { HSDSCH-DeleteItem-RL-ReconfPrepFDD-ExtIEs } } OPTIONAL,
...
}

HSDSCH-DeleteItem-RL-ReconfPrepFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
...
}

/* partly omitted */

-- ****
-- 
-- RADIO LINK RECONFIGURATION READY FDD
-- 

```

```

RadioLinkReconfigurationReadyFDD ::= SEQUENCE {
    protocolIEs          ProtocolIE-Container {{RadioLinkReconfigurationReadyFDD-IEs}},
    protocolExtensions   ProtocolExtensionContainer {{RadioLinkReconfigurationReadyFDD-Extensions}} OPTIONAL,
    ...
}

RadioLinkReconfigurationReadyFDD-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-InformationResponseList-RL-ReconfReadyFDD CRITICALITY ignore TYPE RL-InformationResponseList-RL-ReconfReadyFDD PRESENCE optional }
} |
{ ID id-CriticalityDiagnostics CRITICALITY ignore TYPE CriticalityDiagnostics PRESENCE optional },
...
}

RL-InformationResponseList-RL-ReconfReadyFDD ::= SEQUENCE (SIZE (0..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-InformationResponse-RL-ReconfReadyFDD-IEs} }

RL-InformationResponse-RL-ReconfReadyFDD-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-InformationResponseItem-RL-ReconfReadyFDD CRITICALITY ignore TYPE RL-InformationResponseItem-RL-ReconfReadyFDD PRESENCE mandatory }
}

RL-InformationResponseItem-RL-ReconfReadyFDD ::= SEQUENCE {
    rL-ID                  RL-ID,
    max-UL-SIR             UL-SIR      OPTIONAL,
    min-UL-SIR             UL-SIR      OPTIONAL,
    maximumDLTxPower       DL-Power    OPTIONAL,
    minimumDLTxPower       DL-Power    OPTIONAL,
    secondary-CCPCH-Info   Secondary-CCPCH-Info OPTIONAL,
    dl-CodeInformationList DL-CodeInformationList-RL-ReconfReadyFDD OPTIONAL,
    dCHInformationResponse DCH-InformationResponseList-RL-ReconfReadyFDD OPTIONAL,
    dsCHsToBeAddedOrModified DSCHsToBeAddedOrModified-RL-ReconfReadyFDD OPTIONAL,
    iE-Extensions          ProtocolExtensionContainer { {RL-InformationResponseItem-RL-ReconfReadyFDD-ExtIEs} } OPTIONAL,
    ...
}

RL-InformationResponseItem-RL-ReconfReadyFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-DL-PowerBalancing-UpdatedIndicator CRITICALITY ignore EXTENSION DL-PowerBalancing-UpdatedIndicator PRESENCE optional } |
    { ID id-HSDSCH-FDD-Information-Response CRITICALITY ignore EXTENSION HSDSCH-FDD-Information-Response PRESENCE optional } |
    { ID id-Primary-CPICH-Usage-For-Channel-Estimation CRITICALITY ignore EXTENSION Primary-CPICH-Usage-For-Channel-Estimation PRESENCE optional } |
    { ID id-Secondary-CPICH-Information-Change CRITICALITY ignore EXTENSION Secondary-CPICH-Information-Change PRESENCE optional },
    ...
}

DL-CodeInformationList-RL-ReconfReadyFDD ::= ProtocolIE-Single-Container {{ DL-CodeInformationListIEs-RL-ReconfReadyFDD }}
```

DL-CodeInformationListIEs-RL-ReconfReadyFDD RNSAP-PROTOCOL-IES ::= {

```

    { ID id-FDD-DL-CodeInformation CRITICALITY ignore TYPE FDD-DL-CodeInformation PRESENCE mandatory }
}
```

```

DCH-InformationResponseList-RL-ReconfReadyFDD ::= ProtocolIE-Single-Container { {DCH-InformationResponseListIEs-RL-ReconfReadyFDD} }

DCH-InformationResponseListIEs-RL-ReconfReadyFDD RNSAP-PROTOCOL-IES ::= {
  { ID id-DCH-InformationResponse CRITICALITY ignore TYPE DCH-InformationResponse PRESENCE mandatory }
}

DSCHsToBeAddedOrModified-RL-ReconfReadyFDD ::= ProtocolIE-Single-Container { {DSCHsToBeAddedOrModifiedIEs-RL-ReconfReadyFDD} }

DSCHsToBeAddedOrModifiedIEs-RL-ReconfReadyFDD RNSAP-PROTOCOL-IES ::= {
  { ID id-DSCHsToBeAddedOrModified-FDD CRITICALITY ignore TYPE DSCH-FDD-InformationResponse PRESENCE mandatory }
}

RadioLinkReconfigurationReadyFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
  { ID id-DSCH-RNTI CRITICALITY ignore EXTENSION DSCH-RNTI PRESENCE optional } |
  { ID id-HSDSCH-RNTI CRITICALITY reject EXTENSION HSDSCH-RNTI PRESENCE optional } |
  { ID id-MACChs-ResetIndicator CRITICALITY reject EXTENSION MACChs-ResetIndicator PRESENCE optional },
  ...
}

/* partly omitted */

-- *****
-- 
-- RADIO LINK RECONFIGURATION REQUEST FDD
-- 
-- *****

RadioLinkReconfigurationRequestFDD ::= SEQUENCE {
  protocolIEs ProtocolIE-Container {{RadioLinkReconfigurationRequestFDD-IEs}},
  protocolExtensions ProtocolExtensionContainer {{RadioLinkReconfigurationRequestFDD-Extensions}}
  OPTIONAL,
  ...
}

RadioLinkReconfigurationRequestFDD-IEs RNSAP-PROTOCOL-IES ::= {
  { ID id-AllowedQueuingTime CRITICALITY reject TYPE AllowedQueuingTime PRESENCE optional } |
  { ID id-UL-DPCH-Information-RL-ReconfRqstFDD CRITICALITY reject TYPE UL-DPCH-Information-RL-ReconfRqstFDD PRESENCE optional } |
  { ID id-DL-DPCH-Information-RL-ReconfRqstFDD CRITICALITY reject TYPE DL-DPCH-Information-RL-ReconfRqstFDD PRESENCE optional } |
  { ID id-FDD-DCHs-to-Modify CRITICALITY reject TYPE FDD-DCHs-to-Modify PRESENCE optional } |
  { ID id-DCHs-to-Add-FDD CRITICALITY reject TYPE DCH-FDD-Information PRESENCE optional } |
  { ID id-DCH-DeleteList-RL-ReconfRqstFDD CRITICALITY reject TYPE DCH-DeleteList-RL-ReconfRqstFDD PRESENCE optional } |
  { ID id-Transmission-Gap-Pattern-Sequence-Information CRITICALITY reject TYPE Transmission-Gap-Pattern-Sequence-Information PRESENCE optional },
  ...
}

UL-DPCH-Information-RL-ReconfRqstFDD ::= SEQUENCE {
  tFCs TFCS OPTIONAL,
  iE-Extensions ProtocolExtensionContainer { {UL-DPCH-Information-RL-ReconfRqstFDD-ExtIEs} } OPTIONAL,
  ...
}

```

```

UL-DPCH-Information-RL-ReconfRqstFDD-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

DL-DPCH-Information-RL-ReconfRqstFDD ::= SEQUENCE {
    tFCs          OPTIONAL,
    tFCI-SignallingMode OPTIONAL,
    limitedPowerIncrease OPTIONAL,
    iE-Extensions ProtocolExtensionContainer { DL-DPCH-Information-RL-ReconfRqstFDD-ExtIES } OPTIONAL,
    ...
}

DL-DPCH-Information-RL-ReconfRqstFDD-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

DCH-DeleteList-RL-ReconfRqstFDD ::= SEQUENCE (SIZE (0..maxNrOfDCHs)) OF DCH-DeleteItem-RL-ReconfRqstFDD

DCH-DeleteItem-RL-ReconfRqstFDD ::= SEQUENCE {
    dCH-ID          DCH-ID,
    iE-Extensions   ProtocolExtensionContainer { DCH-DeleteItem-RL-ReconfRqstFDD-ExtIES } OPTIONAL,
    ...
}

DCH-DeleteItem-RL-ReconfRqstFDD-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

RadioLinkReconfigurationRequestFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-RL-ReconfigurationRequestFDD-RL-InformationList CRITICALITY ignore      EXTENSION RL-ReconfigurationRequestFDD-RL-InformationList
      PRESENCE optional }|
    { ID id-DL-ReferencePowerInformation     CRITICALITY ignore      EXTENSION DL-ReferencePowerInformation      PRESENCE optional }|
    { ID id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation      CRITICALITY ignore      EXTENSION UE-Support-Of-Dedicated-Pilots-For-Channel-
      Estimation      PRESENCE optional }|
    { ID id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH      CRITICALITY ignore      EXTENSION UE-Support-Of-Dedicated-Pilots-
      For-Channel-Estimation-Of-HS-DSCH      PRESENCE optional },
    ...
}

RL-ReconfigurationRequestFDD-RL-InformationList ::= SEQUENCE (SIZE (0..maxNrOfRLs)) OF ProtocolIE-Single-Container {
    {RL-ReconfigurationRequestFDD-RL-Information-ListItem} }

RL-ReconfigurationRequestFDD-RL-Information-ListItem RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-ReconfigurationRequestFDD-RL-Information-IES CRITICALITY ignore      TYPE RL-ReconfigurationRequestFDD-RL-Information-IES PRESENCE optional
      } }
}

RL-ReconfigurationRequestFDD-RL-Information-IES ::= SEQUENCE {
    rL-ID          RL-ID,
    rL-Specific-DCH-Info   RL-Specific-DCH-Info OPTIONAL,
}

```

## Release 5

## 3GPP TS 25.423 V5.0.0(2002-03)

```

iE-Extensions          ProtocolExtensionContainer { { RL-ReconfigurationRequestFDD-RL-Information-ExtIEs } } OPTIONAL,
...
}

RL-ReconfigurationRequestFDD-RL-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
...
}

/* partly omitted */

-- ****
-- 
-- RADIO LINK PARAMETER UPDATE INDICATION FDD
-- 

RadioLinkParameterUpdateIndicationFDD ::= SEQUENCE {
    protocolIEs          ProtocolIE-Container {{RadioLinkParameterUpdateIndicationFDD-IEs}},
    protocolExtensions   ProtocolExtensionContainer {{RadioLinkParameterUpdateIndicationFDD-Extensions}} OPTIONAL,
...
}

RadioLinkParameterUpdateIndicationFDD-IEs RNSAP-PROTOCOL-IES ::= {
{ ID      id-HSDSCH-FDD-Update-Information      CRITICALITY      reject      TYPE      HSDSCH-FDD-Update-Information      PRESENCE optional},
{ ID      id-RL-ParameterUpdateIndicationFDD-RL-InformationList      CRITICALITY      reject      TYPE      RL-ParameterUpdateIndicationFDD-RL-InformationList      PRESENCE optional },
...
}

RL-ParameterUpdateIndicationFDD-RL-InformationList ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container { { RL-ParameterUpdateIndicationFDD-RL-InformationList-IEs } }

RL-ParameterUpdateIndicationFDD-RL-InformationList-IEs RNSAP-PROTOCOL-IES ::= {
{ ID      id-RL-ParameterUpdateIndicationFDD-RL-Information-Item      CRITICALITY      reject      TYPE      RL-ParameterUpdateIndicationFDD-RL-Information-Item      PRESENCE mandatory }
}

RL-ParameterUpdateIndicationFDD-RL-Information-Item ::= SEQUENCE {
    rL-ID                  RL-ID,
    phase-Reference-Update-Indicator Phase-Reference-Update-Indicator OPTIONAL,
    iE-Extensions          ProtocolExtensionContainer { { RL-ParameterUpdateIndicationFDD-RL-Information-ExtIEs } } OPTIONAL,
...
}

RL-ParameterUpdateIndicationFDD-RL-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
...
}

RadioLinkParameterUpdateIndicationFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
...
}

```

**/\* partly omitted \*/**

### 9.3.4 Information Element Definitions

```
-- ****
-- Information Element Definitions
-- ****

/* partly omitted */

-- C

Cause ::= CHOICE {
    radioNetwork      CauseRadioNetwork,
    transport         CauseTransport,
    protocol          CauseProtocol,
    misc              CauseMisc,
    ...
}

CauseMisc ::= ENUMERATED {
    control-processing-overload,
    hardware-failure,
    om-intervention,
    not-enough-user-plane-processing-resources,
    unspecified,
    ...
}

CauseProtocol ::= ENUMERATED {
    transfer-syntax-error,
    abstract-syntax-error-reject,
    abstract-syntax-error-ignore-and-notify,
    message-not-compatible-with-receiver-state,
    semantic-error,
    unspecified,
    abstract-syntax-error-falsely-constructed-message,
    ...
}

CauseRadioNetwork ::= ENUMERATED {
    unknown-C-ID,
    cell-not-available,
    power-level-not-supported,
    ul-scrambling-code-already-in-use,
    dl-radio-resources-not-available,
    ul-radio-resources-not-available,
    measurement-not-supported-for-the-object,
    combining-resources-not-available,
    combining-not-supported,
```

```
reconfiguration-not-allowed,
requested-configuration-not-supported,
synchronisation-failure,
requested-tx-diversity-mode-not-supported,
measurement-temporarily-not-available,
unspecified,
invalid-CM-settings,
reconfiguration-CFN-not-elapsed,
number-of-DL-codes-not-supported,
dedicated-transport-channel-type-not-supported,
dl-shared-channel-type-not-supported,
ul-shared-channel-type-not-supported,
common-transport-channel-type-not-supported,
ul-spreading-factor-not-supported,
dl-spreading-factor-not-supported,
cm-not-supported,
transaction-not-supported-by-destination-node-b,
rl-already-activated-or-allocated,
...
number-of-UL-codes-not-supported,
cell-reserved-for-operator-use,
dpc-mode-change-not-supported,
information-temporarily-not-available,
information-provision-not-supported-for-the-object,
power-balancing-status-not-compatible,
delayed-activation-not-supported,
rl-timing-adjustment-not-supported,
unknown-RNTI
}
```

```
CauseTransport ::= ENUMERATED {
    transport-resource-unavailable,
    unspecified,
    ...
}
```

```
CellCapabilityContainer-FDD ::= BIT STRING (SIZE (32))
-- First bit: Flexible Hard Split Support Indicator
-- Second bit: Delayed Activation Support Indicator
-- Third bit: HS-DSCH Support Indicator
-- Fourth bit: DSCH Support Indicator
-- Note that undefined bits are considered as a spare bit and spare bits shall be set to 0 by the transmitter and shall be ignored by the receiver.
```

```
CellCapabilityContainer-TDD ::= BIT STRING (SIZE (32))
-- First bit: Delayed Activation Support Indicator
-- Second bit: HS-DSCH Support Indicator
-- Third bit: DSCH Support Indicator
-- Note that undefined bits are considered as a spare bit and spare bits shall be set to 0 by the transmitter and shall be ignored by the receiver.
```

```
CellCapabilityContainer-TDD-LCR ::= BIT STRING (SIZE (32))
-- First bit: Delayed Activation Support Indicator
```

-- Second bit: HS-DSCH Support Indicator  
-- Third bit: DSCH Support Indicator  
-- Note that undefined bits are considered as a spare bit and spare bits shall be set to 0 by the transmitter and shall be ignored by the receiver.

C-ID ::= INTEGER (0..65535)

CCTrCH-ID ::= INTEGER (0..15)

Cell-Capacity-Class-Value ::= SEQUENCE {  
 uplinkCellCapacityClassValue INTEGER(1..100,...),  
 downlinkCellCapacityClassValue INTEGER(1..100,...)  
}

CellIndividualOffset ::= INTEGER (-20..20)

CellParameterID ::= INTEGER (0..127,...)

CFN ::= INTEGER (0..255)

CGI ::= SEQUENCE {  
 LAI SEQUENCE {  
 pLMN-Identity PLMN-Identity,  
 LAC LAC,  
 iE-Extensions ProtocolExtensionContainer { {LAI-ExtIEs} } OPTIONAL,  
 ...  
 },  
 cI CI,  
 iE-Extensions ProtocolExtensionContainer { {CGI-ExtIEs} } OPTIONAL  
}

LAI-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {  
 ...  
}

CGI-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {  
 ...  
}

ChannelCodingType ::= ENUMERATED {  
 no-codingTDD,  
 convolutional-coding,  
 turbo-coding,  
 ...  
}

ChipOffset ::= INTEGER (0..38399)

CI ::= OCTET STRING (SIZE (2))

ClosedLoopModel-SupportIndicator ::= ENUMERATED {

```
closedLoop-Model-Supported,
closedLoop-Model-not-Supported
}

ClosedLoopMode2-SupportIndicator ::= ENUMERATED {
    closedLoop-Mode2-Supported,
    closedLoop-Mode2-not-Supported
}

ClosedloopTimingadjustmentmode ::= ENUMERATED {
    adj-1-slot,
    adj-2-slot,
    ...
}

CodeNumber ::= INTEGER (0..maxCodeNumComp-1)

CodingRate ::= ENUMERATED {
    half,
    third,
    ...
}

CommonMeasurementAccuracy ::= CHOICE {
    tUTRANGPSMeasurementAccuracyClass      TUTRANGPSAccuracyClass,
    ...
}

CommonMeasurementType ::= ENUMERATED {
    uTRAN-GPS-timing-of-cell-frames-for-UE-Positioning,
    sFN-SFN-observerd-time-difference,
    load,
    transmitted-carrier-power,
    received-total-wide-band-power,
    uplink-timeslot-iscp,
    ...,
    rT-load,
    nRT-load-Information
}
-- For measurements on the Iur-g interface, only load, RT Load and NRT Load information are requested.

CommonMeasurementValue ::= CHOICE {
    tUTRANGPSMeasurementValueInformation      TUTRANGPSMeasurementValueInformation,
    sFNSFNMeasurementValueInformation        SFNSFNMeasurementValueInformation,
    loadValue                                LoadValue,
    transmittedCarrierPowerValue            INTEGER(0..100),
    receivedTotalWideBandPowerValue         INTEGER(0..621),
    uplinkTimeslotISCPValue                UL-TimeslotISCP,
    ...,
    rTLoadValue                            RTLoadValue,
    nRTLoadInformationValue                 NRTLoadInformationValue
}
```

```
}

-- For measurements on the Iur-g interface, only load, RT Load and NRT Load values are reported.

CommonMeasurementValueInformation ::= CHOICE {
    measurementAvailable      CommonMeasurementAvailable,
    measurementnotAvailable   NULL
}

CommonMeasurementAvailable ::= SEQUENCE {
    commonMeasurementValue      CommonMeasurementValue,
    iE-Extensions               ProtocolExtensionContainer { { CommonMeasurementAvailableItem-ExtIEs} }      OPTIONAL,
    ...
}

CommonMeasurementAvailableItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

CongestionCause ::= ENUMERATED {
    uTRAN-dynamic-resources,
    uTRAN-semistatic-resources,
    ...
}

CommonTransportChannelResourcesInitialisationNotRequired ::= ENUMERATED {
    not-Required
}

CoverageIndicator ::= ENUMERATED {
    overlap,
    covers,
    containedIn,
    ...
}

CRC-Size ::= ENUMERATED {
    v0,
    v8,
    v12,
    v16,
    v24,
    ...
}

CriticalityDiagnostics ::= SEQUENCE {
    procedureID          ProcedureID      OPTIONAL,
    triggeringMessage    TriggeringMessage OPTIONAL,
    procedureCriticality Criticality       OPTIONAL,
    transactionID        TransactionID   OPTIONAL,
    iEsCriticalityDiagnostics CriticalityDiagnostics-IE-List OPTIONAL,
    iE-Extensions         ProtocolExtensionContainer { { CriticalityDiagnostics-ExtIEs} } OPTIONAL,
```

```
...
}

CriticalityDiagnostics-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

CriticalityDiagnostics-IE-List ::= SEQUENCE (SIZE (1..maxNrOfErrors)) OF
    SEQUENCE {
        iECriticality          Criticality,
        iE-ID                  ProtocolIE-ID,
        repetitionNumber        RepetitionNumber0      OPTIONAL,
        iE-Extensions           ProtocolExtensionContainer { {CriticalityDiagnostics-IE-List-ExtIEs} } OPTIONAL,
        ...
    }

CriticalityDiagnostics-IE-List-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-MessageStructure      CRITICALITY ignore      EXTENSION MessageStructure      PRESENCE optional } |
    { ID id-TypeOfError          CRITICALITY ignore      EXTENSION TypeOfError          PRESENCE mandatory },
    ...
}

MessageStructure ::= SEQUENCE (SIZE (1..maxNrOfLevels)) OF
    SEQUENCE {
        iE-ID                  ProtocolIE-ID,
        repetitionNumber        RepetitionNumber1      OPTIONAL,
        iE-Extensions           ProtocolExtensionContainer { {MessageStructure-ExtIEs} } OPTIONAL,
        ...
    }

MessageStructure-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

CN-CS-DomainIdentifier ::= SEQUENCE {
    pLMN-Identity          PLMN-Identity,
    LAC,
    iE-Extensions           ProtocolExtensionContainer { {CN-CS-DomainIdentifier-ExtIEs} } OPTIONAL
}

CN-CS-DomainIdentifier-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

CN-PS-DomainIdentifier ::= SEQUENCE {
    pLMN-Identity          PLMN-Identity,
    LAC,
    rAC,
    iE-Extensions           ProtocolExtensionContainer { {CN-PS-DomainIdentifier-ExtIEs} } OPTIONAL
}
```

```
CN-PS-DomainIdentifier-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {  
    ...  
}  
  
CNDomainType ::= ENUMERATED {  
    cs-domain,  
    ps-domain,  
    dont-care,  
    ...  
}  
-- See in [16]  
  
CQI-Feedback-Cycle ::= ENUMERATED {v0, v1, v5, v10, v20, v40, v80,...}  
  
CQI-Power-Offset ::= INTEGER (0..8,...)  
-- According to mapping in ref. [21] subclause 4.2.1  
  
CQI-RepetitionFactor ::= INTEGER (1..4,...)  
-- Step: 1  
  
C-RNTI ::= INTEGER (0..65535)  
  
/* partly omitted */  
  
-- P  
  
PagingCause ::= ENUMERATED {  
    terminating-conversational-call,  
    terminating-streaming-call,  
    terminating-interactive-call,  
    terminating-background-call,  
    terminating-low-priority-signalling,  
    ...  
    terminating-high-priority-signalling,  
    terminating-cause-unknown  
}  
-- See in [16]  
  
PagingRecordType ::= ENUMERATED {  
    imsi-gsm-map,  
    tmsi-gsm-map,  
    p-tmsi-gsm-map,  
    imsi-ds-41,  
    tmsi-ds-41,  
    ...  
}  
-- See in [16]  
  
PartialReportingIndicator ::= ENUMERATED {  
    partial-reporting-allowed
```

```

}

PayloadCRC-PresenceIndicator ::= ENUMERATED {
    crc-included,
    crc-not-included
}

PCCPCH-Power ::= INTEGER (-150..400,...)
-- PCCPCH-power = power * 10
-- If power <= -15 PCCPCH shall be set to -150
-- If power >= 40 PCCPCH shall be set to 400
-- Unit dBm, Range -15dBm .. +40 dBm, Step 0.1dBm

PCH-InformationList ::= SEQUENCE (SIZE(0..1)) OF PCH-InformationItem

PCH-InformationItem ::= SEQUENCE {
    transportFormatSet          TransportFormatSet,
    iE-Extensions               ProtocolExtensionContainer { { PCH-InformationItem-ExtIEs} } OPTIONAL,
    ...
}

PCH-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

PC-Preamble ::= INTEGER(0..7,...)

PDSCHCodeMapping ::= SEQUENCE {
    dL-ScramblingCode           DL-ScramblingCode,
    signallingMethod             PDSCHCodeMapping-SignallingMethod,
    iE-Extensions               ProtocolExtensionContainer { { PDSCHCodeMapping-ExtIEs} } OPTIONAL,
    ...
}

PDSCHCodeMapping-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

PDSCHCodeMapping-SignallingMethod ::= CHOICE {
    pDSCHCodeMapping-SignallingMethod-CodeRange      PDSCHCodeMapping-SignallingMethod-CodeRange,
    pDSCHCodeMapping-SignallingMethod-TFCIRange       PDSCHCodeMapping-SignallingMethod-TFCIRange,
    pDSCHCodeMapping-SignallingMethod-Explicit        PDSCHCodeMapping-SignallingMethod-Explicit,
    ...,
    pDSCHCodeMapping-SignallingMethod-Replace         PDSCHCodeMapping-SignallingMethod-Replace
}

PDSCHCodeMapping-SignallingMethod-CodeRange ::= SEQUENCE (SIZE (1..maxNoCodeGroups)) OF
SEQUENCE {
    spreadingFactor              SpreadingFactor,
    multi-code-info               Multi-code-info,
    start-CodeNumber              CodeNumber,
}

```

```

stop-CodeNumber           CodeNumber,
iE-Extensions             ProtocolExtensionContainer { { PDSCHCodeMapping-SignallingMethod-CodeRange-ExtIEs} } OPTIONAL,
...
}

PDSCHCodeMapping-SignallingMethod-CodeRange-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
...
}

PDSCHCodeMapping-SignallingMethod-TFCIRange ::= SEQUENCE (SIZE (1..maxNoTFCIGroups)) OF
SEQUENCE {
    maxTFCIvalue          MaxTFCIvalue,
    spreadingFactor        SpreadingFactor,
    multi-code-info        Multi-code-info,
    codeNumber             CodeNumber,
    iE-Extensions          ProtocolExtensionContainer { { PDSCHCodeMapping-SignallingMethod-TFCIRange-ExtIEs} } OPTIONAL,
...
}

PDSCHCodeMapping-SignallingMethod-TFCIRange-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
...
}

PDSCHCodeMapping-SignallingMethod-Explicit ::= SEQUENCE (SIZE (1..maxTFCI2Combs)) OF
SEQUENCE {
    spreadingFactor        SpreadingFactor,
    multi-code-info        Multi-code-info,
    codeNumber             CodeNumber,
    iE-Extensions          ProtocolExtensionContainer { { PDSCHCodeMapping-SignallingMethod-Explicit-ExtIEs} } OPTIONAL,
...
}

PDSCHCodeMapping-SignallingMethod-Explicit-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
...
}

PDSCHCodeMapping-SignallingMethod-Replace ::= SEQUENCE (SIZE (1..maxTFCI2Combs)) OF
SEQUENCE {
    tfci-Field2            TFCS-MaxTFCI-field2-Value,
    spreadingFactor         SpreadingFactor,
    multi-CodeInfo          Multi-code-info,
    codeNumber              CodeNumber,
    iE-Extensions           ProtocolExtensionContainer { { PDSCHCodeMapping-SignallingMethod-Replace-ExtIEs} } OPTIONAL,
...
}

PDSCHCodeMapping-SignallingMethod-Replace-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
...
}

Periodic ::= SEQUENCE {

```

```
reportPeriodicity      ReportPeriodicity,
iE-Extensions         ProtocolExtensionContainer { {Periodic-ExtIEs} } OPTIONAL,
...
}

Periodic-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
  ...
}

PeriodicInformation ::= SEQUENCE {
  informationReportPeriodicity      InformationReportPeriodicity,
  iE-Extensions                     ProtocolExtensionContainer { {PeriodicInformation-ExtIEs} } OPTIONAL,
  ...
}

PeriodicInformation-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
  ...
}

Permanent-NAS-UE-Identity ::= CHOICE {
  imsi             IMSI,
  ...
}

Phase-Reference-Update-Indicator ::= ENUMERATED {
  Phase-reference-needs-to-be-changed
}

PLMN-Identity ::= OCTET STRING (SIZE(3))

PowerAdjustmentType ::= ENUMERATED {
  none,
  common,
  individual
}

PowerOffset           ::= INTEGER (0..24)

PRC ::= INTEGER (-2047..2047)
--pseudo range correction; scaling factor 0.32 meters

PRCDeviation ::= ENUMERATED {
  prcd1,
  prcd2,
  prcd5,
  prcd10,
  ...
}

Pre-emptionCapability ::= ENUMERATED {
  shall-not-trigger-pre-emption,
```

```
may-trigger-pre-emption
}

Pre-emptionVulnerability ::= ENUMERATED {
    not-pre-emptable,
    pre-emptable
}

PredictedSFNSFNDeviationLimit ::= INTEGER (1..256)
-- Unit chip, Step 1/16 chip, Range 1/16..16 chip

PredictedTUTRANGPSDeviationLimit ::= INTEGER (1..256)
-- Unit chip, Step 1/16 chip, Range 1/16..16 chip

PrimaryCPICH-Power      ::= INTEGER (-100..500)
-- step 0.1 (Range -10.0..50.0) Unit is dBm

PrimaryCPICH-EcNo       ::= INTEGER (-30..30)

Primary-CPICH-Usage-For-Channel-Estimation ::= ENUMERATED {
    primary-CPICH-may-be-used,
    primary-CPICH-shall-not-be-used
}

PrimaryCCPCH-RSCP      ::= INTEGER (0..91)
-- According to mapping in [14]

PrimaryScramblingCode  ::= INTEGER (0..511)

PriorityLevel          ::= INTEGER (0..15)
-- 0 = spare, 1 = highest priority, ...14 = lowest priority and 15 = no priority

PriorityQueue-Id       ::= INTEGER (0..maxNrOfPrioQueues-1)

PriorityQueue-InfoList ::= SEQUENCE (SIZE (1..maxNrOfPrioQueues)) OF PriorityQueue-InfoItem

PriorityQueue-InfoItem ::= SEQUENCE {
    priorityQueue-Id           PriorityQueue-Id,
    schedulingPriorityIndicator SchedulingPriorityIndicator,
    t1                           T1,
    mAC-hsWindowSize            MAC-hsWindowSize,
    mAChsGuaranteedBitRate     MAChsGuaranteedBitRate OPTIONAL,
    mACdPDU-Size-Index          MACdPDU-Size-IndexList,
    iE-Extensions                ProtocolExtensionContainer { { PriorityQueue-InfoItem-ExtIEs } } OPTIONAL,
    ...
}

PriorityQueue-InfoItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {  
    ...  
}
```

**Release 5****3GPP TS 25.423 V5.0.0(2002-03)**

```
PriorityQueue-InfoList-to-Modify ::= SEQUENCE (SIZE (1..maxNrOfPrioQueues)) OF PriorityQueue-InfoItem-to-Modify

PriorityQueue-InfoItem-to-Modify ::= SEQUENCE {
    priorityQueue-Id                  PriorityQueue-Id,
    schedulingPriorityIndicator       SchedulingPriorityIndicator      OPTIONAL,
    t1                                T1                               OPTIONAL,
    mAC-hsWindowSize                 MAC-hsWindowSize            OPTIONAL,
    mAChsGuaranteedBitRate           MACChsGuaranteedBitRate   OPTIONAL,
    mACdPDU-Size-Index-to-Modify     MACdPDU-Size-IndexList-to-Modify   OPTIONAL,
    iE-Extensions                     ProtocolExtensionContainer { {PriorityQueue-InfoItem-to-Modify-ExtIEs} }      OPTIONAL,
    ...
}

PriorityQueue-InfoItem-to-Modify-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

PropagationDelay          ::= INTEGER (0..255)

PunctureLimit             ::= INTEGER (0..15)
-- 0: 40%; 1: 44%; ... 14: 96%; 15: 100

/* partly omitted */

-- S

SAC                      ::= OCTET STRING (SIZE (2))

SAI ::= SEQUENCE {
    pLMN-Identity        PLMN-Identity,
    LAC                  LAC,
    sAC                  SAC,
    iE-Extensions        ProtocolExtensionContainer { {SAI-ExtIEs} } OPTIONAL
}

SAI-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

SAT-ID      ::= INTEGER (0..63)

SCH-TimeSlot          ::= INTEGER (0..6)

ScaledAdjustmentRatio  ::= INTEGER(0..100)
-- AdjustmentRatio = ScaledAdjustmentRatio / 100

Secondary-CCPCH-Info ::= SEQUENCE {
    fDD-S-CCPCH-Offset      FDD-S-CCPCH-Offset,
    dl-ScramblingCode       DL-ScramblingCode,
    fDD-DL-ChannelisationCodeNumber FDD-DL-ChannelisationCodeNumber,
    dl-TFCS                TFCS,
```

```

secondaryCCPCH-SlotFormat           SecondaryCCPCH-SlotFormat,
tFCI-Presence                      TFCI-Presence OPTIONAL,
-- This IE shall be present only if the Secondary CCPCH Slot Format IE is equal to any of the values from 8 to 17
multiplexingPosition               MultiplexingPosition,
sTDD-Indicator                      STTD-Indicator,
fACH-PCH-InformationList           FACH-PCH-InformationList,
iB-schedulingInformation           IB-SchedulingInformation,
iE-Extensions                       ProtocolExtensionContainer { { Secondary-CCPCH-Info-ExtIEs } } OPTIONAL,
...
}

Secondary-CCPCH-Info-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
  ...
}

Secondary-CCPCH-Info-TDD ::= SEQUENCE {
  dl-TFCS                           TFCS,
  tFCI-Coding                        TFCI-Coding,
  secondary-CCPCH-TDD-InformationList Secondary-CCPCH-TDD-InformationList,
  fACH-InformationList                FACH-InformationList,
  pCH-InformationList                 PCH-InformationList,
  iE-Extensions                      ProtocolExtensionContainer { { Secondary-CCPCH-Info-TDD-ExtIEs } } OPTIONAL,
  ...
}

Secondary-CCPCH-Info-TDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
  ...
}

Secondary-CPICH-Information ::= SEQUENCE {
    dl-ScramblingCode              DL-ScramblingCode,
    fDD-DL-ChannelisationCodeNumber FDD-DL-ChannelisationCodeNumber,
    iE-Extensions                  ProtocolExtensionContainer { { Secondary-CPICH-Information-ExtIEs } } OPTIONAL,
  ...
}

Secondary-CPICH-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
  ...
}

Secondary-CPICH-Information-Change ::= CHOICE {
    new-secondary-CPICH            Secondary-CPICH-Information,
    secondary-CPICH-shall-not-be-used NULL,
  ...
}

Secondary-LCR-CCPCH-Info-TDD ::= SEQUENCE {
    dl-TFCS                         TFCS,
    tFCI-Coding                     TFCI-Coding,
    secondary-LCR-CCPCH-TDD-InformationList Secondary-LCR-CCPCH-TDD-InformationList,
    fACH-InformationList             FACH-InformationList,

```

```

pCH-InformationList
iE-Extensions
...
}

Secondary-LCR-CCPCH-Info-TDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
  ...
}

Secondary-CCPCH-TDD-InformationList ::= SEQUENCE (SIZE(0.. maxNrOfSCCPCHs)) OF Secondary-CCPCH-TDD-InformationItem

Secondary-CCPCH-TDD-InformationItem ::= SEQUENCE {
  timeSlot                      TimeSlot,
  midambleShiftAndBurstType     MidambleShiftAndBurstType,
  tFCI-Presence                 TFCI-Presence,
  secondary-CCPCH-TDD-Code-Information Secondary-CCPCH-TDD-Code-Information,
  tDD-PhysicalChannelOffset      TDD-PhysicalChannelOffset,
  repetitionLength               RepetitionLength,
  repetitionPeriod               RepetitionPeriod,
  iE-Extensions                  ProtocolExtensionContainer { { Secondary-CCPCH-TDD-InformationItem-ExtIEs } } OPTIONAL,
  ...
}

Secondary-CCPCH-TDD-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
  ...
}

Secondary-LCR-CCPCH-TDD-InformationList ::= SEQUENCE (SIZE(0.. maxNrOfSCCPCHs)) OF Secondary-LCR-CCPCH-TDD-InformationItem

Secondary-LCR-CCPCH-TDD-InformationItem ::= SEQUENCE {
  timeSlotLCR                   TimeSlotLCR,
  midambleShiftLCR              MidambleShiftLCR,
  tFCI-Presence                 TFCI-Presence,
  secondary-LCR-CCPCH-TDD-Code-Information Secondary-LCR-CCPCH-TDD-Code-Information,
  tDD-PhysicalChannelOffset      TDD-PhysicalChannelOffset,
  repetitionLength               RepetitionLength,
  repetitionPeriod               RepetitionPeriod,
  iE-Extensions                  ProtocolExtensionContainer { { Secondary-LCR-CCPCH-TDD-InformationItem-ExtIEs } } OPTIONAL,
  ...
}

Secondary-LCR-CCPCH-TDD-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
  ...
}

Secondary-CCPCH-TDD-Code-Information ::= SEQUENCE ( SIZE (1..maxNrOfSCCPCHs) ) OF Secondary-CCPCH-TDD-Code-InformationItem

Secondary-CCPCH-TDD-Code-InformationItem ::= SEQUENCE {
  tDD-ChannelisationCode        TDD-ChannelisationCode,
  iE-Extensions                  ProtocolExtensionContainer { { Secondary-CCPCH-TDD-Code-InformationItem-ExtIEs } } OPTIONAL,
  ...
}

```

```
}

Secondary-CCPCH-TDD-Code-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

Secondary-LCR-CCPCH-TDD-Code-Information ::= SEQUENCE ( SIZE (1..maxNrOfSCCPCHs) ) OF Secondary-LCR-CCPCH-TDD-Code-InformationItem

Secondary-LCR-CCPCH-TDD-Code-InformationItem ::= SEQUENCE {
    tDD-ChannelisationCodeLCR      TDD-ChannelisationCodeLCR,
    s-CCPCH-TimeSlotFormat-LCR    TDD-DL-DPCH-TimeSlotFormat-LCR,
    iE-Extensions                 ProtocolExtensionContainer { {Secondary-LCR-CCPCH-TDD-Code-InformationItem-ExtIEs} } OPTIONAL,
    ...
}

Secondary-LCR-CCPCH-TDD-Code-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

SecondInterleavingMode ::= ENUMERATED {
    frame-related,
    timeslot-related,
    ...
}

Seed ::= INTEGER (0..63)

SFN ::= INTEGER (0..4095)

SFNSFN-FDD ::= INTEGER(0..614399)

SFNSFN-TDD ::= INTEGER(0..40961)

GA-AccessPointPositionwithOptionalAltitude ::= SEQUENCE {
    geographicalCoordinate          GeographicalCoordinate,
    altitudeAndDirection           GA-AltitudeAndDirection OPTIONAL,
    iE-Extensions                  ProtocolExtensionContainer { {GA-AccessPointPositionwithOptionalAltitude-ExtIEs} } OPTIONAL,
    ...
}

GA-AccessPointPositionwithOptionalAltitude-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

SFNSFNChangeLimit ::= INTEGER (1..256)
-- Unit chip, Step 1/16 chip, Range 1/16..16 chip

SFNSFNDriftRate ::= INTEGER (-100..100)
-- Unit chip/s, Step 1/256 chip/s, Range -100/256..+100/256 chip/s

SFNSFNDriftRateQuality ::= INTEGER (0..100)
```

```
-- Unit chip/s, Step 1/256 chip/s, Range 0..100/256 chip/s

SFNSFNMeasurementThresholdInformation ::= SEQUENCE {
    sFNSFNChangeLimit          SFNSFNChangeLimit           OPTIONAL,
    predictedSFNSFNDeviationLimit PredictedSFNSFNDeviationLimit   OPTIONAL,
    iE-Extensions               ProtocolExtensionContainer { { SFNSFNMeasurementThresholdInformation-ExtIEs} }      OPTIONAL,
    ...
}

SFNSFNMeasurementThresholdInformation-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

SFNSFNMeasurementValueInformation ::= SEQUENCE {
    successfullNeighbouringCellSFNSFNObservedTimeDifferenceMeasurementInformation      SEQUENCE (SIZE(1..maxNrOfMeasNCell)) OF
    SEQUENCE {
        uC-ID          UC-ID,
        sFNSFNValue     SFNSFNValue,
        sFNSFNQuality   SFNSFNQuality           OPTIONAL,
        sFNSFNDriftRate SFNSFNDriftRate,
        sFNSFNDriftRateQuality SFNSFNDriftRateQuality,
        sFNSFNTimeStampInformation SFNSFNTimeStampInformation   OPTIONAL,
        iE-Extensions   ProtocolExtensionContainer { { SuccessfullNeighbouringCellSFNSFNObservedTimeDifferenceMeasurementInformationItem-ExtIEs} }      OPTIONAL,
        ...
    },
    unsuccessfullNeighbouringCellsSFNSFNObservedTimeDifferenceMeasurementInformation      SEQUENCE (SIZE(0..maxNrOfMeasNCell-1)) OF
    SEQUENCE {
        uC-ID          UC-ID,
        iE-Extensions   ProtocolExtensionContainer { { UnsuccessfullNeighbouringCellsSFNSFNObservedTimeDifferenceMeasurementInformationItem-ExtIEs} }      OPTIONAL,
        ...
    },
    iE-Extensions   ProtocolExtensionContainer { { SFNSFNMeasurementValueInformationItem-ExtIEs} }      OPTIONAL,
    ...
}

SFNSFNMeasurementValueInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

SuccessfullNeighbouringCellSFNSFNObservedTimeDifferenceMeasurementInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

UnsuccessfullNeighbouringCellsSFNSFNObservedTimeDifferenceMeasurementInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}
```

```
}

SFNSFNQuality ::= INTEGER (0..255)
-- Unit chip, Step 1/16 chip, Range 0.. 255/16 chip

SFNSFNTimeStampInformation ::= CHOICE {
    SFNSFNTimeStamp-FDD      SFN,
    SFNSFNTimeStamp-TDD      SFNSFNTimeStamp-TDD,
    ...
}

SFNSFNTimeStamp-TDD ::= SEQUENCE {
    SFN                  SFN,
    timeSlot             TimeSlot,
    iE-Extensions        ProtocolExtensionContainer { { SFNSFNTimeStamp-ExtIEs } } OPTIONAL,
    ...
}

SFNSFNTimeStamp-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {

}

SFNSFNValue ::= CHOICE {
    SFNSFN-FDD      SFNSFN-FDD,
    SFNSFN-TDD      SFNSFN-TDD,
    ...
}

SID ::= INTEGER (0..maxNrOfPDUIndexes-1)

SIR-Error-Value          ::= INTEGER (0..125)

SIR-Error-Value-IncrDecrThres      ::= INTEGER (0..124)

SIR-Value                ::= INTEGER (0..63)
-- According to mapping in 25.215/25.225

SIR-Value-IncrDecrThres ::= INTEGER (0..62)

SecondaryCCPCH-SlotFormat      ::= INTEGER (0..17,...)
-- refer to 25.211

S-FieldLength           ::= ENUMERATED {
    v1,
    v2,
    ...
}
```

```
SNA-Information ::= SEQUENCE {
    pLMN-Identity    PLMN-Identity,
    listOfSNAs        ListOfSNAs                               OPTIONAL,
    iE-Extensions     ProtocolExtensionContainer { { SNA-Information-ExtIEs } } OPTIONAL,
    ...
}

SNA-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

ListOfSNAs ::= SEQUENCE (SIZE (1.. maxNrOfSNAs, ...)) OF SNACode

SNACode ::= INTEGER (0..65535)

SpecialBurstScheduling ::= INTEGER (1..256)

SplitType ::= ENUMERATED {
    hard,
    logical
}

SpreadingFactor       ::= INTEGER (4| 8| 16| 32| 64| 128| 256)

S-RNTI               ::= INTEGER (0..1048575)
-- From 0 to 2^20-1

SRB-Delay ::= INTEGER(0..7,...)

SSDT-CellID ::= ENUMERATED {
    a,
    b,
    c,
    d,
    e,
    f,
    g,
    h
}

SSDT-CellID-Length ::= ENUMERATED {
    short,
    medium,
    long
}

SSDT-Indication ::= ENUMERATED {
    SSDT-active-in-the-UE,
    SSDT-not-active-in-the-UE
}
```

```

SSDT-SupportIndicator ::= ENUMERATED {
    sSDT-supported,
    sSDT-not-supported
}

STTD-Indicator ::= ENUMERATED {
    active,
    inactive
}

STTD-SupportIndicator ::= ENUMERATED {
    sTTD-Supported,
    sTTD-not-Supported
}

Support-8PSK ::= ENUMERATED {
    v8PSK-Supported
}

SyncCase ::= INTEGER (1..2,...)

SynchronisationConfiguration ::= SEQUENCE {
    n-INSYNC-IND          INTEGER (1..256),
    n-OUTSYNC-IND         INTEGER (1..256),
    t-RLFAILURE           INTEGER (0..255),
    -- Unit seconds, Range 0s .. 25.5s, Step 0.1s
    iE-Extensions         ProtocolExtensionContainer { { SynchronisationConfiguration-ExtIEs} }   OPTIONAL,
    ...
}

SynchronisationConfiguration-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

SYNC-UL-ProcParameters ::= SEQUENCE {
    maxSYNC-UL-transmissions      ENUMERATED {v1, v2, v4, v8, ...},
    powerRampStep                 INTEGER (0..3, ...),
    ...
}

/* partly omitted */

-- U

UARFCN ::= INTEGER (0..16383,...)
-- Corresponds to: 0.0Hz..3276.6Mhz. See 25.101, 25.105

UDRE ::= ENUMERATED {
    lessThan1,
    between1-and-4,
}

```

```

between4-and-8,
over8,
...
}

UE-Capabilities-InfoFDD ::= SEQUENCE {
    hSDSCH-TrCH-Bits-Per-HSDSCH-TTI      ENUMERATED {v7300, v14600, v20456, v28800,...},
    hSDSCH-Multi-Code-Capability          ENUMERATED {v5, v10, v15,...},
    min-Inter-TTI-Interval                INTEGER (1..3,...),
    mAChs-Reordering-Buffer-Size         INTEGER (1..300,...),
    iE-Extensions                         ProtocolExtensionContainer { { UE-Capabilities-InfoFDD-ExtIEs } }           OPTIONAL,
    ...
}

UE-Capabilities-InfoFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

UE-Capabilities-InfoTDD ::= SEQUENCE {
    hSDSCH-TrCH-Bits-Per-HSDSCH-TTI      ENUMERATED {v7040, v10228, v14080,...},
    hSDSCH-Multi-Code-Capability          ENUMERATED {v8, v12, v16,...},
    mAChs-Reordering-Buffer-Size         INTEGER (1..300,...),
    iE-Extensions                         ProtocolExtensionContainer { { UE-Capabilities-InfoTDD-ExtIEs } }           OPTIONAL,
    ...
}

UE-Capabilities-InfoTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation ::= ENUMERATED {
    dedicated-pilots-for-channel-estimation-supported
}

UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH ::= ENUMERATED {
    dedicated-pilots-for-channel-estimation-supported
}

UL-DL-mode ::= ENUMERATED {
    ul-only,
    dl-only,
    both-ul-and-dl
}

UL-Timeslot-Information ::= SEQUENCE ( SIZE (1..maxNrOfTS) ) OF UL-Timeslot-InformationItem

UL-Timeslot-InformationItem ::= SEQUENCE {
    timeSlot                      TimeSlot,
    midambleShiftAndBurstType     MidambleShiftAndBurstType,
    tFCI-Presence                 TFCI-Presence,
    uL-Code-Information           TDD-UL-Code-Information,
}

```

**Release 5**

**3GPP TS 25.423 V5.0.0(2002-03)**

```
iE-Extensions          ProtocolExtensionContainer { {UL-Timeslot-InformationItem-ExtIEs} } OPTIONAL,
...
}

UL-Timeslot-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

UL-TimeslotLCR-Information ::= SEQUENCE (SIZE (1..maxNrOfULTsLCR)) OF UL-TimeslotLCR-InformationItem

UL-TimeslotLCR-InformationItem ::= SEQUENCE {
    timeSlotLCR                  TimeSlotLCR,
    midambleShiftLCR              MidambleShiftLCR,
    tFCI-Presence                 TFCI-Presence,
    uL-Code-LCR-InformationList   TDD-UL-Code-LCR-Information,
    iE-Extensions                 ProtocolExtensionContainer { { UL-TimeslotLCR-InformationItem-ExtIEs} } OPTIONAL,
    ...
}

UL-TimeslotLCR-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

UL-TimeSlot-ISCP-Info ::= SEQUENCE (SIZE (1..maxNrOfULTs)) OF UL-TimeSlot-ISCP-InfoItem

UL-TimeSlot-ISCP-InfoItem ::= SEQUENCE {
    timeSlot                  TimeSlot,
    uL-TimeslotISCP            UL-TimeslotISCP,
    iE-Extensions              ProtocolExtensionContainer { { UL-TimeSlot-ISCP-InfoItem-ExtIEs} } OPTIONAL,
    ...
}

UL-TimeSlot-ISCP-InfoItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

UL-TimeSlot-ISCP-LCR-Info ::= SEQUENCE (SIZE (1..maxNrOfULTsLCR)) OF     UL-TimeSlot-ISCP-LCR-InfoItem

UL-TimeSlot-ISCP-LCR-InfoItem ::= SEQUENCE {
    timeSlotLCR                  TimeSlotLCR,
    iSCP                         UL-Timeslot-ISCP-Value,
    iE-Extensions                 ProtocolExtensionContainer { { UL-TimeSlot-ISCP-LCR-InfoItem-ExtIEs} } OPTIONAL,
    ...
}

UL-TimeSlot-ISCP-LCR-InfoItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

UL-Timeslot-ISCP-Value ::= UL-TimeslotISCP
```

```

UL-Timeslot-ISCP-Value-IncrDecrThres ::= INTEGER(0..126)
-- Unit dB. Step 0.5dB
-- e.g. Value 100 means 50dB

UL-TimingAdvanceCtrl-LCR ::= SEQUENCE {
    sync-UL-codes-bitmap           BIT STRING (SIZE(8)),
    fPACH-info                      FPACH-Information,
    prxUpPCHdes                    INTEGER (-120 .. -58, ...),
    syncUL-procParameter            SYNC-UL-ProcParameters,
    mMax                            INTEGER (1..32),
    ...
}

Uplink-Compressed-Mode-Method ::= ENUMERATED {
    sFdiv2,
    higher-layer-scheduling,
    ...
}

UL-SIR ::= INTEGER (-82..173)
-- The UL-SIR gives the UL-SIR in number of 0.1 dB steps.
-- E.g. Value 173 means 17.3 dB
-- Unit dB. Step 0.1 dB.

UC-ID ::= SEQUENCE {
    rNC-ID             RNC-ID,
    c-ID               C-ID,
    iE-Extensions      ProtocolExtensionContainer { {UC-ID-ExtIEs} } OPTIONAL,
    ...
}

UC-ID-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

UL-DPCCH-SlotFormat ::= INTEGER (0..5,...)

UL-FP-Mode ::= ENUMERATED {
    normal,
    silent,
    ...
}

UL-PhysCH-SF-Variation ::= ENUMERATED {
    sf-variation-supported,
    sf-variation-not-supported
}

UL-ScramblingCode ::= SEQUENCE {
    ul-ScramblingCodeNumber     UL-ScramblingCodeNumber,
    ul-ScramblingCodeLength     UL-ScramblingCodeLength,
}

```

**Release 5****3GPP TS 25.423 V5.0.0(2002-03)**

```
iE-Extensions          ProtocolExtensionContainer { {UL-ScramblingCode-ExtIEs} } OPTIONAL
}

UL-ScramblingCode-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
  ...
}

UL-ScramblingCodeLength ::= ENUMERATED {
  short,
  long
}

UL-ScramblingCodeNumber ::= INTEGER (0..16777215)

UL-Synchronisation-Parameters-LCR ::= SEQUENCE {
  uL-Synchronisation-StepSize      UL-Synchronisation-StepSize,
  uL-Synchronisation-Frequency    UL-Synchronisation-Frequency,
  iE-Extensions                  ProtocolExtensionContainer { {UL-Synchronisation-Parameters-LCR-ExtIEs} } OPTIONAL,
  ...
}

UL-Synchronisation-Parameters-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
  ...
}

UL-Synchronisation-StepSize ::= INTEGER (1..8)

UL-Synchronisation-Frequency ::= INTEGER (1..8)

UL-TimeslotISCP ::= INTEGER (0..127)
-- According to mapping in [14]

URA-ID ::= INTEGER (0..65535)

URA-Information ::= SEQUENCE {
  uRA-ID,
  multipleURAsIndicator,
  rNCsWithCellsInTheAccessedURA-List RNCsWithCellsInTheAccessedURA-List OPTIONAL,
  iE-Extensions                  ProtocolExtensionContainer { {URA-Information-ExtIEs} } OPTIONAL,
  ...
}

URA-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
  ...
}

RNCsWithCellsInTheAccessedURA-List ::= SEQUENCE (SIZE (1..maxRNCinURA-1)) OF RNCsWithCellsInTheAccessedURA-Item

RNCsWithCellsInTheAccessedURA-Item ::= SEQUENCE {
  rNC-ID,
  iE-Extensions                  ProtocolExtensionContainer { {RNCsWithCellsInTheAccessedURA-Item-ExtIEs} } OPTIONAL,
```

```
...
}

RNCsWithCellsInTheAccessedURA-Item-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ...
}

USCH-ID          ::= INTEGER (0..255)

USCH-Information ::= SEQUENCE (SIZE (1..maxNoOfUSCHs)) OF USCH-InformationItem

USCH-InformationItem ::= SEQUENCE {
    uSCH-ID                  USCH-ID,
    ul-CCTrCH-ID             CCTrCH-ID,
    trChSourceStatisticsDescriptor TrCH-SrcStatisticsDescr,
    transportFormatSet         TransportFormatSet,
    allocationRetentionPriority AllocationRetentionPriority,
    schedulingPriorityIndicator SchedulingPriorityIndicator,
    rb-Info                   RB-Info,
    iE-Extensions             ProtocolExtensionContainer { {USCH-InformationItem-ExtIEs} } OPTIONAL,
    ...
}

USCH-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-TrafficClass      CRITICALITY ignore EXTENSION TrafficClass      PRESENCE mandatory } |
    { ID id-BindingID         CRITICALITY ignore EXTENSION BindingID      PRESENCE           optional } |
    -- Shall be ignored if bearer establishment with ALCAP.
    { ID id-TransportLayerAddress CRITICALITY ignore EXTENSION TransportLayerAddress PRESENCE optional },
    -- Shall be ignored if bearer establishment with ALCAP.
    ...
}

-- V
-- W
-- X
-- Y
-- Z

END
```

### 9.3.6 Constant Definitions

```
-- ****
-- Constant definitions
-- ****

RNSAP-Constants {
    itu-t (0) identified-organization (4) etsi (0) mobileDomain (0)
    umts-Access (20) modules (3) rnsap (1) version1 (1) rnsap-Constants (4) }

DEFINITIONS AUTOMATIC TAGS ::=

BEGIN

IMPORTS
    ProcedureCode,
    ProtocolIE-ID
FROM RNSAP-CommonDataTypes;

-- ****
-- Elementary Procedures
-- ****

id-commonTransportChannelResourcesInitialisation      ProcedureCode ::= 0
id-commonTransportChannelResourcesRelease            ProcedureCode ::= 1
id-compressedModeCommand                           ProcedureCode ::= 2
id-downlinkPowerControl                            ProcedureCode ::= 3
id-downlinkPowerTimeslotControl                   ProcedureCode ::= 4
id-downlinkSignallingTransfer                     ProcedureCode ::= 5
id-errorIndication                                ProcedureCode ::= 6
id-dedicatedMeasurementFailure                  ProcedureCode ::= 7
id-dedicatedMeasurementInitiation                ProcedureCode ::= 8
id-dedicatedMeasurementReporting                 ProcedureCode ::= 9
id-dedicatedMeasurementTermination               ProcedureCode ::= 10
id-paging                                       ProcedureCode ::= 11
id-physicalChannelReconfiguration                ProcedureCode ::= 12
id-privateMessage                                 ProcedureCode ::= 13
id-radioLinkAddition                            ProcedureCode ::= 14
id-radioLinkCongestion                          ProcedureCode ::= 34
id-radioLinkDeletion                            ProcedureCode ::= 15
id-radioLinkFailure                             ProcedureCode ::= 16
id-radioLinkPreemption                         ProcedureCode ::= 17
id-radioLinkRestoration                        ProcedureCode ::= 18
id-radioLinkSetup                               ProcedureCode ::= 19
id-relocationCommit                           ProcedureCode ::= 20
id-synchronisedRadioLinkReconfigurationCancellation ProcedureCode ::= 21
```

**Release 5**

```
id-synchronisedRadioLinkReconfigurationCommit  
id-synchronisedRadioLinkReconfigurationPreparation  
id-unSynchronisedRadioLinkReconfiguration  
id-uplinkSignallingTransfer  
id-commonMeasurementFailure  
id-commonMeasurementInitiation  
id-commonMeasurementReporting  
id-commonMeasurementTermination  
id-informationExchangeFailure  
id-informationExchangeInitiation  
id-informationReporting  
id-informationExchangeTermination  
id-reset  
id-radioLinkActivation  
id-gERANuplinkSignallingTransfer  
id-radioLinkParameterUpdate
```

```
-- ****  
--  
-- Lists  
--  
-- ****
```

maxCodeNumComp-1	INTEGER ::= 255
maxRateMatching	INTEGER ::= 256
maxNoCodeGroups	INTEGER ::= 256
maxNoOfDSCHs	INTEGER ::= 10
maxNoOfDSCHsLCR	INTEGER ::= 10
maxNoOfRB	INTEGER ::= 32
maxNoOfUSCHs	INTEGER ::= 10
maxNoOfUSCHsLCR	INTEGER ::= 10
maxNoTFCIGroups	INTEGER ::= 256
maxNrOfTFCs	INTEGER ::= 1024
maxNrOfTFs	INTEGER ::= 32
maxNrOfCCTrCHs	INTEGER ::= 16
maxNrOfCCTrCHsLCR	INTEGER ::= 16
maxNrOfDCHs	INTEGER ::= 128
maxNrOfDL-Codes	INTEGER ::= 8
maxNrOfDPCHs	INTEGER ::= 240
maxNrOfDPCHsLCR	INTEGER ::= 240
maxNrOfErrors	INTEGER ::= 256
maxNrOfMACcshSDU-Length	INTEGER ::= 16
maxNrOfPoints	INTEGER ::= 15
maxNrOfRLs	INTEGER ::= 16
maxNrOfRLSets	INTEGER ::= maxNrOfRLs
maxNrOfRLSets-1	INTEGER ::= 15 -- maxNrOfRLSets - 1
maxNrOfRLs-1	INTEGER ::= 15 -- maxNrOfRLs - 1
maxNrOfRLs-2	INTEGER ::= 14 -- maxNrOfRLs - 2
maxNrOfULTs	INTEGER ::= 15
maxNrOfULTsLCR	INTEGER ::= 6
maxNrOfDLTs	INTEGER ::= 15

**3GPP TS 25.423 V5.0.0(2002-03)**

ProcedureCode ::= 22
ProcedureCode ::= 23
ProcedureCode ::= 24
ProcedureCode ::= 25
ProcedureCode ::= 26
ProcedureCode ::= 27
ProcedureCode ::= 28
ProcedureCode ::= 29
ProcedureCode ::= 30
ProcedureCode ::= 31
ProcedureCode ::= 32
ProcedureCode ::= 33
ProcedureCode ::= 35
ProcedureCode ::= 36
ProcedureCode ::= 37
ProcedureCode ::= 38

**Release 5****3GPP TS 25.423 V5.0.0(2002-03)**

```
maxNrOfDLTsLCR           INTEGER ::= 6
maxRNCinURA-1            INTEGER ::= 15
maxTTI-Count              INTEGER ::= 4
maxCTFC                   INTEGER ::= 16777215
maxNrOfNeighbouringRNCs  INTEGER ::= 10
maxNrOfFDDNeighboursPerRNC INTEGER ::= 256
maxNrOfGSMNeighboursPerRNC INTEGER ::= 256
maxNrOfTDDNeighboursPerRNC INTEGER ::= 256
maxNrOfFACHs               INTEGER ::= 8
maxNrOfLCRTDDNeighboursPerRNC INTEGER ::= 256
maxFACHCountPlus1         INTEGER ::= 10
maxIBSEG                  INTEGER ::= 16
maxNrOfSCCPCHs            INTEGER ::= 8
maxTFCI1Combs             INTEGER ::= 512
maxTFCI2Combs             INTEGER ::= 1024
maxTFCI2Combs-1           INTEGER ::= 1023
maxTGPS                   INTEGER ::= 6
maxNrOfTS                  INTEGER ::= 15
maxNrOfLevels              INTEGER ::= 256
maxNrOfDSCHs-1             INTEGER ::= 9
maxNrOfTsLCR               INTEGER ::= 6
maxNoSat                  INTEGER ::= 16
maxNoGPSTypes              INTEGER ::= 8
maxNrOfMeasNCell           INTEGER ::= 96
maxNrOfMeasNCell-1         INTEGER ::= 95 -- maxNrOfMeasNCell - 1
maxResetContext             INTEGER ::= 250
maxNrOfHARQProc             INTEGER ::= 8
maxNrOfHSSCCHCodes          INTEGER ::= 4
maxNrOfHSSICHs              INTEGER ::= 4
maxNrOfMACdFlows            INTEGER ::= 8
maxNrOfMACdFlows-1          INTEGER ::= 7 -- maxNrOfMACdFlows - 1
maxNrOfPDUIndexes            INTEGER ::= 8
maxNrOfPDUIndexes-1          INTEGER ::= 7 -- maxNrOfPDUIndexes - 1
maxNrOfPrioQueues            INTEGER ::= 8
maxNrOfPrioQueues-1          INTEGER ::= 7 -- maxNrOfPrioQueues - 1
maxNrOfSNAs                 INTEGER ::= 65535

-- *****
-- 
-- IEs
-- 
-- *****
```

```
id-AllowedQueueingTime        ProtocolIE-ID ::= 4
id-Allowed-Rate-Information   ProtocolIE-ID ::= 42
id-AntennaColocationIndicator ProtocolIE-ID ::= 309
id-BindingID                  ProtocolIE-ID ::= 5
id-C-ID                       ProtocolIE-ID ::= 6
id-C-RNTI                     ProtocolIE-ID ::= 7
id-Cell-Capacity-Class-Value  ProtocolIE-ID ::= 303
id-CFN                        ProtocolIE-ID ::= 8
```

**Release 5**

id-CN-CS-DomainIdentifier  
id-CN-PS-DomainIdentifier  
id-Cause  
id-CoverageIndicator  
id-CriticalityDiagnostics  
id-ContextInfoItem-Reset  
id-D-RNTI  
id-D-RNTI-ReleaseIndication  
id-DCHs-to-Add-FDD  
id-DCHs-to-Add-TDD  
id-DCH-DeleteList-RL-ReconfPrepFDD  
id-DCH-DeleteList-RL-ReconfPrepTDD  
id-DCH-DeleteList-RL-ReconfRqstFDD  
id-DCH-DeleteList-RL-ReconfRqstTDD  
id-DCH-FDD-Information  
id-DCH-TDD-Information  
id-FDD-DCHs-to-Modify  
id-TDD-DCHs-to-Modify  
id-DCH-InformationResponse  
id-DCH-Rate-InformationItem-RL-CongestInd  
id-DL-CCTrCH-InformationAddItem-RL-ReconfPrepTDD  
id-DL-CCTrCH-InformationListIE-RL-ReconfReadyTDD  
id-DL-CCTrCH-InformationDeleteItem-RL-ReconfRqstTDD  
id-DL-CCTrCH-InformationItem-RL-SetupRqstTDD  
id-DL-CCTrCH-InformationListIE-PhyChReconfRqstTDD  
id-DL-CCTrCH-InformationListIE-RL-AdditionRspTDD  
id-DL-CCTrCH-InformationListIE-RL-SetupRspTDD  
id-DL-CCTrCH-InformationAddList-RL-ReconfPrepTDD  
id-DL-CCTrCH-InformationDeleteList-RL-ReconfRqstTDD  
id-DL-CCTrCH-InformationList-RL-SetupRqstTDD  
id-FDD-DL-CodeInformation  
id-DL-DPCH-Information-RL-ReconfPrepFDD  
id-DL-DPCH-Information-RL-SetupRqstFDD  
id-DL-DPCH-Information-RL-ReconfRqstFDD  
id-DL-DPCH-InformationItem-PhyChReconfRqstTDD  
id-DL-DPCH-InformationItem-RL-AdditionRspTDD  
id-DL-DPCH-InformationItem-RL-SetupRspTDD  
id-DL-DPCH-TimingAdjustment  
id-DLReferencePower  
id-DLReferencePowerList-DL-PC-Rqst  
id-DL-ReferencePowerInformation-DL-PC-Rqst  
id-DPC-Mode  
id-DRXCycleLengthCoefficient  
id-DedicatedMeasurementObjectType-DM-Fail-Ind  
id-DedicatedMeasurementObjectType-DM-Fail  
id-DedicatedMeasurementObjectType-DM-Rprt  
id-DedicatedMeasurementObjectType-DM-Rqst  
id-DedicatedMeasurementObjectType-DM-Rsp  
id-DedicatedMeasurementType  
id-FACH-InfoForUESelectedS-CCPCH-CTCH-ResourceRspFDD  
id-FACH-InfoForUESelectedS-CCPCH-CTCH-ResourceRspTDD

**3GPP TS 25.423 V5.0.0(2002-03)**

ProtocolIE-ID ::= 9  
ProtocolIE-ID ::= 10  
ProtocolIE-ID ::= 11  
ProtocolIE-ID ::= 310  
ProtocolIE-ID ::= 20  
ProtocolIE-ID ::= 211  
ProtocolIE-ID ::= 21  
ProtocolIE-ID ::= 22  
ProtocolIE-ID ::= 26  
ProtocolIE-ID ::= 27  
ProtocolIE-ID ::= 30  
ProtocolIE-ID ::= 31  
ProtocolIE-ID ::= 32  
ProtocolIE-ID ::= 33  
ProtocolIE-ID ::= 34  
ProtocolIE-ID ::= 35  
ProtocolIE-ID ::= 39  
ProtocolIE-ID ::= 40  
ProtocolIE-ID ::= 43  
ProtocolIE-ID ::= 38  
ProtocolIE-ID ::= 44  
ProtocolIE-ID ::= 45  
ProtocolIE-ID ::= 46  
ProtocolIE-ID ::= 47  
ProtocolIE-ID ::= 48  
ProtocolIE-ID ::= 49  
ProtocolIE-ID ::= 50  
ProtocolIE-ID ::= 51  
ProtocolIE-ID ::= 52  
ProtocolIE-ID ::= 53  
ProtocolIE-ID ::= 54  
ProtocolIE-ID ::= 59  
ProtocolIE-ID ::= 60  
ProtocolIE-ID ::= 61  
ProtocolIE-ID ::= 62  
ProtocolIE-ID ::= 63  
ProtocolIE-ID ::= 64  
ProtocolIE-ID ::= 278  
ProtocolIE-ID ::= 67  
ProtocolIE-ID ::= 68  
ProtocolIE-ID ::= 69  
ProtocolIE-ID ::= 12  
ProtocolIE-ID ::= 70  
ProtocolIE-ID ::= 470  
ProtocolIE-ID ::= 471  
ProtocolIE-ID ::= 71  
ProtocolIE-ID ::= 72  
ProtocolIE-ID ::= 73  
ProtocolIE-ID ::= 74  
ProtocolIE-ID ::= 82  
ProtocolIE-ID ::= 83

**Release 5**

id-Guaranteed-Rate-Information  
id-IMSI  
id-HCS-Prio  
id-L3-Information  
id-AdjustmentPeriod  
id-MaxAdjustmentStep  
id-MeasurementFilterCoefficient  
id-MessageStructure  
id-MeasurementID  
id-Neighbouring-GSM-CellInformation  
id-Neighbouring-UMTS-CellInformationItem  
id-NRT-Load-Information-Value  
id-NRT-Load-Information-Value-IncrDecrThres  
id-PagingArea-PagingRqst  
id-FACH-FlowControlInformation  
id-PartialReportingIndicator  
id-Permanent-NAS-UE-Identity  
id-PowerAdjustmentType  
id-RANAP-RelocationInformation  
id-RL-Information-PhyChReconfRqstFDD  
id-RL-Information-PhyChReconfRqstTDD  
id-RL-Information-RL-AdditionRqstFDD  
id-RL-Information-RL-AdditionRqstTDD  
id-RL-Information-RL-DeletionRqst  
id-RL-Information-RL-FailureInd  
id-RL-Information-RL-ReconfPrepFDD  
id-RL-Information-RL-RestoreInd  
id-RL-Information-RL-SetupRqstFDD  
id-RL-Information-RL-SetupRqstTDD  
id-RL-InformationItem-RL-CongestInd  
id-RL-InformationItem-DM-Rprt  
id-RL-InformationItem-DM-Rqst  
id-RL-InformationItem-DM-Rsp  
id-RL-InformationItem-RL-PreemptRequiredInd  
id-RL-InformationItem-RL-SetupRqstFDD  
id-RL-InformationList-RL-CongestInd  
id-RL-InformationList-RL-AdditionRqstFDD  
id-RL-InformationList-RL-DeletionRqst  
id-RL-InformationList-RL-PreemptRequiredInd  
id-RL-InformationList-RL-ReconfPrepFDD  
id-RL-InformationResponse-RL-AdditionRspTDD  
id-RL-InformationResponse-RL-ReconfReadyTDD  
id-RL-InformationResponse-RL-SetupRspTDD  
id-RL-InformationResponseItem-RL-AdditionRspFDD  
id-RL-InformationResponseItem-RL-ReconfReadyFDD  
id-RL-InformationResponseItem-RL-ReconfRspFDD  
id-RL-InformationResponseList-RL-AdditionRspFDD  
id-RL-InformationResponseList-RL-ReconfReadyFDD  
id-RL-InformationResponseList-RL-ReconfRspFDD  
id-RL-InformationResponse-RL-ReconfRspTDD

**3GPP TS 25.423 V5.0.0(2002-03)**

ProtocolIE-ID ::= 41  
ProtocolIE-ID ::= 84  
ProtocolIE-ID ::= 311  
ProtocolIE-ID ::= 85  
ProtocolIE-ID ::= 90  
ProtocolIE-ID ::= 91  
ProtocolIE-ID ::= 92  
ProtocolIE-ID ::= 57  
ProtocolIE-ID ::= 93  
ProtocolIE-ID ::= 13  
ProtocolIE-ID ::= 95  
ProtocolIE-ID ::= 305  
ProtocolIE-ID ::= 306  
ProtocolIE-ID ::= 102  
ProtocolIE-ID ::= 103  
ProtocolIE-ID ::= 472  
ProtocolIE-ID ::= 17  
ProtocolIE-ID ::= 107  
ProtocolIE-ID ::= 109  
ProtocolIE-ID ::= 110  
ProtocolIE-ID ::= 111  
ProtocolIE-ID ::= 112  
ProtocolIE-ID ::= 113  
ProtocolIE-ID ::= 114  
ProtocolIE-ID ::= 115  
ProtocolIE-ID ::= 116  
ProtocolIE-ID ::= 117  
ProtocolIE-ID ::= 118  
ProtocolIE-ID ::= 119  
ProtocolIE-ID ::= 55  
ProtocolIE-ID ::= 120  
ProtocolIE-ID ::= 121  
ProtocolIE-ID ::= 122  
ProtocolIE-ID ::= 2  
ProtocolIE-ID ::= 123  
ProtocolIE-ID ::= 56  
ProtocolIE-ID ::= 124  
ProtocolIE-ID ::= 125  
ProtocolIE-ID ::= 1  
ProtocolIE-ID ::= 126  
ProtocolIE-ID ::= 127  
ProtocolIE-ID ::= 128  
ProtocolIE-ID ::= 129  
ProtocolIE-ID ::= 130  
ProtocolIE-ID ::= 131  
ProtocolIE-ID ::= 132  
ProtocolIE-ID ::= 133  
ProtocolIE-ID ::= 134  
ProtocolIE-ID ::= 135  
ProtocolIE-ID ::= 136  
ProtocolIE-ID ::= 28

## Release 5

id-RL-InformationResponseList-RL-SetupRspFDD  
id-RL-ReconfigurationFailure-RL-ReconfFail  
id-RL-Set-InformationItem-DM-Rprt  
id-RL-Set-InformationItem-DM-Rqst  
id-RL-Set-InformationItem-DM-Rsp  
id-RL-Set-Information-RL-FailureInd  
id-RL-Set-Information-RL-RestoreInd  
id-RL-Set-Successful-InformationItem-DM-Fail  
id-RL-Set-Unsuccessful-InformationItem-DM-Fail  
id-RL-Set-Unsuccessful-InformationItem-DM-Fail-Ind  
id-RL-Successful-InformationItem-DM-Fail  
id-RL-Unsuccessful-InformationItem-DM-Fail  
id-RL-Unsuccessful-InformationItem-DM-Fail-Ind  
id-ReportCharacteristics  
id-Reporting-Object-RL-FailureInd  
id-Reporting-Object-RL-RestoreInd  
id-RT-Load-Value  
id-RT-Load-Value-IncrDecrThres  
id-S-RNTI  
id-ResetIndicator  
id-RNC-ID  
id-SAI  
id-SRNC-ID  
id-SuccessfulRL-InformationResponse-RL-AdditionFailureFDD  
id-SuccessfulRL-InformationResponse-RL-SetupFailureFDD  
id-TransportBearerID  
id-TransportBearerRequestIndicator  
id-TransportLayerAddress  
id-TypeOfError  
id-UC-ID  
id-UL-CCTrCH-AddInformation-RL-ReconfPrepTDD  
id-UL-CCTrCH-InformationAddList-RL-ReconfPrepTDD  
id-UL-CCTrCH-InformationItem-RL-SetupRqstTDD  
id-UL-CCTrCH-InformationList-RL-SetupRqstTDD  
id-UL-CCTrCH-InformationListIE-PhyChReconfRqstTDD  
id-UL-CCTrCH-InformationListIE-RL-AdditionRspTDD  
id-UL-CCTrCH-InformationListIE-RL-ReconfReadyTDD  
id-UL-CCTrCH-InformationListIE-RL-SetupRspTDD  
id-UL-DPCH-Information-RL-ReconfPrepFDD  
id-UL-DPCH-Information-RL-ReconfRqstFDD  
id-UL-DPCH-Information-RL-SetupRqstFDD  
id-UL-DPCH-InformationItem-PhyChReconfRqstTDD  
id-UL-DPCH-InformationItem-RL-AdditionRspTDD  
id-UL-DPCH-InformationItem-RL-SetupRspTDD  
id-UL-DPCH-InformationAddListIE-RL-ReconfReadyTDD  
id-UL-SIRTarget  
id-URA-Information  
id-UnsuccessfulRL-InformationResponse-RL-AdditionFailureFDD  
id-UnsuccessfulRL-InformationResponse-RL-SetupFailureFDD  
id-UnsuccessfulRL-InformationResponse-RL-SetupFailureTDD  
id-Active-Pattern-Sequence-Information

## 3GPP TS 25.423 V5.0.0(2002-03)

ProtocolIE-ID ::= 137  
ProtocolIE-ID ::= 141  
ProtocolIE-ID ::= 143  
ProtocolIE-ID ::= 144  
ProtocolIE-ID ::= 145  
ProtocolIE-ID ::= 146  
ProtocolIE-ID ::= 147  
ProtocolIE-ID ::= 473  
ProtocolIE-ID ::= 474  
ProtocolIE-ID ::= 475  
ProtocolIE-ID ::= 476  
ProtocolIE-ID ::= 477  
ProtocolIE-ID ::= 478  
ProtocolIE-ID ::= 152  
ProtocolIE-ID ::= 153  
ProtocolIE-ID ::= 154  
ProtocolIE-ID ::= 307  
ProtocolIE-ID ::= 308  
ProtocolIE-ID ::= 155  
ProtocolIE-ID ::= 244  
ProtocolIE-ID ::= 245  
ProtocolIE-ID ::= 156  
ProtocolIE-ID ::= 157  
ProtocolIE-ID ::= 159  
ProtocolIE-ID ::= 160  
ProtocolIE-ID ::= 163  
ProtocolIE-ID ::= 164  
ProtocolIE-ID ::= 165  
ProtocolIE-ID ::= 140  
ProtocolIE-ID ::= 166  
ProtocolIE-ID ::= 167  
ProtocolIE-ID ::= 169  
ProtocolIE-ID ::= 171  
ProtocolIE-ID ::= 172  
ProtocolIE-ID ::= 173  
ProtocolIE-ID ::= 174  
ProtocolIE-ID ::= 175  
ProtocolIE-ID ::= 176  
ProtocolIE-ID ::= 177  
ProtocolIE-ID ::= 178  
ProtocolIE-ID ::= 179  
ProtocolIE-ID ::= 180  
ProtocolIE-ID ::= 181  
ProtocolIE-ID ::= 182  
ProtocolIE-ID ::= 183  
ProtocolIE-ID ::= 184  
ProtocolIE-ID ::= 185  
ProtocolIE-ID ::= 188  
ProtocolIE-ID ::= 189  
ProtocolIE-ID ::= 190  
ProtocolIE-ID ::= 193

**Release 5**

id-AdjustmentRatio  
id-CauseLevel-RL-AdditionFailureFDD  
id-CauseLevel-RL-AdditionFailureTDD  
id-CauseLevel-RL-ReconfFailure  
id-CauseLevel-RL-SetupFailureFDD  
id-CauseLevel-RL-SetupFailureTDD  
id-DL-CCTrCH-InformationDeleteItem-RL-ReconfPrepTDD  
id-DL-CCTrCH-InformationModifyItem-RL-ReconfPrepTDD  
id-DL-CCTrCH-InformationModifyItem-RL-ReconfRqstTDD  
id-DL-CCTrCH-InformationDeleteList-RL-ReconfPrepTDD  
id-DL-CCTrCH-InformationModifyList-RL-ReconfPrepTDD  
id-DL-CCTrCH-InformationModifyList-RL-ReconfRqstTDD  
id-DL-DPCH-InformationAddListIE-RL-ReconfReadyTDD  
id-DL-DPCH-InformationDeleteListIE-RL-ReconfReadyTDD  
id-DL-DPCH-InformationModifyListIE-RL-ReconfReadyTDD  
id-DSCHs-to-Add-TDD  
id-DSCHs-to-Add-FDD  
id-DSCH-DeleteList-RL-ReconfPrepTDD  
id-DSCH-Delete-RL-ReconfPrepFDD  
id-DSCH-FDD-Information  
id-DSCH-InformationListIE-RL-AdditionRspTDD  
id-DSCH-InformationListIES-RL-SetupRspTDD  
id-DSCH-TDD-Information  
id-DSCH-FDD-InformationResponse  
id-DSCH-Information-RL-SetupRqstFDD  
id-DSCH-ModifyList-RL-ReconfPrepTDD  
id-DSCH-Modify-RL-ReconfPrepFDD  
id-DSCH-Specific-FDD-Additional-List  
id-DSCHsToBeAddedOrModified-FDD  
id-DSCHToBeAddedOrModifiedList-RL-ReconfReadyTDD  
id-EnhancedDSCHPC  
id-EnhancedDSCHPCIndicator  
id-GA-Cell  
id-GA-CellAdditionalShapes  
id-SSDT-CellIDforEDSCHPC  
id-Transmission-Gap-Pattern-Sequence-Information  
id-UL-CCTrCH-DeleteInformation-RL-ReconfPrepTDD  
id-UL-CCTrCH-ModifyInformation-RL-ReconfPrepTDD  
id-UL-CCTrCH-InformationModifyItem-RL-ReconfRqstTDD  
id-UL-CCTrCH-InformationDeleteList-RL-ReconfPrepTDD  
id-UL-CCTrCH-InformationModifyList-RL-ReconfPrepTDD  
id-UL-CCTrCH-InformationModifyList-RL-ReconfRqstTDD  
id-UL-CCTrCH-InformationDeleteItem-RL-ReconfRqstTDD  
id-UL-CCTrCH-InformationDeleteList-RL-ReconfRqstTDD  
id-UL-DPCH-InformationDeleteListIE-RL-ReconfReadyTDD  
id-UL-DPCH-InformationModifyListIE-RL-ReconfReadyTDD  
id-UnsuccessfulRL-InformationResponse-RL-AdditionFailureTDD  
id-USCHs-to-Add  
id-USCH-DeleteList-RL-ReconfPrepTDD  
id-USCH-InformationListIE-RL-AdditionRspTDD  
id-USCH-InformationListIES-RL-SetupRspTDD

**3GPP TS 25.423 V5.0.0(2002-03)**

ProtocolIE-ID ::= 194  
ProtocolIE-ID ::= 197  
ProtocolIE-ID ::= 198  
ProtocolIE-ID ::= 199  
ProtocolIE-ID ::= 200  
ProtocolIE-ID ::= 201  
ProtocolIE-ID ::= 205  
ProtocolIE-ID ::= 206  
ProtocolIE-ID ::= 207  
ProtocolIE-ID ::= 208  
ProtocolIE-ID ::= 209  
ProtocolIE-ID ::= 210  
ProtocolIE-ID ::= 212  
ProtocolIE-ID ::= 213  
ProtocolIE-ID ::= 214  
ProtocolIE-ID ::= 215  
ProtocolIE-ID ::= 216  
ProtocolIE-ID ::= 217  
ProtocolIE-ID ::= 218  
ProtocolIE-ID ::= 219  
ProtocolIE-ID ::= 220  
ProtocolIE-ID ::= 221  
ProtocolIE-ID ::= 222  
ProtocolIE-ID ::= 223  
ProtocolIE-ID ::= 226  
ProtocolIE-ID ::= 227  
ProtocolIE-ID ::= 228  
ProtocolIE-ID ::= 324  
ProtocolIE-ID ::= 229  
ProtocolIE-ID ::= 230  
ProtocolIE-ID ::= 29  
ProtocolIE-ID ::= 225  
ProtocolIE-ID ::= 232  
ProtocolIE-ID ::= 3  
ProtocolIE-ID ::= 246  
ProtocolIE-ID ::= 255  
ProtocolIE-ID ::= 256  
ProtocolIE-ID ::= 257  
ProtocolIE-ID ::= 258  
ProtocolIE-ID ::= 259  
ProtocolIE-ID ::= 260  
ProtocolIE-ID ::= 261  
ProtocolIE-ID ::= 262  
ProtocolIE-ID ::= 263  
ProtocolIE-ID ::= 264  
ProtocolIE-ID ::= 265  
ProtocolIE-ID ::= 266  
ProtocolIE-ID ::= 267  
ProtocolIE-ID ::= 268  
ProtocolIE-ID ::= 269  
ProtocolIE-ID ::= 270

**Release 5**

id-USCH-Information  
id-USCH-ModifyList-RL-ReconfPrepTDD  
id-USCHToBeAddedOrModifiedList-RL-ReconfReadyTDD  
id-DL-Physical-Channel-Information-RL-SetupRqstTDD  
id-UL-Physical-Channel-Information-RL-SetupRqstTDD  
id-ClosedLoopMode1-SupportIndicator  
id-ClosedLoopMode2-SupportIndicator  
id-STTD-SupportIndicator  
id-CFNReportingIndicator  
id-CNoriginatedPage-PagingRqst  
id-InnerLoopDLPCTStatus  
id-PropagationDelay  
id-RxTimingDeviationForTA  
id-timeSlot-ISCP  
id-CCTrCH-InformationItem-RL-FailureInd  
id-CCTrCH-InformationItem-RL-RestoreInd  
id-CommonMeasurementAccuracy  
id-CommonMeasurementObjectType-CM-Rprt  
id-CommonMeasurementObjectType-CM-Rqst  
id-CommonMeasurementObjectType-CM-Rsp  
id-CommonMeasurementType  
id-CongestionCause  
id-SFN  
id-SFNReportingIndicator  
id-InformationExchangeID  
id-InformationExchangeObjectType-InfEx-Rprt  
id-InformationExchangeObjectType-InfEx-Rqst  
id-InformationExchangeObjectType-InfEx-Rsp  
id-InformationReportCharacteristics  
id-InformationType  
id-neighbouring-LCR-TDD-CellInformation  
id-DL-Timeslot-ISCP-LCR-Information-RL-SetupRqstTDD  
id-RL-LCR-InformationResponse-RL-SetupRspTDD  
id-UL-CCTrCH-LCR-InformationListIE-RL-SetupRspTDD  
id-UL-DPCH-LCR-InformationItem-RL-SetupRspTDD  
id-DL-CCTrCH-LCR-InformationListIE-RL-SetupRspTDD  
id-DL-DPCH-LCR-InformationItem-RL-SetupRspTDD  
id-DSCH-LCR-InformationListIES-RL-SetupRspTDD  
id-USCH-LCR-InformationListIES-RL-SetupRspTDD  
id-DL-Timeslot-ISCP-LCR-Information-RL-AdditionRqstTDD  
id-RL-LCR-InformationResponse-RL-AdditionRspTDD  
id-UL-CCTrCH-LCR-InformationListIE-RL-AdditionRspTDD  
id-UL-DPCH-LCR-InformationItem-RL-AdditionRspTDD  
id-DL-CCTrCH-LCR-InformationListIE-RL-AdditionRspTDD  
id-DL-DPCH-LCR-InformationItem-RL-AdditionRspTDD  
id-DSCH-LCR-InformationListIES-RL-AdditionRspTDD  
id-USCH-LCR-InformationListIES-RL-AdditionRspTDD  
id-UL-DPCH-LCR-InformationAddListIE-RL-ReconfReadyTDD  
id-UL-Timeslot-LCR-InformationModifyList-RL-ReconfReadyTDD  
id-DL-DPCH-LCR-InformationAddListIE-RL-ReconfReadyTDD  
id-DL-Timeslot-LCR-InformationModifyList-RL-ReconfReadyTDD

**3GPP TS 25.423 V5.0.0(2002-03)**

ProtocolIE-ID ::= 271  
ProtocolIE-ID ::= 272  
ProtocolIE-ID ::= 273  
ProtocolIE-ID ::= 274  
ProtocolIE-ID ::= 275  
ProtocolIE-ID ::= 276  
ProtocolIE-ID ::= 277  
ProtocolIE-ID ::= 279  
ProtocolIE-ID ::= 14  
ProtocolIE-ID ::= 23  
ProtocolIE-ID ::= 24  
ProtocolIE-ID ::= 25  
ProtocolIE-ID ::= 36  
ProtocolIE-ID ::= 37  
ProtocolIE-ID ::= 15  
ProtocolIE-ID ::= 16  
ProtocolIE-ID ::= 280  
ProtocolIE-ID ::= 281  
ProtocolIE-ID ::= 282  
ProtocolIE-ID ::= 283  
ProtocolIE-ID ::= 284  
ProtocolIE-ID ::= 18  
ProtocolIE-ID ::= 285  
ProtocolIE-ID ::= 286  
ProtocolIE-ID ::= 287  
ProtocolIE-ID ::= 288  
ProtocolIE-ID ::= 289  
ProtocolIE-ID ::= 290  
ProtocolIE-ID ::= 291  
ProtocolIE-ID ::= 292  
ProtocolIE-ID ::= 58  
ProtocolIE-ID ::= 65  
ProtocolIE-ID ::= 66  
ProtocolIE-ID ::= 75  
ProtocolIE-ID ::= 76  
ProtocolIE-ID ::= 77  
ProtocolIE-ID ::= 78  
ProtocolIE-ID ::= 79  
ProtocolIE-ID ::= 80  
ProtocolIE-ID ::= 81  
ProtocolIE-ID ::= 86  
ProtocolIE-ID ::= 87  
ProtocolIE-ID ::= 88  
ProtocolIE-ID ::= 89  
ProtocolIE-ID ::= 94  
ProtocolIE-ID ::= 96  
ProtocolIE-ID ::= 97  
ProtocolIE-ID ::= 98  
ProtocolIE-ID ::= 100  
ProtocolIE-ID ::= 101  
ProtocolIE-ID ::= 104

**Release 5**

id-UL-Timeslot-LCR-InformationList-PhyChReconfRqstTDD  
id-DL-Timeslot-LCR-InformationList-PhyChReconfRqstTDD  
id-timeSlot-ISCP-LCR-List-DL-PC-Rqst-TDD  
id-TSTD-Support-Indicator-RL-SetupRqstTDD  
id-RestrictionStateIndicator  
id-Load-Value  
id-Load-Value-IncrDecrThres  
id-OnModification  
id-Received-Total-Wideband-Power-Value  
id-Received-Total-Wideband-Power-Value-IncrDecrThres  
id-SFNSFNMeasurementThresholdInformation  
id-Transmitted-Carrier-Power-Value  
id-Transmitted-Carrier-Power-Value-IncrDecrThres  
id-TUTRANGPSMeasurementThresholdInformation  
id-UL-Timeslot-ISCP-Value-IncrDecrThres  
id-UL-Timeslot-ISCP-Value-IncrDecrThres  
id-Rx-Timing-Deviation-Value-LCR  
id-DPC-Mode-Change-SupportIndicator  
id-SplitType  
id-LengthOfTFCI2  
id-PrimaryCCPCH-RSCP-RL-ReconfPrepTDD  
id-DL-TimeSlot-ISCP-Info-RL-ReconfPrepTDD  
id-DL-Timeslot-ISCP-LCR-Information-RL-ReconfPrepTDD  
id-DSCH-RNTI  
id-DL-PowerBalancing-Information  
id-DL-PowerBalancing-ActivationIndicator  
id-DL-PowerBalancing-UpdatedIndicator  
id-DL-ReferencePowerInformation  
id-Enhanced-PrimaryCPICH-EcNo  
id-IPDL-TDD-ParametersLCR  
id-CellCapabilityContainer-FDD  
id-CellCapabilityContainer-TDD  
id-CellCapabilityContainer-TDD-LCR  
id-RL-Specific-DCH-Info  
id-RL-ReconfigurationRequestFDD-RL-InformationList  
id-RL-ReconfigurationRequestFDD-RL-Information-IEs  
id-RL-ReconfigurationReadyTDD-RL-Information  
id-RL-ReconfigurationRequestTDD-RL-Information  
id-CommonTransportChannelResourcesInitialisationNotRequired  
id-DelayedActivation  
id-DelayedActivationList-RL-ActivationCmdFDD  
id-DelayedActivationInformation-RL-ActivationCmdFDD  
id-DelayedActivationList-RL-ActivationCmdTDD  
id-DelayedActivationInformation-RL-ActivationCmdTDD  
id-neighbouringTDDCellMeasurementInformationLCR  
id-UL-SIR-Target-CCTrCH-InformationItem-RL-SetupRspTDD  
id-UL-SIR-Target-CCTrCH-LCR-InformationItem-RL-SetupRspTDD  
id-PrimCCPCH-RSCP-DL-PC-RqstTDD  
id-HSDSCH-FDD-Information  
id-HSDSCH-FDD-Information-Response  
id-HSDSCH-FDD-Information-to-Add

**3GPP TS 25.423 V5.0.0(2002-03)**

ProtocolIE-ID ::= 105  
ProtocolIE-ID ::= 106  
ProtocolIE-ID ::= 138  
ProtocolIE-ID ::= 139  
ProtocolIE-ID ::= 142  
ProtocolIE-ID ::= 233  
ProtocolIE-ID ::= 234  
ProtocolIE-ID ::= 235  
ProtocolIE-ID ::= 236  
ProtocolIE-ID ::= 237  
ProtocolIE-ID ::= 238  
ProtocolIE-ID ::= 239  
ProtocolIE-ID ::= 240  
ProtocolIE-ID ::= 241  
ProtocolIE-ID ::= 242  
ProtocolIE-ID ::= 243  
ProtocolIE-ID ::= 293  
ProtocolIE-ID ::= 19  
ProtocolIE-ID ::= 247  
ProtocolIE-ID ::= 295  
ProtocolIE-ID ::= 202  
ProtocolIE-ID ::= 203  
ProtocolIE-ID ::= 204  
ProtocolIE-ID ::= 249  
ProtocolIE-ID ::= 296  
ProtocolIE-ID ::= 297  
ProtocolIE-ID ::= 298  
ProtocolIE-ID ::= 299  
ProtocolIE-ID ::= 224  
ProtocolIE-ID ::= 252  
ProtocolIE-ID ::= 300  
ProtocolIE-ID ::= 301  
ProtocolIE-ID ::= 302  
ProtocolIE-ID ::= 317  
ProtocolIE-ID ::= 318  
ProtocolIE-ID ::= 319  
ProtocolIE-ID ::= 320  
ProtocolIE-ID ::= 321  
ProtocolIE-ID ::= 250  
ProtocolIE-ID ::= 312  
ProtocolIE-ID ::= 313  
ProtocolIE-ID ::= 314  
ProtocolIE-ID ::= 315  
ProtocolIE-ID ::= 316  
ProtocolIE-ID ::= 251  
ProtocolIE-ID ::= 150  
ProtocolIE-ID ::= 151  
ProtocolIE-ID ::= 451  
ProtocolIE-ID ::= 452  
ProtocolIE-ID ::= 453  
ProtocolIE-ID ::= 454

**Release 5**

id-HSDSCH-FDD-Information-to-Delete  
id-HSDSCH-FDD-Update-Information  
id-HSDSCH-Information-to-Modify  
id-HSDSCH-RNTI  
id-HSDSCH-TDD-Information  
id-HSDSCH-TDD-Information-Response  
id-HSDSCH-TDD-Information-Response-LCR  
id-HSDSCH-TDD-Information-to-Add  
id-HSDSCH-TDD-Information-to-Delete  
id-HSDSCH-TDD-Update-Information  
id-HSPDSCH-RL-ID  
id-Angle-Of-Arrival-Value-LCR  
id-TrafficClass  
id-TFCI-PC-SupportIndicator  
id-Qth-Parameter  
id-PDSCH-RL-ID  
id-TimeSlot-RL-SetupRspTDD  
id-GERAN-Cell-Capability  
id-GERAN-Classmark  
id-DSCH-InitialWindowSize  
id-UL-Synchronisation-Parameters-LCR  
id-SNA-Information  
id-MACHs-ResetIndicator  
id-TDD-DL-DPCH-TimeSlotFormatModifyItem-LCR-RL-ReconfReadyTDD  
id-TDD-UL-DPCH-TimeSlotFormatModifyItem-LCR-RL-ReconfReadyTDD  
id-TDD-TPC-UplinkStepSize-LCR-RL-SetupRqstTDD  
id-UL-CCTrCH-InformationList-RL-AdditionRqstTDD  
id-UL-CCTrCH-InformationItem-RL-AdditionRqstTDD  
id-DL-CCTrCH-InformationList-RL-AdditionRqstTDD  
id-DL-CCTrCH-InformationItem-RL-AdditionRqstTDD  
id-TDD-TPC-UplinkStepSize-InformationAdd-LCR-RL-ReconfPrepTDD  
id-TDD-TPC-UplinkStepSize-InformationModify-LCR-RL-ReconfPrepTDD  
id-TDD-TPC-DownlinkStepSize-InformationAdd-RL-ReconfPrepTDD  
id-TDD-TPC-DownlinkStepSize-InformationModify-RL-ReconfPrepTDD  
id-UL-TimingAdvanceCtrl-LCR  
id-HSPDSCH-Timeslot-InformationList-PhyChReconfRqstTDD  
id-HSPDSCH-Timeslot-InformationListLCR-PhyChReconfRqstTDD  
id-HS-SICH-Reception-Quality  
id-HS-SICH-Reception-Quality-Measurement-Value  
id-HSSICH-Info-DM-Rprt  
id-HSSICH-Info-DM-Rqst  
id-HSSICH-Info-DM-Rsp  
id-CCTrCH-Maximum-DL-Power-RL-SetupRspTDD  
id-CCTrCH-Minimum-DL-Power-RL-SetupRspTDD  
id-CCTrCH-Maximum-DL-Power-RL-AdditionRspTDD  
id-CCTrCH-Minimum-DL-Power-RL-AdditionRspTDD  
id-CCTrCH-Maximum-DL-Power-RL-ReconfReadyTDD  
id-CCTrCH-Minimum-DL-Power-RL-ReconfReadyTDD  
id-Maximum-DL-Power-TimeslotLCR-InformationModifyItem-RL-ReconfReadyTDD  
id-Minimum-DL-Power-TimeslotLCR-InformationModifyItem-RL-ReconfReadyTDD  
id-DL-CCTrCH-InformationList-RL-ReconfRspTDD

**3GPP TS 25.423 V5.0.0(2002-03)**

ProtocolIE-ID ::= 455  
ProtocolIE-ID ::= 466  
ProtocolIE-ID ::= 456  
ProtocolIE-ID ::= 457  
ProtocolIE-ID ::= 458  
ProtocolIE-ID ::= 459  
ProtocolIE-ID ::= 460  
ProtocolIE-ID ::= 461  
ProtocolIE-ID ::= 462  
ProtocolIE-ID ::= 467  
ProtocolIE-ID ::= 463  
ProtocolIE-ID ::= 148  
ProtocolIE-ID ::= 158  
ProtocolIE-ID ::= 248  
ProtocolIE-ID ::= 253  
ProtocolIE-ID ::= 323  
ProtocolIE-ID ::= 325  
ProtocolIE-ID ::= 468  
ProtocolIE-ID ::= 469  
ProtocolIE-ID ::= 480  
ProtocolIE-ID ::= 464  
ProtocolIE-ID ::= 479  
ProtocolIE-ID ::= 465  
ProtocolIE-ID ::= 481  
ProtocolIE-ID ::= 482  
ProtocolIE-ID ::= 483  
ProtocolIE-ID ::= 484  
ProtocolIE-ID ::= 485  
ProtocolIE-ID ::= 486  
ProtocolIE-ID ::= 487  
ProtocolIE-ID ::= 488  
ProtocolIE-ID ::= 489  
ProtocolIE-ID ::= 490  
ProtocolIE-ID ::= 491  
ProtocolIE-ID ::= 492  
ProtocolIE-ID ::= 493  
ProtocolIE-ID ::= 494  
ProtocolIE-ID ::= 495  
ProtocolIE-ID ::= 496  
ProtocolIE-ID ::= 497  
ProtocolIE-ID ::= 498  
ProtocolIE-ID ::= 499  
ProtocolIE-ID ::= 500  
ProtocolIE-ID ::= 501  
ProtocolIE-ID ::= 502  
ProtocolIE-ID ::= 503  
ProtocolIE-ID ::= 504  
ProtocolIE-ID ::= 505  
ProtocolIE-ID ::= 506  
ProtocolIE-ID ::= 507  
ProtocolIE-ID ::= 508

**Release 5**

id-DL-DPCH-InformationModifyItem-LCR-RL-ReconfRspTDD  
id-Maximum-DL-Power-TimeslotLCR-InformationItem  
id-Minimum-DL-Power-TimeslotLCR-InformationItem  
id-TDD-Support-8PSK  
id-TDD-maxNrDLPhysicalchannels  
id-ExtendedGSMCellIndividualOffset  
id-RL-ParameterUpdateIndicationFDD-RL-Information-Item  
id-RL-ParameterUpdateIndicationFDD-RL-InformationList  
id-Primary-CPICH-Usage-For-Channel-Estimation  
id-Secondary-CPICH-Information  
id-Secondary-CPICH-Information-Change  
id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation  
id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH

**3GPP TS 25.423 V5.0.0(2002-03)**

ProtocolIE-ID ::= 509  
ProtocolIE-ID ::= 510  
ProtocolIE-ID ::= 511  
ProtocolIE-ID ::= 512  
ProtocolIE-ID ::= 513  
ProtocolIE-ID ::= 514  
**ProtocolIE-ID ::= 524**  
**ProtocolIE-ID ::= 518**  
**ProtocolIE-ID ::= 519**  
**ProtocolIE-ID ::= 520**  
**ProtocolIE-ID ::= 521**  
**ProtocolIE-ID ::= 522**  
**ProtocolIE-ID ::= 523**

END

**3GPP TSG-RAN3 Meeting #36**  
**Paris, France, 19<sup>th</sup> – 23<sup>rd</sup>, May 2003**

**Tdoc #R3-030xxx**

CR-Form-v7

## CHANGE REQUEST

# **25.433 CR 836** #rev **2** # Current version: **5.4.0** #

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the # symbols.

**Proposed change affects:** UICC apps #  ME #  Radio Access Network  Core Network #

<b>Title:</b>	# Phase Reference Signalling Support	
<b>Source:</b>	# Nokia	
<b>Work item code:</b>	# TEIX	<b>Date:</b> # 19/05/2003
<b>Category:</b>	# <b>F</b> Use <u>one</u> of the following categories: <b>F</b> (correction) <b>A</b> (corresponds to a correction in an earlier release) <b>B</b> (addition of feature), <b>C</b> (functional modification of feature) <b>D</b> (editorial modification) Detailed explanations of the above categories can be found in 3GPP <a href="#">TR 21.900</a> .	<b>Release:</b> # Rel-X Use <u>one</u> of the following releases: 2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) Rel-4 (Release 4) Rel-5 (Release 5) Rel-6 (Release 6)

<b>Reason for change:</b>	# According to the current understanding in RAN1, the Node B is not provided with knowledge over the Iub of which phase reference a certain UE is using.  This problem can be avoided by introducing phase reference signalling over Iub and Iur. Note that the phase reference is one of <ul style="list-style-type: none"><li>▪ P-CPICH</li><li>▪ one of possibly several S-CPICHs</li><li>▪ dedicated pilot</li></ul> as specified in 25.211.  During RAN1 and RNA3 unofficial joint session, it turned out that without the measurement, in principle S-CPICH cannot be used. Thus the measurement enhancement(which has been studied under Rel-6 WI) is indeed a correction of incomplete feature. To completed Rel99 beamforming feature, Best Received Cell Portion measurement as well as other measurements for cell portion are included in this CR.
---------------------------	--

<b>Summary of change:</b>	# Rev.2 <ul style="list-style-type: none"><li>- Some clarification was added.</li><li>- IE name was changed.</li></ul>
---------------------------	--

	<p>Rev.1</p> <ul style="list-style-type: none"> <li>- UE capabilities to support dedicated pilot for phase reference or not is delivered to Node B.</li> <li>- Best Received Cell Proportion Measurement was included.</li> </ul> <hr/> <p>Phase reference signalling is added in RL setup request, RL addition request and RL reconfiguration prepare.</p>								
<b>Consequences if not approved:</b>	<p>⌘ RAN1 has identified the following problems if the Node B does not have knowledge of the phase reference used by a certain UE:</p> <ul style="list-style-type: none"> <li>▪ Node B beam-forming is impossible without knowledge of the phase reference used by each UE.</li> <li>▪ Proper operation of HSDPA in Rel-5 requires the suggested signalling.</li> </ul> <p><u>Impact Analysis:</u></p> <p>Impact assessment towards the previous version of the specification (same release):</p> <p>This CR has isolated impact with the previous version of the specification. The change is limited only to the phase reference functionality.</p> <p>Impact assessment towards the previous release of the specification:</p> <p>This CR has no impact on previous releases because the functionality is introduced in backward compatible way.</p>								
<b>Clauses affected:</b>	<p>⌘ 8.2.17.2, 8.3.2.2, 8.3.5.2, 8.3.8.4, 9.1.18, 9.1.36.1, 9.1.42.1, 9.1.47.1, 9.2.1.23, 9.2.1.24, new 9.2.2.xz, new 9.2.2.xx, new 9.2.2.x, new 9.2.2.xy, new 9.2.2.x5, new 9.2.2.x2, new 9.2.2.x3, new 9.2.2.x3, 9.3.3, 9.3.4, 9.3.6</p>								
<b>Other specs affected:</b>	<table border="1" style="margin-bottom: 10px;"> <tr> <td style="text-align: center;">Y</td><td style="text-align: center;">N</td></tr> <tr> <td style="text-align: center;">X</td><td></td></tr> <tr> <td></td><td></td></tr> <tr> <td></td><td></td></tr> </table> <p>Other core specifications      ⌘ CR817 TS 25.423 v5.5.0 Test specifications              CR138 TS 25.215 v5.3.0 O&amp;M Specifications</p>	Y	N	X					
Y	N								
X									
<b>Other comments:</b>	⌘								

### How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

## 8.2.17 Radio Link Setup

### 8.2.17.2 Successful Operation

*/\* partly omitted \*/*

#### Physical Channels Handling:

##### [FDD - Compressed Mode]:

[FDD - If the RADIO LINK SETUP REQUEST message includes the *Transmission Gap Pattern Sequence Information* IE, the Node B shall store the information about the Transmission Gap Pattern Sequences to be used in the Compressed Mode Configuration. This Compressed Mode Configuration shall be valid in the Node B until the next Compressed Mode Configuration is configured in the Node B or the Node B Communication Context is deleted.]

[FDD - If the *Downlink compressed mode method* IE in one or more Transmission Gap Pattern Sequence is set to "SF/2" in the RADIO LINK SETUP REQUEST message, the Node B shall use or not the alternate scrambling code as indicated for each DL Channelisation Code in the *Transmission Gap Pattern Sequence Code Information* IE.]

[FDD - If the RADIO LINK SETUP REQUEST message includes the *Transmission Gap Pattern Sequence Information* IE and the *Active Pattern Sequence Information* IE, the Node B shall use the information to activate the indicated Transmission Gap Pattern Sequence(s) in the new RL. The received *CM Configuration Change CFN* refers to the latest passed CFN with that value. The Node B shall treat the received *TGCFN* IEs as follows:]

- [FDD - If any received *TGCFN* IE has the same value as the received *CM Configuration Change CFN* IE, the Node B shall consider the concerned Transmission Gap Pattern Sequence as activated at that CFN.]
- [FDD - If any received *TGCFN* IE does not have the same value as the received *CM Configuration Change CFN* IE but the first CFN after the CM Configuration Change CFN with a value equal to the *TGCFN* IE has already passed, the Node B shall consider the concerned Transmission Gap Pattern Sequence as activated at that CFN.]
- [FDD - For all other Transmission Gap Pattern Sequences included in the *Active Pattern Sequence Information* IE, the Node B shall activate each Transmission Gap Pattern Sequence at the first CFN after the CM Configuration Change CFN with a value equal to the *TGCFN* IE for the Transmission Gap Pattern Sequence.]

##### [FDD - DL Code Information]:

[FDD - When more than one DL DPDCH is assigned per RL, the segmented physical channel shall be mapped on to DL DPDCHs according to [8]. When  $p$  number of DL DPDCHs are assigned to each RL, the first pair of DL Scrambling Code and FDD DL Channelisation Code Number corresponds to "*PhCH number 1*", the second to "*PhCH number 2*", and so on until the  $p$ th to "*PhCH number  $p$* ".]

##### [TDD - PDSCH RL ID]:

[TDD - If the *PDSCH RL ID* IE is included in RADIO LINK SETUP REQUEST message, the Node B shall use the PDSCH RL ID as an identifier for the PDSCH and/or PUSCH in this radio link.]

##### [FDD – Phase Reference Handling]:

[FDD – If the RADIO LINK SETUP REQUEST message includes the *UE Support Of Dedicated Pilots For Channel Estimation* IE the Node B shall assume that dedicated pilots may be used for channel estimation with DCH or DSCH.]

[FDD – If the RADIO LINK SETUP REQUEST message includes the *UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH* IE the Node B shall assume that dedicated pilots may be used for channel estimation with HS-DSCH.]

[FDD – The Node B shall, when Cell Portions are defined in the Cell, use the *Primary CPICH Usage for Channel Estimation* IE if it is included in the RADIO LINK SETUP REQUEST message.]

[FDD – If the RADIO LINK SETUP REQUEST message includes the *Secondary CPICH Information IE*, the Node B shall assume that the Secondary CPICH indicated by the *Common Physical Channel ID IE* may be used for channel estimation.]

### **General:**

[FDD - If the *Propagation Delay IE* is included, the Node B may use this information to speed up the detection of L1 synchronisation.]

[FDD - The *UL SIR Target IE* included in the message shall be used by the Node B as initial UL SIR target for the UL inner loop power control.]

[1.28Mcps TDD - The *UL SIR Target IE* included in the message shall be used by the Node B as initial UL SIR target for the UL inner loop power control according [19] and [21].]

[FDD - If the received *Limited Power Increase IE* is set to "Used", the Node B shall, if supported, use Limited Power Increase according to ref. [10] subclause 5.2.1 for the inner loop DL power control.]

[FDD - If the *TFCI Signalling Mode IE* within the RADIO LINK SETUP REQUEST message indicates that there shall be a hard split on the TFCI field but the *TFCI2 Bearer Information IE* is not included in the message, then the Node B shall transmit the TFCI2 field with zero power.]

[FDD - If the *TFCI Signalling Mode IE* within the RADIO LINK SETUP REQUEST message indicates that there shall be a hard split on the TFCI and the *TFCI2 Bearer Information IE* is included in the message, then the Node B shall transmit the TFCI2 field with zero power until Synchronization is achieved on the TFCI2 transport bearer and the first valid DSCH TFCI Signalling control frame is received on this bearer (see ref. [24]).]

[FDD - If the RADIO LINK SETUP REQUEST message includes the *Length Of TFCI2 IE*, then the Node B shall apply the length of TFCI (field 2) indicated in the message.]

[FDD - If the RADIO LINK SETUP REQUEST message does not include the *Length Of TFCI2 IE* and the *Split Type IE* is present with the value "Hard", then the Node B shall assume the length of the TFCI (field 2) is 5 bits.]

[1.28Mcps TDD - If the *UL CCTrCH Information IE* includes the *TDD TPC UL Step Size IE*, the Node B shall configure the uplink TPC step size according to the parameters given in the message.]

### **Radio Link Handling:**

#### **[FDD - Transmit Diversity]:**

[FDD - When the *Diversity Mode IE* is set to "STTD", "Closedloop mode1" or "Closedloop mode2", the Node B shall activate/deactivate the Transmit Diversity for each Radio Link in accordance with the *Transmit Diversity Indication IE*]

#### **DL Power Control:**

[FDD - The Node B shall start any DL transmission using the initial DL power specified in the message on each DL DPCH of the RL until either UL synchronisation on the Uu interface is achieved for the RLS or Power Balancing is activated. No inner loop power control or balancing shall be performed during this period. The DL power shall then vary according to the inner loop power control (see ref.[10], subclause 5.2.1.2) and the power control procedure (see subclause 8.3.7), but shall always be kept within the maximum and minimum limit specified in the RADIO LINK SETUP REQUEST message. During compressed mode, the  $\delta P_{curr}$ , as described in ref.[10] subclause 5.2.1.3, shall be added to the maximum DL power for the associated compressed frame.]

[FDD - If the *DPC Mode IE* is present in the RADIO LINK SETUP REQUEST message, the Node B shall apply the DPC mode indicated in the message and be prepared that the DPC mode may be changed during the life time of the RL. If the *DPC Mode IE* is not present in the RADIO LINK SETUP REQUEST message, DPC mode 0 shall be applied (see ref. [10]).]

[3.84 Mcps TDD - The Node B shall determine the initial CCTrCH DL power for each DCH type CCTrCH by the following rule: If the *CCTrCH Initial DL Transmission Power IE* is included for that CCTrCH, then the Node B shall use that power for the initial CCTrCH DL power, otherwise the initial CCTrCH DL power

is the *Initial DL Transmission Power IE* included in the *RL Information IE*. The Node B shall start any DL transmission on each DCH type CCTrCH using the initial CCTrCH DL power, as determined above, on each DL DPCH and on each Time Slot of the CCTrCH until the UL synchronisation on the Uu interface is achieved for the CCTrCH. No inner loop power control shall be performed during this period. The DL power shall then vary according to the inner loop power control (see ref.[21], subclause 4.2.3.4), but shall always be kept within the maximum and minimum limit specified in the RADIO LINK SETUP REQUEST message.]

[3.84 Mcps TDD - The Node B shall determine the maximum DL power for each DCH type CCTrCH by the following rule: If the *CCTrCH Maximum DL Transmission Power IE* is included for that CCTrCH, then the Node B shall use that power for the maximum DL power, otherwise the maximum DL power is the *Maximum DL Power IE* included in the *RL Information IE*.]

[3.84 Mcps TDD - The Node B shall determine the minimum DL power for each DCH type CCTrCH by the following rule: If the *CCTrCH Minimum DL Transmission Power IE* is included for that CCTrCH, then the Node B shall use that power for the minimum DL power, otherwise the minimum DL power is the *Minimum DL Power IE* included in the *RL Information IE*.]

[1.28 Mcps TDD - The Node B shall determine the initial DL power for each timeslot within the DCH type CCTrCH by the following rule: If the *Initial DL Transmission Power IE* is included in the *DL Timeslot Information LCR IE*, then the Node B shall use that power for the Initial DL Power and ignore the *DL Time Slot ISCP info LCR IE*, otherwise the initial DL Power is the *Initial DL Transmission Power IE* included in the *RL Information IE* and if *DL Time Slot ISCP info LCR IE* is present, the Node B shall use the indicated value when deciding the initial DL TX Power for each timeslot as specified in [21], it shall reduce the DL TX power in those downlink timeslots of the radio link where the interference is low, and increase the DL TX power in those timeslots where the interference is high, while keeping the total downlink power in the radio link unchanged. The Node B shall start any DL transmission on each timeslot within each DCH type CCTrCH using the initial DL power, as determined above, on each DL DPCH and on each timeslot of the CCTrCH until the UL synchronisation on the Uu interface is achieved for the CCTrCH. No inner loop power control shall be performed during this period. The DL power shall then vary according to the inner loop power control (see ref.[21], subclause 5.1.2.4), but shall always be kept within the maximum and minimum limit specified in the RADIO LINK SETUP REQUEST message.]

[1.28 Mcps TDD - The Node B shall determine the maximum DL power for each timeslot within the DCH type CCTrCH by the following rule: If the *Maximum DL Power IE* is included in the *DL Timeslot Information LCR IE*, then the Node B shall use that power for the maximum DL power, otherwise the maximum DL power is the *Maximum DL Power IE* included in the *RL Information IE*.]

[1.28 Mcps TDD - The Node B shall determine the minimum DL power for each timeslot within the DCH type CCTrCH by the following rule: If the *Minimum DL Power IE* is included in the *DL Timeslot Information LCR IE*, then the Node B shall use that power for the minimum DL power, otherwise the minimum DL power is the *Minimum DL Power IE* included in the *RL Information IE*.]

[3.84 Mcps TDD - If the *DL Time Slot ISCP Info IE* is present, the Node B shall use the indicated value when deciding the initial DL TX Power for each timeslot as specified in [21], i.e. it shall reduce the DL TX power in those downlink timeslots of the radio link where the interference is low, and increase the DL TX power in those timeslots where the interference is high, while keeping the total downlink power in the radio link unchanged].

[FDD - If the received *Inner Loop DL PC Status IE* is set to "Active", the Node B shall activate the inner loop DL power control for all RLs. If *Inner Loop DL PC Status IE* is set to "Inactive", the Node B shall deactivate the inner loop DL power control for all RLs according to ref. [10].]

[FDD - If the RADIO LINK SETUP REQUEST message includes the *DL Power Balancing Information IE* and the *Power Adjustment Type IE* is set to "Common" or "Individual", the Node B shall activate the power balancing, if activation of power balancing by the RADIO LINK SETUP REQUEST message is supported, according to subclause 8.3.7, using the *DL Power Balancing Information IE*. If the Node B starts the DL transmission and the activation of the power balancing at the same CFN, the initial power of the power balancing, i.e.  $P_{init}$  shall be set to the power level indicated by the *Initial DL Transmission Power IE*.]

[FDD - If activation of power balancing by the RADIO LINK SETUP REQUEST message is supported by the Node B, the Node B shall include the *DL Power Balancing Activation Indicator IE* in the *RL Information Response IE* in the RADIO LINK SETUP RESPONSE message.]

**[1.28Mcps TDD - Uplink Synchronisation Parameters LCR]:**

[1.28Mcps TDD - If the RADIO LINK SETUP REQUEST message contains the *Uplink Synchronisation Parameters LCR* IE, the Node B shall use the indicated values of *Uplink Synchronisation Stepsize* IE and *Uplink Synchronisation Frequency* IE when evaluating the timing of the UL synchronisation.]

#### General:

If the RADIO LINK SETUP REQUEST message includes the *RL Specific DCH Information* IE, the Node B may use the transport layer address and the binding identifier received from the CRNC when establishing a transport bearer for the DCH or the set of co-ordinated DCHs.

[FDD - If the RADIO LINK SETUP REQUEST message includes the *SSDT Cell Identity* IE and the *S-Field Length* IE, the Node B shall activate SSDT, if supported, using the *SSDT Cell Identity* IE and *SSDT Cell Identity Length* IE.]

[FDD - If the RADIO LINK SETUP REQUEST message includes the *Qth Parameter* IE in addition to the *SSDT Cell Identity* IE, the Node B shall use the *Qth Parameter* IE, if Qth signalling is supported, when SSDT is activated.]

[FDD - Irrespective of SSDT activation, the Node B shall include in the RADIO LINK SETUP RESPONSE message an indication concerning the capability to support SSDT on this RL. Only if the RADIO LINK SETUP REQUEST message requested SSDT activation and the RADIO LINK SETUP RESPONSE message indicates that the SSDT capability is supported for this RL, SSDT is activated in the Node B.]

[FDD - If the RADIO LINK SETUP REQUEST message includes the *SSDT Cell Identity for EDSCHPC* IE, the Node B shall activate enhanced DSCH power control, if supported, using the *SSDT Cell Identity For EDSCHPC* IE and *SSDT Cell Identity Length* IE as well as *Enhanced DSCH PC* IE in accordance with ref. [10] subclause 5.2.2. If the RADIO LINK SETUP REQUEST message includes both *SSDT Cell Identity* IE and *SSDT Cell Identity For EDSCHPC* IE, then the Node B shall ignore the value in *SSDT Cell Identity For EDSCHPC* IE. If the enhanced DSCH power control is activated and the TFCI power control in DSCH hard split mode is supported, the primary/secondary status determination in the enhanced DSCH power control is also applied to the TFCI power control in DSCH hard split mode.]

The Node B shall start reception on the new RL(s) after the RLs are successfully established.

/\* partly omitted \*/

### 8.3.1 Radio Link Addition

#### 8.3.1.2 Successful Operation

*/\* partly omitted \*/*

##### Physical Channels Handling:

[TDD – If the *UL DPCH Information* IE is present, the Node B shall configure the new UL DPCH(s) according to the parameters given in the message.]

[TDD – If the *DL DPCH Information* IE is present, the Node B shall configure the new DL DPCH(s) according to the parameters given in the message.]

##### **[FDD – Compressed Mode]:**

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *Compressed Mode Deactivation Flag* IE with value "Deactivate", the Node B shall not activate any compressed mode pattern in the new RLs. In all the other cases (Flag set to "Maintain Active" or not present), the ongoing compressed mode (if existing) shall be applied also to the added RLs.]

[FDD- If the RADIO LINK ADDITION REQUEST message contains the *Transmission Gap Pattern Sequence Code Information* IE for any of the allocated DL Channelisation Codes, the Node B shall apply the alternate scrambling code as indicated for each DL Channelisation Code for which the *Transmission Gap Pattern Sequence Code Information* IE is set to "Code Change".]

##### **[FDD – DL Code Information]:**

[FDD – When more than one DL DPDCH are assigned per RL, the segmented physical channel shall be mapped on to DL DPDCHs according to ref. [8]. When  $p$  number of DL DPDCHs are assigned to each RL, the first pair of DL Scrambling Code and FDD DL Channelisation Code Number corresponds to "*PhCH number 1*", the second to "*PhCH number 2*", and so on until the  $p$ th to "*PhCH number  $p$* ".]

##### **[TDD – CCTrCH Handling]:**

[TDD – If the *UL CCTrCH Information* IE is present, the Node B shall configure the new UL CCTrCH(s) according to the parameters given in the message.]

[1.28Mcps TDD - If the *UL CCTrCH Information* IE includes the *TDD TPC UL Step Size* IE, the Node B shall configure the uplink TPC step size according to the parameters given in the message, otherwise it shall use the step size configured in other radio link.]

[TDD – If the *DL CCTrCH Information* IE is present, the Node B shall configure the new DL CCTrCH(s) according to the parameters given in the message.]

[TDD - If the *DL CCTrCH Information* IE includes the *TDD TPC DL Step Size* IE, the Node B shall configure the downlink TPC step size according to the parameters given in the message, otherwise it shall use the step size configured in other radio link.]

##### **[FDD – Phase Reference Handling]:**

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *UE Support Of Dedicated Pilots For Channel Estimation* IE the Node B shall assume that dedicated pilots may be used for channel estimation with DCH or DSCH.]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH* IE the Node B shall assume that dedicated pilots may be used for channel estimation with HS-DSCH.]

[FDD – The Node B shall, when Cell Portions are defined in the Cell, use the *Primary CPICH Usage for Channel Estimation* IE if it is included in the RADIO LINK ADDITION REQUEST message.]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *Secondary CPICH Information IE*, the Node B shall assume that the Secondary CPICH indicated by the *Common Physical Channel ID IE* may be used for channel estimation.]

## Radio Link Handling:

### Diversity Combination Control:

The *Diversity Control Field IE* indicates for each RL whether the Node B shall combine the new RL with existing RL(s) or not.

- If the *Diversity Control Field IE* is set to "May", the Node B shall decide for any of the alternatives.
- If the *Diversity Control Field IE* is set to "Must", the Node B shall combine the RL with one of the other - RL.
- If the *Diversity Control Field IE* is set to "Must not", the Node B shall not combine the RL with any other existing RL.

When a new RL is to be combined, the Node B shall choose which RL(s) to combine it with.

In the case of not combining a RL with a RL established with a previous Radio Link Setup or Radio Link Addition Procedure or a RL previously listed in the RADIO LINK ADDITION RESPONSE message, the Node B shall indicate with the Diversity Indication in the *RL Information Response IE* in the RADIO LINK ADDITION RESPONSE message that no combining is done. In this case, the Node B shall include in the *DCH Information Response IE* both the *Transport Layer Address IE* and the *Binding ID IE* for the transport bearer to be established for each DCH of the RL in the RADIO LINK ADDITION RESPONSE message.

In the case of combining with a RL established with a previous Radio Link Setup or Radio Link Addition Procedure or with a RL previously listed in this RADIO LINK ADDITION RESPONSE message, the Node B shall indicate with the Diversity Indication in the *RL Information Response IE* in the RADIO LINK ADDITION RESPONSE message that the RL is combined. In this case, the *RL ID IE* indicates (one of) the previously established RL(s) or a RL previously listed in this RADIO LINK ADDITION RESPONSE message with which the new RL is combined.

In the case of a set of co-ordinated DCHs, the *Binding ID IE* and the *Transport Layer Address IE* shall be included for only one of the DCHs in a set of coordinated DCHs.

[TDD – The Node B shall include in the RADIO LINK ADDITION RESPONSE message both the *Transport Layer Address IE* and the *Binding ID IE* for the transport bearer to be established for each DSCH and USCH.]

### [FDD – Transmit Diversity]:

[FDD – If the *Transmit Diversity Indicator IE* is included in the RADIO LINK ADDITION REQUEST message, the Node B shall activate/deactivate the Transmit Diversity for each new Radio Link in accordance with the *Transmit Diversity Indicator IE* and the already known diversity mode.]

### DL Power Control:

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *Initial DL Transmission Power IE*, the Node B shall apply the given power to the transmission on each DL DPCH of the RL when starting transmission until either UL synchronisation on the Uu interface is achieved for the RLS or Power Balancing is activated. If no *Initial DL Transmission Power IE* is included, the Node B shall use any transmission power level currently used on already existing RLs for this Node B Communication Context. No inner loop power control or balancing shall be performed during this period. The DL power shall then vary according to the inner loop power control (see ref.[10], subclause 5.2.1.2) with DPC MODE currently configured for the relevant Node B Communication Context and the downlink power control procedure (see subclause 8.3.7).]

[3.84 Mcps TDD – If the RADIO LINK ADDITION REQUEST message includes the *Initial DL Transmission Power IE*, the Node B shall determine the initial CCTrCH DL power for each DCH type CCTrCH by the following rule: If the *CCTrCH Initial DL Transmission Power IE* is included for that CCTrCH, then the Node B shall use that power for the initial CCTrCH DL power, otherwise the initial CCTrCH DL power is the *Initial DL Transmission Power IE* included in the *RL Information IE*. The Node B shall apply the given power to the transmission on each DL DPCH and on each Time Slot of the CCTrCH

when starting transmission until the UL synchronisation on the Uu interface is achieved for the CCTrCH. If no *Initial DL Transmission Power* IE is included (even if CCTrCH *Initial DL Transmission Power* IEs are included), the Node B shall use any transmission power level currently used on already existing CCTrCHs for this Node B Communication Context. No inner loop power control shall be performed during this period. The DL power shall then vary according to the inner loop power control (see ref.[21], subclause 4.2.3.4).]

[1.28 Mcps TDD - If the RADIO LINK ADDITION REQUEST message includes the *Initial DL Transmission Power* IE, the Node B shall determine the initial DL power for each timeslot within a DCH type CCTrCH by the following rule: If the *Initial DL Transmission Power* IE is included in the *DL Timeslot Information LCR* IE, then the Node B shall use that power for the initial DL power and ignore the *DL Time Slot ISCP info LCR*, otherwise the initial DL power is the *Initial DL Transmission Power* IE included in the *RL Information* IE and if *DL Time Slot ISCP info LCR* IE is present, the Node B shall use the indicated value when deciding the initial DL TX Power for each timeslot as specified in [21], it shall reduce the DL TX power in those downlink timeslots of the radio link where the interference is low, and increase the DL TX power in those timeslots where the interference is high, while keeping the total downlink power in the radio link unchanged. The Node B shall apply the given power to the transmission on each DL DPCH and on each Time Slot of the CCTrCH when starting transmission until the UL synchronisation on the Uu interface is achieved for the CCTrCH. If no *Initial DL Transmission Power* IE is included, the Node B shall use any transmission power level currently used on already existing RL/timeslots for this Node B Communication Context. No inner loop power control shall be performed during this period. The DL power shall then vary according to the inner loop power control (see ref.[21], subclause 5.1.2.4).]

[FDD - If the RADIO LINK ADDITION REQUEST message includes the *Maximum DL Power* IE, the Node B shall store this value and not transmit with a higher power on any DL DPCH of the RL. If no *Maximum DL Power* IE is included, any Maximum DL power stored for already existing RLs for this Node B Communication Context shall be applied. During compressed mode, the  $\delta P_{curr}$ , as described in ref.[10] subclause 5.2.1.3, shall be added to the maximum DL power for the associated compressed frame.]

[FDD - If the RADIO LINK ADDITION REQUEST message includes the *Minimum DL Power* IE, the Node B shall store this value and never transmit with a lower power on any DL DPCH of the RL. If no *Minimum DL Power* IE is included, any Minimum DL power stored for already existing RLs for this Node B Communication Context shall be applied.]

[3.84 Mcps TDD - If the RADIO LINK ADDITION REQUEST message includes the *Maximum DL Power* IE, the Node B shall determine the maximum CCTrCH DL power for each DCH type CCTrCH by the following rule: If the *CCTrCH Maximum DL Transmission Power* IE is included for that CCTrCH, then the Node B shall use that power for the maximum CCTrCH DL power, otherwise the maximum CCTrCH DL power is the *Maximum DL Power* IE included in the *RL Information* IE. If no *Maximum DL Power* IE is included (even if *CCTrCH Maximum DL Transmission Power* IEs are included), any maximum DL power stored for already existing DCH type CCTrCHs for this Node B Communication Context shall be applied.]

[3.84 Mcps TDD - If the RADIO LINK ADDITION REQUEST message includes the *Minimum DL Power* IE, the Node B shall determine the minimum CCTrCH DL power for each DCH type CCTrCH by the following rule: If the *CCTrCH Minimum DL Transmission Power* IE is included for that CCTrCH, then the Node B shall use that power for the minimum CCTrCH DL power, otherwise the minimum CCTrCH DL power is the *Minimum DL Power* IE included in the *RL Information* IE. If no *Minimum DL Power* IE is included (even if *CCTrCH Minimum DL Transmission Power* IEs are included), any minimum DL power stored for already existing DCH type CCTrCHs for this Node B Communication Context shall be applied.]

[1.28 Mcps TDD - If the RADIO LINK ADDITION REQUEST message includes the *Maximum DL Power* IE, the Node B shall determine the maximum DL power for each timeslot within a DCH type CCTrCH by the following rule: If the *Maximum DL Power* IE is included in the *DL Timeslot Information LCR* IE for that timeslot, then the Node B shall use that power for the maximum DL power, otherwise the maximum DL power is the *Maximum DL Power* IE included in the *RL Information* IE. The Node B shall store this value and not transmit with a higher power on any applicable DL DPCH. If no *Maximum DL Power* IE is included, any maximum DL power stored for already existing RL/timeslots for this Node B Communication Context shall be applied.]

[1.28 Mcps TDD - If the RADIO LINK ADDITION REQUEST message includes the *Minimum DL Power* IE, the Node B shall determine the minimum DL power for each timeslot within a DCH type CCTrCH by the following rule: If the *Minimum DL Power* IE is included in the *DL Timeslot Information LCR* IE for that timeslot, then the Node B shall use that power for the minimum DL power, otherwise the minimum DL power is the *Minimum DL Power* IE included in the *RL Information* IE. The Node B shall store this value and

not transmit with a lower power on any applicable DL DPCH. If no *Minimum DL Power* IE is included, any minimum DL power stored for already existing RL/timeslots for this Node B Communication Context shall be applied.]

[3.84Mcps TDD – If the RADIO LINK ADDITION REQUEST message includes the *DL Time Slot ISCP Info* IE, the Node B shall use the indicated value when deciding the DL TX Power for each timeslot as specified in ref. [21], i.e. it shall reduce the DL TX power in those downlink timeslots of the radio link where the interference is low, and increase the DL TX power in those timeslots where the interference is high, while keeping the total downlink power in the radio link unchanged].

[FDD – If the power balancing is active with the Power Balancing Adjustment Type of the Node B Communication Context set to "Individual" in the existing RL(s) and the RADIO LINK ADDITION REQUEST message includes the *DL Reference Power* IE, the Node B shall activate the power balancing and use the *DL Reference Power* IE for the power balancing procedure in the new RL(s), if activation of power balancing by the RADIO LINK ADDITION REQUEST message is supported, according to subclause 8.3.7. If the Node B starts the DL transmission and the activation of the power balancing at the same CFN, the initial power of the power balancing, i.e.  $P_{init}$  shall be set to the power level indicated by the *Initial DL Transmission Power* IE (if received) or the decided DL TX power level on each DL channelisation code of a RL based on power level of existing RLs.]

[FDD – If activation of power balancing by the RADIO LINK ADDITION REQUEST message is supported by the Node B, the Node B shall include the *DL Power Balancing Activation Indicator* IE in the *RL Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]

#### **[1.28Mcps TDD – Uplink Synchronisation Parameters LCR]:**

[1.28Mcps TDD - If the RADIO LINK ADDITION REQUEST message contains the *Uplink Synchronisation Parameters LCR* IE, the Node B shall use the indicated values of *Uplink Synchronisation Stepsize* IE and *Uplink Synchronisation Frequency* IE when evaluating the timing of the UL synchronisation.]

#### **General:**

If the RADIO LINK ADDITION REQUEST message includes the *RL Specific DCH Information* IE, the Node B may use the transport layer address and the binding identifier received from the CRNC when establishing a transport bearer for the DCH or the set of co-ordinated DCHs.

[FDD – If the RADIO LINK ADDITION REQUEST message contains an *SSDT Cell Identity* IE, the Node B shall activate SSDT, if supported, for the concerned new RL, with the indicated SSDT cell identity used for that RL.]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *Qth Parameter* IE in addition to the *SSDT Cell Identity* IE, the Node B shall use the *Qth Parameter* IE, if Qth signalling is supported, when SSDT is activated in the concerned new RL.]

The Node B shall start reception on the new RL(s) after the RLs are successfully established.

/\* partly omitted \*/

## 8.3.2 Synchronised Radio Link Reconfiguration Preparation

### 8.3.2.2 Successful Operation

/\* partly omitted \*/

#### Signalling bearer rearrangement:

If the RADIO LINK RECONFIGURATION PREPARE message includes the *Signalling Bearer Request Indicator* IE the Node B shall, if supported, allocate a new Communication Control Port for the control of the Node B Communication Context and include the *Target Communication Control Port ID* IE in the RADIO LINK RECONFIGURATION READY message.

#### HS-DSCH Addition/Modification/Deletion:

If the RADIO LINK RECONFIGURATION PREPARE message includes any *HS-DSCH To Add* IE or *HS-DSCH To Modify* IE or *HS-DSCH To Delete* IE, then the Node B shall use this information to add/modify/delete the indicated HS-DSCH channel to/from the radio link.

[FDD – If the *HS-SCCH Power Offset* IE is included in the *HS-DSCH Information To Add* IE or *HS-DSCH Information To Modify* IE, the Node B may use this value to determine the HS-SCCH power. The HS-SCCH Power Offset should be applied for any HS-SCCH transmission to this UE.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *CQI Feedback Cycle k* IE, the *CQI Repetition Factor* IE, the *ACK-NACK Repetition Factor* IE, the *ACK Power Offset* IE, the *NACK Power Offset* IE or the *CQI Power Offset* IE in the *HS-DSCH Information To Modify* IE, then the DRNS shall use the indicated CQI Feedback Cycle k value, the CQI Repetition Factor or the ACK-NACK Repetition Factor, ACK Power Offset, the NACK Power Offset or the CQI Power Offset in the new configuration.]

If the RADIO LINK RECONFIGURATION PREPARE message includes an *HS-PDSCH RL ID* IE, then the Node B shall configure the HS-PDSCH in the radio link indicated by this IE, while removing any existing HS-PDSCH resources from other radio links associated with the Node B Communication Context.

If the RADIO LINK RECONFIGURATION PREPARE message includes an *HS-DSCH-RNTI* IE, then the Node B shall use the HS-DSCH-RNTI for the Node B Communication Context.

If the new configuration does not include a HS-DSCH, the HS-DSCH-RNTI, if existing in the Node B Communication Context, shall be deleted from the Node B Communication Context.

If the RADIO LINK RECONFIGURATION PREPARE message includes an *HS-DSCH To Delete* IE requesting the deletion of certain HS-DSCH resources for the Node B Communication Context, the Node B shall remove the indicated HS-DSCH in the new configuration.

The Node B shall include the *HS-DSCH Initial Capacity Allocation* IE in the RADIO LINK RECONFIGURATION READY message for each MAC-d flow, if the Node B allows the CRNC to start transmission of MAC-d PDUs before the Node B has allocated capacity on user plane as described in [24].

If the RADIO LINK RECONFIGURATION PREPARE message includes the *MAC-hs Window Size* IE in the *HS-DSCH Information To Modify* IE, then the Node B shall use the indicated MAC-hs window size value in the new configuration.

[FDD - If the RADIO LINK RECONFIGURATION PREPARE message includes *Measurement Power Offset* IE in the *HS-DSCH To Add* IE or the *HS-DSCH To Modify* IE, then the Node B shall use the measurement power offset as described in [10] subclause 6A.2.]

If the RADIO LINK RECONFIGURATION PREPARE message includes the *MAC-hs Guaranteed Bit Rate* IE in the *HS-DSCH Information To Add* IE or *HS-DSCH Information To Modify* IE, the Node B shall use this information to optimise MAC-hs scheduling decisions.

If the RADIO LINK RECONFIGURATION PREPARE message includes the *T1* IE in the *HS-DSCH Information To Modify* IE, then the Node B shall use the indicated T1 value in the new configuration.

#### [FDD - Phase Reference Handling]:

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *UE Support Of Dedicated Pilots For Channel Estimation* IE, the Node B shall assume that dedicated pilots may be used for channel estimation with DCH or DSCH.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH* IE, the Node B shall assume that dedicated pilots may be used for channel estimation with HS-DSCH.]

[FDD – The Node B shall, when Cell Portions are defined in the Cell, use the *Primary CPICH Usage for Channel Estimation* IE if it is included in the RADIO LINK RECONFIGURATION PREPARE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Secondary CPICH Information IE*, the Node B shall assume that the Secondary CPICH indicated by the *Common Physical Channel ID* IE, may be used for channel estimation.]

## General

If the RADIO LINK RECONFIGURATION PREPARE message includes the *Transport Layer Address* IE and *Binding ID* IEs in the *DSCHs To Modify*, *DSCHs To Add*, [*TDD - USCHs To Modify*, *USCHs To Add*], *HS-DSCH To Modify*, *HS-DSCH To Add* or in the *RL Specific DCH Information* IEs, the Node B may use the transport layer address and the binding identifier received from the CRNC when establishing a transport bearer for any Transport Channel or HS-DSCH MAC-d flow being added, or any Transport Channel or HS-DSCH MAC-d flow being modified for which a new transport bearer was requested with the *Transport Bearer Request Indicator* IE.

If the requested modifications are allowed by the Node B and the Node B has successfully reserved the required resources for the new configuration of the Radio Link(s), it shall respond to the CRNC with the RADIO LINK RECONFIGURATION READY message. When this procedure has been completed successfully there exists a Prepared Reconfiguration, as defined in subclause 3.1.

The Node B shall include in the RADIO LINK RECONFIGURATION READY message the *Transport Layer Address* IE and the *Binding ID* IE for any Transport Channel or HS-DSCH MAC-d flow being added or any Transport Channel or HS-DSCH MAC-d flow being modified for which a new transport bearer was requested with the *Transport Bearer Request Indicator* IE.

In the case of a set of co-ordinated DCHs requiring a new transport bearer on the Iub interface, the *Transport Layer Address* IE and the *Binding ID* IE in the *DCH Information Response* IE shall be included only for one of the DCH in the set of co-ordinated DCHs.

In the case of a Radio Link being combined with another Radio Link within the Node B, the *Transport Layer Address* IE and the *Binding ID* IE in the *DCH Information Response* IE shall be included only for one of the combined Radio Links.

## 8.3.5 Un同步ised Radio Link Reconfiguration

### 8.3.5.2 Successful Operation

/\* partly omitted \*/

[TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes any *UL CCTrCH To Modify* IE or *DL CCTrCH To Modify* IE in the Radio Link(s), the Node B shall reserve necessary resources for the new configuration of the Radio Link(s) according to the parameters given in the message.]

[TDD – If the *UL/DL CCTrCH To Modify* IE includes *TFCS* IE and/or *Puncture Limit* IE, the Node B shall apply these as the new values, otherwise the old values specified for this CCTrCH are still applicable.]

[1.28Mcps TDD - If the *UL CCTrCH To Modify* IE includes *UL SIR Target* IE, the Node B shall apply this value as the new configuration and use it for the UL inner loop power control according [19] and [21].]

#### [TDD – UL/DL CCTrCH Deletion]

[TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes any *UL CCTrCH To Delete* IE or *DL CCTrCH To Delete* IE, the Node B shall not include this CCTrCH in the new configuration.]

#### DL Power Control:

- [FDD – If the *Radio Link Information* IE includes the *DL Reference Power* IE and the power balancing is active, the Node B shall update the reference power of the power balancing in the indicated RL(s), if updating of power balancing parameters by the RADIO LINK RECONFIGURATION REQUEST message is supported, using the *DL Reference Power* IE in the RADIO LINK RECONFIGURATION REQUEST message. The updated reference power shall be used from the next adjustment period.]

[FDD – If updating of power balancing parameters by the RADIO LINK RECONFIGURATION REQUEST message is supported by the Node B, the Node B shall include the *DL Power Balancing Updated Indicator* IE in the *RL Information Response* IE for each affected RL in the RADIO LINK RECONFIGURATION RESPONSE message.]

#### RL Information:

If the RADIO LINK RECONFIGURATION REQUEST message includes the *RL Information* IE, the Node B shall treat it as follows:

- [FDD - If the *RL Information* IE includes the *Maximum DL Power* IE, the Node B shall apply this value to the new configuration and not transmit with a higher power on any Downlink DPCH of the Radio Link once the new configuration is being used. During compressed mode, the  $\delta P_{curr}$ , as described in ref.[10] subclause 5.2.1.3, shall be added to the maximum DL power for the associated compressed frame.]
- [FDD - If the *RL Information* IE includes the *Minimum DL Power* IE, the Node B shall apply this value to the new configuration and never transmit with a lower power on any Downlink Channelisation Code of the Radio Link once the new configuration is being used.]
- [3.84 Mcps TDD - If *Maximum CCTrCH DL Power* IE and/or *Minimum CCTrCH DL Power* IE are included, the Node B shall apply the values in the new configuration for this DCH type CCTrCH, if the *RL Information* IE includes *Maximum Downlink Power* and/or the *Minimum Downlink Power* IEs, the Node B shall apply the values in the new configuration for all other DCH type CCTrCHs.]
- [1.28 Mcps TDD - If *Maximum DL Power* IE and/or *Minimum DL Power* IE are included within *DL Timeslot Information LCR* IE, the the Node B shall apply the values in the new configuration for this timeslot, if the *RL Information* IE includes *Maximum Downlink Power* and/or the *Minimum Downlink Power* IEs, the Node B shall apply the values in the new configuration for all other timeslots.]
- [FDD – If the *RL Information* IE contains the *Transmission Gap Pattern Sequence Code Information* IE in the *DL Code Information* IE for any of the allocated DL Channelisation Codes, the Node B shall apply the alternate scrambling code as indicated whenever the downlink compressed mode method SF/2 is active in the new configuration.]

- [1.28Mcps TDD – If the *RL Information* IE contains the *Uplink Synchronisation Parameters LCR* IE, the Node B shall use the indicated values of *Uplink Synchronisation Stepsize* IE and *Uplink Synchronisation Frequency* IE when evaluating the timing of the UL synchronisation.]

#### Signalling Bearer Re-arrangement:

If the RADIO LINK RECONFIGURATION REQUEST message includes the *Signalling Bearer Request Indicator* IE, the Node B shall, if supported, allocate a new Communication Control Port for the control of the Node B Communication Context and include the *Target Communication Control Port ID* IE in the RADIO LINK RECONFIGURATION RESPONSE message.

#### [FDD – Phase Reference Handling]:

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *UE Support Of Dedicated Pilots For Channel Estimation* IE, the Node B shall assume that dedicated pilots may be used for channel estimation with DCH or DSCH.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH* IE, Node B shall assume that dedicated pilots may be used for channel estimation with HS-DSCH.]

#### General

If the RADIO LINK RECONFIGURATION REQUEST message includes the *RL Specific DCH Information* IE, the Node B may use the transport layer address and the binding identifier received from the CRNC when establishing a transport bearer for any Transport Channel being added or any Transport Channel being modified for which a new transport bearer was requested with the *Transport Bearer Request Indicator* IE.

If the requested modifications are allowed by the Node B, the Node B has successfully allocated the required resources, and changed to the new configuration, it shall respond to the CRNC with the RADIO LINK RECONFIGURATION RESPONSE message.

The Node B shall include in the RADIO LINK RECONFIGURATION RESPONSE message the *Transport Layer Address* IE and the *Binding ID* IE for any Transport Channel being added or any Transport Channel being modified for which a new transport bearer was requested with the *Transport Bearer Request Indicator* IE. The detailed frame protocol handling during transport bearer replacement is described in [16], subclause 5.10.1.

In the case of a set of co-ordinated DCHs requiring a new transport bearer on the Iub interface, the *Transport Layer Address* IE and the *Binding ID* IE in the *DCH Information Response* IE shall be included only for one of the DCH in the set of coordinated DCHs.

In the case of a Radio Link being combined with another Radio Link within the Node B, the *Transport Layer Address* IE and the *Binding ID* IE in the *DCH Information Response* IE shall be included only for one of the combined Radio Links.

In the case of a signalling bearer re-arrangement, the new Communication Control Port shall be used once the Node B has sent the RADIO LINK RECONFIGURATION RESPONSE message via the old Communication Control Port.

### 8.3.8.4 Abnormal Conditions

The allowed combinations of the Dedicated Measurement Type and Report Characteristics Type are shown in the table below marked with "X". For not allowed combinations, the Node B shall regard the Dedicated Measurement Initiation procedure as failed.

**Table 4: Allowed Dedicated Measurement Type and Report Characteristics Type combinations**

Dedicated Measurement Type	Report Characteristics Type								
	On Demand	Periodic	Event A	Event B	Event C	Event D	Event E	Event F	On Modification
SIR	X	X	X	X	X	X	X	X	
SIR Error	X	X	X	X	X	X	X	X	
Transmitted Code Power	X	X	X	X	X	X	X	X	
RSCP	X	X	X	X	X	X	X	X	
Rx Timing Deviation	X	X	X	X			X	X	
Round Trip Time	X	X	X	X	X	X	X	X	
Rx Timing Deviation LCR	X	X	X	X			X	X	
HS-SICH reception quality	X	X	X	X			X	X	
<b>Best Cell Portions</b>	<b>X</b>	<b>X</b>							

If the Dedicated Measurement Type received in the *Dedicated Measurement Type* IE is not defined in ref. [4] or [5] to be measured on the Dedicated Measurement Object Type received in the DEDICATED MEASUREMENT INITIATION REQUEST message, the Node B shall regard the Dedicated Measurement Initiation procedure as failed.

If the *CFN* IE is included in the DEDICATED MEASUREMENT INITIATION REQUEST message and the *Report Characteristics* IE is other than "Periodic" or "On Demand", the Node B shall regard the Dedicated Measurement Initiation procedure as failed.

### 9.1.18 COMMON MEASUREMENT INITIATION REQUEST

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Discriminator	M		9.2.1.45		—	
Message Type	M		9.2.1.46		YES	reject
Transaction ID	M		9.2.1.62		—	
Measurement ID	M		9.2.1.42		YES	reject
CHOICE Common Measurement Object Type	M				YES	reject
>Cell					—	
>>C-ID	M		9.2.1.9		—	
>>Time Slot	O		9.2.3.23	Applicable to 3.84Mcps TDD only	—	
>>Time Slot LCR	O		9.2.3.24A	Applicable to 1.28Mcps TDD only	YES	reject
>>Neighbouring Cell Measurement Information		0..<maxno MeasNCell s>			GLOBAL	ignore
>>>CHOICE Neighbouring Cell Measurement Information					—	—
>>>>Neighbouring FDD Cell Measurement Information				FDD only	—	—
>>>>> Neighbouring FDD Cell Measurement Information	M		9.2.1.47C		—	—
>>>>> Neighbouring TDD Cell Measurement Information				Applicable to 3.84Mcps TDD only	—	—
>>>>> Neighbouring TDD Cell Measurement Information LCR				Applicable to 1.28Mcps TDD only	—	—
>>>>> Neighbouring TDD Cell Measurement Information LCR	M		9.2.1.47D		—	—
>>>>> Neighbouring TDD Cell Measurement Information LCR	M		9.2.1.47E		—	—
>RACH				FDD only	—	
>>C-ID	M		9.2.1.9		—	
>>Common Transport Channel ID	M		9.2.1.14		—	
>CPCH				FDD only	—	
>>C-ID	M		9.2.1.9		—	
>>Common Transport Channel ID	M		9.2.1.14		—	
>>Spreading Factor	O		Minimum UL Channelisation Code Length 9.2.2.22		—	
>CellPortion				Applicable only for Transmitted Carrier Power	=	

				<a href="#">Value. Received Total Wide Band Power Value and Transmitted carrier power of all codes not used for HS- PDSCH or HS- SCCH transmission Value measurements FDD only</a>		
<a href="#">&gt;&gt;Reference Cell Portion ID</a>	M		<a href="#">9.2.2.xy</a>		=	
Common Measurement Type	M		9.2.1.11		YES	reject
Measurement Filter Coefficient	O		9.2.1.41		YES	reject
Report Characteristics	M		9.2.1.51		YES	reject
SFN Reporting Indicator	M		FN Reporting Indicator 9.2.1.29B		YES	reject
SFN	O		9.2.1.53A		YES	reject
Common Measurement Accuracy	O		9.2.1.9B		YES	reject

Range Bound	Explanation
<i>maxnoMeasNCells</i>	Maximum number of neighbouring cells that can be measured on.

## 9.1.36 RADIO LINK SETUP REQUEST

### 9.1.36.1 FDD message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Discriminator	M		9.2.1.45		—	
Message Type	M		9.2.1.46		YES	reject
Transaction ID	M		9.2.1.62		—	
CRNC Communication Context ID	M		9.2.1.18	The reserved value "All CRNCCC" shall not be used.	YES	reject
<b>UL DPCH Information</b>		1			YES	reject
>UL Scrambling Code	M		9.2.2.59		—	
>Min UL Channelisation Code Length	M		9.2.2.22		—	
>Max Number of UL DPDCHs	C-CodeLen		9.2.2.21		—	
>Puncture Limit	M		9.2.1.50	For UL	—	
>TFCS	M		9.2.1.58	For UL	—	
>UL DPCCH Slot Format	M		9.2.2.57		—	
> UL SIR Target	M		UL SIR 9.2.1.67A		—	
>Diversity Mode	M		9.2.2.9		—	
>SSDT Cell ID Length	O		9.2.2.45		—	
>S Field Length	O		9.2.2.40		—	
>DPC Mode	O		9.2.2.13C		YES	reject
<b>DL DPCH Information</b>		1			YES	reject
>TFCS	M		9.2.1.58	For DL	—	
>DL DPCH Slot Format	M		9.2.2.10		—	
>TFCI Signalling Mode	M		9.2.2.50		—	
>TFCI Presence	C-SlotFormat		9.2.1.57		—	
>Multiplexing Position	M		9.2.2.23		—	
>PDSCH RL ID	C-DSCH		RL ID 9.2.1.53		—	
>PDSCH Code Mapping	C-DSCH		9.2.2.25		—	
<b>&gt;Power Offset Information</b>		1			—	
>>PO1	M		Power Offset 9.2.2.29	Power offset for the TFCI bits	—	
>>PO2	M		Power Offset 9.2.2.29	Power offset for the TPC bits	—	
>>PO3	M		Power Offset 9.2.2.29	Power offset for the pilot bits	—	
>FDD TPC DL Step Size	M		9.2.2.16		—	
>Limited Power Increase	M		9.2.2.18A		—	
>Inner Loop DL PC Status	M		9.2.2.18B		—	
DCH Information	M		DCH FDD Information 9.2.2.4D		YES	reject
DSCH Information	O		DSCH FDD Information 9.2.2.13B		YES	reject
<b>TFCI2 bearer information</b>		0..1			YES	ignore
>ToAWS	M		9.2.1.61		—	

>ToAWE	M		9.2.1.60		–	
>Binding ID	O		9.2.1.4	Shall be ignored if bearer establishment with ALCAP.	YES	ignore
>Transport Layer Address	O		9.2.1.63	Shall be ignored if bearer establishment with ALCAP.	YES	ignore
<b>RL Information</b>		1..<maxno ofRLs>			EACH	notify
>RL ID	M		9.2.1.53		–	
>C-ID	M		9.2.1.9		–	
>First RLS Indicator	M		9.2.2.16A		–	
>Frame Offset	M		9.2.1.31		–	
>Chip Offset	M		9.2.2.2		–	
>Propagation Delay	O		9.2.2.35		–	
>Diversity Control Field	C-NotFirstRL		9.2.1.25		–	
>DL Code Information	M		FDD DL Code Information 9.2.2.14A		–	
>Initial DL Transmission Power	M		DL Power 9.2.1.21	Initial power on DPCH	–	
>Maximum DL Power	M		DL Power 9.2.1.21	Maximum allowed power on DPCH	–	
>Minimum DL Power	M		DL Power 9.2.1.21	Minimum allowed power on DPCH	–	
>SSDT Cell Identity	O		9.2.2.44		–	
>Transmit Diversity Indicator	C-Diversity mode		9.2.2.53		–	
>SSDT Cell Identity For EDSCHPC	C-EDSCHPC		9.2.2.44A		YES	ignore
>RL Specific DCH Information	O		9.2.1.53G		YES	ignore
>Delayed Activation	O		9.2.1.24C		YES	reject
>Qth Parameter	O		9.2.2.36A		YES	ignore
> <a href="#">Primary CPICH Usage for Channel Estimation</a>	<a href="#">O</a>		<a href="#">9.2.2.x</a>		<a href="#">YES</a>	<a href="#">ignore</a>
> <a href="#">Secondary CPICH Information</a>	<a href="#">O</a>		<a href="#">Common Physical Channel ID 9.2.1.13</a>		<a href="#">YES</a>	<a href="#">ignore</a>
Transmission Gap Pattern Sequence Information	O		9.2.2.53A		YES	reject
Active Pattern Sequence Information	O		9.2.2.A		YES	reject
DSCH Common Information	O		DSCH FDD Common Information 9.2.2.13D		YES	ignore
DL Power Balancing Information	O		9.2.2.12B		YES	ignore
HS-DSCH Information	O		HS-DSCH FDD Information 9.2.2.18D		YES	reject
HS-DSCH-RNTI	C-		9.2.1.31J		YES	reject

	InfoHSDS CH					
HS-PDSCH RL ID	C- InfoHSDS CH		RL ID 9.2.1.53		YES	reject
<a href="#">UE Support Of Dedicated Pilots For Channel Estimation</a>	O		<a href="#">9.2.2.x2</a>		<a href="#">YES</a>	<a href="#">ignore</a>
<a href="#">UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH</a>	O		<a href="#">9.2.2.x3</a>		<a href="#">YES</a>	<a href="#">ignore</a>

Condition	Explanation
CodeLen	The IE shall be present if <i>Min UL Channelisation Code Length</i> IE equals to 4.
NotFirstRL	The IE shall be present if the RL is not the first one in the <i>RL Information</i> IE.
DSCH	The IE shall be present if the <i>DSCH Information</i> IE is present.
SlotFormat	The IE shall be present if the <i>DL DPCH Slot Format</i> IE is equal to any of the values from 12 to 16.
Diversity mode	The IE shall be present if <i>Diversity Mode</i> IE in <i>UL DPCH Information</i> IE is not set to "none".
EDSCHPC	The IE shall be present if <i>Enhanced DSCH PC</i> IE is present in the <i>DSCH Common Information</i> IE.
InfoHSDSCH	The IE shall be present if <i>HS-DSCH Information</i> IE is present.

Range Bound	Explanation
<i>maxnoofRLs</i>	Maximum number of RLs for one UE

## 9.1.39 RADIO LINK ADDITION REQUEST

### 9.1.39.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Discriminator	M		9.2.1.45		—	
Message Type	M		9.2.1.46		YES	reject
Transaction ID	M		9.2.1.62		—	
Node B Communication Context ID	M		9.2.1.48	The reserved value "All NBCC" shall not be used.	YES	reject
Compressed Mode Deactivation Flag	O		9.2.2.3A		YES	reject
<b>RL Information</b>		1..<maxno ofRLs-1>			EACH	notify
>RL ID	M		9.2.1.53		—	
>C-ID	M		9.2.1.9		—	
>Frame Offset	M		9.2.1.31		—	
>Chip Offset	M		9.2.2.2		—	
>Diversity Control Field	M		9.2.1.25		—	
>DL Code Information	M		FDD DL Code Information 9.2.2.14A		—	
>Initial DL Transmission Power	O		DL Power 9.2.1.21	Initial power on DPCH	—	
>Maximum DL Power	O		DL Power 9.2.1.21	Maximum allowed power on DPCH	—	
>Minimum DL Power	O		DL Power 9.2.1.21	Minimum allowed power on DPCH	—	
>SSDT Cell Identity	O		9.2.2.44		—	
>Transmit Diversity Indicator	O		9.2.2.53		—	
>DL Reference Power	O		DL power 9.2.1.21	Power on DPCH	YES	ignore
>RL Specific DCH Information	O		9.2.1.53G		YES	ignore
>Delayed Activation	O		9.2.1.24C		YES	reject
>Qth Parameter	O		9.2.2.36A		YES	ignore
<a href="#"><u>&gt;Primary CPICH Usage for Channel Estimation</u></a>	<u>O</u>		<u>9.2.2.x</u>		<u>YES</u>	<u>ignore</u>
<a href="#"><u>&gt;Secondary CPICH Information</u></a>	<u>O</u>		<u>Common Physical Channel ID 9.2.1.13</u>		<u>YES</u>	<u>ignore</u>
<a href="#"><u>UE Support Of Dedicated Pilots For Channel Estimation</u></a>	<u>O</u>		<u>9.2.2.x2</u>		<u>YES</u>	<u>ignore</u>
<a href="#"><u>UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH</u></a>	<u>O</u>		<u>9.2.2.x3</u>		<u>YES</u>	<u>ignore</u>

Range Bound	Explanation
maxnoofRLs	Maximum number of RLs for one UE

## 9.1.42 RADIO LINK RECONFIGURATION PREPARE

### 9.1.42.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Discriminator	M		9.2.1.45		—	
Message Type	M		9.2.1.46		YES	reject
Transaction ID	M		9.2.1.62		—	
Node B Communication Context ID	M		9.2.1.48	The reserved value "All NBCC" shall not be used.	YES	reject
<b>UL DPCH Information</b>		0..1			YES	reject
>UL Scrambling Code	O		9.2.2.59		—	
>UL SIR Target	O		UL SIR 9.2.1.67A		—	
>Min UL Channelistion Code Length	O		9.2.2.22		—	
>Max Number of UL DPDCHs	C-CodeLen		9.2.2.21		—	
>Puncture Limit	O		9.2.1.50	For UL	—	
>TFCS	O		9.2.1.58		—	
>UL DPCCH Slot Format	O		9.2.2.57		—	
>Diversity Mode	O		9.2.2.9		—	
>SSDT Cell Identity Length	O		9.2.2.45		—	
>S-Field Length	O		9.2.2.40		—	
<b>DL DPCH Information</b>		0..1			YES	reject
>TFCS	O		9.2.1.58		—	
>DL DPCH Slot Format	O		9.2.2.10		—	
>TFCI Signalling Mode	O		9.2.2.50		—	
>TFCI Presence	C-SlotFormat		9.2.1.57		—	
>Multiplexing Position	O		9.2.2.23		—	
>PDSCH Code Mapping	O		9.2.2.25		—	
>PDSCH RL ID	O		RL ID 9.2.1.53		—	
>Limited Power Increase	O		9.2.2.18A		—	
DCHs To Modify	O		DCHs FDD To Modify 9.2.2.4E		YES	reject
DCHs To Add	O		DCH FDD Information 9.2.2.4D		YES	reject
<b>DCHs To Delete</b>		0..<maxno ofDCHs>			GLOBAL	reject
>DCH ID	M		9.2.1.20		—	
<b>DSCH To Modify</b>		0..<maxno ofDSCHs>			EACH	reject
>DSCH ID	M		9.2.1.27		—	
>Transport Format Set	O		9.2.1.59	For the DL.	—	
>Allocation/Retention Priority	O		9.2.1.1A		—	
>Frame Handling Priority	O		9.2.1.30		—	
>ToAWS	O		9.2.1.61		—	
>ToAWE	O		9.2.1.60		—	
>Transport Bearer Request Indicator	M		9.2.1.62A		—	

>Binding ID	O		9.2.1.4	Shall be ignored if bearer establishment with ALCAP.	YES	ignore
>Transport Layer Address	O		9.2.1.63	Shall be ignored if bearer establishment with ALCAP.	YES	ignore
DSCH To Add	O		DSCH FDD Information 9.2.2.13B		YES	reject
<b>DSCH To Delete</b>		0..<maxno ofDSCHs>			EACH	reject
>DSCH ID	M		9.2.1.27		–	
<b>TFCI2 Bearer Information</b>		0..1			YES	reject
>CHOICE TFCI2 Bearer Action	M				–	
>>Add or modify					–	
>>>ToAWS	M		9.2.1.61		–	
>>>ToAWE	M		9.2.1.60		–	
>>> TFCI2 Bearer Request Indicator	O		9.2.1.56C		YES	reject
>>>Binding ID	O		9.2.1.4	Shall be ignored if bearer establishment with ALCAP.	YES	ignore
>>>Transport Layer Address	O		9.2.1.63	Shall be ignored if bearer establishment with ALCAP.	YES	ignore
>>Delete			NULL		–	
<b>RL Information</b>		0..<maxno ofRLs>			EACH	reject
>RL ID	M		9.2.1.53		–	
>DL Code Information	O		FDD DL Code Information 9.2.2.14A		–	
>Maximum DL Power	O		DL Power 9.2.1.21	Maximum allowed power on DPCH	–	
>Minimum DL Power	O		DL Power 9.2.1.21	Minimum allowed power on DPCH	–	
>SSDT Indication	O		9.2.2.47		–	
>SSDT Cell Identity	C-SSDTIndON		9.2.2.44		–	
>Transmit Diversity Indicator	CDiversity mode		9.2.2.53		–	
>SSDT Cell Identity For EDSCHPC	C-EDSCHPC		9.2.2.44A		YES	ignore
>DL Reference Power	O		DL Power 9.2.1.21	Power on DPCH	YES	ignore
>RL Specific DCH Information	O		9.2.1.53G		YES	ignore
>DL DPCH Timing Adjustment	O		9.2.2.10A	Required RL Timing Adjustment	YES	reject

>Qth Parameter	O		9.2.2.36A		YES	ignore
<a href="#">&gt;Primary CPICH Usage for Channel Estimation</a>	O		<a href="#">9.2.2.x</a>		<a href="#">YES</a>	<a href="#">ignore</a>
<a href="#">&gt;Secondary CPICH Information Change</a>	O		<a href="#">9.2.1.x5</a>		<a href="#">YES</a>	<a href="#">ignore</a>
Transmission Gap Pattern Sequence Information	O		9.2.2.53A		YES	reject
DSCH Common Information	O		DSCH FDD Common Information 9.2.2.13D		YES	ignore
Signalling Bearer Request Indicator	O		9.2.1.55A		YES	reject
HS-DSCH To Modify	O		9.2.1.31H		YES	reject
HS-DSCH To Add	O		HS-DSCH FDD Information 9.2.2.18D		YES	reject
<b>HS-DSCH To Delete</b>		<i>0..&lt;maxno ofMACdFlows&gt;</i>			GLOBAL	reject
>HS-DSCH MAC-D Flow ID	M		9.2.1.31I		—	
HS-DSCH-RNTI	O		9.2.1.31J		YES	reject
HS-PDSCH RL ID	O		RL ID 9.2.1.53		YES	reject
<a href="#">UE Support Of Dedicated Pilots For Channel Estimation</a>	O		<a href="#">9.2.2.x2</a>		<a href="#">YES</a>	<a href="#">ignore</a>
<a href="#">UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH</a>	O		<a href="#">9.2.2.x3</a>		<a href="#">YES</a>	<a href="#">ignore</a>

Condition	Explanation
SSDTIndON	The IE shall be present if the <i>SSDT Indication</i> IE is set to "SSDT Active in the UE".
CodeLen	The IE shall be present if the <i>Min UL Channelisation Code Length</i> IE is equals to 4.
SlotFormat	The IE shall be present if the <i>DL DPCH Slot Format</i> IE is equal to any of the values from 12 to 16.
Diversity mode	The IE shall be present if the <i>Diversity Mode</i> IE is present in the <i>UL DPCH Information</i> IEand is not set to "none".
EDSCHPC	The IE shall be present if the <i>Enhanced DSCH PC</i> IE is present in the <i>DSCH Common Information</i> IE.

Range Bound	Explanation
<i>maxnoofDCHs</i>	Maximum number of DCHs for a UE
<i>maxnoofDSCHs</i>	Maximum number of DSCHs for a UE
<i>maxnoofRLs</i>	Maximum number of RLs for a UE
<i>maxnoofMACdFlows</i>	Maximum number of MAC-d Flows

## 9.1.47 RADIO LINK RECONFIGURATION REQUEST

### 9.1.47.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Discriminator	M		9.2.1.45		—	
Message Type	M		9.2.1.46		YES	reject
Transaction ID	M		9.2.1.62		—	
Node B Communication Context ID	M		9.2.1.48	The reserved value "All NBCC" shall not be used.	YES	reject
<b>UL DPCH Information</b>		0..1			YES	reject
>TFCS	O		9.2.1.58	For the UL.	—	
<b>DL DPCH Information</b>		0..1			YES	reject
>TFCS	O		9.2.1.58	For the DL.	—	
>TFCI Signalling Mode	O		9.2.2.50		—	
>Limited Power Increase	O		9.2.2.18A		—	
DCHs To Modify	O		DCHs FDD To Modify 9.2.2.4E		YES	reject
DCHs To Add	O		DCH FDD Information 9.2.2.4D		YES	reject
<b>DCHs To Delete</b>		0..<maxno ofDCHs>			GLOBAL	reject
>DCH ID	M		9.2.1.20		—	
<b>Radio Link Information</b>		0..<maxno ofRLs>			EACH	reject
>RL ID	M		9.2.1.53		—	
>Maximum DL Power	O		DL Power 9.2.1.21	Maximum allowed power on DPCH	—	
>Minimum DL Power	O		DL Power 9.2.1.21	Minimum allowed power on DPCH	—	
>DL Code Information	C-SF/2		FDD DL Code Information 9.2.2.14A		—	
>DL Reference Power	O		DL Power 9.2.1.21	Power on DPCH	YES	ignore
>RL Specific DCH Information	O		9.2.1.53G		YES	ignore
Transmission Gap Pattern Sequence Information	O		9.2.2.53A		YES	reject
Signalling Bearer Request Indicator	O		9.2.1.55A		YES	reject
<a href="#">UE Support Of Dedicated Pilots For Channel Estimation</a>	<a href="#">O</a>		<a href="#">9.2.2.x2</a>		<a href="#">YES</a>	<a href="#">ignore</a>
<a href="#">UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH</a>	<a href="#">O</a>		<a href="#">9.2.2.x3</a>		<a href="#">YES</a>	<a href="#">ignore</a>

Range Bound	Explanation
<i>maxnoofDCHs</i>	Maximum number of DCHs for a UE
<i>maxnoofRLs</i>	Maximum number of RLs for a UE

Condition	Explanation
SF/2	The IE shall be present if the <i>Transmission Gap Pattern Sequence Information</i> IE is included and the indicated Downlink Compressed Mode method for at least one of the included Transmission Gap Pattern Sequence is set to "SF/2".

### 9.2.1.23 Dedicated Measurement Type

The Dedicated Measurement Type identifies the type of measurement that shall be performed.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Dedicated Measurement Type			ENUMERATED ( SIR, SIR Error, Transmitted Code Power, RSCP, Rx Timing Deviation, Round Trip Time, ..., Rx Timing Deviation LCR, Angle Of Arrival LCR, HS-SICH reception quality. <a href="#">Best Rx Cell Portion</a> )	"RSCP" and "HS-SICH reception quality" are used by TDD only. "Rx Timing Deviation" is used by 3.84Mcps TDD only. "Rx Timing Deviation LCR", "Angle Of Arrival LCR" are used by 1.28Mcps TDD only. "Round Trip Time", "SIR Error" are used by FDD only. <a href="#">Best Rx Cell Portion is used by FDD only.</a>

Note: For definitions of the measurement types refer to [4] and [5].

### 9.2.1.24 Dedicated Measurement Value

The Dedicated Measurement Value shall be the most recent value for this measurement, for which the reporting criteria were met.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
<i>CHOICE Dedicated Measurement Value</i>					–	
> <i>SIR Value</i>					–	
>> <i>SIR Value</i>	M		INTEGER (0..63)	According to mapping in [22] and [23]	–	
> <i>SIR Error Value</i>				FDD only	–	
>> <i>SIR Error Value</i>	M		INTEGER (0..125)	According to mapping in [22]	–	
> <i>Transmitted Code Power Value</i>					–	
>> <i>Transmitted Code Power Value</i>	M		INTEGER (0..127)	According to mapping in [22] and [23]. Values 0 to 9 and 123 to 127 shall not be used.	–	
> <i>RSCP</i>				TDD only	–	
>> <i>RSCP</i>	M		INTEGER (0..127)	According to mapping in [23]	–	
> <i>Rx Timing Deviation Value</i>				Applicable to 3.84Mcps TDD only	–	
>> <i>Rx Timing Deviation</i>	M		INTEGER (0..8191)	According to mapping in [23]	–	
> <i>Round Trip Time</i>				FDD only	–	
>> <i>Round Trip Time</i>	M		INTEGER (0..32767)	According to mapping in [22]	–	
> <i>Additional Dedicated Measurement Values</i>					–	
>> <i>Rx Timing Deviation Value LCR</i>				Applicable to 1.28Mcps TDD only	–	
>>> <i>Rx Timing Deviation LCR</i>	M		INTEGER (0..511)	According to mapping in [23]	YES	reject
>> <i>Angle Of Arrival Value LCR</i>				Applicable to 1.28Mcps TDD only	–	
>>> <i>AOA Value LCR</i>		1			YES	reject
>>>> <i>AOA LCR</i>	M		INTEGER (0..719)	According to mapping in [23]	–	
>>> <i>AOA LCR Accuracy Class</i>	M		ENUMERATE D ( A, B, C, D, E, F, G, H,...)	According to mapping in [23]	–	
>> <i>HS-SICH reception quality</i>				Applicable to TDD only	–	
>>> <i>HS-SICH reception quality Value</i>		1			YES	reject
>>>> <i>Failed HS-SICH</i>	M		INTEGER (0..20)	According to mapping in [23]	–	
>>>> <i>Missed HS-SICH</i>	M		INTEGER (0..20)	According to mapping in [23]	–	
>>>> <i>Total HS-SICH</i>	M		INTEGER (0..20)	According to mapping in [23]	–	
>>> <i>Best Rx Cell Portion</i>				<a href="#">FDD only</a>	<a href="#">YES</a>	<a href="#">reject</a>
>>> <i>Best Rx Cell Portion</i>	M		<a href="#">9.2.2.xz</a>		=	

### 9.2.2.xz Best Cell Portions

*Best Cell Portions IE* indicates the best received cell portions and their SIR values when Cell Portions are defined in the cell. If the number of Cell Portions in a cell is larger than 4, 4 Cell Portions with best 4 SIR values will be reported. Otherwise, Cell Portions will be reported as many as the number of Cell Portions in a cell.

<u>IE/Group Name</u>	<u>Presence</u>	<u>Range</u>	<u>IE Type and Reference</u>	<u>Semantics Description</u>
<a href="#">Best Cell Portions</a>		<a href="#">1..&lt;maxno ofBestCell Portions&gt;</a>		<a href="#">DCH Information Response</a>
<a href="#">&gt;Cell Portion ID</a>	<a href="#">M</a>		<a href="#">9.2.2.xx</a>	
<a href="#">&gt;SIR Value</a>	<a href="#">M</a>		<a href="#">INTEGER (0..63)</a>	<a href="#">According to mapping in [22] and [23]</a>

<u>Range Bound</u>	<u>Explanation</u>
<a href="#">maxnoofBestCellPortions</a>	<a href="#">Maximum number of reported Best Received Cell Portions</a>

### 9.2.2.xx Cell Portion ID

*Cell Portion ID* is the unique identifier for a cell portion within a cell. See [4].

<u>IE/Group Name</u>	<u>Presence</u>	<u>Range</u>	<u>IE Type and Reference</u>	<u>Semantics Description</u>
<a href="#">Cell Portion ID</a>			<a href="#">INTEGER (0..63,...)</a>	

### 9.2.2.x Primary CPICH Usage for Channel Estimation

*The Primary CPICH Usage for Channel Estimation IE* indicates whether the Primary CPICH may be used for channel estimation or not.

<u>IE/Group Name</u>	<u>Presence</u>	<u>Range</u>	<u>IE Type and Reference</u>	<u>Semantics Description</u>
<a href="#">Primary CPICH Usage for Channel Estimation</a>			<a href="#">ENUMERATED (Primary CPICH may be used, Primary CPICH shall not be used)</a>	

### 9.2.2.xy Reference Cell Portion ID

*Cell Portion ID* is the unique identifier for a cell portion within one RNC.

<u>IE/Group Name</u>	<u>Presence</u>	<u>Range</u>	<u>IE Type and Reference</u>	<u>Semantics Description</u>
<a href="#">C-ID</a>			<a href="#">9.2.1.9</a>	
<a href="#">Cell Portion ID</a>			<a href="#">9.2.2.xx</a>	

### 9.2.2.x5 Secondary CPICH Information Change

*The Secondary CPICH Information Change IE* indicates modification of information of the Secondary CPICH for channel estimation.

<u>IE/Group Name</u>	<u>Presence</u>	<u>Range</u>	<u>IE Type and Reference</u>	<u>Semantics Description</u>
<a href="#"><u>CHOICE Secondary CPICH Information Change</u></a>				
<a href="#"><u>&gt;New Secondary CPICH</u></a>				
<a href="#"><u>&gt;&gt;Secondary CPICH Information</u></a>	M		<a href="#"><u>Common Physical Channel ID</u></a> <a href="#"><u>9.2.1.13</u></a>	
<a href="#"><u>&gt;Secondary CPICH Shall Not Be Used</u></a>			<a href="#"><u>NULL</u></a>	

### 9.2.2.x2 UE Support Of Dedicated Pilots For Channel Estimation

The [UE Support Of Dedicated Pilots For Channel Estimation](#) IE indicates whether the UE supports dedicated pilots for channel estimation or not with DCH or DSCH.

<u>IE/Group Name</u>	<u>Presence</u>	<u>Range</u>	<u>IE Type and Reference</u>	<u>Semantics Description</u>
<a href="#"><u>UE Support Of Dedicated Pilots For Channel Estimation</u></a>			<a href="#"><u>ENUMERATED</u></a> <a href="#"><u>(Dedicated pilots for channel estimation supported)</u></a>	

### 9.2.2.x3 UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH

The [UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH](#) IE indicates whether the UE supports dedicated pilots for channel estimation or not with HS-DSCH.

<u>IE/Group Name</u>	<u>Presence</u>	<u>Range</u>	<u>IE Type and Reference</u>	<u>Semantics Description</u>
<a href="#"><u>UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH</u></a>			<a href="#"><u>ENUMERATED</u></a> <a href="#"><u>(Dedicated pilots for channel estimation supported)</u></a>	

### 9.3.3 PDU Definitions

```
-- ****
-- PDU definitions for NBAP.
-- ****

NBAP-PDU-Contents {
    itu-t (0) identified-organization (4) etsi (0) mobileDomain (0)
    umts-Access (20) modules (3) nbap (2) version1 (1) nbap-PDU-Contents (1) }

DEFINITIONS AUTOMATIC TAGS ::=

BEGIN

-- ****
-- IE parameter types from other modules.
-- ****

IMPORTS
    Active-Pattern-Sequence-Information,
    AddorDeleteIndicator,
    AICH-Power,
    AICH-TransmissionTiming,
    AllocationRetentionPriority,
    APPreambleSignature,
    APSubChannelNumber,
    AvailabilityStatus,
    BCCH-ModificationTime,
    BindingID,
    BlockingPriorityIndicator,
    SCTD-Indicator,
    Cause,
    CCTrCH-ID,
    CDSubChannelNumbers,
    CellParameterID,
    CellPortionID,
    CellSyncBurstCode,
    CellSyncBurstCodeShift,
    CellSyncBurstRepetitionPeriod,
    CellSyncBurstSIR,
    CellSyncBurstTiming,
    CellSyncBurstTimingThreshold,
    CFN,
    Channel-Assignment-Indication,
    ChipOffset,
    C-ID,
    ClosedloopTimingadjustmentmode,
```

CommonChannelsCapacityConsumptionLaw,  
Compressed-Mode-Deactivation-Flag,  
CommonMeasurementAccuracy,  
CommonMeasurementType,  
CommonMeasurementValue,  
CommonMeasurementValueInformation,  
CommonPhysicalChannelID,  
Common-PhysicalChannel-Status-Information,  
Common-TransportChannel-Status-Information,  
CommonTransportChannelID,  
CommonTransportChannel-InformationResponse,  
CommunicationControlPortID,  
ConfigurationGenerationID,  
ConstantValue,  
CriticalityDiagnostics,  
CPCH-Allowed-Total-Rate,  
CPCHScramblingCodeNumber,  
CPCH-UL-DPCCH-SlotFormat,  
CRNC-CommunicationContextID,  
CSBMeasurementID,  
CSBTransmissionID,  
DCH-FDD-Information,  
DCH-InformationResponse,  
DCH-ID,  
FDD-DCHs-to-Modify,  
TDD-DCHs-to-Modify,  
DCH-TDD-Information,  
DedicatedChannelsCapacityConsumptionLaw,  
DedicatedMeasurementType,  
DedicatedMeasurementValue,  
DedicatedMeasurementValueInformation,  
DelayedActivation,  
DelayedActivationUpdate,  
DiversityControlField,  
DiversityMode,  
DL-DPCH-SlotFormat,  
DL-DPCH-TimingAdjustment,  
DL-or-Global-CapacityCredit,  
DL-Power,  
DL-PowerBalancing-Information,  
DL-PowerBalancing-ActivationIndicator,  
DLPowerAveragingWindowSize,  
DL-PowerBalancing-UpdatedIndicator,  
DL-ScramblingCode,  
DL-TimeslotISCP,  
DL-Timeslot-Information,  
DL-TimeslotLCR-Information,  
DL-TimeslotISCPInfo,  
DL-TimeslotISCPInfoLCR,  
DL-TPC-Pattern01Count,  
DPC-Mode,  
DPCH-ID,  
DSCH-ID,

DSCH-FDD-Common-Information,  
DSCH-FDD-Information,  
DSCH-InformationResponse,  
DSCH-TDD-Information,  
DwPCH-Power,  
End-Of-Audit-Sequence-Indicator,  
EnhancedDSCHPC,  
EnhancedDSCHPCCounter,  
EnhancedDSCHPCIndicator,  
EnhancedDSCHPCWnd,  
EnhancedDSCHPowerOffset,  
FDD-DL-ChannelisationCodeNumber,  
FDD-DL-CodeInformation,  
FDD-S-CCPCH-Offset,  
FDD-TPC-DownlinkStepSize,  
FirstRLS-Indicator,  
FNReportingIndicator,  
FPACH-Power,  
FrameAdjustmentValue,  
FrameHandlingPriority,  
FrameOffset,  
HS-PDSCH-FDD-Code-Information,  
HS-SCCH-ID,  
HS-SCCH-FDD-Code-Information,  
HS-SICH-ID,  
IB-OC-ID,  
IB-SG-DATA,  
IB-SG-POS,  
IB-SG-REP,  
IB-Type,  
InformationExchangeID,  
InformationReportCharacteristics,  
InformationType,  
InnerLoopDLPCTStatus,  
IPDL-FDD-Parameters,  
IPDL-TDD-Parameters,  
IPDL-Indicator,  
IPDL-TDD-Parameters-LCR,  
LimitedPowerIncrease,  
Local-Cell-ID,  
MaximumDL-PowerCapability,  
Maximum-PDSCH-Power,  
MaximumTransmissionPower,  
Max-Number-of-PCPCHes,  
MaxNrOfUL-DPDCHs,  
MaxPRACH-MidambleShifts,  
MeasurementFilterCoefficient,  
MeasurementID,  
MidambleAllocationMode,  
MidambleShiftAndBurstType,  
MidambleShiftLCR,  
MinimumDL-PowerCapability,  
MinSpreadingFactor,

```
MinUL-ChannelisationCodeLength,  
MultiplexingPosition,  
NEOT,  
NCyclesPerSFNperiod,  
NFmax,  
NRepetitionsPerCyclePeriod,  
N-INSYNC-IND,  
N-OUTSYNC-IND,  
NeighbouringCellMeasurementInformation,  
NeighbouringFDDCellMeasurementInformation,  
NeighbouringTDDCellMeasurementInformation,  
NodeB-CommunicationContextID,  
NStartMessage,  
NSubCyclesPerCyclePeriod,  
PagingIndicatorLength,  
PayloadCRC-PresenceIndicator,  
PCCPCH-Power,  
PCP-Length,  
PDSCH-CodeMapping,  
PDSCHSet-ID,  
PDSCH-ID,  
PICH-Mode,  
PICH-Power,  
PowerAdjustmentType,  
PowerOffset,  
PowerRaiseLimit,  
PRACH-Midamble,  
PreambleSignatures,  
PreambleThreshold,  
PredictedSFNSFNDeviationLimit,  
PredictedUTRANGPSDeviationLimit,  
PrimaryCPICH-Power,  
Primary-CPICH-Usage-for-Channel-Estimation,  
PrimaryScramblingCode,  
PropagationDelay,  
SCH-TimeSlot,  
PunctureLimit,  
PUSCHSet-ID,  
PUSCH-ID,  
QE-Selector,  
Qth-Parameter,  
RACH-SlotFormat,  
RACH-SubChannelNumbers,  
ReferenceClockAvailability,  
ReferenceSFNoffset,  
RepetitionLength,  
RepetitionPeriod,  
ReportCharacteristics,  
RequestedDataValue,  
RequestedDataValueInformation,  
ResourceOperationalState,  
RL-Set-ID,  
RL-ID,
```

RL-Specific-DCH-Info,  
Received-total-wide-band-power-Value,  
AdjustmentPeriod,  
ScaledAdjustmentRatio,  
MaxAdjustmentStep,  
RNC-ID,  
ScramblingCodeNumber,  
Secondary-CPICH-Information-Change,  
SecondaryCCPCH-SlotFormat,  
Segment-Type,  
S-FieldLength,  
SFN,  
SFNSFNChangeLimit,  
SFNSFNDriftRate,  
SFNSFNDriftRateQuality,  
SFNSFNQuality,  
ShutdownTimer,  
SIB-Originator,  
SpecialBurstScheduling,  
SignallingBearerRequestIndicator,  
SSDT-Cell-Identity,  
SSDT-CellID-Length,  
SSDT-Indication,  
Start-Of-Audit-Sequence-Indicator,  
STD-Indicator,  
SSDT-SupportIndicator,  
SyncCase,  
SYNCDlCodeId,  
SyncFrameNumber,  
SynchronisationReportCharacteristics,  
SynchronisationReportType,  
T-Cell,  
T-RLFFAILURE,  
TDD-ChannelisationCode,  
TDD-ChannelisationCodeLCR,  
TDD-DL-Code-LCR-Information,  
TDD-DPCHOffset,  
TDD-TPC-DownlinkStepSize,  
TDD-PhysicalChannelOffset,  
TDD-UL-Code-LCR-Information,  
TFCI2-BearerInformationResponse,  
TFCI2BearerRequestIndicator,  
TFCI-Coding,  
TFCI-Presence,  
TFCI-SignallingMode,  
TFCS,  
TimeSlot,  
TimeSlotLCR,  
TimeSlotDirection,  
TimeSlotStatus,  
TimingAdjustmentValue,  
TimingAdvanceApplied,  
ToAWE,

ToAWS,  
TransmissionDiversityApplied,  
TransmitDiversityIndicator,  
TransmissionGapPatternSequenceCodeInformation,  
Transmission-Gap-Pattern-Sequence-Information,  
TransportBearerRequestIndicator,  
TransportFormatSet,  
TransportLayerAddress,  
TSTD-Indicator,  
TUTRANGPS,  
TUTRANGPSChangeLimit,  
TUTRANGPSDriftRate,  
TUTRANGPSDriftRateQuality,  
TUTRANGPSQuality,  
UARFCN,  
UC-Id,  
[UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation,](#)  
[UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH,](#)  
USCH-Information,  
USCH-InformationResponse,  
UL-CapacityCredit,  
UL-DPCCH-SlotFormat,  
UL-SIR,  
UL-FP-Mode,  
UL-PhysCH-SF-Variation,  
UL-ScramblingCode,  
UL-Timeslot-Information,  
UL-TimeslotLCR-Information,  
UL-TimeSlot-ISCP-Info,  
UL-TimeSlot-ISCP-LCR-Info,  
UL-TimeslotISCP-Value,  
UL-TimeslotISCP-Value-IncrDecrThres,  
USCH-ID,  
HSDSCH-FDD-Information,  
HSDSCH-FDD-Information-Response,  
HSDSCH-Information-to-Modify,  
HSDSCH-MACdFlow-ID,  
HSDSCH-RNTI,  
HSDSCH-TDD-Information,  
HSDSCH-TDD-Information-Response,  
PrimaryCCPCH-RSCP,  
HSDSCH-FDD-Update-Information,  
HSDSCH-TDD-Update-Information,  
UL-Synchronisation-Parameters-LCR,  
TDD-DL-DPCH-TimeSlotFormat-LCR,  
TDD-UL-DPCH-TimeSlotFormat-LCR,  
TDD-TPC-UplinkStepSize-LCR  
FROM NBAP-IES  
  
PrivateIE-Container{},  
ProtocolExtensionContainer{},  
ProtocolIE-Container{},

```
ProtocolIE-Single-Container{},
ProtocolIE-ContainerList{},
NBAP-PRIVATE-IES,
NBAP-PROTOCOL-IES,
NBAP-PROTOCOL-EXTENSION
FROM NBAP-Containers

id-Active-Pattern-Sequence-Information,
id-AdjustmentRatio,
id-AICH-Information,
id-AICH-ParametersListIE-CTCH-ReconfRqstFDD,
id-AP-AICH-Information,
id-AP-AICH-ParametersListIE-CTCH-ReconfRqstFDD,
id-BCH-Information,
id-BCCH-ModificationTime,
id-bindingID,
id-BlockingPriorityIndicator,
id-Cause,
id-CauseLevel-PSCH-ReconfFailure,
id-CauseLevel-RL-AdditionFailureFDD,
id-CauseLevel-RL-AdditionFailureTDD,
id-CauseLevel-RL-ReconfFailure,
id-CauseLevel-RL-SetupFailureFDD,
id-CauseLevel-RL-SetupFailureTDD,
id-CauseLevel-SyncAdjustmntFailureTDD,
id-CCP-InformationItem-AuditRsp,
id-CCP-InformationList-AuditRsp,
id-CCP-InformationItem-ResourceStatusInd,
id-CCTrCH-InformationItem-RL-FailureInd,
id-CCTrCH-InformationItem-RL-RestoreInd,
id-CCTrCH-Initial-DL-Power-RL-AdditionRqstTDD,
id-CCTrCH-Initial-DL-Power-RL-ReconfPrepTDD,
id-CCTrCH-Initial-DL-Power-RL-SetupRqstTDD,
id-CDCA-ICH-Information,
id-CDCA-ICH-ParametersListIE-CTCH-ReconfRqstFDD,
id-CellAdjustmentInfo-SyncAdjustmntRqstTDD,
id-CellAdjustmentInfoItem-SyncAdjustmentRqstTDD,
id-Cell-InformationItem-AuditRsp,
id-Cell-InformationItem-ResourceStatusInd,
id-Cell-InformationList-AuditRsp,
id-CellParameterID,
id-CellSyncBurstTransInit-CellSyncInitiationRqstTDD,
id-CellSyncBurstMeasureInit-CellSyncInitiationRqstTDD,
id-cellSyncBurstRepetitionPeriod,
id-CellSyncBurstTransReconfiguration-CellSyncReconfRqstTDD,
id-CellSyncBurstTransReconfInfo-CellSyncReconfRqstTDD,
id-CellSyncBurstMeasReconfiguration-CellSyncReconfRqstTDD,
id-CellSyncBurstMeasInfoList-CellSyncReconfRqstTDD,
id-CellSyncBurstInfoList-CellSyncReconfRqstTDD,
id-CellSyncInfo-CellSyncReprtTDD,
id-CFN,
id-CFNReportingIndicator,
id-C-ID,
```

id-Closed-Loop-Timing-Adjustment-Mode,  
id-CommonMeasurementAccuracy,  
id-CommonMeasurementObjectType-CM-Rprt,  
id-CommonMeasurementObjectType-CM-Rqst,  
id-CommonMeasurementObjectType-CM-Rsp,  
id-CommonMeasurementType,  
id-CommonPhysicalChannelID,  
id-CommonPhysicalChannelType-CTCH-ReconfRqstFDD,  
id-CommonPhysicalChannelType-CTCH-SetupRqstFDD,  
id-CommonPhysicalChannelType-CTCH-SetupRqstTDD,  
id-CommunicationContextInfoItem-Reset,  
id-CommunicationControlPortID,  
id-CommunicationControlPortInfoItem-Reset,  
id-Compressed-Mode-Deactivation-Flag,  
id-ConfigurationGenerationID,  
id-CPCH-Information,  
id-CPCH-Parameters-CTCH-SetupRsp,  
id-CPCH-ParametersListIE-CTCH-ReconfRqstFDD,  
id-CRNC-CommunicationContextID,  
id-CriticalityDiagnostics,  
id-CSBTransmissionID,  
id-CSBMeasurementID,  
id-DCHs-to-Add-FDD,  
id-DCHs-to-Add-TDD,  
id-DCH-AddList-RL-ReconfPrepTDD,  
id-DCH-DeleteList-RL-ReconfPrepFDD,  
id-DCH-DeleteList-RL-ReconfPrepTDD,  
id-DCH-DeleteList-RL-ReconfRqstFDD,  
id-DCH-DeleteList-RL-ReconfRqstTDD,  
id-DCH-FDD-Information,  
id-DCH-TDD-Information,  
id-DCH-InformationResponse,  
id-DCH-RearrangeList-Bearer-RearrangeInd,  
id-DSCH-RearrangeList-Bearer-RearrangeInd,  
id-FDD-DCHs-to-Modify,  
id-TDD-DCHs-to-Modify,  
id-DedicatedMeasurementObjectType-DM-Rprt,  
id-DedicatedMeasurementObjectType-DM-Rqst,  
id-DedicatedMeasurementObjectType-DM-Rsp,  
id-DedicatedMeasurementType,  
id-DelayedActivation,  
id-DelayedActivationList-RL-ActivationCmdFDD,  
id-DelayedActivationList-RL-ActivationCmdTDD,  
id-DelayedActivationInformation-RL-ActivationCmdFDD,  
id-DelayedActivationInformation-RL-ActivationCmdTDD,  
id-DL-CCTrCH-InformationAddList-RL-ReconfPrepTDD,  
id-DL-CCTrCH-InformationDeleteItem-RL-ReconfRqstTDD,  
id-DL-CCTrCH-InformationDeleteList-RL-ReconfPrepTDD,  
id-DL-CCTrCH-InformationDeleteList-RL-ReconfRqstTDD,  
id-DL-CCTrCH-InformationItem-RL-SetupRqstTDD,  
id-DL-CCTrCH-InformationList-RL-AdditionRqstTDD,  
id-DL-CCTrCH-InformationList-RL-SetupRqstTDD,  
id-DL-CCTrCH-InformationModifyItem-RL-ReconfRqstTDD,

id-DL-CCTrCH-InformationModifyList-RL-ReconfPrepTDD,  
id-DL-CCTrCH-InformationModifyList-RL-ReconfRqstTDD,  
id-DL-DPCH-InformationAddListIE-RL-ReconfPrepTDD,  
id-DL-DPCH-InformationItem-RL-AdditionRqstTDD,  
id-DL-DPCH-InformationList-RL-SetupRqstTDD,  
id-DL-DPCH-InformationModify-AddListIE-RL-ReconfPrepTDD,  
id-DL-DPCH-InformationModify-DeleteListIE-RL-ReconfPrepTDD,  
id-DL-DPCH-InformationModify-ModifyListIE-RL-ReconfPrepTDD,  
id-DL-DPCH-Information-RL-ReconfPrepFDD,  
id-DL-DPCH-Information-RL-ReconfRqstFDD,  
id-DL-DPCH-Information-RL-SetupRqstFDD,  
id-DL-DPCH-TimingAdjustment,  
id-DL-PowerBalancing-Information,  
id-DL-PowerBalancing-ActivationIndicator,  
id-DL-ReferencePowerInformationItem-DL-PC-Rqst,  
id-DL-PowerBalancing-UpdatedIndicator,  
id-DLReferencePower,  
id-DLReferencePowerList-DL-PC-Rqst,  
id-DL-TPC-Pattern01Count,  
id-DPC-Mode,  
id-DPCHConstant,  
id-DSCH-AddItem-RL-ReconfPrepFDD,  
id-DSCHs-to-Add-FDD,  
id-DSCH-DeleteItem-RL-ReconfPrepFDD,  
id-DSCH-DeleteList-RL-ReconfPrepFDD,  
id-DSCHs-to-Add-TDD,  
id-DSCH-Information-DeleteList-RL-ReconfPrepTDD,  
id-DSCH-Information-ModifyList-RL-ReconfPrepTDD,  
id-DSCH-InformationResponse,  
id-DSCH-FDD-Information,  
id-DSCH-FDD-Common-Information,  
id-DSCH-TDD-Information,  
id-DSCH-ModifyItem-RL-ReconfPrepFDD,  
id-DSCH-ModifyList-RL-ReconfPrepFDD,  
id-End-Of-Audit-Sequence-Indicator,  
id-EnhancedDSCHPC,  
id-EnhancedDSCHPCIndicator,  
id-FACH-Information,  
id-FACH-ParametersList-CTCH-ReconfRqstTDD,  
id-FACH-ParametersList-CTCH-SetupRsp,  
id-FACH-ParametersListIE-CTCH-ReconfRqstFDD,  
id-FACH-ParametersListIE-CTCH-SetupRqstFDD,  
id-FACH-ParametersListIE-CTCH-SetupRqstTDD,  
id-IndicationType-ResourceStatusInd,  
id-InformationExchangeID,  
id-InformationExchangeObjectType-InfEx-Rqst,  
id-InformationExchangeObjectType-InfEx-Rsp,  
id-InformationExchangeObjectType-InfEx-Rprt,  
id-InformationReportCharacteristics,  
id-InformationType,  
id-InitDL-Power,  
id-InnerLoopDLPResponseStatus,  
id-IntStdPhCellSyncInfoItem-CellSyncReprtTDD,

id-IPDLParameter-Information-Cell-ReconfRqstFDD,  
id-IPDLParameter-Information-Cell-SetupRqstFDD,  
id-IPDLParameter-Information-Cell-ReconfRqstTDD,  
id-IPDLParameter-Information-Cell-SetupRqstTDD,  
id-LateEntranceCellSyncInfoItem-CellSyncReprtTDD,  
id-Limited-power-increase-information-Cell-SetupRqstFDD,  
id-Local-Cell-ID,  
id-Local-Cell-Group-InformationItem-AuditRsp,  
id-Local-Cell-Group-InformationItem-ResourceStatusInd,  
id-Local-Cell-Group-InformationItem2-ResourceStatusInd,  
id-Local-Cell-Group-InformationList-AuditRsp,  
id-Local-Cell-InformationItem-AuditRsp,  
id-Local-Cell-InformationItem-ResourceStatusInd,  
id-Local-Cell-InformationItem2-ResourceStatusInd,  
id-Local-Cell-InformationList-AuditRsp,  
id-AdjustmentPeriod,  
id-MaxAdjustmentStep,  
id-MaximumTransmissionPower,  
id-MeasurementFilterCoefficient,  
id-MeasurementID,  
id-MIB-SB-SIB-InformationList-SystemInfoUpdateRqst,  
id-NCyclesPerSFNperiod,  
id-NeighbouringCellMeasurementInformation,  
id-NodeB-CommunicationContextID,  
id-NRepetitionsPerCyclePeriod,  
id-P-CCPCH-Information,  
id-P-CPICH-Information,  
id-P-SCH-Information,  
id-PCCPCH-Information-Cell-ReconfRqstTDD,  
id-PCCPCH-Information-Cell-SetupRqstTDD,  
id-PCH-Parameters-CTCH-ReconfRqstTDD,  
id-PCH-Parameters-CTCH-SetupRsp,  
id-PCH-ParametersItem-CTCH-ReconfRqstFDD,  
id-PCH-ParametersItem-CTCH-SetupRqstFDD,  
id-PCH-ParametersItem-CTCH-SetupRqstTDD,  
id-PCH-Information,  
id-PCPCH-Information,  
id-PICH-ParametersItem-CTCH-ReconfRqstFDD,  
id-PDSCH-Information-AddListIE-PSCH-ReconfRqst,  
id-PDSCH-Information-Cell-SetupRqstFDD,  
id-PDSCH-Information-Cell-ReconfRqstFDD,  
id-PDSCH-Information-ModifyListIE-PSCH-ReconfRqst,  
id-PDSCH-RL-ID,  
id-PDSCHSets-AddList-PSCH-ReconfRqst,  
id-PDSCHSets-DeleteList-PSCH-ReconfRqst,  
id-PDSCHSets-ModifyList-PSCH-ReconfRqst,  
id-PICH-Information,  
id-PICH-Parameters-CTCH-ReconfRqstTDD,  
id-PICH-ParametersItem-CTCH-SetupRqstTDD,  
id-PowerAdjustmentType,  
id-Power-Local-Cell-Group-InformationItem-AuditRsp,  
id-Power-Local-Cell-Group-InformationItem-ResourceStatusInd,  
id-Power-Local-Cell-Group-InformationItem2-ResourceStatusInd,

| [id-Primary-CPICH-Usage-for-Channel-Estimation,](#)  
id-Power-Local-Cell-Group-InformationList-AuditRsp,  
id-Power-Local-Cell-Group-InformationList-ResourceStatusInd,  
id-Power-Local-Cell-Group-InformationList2-ResourceStatusInd,  
id-Power-Local-Cell-Group-ID,  
id-PRACH-Information,  
id-PRACHConstant,  
id-PRACH-ParametersItem-CTCH-SetupRqstTDD,  
id-PRACH-ParametersListIE-CTCH-ReconfRqstFDD,  
id-PrimaryCCPCH-Information-Cell-ReconfRqstFDD,  
id-PrimaryCCPCH-Information-Cell-SetupRqstFDD,  
id-PrimaryCPICH-Information-Cell-ReconfRqstFDD,  
id-PrimaryCPICH-Information-Cell-SetupRqstFDD,  
| [id-Primary-CPICH-Usage-for-Channel-Estimation,](#)  
id-PrimarySCH-Information-Cell-ReconfRqstFDD,  
id-PrimarySCH-Information-Cell-SetupRqstFDD,  
id-PrimaryScramblingCode,  
id-SCH-Information-Cell-ReconfRqstTDD,  
id-SCH-Information-Cell-SetupRqstTDD,  
id-PUSCH-Information-AddListIE-PSCH-ReconfRqst,  
id-PUSCH-Information-ModifyListIE-PSCH-ReconfRqst,  
id-PUSCHConstant,  
id-PUSCHSets-AddList-PSCH-ReconfRqst,  
id-PUSCHSets-DeleteList-PSCH-ReconfRqst,  
id-PUSCHSets-ModifyList-PSCH-ReconfRqst,  
id-Qth-Parameter,  
id-RACH-Information,  
id-RACH-Parameters-CTCH-SetupRsp,  
id-RACH-ParametersItem-CTCH-SetupRqstFDD,  
id-RACH-ParameterItem-CTCH-SetupRqstTDD,  
id-ReferenceClockAvailability,  
id-ReferenceSFNoffset,  
id-ReportCharacteristics,  
id-Reporting-Object-RL-FailureInd,  
id-Reporting-Object-RL-RestoreInd,  
id-ResetIndicator,  
id-RL-InformationItem-DM-Rprt,  
id-RL-InformationItem-DM-Rqst,  
id-RL-InformationItem-DM-Rsp,  
id-RL-InformationItem-RL-AdditionRqstFDD,  
id-RL-informationItem-RL-DeletionRqst,  
id-RL-InformationItem-RL-FailureInd,  
id-RL-InformationItem-RL-PreemptRequiredInd,  
id-RL-InformationItem-RL-ReconfPrepFDD,  
id-RL-InformationItem-RL-ReconfRqstFDD,  
id-RL-InformationItem-RL-RestoreInd,  
id-RL-InformationItem-RL-SetupRqstFDD,  
id-RL-InformationList-RL-AdditionRqstFDD,  
id-RL-informationList-RL-DeletionRqst,  
id-RL-InformationList-RL-PreemptRequiredInd,  
id-RL-InformationList-RL-ReconfPrepFDD,  
id-RL-InformationList-RL-ReconfRqstFDD,  
id-RL-InformationList-RL-SetupRqstFDD,  
id-RL-InformationResponseItem-RL-AdditionRspFDD,

id-RL-InformationResponseItem-RL-ReconfReady,  
id-RL-InformationResponseItem-RL-ReconfRsp,  
id-RL-InformationResponseItem-RL-SetupRspFDD,  
id-RL-InformationResponseList-RL-AdditionRspFDD,  
id-RL-InformationResponseList-RL-ReconfReady,  
id-RL-InformationResponseList-RL-ReconfRsp,  
id-RL-InformationResponseList-RL-SetupRspFDD,  
id-RL-InformationResponse-RL-AdditionRspTDD,  
id-RL-InformationResponse-RL-SetupRspTDD,  
id-RL-Information-RL-AdditionRqstTDD,  
id-RL-Information-RL-ReconfRqstTDD,  
id-RL-Information-RL-ReconfPrepTDD,  
id-RL-Information-RL-SetupRqstTDD,  
id-RL-ReconfigurationFailureItem-RL-ReconfFailure,  
id-RL-Set-InformationItem-DM-Rprt,  
id-RL-Set-InformationItem-DM-Rsp,  
id-RL-Set-InformationItem-RL-FailureInd,  
id-RL-Set-InformationItem-RL-RestoreInd,  
id-RL-Specific-DCH-Info,  
id-S-CCPCH-Information,  
id-S-CPICH-Information,  
id-SCH-Information,  
id-S-SCH-Information,  
id-Secondary-CCPCHListIE-CTCH-ReconfRqstTDD,  
id-Secondary-CCPCH-parameterListIE-CTCH-SetupRqstTDD,  
id-Secondary-CCPCH-Parameters-CTCH-ReconfRqstTDD,  
id-SecondaryCPICH-InformationItem-Cell-ReconfRqstFDD,  
id-SecondaryCPICH-InformationItem-Cell-SetupRqstFDD,  
id-SecondaryCPICH-InformationList-Cell-ReconfRqstFDD,  
id-SecondaryCPICH-InformationList-Cell-SetupRqstFDD,  
id-Secondary-CPICH-Information-Change,  
id-SecondarySCH-Information-Cell-ReconfRqstFDD,  
id-SecondarySCH-Information-Cell-SetupRqstFDD,  
id-SegmentInformationListIE-SystemInfoUpdate,  
id-SFN,  
id-SFNReportingIndicator,  
id-ShutdownTimer,  
id-SignallingBearerRequestIndicator,  
id-SSDT-CellIDforEDSCHPC,  
id-Start-Of-Audit-Sequence-Indicator,  
id-Successful-RL-InformationRespItem-RL-AdditionFailureFDD,  
id-Successful-RL-InformationRespItem-RL-SetupFailureFDD,  
id-Synchronisation-Configuration-Cell-ReconfRqst,  
id-Synchronisation-Configuration-Cell-SetupRqst,  
id-SyncCase,  
id-SyncCaseIndicatorItem-Cell-SetupRqstTDD-PSCH,  
id-SyncFrameNumber,  
id-SynchronisationReportType,  
id-SynchronisationReportCharacteristics,  
id-SyncReportType-CellSyncReprtTDD,  
id-T-Cell,  
id-TargetCommunicationControlPortID,  
id-TFCI2-Bearer-Information-RL-SetupRqstFDD,

```
id-TFCI2-BearerInformationResponse,  
id-TFCI2BearerRequestIndicator,  
id-TFCI2-BearerSpecificInformation-RL-ReconfPrepFDD,  
id-Transmission-Gap-Pattern-Sequence-Information,  
id-TimeSlotConfigurationList-Cell-ReconfRqstTDD,  
id-TimeSlotConfigurationList-Cell-SetupRqstTDD,  
id-timeslotInfo-CellSyncInitiationRqstTDD,  
id-TimeslotISCPInfo,  
id-TimingAdvanceApplied,  
id-TransmissionDiversityApplied,  
id-transportlayeraddress,  
id-UARFCNforNt,  
id-UARFCNforNd,  
id-UARFCNforNu,  
id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation,  
id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH,  
id-UL-CCTrCH-InformationAddList-RL-ReconfPrepTDD,  
id-UL-CCTrCH-InformationDeleteItem-RL-ReconfRqstTDD,  
id-UL-CCTrCH-InformationDeleteList-RL-ReconfPrepTDD,  
id-UL-CCTrCH-InformationDeleteList-RL-ReconfRqstTDD,  
id-UL-CCTrCH-InformationItem-RL-SetupRqstTDD,  
id-UL-CCTrCH-InformationList-RL-AdditionRqstTDD,  
id-UL-CCTrCH-InformationList-RL-SetupRqstTDD,  
id-UL-CCTrCH-InformationModifyItem-RL-ReconfRqstTDD,  
id-UL-CCTrCH-InformationModifyList-RL-ReconfPrepTDD,  
id-UL-CCTrCH-InformationModifyList-RL-ReconfRqstTDD,  
id-UL-DPCH-InformationAddListIE-RL-ReconfPrepTDD,  
id-UL-DPCH-InformationItem-RL-AdditionRqstTDD,  
id-UL-DPCH-InformationList-RL-SetupRqstTDD,  
id-UL-DPCH-InformationModify-AddListIE-RL-ReconfPrepTDD,  
id-UL-DPCH-InformationModify-DeleteListIE-RL-ReconfPrepTDD,  
id-UL-DPCH-InformationModify-ModifyListIE-RL-ReconfPrepTDD,  
id-UL-DPCH-Information-RL-ReconfPrepFDD,  
id-UL-DPCH-Information-RL-ReconfRqstFDD,  
id-UL-DPCH-Information-RL-SetupRqstFDD,  
id-Unsuccessful-cell1-InformationRespItem-SyncAdjustmntFailureTDD,  
id-Unsuccessful-PDSCHSetItem-PSCH-ReconfFailureTDD,  
id-Unsuccessful-PUSCHSetItem-PSCH-ReconfFailureTDD,  
id-Unsuccessful-RL-InformationRespItem-RL-AdditionFailureFDD,  
id-Unsuccessful-RL-InformationRespItem-RL-SetupFailureFDD,  
id-Unsuccessful-RL-InformationResp-RL-AdditionFailureTDD,  
id-Unsuccessful-RL-InformationResp-RL-SetupFailureTDD,  
id-USCH-Information-Add,  
id-USCH-Information-DeleteList-RL-ReconfPrepTDD,  
id-USCH-Information-ModifyList-RL-ReconfPrepTDD,  
id-USCH-InformationResponse,  
id-USCH-Information,  
id-USCH-RearrangeList-Bearer-RearrangeInd,  
id-DL-DPCH-LCR-Information-RL-SetupRqstTDD,  
id-DwPCH-LCR-Information,  
id-DwPCH-LCR-InformationList-AuditRsp,  
id-DwPCH-LCR-Information-Cell-SetupRqstTDD,  
id-DwPCH-LCR-Information-Cell-ReconfRqstTDD,
```

id-DwPCH-LCR-Information-ResourceStatusInd,  
id-maxFACH-Power-LCR-CTCH-SetupRqstTDD,  
id-maxFACH-Power-LCR-CTCH-ReconfRqstTDD,  
id-FPACH-LCR-Information,  
id-FPACH-LCR-Information-AuditRsp,  
id-FPACH-LCR-InformationList-AuditRsp,  
id-FPACH-LCR-InformationList-ResourceStatusInd,  
id-FPACH-LCR-Parameters-CTCH-SetupRqstTDD,  
id-FPACH-LCR-Parameters-CTCH-ReconfRqstTDD,  
id-PCCPCH-LCR-Information-Cell-SetupRqstTDD,  
id-PCH-Power-LCR-CTCH-SetupRqstTDD,  
id-PCH-Power-LCR-CTCH-ReconfRqstTDD,  
id-PICH-LCR-Parameters-CTCH-SetupRqstTDD,  
id-PRACH-LCR-ParametersList-CTCH-SetupRqstTDD,  
id-RL-InformationResponse-LCR-RL-SetupRspTDD,  
id-Secondary-CCPCH-LCR-parameterList-CTCH-SetupRqstTDD,  
id-TimeSlot,  
id-TimeSlotConfigurationList-LCR-Cell-ReconfRqstTDD,  
id-TimeSlotConfigurationList-LCR-Cell-SetupRqstTDD,  
id-TimeslotISCP-LCR-InfoList-RL-SetupRqstTDD,  
id-TimeSlotLCR-CM-Rqst,  
id-UL-DPCH-LCR-Information-RL-SetupRqstTDD,  
id-DL-DPCH-InformationItem-LCR-RL-AdditionRqstTDD,  
id-UL-DPCH-InformationItem-LCR-RL-AdditionRqstTDD,  
id-TimeslotISCP-InformationList-LCR-RL-AdditionRqstTDD,  
id-DL-DPCH-LCR-InformationAddList-RL-ReconfPrepTDD,  
id-DL-DPCH-LCR-InformationModify-AddList-RL-ReconfPrepTDD,  
id-DL-Timeslot-LCR-InformationModify-ModifyList-RL-ReconfPrepTDD,  
id-TimeslotISCPInfoList-LCR-DL-PC-RqstTDD,  
id-UL-DPCH-LCR-InformationAddListIE-RL-ReconfPrepTDD,  
id-UL-DPCH-LCR-InformationModify-AddList,  
id-UL-TimeslotLCR-Information-RL-ReconfPrepTDD,  
id-UL-SIRTtarget,  
id-PDSCH-AddInformation-LCR-PSCH-ReconfRqst,  
id-PDSCH-AddInformation-LCR-AddListIE-PSCH-ReconfRqst,  
id-PDSCH-ModifyInformation-LCR-PSCH-ReconfRqst,  
id-PDSCH-ModifyInformation-LCR-ModifyListIE-PSCH-ReconfRqst,  
id-PUSCH-AddInformation-LCR-PSCH-ReconfRqst,  
id-PUSCH-AddInformation-LCR-AddListIE-PSCH-ReconfRqst,  
id-PUSCH-ModifyInformation-LCR-PSCH-ReconfRqst,  
id-PUSCH-ModifyInformation-LCR-ModifyListIE-PSCH-ReconfRqst,  
id-PUSCH-Info-DM-Rqst,  
id-PUSCH-Info-DM-Rsp,  
id-PUSCH-Info-DM-Rprt,  
id-RL-InformationResponse-LCR-RL-AdditionRspTDD,  
id-IPDLParameter-Information-LCR-Cell-SetupRqstTDD,  
id-IPDLParameter-Information-LCR-Cell-ReconfRqstTDD,  
id-HS-PDSCH-HS-SCCH-MaxPower-PSCH-ReconfRqst,  
id-HS-PDSCH-HS-SCCH-ScramblingCode-PSCH-ReconfRqst,  
id-HS-PDSCH-FDD-Code-Information-PSCH-ReconfRqst,  
id-HS-SCCH-FDD-Code-Information-PSCH-ReconfRqst,  
id-HS-PDSCH-TDD-Information-PSCH-ReconfRqst,  
id-Add-To-HS-SCCH-Resource-Pool-PSCH-ReconfRqst,

```
id-Modify-HS-SCCH-Resource-Pool-PSCH-ReconfRqst,
id-Delete-From-HS-SCCH-Resource-Pool-PSCH-ReconfRqst,
id-SYNCDlCodeId-TransInitLCR-CellSyncInitiationRqstTDD,
id-SYNCDlCodeId-MeasureInitLCR-CellSyncInitiationRqstTDD,
id-SYNCDlCodeIdTransReconfInfoLCR-CellSyncReconfRqstTDD,
id-SYNCDlCodeIdMeasReconfigurationLCR-CellSyncReconfRqstTDD,
id-SYNCDlCodeIdMeasInfoList-CellSyncReconfRqstTDD,
id-SyncDlCodeIdsMeasInfoList-CellSyncReprtTDD,
id-NSubCyclesPerCyclePeriod-CellSyncReconfRqstTDD,
id-DwPCH-Power,
id-AccumulatedClockupdate-CellSyncReprtTDD,
id-HSDSCH-FDD-Information,
id-HSDSCH-FDD-Information-Response,
id-HSDSCH-FDD-Information-to-Add,
id-HSDSCH-FDD-Information-to-Delete,
id-HSDSCH-Information-to-Modify,
id-HSDSCH-RearrangeList-Bearer-RearrangeInd,
id-HSDSCH-RNTI,
id-HSDSCH-TDD-Information,
id-HSDSCH-TDD-Information-Response,
id-HSDSCH-TDD-Information-Response-LCR,
id-HSDSCH-TDD-Information-to-Add,
id-HSDSCH-TDD-Information-to-Delete,
id-HSPDSCH-RL-ID,
id-HSSICH-Info-DM-Rpprt,
id-HSSICH-Info-DM-Rqst,
id-HSSICH-Info-DM-Rsp,
id-PrimCCPCH-RSCP-DL-PC-RqstTDD,
id-HSDSCH-FDD-Update-Information,
id-HSDSCH-TDD-Update-Information,
id-UL-Synchronisation-Parameters-LCR,
id-DL-DPCH-TimeSlotFormat-LCR-ModifyItem-RL-ReconfPrepTDD,
id-UL-DPCH-TimeSlotFormat-LCR-ModifyItem-RL-ReconfPrepTDD,
id-CCTrCH-Maximum-DL-Power-RL-SetupRqstTDD,
id-CCTrCH-Minimum-DL-Power-RL-SetupRqstTDD,
id-CCTrCH-Maximum-DL-Power-RL-AdditionRqstTDD,
id-CCTrCH-Minimum-DL-Power-RL-AdditionRqstTDD,
id-CCTrCH-Maximum-DL-Power-InformationAdd-RL-ReconfPrepTDD,
id-CCTrCH-Minimum-DL-Power-InformationAdd-RL-ReconfPrepTDD,
id-CCTrCH-Maximum-DL-Power-InformationModify-RL-ReconfPrepTDD,
id-CCTrCH-Minimum-DL-Power-InformationModify-RL-ReconfPrepTDD,
id-Maximum-DL-Power-Modify-LCR-InformationModify-RL-ReconfPrepTDD,
id-Minimum-DL-Power-Modify-LCR-InformationModify-RL-ReconfPrepTDD,
id-DL-DPCH-LCR-InformationModify-ModifyList-RL-ReconfRqstTDD,
id-CCTrCH-Maximum-DL-Power-InformationModify-RL-ReconfRqstTDD,
id-CCTrCH-Minimum-DL-Power-InformationModify-RL-ReconfRqstTDD,
id-TDD-TPC-UplinkStepSize-LCR-RL-SetupRqstTDD,
id-TDD-TPC-UplinkStepSize-LCR-RL-AdditionRqstTDD,
id-TDD-TPC-DownlinkStepSize-RL-AdditionRqstTDD,
id-TDD-TPC-UplinkStepSize-InformationAdd-LCR-RL-ReconfPrepTDD,
id-TDD-TPC-UplinkStepSize-InformationModify-LCR-RL-ReconfPrepTDD,
id-TDD-TPC-DownlinkStepSize-InformationModify-RL-ReconfPrepTDD,
id-TDD-TPC-DownlinkStepSize-InformationAdd-RL-ReconfPrepTDD,
```

```
maxNrOfCCTrCHs,  
maxNrOfCellSyncBursts,  
maxNrOfCodes,  
maxNrOfCPCHs,  
maxNrOfDCHs,  
maxNrOfDLTSSs,  
maxNrOfDLTSLCRs,  
maxNrOfDPCHs,  
maxNrOfDSCHs,  
maxNrOfFACHs,  
maxNrOfRLs,  
maxNrOfRLs-1,  
maxNrOfRLs-2,  
maxNrOfRLSets,  
maxNrOfPCPCHs,  
maxNrOfPDSCHs,  
maxNrOfPUSCHs,  
maxNrOfPRACHLCRs,  
maxNrOfPDSCHSets,  
maxNrOfPUSCHSets,  
maxNrOfReceptsPerSyncFrame,  
maxNrOfSCCPCHs,  
maxNrOfSCCPCHLCRs,  
maxNrOfULTSs,  
maxNrOfULTSLCRs,  
maxNrOfUSCHs,  
maxAPSigNum,  
maxCPCHCell,  
maxFACHCell,  
maxFPACHCell,  
maxNoofLen,  
maxRACHCell,  
maxPCPCHCell,  
maxPRACHCell,  
maxSCCPCHCell,  
maxSCPICHCell,  
maxCellinNodeB,  
maxCCPinNodeB,  
maxCommunicationContext,  
maxLocalCellinNodeB,  
maxNrOfSlotFormatsPRACH,  
maxIB,  
maxIBSEG,  
maxNrOfHSSCCHs,  
maxNrOfHSSICHs,  
maxNrOfHSPDSCHs,  
maxNrOfSyncFramesLCR,  
maxNrOfReceptionsperSyncFrameLCR,  
maxNrOfSyncDLCodesLCR,  
maxNrOfMACdFlows  
FROM NBAP-Constants;
```

```
/* partly omitted */
```

```
-- ****
-- COMMON MEASUREMENT INITIATION REQUEST
-- ****

CommonMeasurementInitiationRequest ::= SEQUENCE {
    protocolIES      ProtocolIE-Container {{CommonMeasurementInitiationRequest-IEs}},
    protocolExtensions ProtocolExtensionContainer {{CommonMeasurementInitiationRequest-Extensions}} OPTIONAL,
    ...
}

CommonMeasurementInitiationRequest-IEs NBAP-PROTOCOL-IES ::= {
    { ID id-MeasurementID           CRITICALITY reject      TYPE MeasurementID             PRESENCE
        mandatory } |
    { ID id-CommonMeasurementObjectType-CM-Rqst   CRITICALITY reject      TYPE CommonMeasurementObjectType-CM-Rqst  PRESENCE
        mandatory } |
    { ID id-CommonMeasurementType       CRITICALITY reject      TYPE CommonMeasurementType        PRESENCE mandatory
        } |
    { ID id-MeasurementFilterCoefficient CRITICALITY reject     TYPE MeasurementFilterCoefficient  PRESENCE
        optional } |
    { ID id-ReportCharacteristics     CRITICALITY reject     TYPE ReportCharacteristics       PRESENCE mandatory
        } |
    { ID id-SFNReportingIndicator     CRITICALITY reject     TYPE FNReportingIndicator        PRESENCE mandatory
        } |
    { ID id-SFN                      CRITICALITY reject     TYPE SFN                         PRESENCE optional
        },
    ...
}

CommonMeasurementInitiationRequest-Extensions NBAP-PROTOCOL-EXTENSION ::= {
    { ID id-CommonMeasurementAccuracy   CRITICALITY reject     EXTENSION CommonMeasurementAccuracy  PRESENCE optional},
    ...
}

CommonMeasurementObjectType-CM-Rqst ::= CHOICE {
    cell                  Cell-CM-Rqst,
    rACH                 RACH-CM-Rqst,
    cPCH                 CPCH-CM-Rqst,
    ...
    cellPortion          CellPortion-CM-Rqst
}

Cell-CM-Rqst ::= SEQUENCE {
    c-ID                C-ID,
    timeSlot           TimeSlot OPTIONAL, -- Applicable to 3.84Mcps TDD only
    iE-Extensions       ProtocolExtensionContainer {{CellItem-CM-Rqst-ExtIEs}} OPTIONAL,
    ...
}
```

```

CellItem-CM-Rqst-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    { ID id-TimeSlotLCR-CM-Rqst      CRITICALITY reject      EXTENSION TimeSlotLCR      PRESENCE optional      } |
    -- Applicable to 1.28Mcps TDD only
    { ID id-NeighbouringCellMeasurementInformation      CRITICALITY ignore      EXTENSION NeighbouringCellMeasurementInformation      PRESENCE
optional},
    ...
}

RACH-CM-Rqst ::= SEQUENCE {
    c-ID,
    commonTransportChannelID,
    iE-Extensions
    ...
}
OPTIONAL,

RACHItem-CM-Rqst-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

CPCH-CM-Rqst ::= SEQUENCE {
    c-ID,
    commonTransportChannelID,
    spreadingfactor
    iE-Extensions
    ...
}
OPTIONAL,

CPCHItem-CM-Rqst-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

CellPortion-CM-Rqst ::= SEQUENCE {
    c-ID,
    cellPortionID,
    iE-Extensions
    ...
}
OPTIONAL,

CellPortionItem-CM-Rqst-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

/* partly omitted */

-- ****
-- 
-- RADIO LINK SETUP REQUEST FDD
-- 
-- ****

RadioLinkSetupRequestFDD ::= SEQUENCE {
    protocolIEs      ProtocolIE-Container  {{RadioLinkSetupRequestFDD-IEs}},
    protocolExtensions  ProtocolExtensionContainer  {{RadioLinkSetupRequestFDD-Extensions}}
}
OPTIONAL,

```

```

}

RadioLinkSetupRequestFDD-IES NBAP-PROTOCOL-IES ::= {
  { ID id-CRNC-CommunicationContextID
    PRESENCE mandatory }|
  { ID id-UL-DPCH-Information-RL-SetupRqstFDD
    PRESENCE mandatory }|
  { ID id-DL-DPCH-Information-RL-SetupRqstFDD
    PRESENCE mandatory }|
  { ID id-DCH-FDD-Information
    CRITICALITY reject
    TYPE DCH-FDD-Information
  }|
  { ID id-DSCH-FDD-Information
    CRITICALITY reject
    TYPE DSCH-FDD-Information
  }|
  { ID id-TFCI2-Bearer-Information-RL-SetupRqstFDD
    CRITICALITY ignore
    TYPE
  }|
  { ID id-RL-InformationList-RL-SetupRqstFDD
    PRESENCE optional }|
  { ID id-Transmission-Gap-Pattern-Sequence-Information
    PRESENCE mandatory }|
  { ID id-Transmission-Gap-Pattern-Sequence-Information
    PRESENCE optional }|
  { ID id-Active-Pattern-Sequence-Information
    CRITICALITY reject
    TYPE Active-Pattern-Sequence-Information
    PRESENCE optional },
  ...
}

RadioLinkSetupRequestFDD-Extensions NBAP-PROTOCOL-EXTENSION ::= {
  { ID id-DSCH-FDD-Common-Information
    CRITICALITY ignore
    EXTENSION DSCH-FDD-Common-Information
  }|
  { ID id-DL-PowerBalancing-Information
    CRITICALITY ignore
    EXTENSION DL-PowerBalancing-Information
  }|
  { ID id-HSDSCH-FDD-Information
    CRITICALITY reject
    EXTENSION HSDSCH-FDD-Information
  }|
  { ID id-HSDSCH-RNTI
    CRITICALITY reject
    EXTENSION HSDSCH-RNTI
  }|
  -- The IE shall be present if HS-DSCH Information IE is present
  { ID id-HSPDSCH-RL-ID
    CRITICALITY reject
    EXTENSION RL-ID
  }|
  -- The IE shall be present if HS-DSCH Information IE is present
  { ID id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation
    CRITICALITY ignore
    EXTENSION UE-Support-Of-Dedicated-Pilots-For-
    Channel-Estimation
    PRESENCE optional }|
  { ID id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH
    CRITICALITY ignore
    EXTENSION UE-Support-Of-
    Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH
    PRESENCE optional },
  ...
}

UL-DPCH-Information-RL-SetupRqstFDD ::= SEQUENCE {
  ul-ScramblingCode
  UL-ScramblingCode,
  minUL-ChannelisationCodeLength
  MinUL-ChannelisationCodeLength,
  maxNrOfUL-DPDCHs
  MaxNrOfUL-DPDCHs OPTIONAL,
  -- This IE shall be present if Min UL Channelisation Code length IE is set to 4 --
  ul-PunctureLimit
  PunctureLimit,
  tFCS
  TFCS,
  ul-DPCCH-SlotFormat
  UL-DPCCH-SlotFormat,
  ul-SIR-Target
  UL-SIR,
  diversityMode
  DiversityMode,
  sSDT-CellID-Length
  SSDT-CellID-Length OPTIONAL,
  s-FieldLength
  S-FieldLength OPTIONAL,
  iE-Extensions
  ProtocolExtensionContainer { { UL-DPCH-Information-RL-SetupRqstFDD-ExtIEs } } OPTIONAL,
}

```

```

}

UL-DPCH-Information-RL-SetupRqstFDD-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    { ID id-DPC-Mode           CRITICALITY reject   EXTENSION DPC-Mode      PRESENCE optional   },
    ...
}

DL-DPCH-Information-RL-SetupRqstFDD ::= SEQUENCE {
    tFCs                      TFCS,
    dl-DPCH-SlotFormat        DL-DPCH-SlotFormat,
    tFCI-SignallingMode       TFCI-SignallingMode,
    tFCI-Presence             TFCI-Presence     OPTIONAL,
    -- this IE shall be present if the DL DPCH slot format IE is set to any of the values from 12 to 16 --
    multiplexingPosition      MultiplexingPosition,
    pDSCH-RL-ID               RL-ID            OPTIONAL,
    -- This IE shall be present if the DSCH Information IE is present --
    pDSCH-CodeMapping         PDSCH-CodeMapping OPTIONAL,
    -- This IE shall be present if the DSCH Information IE is present --
    powerOffsetInformation    PowerOffsetInformation-RL-SetupRqstFDD,
    fdd-TPC-DownlinkStepSize  FDD-TPC-DownlinkStepSize,
    limitedPowerIncrease       LimitedPowerIncrease,
    innerLoopDLPcStatus       InnerLoopDLPcStatus,
    iE-Extensions             ProtocolExtensionContainer { { DL-DPCH-Information-RL-SetupRqstFDD-ExtIEs} } OPTIONAL,
    ...
}

DL-DPCH-Information-RL-SetupRqstFDD-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

PowerOffsetInformation-RL-SetupRqstFDD ::= SEQUENCE {
    pO1-ForTFCI-Bits          PowerOffset,
    pO2-ForTPC-Bits            PowerOffset,
    pO3-ForPilotBits           PowerOffset,
    iE-Extensions              ProtocolExtensionContainer { { PowerOffsetInformation-RL-SetupRqstFDD-ExtIEs} } OPTIONAL,
    ...
}

PowerOffsetInformation-RL-SetupRqstFDD-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

TFCI2-Bearer-Information-RL-SetupRqstFDD ::= SEQUENCE {
    toAWS                     ToAWS,
    toAWE                     ToAWE,
    iE-Extensions              ProtocolExtensionContainer { { TFCI2-Bearer-Information-RL-SetupRqstFDD-ExtIEs} } OPTIONAL,
    ...
}

TFCI2-Bearer-Information-RL-SetupRqstFDD-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    { ID id-bindingID          CRITICALITY ignore   EXTENSION BindingID      PRESENCE optional } |
    { ID id-transportlayeraddress CRITICALITY ignore EXTENSION TransportLayerAddress PRESENCE optional },
    ...
}

```

```

}

RL-InformationList-RL-SetupRqstFDD ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF
    ProtocolIE-Single-Container{{ RL-InformationItemIE-RL-SetupRqstFDD }}

RL-InformationItemIE-RL-SetupRqstFDD NBAP-PROTOCOL-IES ::= {
    { ID      id-RL-InformationItem-RL-SetupRqstFDD           CRITICALITY      notify      TYPE
      SetupRqstFDD      PRESENCE      mandatory}                         RL-InformationItem-RL-
}
}

RL-InformationItem-RL-SetupRqstFDD ::= SEQUENCE {
    rL-ID                  RL-ID,
    c-ID                   C-ID,
    firstRLS-indicator    FirstRLS-Indicator,
    frameOffset            FrameOffset,
    chipOffset              ChipOffset,
    propagationDelay       PropagationDelay      OPTIONAL,
    diversityControlField  DiversityControlField  OPTIONAL,
    -- This IE shall be present if the RL is not the first one in the RL Information IE
    dl-CodeInformation     FDD-DL-CodeInformation,
    initialDL-transmissionPower  DL-Power,
    maximumDL-power        DL-Power,
    minimumDL-power        DL-Power,
    ssDT-Cell-Identity     SSDT-Cell-Identity      OPTIONAL,
    transmitDiversityIndicator  TransmitDiversityIndicator  OPTIONAL,
    -- This IE shall be present if Diversity Mode IE in UL DPCH Information group is not set to "none"
    iE-Extensions          ProtocolExtensionContainer { { RL-InformationItem-RL-SetupRqstFDD-ExtIES } }  OPTIONAL,
    ...
}

RL-InformationItem-RL-SetupRqstFDD-ExtIES NBAP-PROTOCOL-EXTENSION ::= {
    { ID      id-SSDT-CellIDforEDSCHPC CRITICALITY ignore EXTENSION SSDT-Cell-Identity      PRESENCE conditional }|
    -- This IE shall be present if Enhanced DSCH PC IE is present in the DSCH Common Information IE.
    { ID      id-RL-Specific-DCH-Info   CRITICALITY ignore EXTENSION RL-Specific-DCH-Info      PRESENCE      optional }|
    { ID      id-DelayedActivation     CRITICALITY reject EXTENSION DelayedActivation PRESENCE optional }|
    { ID      id-Qth-Parameter        CRITICALITY ignore EXTENSION Qth-Parameter      PRESENCE optional }|
    { ID      id-Primary-CPICH-Usage-for-Channel-Estimation  CRITICALITY ignore EXTENSION Primary-CPICH-Usage-for-Channel-Estimation  PRESENCE optional }|
    { ID      id-Secondary-CPICH-Information    CRITICALITY ignore EXTENSION CommonPhysicalChannelID      PRESENCE optional },
    ...
}

/* partly omitted */

-- ****
-- 
-- RADIO LINK ADDITION REQUEST FDD
-- 
-- ****

RadioLinkAdditionRequestFDD ::= SEQUENCE {
    protocolIES          ProtocolIE-Container  {{RadioLinkAdditionRequestFDD-IEs}},
```

```

protocolExtensions      ProtocolExtensionContainer { {RadioLinkAdditionRequestFDD-Extensions} }
                                         OPTIONAL,
...
}

RadioLinkAdditionRequestFDD-IES NBAP-PROTOCOL-IES ::= {
  { ID   id-NodeB-CommunicationContextID           CRITICALITY reject          TYPE   NodeB-CommunicationContextID      PRESENCE
    mandatory } |
  { ID   id-Compressed-Mode-Deactivation-Flag     CRITICALITY reject          TYPE   Compressed-Mode-Deactivation-Flag  PRESENCE optional } |
  { ID   id-RL-InformationList-RL-AdditionRqstFDD  CRITICALITY notify         TYPE   RL-InformationList-RL-AdditionRqstFDD
    PRESENCE mandatory } |
  { ID   id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation  CRITICALITY ignore        EXTENSION UE-Support-Of-Dedicated-Pilots-For-
    Channel-Estimation  PRESENCE optional } |
  { ID   id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH  CRITICALITY ignore        EXTENSION UE-Support-Of-
    Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH  PRESENCE optional },
...
}

RadioLinkAdditionRequestFDD-Extensions NBAP-PROTOCOL-EXTENSION ::= {
...
}

RL-InformationList-RL-AdditionRqstFDD ::= SEQUENCE (SIZE (1..maxNrOfRLs-1)) OF ProtocolIE-Single-Container {{ RL-InformationItemIE-RL-
AdditionRqstFDD }}
```

**RL-InformationItemIE-RL-AdditionRqstFDD NBAP-PROTOCOL-IES ::= {**

```

  { ID   id-RL-InformationItem-RL-AdditionRqstFDD      CRITICALITY    notify      TYPE
    AdditionRqstFDD      PRESENCE      mandatory }
```

**RL-InformationItem-RL-AdditionRqstFDD ::= SEQUENCE {**

```

  rL-ID                      RL-ID,
  c-ID                       C-ID,
  frameOffset                FrameOffset,
  chipOffset                 ChipOffset,
  diversityControlField     DiversityControlField,
  dl-CodeInformation         FDD-DL-CodeInformation,
  initialDL-TransmissionPower DL-Power          OPTIONAL,
  maximumDL-Power            DL-Power          OPTIONAL,
  minimumDL-Power            DL-Power          OPTIONAL,
  ssDT-CellIdentity          SSDT-Cell-Identity OPTIONAL,
  transmitDiversityIndicator TransmitDiversityIndicator OPTIONAL,
  iE-Extensions               ProtocolExtensionContainer { { RL-InformationItem-RL-AdditionRqstFDD-ExtIEs } }      OPTIONAL,
...
}
```

**RL-InformationItem-RL-AdditionRqstFDD-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {**

```

  { ID   id-DLReferencePower    CRITICALITY ignore    EXTENSION   DL-Power      PRESENCE optional } |
  { ID   id-RL-Specific-DCH-Info  CRITICALITY ignore    EXTENSION   RL-Specific-DCH-Info      PRESENCE      optional } |
  { ID   id-DelayedActivation  CRITICALITY reject     EXTENSION   DelayedActivation PRESENCE optional } |
  { ID   id-Qth-Parameter      CRITICALITY ignore    EXTENSION   Qth-Parameter  PRESENCE optional } |
  { ID   id-Primary-CPICH-Usage-for-Channel-Estimation  CRITICALITY ignore    EXTENSION   Primary-CPICH-Usage-for-Channel-Estimation  PRESENCE
    optional } |
  { ID   id-Secondary-CPICH-Information  CRITICALITY ignore    EXTENSION   CommonPhysicalChannelID      PRESENCE optional },
```

```

}

/* partly omitted */

-- *****
-- RADIO LINK RECONFIGURATION PREPARE FDD
-- *****

RadioLinkReconfigurationPrepareFDD ::= SEQUENCE {
    protocolIEs      ProtocolIE-Container {{RadioLinkReconfigurationPrepareFDD-IEs}},
    protocolExtensions  ProtocolExtensionContainer {{RadioLinkReconfigurationPrepareFDD-Extensions}} OPTIONAL,
    ...
}

RadioLinkReconfigurationPrepareFDD-IEs NBAP-PROTOCOL-IES ::= {
    { ID id-NodeB-CommunicationContextID          CRITICALITY reject      TYPE NodeB-CommunicationContextID
        PRESENCE mandatory } |
    { ID id-UL-DPCH-Information-RL-ReconfPrepFDD  CRITICALITY reject      TYPE UL-DPCH-Information-RL-
ReconfPrepFDD   PRESENCE optional } |
    { ID id-DL-DPCH-Information-RL-ReconfPrepFDD  CRITICALITY reject      TYPE DL-DPCH-Information-RL-
ReconfPrepFDD   PRESENCE optional } |
    { ID id-FDD-DCHs-to-Modify          CRITICALITY reject      TYPE FDD-DCHs-to-Modify
        { ID id-DCHs-to-Add-FDD          CRITICALITY reject      TYPE DCH-FDD-Information
            { ID id-DCH-DeleteList-RL-ReconfPrepFDD  CRITICALITY reject      TYPE DCH-DeleteList-RL-ReconfPrepFDD
                PRESENCE optional } |
                { ID id-DSCH-ModifyList-RL-ReconfPrepFDD  CRITICALITY reject      TYPE DSCH-ModifyList-RL-ReconfPrepFDD
                    PRESENCE optional } |
                    { ID id-DSCHs-to-Add-FDD          CRITICALITY reject      TYPE DSCH-FDD-Information
                        { ID id-DSCH-DeleteList-RL-ReconfPrepFDD  CRITICALITY reject      TYPE DSCH-DeleteList-RL-ReconfPrepFDD
                            PRESENCE optional } |
                            { ID id-TFCI2-BearerSpecificInformation-RL-ReconfPrepFDD  CRITICALITY reject      TYPE TFCI2-BearerSpecificInformation-
RL-ReconfPrepFDD
                                PRESENCE optional } |
                                { ID id-RL-InformationList-RL-ReconfPrepFDD  CRITICALITY reject      TYPE RL-InformationList-RL-
ReconfPrepFDD   PRESENCE optional } |
                                { ID id-Transmission-Gap-Pattern-Sequence-Information  CRITICALITY reject      TYPE Transmission-Gap-Pattern-Sequence-Information
                                    PRESENCE optional },
                                    ...
    }
}

RadioLinkReconfigurationPrepareFDD-Extensions NBAP-PROTOCOL-EXTENSION ::= {
    { ID id-DSCH-FDD-Common-Information          CRITICALITY ignore EXTENSION DSCH-FDD-Common-Information
        PRESENCE optional
    } |
    { ID id-SignallingBearerRequestIndicator  CRITICALITY reject EXTENSION SignallingBearerRequestIndicator
        PRESENCE optional } |
    { ID id-HSDSCH-Information-to-Modify       CRITICALITY reject EXTENSION HSDSCH-Information-to-Modify
        PRESENCE optional } |
    { ID id-HSDSCH-FDD-Information-to-Add      CRITICALITY reject EXTENSION HSDSCH-FDD-Information
        PRESENCE optional } |
    { ID id-HSDSCH-FDD-Information-to-Delete    CRITICALITY reject EXTENSION HSDSCH-DeleteList-RL-ReconfPrepFDD
        PRESENCE optional } |
    { ID id-HSDSCH-RNTI                      CRITICALITY reject EXTENSION HSDSCH-RNTI
        PRESENCE optional } |
    { ID id-HSPDSCH-RL-ID                     CRITICALITY reject EXTENSION RL-ID
        PRESENCE optional } |
}

```

```

{ ID   id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation      CRITICALITY ignore    EXTENSION    UE-Support-Of-Dedicated-Pilots-For-
  Channel-Estimation      PRESENCE optional}|
{ ID   id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH    CRITICALITY ignore    EXTENSION    UE-Support-Of-
  Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH    PRESENCE optional},
...
}

UL-DPCH-Information-RL-ReconfPrepFDD ::= SEQUENCE {
  ul-ScramblingCode          UL-ScramblingCode           OPTIONAL,
  ul-SIR-Target               UL-SIR                     OPTIONAL,
  minUL-ChannelisationCodeLength MinUL-ChannelisationCodeLength OPTIONAL,
  maxNrOfUL-DPDCHs           MaxNrOfUL-DPDCHs        OPTIONAL,
  -- This IE shall be present if minUL-ChannelisationCodeLength Ie is set to 4
  ul-PunctureLimit            PunctureLimit             OPTIONAL,
  tFCS                         TFCS                      OPTIONAL,
  ul-DPCCH-SlotFormat         UL-DPCCH-SlotFormat       OPTIONAL,
  diversityMode                DiversityMode             OPTIONAL,
  sSDT-CellIDLength           SSDT-CellID-Length        OPTIONAL,
  s-FieldLength                S-FieldLength             OPTIONAL,
  iE-Extensions                ProtocolExtensionContainer { { UL-DPCH-Information-RL-ReconfPrepFDD-ExtIEs} }    OPTIONAL,
  ...
}

UL-DPCH-Information-RL-ReconfPrepFDD-ExtIEs  NBAP-PROTOCOL-EXTENSION ::= {
  ...
}

DL-DPCH-Information-RL-ReconfPrepFDD ::= SEQUENCE {
  tFCS                         TFCS                      OPTIONAL,
  dl-DPCH-SlotFormat           DL-DPCH-SlotFormat        OPTIONAL,
  tFCI-SignallingMode          TFCI-SignallingMode       OPTIONAL,
  tFCI-Presence                 TFCI-Presence             OPTIONAL,
  -- This IE shall be present if the DL DPCH Slot Format IE is set to any of the values from 12 to 16
  multiplexingPosition         MultiplexingPosition       OPTIONAL,
  pDSCH-CodeMapping             PDSCH-CodeMapping         OPTIONAL,
  pDSCH-RL-ID                  RL-ID                     OPTIONAL,
  limitedPowerIncrease          LimitedPowerIncrease       OPTIONAL,
  iE-Extensions                ProtocolExtensionContainer { { DL-DPCH-Information-RL-ReconfPrepFDD-ExtIEs} }    OPTIONAL,
  ...
}

DL-DPCH-Information-RL-ReconfPrepFDD-ExtIEs  NBAP-PROTOCOL-EXTENSION ::= {
  ...
}

DCH-DeleteList-RL-ReconfPrepFDD ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF DCH-DeleteItem-RL-ReconfPrepFDD

DCH-DeleteItem-RL-ReconfPrepFDD ::= SEQUENCE {
  dCH-ID,
  iE-Extensions                ProtocolExtensionContainer { { DCH-DeleteItem-RL-ReconfPrepFDD-ExtIEs} }    OPTIONAL,
  ...
}

```

```

DCH-DeleteItem-RL-ReconfPrepFDD-ExtIEs  NBAP-PROTOCOL-EXTENSION ::= {
  ...
}

DSCH-ModifyList-RL-ReconfPrepFDD ::= SEQUENCE (SIZE (1..maxNrOfDSCHs)) OF ProtocolIE-Single-Container { { DSCH-ModifyItemIE-RL-ReconfPrepFDD } }

DSCH-ModifyItemIE-RL-ReconfPrepFDD NBAP-PROTOCOL-IES ::= {
  { ID      id-DSCH-ModifyItem-RL-ReconfPrepFDD      CRITICALITY reject      TYPE      DSCH-ModifyItem-RL-ReconfPrepFDD      PRESENCE mandatory}
}

DSCH-ModifyItem-RL-ReconfPrepFDD ::= SEQUENCE {
  dSCH-ID
  dl-TransportFormatSet
  allocationRetentionPriority
  frameHandlingPriority
  toAWS
  toAWE
  transportBearerRequestIndicator
  iE-Extensions
  ...
}

DSCH-ModifyItem-RL-ReconfPrepFDD-ExtIEs  NBAP-PROTOCOL-EXTENSION ::= {
  { ID      id-bindingID          CRITICALITY ignore      EXTENSION      BindingID      PRESENCE      optional } |
  { ID      id-transportlayeraddress  CRITICALITY ignore      EXTENSION      TransportLayerAddress  PRESENCE      optional },
  ...
}

DSCH-DeleteList-RL-ReconfPrepFDD ::= SEQUENCE (SIZE (1..maxNrOfDSCHs)) OF ProtocolIE-Single-Container { { DSCH-DeleteItemIE-RL-ReconfPrepFDD } }

DSCH-DeleteItemIE-RL-ReconfPrepFDD NBAP-PROTOCOL-IES ::= {
  { ID      id-DSCH-DeleteItem-RL-ReconfPrepFDD      CRITICALITY reject      TYPE      DSCH-DeleteItem-RL-ReconfPrepFDD      PRESENCE mandatory}
}

DSCH-DeleteItem-RL-ReconfPrepFDD ::= SEQUENCE {
  dSCH-ID,
  iE-Extensions
  ...
}

DSCH-DeleteItem-RL-ReconfPrepFDD-ExtIEs  NBAP-PROTOCOL-EXTENSION ::= {
  ...
}

TFCI2-BearerSpecificInformation-RL-ReconfPrepFDD ::= CHOICE {
  addOrModify      AddOrModify-TFCI2-RL-ReconfPrepFDD,
  delete          NULL
}

AddOrModify-TFCI2-RL-ReconfPrepFDD ::= SEQUENCE {
  toAWS,
  toAWE,
  iE-Extensions
  ...
}

```

```

}

AddOrModify-TFCI2-RL-ReconfPrepFDD-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
  { ID id-TFCI2BearerRequestIndicator CRITICALITY reject EXTENSION TFCI2BearerRequestIndicator PRESENCE optional } |
  { ID id-bindingID CRITICALITY ignore EXTENSION BindingID PRESENCE optional } |
  { ID id-transportlayeraddress CRITICALITY ignore EXTENSION TransportLayerAddress PRESENCE optional },
  ...
}

RL-InformationList-RL-ReconfPrepFDD ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container {{ RL-InformationItemIE-RL-ReconfPrepFDD }}
```

RL-InformationItemIE-RL-ReconfPrepFDD NBAP-PROTOCOL-IES ::= {  
 { ID id-RL-InformationItem-RL-ReconfPrepFDD CRITICALITY reject TYPE RL-InformationItem-RL-ReconfPrepFDD PRESENCE mandatory}  
}

RL-InformationItem-RL-ReconfPrepFDD ::= SEQUENCE {  
 rL-ID RL-ID,  
 dl-CodeInformation FDD-DL-CodeInformation OPTIONAL,  
 maxDL-Power DL-Power OPTIONAL,  
 minDL-Power DL-Power OPTIONAL,  
 ssDT-Indication SSDT-Indication OPTIONAL,  
 ssDT-Cell-Identity SSDT-Cell-Identity OPTIONAL,  
 -- The IE shall be present if the SSDT Indication IE is set to "SSDT Active in the UE"  
 transmitDiversityIndicator TransmitDiversityIndicator OPTIONAL,  
 -- This IE shall be present if Diversity Mode IE is present in UL DPCH Information IE and it is not set to "none"  
 iE-Extensions ProtocolExtensionContainer { { RL-InformationItem-RL-ReconfPrepFDD-ExtIEs } } OPTIONAL,  
 ...
}

RL-InformationItem-RL-ReconfPrepFDD-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {  
 { ID id-SSDT-CellIDforEDSCHPC CRITICALITY ignore EXTENSION SSDT-Cell-Identity PRESENCE conditional } |  
 -- This IE shall be present if Enhanced DSCH PC IE is present in the DSCH Common Information IE.  
 { ID id-DLReferencePower CRITICALITY ignore EXTENSION DL-Power PRESENCE optional } |  
 { ID id-RL-Specific-DCH-Info CRITICALITY ignore EXTENSION RL-Specific-DCH-Info PRESENCE optional } |  
 { ID id-DL-DPCH-TimingAdjustment CRITICALITY reject EXTENSION DL-DPCH-TimingAdjustment PRESENCE optional } |  
 { ID id-Qth-Parameter CRITICALITY ignore EXTENSION Qth-Parameter PRESENCE optional } |  
 { ID id-Primary-CPICH-Usage-for-Channel-Estimation CRITICALITY ignore EXTENSION Primary-CPICH-Usage-for-Channel-Estimation PRESENCE optional } |  
 { ID id-Secondary-CPICH-Information-Change CRITICALITY ignore EXTENSION Secondary-CPICH-Information-Change PRESENCE optional } ,  
 ...
}

HSDSCH-DeleteList-RL-ReconfPrepFDD ::= SEQUENCE (SIZE (1..maxNrOfMACdFlows)) OF HSDSCH-DeleteItem-RL-ReconfPrepFDD

HSDSCH-DeleteItem-RL-ReconfPrepFDD ::= SEQUENCE {  
 hsDSCH-MACdFlow-ID HSDSCH-MACdFlow-ID,  
 iE-Extensions ProtocolExtensionContainer { { HSDSCH-DeleteItem-RL-ReconfPrepFDD-ExtIEs } } OPTIONAL,  
 ...
}

HSDSCH-DeleteItem-RL-ReconfPrepFDD-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {

```

}

/* partly omitted */

-- *****
-- 
-- RADIO LINK RECONFIGURATION REQUEST FDD
-- 
-- *****

RadioLinkReconfigurationRequestFDD ::= SEQUENCE {
    protocolIEs      ProtocolIE-Container {{RadioLinkReconfigurationRequestFDD-IEs}},
    protocolExtensions  ProtocolExtensionContainer {{RadioLinkReconfigurationRequestFDD-Extensions}} OPTIONAL,
    ...
}

RadioLinkReconfigurationRequestFDD-IEs NBAP-PROTOCOL-IES ::= {
    { ID id-NodeB-CommunicationContextID           CRITICALITY reject      TYPE NodeB-CommunicationContextID           PRESENCE
        mandatory } |
    { ID id-UL-DPCH-Information-RL-ReconfRqstFDD   CRITICALITY reject      TYPE UL-DPCH-Information-RL-ReconfRqstFDD   PRESENCE
        optional } |
    { ID id-DL-DPCH-Information-RL-ReconfRqstFDD   CRITICALITY reject      TYPE DL-DPCH-Information-RL-ReconfRqstFDD   PRESENCE
        optional } |
    { ID id-FDD-DCHs-to-Modify          CRITICALITY reject      TYPE FDD-DCHs-to-Modify           PRESENCE optional } |
    { ID id-DCHs-to-Add-FDD           CRITICALITY reject      TYPE DCH-FDD-Information          PRESENCE optional } |
    { ID id-DCH-DeleteList-RL-ReconfRqstFDD     CRITICALITY reject      TYPE DCH-DeleteList-RL-ReconfRqstFDD   PRESENCE
        optional } |
    { ID id-RL-InformationList-RL-ReconfRqstFDD   CRITICALITY reject      TYPE RL-InformationList-RL-ReconfRqstFDD   PRESENCE
        optional } |
    { ID id-Tx-Pattern-Sequence-Information     CRITICALITY reject      TYPE Transmission-Gap-Pattern-Sequence-Information
        PRESENCE optional },
    ...
}

RadioLinkReconfigurationRequestFDD-Extensions NBAP-PROTOCOL-EXTENSION ::= {
    { ID id-SignallingBearerRequestIndicator   CRITICALITY reject      EXTENSION SignallingBearerRequestIndicator           PRESENCE optional } |
    { ID id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation   CRITICALITY ignore     EXTENSION UE-Support-Of-Dedicated-Pilots-For-
        Channel-Estimation   PRESENCE optional } |
    { ID id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH   CRITICALITY ignore     EXTENSION UE-Support-Of-
        Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH   PRESENCE optional },
    ...
}

UL-DPCH-Information-RL-ReconfRqstFDD ::= SEQUENCE {
    ul-TFCs           OPTIONAL,
    iE-Extensions     ProtocolExtensionContainer { { UL-DPCH-Information-RL-ReconfRqstFDD-ExtIEs } } OPTIONAL,
    ...
}

UL-DPCH-Information-RL-ReconfRqstFDD-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

```

```

}

DL-DPCH-Information-RL-ReconfRqstFDD ::= SEQUENCE {
    dl-TFCI
    tFCI-SignallingMode
    limitedPowerIncrease
    iE-Extensions
    ...
}
TFCS           OPTIONAL,
TFCI-SignallingMode   OPTIONAL,
LimitedPowerIncrease   OPTIONAL,
ProtocolExtensionContainer { { DL-DPCH-Information-RL-ReconfRqstFDD-ExtIEs } }   OPTIONAL,

DL-DPCH-Information-RL-ReconfRqstFDD-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

DCH-DeleteList-RL-ReconfRqstFDD ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF DCH-DeleteItem-RL-ReconfRqstFDD

DCH-DeleteItem-RL-ReconfRqstFDD ::= SEQUENCE {
    dCH-ID
    iE-Extensions
    ...
}
DCH-ID,
ProtocolExtensionContainer { { DCH-DeleteItem-RL-ReconfRqstFDD-ExtIEs } }   OPTIONAL,

DCH-DeleteItem-RL-ReconfRqstFDD-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

RL-InformationList-RL-ReconfRqstFDD ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container {{ RL-InformationItemIE-RL-ReconfRqstFDD} }

RL-InformationItemIE-RL-ReconfRqstFDD NBAP-PROTOCOL-IES ::= {
    { ID id-RL-InformationItem-RL-ReconfRqstFDD          CRITICALITY      reject      TYPE
      ReconfRqstFDD          PRESENCE        mandatory }          RL-InformationItem-RL-
}
RL-InformationItem-RL-ReconfRqstFDD ::= SEQUENCE {
    rL-ID
    maxDL-Power
    minDL-Power
    dl-CodeInformation
    ...
}
RL-ID,
DL-Power      OPTIONAL,
DL-Power      OPTIONAL,
FDD-DL-CodeInformation   OPTIONAL,
-- The IE shall be present if the Transmission Gap Pattern Sequence Information IE is included and the indicated Downlink Compressed Mode method for
at least one of the included Transmission Gap Pattern Sequence is set to "SF/2".
iE-Extensions
ProtocolExtensionContainer { { RL-InformationItem-RL-ReconfRqstFDD-ExtIEs } }   OPTIONAL,
...
}

RL-InformationItem-RL-ReconfRqstFDD-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    { ID id-DLReferencePower      CRITICALITY ignore  EXTENSION  DL-Power      PRESENCE optional  }|
      { ID id-RL-Specific-DCH-Info  CRITICALITY ignore  EXTENSION  RL-Specific-DCH-Info  PRESENCE optional },
    ...
}
/* partly omitted */

```

### 9.3.4 Information Elements Definitions

```
--*****
-- Information Element Definitions
--*****
NBAP-IEs {
itu-t (0) identified-organization (4) etsi (0) mobileDomain (0)
umts-Access (20) modules (3) nbap (2) version1 (1) nbap-IEs (2) }

DEFINITIONS AUTOMATIC TAGS ::=

BEGIN

IMPORTS
maxNrOfRLs,
maxNrOfTFCs,
maxNrOfErrors,
maxCTFC,
maxNrOfTFS,
maxTTI-count,
maxRateMatching,
maxCodeNrComp-1,
maxNrOfCellSyncBursts,
maxNrOfCodeGroups,
maxNrOfMeasNCell,
maxNrOfMeasNCell-1,
maxNrOfReceptsPerSyncFrame,
maxNrOfTFCIGroups,
maxNrOfTFCI1Combs,
maxNrOfTFCI2Combs,
maxNrOfTFCI2Combs-1,
maxNrOfSF,
maxTGPS,
maxNrOfUSCHs,
maxNrOfULTSSs,
maxNrOfULTSLCRs,
maxNrOfDPCHs,
maxNrOfDPCHLCRs,
maxNrOfCodes,
maxNrOfDSCHs,
maxNrOfDLTSSs,
maxNrOfDLTSLCRs,
maxNrOfDCHs,
maxNrOfLevels,
maxNoGPSItems,
maxNoSat,
maxNrOfHSSCCHs,
maxNrOfHSSCCHCodes,
maxNrOfMACdFlows,
```

```
maxNrOfMACdFlows-1,  
maxNrOfMACdPDUIndexes,  
maxNrOfMACdPDUIndexes-1,  
maxNrOfPriorityQueues,  
maxNrOfPriorityQueues-1,  
maxNrOfHARQProcesses,  
maxNrOfSyncDLCodesLCR,  
maxNrOfSyncFramesLCR,  
  
id-MessageStructure,  
id-ReportCharacteristicsType-OnModification,  
id-Rx-Timing-Deviation-Value-LCR,  
id-SFNSFNMeasurementValueInformation,  
id-SFNSFNMeasurementThresholdInformation,  
id-TUTRANGPSMeasurementValueInformation,  
id-TUTRANGPSMeasurementThresholdInformation,  
id-TypeOfError,  
id-transportlayeraddress,  
id-bindingID,  
id-Angle-Of-Arrival-Value-LCR,  
id-SyncDLCODEIdThreInfoLCR,  
id-neighbouringTDDCellMeasurementInformationLCR,  
id-HS-SICH-Reception-Quality,  
id-HS-SICH-Reception-Quality-Measurement-Value,  
id-Initial-DL-Power-TimeslotLCR-InformationItem,  
id-Maximum-DL-Power-TimeslotLCR-InformationItem,  
id-Minimum-DL-Power-TimeslotLCR-InformationItem,  
id-TransmittedCarrierPowerOfAllCodesNotUsedForHS-PDSCHOrHS-SCCHTransmission,  
id-Best-Cell-Portions-Value  
  
FROM NBAP-Constants  
  
Criticality,  
ProcedureID,  
ProtocolIE-ID,  
TransactionID,  
TriggeringMessage  
FROM NBAP-CommonDataTypes  
  
NBAP-PROTOCOL-IES,  
ProtocolExtensionContainer{},  
ProtocolIE-Single-Container{},  
NBAP-PROTOCOL-EXTENSION  
FROM NBAP-Containers;  
  
/* partly omitted */  
  
-- =====  
-- B  
-- =====  
  
BCCH-ModificationTime ::= INTEGER (0..511)  
-- Time = BCCH-ModificationTime * 8
```

-- Range 0 to 4088, step 8  
-- All SFN values in which MIB may be mapped are allowed

```

Best-Cell-Portions-Value::= SEQUENCE (SIZE (1..maxNrOfBestCellPortions)) OF Best-Cell-Portions-Item

Best-Cell-Portions-Item ::= SEQUENCE {
    CellPortionID           CellPortionID,
    SIRValue                SIR-Value,
    iE-Extensions           ProtocolExtensionContainer { { Best-Cell-Portions-Item-ExtIEs } }
                                OPTIONAL
    ...
}

```

```
Best-Cell-Portions-Item-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {  
    ...  
}
```

BindingID ::= OCTET STRING (SIZE (1..4, ...))  
-- If the Binding ID includes a UDP port, the UDP port is included in octet 1 and 2. The first octet of  
-- the UDP port field is included in the first octet of the Binding ID.

BetaCD ::= INTEGER (0..15)

```
BlockingPriorityIndicator ::= ENUMERATED {
    high,
    normal,
    low,
    ...
}
-- High priority: Block resource immediately.
-- Normal priority: Block resource when idle or upon timer expiry.
-- Low priority: Block resource when idle.
```

```
SCTD-Indicator ::= ENUMERATED  
    active,  
    inactive  
}
```

-- C

```
Cause ::= CHOICE {  
    radioNetwork           CauseRadioNetwork,  
    transport              CauseTransport,  
    protocol               CauseProtocol,  
    misc                   CauseMisc,  
    ...  
}
```

```
CauseMisc ::= ENUMERATED {  
    control-processing-overload,  
    hardware-failure,  
    oam-intervention,
```

```
not-enough-user-plane-processing-resources,  
unspecified,  
...  
}  
  
CauseProtocol ::= ENUMERATED {  
    transfer-syntax-error,  
    abstract-syntax-error-reject,  
    abstract-syntax-error-ignore-and-notify,  
    message-not-compatible-with-receiver-state,  
    semantic-error,  
    unspecified,  
    abstract-syntax-error-falsely-constructed-message,  
    ...  
}  
  
CauseRadioNetwork ::= ENUMERATED {  
    unknown-C-ID,  
    cell-not-available,  
    power-level-not-supported,  
    dl-radio-resources-not-available,  
    ul-radio-resources-not-available,  
    rl-already-ActivatedOrAllocated,  
    nodeB-Resources-unavailable,  
    measurement-not-supported-for-the-object,  
    combining-resources-not-available,  
    requested-configuration-not-supported,  
    synchronisation-failure,  
    priority-transport-channel-established,  
    sIB-Origination-in-Node-B-not-Supported,  
    requested-tx-diversity-mode-not-supported,  
    unspecified,  
    bCCH-scheduling-error,  
    measurement-temporarily-not-available,  
    invalid-CM-settings,  
    reconfiguration-CFN-not-elapsed,  
    number-of-DL-codes-not-supported,  
    s-cipch-not-supported,  
    combining-not-supported,  
    ul-sf-not-supported,  
    dl-SF-not-supported,  
    common-transport-channel-type-not-supported,  
    dedicated-transport-channel-type-not-supported,  
    downlink-shared-channel-type-not-supported,  
    uplink-shared-channel-type-not-supported,  
    cm-not-supported,  
    tx-diversity-no-longer-supported,  
    unknown-Local-Cell-ID,  
    ...  
    number-of-UL-codes-not-supported,  
    information-temporarily-not-available,  
    information-provision-not-supported-for-the-object,  
    cell-synchronisation-not-supported,
```

```
cell-synchronisation-adjustment-not-supported,  
dpc-mode-change-not-supported,  
iPDL-already-activated,  
iPDL-not-supported,  
iPDL-parameters-not-available,  
frequency-acquisition-not-supported,  
power-balancing-status-not-compatible,  
requested-typeofbearer-re-arrangement-not-supported,  
signalling-Bearer-Re-arrangement-not-supported,  
bearer-Re-arrangement-needed,  
delayed-activation-not-supported,  
rl-timing-adjustment-not-supported  
}
```

```
CauseTransport ::= ENUMERATED {  
    transport-resource-unavailable,  
    unspecified,  
    ...  
}
```

```
CCTrCH-ID ::= INTEGER (0..15)
```

```
CDSubChannelNumbers ::= BIT STRING {  
    subCh11(0),  
    subCh10(1),  
    subCh9(2),  
    subCh8(3),  
    subCh7(4),  
    subCh6(5),  
    subCh5(6),  
    subCh4(7),  
    subCh3(8),  
    subCh2(9),  
    subCh1(10),  
    subCh0(11)  
} (SIZE (12))
```

```
CellParameterID ::= INTEGER (0..127,...)
```

```
| CellPortionID ::= INTEGER (0..15,...)
```

```
CellSyncBurstCode ::= INTEGER(0..7, ...)
```

```
CellSyncBurstCodeShift ::= INTEGER(0..7)
```

```
CellSyncBurstRepetitionPeriod ::= INTEGER (0..4095)
```

```
CellSyncBurstSIR ::= INTEGER (0..31)
```

```
CellSyncBurstTiming ::= CHOICE {  
    initialPhase      INTEGER (0..1048575),  
    steadyStatePhase  INTEGER (0..255)  
}
```

```
CellSyncBurstTimingThreshold ::= INTEGER(0..254)

CFN ::= INTEGER (0..255)

Channel-Assignment-Indication ::= ENUMERATED {
    cA-Active,
    cA-Inactive
}

ChipOffset ::= INTEGER (0..38399)
-- Unit Chip

C-ID ::= INTEGER (0..65535)

ClosedloopTimingAdjustmentMode ::= ENUMERATED {
    adj-1-slot,
    adj-2-slot,
    ...
}

CommonChannelsCapacityConsumptionLaw ::= SEQUENCE (SIZE(1..maxNrOfSF)) OF
SEQUENCE {
    dl-Cost      INTEGER (0..65535),
    ul-Cost      INTEGER (0..65535),
    iE-Extensions ProtocolExtensionContainer { { CommonChannelsCapacityConsumptionLaw-ExtIEs } } OPTIONAL,
    ...
}

CommonChannelsCapacityConsumptionLaw-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

CommonMeasurementAccuracy ::= CHOICE {
    tUTRANGPSMeasurementAccuracyClass      TUTRANGPSAccuracyClass,
    ...
}

CommonMeasurementType ::= ENUMERATED {
    received-total-wide-band-power,
    transmitted-carrier-power,
    acknowledged-prach-preambles,
    ul-timeslot-iscp,
    acknowledged-PCPCH-access-preambles,
    detected-PCPCH-access-preambles,
    ...,
    uTRAN-GPS-Timing-of-Cell-Frames-for-UE-Positioning,
    sFN-SFN-Observed-Time-Difference,
    transmittedCarrierPowerOfAllCodesNotUsedForHS-PDSCHOrHS-SCCHTransmission
}

CommonMeasurementValue ::= CHOICE {
    transmitted-carrier-power          Transmitted-Carrier-Power-Value,
```

```

received-total-wide-band-power          Received-total-wide-band-power-Value,
acknowledged-prach-preambles          Acknowledged-PRACH-preambles-Value,
uL-TimeslotISCP                      UL-TimeslotISCP-Value,
acknowledged-PCPCH-access-preambles   Acknowledged-PCPCH-access-preambles,
detected-PCPCH-access-preambles      Detected-PCPCH-access-preambles,
...
extension-CommonMeasurementValue      Extension-CommonMeasurementValue
}

Extension-CommonMeasurementValue      ::= ProtocolIE-Single-Container {{ Extension-CommonMeasurementValueIE }}
```

**Extension-CommonMeasurementValueIE NBAP-PROTOCOL-IES** ::= {  
  { ID id-TUTRANGPSMeasurementValueInformation CRITICALITY ignore TYPE TUTRANGPSMeasurementValueInformation PRESENCE mandatory } |  
  { ID id-SFNSFNMeasurementValueInformation CRITICALITY ignore TYPE SFNSFNMeasurementValueInformation PRESENCE mandatory } |  
  { ID id-TransmittedCarrierPowerOfAllCodesNotUsedForHS-PDSCHOrHS-SCCHTransmission CRITICALITY ignore TYPE  
TransmittedCarrierPowerOfAllCodesNotUsedForHS-PDSCHOrHS-SCCHTransmissionValue PRESENCE mandatory }  
}

**CommonMeasurementValueInformation** ::= CHOICE {  
  measurementAvailable CommonMeasurementAvailable,  
  measurementnotAvailable CommonMeasurementnotAvailable  
}

**CommonMeasurementAvailable** ::= SEQUENCE {  
  commonmeasurementValue CommonMeasurementValue,  
  ie-Extensions ProtocolExtensionContainer { { CommonMeasurementAvailableItem-ExtIEs } } OPTIONAL,  
  ...  
}

**CommonMeasurementAvailableItem-ExtIEs NBAP-PROTOCOL-EXTENSION** ::= {  
  ...  
}

**CommonMeasurementnotAvailable** ::= NULL

**CommonPhysicalChannelID** ::= INTEGER (0..255)

**Common-PhysicalChannel-Status-Information** ::= SEQUENCE {  
  commonPhysicalChannelID CommonPhysicalChannelID,  
  resourceOperationalState ResourceOperationalState,  
  availabilityStatus AvailabilityStatus,  
  ie-Extensions ProtocolExtensionContainer { { Common-PhysicalChannel-Status-Information-ExtIEs } } OPTIONAL,  
  ...  
}

**Common-PhysicalChannel-Status-Information-ExtIEs NBAP-PROTOCOL-EXTENSION** ::= {  
  ...  
}

```
CommonTransportChannelID ::= INTEGER (0..255)

CommonTransportChannel-InformationResponse ::= SEQUENCE {
    commonTransportChannelID           CommonTransportChannelID,
    bindingID                         BindingID          OPTIONAL,
    transportLayerAddress             TransportLayerAddress  OPTIONAL,
    iE-Extensions                     ProtocolExtensionContainer { { CommonTransportChannel-InformationResponse-ExtIEs } }  OPTIONAL,
    ...
}

CommonTransportChannel-InformationResponse-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {

}

Common-TransportChannel-Status-Information ::= SEQUENCE {
    commonTransportChannelID           CommonTransportChannelID,
    resourceOperationalState          ResourceOperationalState,
    availabilityStatus                AvailabilityStatus,
    iE-Extensions                     ProtocolExtensionContainer { { Common-TransportChannel-Status-Information-ExtIEs } }  OPTIONAL,
    ...
}

Common-TransportChannel-Status-Information-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {

}

CommunicationControlPortID ::= INTEGER (0..65535)

Compressed-Mode-Deactivation-Flag ::= ENUMERATED {
    deactivate,
    maintain-Active
}

ConfigurationGenerationID ::= INTEGER (0..255)
-- Value '0' means "No configuration"

ConstantValue ::= INTEGER (-10..10,...)
-- -10 dB - +10 dB
-- unit dB
-- step 1 dB

CPCH-Allowed-Total-Rate ::= ENUMERATED {
    v15,
    v30,
    v60,
    v120,
    v240,
    v480,
    v960,
    v1920,
    v2880,
```

```

v3840,
v4800,
v5760,
...
}

CPCHScramblingCodeNumber ::= INTEGER (0..79)

CPCH-UL-DPCCH-SlotFormat ::= INTEGER (0..2,...)

CQI-Feedback-Cycle ::= ENUMERATED {v0, v1, v5, v10, v20, v40, v80,...}

CQI-Power-Offset ::= INTEGER (0..8,...)
-- According to mapping in ref. [9] subclause 4.2.1

CQI-RepetitionFactor ::= INTEGER (1..4,...)
-- Step: 1

CriticalityDiagnostics ::= SEQUENCE {
    procedureID          ProcedureID      OPTIONAL,
    triggeringMessage    TriggeringMessage OPTIONAL,
    procedureCriticality Criticality       OPTIONAL,
    transactionID        TransactionID   OPTIONAL,
    iEsCriticalityDiagnostics CriticalityDiagnostics-IE-List OPTIONAL,
    iE-Extensions         ProtocolExtensionContainer { {CriticalityDiagnostics-ExtIEs} }           OPTIONAL,
    ...
}

CriticalityDiagnostics-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

CriticalityDiagnostics-IE-List ::= SEQUENCE (SIZE (1..maxNrOfErrors)) OF
SEQUENCE {
    iECriticality     Criticality,
    iE-ID              ProtocolIE-ID,
    repetitionNumber0 RepetitionNumber0 OPTIONAL,
    iE-Extensions      ProtocolExtensionContainer { {CriticalityDiagnostics-IE-List-ExtIEs} }           OPTIONAL,
    ...
}

CriticalityDiagnostics-IE-List-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    { ID id-MessageStructure    CRITICALITY ignore    EXTENSION MessageStructure    PRESENCE optional    } |
    { ID id-TypeOfError         CRITICALITY ignore    EXTENSION TypeOfError        PRESENCE mandatory } ,
    ...
}

CRNC-CommunicationContextID ::= INTEGER (0..1048575)

CSBMeasurementID ::= INTEGER (0..65535)

CSBTransmissionID ::= INTEGER (0..65535)

```

```

-- =====
-- D
-- =====

DATA-ID ::= INTEGER (0..3)

DCH-ID ::= INTEGER (0..255)

DCH-FDD-Information ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF DCH-FDD-InformationItem

DCH-FDD-InformationItem ::= SEQUENCE {
    payloadCRC-PresenceIndicator      PayloadCRC-PresenceIndicator,
    ul-FP-Mode                         UL-FP-Mode,
    toAWS                             ToAWS,
    toAWE                             ToAWE,
    dCH-SpecificInformationList        DCH-Specific-FDD-InformationList,
    iE-Extensions                      ProtocolExtensionContainer { { DCH-FDD-InformationItem-ExtIEs} }           OPTIONAL,
    ...
}

DCH-FDD-InformationItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {

    ...
}

DCH-Specific-FDD-InformationList ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF DCH-Specific-FDD-Item

DCH-Specific-FDD-Item ::= SEQUENCE {
    dCH-ID                            DCH-ID,
    ul-TransportFormatSet              TransportFormatSet,
    dl-TransportFormatSet              TransportFormatSet,
    allocationRetentionPriority       AllocationRetentionPriority,
    frameHandlingPriority             FrameHandlingPriority,
    qE-Selector                        QE-Selector,
    iE-Extensions                      ProtocolExtensionContainer { { DCH-Specific-FDD-Item-ExtIEs} }           OPTIONAL,
    ...
}

DCH-Specific-FDD-Item-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {

    ...
}

DCH-InformationResponse ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF DCH-InformationResponseItem

DCH-InformationResponseItem ::= SEQUENCE {
    dCH-ID                            DCH-ID,
    bindingID                         BindingID           OPTIONAL,
    transportLayerAddress              TransportLayerAddress   OPTIONAL,
    iE-Extensions                      ProtocolExtensionContainer { { DCH-InformationResponseItem-ExtIEs} }           OPTIONAL,
    ...
}

DCH-InformationResponseItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {

    ...
}

```

```

}

DCH-TDD-Information ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF DCH-TDD-InformationItem

DCH-TDD-InformationItem ::= SEQUENCE {
    payloadCRC-PresenceIndicator          PayloadCRC-PresenceIndicator,
    ul-FP-Mode                            UL-FP-Mode,
    toAWS                                 ToAWS,
    toAWE                                 ToAWE,
    dCH-SpecificInformationList           DCH-Specific-TDD-InformationList,
    iE-Extensions                         ProtocolExtensionContainer { { DCH-TDD-InformationItem-ExtIEs} }           OPTIONAL,
    ...
}

DCH-TDD-InformationItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

DCH-Specific-TDD-InformationList ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF DCH-Specific-TDD-Item

DCH-Specific-TDD-Item ::= SEQUENCE {
    dCH-ID                               DCH-ID,
    ul-CCTrCH-ID                         CCTrCH-ID,
    dl-CCTrCH-ID                         CCTrCH-ID,
    ul-TransportFormatSet                 TransportFormatSet,
    dl-TransportFormatSet                 TransportFormatSet,
    allocationRetentionPriority          AllocationRetentionPriority,
    frameHandlingPriority                FrameHandlingPriority,
    qE-Selector                           QE-Selector           OPTIONAL,
    -- This IE shall be present if DCH is part of set of Coordinated DCHs
    iE-Extensions                         ProtocolExtensionContainer { { DCH-Specific-TDD-Item-ExtIEs} }           OPTIONAL,
    ...
}

DCH-Specific-TDD-Item-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

FDD-DCHs-to-Modify ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF FDD-DCHs-to-ModifyItem

FDD-DCHs-to-ModifyItem ::= SEQUENCE {
    ul-FP-Mode                           UL-FP-Mode           OPTIONAL,
    toAWS                                ToAWS              OPTIONAL,
    toAWE                                ToAWE              OPTIONAL,
    transportBearerRequestIndicator       TransportBearerRequestIndicator,
    dCH-SpecificInformationList          DCH-ModifySpecificInformation-FDD,
    iE-Extensions                         ProtocolExtensionContainer { { FDD-DCHs-to-ModifyItem-ExtIEs} }           OPTIONAL,
    ...
}

FDD-DCHs-to-ModifyItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

```

```

DCH-ModifySpecificInformation-FDD ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF DCH-ModifySpecificItem-FDD

DCH-ModifySpecificItem-FDD ::= SEQUENCE {
    dCH-ID,
    ul-TransportFormatSet           DCH-ID,
    dl-TransportFormatSet           TransportFormatSet      OPTIONAL,
    allocationRetentionPriority     TransportFormatSet      OPTIONAL,
    frameHandlingPriority          AllocationRetentionPriority OPTIONAL,
    iE-Extensions                   FrameHandlingPriority OPTIONAL,
    ...
    ProtocolExtensionContainer { { DCH-ModifySpecificItem-FDD-ExtIEs} }      OPTIONAL,
}

DCH-ModifySpecificItem-FDD-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

TDD-DCHs-to-Modify ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF DCH-ModifyItem-TDD

DCH-ModifyItem-TDD ::= SEQUENCE {
    ul-FP-Mode                      UL-FP-Mode      OPTIONAL,
    toAWS                           ToAWS         OPTIONAL,
    toAWE                           ToAWE         OPTIONAL,
    transportBearerRequestIndicator TransportBearerRequestIndicator,
    dCH-SpecificInformationList     DCH-ModifySpecificInformation-TDD,
    iE-Extensions                   ProtocolExtensionContainer { { TDD-DCHs-to-ModifyItem-ExtIEs} }      OPTIONAL,
    ...
}

TDD-DCHs-to-ModifyItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

DCH-ModifySpecificInformation-TDD ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF DCH-ModifySpecificItem-TDD

DCH-ModifySpecificItem-TDD ::= SEQUENCE {
    dCH-ID,
    ul-CCTrCH-ID                    CCTrCH-ID      OPTIONAL,
    dl-CCTrCH-ID                    CCTrCH-ID      OPTIONAL,
    ul-TransportFormatSet           TransportFormatSet OPTIONAL,
    dl-TransportFormatSet           TransportFormatSet OPTIONAL,
    allocationRetentionPriority     AllocationRetentionPriority OPTIONAL,
    frameHandlingPriority          FrameHandlingPriority OPTIONAL,
    iE-Extensions                   ProtocolExtensionContainer { { DCH-ModifySpecificItem-TDD-ExtIEs} }      OPTIONAL,
    ...
}

DCH-ModifySpecificItem-TDD-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

DedicatedChannelsCapacityConsumptionLaw ::= SEQUENCE ( SIZE(1..maxNrOfSF) ) OF

```

```

SEQUENCE {
    dl-Cost-1      INTEGER (0..65535),
    dl-Cost-2      INTEGER (0..65535),
    ul-Cost-1      INTEGER (0..65535),
    ul-Cost-2      INTEGER (0..65535),
    iE-Extensions   ProtocolExtensionContainer { { DedicatedChannelsCapacityConsumptionLaw-ExtIEs } }           OPTIONAL,
    ...
}

DedicatedChannelsCapacityConsumptionLaw-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

DedicatedMeasurementType ::= ENUMERATED {
    sir,
    sir-error,
    transmitted-code-power,
    rscp,
    rx-timing-deviation,
    round-trip-time,
    ...,
    rx-timing-deviation-LCR,
    angle-Of-Arrival-LCR,
    hs-sich-quality,
    best-Cell-Portions
}
|_____best-Cell-Portions

DedicatedMeasurementValue ::= CHOICE {
    sIR-Value          SIR-Value,
    sIR-ErrorValue     SIR-Error-Value,
    transmittedCodePowerValue Transmitted-Code-Power-Value,
    rSCP               RSCP-Value,
    rxTimingDeviationValue Rx-Timing-Deviation-Value,
    roundTripTime      Round-Trip-Time-Value,
    ...,
    extension-DedicatedMeasurementValue Extension-DedicatedMeasurementValue
}

Extension-DedicatedMeasurementValue ::= ProtocolIE-Single-Container {{ Extension-DedicatedMeasurementValueIE }}
```

best-Cell-Portions

```

Extension-DedicatedMeasurementValueIE NBAP-PROTOCOL-IES ::= {
    { ID id-Rx-Timing-Deviation-Value-LCR CRITICALITY reject TYPE Rx-Timing-Deviation-Value-LCR PRESENCE mandatory } |
    { ID id-Angle-Of-Arrival-Value-LCR CRITICALITY reject TYPE Angle-Of-Arrival-Value-LCR PRESENCE mandatory } |
    { ID id-HS-SICH-Reception-Quality CRITICALITY reject TYPE HS-SICH-Reception-Quality-Value PRESENCE mandatory } |
    { ID id-Best-Cell-Portions-Value CRITICALITY reject TYPE Best-Cell-Portions-Value PRESENCE mandatory },
    ...
}
```

best-Cell-Portions

```

DedicatedMeasurementValueInformation ::= CHOICE {
```

```
measurementAvailable      DedicatedMeasurementAvailable,
measurementnotAvailable  DedicatedMeasurementnotAvailable
}

DedicatedMeasurementAvailable ::= SEQUENCE {
    dedicatedmeasurementValue   DedicatedMeasurementValue,
    cFN                         CFN           OPTIONAL,
    ie-Extensions                ProtocolExtensionContainer { { DedicatedMeasurementAvailableItem-ExtIEs} }           OPTIONAL,
    ...
}

DedicatedMeasurementAvailableItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {

}

DedicatedMeasurementnotAvailable ::= NULL

DelayedActivation ::= CHOICE {
    cfn            CFN,
    separate-indication  NULL
}

DelayedActivationUpdate ::= CHOICE {
    activate        Activate-Info,
    deactivate     Deactivate-Info
}

Activate-Info ::= SEQUENCE {
    activation-type   Execution-Type,
    initial-dl-tx-power DL-Power,
    firstRLS-Indicator FirstRLS-Indicator
    propagation-delay PropagationDelay
    iE-Extensions     ProtocolExtensionContainer { { Activate-Info-ExtIEs} }
    ...
}

Activate-Info-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {

}

Deactivate-Info ::= SEQUENCE {
    deactivation-type   Execution-Type,
    iE-Extensions       ProtocolExtensionContainer { { Deactivate-Info-ExtIEs} }
    ...
}
```

```
Deactivate-Info-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {  
    ...  
}  
  
Execution-Type ::= CHOICE {  
    synchronised    CFN,  
    unsynchronised  NULL  
}  
  
Detected-PCPCH-access-preambles ::= INTEGER (0..240,...)  
-- According to mapping in [22].  
  
DeltaSIR          ::= INTEGER (0..30)  
-- Unit dB, Step 0.1 dB, Range 0..3 dB.  
  
DGPSCorrections ::= SEQUENCE {  
    gpstow           GPSTOW,  
    status-health    GPS-Status-Health,  
    satelliteinfo   SAT-Info-DGPSCorrections,  
    ie-Extensions    ProtocolExtensionContainer { { DGPSCorrections-ExtIEs} }      OPTIONAL,  
    ...  
}  
  
DGPSCorrections-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {  
    ...  
}  
  
DGPSThresholds ::= SEQUENCE {  
    prcdeviation     PRCDeviation,  
    ie-Extensions    ProtocolExtensionContainer { { DGPSThresholds-ExtIEs} }      OPTIONAL,  
    ...  
}  
  
DGPSThresholds-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {  
    ...  
}  
  
DiversityControlField ::= ENUMERATED {  
    may,  
    must,  
    must-not,  
    ...  
}  
  
DiversityMode ::= ENUMERATED {  
    none,  
    sTTD,  
    closed-loop-mode1,  
    closed-loop-mode2,  
}
```

```

}

DL-DPCH-SlotFormat ::= INTEGER (0..16,...)

DL-DPCH-TimingAdjustment ::= ENUMERATED {
    timing-advance,
    timing-delay
}

DL-Timeslot-Information ::= SEQUENCE (SIZE (1.. maxNrOfDLTSS)) OF DL-Timeslot-InformationItem

DL-Timeslot-InformationItem ::= SEQUENCE {
    timeSlot,
    midambleShiftAndBurstType,
    tFCI-Presence,
    dL-Code-Information,
    iE-Extensions
        ProtocolExtensionContainer { { DL-Timeslot-InformationItem-ExtIEs} } OPTIONAL,
    ...
}

DL-Timeslot-InformationItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

DL-TimeslotLCR-Information ::= SEQUENCE (SIZE (1.. maxNrOfDLTSLCRs)) OF DL-TimeslotLCR-InformationItem

DL-TimeslotLCR-InformationItem ::= SEQUENCE {
    timeSlotLCR,
    midambleShiftLCR,
    tFCI-Presence,
    dL-Code-LCR-Information,
    iE-Extensions
        ProtocolExtensionContainer { { DL-TimeslotLCR-InformationItem-ExtIEs} } OPTIONAL,
    ...
}

DL-TimeslotLCR-InformationItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    { ID id-Initial-DL-Power-TimeslotLCR-InformationItem CRITICALITY ignore EXTENSION DL-Power
        PRESENCE optional } |
    -- Applicable to 1.28Mcps TDD only
    { ID id-Maximum-DL-Power-TimeslotLCR-InformationItem CRITICALITY ignore EXTENSION DL-Power
        PRESENCE optional } |
    -- Applicable to 1.28Mcps TDD only
    { ID id-Minimum-DL-Power-TimeslotLCR-InformationItem CRITICALITY ignore EXTENSION DL-Power
        PRESENCE optional },
    -- Applicable to 1.28Mcps TDD only
    ...
}

DL-FrameType ::= ENUMERATED {
    typeA,
    typeB,
    ...
}

DL-or-Global-CapacityCredit ::= INTEGER (0..65535)

```

```

DL-Power ::= INTEGER (-350..150)
-- Value = DL-Power/10
-- Unit dB, Range -35dB .. +15dB, Step +0.1dB

DLPowerAveragingWindowSize ::= INTEGER (1..60)

DL-PowerBalancing-Information ::= SEQUENCE {
    powerAdjustmentType          PowerAdjustmentType,
    dLReferencePower             DL-Power      OPTIONAL,
    -- This IE shall be present if Power Adjustment Type IE equals to 'Common'
    dLReferencePowerList-DL-PC-Rqst   DL-ReferencePowerInformationList      OPTIONAL,
    -- This IE shall be present if Power Adjustment Type IE equals to 'Individual'
    maxAdjustmentStep            MaxAdjustmentStep      OPTIONAL,
    -- This IE shall be present if Power Adjustment Type IE equals to 'Common' or 'Individual'
    adjustmentPeriod             AdjustmentPeriod      OPTIONAL,
    -- This IE shall be present if Power Adjustment Type IE equals to 'Common' or 'Individual'
    adjustmentRatio              ScaledAdjustmentRatio      OPTIONAL,
    -- This IE shall be present if Power Adjustment Type IE equals to 'Common' or 'Individual'
    iE-Extensions                ProtocolExtensionContainer { { DL-PowerBalancing-Information-ExtIEs } } OPTIONAL,
    ...
}

DL-PowerBalancing-Information-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

DL-ReferencePowerInformationList      ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF DL-ReferencePowerInformationItem

DL-ReferencePowerInformationItem ::= SEQUENCE {
    rL-ID                      RL-ID,
    dl-Reference-Power          DL-Power,
    iE-Extensions               ProtocolExtensionContainer { {DL-ReferencePowerInformationItem-ExtIEs} } OPTIONAL,
    ...
}

DL-ReferencePowerInformationItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

DL-PowerBalancing-ActivationIndicator ::= ENUMERATED {
    dL-PowerBalancing-Activated
}

DL-PowerBalancing-UpdatedIndicator  ::= ENUMERATED {
    dL-PowerBalancing-Updated
}

DL-ScramblingCode ::= INTEGER (0..15)
-- 0= Primary scrambling code of the cell, 1..15= Secondary scrambling code --

DL-TimeslotISCP ::= INTEGER (0..91)

```

```

DL-TimeslotISCPInfo ::= SEQUENCE (SIZE (1..maxNrOfDLTSS)) OF DL-TimeslotISCPInfoItem

DL-TimeslotISCPInfoItem ::= SEQUENCE {
    timeSlot                      TimeSlot,
    dL-TimeslotISCP                DL-TimeslotISCP,
    iE-Extensions                  ProtocolExtensionContainer { {DL-TimeslotISCPInfoItem-ExtIEs} }
                                            OPTIONAL,
    ...
}

DL-TimeslotISCPInfoItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

DL-TimeslotISCPInfoLCR ::= SEQUENCE (SIZE (1..maxNrOfDLTSLCRs)) OF DL-TimeslotISCPInfoItemLCR

DL-TimeslotISCPInfoItemLCR ::= SEQUENCE {
    timeSlotLCR                    TimeSlotLCR,
    dL-TimeslotISCP                DL-TimeslotISCP,
    iE-Extensions                  ProtocolExtensionContainer { {DL-TimeslotISCPInfoItemLCR-ExtIEs} }
                                            OPTIONAL,
    ...
}

DL-TimeslotISCPInfoItemLCR-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

DL-TPC-Pattern01Count ::= INTEGER (0..30,...)

Downlink-Compressed-Mode-Method      ::= ENUMERATED {
    puncturing,
    sFdiv2,
    higher-layer-scheduling,
    ...
}

DPC-Mode ::= ENUMERATED {
    mode0,
    mode1,
    ...
}

DPCH-ID ::= INTEGER (0..239)

DSCH-ID ::= INTEGER (0..255)

DSCH-InformationResponse ::= SEQUENCE (SIZE (1..maxNrOfDSCHs)) OF DSCH-InformationResponseItem

DSCH-InformationResponseItem ::= SEQUENCE {
    dSCH-ID                         DSCH-ID,
    bindingID                       BindingID
                                            OPTIONAL,
    transportLayerAddress           TransportLayerAddress
                                            OPTIONAL,
    ...
}

```

```

iE-Extensions
...
}

ProtocolExtensionContainer { { DSCH-InformationResponseItem-ExtIEs } } OPTIONAL,
DSCH-InformationResponseItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
...
}

DSCH-FDD-Common-Information ::= SEQUENCE {
    enhancedDSCHPCIndicator EnhancedDSCHPCIndicator OPTIONAL,
    enhancedDSCHPC EnhancedDSCHPC OPTIONAL,
    -- The IE shall be present if the Enhanced DSCH PC Indicator IE is set to "Enhanced DSCH PC Active in the UE".
    iE-Extensions ProtocolExtensionContainer { { DSCH-FDD-Common-Information-ExtIEs } } OPTIONAL,
...
}

DSCH-FDD-Common-Information-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
...
}

DSCH-FDD-Information ::= SEQUENCE (SIZE (1..maxNrOfDSCHs)) OF DSCH-FDD-InformationItem

DSCH-FDD-InformationItem ::= SEQUENCE {
    dSCH-ID DSCH-ID,
    transportFormatSet TransportFormatSet,
    allocationRetentionPriority AllocationRetentionPriority,
    frameHandlingPriority FrameHandlingPriority,
    toAWS ToAWS,
    toAWE ToAWE,
    iE-Extensions ProtocolExtensionContainer { { DSCH-FDD-InformationItem-ExtIEs } } OPTIONAL,
...
}

DSCH-FDD-InformationItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    { ID id-bindingID CRITICALITY ignore EXTENSION BindingID PRESENCE optional } |
    { ID id-transportlayeraddress CRITICALITY ignore EXTENSION TransportLayerAddress PRESENCE optional },
...
}

DSCH-TDD-Information ::= SEQUENCE (SIZE (1..maxNrOfDSCHs)) OF DSCH-TDD-InformationItem

DSCH-TDD-InformationItem ::= SEQUENCE {
    dSCH-ID DSCH-ID,
    cCTrCH-ID CCTrCH-ID,
    transportFormatSet TransportFormatSet,
    allocationRetentionPriority AllocationRetentionPriority,
    frameHandlingPriority FrameHandlingPriority,
    toAWS ToAWS,
    toAWE ToAWE,
    iE-Extensions ProtocolExtensionContainer { { DSCH-TDD-InformationItem-ExtIEs } } OPTIONAL,
...
}

```

```

DSCH-TDD-InformationItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
  { ID id-bindingID           CRITICALITY ignore      EXTENSION BindingID      PRESENCE      optional }|
  { ID id-transportlayeraddress CRITICALITY ignore    EXTENSION TransportLayerAddress PRESENCE      optional },
  ...
}

DwPCH-Power ::= ENUMERATED {minus10, minus9, minus8, minus7, minus6, minus5, minus4, minus3, minus2, minus1, zero, plus1, plus2, plus3, plus4, plus5, ...}

/* partly omitted */

-- =====
-- P
-- =====

PagingIndicatorLength ::= ENUMERATED {
  v2,
  v4,
  v8,
  ...
}

PayloadCRC-PresenceIndicator ::= ENUMERATED {
  cRC-Included,
  cRC-NotIncluded,
  ...
}

PCCPCH-Power ::= INTEGER (-150..400,...)
-- PCCPCH-power = power * 10
-- If power <= -15 PCCPCH shall be set to -150
-- If power >= 40 PCCPCH shall be set to 400
-- Unit dBm, Range -15dBm .. +40 dBm, Step +0.1dB

PCP-Length ::= ENUMERATED{
  v0,
  v8
}

PDSCH-CodeMapping ::= SEQUENCE {
  dl-ScramblingCode,
  signallingMethod          CHOICE {
    code-Range               PDSCH-CodeMapping-PDSCH-CodeMappingInformationList,
    tFCI-Range                PDSCH-CodeMapping-DSCH-MappingInformationList,
    explicit                  PDSCH-CodeMapping-PDSCH-CodeInformationList,
    ...,
    replace                  PDSCH-CodeMapping-ReplacedPDSCH-CodeInformationList
  },
  iE-Extensions             ProtocolExtensionContainer { { PDSCH-CodeMapping-ExtIEs} }
  ...
}

PDSCH-CodeMapping-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {

```

```
...
}

PDSCH-CodeMapping-CodeNumberComp ::= INTEGER (0..maxCodeNrComp-1)

PDSCH-CodeMapping-SpreadingFactor ::= ENUMERATED {
    v4,
    v8,
    v16,
    v32,
    v64,
    v128,
    v256,
    ...
}

PDSCH-CodeMapping-PDSCH-CodeMappingInformationList ::= SEQUENCE (SIZE (1..maxNrOfCodeGroups)) OF
SEQUENCE {
    spreadingFactor      PDSCH-CodeMapping-SpreadingFactor,
    multi-CodeInfo       PDSCH-Multi-CodeInfo,
    start-CodeNumber     PDSCH-CodeMapping-CodeNumberComp,
    stop-CodeNumber      PDSCH-CodeMapping-CodeNumberComp,
    iE-Extensions        ProtocolExtensionContainer { { PDSCH-CodeMapping-PDSCH-CodeMappingInformationList-ExtIEs} } OPTIONAL,
    ...
}

PDSCH-CodeMapping-PDSCH-CodeMappingInformationList-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

PDSCH-CodeMapping-DSCH-MappingInformationList ::= SEQUENCE (SIZE (1..maxNrOfTFCIGroups)) OF
SEQUENCE {
    maxTFCI-field2-Value   PDSCH-CodeMapping-MaxTFCI-Field2-Value,
    spreadingFactor        PDSCH-CodeMapping-SpreadingFactor,
    multi-CodeInfo         PDSCH-Multi-CodeInfo,
    codeNumber              PDSCH-CodeMapping-CodeNumberComp,
    iE-Extensions          ProtocolExtensionContainer { { PDSCH-CodeMapping-DSCH-MappingInformationList-ExtIEs} } OPTIONAL,
    ...
}

PDSCH-CodeMapping-DSCH-MappingInformationList-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

PDSCH-CodeMapping-MaxTFCI-Field2-Value ::= INTEGER (1..1023)

PDSCH-CodeMapping-PDSCH-CodeInformationList ::= SEQUENCE (SIZE (1..maxNrOfTFCI2Combs)) OF
SEQUENCE {
    spreadingFactor        PDSCH-CodeMapping-SpreadingFactor,
    multi-CodeInfo         PDSCH-Multi-CodeInfo,
    codeNumber              PDSCH-CodeMapping-CodeNumberComp,
    iE-Extensions          ProtocolExtensionContainer { { PDSCH-CodeMapping-PDSCH-CodeInformationList-ExtIEs} } OPTIONAL,
    ...
}
```

```
}
```

PDSCH-CodeMapping-PDSCH-CodeInformationList-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {  
 ...  
}

PDSCH-CodeMapping-ReplacedPDSCH-CodeInformationList ::= SEQUENCE (SIZE (1..maxNrOfTFCI2Combs)) OF  
SEQUENCE {  
 tfci-Field2 TFCS-MaxTFCI-field2-Value,  
 spreadingFactor PDSCH-CodeMapping-SpreadFactor,  
 multi-CodeInfo PDSCH-Multi-CodeInfo,  
 codeNumber PDSCH-CodeMapping-CodeNumberComp,  
 iE-Extensions ProtocolExtensionContainer { { PDSCH-CodeMapping-ReplacedPDSCH-CodeInformationList-ExtIEs } } OPTIONAL,  
 ...  
}

PDSCH-CodeMapping-ReplacedPDSCH-CodeInformationList-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {  
 ...  
}

PDSCH-Multi-CodeInfo ::= INTEGER (1..16)

PDSCH-ID ::= INTEGER (0..255)

PDSCHSet-ID ::= INTEGER (0..255)

PICH-Mode ::= ENUMERATED {  
 v18,  
 v36,  
 v72,  
 v144,  
 ...  
}

PICH-Power ::= INTEGER (-10..5)  
-- Unit dB, Range -10dB .. +5dB, Step +1dB

PowerAdjustmentType ::= ENUMERATED {  
 none,  
 common,  
 individual  
}

PowerOffset ::= INTEGER (0..24)  
-- PowerOffset = offset \* 0.25  
-- Unit dB, Range 0dB .. +6dB, Step +0.25dB

PowerRaiseLimit ::= INTEGER (0..10)

PRACH-Midamble ::= ENUMERATED {  
 inverted,  
 direct,  
 ...  
}

```
}
```

PRC ::= INTEGER (-2047..2047)  
--pseudo range correction; scaling factor 0.32 meters

PRCDeviation ::= ENUMERATED {  
 one,  
 two,  
 five,  
 ten,  
 ...  
}

PreambleSignatures ::= BIT STRING {  
 signature15(0),  
 signature14(1),  
 signature13(2),  
 signature12(3),  
 signature11(4),  
 signature10(5),  
 signature9(6),  
 signature8(7),  
 signature7(8),  
 signature6(9),  
 signature5(10),  
 signature4(11),  
 signature3(12),  
 signature2(13),  
 signature1(14),  
 signature0(15)  
} (SIZE (16))

PreambleThreshold ::= INTEGER (0..72)  
-- 0= -36.0dB, 1= -35.5dB, ... , 72= 0.0dB

PredictedSFNSFNDeviationLimit ::= INTEGER (1..256)  
-- Unit chip, Step 1/16 chip, Range 1/16..16 chip

PredictedTUTRANGPSDeviationLimit ::= INTEGER (1..256)  
-- Unit chip, Step 1/16 chip, Range 1/16..16 chip

Pre-emptionCapability ::= ENUMERATED {  
 shall-not-trigger-pre-emption,  
 may-trigger-pre-emption  
}

Pre-emptionVulnerability ::= ENUMERATED {  
 not-pre-emptable,  
 pre-emptable  
}

PrimaryCPICH-Power ::= INTEGER(-100..500)  
-- step 0.1 (Range -10.0..50.0) Unit is dBm

```

Primary-CPICH-Usage-for-Channel-Estimation ::= ENUMERATED {
    primary-CPICH-may-be-used,
    primary-CPICH-shall-not-be-used
}

PrimaryScramblingCode ::= INTEGER (0..511)

PriorityLevel          ::= INTEGER (0..15)
-- 0 = spare, 1 = highest priority, ...14 = lowest priority and 15 = no priority

PriorityQueue-Id ::= INTEGER (0..maxNrOfPriorityQueues-1)

PriorityQueue-InfoList ::= SEQUENCE (SIZE (1..maxNrOfPriorityQueues)) OF PriorityQueue-InfoItem

PriorityQueue-InfoItem ::= SEQUENCE {
    priorityQueueId           PriorityQueue-Id,
    schedulingPriorityIndicator SchedulingPriorityIndicator,
    t1                         T1,
    mAC-hsWindowSize           MAC-hsWindowSize,
    mAChsGuaranteedBitRate     MAChsGuaranteedBitRate
                                OPTIONAL,
    macdPDU-Size-Index         MACdPDU-Size-Indexlist,
    iE-Extensions              ProtocolExtensionContainer { { PriorityQueue-InfoItem-ExtIEs} }
                                OPTIONAL,
    ...
}

PriorityQueue-InfoItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

PriorityQueue-InfoList-to-Modify ::= SEQUENCE (SIZE (1..maxNrOfPriorityQueues)) OF PriorityQueue-InfoItem-to-Modify

PriorityQueue-InfoItem-to-Modify ::= SEQUENCE {
    priorityQueueId           PriorityQueue-Id,
    schedulingPriorityIndicator SchedulingPriorityIndicator
                                OPTIONAL,
    t1                         T1
                                OPTIONAL,
    mAC-hsWindowSize           MAC-hsWindowSize
                                OPTIONAL,
    mAChsGuaranteedBitRate     MAChsGuaranteedBitRate
                                OPTIONAL,
    macdPDU-Size-Index-to-Modify MACdPDU-Size-Indexlist-to-Modify
                                OPTIONAL,
    iE-Extensions              ProtocolExtensionContainer { { PriorityQueue-InfoItem-to-Modify-ExtIEs} }
                                OPTIONAL,
    ...
}

PriorityQueue-InfoItem-to-Modify-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

PrimaryCCPCH-RSCP ::= INTEGER (0..91)

PropagationDelay ::= INTEGER (0..255)
-- Unit: chips, step size 3 chips
-- example: 0 = 0chip, 1 = 3chips

```

```

SCH-TimeSlot ::= INTEGER (0..6)

PunctureLimit ::= INTEGER (0..15)
-- 0: 40%; 1: 44%; ... 14: 96%; 15: 100%

PUSCH-ID ::= INTEGER (0..255)

PUSCHSet-ID ::= INTEGER (0..255)

/* partly omitted */

-- =====
-- S
-- =====

AdjustmentPeriod ::= INTEGER(1..256)
-- Unit Frame

SAT-ID ::= INTEGER (0..63)

SAT-Info-Almanac ::= SEQUENCE (SIZE (1..maxNoSat)) OF SAT-Info-Almanac-Item

SAT-Info-Almanac-Item ::= SEQUENCE {
    data-id          DATA-ID,
    sat-id           SAT-ID,
    gps-e-alm       BIT STRING (SIZE (16)),
    gps-toa-alm     BIT STRING (SIZE (8)),
    gps-delta-I-alm BIT STRING (SIZE (16)),
    omegadot-alm   BIT STRING (SIZE (16)),
    svhealth-alm   BIT STRING (SIZE (8)),
    gps-a-sqrt-alm BIT STRING (SIZE (24)),
    omegazero-alm  BIT STRING (SIZE (24)),
    m-zero-alm     BIT STRING (SIZE (24)),
    gps-omega-alm  BIT STRING (SIZE (24)),
    gps-af-zero-alm BIT STRING (SIZE (11)),
    gps-af-one-alm BIT STRING (SIZE (11)),
    ie-Extensions   ProtocolExtensionContainer { { SAT-Info-Almanac-Item-ExtIEs } }      OPTIONAL,
    ...
}

SAT-Info-Almanac-Item-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

SAT-Info-DGPSCorrections ::= SEQUENCE (SIZE (1..maxNoSat)) OF SAT-Info-DGPSCorrections-Item

SAT-Info-DGPSCorrections-Item ::= SEQUENCE {
    sat-id           SAT-ID,
    iode-dgps       BIT STRING (SIZE (8)),
    udre            UDRE,
    prc             PRC,
    range-correction-rate Range-Correction-Rate,
}

```

```
ie-Extensions
...
}

SAT-Info-DGPSCorrections-Item-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

SAT-Info-RealTime-Integrity ::= SEQUENCE (SIZE (1..maxNoSat)) OF SAT-Info-RealTime-Integrity-Item

SAT-Info-RealTime-Integrity-Item ::= SEQUENCE {
    bad-sat-id      SAT-ID,
    ie-Extensions   ProtocolExtensionContainer { { SAT-Info-RealTime-Integrity-Item-ExtIEs} }           OPTIONAL,
    ...
}

SAT-Info-RealTime-Integrity-Item-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

ScaledAdjustmentRatio      ::= INTEGER(0..100)
-- AdjustmentRatio = ScaledAdjustmentRatio / 100

MaxAdjustmentStep          ::= INTEGER(1..10)
-- Unit Slot

SchedulingPriorityIndicator ::= INTEGER (0..15)      -- lowest (0), highest (15)

SID ::= INTEGER (0..maxNrOfMACdPDUIIndexes-1)

ScramblingCodeNumber ::= INTEGER (0..15)

Secondary-CPICH-Information-Change ::= CHOICE {
    new-secondary-CPICH      CommonPhysicalChannelID,
    secondary-CPICH-shall-not-be-used  NULL,
    ...
}

SecondaryCCPCH-SlotFormat ::= INTEGER(0..17,...)

Segment-Type ::= ENUMERATED {
    first-segment,
    first-segment-short,
    subsequent-segment,
    last-segment,
    last-segment-short,
    complete-SIB,
    complete-SIB-short,
    ...
}
```

```

S-FieldLength ::= ENUMERATED {
    v1,
    v2,
    ...
}

SFN ::= INTEGER (0..4095)

SFNSFN-FDD ::= INTEGER (0..614399)

SFNSFN-TDD ::= INTEGER (0..40961)

SFNSFNChangeLimit ::= INTEGER (1..256)
-- Unit chip, Step 1/16 chip, Range 1/16..16 chip

SFNSFNDriftRate ::= INTEGER (-100..100)
-- Unit chip/s, Step 1/256 chip/s, Range -100/256..+100/256 chip/s

SFNSFNDriftRateQuality ::= INTEGER (0..100)
-- Unit chip/s, Step 1/256 chip/s, Range 0..100/256 chip/s

SFNSFNMeasurementThresholdInformation ::= SEQUENCE {
    SFNSFNChangeLimit          SFNSFNChangeLimit      OPTIONAL,
    predictedSFNSFNDeviationLimit PredictedSFNSFNDeviationLimit OPTIONAL,
    iE-Extensions               ProtocolExtensionContainer { { SFNSFNMeasurementThresholdInformation-ExtIEs} }      OPTIONAL,
    ...
}

SFNSFNMeasurementThresholdInformation-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

SFNSFNMeasurementValueInformation ::= SEQUENCE {
    successfullNeighbouringCellSFNSFNObservedTimeDifferenceMeasurementInformation
        SEQUENCE (SIZE(1..maxNrOfMeasNCell)) OF
        SEQUENCE {
            uC-Id,
            SFNSFNValue,
            SFNSFNQuality           OPTIONAL,
            SFNSFNDriftRate,
            SFNSFNDriftRateQuality   OPTIONAL,
            SFNSFNTimeStampInformation SFNSFNTimeStampInformation,
            iE-Extensions             ProtocolExtensionContainer { { SuccessfullNeighbouringCellsSFNSFNObservedTimeDifferenceMeasurementInformationItem-ExtIEs} }      OPTIONAL,
            ...
        },
    unsuccessfullNeighbouringCellsSFNSFNObservedTimeDifferenceMeasurementInformation
        SEQUENCE (SIZE(0..maxNrOfMeasNCell-1)) OF
        SEQUENCE {
            uC-Id,
            iE-Extensions             ProtocolExtensionContainer { { UnsuccessfullNeighbouringCellsSFNSFNObservedTimeDifferenceMeasurementInformationItem-ExtIEs} }      OPTIONAL,
        }
}

```

```
        },
        ...
    iE-Extensions      ProtocolExtensionContainer { { SFNSFNMeasurementValueInformationItem-ExtIEs } }           OPTIONAL,
    ...
}

SFNSFNMeasurementValueInformationItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

SuccessfullNeighbouringCellsSFNSFNObservedTimeDifferenceMeasurementInformationItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

UnsuccessfullNeighbouringCellsSFNSFNObservedTimeDifferenceMeasurementInformationItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

SFNSFQuality ::= INTEGER (0..255)
-- Unit chip, Step 1/16 chip, Range 0.. 255/16 chip

ShutdownTimer ::= INTEGER (1..3600)
-- Unit sec

SIB-Originator ::= ENUMERATED {
    nodeB,
    cRNC,
    ...
}

SIR-Error-Value ::= INTEGER (0..125)
-- According to mapping in [22]

SFNSFNTimeStampInformation ::= CHOICE {
    SFNSFNTimeStamp-FDD     SFN,
    SFNSFNTimeStamp-TDD     SFNSFNTimeStamp-TDD,
    ...
}

SFNSFNTimeStamp-TDD ::= SEQUENCE {
    sFN                  SFN,
    timeSlot             TimeSlot,
    iE-Extensions        ProtocolExtensionContainer { { SFNSFNTimeStamp-ExtIEs } }           OPTIONAL,
    ...
}

SFNSFNTimeStamp-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}
```

```
}

SFNSFNValue ::= CHOICE {
    SFNSFN-FDD      SFNSFN-FDD,
    SFNSFN-TDD      SFNSFN-TDD,
    ...
}
SIR-Error-Value-IncrDecrThres ::= INTEGER (0..124)

SIR-Value ::= INTEGER (0..63)
-- According to mapping in [22]/[23]

SIR-Value-IncrDecrThres ::= INTEGER (0..62)

SignallingBearerRequestIndicator ::= ENUMERATED {bearerRequested}

SpecialBurstScheduling ::= INTEGER (1..256)

SSDT-Cell-Identity ::= ENUMERATED {a, b, c, d, e, f, g, h}

SSDT-CellID-Length ::= ENUMERATED {
    short,
    medium,
    long
}

SSDT-Indication ::= ENUMERATED {
    ssdt-active-in-the-UE,
    ssdt-not-active-in-the-UE
}

Start-Of-Audit-Sequence-Indicator ::= ENUMERATED {
    start-of-audit-sequence,
    not-start-of-audit-sequence
}

STTD-Indicator ::= ENUMERATED {
    active,
    inactive,
    ...
}

SSDT-SupportIndicator ::= ENUMERATED {
    sSDT-Supported,
    sSDT-not-supported
}

SyncCase ::= INTEGER (1..2,...)

SYNCDlCodeId ::= INTEGER (1..32,...)
```

```

SyncFrameNumber ::= INTEGER (1..10)

SynchronisationReportCharacteristics ::= SEQUENCE {
    synchronisationReportCharacteristicsType      SynchronisationReportCharacteristicsType,
    synchronisationReportCharactThreExc          SynchronisationReportCharactThreExc      OPTIONAL,
    -- This IE shall be included if the synchronisationReportCharacteristicsType IE is set to "thresholdExceeding".
    iE-Extensions                                ProtocolExtensionContainer { { SynchronisationReportCharacteristics-ExtIEs } } OPTIONAL,
    ...
}

SynchronisationReportCharacteristics-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    { ID id-SyncDLCodeIdThreInfoLCR CRITICALITY ignore EXTENSION      SyncDLCodeIdThreInfoLCR      PRESENCE optional },
    ...
}

SynchronisationReportCharactThreExc ::=      SEQUENCE (SIZE (1..maxNrOfCellSyncBursts)) OF SynchronisationReportCharactThreInfoItem -- Mandatory for
3.84Mcps TDD only

SynchronisationReportCharactThreInfoItem ::= SEQUENCE {
    syncFrameNumber           SyncFrameNumber,
    cellSyncBurstInformation SEQUENCE (SIZE (1.. maxNrOfReceiptsPerSyncFrame)) OF SynchronisationReportCharactCellSyncBurstInfoItem,
    iE-Extensions             ProtocolExtensionContainer { { SynchronisationReportCharactThreInfoItem-ExtIEs } }      OPTIONAL,
    ...
}

SynchronisationReportCharactThreInfoItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

SynchronisationReportCharactCellSyncBurstInfoItem ::= SEQUENCE {
    cellSyncBurstCode          CellSyncBurstCode,
    cellSyncBurstCodeShift     CellSyncBurstCodeShift,
    cellSyncBurstTiming        CellSyncBurstTiming      OPTIONAL,
    cellSyncBurstTimingThreshold CellSyncBurstTimingThreshold      OPTIONAL,
    iE-Extensions               ProtocolExtensionContainer { { SynchronisationReportCharactCellSyncBurstInfoItem-ExtIEs } }      OPTIONAL,
    ...
}

SynchronisationReportCharactCellSyncBurstInfoItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

SyncDLCodeIdThreInfoLCR ::= SEQUENCE (SIZE (0..maxNrOfSyncFramesLCR)) OF SyncDLCodeIdThreInfoList --Mandatory for 1.28Mcps TDD only

SyncDLCodeIdThreInfoList ::= SEQUENCE {
    syncFrameNoToReceive         SyncFrameNumber,
    syncDLCodeIdInfoLCR          SyncDLCodeInfoListLCR,
    iE-Extensions                ProtocolExtensionContainer { { SyncDLCodeIdThreInfoList-ExtIEs } }      OPTIONAL,
    ...
}

SyncDLCodeIdThreInfoList-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

```

```
...
}

SyncDLCodeInfoListLCR ::= SEQUENCE (SIZE (1..maxNrOfSyncDLCodesLCR)) OF SyncDLCodeInfoItemLCR

SyncDLCodeInfoItemLCR ::= SEQUENCE {
    syncDLCODEId           SYNCDLCodeId,
    syncDLCODEIdArrivTime   CellSyncBurstTiming      OPTIONAL,
    syncDLCODEIdTimingThre  CellSyncBurstTimingThreshold OPTIONAL,
    iE-Extensions           ProtocolExtensionContainer { { SyncDLCodeInfoItem-LCR-ExtIEs } }      OPTIONAL,
    ...
}

SyncDLCodeInfoItem-LCR-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {

}

SynchronisationReportCharacteristicsType ::= ENUMERATED {
    frameRelated,
    sFNperiodRelated,
    cycleLengthRelated,
    thresholdExceeding,
    frequencyAcquisitionCompleted,
    ...
}

SynchronisationReportType ::= ENUMERATED {
    initialPhase,
    steadyStatePhase,
    lateEntrantCell,
    frequencyAcquisition,
    ...
}

/* partly omitted */

-- =====
-- U
-- =====

UARFCN ::= INTEGER (0..16383, ...)
-- corresponds to 1885.2MHz .. 2024.8MHz

UC-Id ::= SEQUENCE {
    rNC-ID          RNC-ID,
    c-ID            C-ID,
    iE-Extensions   ProtocolExtensionContainer { {UC-Id-ExtIEs} } OPTIONAL,
    ...
}

UC-Id-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}
```

```

UDRE ::= ENUMERATED {
    udre-minusequal-one-m,
    udre-betweenoneandfour-m,
    udre-betweenfourandeight-m,
    udre-greaterequaleight-m
}

UE-Capability-InformationFDD ::= SEQUENCE {
    hSDSCH-TrCH-Bits-Per-HSDSCH-TTI      ENUMERATED {v7300, v14600, v20456, v28800,...},
    hSDSCH-Multi-Code-Capability          ENUMERATED {v5, v10, v15,...},
    min-Inter-TTI-Interval                INTEGER (1..3,...),
    mAChs-Reordering-Buffer-Size         INTEGER (1..300,...),
    iE-Extensions                         ProtocolExtensionContainer { { UE-Capability-InformationFDD-ExtIEs } }           OPTIONAL,
    ...
}

UE-Capability-InformationFDD-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

UE-Capability-InformationTDD ::= SEQUENCE {
    hSDSCHTrCHBitsPerTTI                 ENUMERATED { v7040, v10228, v14080, ... },
    hSDSCH-Multi-Code-Capability          ENUMERATED {v8, v12, v16,...},
    mAChs-Reordering-Buffer-Size         INTEGER (1..300,...),
    iE-Extensions                         ProtocolExtensionContainer { { UE-Capability-InformationTDD-ExtIEs } }           OPTIONAL,
    ...
}

UE-Capability-InformationTDD-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation ::= ENUMERATED {
    dedicated-pilots-for-channel-estimation-supported
}

UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH ::= ENUMERATED {
    dedicated-pilots-for-channel-estimation-supported
}

UL-CapacityCredit ::= INTEGER (0..65535)

UL-DL-mode ::= ENUMERATED {
    ul-only,
    dl-only,
    both-ul-and-dl
}

Uplink-Compressed-Mode-Method ::= ENUMERATED {
}

```

```

sFdiv2,
higher-layer-scheduling,
...
}

UL-Timeslot-Information ::= SEQUENCE (SIZE (1..maxNrOfULTSs)) OF UL-Timeslot-InformationItem

UL-Timeslot-InformationItem ::= SEQUENCE {
    timeSlot                                TimeSlot,
    midambleShiftAndBurstType                MidambleShiftAndBurstType,
    tFCI-Presence                            TFCI-Presence,
    uL-Code-InformationList                 TDD-UL-Code-Information,
    iE-Extensions                            ProtocolExtensionContainer { { UL-Timeslot-InformationItem-ExtIEs} }      OPTIONAL,
    ...
}

UL-Timeslot-InformationItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

UL-TimeslotLCR-Information ::= SEQUENCE (SIZE (1..maxNrOfULTSLCRs)) OF UL-TimeslotLCR-InformationItem

UL-TimeslotLCR-InformationItem ::= SEQUENCE {
    timeSlotLCR                             TimeSlotLCR,
    midambleShiftLCR                         MidambleShiftLCR,
    tFCI-Presence                            TFCI-Presence,
    uL-Code-InformationList                 TDD-UL-Code-LCR-Information,
    iE-Extensions                            ProtocolExtensionContainer { { UL-TimeslotLCR-InformationItem-ExtIEs} }      OPTIONAL,
    ...
}

UL-TimeslotLCR-InformationItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

UL-DPCCCH-SlotFormat ::= INTEGER (0..5,...)

UL-SIR ::= INTEGER (-82..173)
-- According to mapping in [16]

UL-FP-Mode ::= ENUMERATED {
    normal,
    silent,
    ...
}

UL-PhysCH-SF-Variation ::= ENUMERATED {
    sf-variation-supported,
    sf-variation-not-supported
}

UL-ScramblingCode ::= SEQUENCE {

```

```

uL-ScramblingCodeNumber          UL-ScramblingCodeNumber,
uL-ScramblingCodeLength          UL-ScramblingCodeLength,
iE-Extensions                     ProtocolExtensionContainer { { UL-ScramblingCode-ExtIEs } }
...                                OPTIONAL,
}

UL-ScramblingCode-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
  ...
}

UL-ScramblingCodeNumber ::= INTEGER (0..16777215)

UL-ScramblingCodeLength ::= ENUMERATED {
  short,
  long
}

UL-Synchronisation-Parameters-LCR ::= SEQUENCE {
  uL-Synchronisation-StepSize      UL-Synchronisation-StepSize,
  uL-Synchronisation-Frequency    UL-Synchronisation-Frequency,
  iE-Extensions                   ProtocolExtensionContainer { { UL-Synchronisation-Parameters-LCR-ExtIEs } }
...                                OPTIONAL,
}
}

UL-Synchronisation-Parameters-LCR-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
  ...
}

UL-Synchronisation-StepSize ::= INTEGER (1..8)

UL-Synchronisation-Frequency ::= INTEGER (1..8)

UL-TimeSlot-ISCP-Info ::= SEQUENCE (SIZE (1..maxNrOfULTSs)) OF UL-TimeSlot-ISCP-InfoItem

UL-TimeSlot-ISCP-InfoItem ::= SEQUENCE {
  timeSlot                      TimeSlot,
  iSCP                          UL-TimeslotISCP-Value,
  iE-Extensions                 ProtocolExtensionContainer { { UL-TimeSlot-ISCP-InfoItem-ExtIEs } }
...                                OPTIONAL,
}
}

UL-TimeSlot-ISCP-InfoItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
  ...
}

UL-TimeSlot-ISCP-LCR-Info ::= SEQUENCE (SIZE (1..maxNrOfULTSLCRs)) OF UL-TimeSlot-ISCP-LCR-InfoItem

UL-TimeSlot-ISCP-LCR-InfoItem ::= SEQUENCE {
  timeSlotLCR                    TimeSlotLCR,
  iSCP                          UL-TimeslotISCP-Value,
  iE-Extensions                 ProtocolExtensionContainer { { UL-TimeSlot-ISCP-LCR-InfoItem-ExtIEs } }
...                                OPTIONAL,
}
}

```

```

UL-TimeSlot-ISCP-LCR-InfoItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

USCH-Information ::= SEQUENCE (SIZE (1..maxNrOfUSCHs)) OF USCH-InformationItem

USCH-InformationItem ::= SEQUENCE {
    uSCH-ID,
    cCTrCH-ID,
    transportFormatSet,
    allocationRetentionPriority,
    iE-Extensions
        ProtocolExtensionContainer { { USCH-InformationItem-ExtIEs} } OPTIONAL,
    ...
}

USCH-InformationItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    { ID id-bindingID           CRITICALITY ignore      EXTENSION BindingID          PRESENCE optional } |
    { ID id-transportlayeraddress CRITICALITY ignore      EXTENSION TransportLayerAddress PRESENCE optional },
    ...
}

USCH-InformationResponse ::= SEQUENCE (SIZE (1..maxNrOfUSCHs)) OF USCH-InformationResponseItem

USCH-InformationResponseItem ::= SEQUENCE {
    uSCH-ID,
    bindingID           OPTIONAL,
    transportLayerAddress OPTIONAL,
    iE-Extensions
        ProtocolExtensionContainer { { USCH-InformationResponseItem-ExtIEs} } OPTIONAL,
    ...
}

USCH-InformationResponseItem-ExtIEs NBAP-PROTOCOL-EXTENSION ::= {
    ...
}

UL-TimeslotISCP-Value ::= INTEGER (0..127)
-- According to mapping in [23]

UL-TimeslotISCP-Value-IncrDecrThres ::= INTEGER (0..126)

USCH-ID ::= INTEGER (0..255)

/* partly omitted */

```

### 9.3.6 Constant Definitions

```
-- ****
-- Constant definitions
-- ****

NBAP-Constants {
    itu-t (0) identified-organization (4) etsi (0) mobileDomain (0)
    umts-Access (20) modules (3) nbap (2) version1 (1) nbap-Constants (4)}

DEFINITIONS AUTOMATIC TAGS ::=

BEGIN

IMPORTS
    ProcedureCode,
    ProtocolIE-ID
FROM NBAP-CommonDataTypes;

-- ****
-- Elementary Procedures
-- ****

id-audit                               ProcedureCode ::= 0
id-auditRequired                        ProcedureCode ::= 1
id-blockResource                         ProcedureCode ::= 2
id-cellDeletion                          ProcedureCode ::= 3
id-cellReconfiguration                   ProcedureCode ::= 4
id-cellSetup                             ProcedureCode ::= 5
id-cellSynchronisationInitiation        ProcedureCode ::= 45
id-cellSynchronisationReconfiguration   ProcedureCode ::= 46
id-cellSynchronisationReporting         ProcedureCode ::= 47
id-cellSynchronisationTermination       ProcedureCode ::= 48
id-cellSynchronisationFailure          ProcedureCode ::= 49
id-commonMeasurementFailure            ProcedureCode ::= 6
id-commonMeasurementInitiation         ProcedureCode ::= 7
id-commonMeasurementReport              ProcedureCode ::= 8
id-commonMeasurementTermination        ProcedureCode ::= 9
id-commonTransportChannelDelete        ProcedureCode ::= 10
id-commonTransportChannelReconfigure   ProcedureCode ::= 11
id-commonTransportChannelSetup          ProcedureCode ::= 12
id-compressedModeCommand                ProcedureCode ::= 14
id-dedicatedMeasurementFailure         ProcedureCode ::= 16
id-dedicatedMeasurementInitiation      ProcedureCode ::= 17
id-dedicatedMeasurementReport          ProcedureCode ::= 18
id-dedicatedMeasurementTermination     ProcedureCode ::= 19
id-downlinkPowerControl                 ProcedureCode ::= 20
```

```

id-downlinkPowerTimeslotControl          ProcedureCode ::= 38
id-errorIndicationForCommon            ProcedureCode ::= 35
id-errorIndicationForDedicated         ProcedureCode ::= 21
id-informationExchangeFailure          ProcedureCode ::= 40
id-informationExchangeInitiation       ProcedureCode ::= 41
id-informationExchangeTermination      ProcedureCode ::= 42
id-informationReporting                ProcedureCode ::= 43
id-BearerRearrangement                 ProcedureCode ::= 50
id-physicalSharedChannelReconfiguration ProcedureCode ::= 37
id-privateMessageForCommon             ProcedureCode ::= 36
id-privateMessageForDedicated          ProcedureCode ::= 22
id-radioLinkAddition                  ProcedureCode ::= 23
id-radioLinkDeletion                  ProcedureCode ::= 24
id-radioLinkFailure                  ProcedureCode ::= 25
id-radioLinkPreemption                ProcedureCode ::= 39
id-radioLinkRestoration               ProcedureCode ::= 26
id-radioLinkSetup                     ProcedureCode ::= 27
id-reset                            ProcedureCode ::= 13
id-resourceStatusIndication          ProcedureCode ::= 28
id-cellSynchronisationAdjustment     ProcedureCode ::= 44
id-synchronisedRadioLinkReconfigurationCancellation ProcedureCode ::= 29
id-synchronisedRadioLinkReconfigurationCommit ProcedureCode ::= 30
id-synchronisedRadioLinkReconfigurationPreparation ProcedureCode ::= 31
id-systemInformationUpdate           ProcedureCode ::= 32
id-unblockResource                   ProcedureCode ::= 33
id-unSynchronisedRadioLinkReconfiguration ProcedureCode ::= 34
id-radioLinkActivation                ProcedureCode ::= 51
id-radioLinkParameterUpdate          ProcedureCode ::= 52

```

-- \*\*\*\*

--

-- Lists

--

-- \*\*\*\*

maxNrOfCodes	INTEGER ::= 10
maxNrOfDLTSS	INTEGER ::= 15
maxNrOfDLTSLCRs	INTEGER ::= 6
maxNrOfErrors	INTEGER ::= 256
maxNrOfTFS	INTEGER ::= 32
maxNrOfTFCs	INTEGER ::= 1024
maxNrOfRLs	INTEGER ::= 16
maxNrOfRLs-1	INTEGER ::= 15 -- maxNrOfRLs - 1
maxNrOfRLs-2	INTEGER ::= 14 -- maxNrOfRLs - 2
maxNrOfRLSets	INTEGER ::= maxNrOfRLs
maxNrOfDPCHs	INTEGER ::= 240
maxNrOfDPCHLCRs	INTEGER ::= 240
maxNrOfSCCPCHs	INTEGER ::= 8
maxNrOfCPCHs	INTEGER ::= 16
maxNrOfPCPCHs	INTEGER ::= 64
maxNrOfDCHs	INTEGER ::= 128
maxNrOfDSCHs	INTEGER ::= 32
maxNrOfFACHs	INTEGER ::= 8

```
maxNrOfCCTrCHs          INTEGER ::= 16
maxNrOfPDSCHs           INTEGER ::= 256
maxNrOfHSPDSCHs         INTEGER ::= 16
maxNrOfPUSCHs           INTEGER ::= 256
maxNrOfPDSCHSets        INTEGER ::= 256
maxNrOfPRACHLCRs        INTEGER ::= 8
maxNrOfPUSCHSets        INTEGER ::= 256
maxNrOfSCCPCHLCRs       INTEGER ::= 8
maxNrOfULTSs             INTEGER ::= 15
maxNrOfULTSLCRs          INTEGER ::= 6
maxNrOfUSCHs              INTEGER ::= 32
maxAPSigNum               INTEGER ::= 16
maxNrOfSlotFormatsPRACH INTEGER ::= 8
maxCellinNodeB            INTEGER ::= 256
maxCCPinNodeB             INTEGER ::= 256
maxCPCHCell                INTEGER ::= maxNrOfCPCHs
maxCTFC                   INTEGER ::= 16777215
maxLocalCellinNodeB       INTEGER ::= maxCellinNodeB
maxNoofLen                 INTEGER ::= 7
maxFPACHCell               INTEGER ::= 8
maxRACHCell                INTEGER ::= maxRACHCell
maxPRACHCell               INTEGER ::= 16
maxPCPCHCell               INTEGER ::= 64
maxSCCPCHCell              INTEGER ::= 32
maxSCPICHCell              INTEGER ::= 32
maxTTI-count                INTEGER ::= 4
maxIBSEG                  INTEGER ::= 16
maxIB                      INTEGER ::= 64
maxFACHCell                INTEGER ::= 256 -- maxNrOfFACHs * maxSCCPCHCell
maxRateMatching            INTEGER ::= 256
maxCodeNrComp-1            INTEGER ::= 256
maxNrOfCellSyncBursts      INTEGER ::= 10
maxNrOfCodeGroups          INTEGER ::= 256
maxNrOfReceptsPerSyncFrame INTEGER ::= 16
maxNrOfMeasNCell           INTEGER ::= 96
maxNrOfMeasNCell-1         INTEGER ::= 95 -- maxNrOfMeasNCell - 1
maxNrOfTFCIGroups          INTEGER ::= 256
maxNrOfTFCI1Combs          INTEGER ::= 512
maxNrOfTFCI2Combs          INTEGER ::= 1024
maxNrOfTFCI2Combs-1        INTEGER ::= 1023
maxNrOfSF                  INTEGER ::= 8
maxTGPS                    INTEGER ::= 6
maxCommunicationContext    INTEGER ::= 1048575
maxNrOfLevels               INTEGER ::= 256
maxNoSat                   INTEGER ::= 16
maxNoGPSItems              INTEGER ::= 8
maxNrOfHSSCCHs             INTEGER ::= 32
maxNrOfHSSICHs              INTEGER ::= 4
maxNrOfSyncFramesLCR        INTEGER ::= 512
maxNrOfReceptionsperSyncFrameLCR INTEGER ::= 8
maxNrOfSyncDLCodesLCR       INTEGER ::= 32
maxNrOfHSSCCHCodes          INTEGER ::= 4
maxNrOfMACdFlows            INTEGER ::= 8
```

```

maxNrOfMACdFlows-1      INTEGER ::= 7    -- maxNrOfMACdFlows - 1
maxNrOfMACdPDUIndexes   INTEGER ::= 8
maxNrOfMACdPDUIndexes-1 INTEGER ::= 7    -- maxNoOfMACdPDUIndexes - 1
maxNrOfPriorityQueues   INTEGER ::= 8
maxNrOfPriorityQueues-1 INTEGER ::= 7    -- maxNoOfPriorityQueues - 1
maxNrOfHARQProcesses    INTEGER ::= 8
maxNrOfBestCellPortions INTEGER ::= 4

-- ****
-- IEs
-- ****

id-AICH-Information          ProtocolIE-ID ::= 0
id-AICH-InformationItem-ResourceStatusInd ProtocolIE-ID ::= 1
id-BCH-Information           ProtocolIE-ID ::= 7
id-BCH-InformationItem-ResourceStatusInd ProtocolIE-ID ::= 8
id-BCCH-ModificationTime     ProtocolIE-ID ::= 9
id-BlockingPriorityIndicator ProtocolIE-ID ::= 10
id-Cause                      ProtocolIE-ID ::= 13
id-CCP-InformationItem-AuditRsp ProtocolIE-ID ::= 14
id-CCP-InformationList-AuditRsp ProtocolIE-ID ::= 15
id-CCP-InformationItem-ResourceStatusInd ProtocolIE-ID ::= 16
id-Cell-InformationItem-AuditRsp ProtocolIE-ID ::= 17
id-Cell-InformationItem-ResourceStatusInd ProtocolIE-ID ::= 18
id-Cell-InformationList-AuditRsp ProtocolIE-ID ::= 19
id-CellParameterID           ProtocolIE-ID ::= 23
id-CFN                        ProtocolIE-ID ::= 24
id-C-ID                        ProtocolIE-ID ::= 25
id-CommonMeasurementAccuracy ProtocolIE-ID ::= 39
id-CommonMeasurementObjectType-CM-Rprt ProtocolIE-ID ::= 31
id-CommonMeasurementObjectType-CM-Rqst ProtocolIE-ID ::= 32
id-CommonMeasurementObjectType-CM-Rsp ProtocolIE-ID ::= 33
id-CommonMeasurementType       ProtocolIE-ID ::= 34
id-CommonPhysicalChannel1ID   ProtocolIE-ID ::= 35
id-CommonPhysicalChannelType-CTCH-SetupRqstFDD ProtocolIE-ID ::= 36
id-CommonPhysicalChannelType-CTCH-SetupRqstTDD ProtocolIE-ID ::= 37
id-CommunicationControlPortID ProtocolIE-ID ::= 40
id-ConfigurationGenerationID  ProtocolIE-ID ::= 43
id-CRNC-CommunicationContextID ProtocolIE-ID ::= 44
id-CriticalityDiagnostics    ProtocolIE-ID ::= 45
id-DCHs-to-Add-FDD            ProtocolIE-ID ::= 48
id-DCH-AddList-RL-ReconfPrepTDD ProtocolIE-ID ::= 49
id-DCHs-to-Add-TDD            ProtocolIE-ID ::= 50
id-DCH-DeleteList-RL-ReconfPrepFDD ProtocolIE-ID ::= 52
id-DCH-DeleteList-RL-ReconfPrepTDD ProtocolIE-ID ::= 53
id-DCH-DeleteList-RL-ReconfRqstFDD ProtocolIE-ID ::= 54
id-DCH-DeleteList-RL-ReconfRqstTDD ProtocolIE-ID ::= 55
id-DCH-FDD-Information        ProtocolIE-ID ::= 56
id-DCH-TDD-Information        ProtocolIE-ID ::= 57
id-DCH-InformationResponse    ProtocolIE-ID ::= 59
id-FDD-DCHs-to-Modify         ProtocolIE-ID ::= 62

```

```

id-TDD-DCHs-to-Modify
id-DCH-ModifyList-RL-ReconfRqstTDD
id-DCH-RearrangeList-Bearer-RearrangeInd
id-DedicatedMeasurementObjectType-DM-Rprt
id-DedicatedMeasurementObjectType-DM-Rqst
id-DedicatedMeasurementObjectType-DM-Rsp
id-DedicatedMeasurementType
id-DL-CCTrCH-InformationItem-RL-SetupRqstTDD
id-DL-CCTrCH-InformationList-RL-AdditionRqstTDD
id-DL-CCTrCH-InformationList-RL-SetupRqstTDD
id-DL-DPCH-InformationItem-RL-AdditionRqstTDD
id-DL-DPCH-InformationList-RL-SetupRqstTDD
id-DL-DPCH-Information-RL-ReconfPrepFDD
id-DL-DPCH-Information-RL-ReconfRqstFDD
id-DL-DPCH-Information-RL-SetupRqstFDD
id-DL-DPCH-TimingAdjustment
id-DL-ReferencePowerInformationItem-DL-PC-Rqst
id-DLReferencePower
id-DLReferencePowerList-DL-PC-Rqst
id-DSCH-AddItem-RL-ReconfPrepFDD
id-DSCHs-to-Add-FDD
id-DSCH-DeleteItem-RL-ReconfPrepFDD
id-DSCH-DeleteList-RL-ReconfPrepFDD
id-DSCHs-to-Add-TDD
id-DSCH-Information-DeleteList-RL-ReconfPrepTDD
id-DSCH-Information-ModifyList-RL-ReconfPrepTDD
id-DSCH-InformationResponse
id-DSCH-FDD-Information
id-DSCH-TDD-Information
id-DSCH-ModifyItem-RL-ReconfPrepFDD
id-DSCH-ModifyList-RL-ReconfPrepFDD
id-DSCH-RearrangeList-Bearer-RearrangeInd
id-End-Of-Audit-Sequence-Indicator
id-FACH-Information
id-FACH-InformationItem-ResourceStatusInd
id-FACH-ParametersList-CTCH-ReconfRqstTDD
id-FACH-ParametersListIE-CTCH-SetupRqstFDD
id-FACH-ParametersListIE-CTCH-SetupRqstTDD
id-IndicationType-ResourceStatusInd
id-Local-Cell-ID
id-Local-Cell-Group-InformationItem-AuditRsp
id-Local-Cell-Group-InformationItem-ResourceStatusInd
id-Local-Cell-Group-InformationItem2-ResourceStatusInd
id-Local-Cell-Group-InformationList-AuditRsp
id-Local-Cell-InformationItem-AuditRsp
id-Local-Cell-InformationItem-ResourceStatusInd
id-Local-Cell-InformationItem2-ResourceStatusInd
id-Local-Cell-InformationList-AuditRsp
id-AdjustmentPeriod
id-MaxAdjustmentStep
id-MaximumTransmissionPower
id-MeasurementFilterCoefficient
id-MeasurementID

```

```

ProtocolIE-ID ::= 63
ProtocolIE-ID ::= 65
ProtocolIE-ID ::= 135
ProtocolIE-ID ::= 67
ProtocolIE-ID ::= 68
ProtocolIE-ID ::= 69
ProtocolIE-ID ::= 70
ProtocolIE-ID ::= 72
ProtocolIE-ID ::= 73
ProtocolIE-ID ::= 76
ProtocolIE-ID ::= 77
ProtocolIE-ID ::= 79
ProtocolIE-ID ::= 81
ProtocolIE-ID ::= 82
ProtocolIE-ID ::= 83
ProtocolIE-ID ::= 21
ProtocolIE-ID ::= 84
ProtocolIE-ID ::= 85
ProtocolIE-ID ::= 86
ProtocolIE-ID ::= 87
ProtocolIE-ID ::= 89
ProtocolIE-ID ::= 91
ProtocolIE-ID ::= 93
ProtocolIE-ID ::= 96
ProtocolIE-ID ::= 98
ProtocolIE-ID ::= 100
ProtocolIE-ID ::= 105
ProtocolIE-ID ::= 106
ProtocolIE-ID ::= 107
ProtocolIE-ID ::= 108
ProtocolIE-ID ::= 112
ProtocolIE-ID ::= 136
ProtocolIE-ID ::= 113
ProtocolIE-ID ::= 116
ProtocolIE-ID ::= 117
ProtocolIE-ID ::= 120
ProtocolIE-ID ::= 121
ProtocolIE-ID ::= 122
ProtocolIE-ID ::= 123
ProtocolIE-ID ::= 124
ProtocolIE-ID ::= 2
ProtocolIE-ID ::= 3
ProtocolIE-ID ::= 4
ProtocolIE-ID ::= 5
ProtocolIE-ID ::= 125
ProtocolIE-ID ::= 126
ProtocolIE-ID ::= 127
ProtocolIE-ID ::= 128
ProtocolIE-ID ::= 129
ProtocolIE-ID ::= 130
ProtocolIE-ID ::= 131
ProtocolIE-ID ::= 132
ProtocolIE-ID ::= 133

```

```

id-MessageStructure
id-MIB-SB-SIB-InformationList-SystemInfoUpdateRqst
id-NodeB-CommunicationContextID
id-NeighbouringCellMeasurementInformation
id-P-CCPCH-Information
id-P-CCPCH-InformationItem-ResourceStatusInd
id-P-CPICH-Information
id-P-CPICH-InformationItem-ResourceStatusInd
id-P-SCH-Information
id-PCCPCH-Information-Cell-ReconfRqstTDD
id-PCCPCH-Information-Cell-SetupRqstTDD
id-PCH-Parameters-CTCH-ReconfRqstTDD
id-PCH-ParametersItem-CTCH-SetupRqstFDD
id-PCH-ParametersItem-CTCH-SetupRqstTDD
id-PCH-Information
id-PDSCH-Information-AddListIE-PSCH-ReconfRqst
id-PDSCH-Information-ModifyListIE-PSCH-ReconfRqst
id-PDSCHSets-AddList-PSCH-ReconfRqst
id-PDSCHSets-DeleteList-PSCH-ReconfRqst
id-PDSCHSets-ModifyList-PSCH-ReconfRqst
id-PICH-Information
id-PICH-Parameters-CTCH-ReconfRqstTDD
id-PowerAdjustmentType
id-PRACH-Information
id-PrimaryCCPCH-Information-Cell-ReconfRqstFDD
id-PrimaryCCPCH-Information-Cell-SetupRqstFDD
id-PrimaryCPICH-Information-Cell-ReconfRqstFDD
id-PrimaryCPICH-Information-Cell-SetupRqstFDD
id-PrimarySCH-Information-Cell-ReconfRqstFDD
id-PrimarySCH-Information-Cell-SetupRqstFDD
id-PrimaryScramblingCode
id-SCH-Information-Cell-ReconfRqstTDD
id-SCH-Information-Cell-SetupRqstTDD
id-PUSCH-Information-AddListIE-PSCH-ReconfRqst
id-PUSCH-Information-ModifyListIE-PSCH-ReconfRqst
id-PUSCHSets-AddList-PSCH-ReconfRqst
id-PUSCHSets-DeleteList-PSCH-ReconfRqst
id-PUSCHSets-ModifyList-PSCH-ReconfRqst
id-RACH-Information
id-RACH-ParametersItem-CTCH-SetupRqstFDD
id-RACH-ParameterItem-CTCH-SetupRqstTDD
id-ReportCharacteristics
id-Reporting-Object-RL-FailureInd
id-Reporting-Object-RL-RestoreInd
id-RL-InformationItem-DM-Rprt
id-RL-InformationItem-DM-Rqst
id-RL-InformationItem-DM-Rsp
id-RL-InformationItem-RL-AdditionRqstFDD
id-RL-informationItem-RL-DeletionRqst
id-RL-InformationItem-RL-FailureInd
id-RL-InformationItem-RL-PreemptRequiredInd
id-RL-InformationItem-RL-ReconfPrepFDD
id-RL-InformationItem-RL-ReconfRqstFDD

```

```

ProtocolIE-ID ::= 115
ProtocolIE-ID ::= 134
ProtocolIE-ID ::= 143
ProtocolIE-ID ::= 455
ProtocolIE-ID ::= 144
ProtocolIE-ID ::= 145
ProtocolIE-ID ::= 146
ProtocolIE-ID ::= 147
ProtocolIE-ID ::= 148
ProtocolIE-ID ::= 150
ProtocolIE-ID ::= 151
ProtocolIE-ID ::= 155
ProtocolIE-ID ::= 156
ProtocolIE-ID ::= 157
ProtocolIE-ID ::= 158
ProtocolIE-ID ::= 161
ProtocolIE-ID ::= 162
ProtocolIE-ID ::= 163
ProtocolIE-ID ::= 164
ProtocolIE-ID ::= 165
ProtocolIE-ID ::= 166
ProtocolIE-ID ::= 168
ProtocolIE-ID ::= 169
ProtocolIE-ID ::= 170
ProtocolIE-ID ::= 175
ProtocolIE-ID ::= 176
ProtocolIE-ID ::= 177
ProtocolIE-ID ::= 178
ProtocolIE-ID ::= 179
ProtocolIE-ID ::= 180
ProtocolIE-ID ::= 181
ProtocolIE-ID ::= 183
ProtocolIE-ID ::= 184
ProtocolIE-ID ::= 185
ProtocolIE-ID ::= 186
ProtocolIE-ID ::= 187
ProtocolIE-ID ::= 188
ProtocolIE-ID ::= 189
ProtocolIE-ID ::= 190
ProtocolIE-ID ::= 196
ProtocolIE-ID ::= 197
ProtocolIE-ID ::= 198
ProtocolIE-ID ::= 199
ProtocolIE-ID ::= 200
ProtocolIE-ID ::= 202
ProtocolIE-ID ::= 203
ProtocolIE-ID ::= 204
ProtocolIE-ID ::= 205
ProtocolIE-ID ::= 206
ProtocolIE-ID ::= 207
ProtocolIE-ID ::= 286
ProtocolIE-ID ::= 208
ProtocolIE-ID ::= 209

```

```

id-RL-InformationItem-RL-RestoreInd
id-RL-InformationItem-RL-SetupRqstFDD
id-RL-InformationList-RL-AdditionRqstFDD
id-RL-informationList-RL-DeletionRqst
id-RL-InformationList-RL-PreemptRequiredInd
id-RL-InformationList-RL-ReconfPrepFDD
id-RL-InformationList-RL-ReconfRqstFDD
id-RL-InformationList-RL-SetupRqstFDD
id-RL-InformationResponseItem-RL-AdditionRspFDD
id-RL-InformationResponseItem-RL-ReconfReady
id-RL-InformationResponseItem-RL-ReconfRsp
id-RL-InformationResponseItem-RL-SetupRspFDD
id-RL-InformationResponseList-RL-AdditionRspFDD
id-RL-InformationResponseList-RL-ReconfReady
id-RL-InformationResponseList-RL-ReconfRsp
id-RL-InformationResponseList-RL-SetupRspFDD
id-RL-InformationResponse-RL-AdditionRspTDD
id-RL-InformationResponse-RL-SetupRspTDD
id-RL-Information-RL-AdditionRqstTDD
id-RL-Information-RL-ReconfRqstTDD
id-RL-Information-RL-ReconfPrepTDD
id-RL-Information-RL-SetupRqstTDD
id-RL-ReconfigurationFailureItem-RL-ReconfFailure
id-RL-Set-InformationItem-DM-Rprt
id-RL-Set-InformationItem-DM-Rsp
id-RL-Set-InformationItem-RL-FailureInd
id-RL-Set-InformationItem-RL-RestoreInd
id-S-CCPCH-Information
id-S-CPICH-Information
id-SCH-Information
id-S-SCH-Information
id-Secondary-CCPCHlistIE-CTCH-ReconfRqstTDD
id-Secondary-CCPCH-parameterListIE-CTCH-SetupRqstTDD
id-Secondary-CCPCH-Parameters-CTCH-ReconfRqstTDD
id-SecondaryCPICH-InformationItem-Cell-ReconfRqstFDD
id-SecondaryCPICH-InformationItem-Cell-SetupRqstFDD
id-SecondaryCPICH-InformationList-Cell-ReconfRqstFDD
id-SecondaryCPICH-InformationList-Cell-SetupRqstFDD
id-SecondarySCH-Information-Cell-ReconfRqstFDD
id-SecondarySCH-Information-Cell-SetupRqstFDD
id-SegmentInformationListIE-SystemInfoUpdate
id-SFN
id-SignallingBearerRequestIndicator
id-ShutdownTimer
id-Start-Of-Audit-Sequence-Indicator
id-Successful-RL-InformationRespItem-RL-AdditionFailureFDD
id-Successful-RL-InformationRespItem-RL-SetupFailureFDD
id-SyncCase
id-SyncCaseIndicatorItem-Cell-SetupRqstTDD-PSCH
id-T-Cell
id-TargetCommunicationControlPortID
id-TimeSlotConfigurationList-Cell-ReconfRqstTDD
id-TimeSlotConfigurationList-Cell-SetupRqstTDD

```

```

ProtocolIE-ID ::= 210
ProtocolIE-ID ::= 211
ProtocolIE-ID ::= 212
ProtocolIE-ID ::= 213
ProtocolIE-ID ::= 237
ProtocolIE-ID ::= 214
ProtocolIE-ID ::= 215
ProtocolIE-ID ::= 216
ProtocolIE-ID ::= 217
ProtocolIE-ID ::= 218
ProtocolIE-ID ::= 219
ProtocolIE-ID ::= 220
ProtocolIE-ID ::= 221
ProtocolIE-ID ::= 222
ProtocolIE-ID ::= 223
ProtocolIE-ID ::= 224
ProtocolIE-ID ::= 225
ProtocolIE-ID ::= 226
ProtocolIE-ID ::= 227
ProtocolIE-ID ::= 228
ProtocolIE-ID ::= 229
ProtocolIE-ID ::= 230
ProtocolIE-ID ::= 236
ProtocolIE-ID ::= 238
ProtocolIE-ID ::= 240
ProtocolIE-ID ::= 241
ProtocolIE-ID ::= 242
ProtocolIE-ID ::= 247
ProtocolIE-ID ::= 249
ProtocolIE-ID ::= 251
ProtocolIE-ID ::= 253
ProtocolIE-ID ::= 257
ProtocolIE-ID ::= 258
ProtocolIE-ID ::= 259
ProtocolIE-ID ::= 260
ProtocolIE-ID ::= 261
ProtocolIE-ID ::= 262
ProtocolIE-ID ::= 263
ProtocolIE-ID ::= 264
ProtocolIE-ID ::= 265
ProtocolIE-ID ::= 266
ProtocolIE-ID ::= 268
ProtocolIE-ID ::= 138
ProtocolIE-ID ::= 269
ProtocolIE-ID ::= 114
ProtocolIE-ID ::= 270
ProtocolIE-ID ::= 271
ProtocolIE-ID ::= 274
ProtocolIE-ID ::= 275
ProtocolIE-ID ::= 276
ProtocolIE-ID ::= 139
ProtocolIE-ID ::= 277
ProtocolIE-ID ::= 278

```

id-TransmissionDiversityApplied  
 id-TypeOfError  
 id-UARFCNforNt  
 id-UARFCNforNd  
 id-UARFCNforNu  
 id-UL-CCTrCH-InformationItem-RL-SetupRqstTDD  
 id-UL-CCTrCH-InformationList-RL-AdditionRqstTDD  
 id-UL-CCTrCH-InformationList-RL-SetupRqstTDD  
 id-UL-DPCH-InformationItem-RL-AdditionRqstTDD  
 id-UL-DPCH-InformationList-RL-SetupRqstTDD  
 id-UL-DPCH-Information-RL-ReconfPrepFDD  
 id-UL-DPCH-Information-RL-ReconfRqstFDD  
 id-UL-DPCH-Information-RL-SetupRqstFDD  
 id-Unsuccessful-RL-InformationRespItem-RL-AdditionFailureFDD  
 id-Unsuccessful-RL-InformationRespItem-RL-SetupFailureFDD  
 id-Unsuccessful-RL-InformationResp-RL-AdditionFailureTDD  
 id-Unsuccessful-RL-InformationResp-RL-SetupFailureTDD  
 id-USCH-Information-Add  
 id-USCH-Information-DeleteList-RL-ReconfPrepTDD  
 id-USCH-Information-ModifyList-RL-ReconfPrepTDD  
 id-USCH-InformationResponse  
 id-USCH-Information  
 id-USCH-RearrangeList-Bearer-RearrangeInd  
 id-Active-Pattern-Sequence-Information  
 id-AICH-ParametersListIE-CTCH-ReconfRqstFDD  
 id-AdjustmentRatio  
 id-AP-AICH-Information  
 id-AP-AICH-ParametersListIE-CTCH-ReconfRqstFDD  
 id-FACH-ParametersListIE-CTCH-ReconfRqstFDD  
 id-CauseLevel-PSCH-ReconfFailure  
 id-CauseLevel-RL-AdditionFailureFDD  
 id-CauseLevel-RL-AdditionFailureTDD  
 id-CauseLevel-RL-ReconfFailure  
 id-CauseLevel-RL-SetupFailureFDD  
 id-CauseLevel-RL-SetupFailureTDD  
 id-CDCA-ICH-Information  
 id-CDCA-ICH-ParametersListIE-CTCH-ReconfRqstFDD  
 id-Closed-Loop-Timing-Adjustment-Mode  
 id-CommonPhysicalChannelType-CTCH-ReconfRqstFDD  
 id-Compressed-Mode-Deactivation-Flag  
 id-CPCH-Information  
 id-CPCH-Parameters-CTCH-SetupRsp  
 id-CPCH-ParametersListIE-CTCH-ReconfRqstFDD  
 id-DL-CCTrCH-InformationAddList-RL-ReconfPrepTDD  
 id-DL-CCTrCH-InformationDeleteItem-RL-ReconfRqstTDD  
 id-DL-CCTrCH-InformationDeleteList-RL-ReconfPrepTDD  
 id-DL-CCTrCH-InformationModifyItem-RL-ReconfRqstTDD  
 id-DL-CCTrCH-InformationModifyList-RL-ReconfPrepTDD  
 id-DL-CCTrCH-InformationModifyList-RL-ReconfRqstTDD  
 id-DL-DPCH-InformationAddListIE-RL-ReconfPrepTDD  
 id-DL-DPCH-InformationModify-AddListIE-RL-ReconfPrepTDD  
 id-DL-DPCH-InformationModify-DeleteListIE-RL-ReconfPrepTDD

ProtocolIE-ID ::= 279  
 ProtocolIE-ID ::= 508  
 ProtocolIE-ID ::= 280  
 ProtocolIE-ID ::= 281  
 ProtocolIE-ID ::= 282  
 ProtocolIE-ID ::= 284  
 ProtocolIE-ID ::= 285  
 ProtocolIE-ID ::= 288  
 ProtocolIE-ID ::= 289  
 ProtocolIE-ID ::= 291  
 ProtocolIE-ID ::= 293  
 ProtocolIE-ID ::= 294  
 ProtocolIE-ID ::= 295  
 ProtocolIE-ID ::= 296  
 ProtocolIE-ID ::= 297  
 ProtocolIE-ID ::= 300  
 ProtocolIE-ID ::= 301  
 ProtocolIE-ID ::= 302  
 ProtocolIE-ID ::= 304  
 ProtocolIE-ID ::= 306  
 ProtocolIE-ID ::= 309  
 ProtocolIE-ID ::= 310  
 ProtocolIE-ID ::= 141  
 ProtocolIE-ID ::= 315  
 ProtocolIE-ID ::= 316  
 ProtocolIE-ID ::= 317  
 ProtocolIE-ID ::= 320  
 ProtocolIE-ID ::= 322  
 ProtocolIE-ID ::= 323  
 ProtocolIE-ID ::= 324  
 ProtocolIE-ID ::= 325  
 ProtocolIE-ID ::= 326  
 ProtocolIE-ID ::= 327  
 ProtocolIE-ID ::= 328  
 ProtocolIE-ID ::= 329  
 ProtocolIE-ID ::= 330  
 ProtocolIE-ID ::= 332  
 ProtocolIE-ID ::= 333  
 ProtocolIE-ID ::= 334  
 ProtocolIE-ID ::= 335  
 ProtocolIE-ID ::= 336  
 ProtocolIE-ID ::= 342  
 ProtocolIE-ID ::= 343  
 ProtocolIE-ID ::= 346  
 ProtocolIE-ID ::= 347  
 ProtocolIE-ID ::= 348  
 ProtocolIE-ID ::= 349  
 ProtocolIE-ID ::= 350  
 ProtocolIE-ID ::= 351  
 ProtocolIE-ID ::= 352  
 ProtocolIE-ID ::= 353  
 ProtocolIE-ID ::= 355  
 ProtocolIE-ID ::= 356

id-DL-DPCH-InformationModify-ModifyListIE-RL-ReconfPrepTDD  
 id-DL-TPC-Pattern01Count  
 id-DPC-Mode  
 id-DPCHConstant  
 id-DSCH-FDD-Common-Information  
 id-EnhancedDSCHPC  
 id-EnhancedDSCHPCIndicator  
 id-FACH-ParametersList-CTCH-SetupRsp  
 id-Limited-power-increase-information-Cell-SetupRqstFDD  
 id-PCH-Parameters-CTCH-SetupRsp  
 id-PCH-ParametersItem-CTCH-ReconfRqstFDD  
 id-PCPCH-Information  
 id-PICH-ParametersItem-CTCH-ReconfRqstFDD  
 id-PRACHConstant  
 id-PRACH-ParametersListIE-CTCH-ReconfRqstFDD  
 id-PUSCHConstant  
 id-RACH-Parameters-CTCH-SetupRsp  
 id-SSDT-CellIDforEDSCHPC  
 id-Synchronisation-Configuration-Cell-ReconfRqst  
 id-Synchronisation-Configuration-Cell-SetupRqst  
 id-Transmission-Gap-Pattern-Sequence-Information  
 id-UL-CCTrCH-InformationAddList-RL-ReconfPrepTDD  
 id-UL-CCTrCH-InformationDeleteItem-RL-ReconfRqstTDD  
 id-UL-CCTrCH-InformationDeleteList-RL-ReconfPrepTDD  
 id-UL-CCTrCH-InformationModifyItem-RL-ReconfRqstTDD  
 id-UL-CCTrCH-InformationModifyList-RL-ReconfPrepTDD  
 id-UL-CCTrCH-InformationModifyList-RL-ReconfRqstTDD  
 id-UL-DPCH-InformationAddListIE-RL-ReconfPrepTDD  
 id-UL-DPCH-InformationModify-AddListIE-RL-ReconfPrepTDD  
 id-UL-DPCH-InformationModify-DeleteListIE-RL-ReconfPrepTDD  
 id-UL-DPCH-InformationModify-ModifyListIE-RL-ReconfPrepTDD  
 id-Unsuccessful-PDSCHSetItem-PSCH-ReconfFailureTDD  
 id-Unsuccessful-PUSCHSetItem-PSCH-ReconfFailureTDD  
 id-CommunicationContextInfoItem-Reset  
 id-CommunicationControlPortInfoItem-Reset  
 id-ResetIndicator  
 id-TFCI2-Bearer-Information-RL-SetupRqstFDD  
 id-TFCI2-BearerSpecificInformation-RL-ReconfPrepFDD  
 id-TFCI2-BearerInformationResponse  
 id-TFCI2BearerRequestIndicator  
 id-TimingAdvanceApplied  
 id-CFNReportingIndicator  
 id-SFNReportingIndicator  
 id-InnerLoopDLCStatus  
 id-TimeslotISCPInfo  
 id-PICH-ParametersItem-CTCH-SetupRqstTDD  
 id-PRACH-ParametersItem-CTCH-SetupRqstTDD  
 id-CCTrCH-InformationItem-RL-FailureInd  
 id-CCTrCH-InformationItem-RL-RestoreInd  
 id-CauseLevel-SyncAdjustmntFailureTDD  
 id-CellAdjustmentInfo-SyncAdjustmntRqstTDD  
 id-CellAdjustmentInfoItem-SyncAdjustmentRqstTDD

ProtocolIE-ID ::= 357  
 ProtocolIE-ID ::= 358  
 ProtocolIE-ID ::= 450  
 ProtocolIE-ID ::= 359  
 ProtocolIE-ID ::= 94  
 ProtocolIE-ID ::= 110  
 ProtocolIE-ID ::= 111  
 ProtocolIE-ID ::= 362  
 ProtocolIE-ID ::= 369  
 ProtocolIE-ID ::= 374  
 ProtocolIE-ID ::= 375  
 ProtocolIE-ID ::= 376  
 ProtocolIE-ID ::= 380  
 ProtocolIE-ID ::= 381  
 ProtocolIE-ID ::= 383  
 ProtocolIE-ID ::= 384  
 ProtocolIE-ID ::= 385  
 ProtocolIE-ID ::= 443  
 ProtocolIE-ID ::= 393  
 ProtocolIE-ID ::= 394  
 ProtocolIE-ID ::= 395  
 ProtocolIE-ID ::= 396  
 ProtocolIE-ID ::= 397  
 ProtocolIE-ID ::= 398  
 ProtocolIE-ID ::= 399  
 ProtocolIE-ID ::= 400  
 ProtocolIE-ID ::= 401  
 ProtocolIE-ID ::= 402  
 ProtocolIE-ID ::= 403  
 ProtocolIE-ID ::= 405  
 ProtocolIE-ID ::= 406  
 ProtocolIE-ID ::= 407  
 ProtocolIE-ID ::= 408  
 ProtocolIE-ID ::= 409  
 ProtocolIE-ID ::= 412  
 ProtocolIE-ID ::= 414  
 ProtocolIE-ID ::= 416  
 ProtocolIE-ID ::= 417  
 ProtocolIE-ID ::= 418  
 ProtocolIE-ID ::= 419  
 ProtocolIE-ID ::= 142  
 ProtocolIE-ID ::= 287  
 ProtocolIE-ID ::= 6  
 ProtocolIE-ID ::= 11  
 ProtocolIE-ID ::= 12  
 ProtocolIE-ID ::= 283  
 ProtocolIE-ID ::= 167  
 ProtocolIE-ID ::= 20  
 ProtocolIE-ID ::= 46  
 ProtocolIE-ID ::= 47  
 ProtocolIE-ID ::= 420  
 ProtocolIE-ID ::= 421  
 ProtocolIE-ID ::= 494

id-CellSyncBurstInfoList-CellSyncReconfRqstTDD  
 id-CellSyncBurstTransInit-CellSyncInitiationRqstTDD  
 id-CellSyncBurstMeasureInit-CellSyncInitiationRqstTDD  
 id-CellSyncBurstTransReconfiguration-CellSyncReconfRqstTDD  
 id-CellSyncBurstMeasReconfiguration-CellSyncReconfRqstTDD  
 id-CellSyncBurstTransInfoList-CellSyncReconfRqstTDD  
 id-CellSyncBurstMeasInfoList-CellSyncReconfRqstTDD  
 id-CellSyncBurstTransReconfInfo-CellSyncReconfRqstTDD  
 id-CellSyncInfo-CellSyncReprtTDD  
 id-CSBTransmissionID  
 id-CSBMeasurementID  
 id-IntStdPhCellSyncInfoItem-CellSyncReprtTDD  
 id-NCyclesPerSFNperiod  
 id-NRepetitionsPerCyclePeriod  
 id-SyncFrameNumber  
 id-SynchronisationReportType  
 id-SynchronisationReportCharacteristics  
 id-Unsuccessful-cell-InformationRespItem-SyncAdjustmntFailureTDD  
 id-LateEntranceCellSyncInfoItem-CellSyncReprtTDD  
 id-ReferenceClockAvailability  
 id-ReferenceSFNoffset  
 id-InformationExchangeID  
 id-InformationExchangeObjectType-InfEx-Rqst  
 id-InformationType  
 id-InformationReportCharacteristics  
 id-InformationExchangeObjectType-InfEx-Rsp  
 id-InformationExchangeObjectType-InfEx-Rprt  
 id-IPDLParameter-Information-Cell-ReconfRqstFDD  
 id-IPDLParameter-Information-Cell-SetupRqstFDD  
 id-IPDLParameter-Information-Cell-ReconfRqstTDD  
 id-IPDLParameter-Information-Cell-SetupRqstTDD  
 id-DL-DPCH-LCR-Information-RL-SetupRqstTDD  
 id-DwPCH-LCR-Information  
 id-DwPCH-LCR-InformationList-AuditRsp  
 id-DwPCH-LCR-Information-Cell-SetupRqstTDD  
 id-DwPCH-LCR-Information-Cell-ReconfRqstTDD  
 id-DwPCH-LCR-Information-ResourceStatusInd  
 id-maxFACH-Power-LCR-CTCH-SetupRqstTDD  
 id-maxFACH-Power-LCR-CTCH-ReconfRqstTDD  
 id-FPACH-LCR-Information  
 id-FPACH-LCR-Information-AuditRsp  
 id-FPACH-LCR-InformationList-AuditRsp  
 id-FPACH-LCR-InformationList-ResourceStatusInd  
 id-FPACH-LCR-Parameters-CTCH-SetupRqstTDD  
 id-FPACH-LCR-Parameters-CTCH-ReconfRqstTDD  
 id-PCCPCH-LCR-Information-Cell-SetupRqstTDD  
 id-PCH-Power-LCR-CTCH-SetupRqstTDD  
 id-PCH-Power-LCR-CTCH-ReconfRqstTDD  
 id-PICH-LCR-Parameters-CTCH-SetupRqstTDD  
 id-PRACH-LCR-ParametersList-CTCH-SetupRqstTDD  
 id-RL-InformationResponse-LCR-RL-SetupRspTDD  
 id-Secondary-CCPCH-LCR-parameterList-CTCH-SetupRqstTDD  
 id-TimeSlot

ProtocolIE-ID ::= 482  
 ProtocolIE-ID ::= 422  
 ProtocolIE-ID ::= 423  
 ProtocolIE-ID ::= 424  
 ProtocolIE-ID ::= 425  
 ProtocolIE-ID ::= 426  
 ProtocolIE-ID ::= 427  
 ProtocolIE-ID ::= 428  
 ProtocolIE-ID ::= 429  
 ProtocolIE-ID ::= 430  
 ProtocolIE-ID ::= 431  
 ProtocolIE-ID ::= 432  
 ProtocolIE-ID ::= 433  
 ProtocolIE-ID ::= 434  
 ProtocolIE-ID ::= 437  
 ProtocolIE-ID ::= 438  
 ProtocolIE-ID ::= 439  
 ProtocolIE-ID ::= 440  
 ProtocolIE-ID ::= 119  
 ProtocolIE-ID ::= 435  
 ProtocolIE-ID ::= 436  
 ProtocolIE-ID ::= 444  
 ProtocolIE-ID ::= 445  
 ProtocolIE-ID ::= 446  
 ProtocolIE-ID ::= 447  
 ProtocolIE-ID ::= 448  
 ProtocolIE-ID ::= 449  
 ProtocolIE-ID ::= 451  
 ProtocolIE-ID ::= 452  
 ProtocolIE-ID ::= 453  
 ProtocolIE-ID ::= 454  
 ProtocolIE-ID ::= 74  
 ProtocolIE-ID ::= 78  
 ProtocolIE-ID ::= 90  
 ProtocolIE-ID ::= 97  
 ProtocolIE-ID ::= 99  
 ProtocolIE-ID ::= 101  
 ProtocolIE-ID ::= 154  
 ProtocolIE-ID ::= 174  
 ProtocolIE-ID ::= 290  
 ProtocolIE-ID ::= 292  
 ProtocolIE-ID ::= 22  
 ProtocolIE-ID ::= 311  
 ProtocolIE-ID ::= 312  
 ProtocolIE-ID ::= 314  
 ProtocolIE-ID ::= 456  
 ProtocolIE-ID ::= 457  
 ProtocolIE-ID ::= 458  
 ProtocolIE-ID ::= 459  
 ProtocolIE-ID ::= 461  
 ProtocolIE-ID ::= 463  
 ProtocolIE-ID ::= 465  
 ProtocolIE-ID ::= 495

id-TimeSlotConfigurationList-LCR-Cell-ReconfRqstTDD  
 id-TimeSlotConfigurationList-LCR-Cell-SetupRqstTDD  
 id-TimeslotISCP-LCR-InfoList-RL-SetupRqstTDD  
 id-TimeSlotLCR-CM-Rqst  
 id-UL-DPCH-LCR-Information-RL-SetupRqstTDD  
 id-DL-DPCH-InformationItem-LCR-RL-AdditionRqstTDD  
 id-UL-DPCH-InformationItem-LCR-RL-AdditionRqstTDD  
 id-TimeslotISCP-InformationList-LCR-RL-AdditionRqstTDD  
 id-DL-DPCH-LCR-InformationAddList-RL-ReconfPrepTDD  
 id-DL-DPCH-LCR-InformationModify-AddList-RL-ReconfPrepTDD  
 id-DL-Timeslot-LCR-InformationModify-ModifyList-RL-ReconfPrepTDD  
 id-TimeslotISCPInfoList-LCR-DL-PC-RqstTDD  
 id-UL-DPCH-LCR-InformationAddListIE-RL-ReconfPrepTDD  
 id-UL-DPCH-LCR-InformationModify-AddList  
 id-UL-TimeslotLCR-Information-RL-ReconfPrepTDD  
 id-UL-SIRTarget  
 id-PDSCH-AddInformation-LCR-PSCH-ReconfRqst  
 id-PDSCH-AddInformation-LCR-AddListIE-PSCH-ReconfRqst  
 id-PDSCH-Information-Cell-SetupRqstFDD  
 id-PDSCH-Information-Cell-ReconfRqstFDD  
 id-PDSCH-ModifyInformation-LCR-PSCH-ReconfRqst  
 id-PDSCH-ModifyInformation-LCR-ModifyListIE-PSCH-ReconfRqst  
 id-PUSCH-AddInformation-LCR-PSCH-ReconfRqst  
 id-PUSCH-AddInformation-LCR-AddListIE-PSCH-ReconfRqst  
 id-PUSCH-ModifyInformation-LCR-PSCH-ReconfRqst  
 id-PUSCH-ModifyInformation-LCR-ModifyListIE-PSCH-ReconfRqst  
 id-timeslotInfo-CellSyncInitiationRqstTDD  
 id-SyncReportType-CellSyncReprtTDD  
 id-Power-Local-Cell-Group-InformationItem-AuditRsp  
 id-Power-Local-Cell-Group-InformationItem-ResourceStatusInd  
 id-Power-Local-Cell-Group-InformationItem2-ResourceStatusInd  
 id-Power-Local-Cell-Group-InformationList-AuditRsp  
 id-Power-Local-Cell-Group-InformationList-ResourceStatusInd  
 id-Power-Local-Cell-Group-InformationList2-ResourceStatusInd  
 id-Power-Local-Cell-Group-ID  
 id-PUSCH-Info-DM-Rqst  
 id-PUSCH-Info-DM-Rsp  
 id-PUSCH-Info-DM-Rprt  
 id-InitDL-Power  
 id-cellSyncBurstRepetitionPeriod  
 id-ReportCharacteristicsType-OnModification  
 id-SFN\_SF\_NMeasurementValueInformation  
 id-SFN\_SF\_NMeasurementThresholdInformation  
 id-TU\_TRA\_NG\_PSMMeasurementValueInformation  
 id-TU\_TRA\_NG\_PSMMeasurementThresholdInformation  
 id-Rx-Timing-Deviation-Value-LCR  
 id-RL-InformationResponse-LCR-RL-AdditionRspTDD  
 id-DL-PowerBalancing-Information  
 id-DL-PowerBalancing-ActivationIndicator  
 id-DL-PowerBalancing-UpdatedIndicator  
 id-CCTrCH-Initial-DL-Power-RL-SetupRqstTDD  
 id-CCTrCH-Initial-DL-Power-RL-AdditionRqstTDD  
 id-CCTrCH-Initial-DL-Power-RL-ReconfPrepTDD

ProtocolIE-ID ::= 466  
 ProtocolIE-ID ::= 467  
 ProtocolIE-ID ::= 468  
 ProtocolIE-ID ::= 469  
 ProtocolIE-ID ::= 470  
 ProtocolIE-ID ::= 472  
 ProtocolIE-ID ::= 473  
 ProtocolIE-ID ::= 474  
 ProtocolIE-ID ::= 475  
 ProtocolIE-ID ::= 477  
 ProtocolIE-ID ::= 479  
 ProtocolIE-ID ::= 480  
 ProtocolIE-ID ::= 481  
 ProtocolIE-ID ::= 483  
 ProtocolIE-ID ::= 485  
 ProtocolIE-ID ::= 510  
 ProtocolIE-ID ::= 486  
 ProtocolIE-ID ::= 487  
 ProtocolIE-ID ::= 26  
 ProtocolIE-ID ::= 27  
 ProtocolIE-ID ::= 488  
 ProtocolIE-ID ::= 489  
 ProtocolIE-ID ::= 490  
 ProtocolIE-ID ::= 491  
 ProtocolIE-ID ::= 492  
 ProtocolIE-ID ::= 493  
 ProtocolIE-ID ::= 496  
 ProtocolIE-ID ::= 497  
 ProtocolIE-ID ::= 498  
 ProtocolIE-ID ::= 499  
 ProtocolIE-ID ::= 500  
 ProtocolIE-ID ::= 501  
 ProtocolIE-ID ::= 502  
 ProtocolIE-ID ::= 503  
 ProtocolIE-ID ::= 504  
 ProtocolIE-ID ::= 505  
 ProtocolIE-ID ::= 506  
 ProtocolIE-ID ::= 507  
 ProtocolIE-ID ::= 509  
 ProtocolIE-ID ::= 511  
 ProtocolIE-ID ::= 512  
 ProtocolIE-ID ::= 513  
 ProtocolIE-ID ::= 514  
 ProtocolIE-ID ::= 515  
 ProtocolIE-ID ::= 516  
 ProtocolIE-ID ::= 520  
 ProtocolIE-ID ::= 51  
 ProtocolIE-ID ::= 28  
 ProtocolIE-ID ::= 29  
 ProtocolIE-ID ::= 30  
 ProtocolIE-ID ::= 517  
 ProtocolIE-ID ::= 518  
 ProtocolIE-ID ::= 519

id-IPDLParameter-Information-LCR-Cell-SetupRqstTDD  
 id-IPDLParameter-Information-LCR-Cell-ReconfRqstTDD  
 id-HS-PDSCH-HS-SCCH-MaxPower-PSCH-ReconfRqst  
 id-HS-PDSCH-HS-SCCH-ScramblingCode-PSCH-ReconfRqst  
 id-HS-PDSCH-FDD-Code-Information-PSCH-ReconfRqst  
 id-HS-SCCH-FDD-Code-Information-PSCH-ReconfRqst  
 id-HS-PDSCH-TDD-Information-PSCH-ReconfRqst  
 id-Add-To-HS-SCCH-Resource-Pool-PSCH-ReconfRqst  
 id-Modify-HS-SCCH-Resource-Pool-PSCH-ReconfRqst  
 id-Delete-From-HS-SCCH-Resource-Pool-PSCH-ReconfRqst  
 id-bindingID  
 id-RL-Specific-DCH-Info  
 id-transportlayeraddress  
 id-DelayedActivation  
 id-DelayedActivationList-RL-ActivationCmdFDD  
 id-DelayedActivationInformation-RL-ActivationCmdFDD  
 id-DelayedActivationList-RL-ActivationCmdTDD  
 id-DelayedActivationInformation-RL-ActivationCmdTDD  
 id-neighbouringTDDCellMeasurementInformationLCR  
 id-SYNCDlCodeId-TransInitLCR-CellSyncInitiationRqstTDD  
 id-SYNCDlCodeId-MeasureInitLCR-CellSyncInitiationRqstTDD  
 id-SYNCDlCodeIdTransReconfInfoLCR-CellSyncReconfRqstTDD  
 id-SYNCDlCodeIdMeasInfoList-CellSyncReconfRqstTDD  
 id-SyncDLCodeIdsMeasInfoList-CellSyncReprtTDD  
 id-SyncDLCodeIdThreInfoLCR  
 id-NSubCyclesPerCyclePeriod-CellSyncReconfRqstTDD  
 id-DwPCH-Power  
 id-AccumulatedClockupdate-CellSyncReprtTDD  
 id-Angle-Of-Arrival-Value-LCR  
 id-HSDSCH-FDD-Information  
 id-HSDSCH-FDD-Information-Response  
 id-HSDSCH-FDD-Information-to-Add  
 id-HSDSCH-FDD-Information-to-Delete  
 id-HSDSCH-Information-to-Modify  
 id-HSDSCH-RNTI  
 id-HSDSCH-TDD-Information  
 id-HSDSCH-TDD-Information-Response  
 id-HSDSCH-TDD-Information-Response-LCR  
 id-HSDSCH-TDD-Information-to-Add  
 id-HSDSCH-TDD-Information-to-Delete  
 id-HSPDSCH-RL-ID  
 id-PrimCCPCH-RSCP-DL-PC-RqstTDD  
 id-Qth-Parameter  
 id-PDSCH-RL-ID  
 id-HSDSCH-RearrangeList-Bearer-RearrangeInd  
 id-UL-Synchronisation-Parameters-LCR  
 id-HSDSCH-FDD-Update-Information  
 id-HSDSCH-TDD-Update-Information  
 id-DL-DPCH-TimeSlotFormat-LCR-ModifyItem-RL-ReconfPrepTDD  
 id-UL-DPCH-TimeSlotFormat-LCR-ModifyItem-RL-ReconfPrepTDD  
 id-TDD-TPC-UplinkStepSize-LCR-RL-SetupRqstTDD  
 id-TDD-TPC-UplinkStepSize-LCR-RL-AdditionRqstTDD

ProtocolIE-ID ::= 41  
 ProtocolIE-ID ::= 42  
 ProtocolIE-ID ::= 522  
 ProtocolIE-ID ::= 523  
 ProtocolIE-ID ::= 524  
 ProtocolIE-ID ::= 525  
 ProtocolIE-ID ::= 526  
 ProtocolIE-ID ::= 527  
 ProtocolIE-ID ::= 528  
 ProtocolIE-ID ::= 529  
 ProtocolIE-ID ::= 102  
 ProtocolIE-ID ::= 103  
 ProtocolIE-ID ::= 104  
 ProtocolIE-ID ::= 231  
 ProtocolIE-ID ::= 232  
 ProtocolIE-ID ::= 233  
 ProtocolIE-ID ::= 234  
 ProtocolIE-ID ::= 235  
 ProtocolIE-ID ::= 58  
 ProtocolIE-ID ::= 543  
 ProtocolIE-ID ::= 544  
 ProtocolIE-ID ::= 545  
 ProtocolIE-ID ::= 546  
 ProtocolIE-ID ::= 547  
 ProtocolIE-ID ::= 548  
 ProtocolIE-ID ::= 549  
 ProtocolIE-ID ::= 550  
 ProtocolIE-ID ::= 551  
 ProtocolIE-ID ::= 552  
 ProtocolIE-ID ::= 521  
 ProtocolIE-ID ::= 530  
 ProtocolIE-ID ::= 531  
 ProtocolIE-ID ::= 532  
 ProtocolIE-ID ::= 533  
 ProtocolIE-ID ::= 534  
 ProtocolIE-ID ::= 535  
 ProtocolIE-ID ::= 536  
 ProtocolIE-ID ::= 537  
 ProtocolIE-ID ::= 538  
 ProtocolIE-ID ::= 539  
 ProtocolIE-ID ::= 540  
 ProtocolIE-ID ::= 541  
 ProtocolIE-ID ::= 542  
 ProtocolIE-ID ::= 64  
 ProtocolIE-ID ::= 66  
 ProtocolIE-ID ::= 553  
 ProtocolIE-ID ::= 554  
 ProtocolIE-ID ::= 555  
 ProtocolIE-ID ::= 556  
 ProtocolIE-ID ::= 558  
 ProtocolIE-ID ::= 559  
 ProtocolIE-ID ::= 560  
 ProtocolIE-ID ::= 561

id-TDD-TPC-DownlinkStepSize-RL-AdditionRqstTDD	ProtocolIE-ID ::= 562
id-TDD-TPC-UplinkStepSize-InformationAdd-LCR-RL-ReconfPrepTDD	ProtocolIE-ID ::= 563
id-TDD-TPC-UplinkStepSize-InformationModify-LCR-RL-ReconfPrepTDD	ProtocolIE-ID ::= 564
id-TDD-TPC-DownlinkStepSize-InformationModify-RL-ReconfPrepTDD	ProtocolIE-ID ::= 565
id-TDD-TPC-DownlinkStepSize-InformationAdd-RL-ReconfPrepTDD	ProtocolIE-ID ::= 566
id-CCTrCH-Maximum-DL-Power-RL-SetupRqstTDD	ProtocolIE-ID ::= 567
id-CCTrCH-Minimum-DL-Power-RL-SetupRqstTDD	ProtocolIE-ID ::= 568
id-CCTrCH-Maximum-DL-Power-RL-AdditionRqstTDD	ProtocolIE-ID ::= 569
id-CCTrCH-Minimum-DL-Power-RL-AdditionRqstTDD	ProtocolIE-ID ::= 570
id-CCTrCH-Maximum-DL-Power-InformationAdd-RL-ReconfPrepTDD	ProtocolIE-ID ::= 571
id-CCTrCH-Minimum-DL-Power-InformationAdd-RL-ReconfPrepTDD	ProtocolIE-ID ::= 572
id-CCTrCH-Maximum-DL-Power-InformationModify-RL-ReconfPrepTDD	ProtocolIE-ID ::= 573
id-CCTrCH-Minimum-DL-Power-InformationModify-RL-ReconfPrepTDD	ProtocolIE-ID ::= 574
id-Maximum-DL-Power-Modify-LCR-InformationModify-RL-ReconfPrepTDD	ProtocolIE-ID ::= 575
id-Minimum-DL-Power-Modify-LCR-InformationModify-RL-ReconfPrepTDD	ProtocolIE-ID ::= 576
id-DL-DPCH-LCR-InformationModify-ModifyList-RL-ReconfRqstTDD	ProtocolIE-ID ::= 577
id-CCTrCH-Maximum-DL-Power-InformationModify-RL-ReconfRqstTDD	ProtocolIE-ID ::= 578
id-CCTrCH-Minimum-DL-Power-InformationModify-RL-ReconfRqstTDD	ProtocolIE-ID ::= 579
id-Initial-DL-Power-TimeslotLCR-InformationItem	ProtocolIE-ID ::= 580
id-Maximum-DL-Power-TimeslotLCR-InformationItem	ProtocolIE-ID ::= 581
id-Minimum-DL-Power-TimeslotLCR-InformationItem	ProtocolIE-ID ::= 582
id-TransmittedCarrierPowerOfAllCodesNotUsedForHS-PDSCHOrHS-SCCHTransmission	ProtocolIE-ID ::= 587
id-HS-SICH-Reception-Quality	ProtocolIE-ID ::= 588
id-HS-SICH-Reception-Quality-Measurement-Value	ProtocolIE-ID ::= 589
id-HSSICH-Info-DM-Rprt	ProtocolIE-ID ::= 590
id-HSSICH-Info-DM-Rqst	ProtocolIE-ID ::= 591
id-HSSICH-Info-DM-Rsp	ProtocolIE-ID ::= 592
<u>id-Best-Cell-Portions-Value</u>	ProtocolIE-ID ::= 593
<u>id-Primary-CPICH-Usage-for-Channel-Estimation</u>	ProtocolIE-ID ::= 594
<u>id-Secondary-CPICH-Information-Change</u>	ProtocolIE-ID ::= 595
<u>id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation</u>	ProtocolIE-ID ::= 596
<u>id-UE-Support-Of-Dedicated-Pilots-For-Channel-Estimation-Of-HS-DSCH</u>	ProtocolIE-ID ::= 597

END