





### 5.1.4 Timeslot ISCP

<b>Definition</b>	Interference Signal Code Power, the interference on the received signal in a specified timeslot <del>after despreading</del> . Only the non-orthogonal part of the interference <u>shall be</u> included in the measurement. The reference point for the ISCP is the antenna connector at the UE.
<b>Applicable for</b>	connected mode (intra-frequency)
<b>Range/mapping</b>	Timeslot ISCP is given with a resolution of 1 dBm with the range [-115, ..., -25] dBm. Timeslot ISCP shall be reported in the unit <del>UE_TS_ISCP_LEV</del> where: <del>UE_TS_ISCP_LEV00:</del> Timeslot_ISCP < -115dBm <del>UE_TS_ISCP_LEV01:</del> -115dBm ≤ Timeslot_ISCP < -114dBm <del>UE_TS_ISCP_LEV02:</del> -114dBm ≤ Timeslot_ISCP < -113dBm ... <del>UE_TS_ISCP_LEV89:</del> -27dBm ≤ Timeslot_ISCP < -26dBm <del>UE_TS_ISCP_LEV90:</del> -26dBm ≤ Timeslot_ISCP < -25dBm <del>UE_TS_ISCP_LEV91:</del> -25dBm ≤ Timeslot_ISCP

### 5.1.5 UTRA carrier RSSI

<b>Definition</b>	Received Signal Strength Indicator, the wide-band received power within the relevant channel bandwidth in a specified timeslot. Measurement shall be performed on a UTRAN DL carrier. The reference point for the RSSI is the antenna connector at the UE.
<b>Applicable for</b>	idle mode, connected mode (intra- & inter-frequency)
<b>Range/mapping</b>	UTRA carrier RSSI is given with a resolution of 1 dBm with the range [-94, ..., -32] dBm. UTRA carrier RSSI shall be reported in the unit UTRA_carrier_RSSI_LEV where: UTRA_carrier_RSSI_LEV00: UTRA_carrier_RSSI < -94dBm UTRA_carrier_RSSI_LEV01: -94dBm ≤ UTRA_carrier_RSSI < -93dBm UTRA_carrier_RSSI_LEV02: -93dBm ≤ UTRA_carrier_RSSI < -92dBm ... UTRA_carrier_RSSI_LEV61: -34dBm ≤ UTRA_carrier_RSSI < -33dBm UTRA_carrier_RSSI_LEV62: -33dBm ≤ UTRA_carrier_RSSI < -32dBm UTRA_carrier_RSSI_LEV63: -32dBm ≤ UTRA_carrier_RSSI

### 5.1.6 GSM carrier RSSI

<b>Definition</b>	Received Signal Strength Indicator, the wide-band received power within the relevant channel bandwidth in a specified timeslot. Measurement shall be performed on a GSM BCCH carrier. The reference point for the RSSI is the antenna connector at the UE.
<b>Applicable for</b>	idle mode, connected mode (inter-frequency)
<b>Range/mapping</b>	According to the definition of RXLEV in GSM 05.08.

### 5.1.7 SIR

<b>Definition</b>	<p><u>Signal to Interference Ratio, defined as: <math>(RSCP/ISCP) \times SF</math>. The reference point for the SIR is the antenna connector of the UE.</u></p> <p>where:  <u>RSCP = Received Signal Code Power, the received power on the code of a specified DPCH or PDSCH.</u>  <u>ISCP = Interference Signal Code Power, the interference on the received signal. Only the non-orthogonal part of the interference is included in the measurement.</u>  <u>SF = The spreading factor used.</u></p> <p><u>Signal to Interference Ratio, defined as the RSCP of a DPCH or PDSCH divided by ISCP of the same timeslot. The reference point for the SIR is the antenna connector of the UE.</u></p>																					
<b>Applicable for</b>	connected mode (intra-frequency)																					
<b>Range/mapping</b>	<p>SIR is given with a resolution of 0.5 dB with the range [-11, ..., 20] dB.                      SIR shall be reported in the unit SIR where:</p> <table border="0"> <tr> <td>SIR_00:</td> <td></td> <td>SIR &lt; -11.0dB</td> </tr> <tr> <td>SIR_01:</td> <td>-11.0dB ≤</td> <td>SIR &lt; -10.5dB</td> </tr> <tr> <td>SIR_02:</td> <td>-10.5dB ≤</td> <td>SIR &lt; -10.0dB</td> </tr> <tr> <td>....</td> <td></td> <td></td> </tr> <tr> <td>SIR_61:</td> <td>19.0dB ≤</td> <td>SIR &lt; 19.5dB</td> </tr> <tr> <td>SIR_62:</td> <td>19.5dB ≤</td> <td>SIR &lt; 20.0dB</td> </tr> <tr> <td>SIR_63:</td> <td>20.0dB ≤</td> <td>SIR</td> </tr> </table>	SIR_00:		SIR < -11.0dB	SIR_01:	-11.0dB ≤	SIR < -10.5dB	SIR_02:	-10.5dB ≤	SIR < -10.0dB	....			SIR_61:	19.0dB ≤	SIR < 19.5dB	SIR_62:	19.5dB ≤	SIR < 20.0dB	SIR_63:	20.0dB ≤	SIR
SIR_00:		SIR < -11.0dB																				
SIR_01:	-11.0dB ≤	SIR < -10.5dB																				
SIR_02:	-10.5dB ≤	SIR < -10.0dB																				
....																						
SIR_61:	19.0dB ≤	SIR < 19.5dB																				
SIR_62:	19.5dB ≤	SIR < 20.0dB																				
SIR_63:	20.0dB ≤	SIR																				

### 5.1.8 CPICH Ec/No

<b>Definition</b>	The received energy per chip divided by the power density in the band. The Ec/No is identical to RSCP/RSSI. The reference point for Ec/No is the antenna connector at the UE.																					
<b>Applicable for</b>	idle mode, connected mode (inter-frequency)																					
<b>Range/mapping</b>	<p>CPICH Ec/No is given with a resolution of 1 dB with the range [-24, ..., 0] dB.                      CPICH Ec/No shall be reported in the unit CPICH_Ec/No where:</p> <table border="0"> <tr> <td>CPICH_Ec/No_00:</td> <td></td> <td>CPICH_Ec/No &lt; -24dB</td> </tr> <tr> <td>CPICH_Ec/No_01:</td> <td>-24dB ≤</td> <td>CPICH_Ec/No &lt; -23dB</td> </tr> <tr> <td>CPICH_Ec/No_02:</td> <td>-23dB ≤</td> <td>CPICH_Ec/No &lt; -22dB</td> </tr> <tr> <td>...</td> <td></td> <td></td> </tr> <tr> <td>CPICH_Ec/No_23:</td> <td>-2dB ≤</td> <td>CPICH_Ec/No &lt; -1dB</td> </tr> <tr> <td>CPICH_Ec/No_24:</td> <td>-1dB ≤</td> <td>CPICH_Ec/No &lt; 0dB</td> </tr> <tr> <td>CPICH_Ec/No_25:</td> <td>0dB ≤</td> <td>CPICH_Ec/No</td> </tr> </table>	CPICH_Ec/No_00:		CPICH_Ec/No < -24dB	CPICH_Ec/No_01:	-24dB ≤	CPICH_Ec/No < -23dB	CPICH_Ec/No_02:	-23dB ≤	CPICH_Ec/No < -22dB	...			CPICH_Ec/No_23:	-2dB ≤	CPICH_Ec/No < -1dB	CPICH_Ec/No_24:	-1dB ≤	CPICH_Ec/No < 0dB	CPICH_Ec/No_25:	0dB ≤	CPICH_Ec/No
CPICH_Ec/No_00:		CPICH_Ec/No < -24dB																				
CPICH_Ec/No_01:	-24dB ≤	CPICH_Ec/No < -23dB																				
CPICH_Ec/No_02:	-23dB ≤	CPICH_Ec/No < -22dB																				
...																						
CPICH_Ec/No_23:	-2dB ≤	CPICH_Ec/No < -1dB																				
CPICH_Ec/No_24:	-1dB ≤	CPICH_Ec/No < 0dB																				
CPICH_Ec/No_25:	0dB ≤	CPICH_Ec/No																				

### 5.1.9 Physical channel BER

<b>Definition</b>	The physical channel BER is an estimation of the average bit error rate (BER) before <u>rate matching processing</u> <del>channel decoding</del> of the data. <u>Only bits from channel coded transport channels shall be taken into account in the estimation.</u>
<b>Applicable for</b>	connected mode (intra-frequency)

<b>Range/mapping</b>	Physical channel BER is given with a logarithmic resolution of 0.065 with the range [10 <sup>-4.03</sup> ... 1] including a separate case Physical channel BER=0. Physical channel BER shall be reported in the unit <del>PhCH_BER_dB</del> <u>PhCH_BER_dBBER_LOG</u> , where: <del>PhCH_BER_dB</del> <u>PhCH_BER_dBBER_LOG</u> 00: BER = 0 <del>PhCH_BER_dB</del> <u>PhCH_BER_dBBER_LOG</u> 01: -∞ < Log10(Physical channel BER) < -4.030 <del>PhCH_BER_dB</del> <u>PhCH_BER_dBBER_LOG</u> 02: -4.030 ≤ Log10(Physical channel BER) < -3.965 <del>PhCH_BER_dB</del> <u>PhCH_BER_dBBER_LOG</u> 03: -3.965 ≤ Log10(Physical channel BER) < -3.900 ... <del>PhCH_BER_dB</del> <u>PhCH_BER_dBBER_LOG</u> 61: -0.195 ≤ Log10(Physical channel BER) < -0.130 <del>PhCH_BER_dB</del> <u>PhCH_BER_dBBER_LOG</u> 62: -0.130 ≤ Log10(Physical channel BER) < -0.065 <del>PhCH_BER_dB</del> <u>PhCH_BER_dBBER_LOG</u> 63: -0.065 ≤ Log10(Physical channel BER) ≤ 0.000
----------------------	---

### 5.1.10 Transport channel BLER

<b>Definition</b>	Estimation of the transport channel block error rate (BLER). The BLER estimation shall be based on evaluating the CRC on each transport block.
<b>Applicable for</b>	connected mode (intra-frequency)
<b>Range/mapping</b>	Transport channel BLER is given with a logarithmic resolution of 0.065 with the range [10 <sup>-4.03</sup> ... 1] including a separate case Transport channel BLER=0. Transport channel BLER shall be reported in the unit <del>TCH_BLER_dB</del> <u>TCH_BLER_dBBLER_LOG</u> , where: <del>TCH_BLER_dB</del> <u>TCH_BLER_dBBLER_LOG</u> 00: BLER = 0 <del>TCH_BLER_dB</del> <u>TCH_BLER_dBBLER_LOG</u> 01: -∞ < Log10(Transport channel BLER) < -4.030 <del>TCH_BLER_dB</del> <u>TCH_BLER_dBBLER_LOG</u> 02: -4.030 ≤ Log10(Transport channel BLER) < -3.965 <del>TCH_BLER_dB</del> <u>TCH_BLER_dBBLER_LOG</u> 03: -3.965 ≤ Log10(Transport channel BLER) < -3.900 ... <del>TCH_BLER_dB</del> <u>TCH_BLER_dBBLER_LOG</u> 61: -0.195 ≤ Log10(Transport channel BLER) < -0.130 <del>TCH_BLER_dB</del> <u>TCH_BLER_dBBLER_LOG</u> 62: -0.130 ≤ Log10(Transport channel BLER) < -0.065 <del>TCH_BLER_dB</del> <u>TCH_BLER_dBBLER_LOG</u> 63: -0.065 ≤ Log10(Transport channel BLER) ≤ 0.000

### 5.1.11 UE transmitted power

<b>Definition</b>	The total UE transmitted power on one carrier measured in a timeslot. The reference point for the UE transmitted power shall be the UE antenna connector.
<b>Applicable for</b>	connected mode (intra-frequency).





## 5.2.2 Timeslot ISCP

<b>Definition</b>	Interference Signal Code Power, the interference on the received signal in a specified timeslot <u>after despreading</u> . Only the non-orthogonal part of the interference <u>shall be</u> included in the measurement. The reference point for the ISCP shall be the antenna connector.
<b>Range/mapping</b>	Timeslot ISCP is given with a resolution of 0.5 dBm with the range [-120, ..., -80] dBm. Timeslot ISCP shall be reported in the unit <u>UTRAN_TS_ISCP_LEV</u> where: UTRAN_TS_ISCP_LEV00: Timeslot_ISCP < -120.0dBm UTRAN_TS_ISCP_LEV01: -120.0dBm ≤ Timeslot_ISCP < -119.5dBm UTRAN_TS_ISCP_LEV02: -119.5dBm ≤ Timeslot_ISCP < -119.0dBm ... UTRAN_TS_ISCP_LEV79: -81.0dBm ≤ Timeslot_ISCP < -80.5dBm UTRAN_TS_ISCP_LEV80: -80.5dBm ≤ Timeslot_ISCP < -80.0dBm UTRAN_TS_ISCP_LEV81: -80.0dBm ≤ Timeslot_ISCP

## 5.2.3 RSSI

<b>Definition</b>	Received Signal Strength Indicator, the wide-band received power within the UTRAN UL <u>carrier</u> channel bandwidth in a specified timeslot. The reference point for the RSSI shall be the antenna connector.
<b>Range/mapping</b>	RSSI is given with a resolution of 0.5dBm with the range [-105, ..., -74] dBm. RSSI shall be reported in the unit <u>RSSI_LEV</u> , where: RSSI_LEV00: RSSI < -105.0dBm RSSI_LEV01: -105.0dBm ≤ RSSI < -104.5dBm RSSI_LEV02: -104.5dBm ≤ RSSI < -104.0dBm ... RSSI_LEV61: -75.0dBm ≤ RSSI < -74.5dBm RSSI_LEV62: -74.5dBm ≤ RSSI < -74.0dBm RSSI_LEV63: -74.0dBm ≤ RSSI

## 5.2.4 SIR

<b>Definition</b>	Signal to Interference Ratio, defined as: $(RSCP/ISCP) \times SF$ . The reference point for the SIR is <u>the antenna connector of the UE</u> .  <u>where:</u> <u>RSCP = Received Signal Code Power, the received power on the code of a specified DPCH, PRACH or PUSCH.</u> <u>ISCP = Interference Signal Code Power, the interference on the received signal. Only the non-orthogonal part of the interference is included in the measurement.</u> <u>SF = The spreading factor used.</u> Signal to Interference Ratio, defined as the <u>RSCP of the DPCH or PUSCH</u> divided by <u>ISCP of the same timeslot</u> . The reference point for the SIR shall be the antenna connector.
-------------------	---



## 5.2.7 Transmitted carrier power

<b>Definition</b>	<p>Transmitted carrier power, is the ratio between the total transmitted power on one carrier [W] from one UTRAN access point and the maximum transmission power [W] that is possible to use on the same carrier during the measurement period, where the maximum transmission power is the configured maximum transmission power for the cell. Measurement shall be possible on any carrier transmitted from the UTRAN access point. The reference point for the transmitted carrier power measurement shall be the antenna connector. In case of Tx diversity the transmitted carrier power for each branch shall be measured. Transmitted carrier power, is the total transmitted power on one DL carrier from one UTRAN access point measured in a timeslot. The reference point for the UTRAN total transmitted power measurement shall be the antenna connector.</p>
<b>Range/mapping</b>	<p>Transmitted carrier power is given with a resolution of 1 %-unit with the range [0, ..., 100] %                  Transmitted carrier power shall be reported in the unit UTRAN_TX_POWER where:</p> <p>UTRAN_TX_POWER_000: Transmitted carrier power = 0 %                  UTRAN_TX_POWER_001: 0 % &lt; Transmitted carrier power ≤ 1 %                  UTRAN_TX_POWER_002: 1 % &lt; Transmitted carrier power ≤ 2 %                  UTRAN_TX_POWER_003: 2 % &lt; Transmitted carrier power ≤ 3 %                  ...                  UTRAN_TX_POWER_098: 97 % &lt; Transmitted carrier power ≤ 98 %                  UTRAN_TX_POWER_099: 98 % &lt; Transmitted carrier power ≤ 99 %                  UTRAN_TX_POWER_100: 99 % &lt; Transmitted carrier power ≤ 100 %                  Transmitted carrier power is given with a resolution of 0.5dBm with the range [0, ..., 50] dBm.                  Transmitted carrier power shall be reported in the unit UTRAN_TX_POWER, where:                  UTRAN_TX_POWER_000 to UTRAN_TX_POWER_015: reserved                  UTRAN_TX_POWER_016: 0.0dBm ≤ Transmitted carrier power &lt; 0.5dBm                  UTRAN_TX_POWER_017: 0.5dBm ≤ Transmitted carrier power &lt; 1.0dBm                  UTRAN_TX_POWER_018: 1.0dBm ≤ Transmitted carrier power &lt; 1.5dBm                  ...                  UTRAN_TX_POWER_114: 49.0dBm ≤ Transmitted carrier power &lt; 49.5dBm                  UTRAN_TX_POWER_115: 49.5dBm ≤ Transmitted carrier power &lt; 50.0dBm                  UTRAN_TX_POWER_116: 50.0dBm ≤ Transmitted carrier power &lt; 50.5dBm</p>

## 5.2.8 Transmitted code power

<b>Definition</b>	<p>Transmitted Code Power, is the transmitted power on one carrier and one channelisation code in one timeslot. The reference point for the transmitted code power measurement shall be the antenna connector at the UTRAN access point cabinet.</p>
<b>Range/mapping</b>	<p>Transmitted code power is given with a resolution of 0.5dBm with the range [-10, ..., 46] dBm.                  Transmitted code power shall be reported in the unit UTRAN_TX_CODE_POWER, where:                  UTRAN_TX_CODE_POWER_000 to UTRAN_TX_CODE_POWER_009: reserved                  UTRAN_TX_CODE_POWER_010: -10.0dBm ≤ CODE_POWER &lt; -9.5dBm                  UTRAN_TX_CODE_POWER_011: -9.5dBm ≤ CODE_POWER &lt; -8.5dBm                  UTRAN_TX_CODE_POWER_012: -8.5dBm ≤ CODE_POWER &lt; -7.5dBm                  ...                  UTRAN_TX_CODE_POWER_120: 45.0dBm ≤ CODE_POWER &lt; 45.5dBm                  UTRAN_TX_CODE_POWER_121: 45.5dBm ≤ CODE_POWER &lt; 46.0dBm                  UTRAN_TX_CODE_POWER_122: 46.0dBm ≤ CODE_POWER &lt; 46.5dBm</p>

## 5.2.9 RX Timing Deviation

<b>Definition</b>	<p>'RX Timing Deviation' is the time difference <math>TRX_{dev} = TTS - TRX_{path}</math> in chips, with</p> <p><math>TRX_{path}</math> : time of the reception in the Node B of the first significant uplink path to be used in the detection process</p> <p><math>TTS</math> : time of the beginning of the respective slot according to the Node B internal timing</p>
<b>Range/mapping</b>	<p>RX Timing Deviation is given with a resolution of 0.25 chip with the range [0; 1024) chips (12 bit).                  RX Timing Deviation cell shall be reported in the unit <code>RX_TIME_DEV</code>, where  <math>RX\_TIME\_DEV: N * 0.25 \text{ chips} \leq RX \text{ Timing Deviation} &lt; (N+1) * 0.25 \text{ chips}</math>                  With <math>N = 0, 1, 2, \dots, 4095</math></p>

**NOTE:** This measurement can be used for timing advance calculation or location services.