
Agenda Item: 12.4
Source: NEC Group
Title: MU-MIMO: Demodulation at the Mobile Station
Document for: Discussion and Decision

1 Introduction

In this document, we consider MU-MIMO where the base station (eNodeB) may schedule several user terminals on the same resource unit. Each scheduled user equipment (UE) is served only a single stream via codebook based precoding. We examine the various demodulator options that are available to a scheduled user depending on the information it has about the precoding vectors, power levels and modulations used to serve the co-scheduled users. Our initial simulation results indicate that providing a scheduled UE knowledge of the modulations used for the other co-scheduled UEs, in addition to their corresponding precoding vectors and power levels, can result in significant performance gains. The gains are obtained due to more sophisticated demodulators that can be employed by the UE to combat residual multi-user interference.

2 Demodulation at the UE

Consider the received signal model on any subcarrier at a user terminal k , which is equipped with N receive antennas and where the eNodeB has M transmit antennas,

$$\mathbf{y}_k = \mathbf{H}_k \mathbf{x} + \mathbf{v}_k, \quad (1)$$

where $\mathbf{H}_k \in \mathbb{C}^{N \times M}$ is the channel matrix and $\mathbf{v}_k \sim \mathcal{CN}(\mathbf{0}, \mathbf{I})$ is the additive noise. The signal vector \mathbf{x} transmitted by the eNodeB can be expanded as

$$\mathbf{x} = \sum_{k \in \mathcal{S}} \mathbf{g}_k s_k \quad (2)$$

where \mathcal{S} is the set of users that are scheduled on the same resource unit, \mathbf{g}_k is the precoding vector and s_k is the data symbol corresponding to user $k \in \mathcal{S}$. The precoding vectors are selected from a codebook \mathcal{C} of unit-norm vectors. The sum power constraint is given by $E[\mathbf{x}^\dagger \mathbf{x}] = \sum_{k=1}^{|\mathcal{S}|} E[|s_k|^2] \leq \rho$. We assume that each scheduled user is informed about the precoding vector, power level as well as the MCS assigned to it by the eNodeB.

The demodulators that are usually considered for an MU-MIMO UE are the linear combiner based demodulators, which in particular are the MRC and MMSE based demodulators. We review these demodulators in Appendix 5.1 and 5.2. Note that in order to employ the MMSE demodulator, the UE must be aware of the precoding vectors and power levels used to serve the other co-scheduled UEs. In the following section we consider another demodulator.

2.1 Non-linear Demodulators

In order to further improve the performance, the user of interest (user-1) may employ non-linear demodulators. Suppose that the user knows the precoding vectors and power levels used to serve the other co-scheduled users. Moreover, the user also knows the modulations used to serve some or all of the other co-scheduled users. In particular, let $\mathcal{J} \subseteq \mathcal{S}$ denote the set of users whose corresponding modulations are known to user 1 and clearly $1 \in \mathcal{J}$. Then, user 1 can first design a filter to suppress the interference from the signals intended for the other co-scheduled users not in \mathcal{J} to obtain the model

$$\mathbf{z} \triangleq \left(\mathbf{I} + \tilde{\rho} \mathbf{H}_1 \sum_{k \notin \mathcal{J}} \mathbf{g}_k \mathbf{g}_k^\dagger \mathbf{H}_1^\dagger \right)^{-1/2} \mathbf{y}_1 = \left(\mathbf{I} + \tilde{\rho} \mathbf{H}_1 \sum_{k \notin \mathcal{J}} \mathbf{g}_k \mathbf{g}_k^\dagger \mathbf{H}_1^\dagger \right)^{-1/2} \mathbf{H}_1 \sum_{k \in \mathcal{J}} \mathbf{g}_k s_k + \boldsymbol{\eta}, \quad (3)$$

Parameter	Assumption
Bandwidth	10.0 MHz
FFT size	1024
Resource block size	24 subcarriers and 6 OFDM symbols
Sub-carrier spacing	15.0 kHz
Number of data sub-carriers per OFDM symbol	900
Coding rates	1/2; 2/3
Number of information bits per block	768 (R=1/2); 512(R=2/3)
Rank-1 precoding codebook	3-bit codebook
Number of antennas at eNodeB	4
Number of antennas at UE	2
Channel model	SCM

Table 1: Simulation Parameters

where $\tilde{\rho} = \frac{\rho}{|\mathcal{S}|}$ and $E[\boldsymbol{\eta}\boldsymbol{\eta}^\dagger] = \mathbf{I}$. Letting $\mathbf{B} = \left(\mathbf{I} + \tilde{\rho}\mathbf{H}_1 \sum_{k \notin \mathcal{J}} \mathbf{g}_k \mathbf{g}_k^\dagger \mathbf{H}_1^\dagger\right)^{-1/2} \mathbf{H}_1 \mathbf{G}_{\mathcal{J}}$ with $\mathbf{G}_{\mathcal{J}} = [\mathbf{g}_k]_{k \in \mathcal{J}}$ denoting the $N \times |\mathcal{J}|$ matrix formed by the precoding vectors employed to serve users in \mathcal{J} and $\mathbf{s}_{\mathcal{J}}$ denoting the $|\mathcal{J}| \times 1$ vector formed by the corresponding symbols transmitted to those users, the model in (3) can be re-written as

$$\mathbf{z} = \mathbf{B}\mathbf{s}_{\mathcal{J}} + \boldsymbol{\eta}. \quad (4)$$

Now we can employ several suitable non-linear demodulators, such as the soft-output sphere decoder [2] and its recent lower-complexity variants over the model in (4). *The key point to be noted is that the LLRs need to be generated only for the coded bits in the symbol s_1 . Note that in order to generate these LLRs, we do not need any information about the coding rates employed to serve any user in \mathcal{J} . This is particularly useful since there are only three distinct modulations that can be used to serve each scheduled user. Also, no attempt is made to decode the codeword of any other user (apart from user 1) in \mathcal{J} .* A particular non-linear demodulator, referred to as the partial-MLD, is provided in Appendix-5.3.

3 Simulation results


The block error rate (BLER) performance is investigated via link-level simulations. We assume that the eNodeB has four transmit antennas whereas the user of interest (UE-1) has two receive antennas. UE-1 reports its preferred PMI (per resource block)¹ to the eNodeB. On each RB, the eNodeB then serves UE-1 using its reported precoding vector and a fixed MCS. It also randomly picks a modulation and another precoding vector per-RB (that is near-orthogonal to the one reported by UE-1) meant for the co-scheduled user. The BLER performance obtained using the match filter (MF) based demodulator, the LMMSE based demodulator and the partial-MLD based demodulator is shown in the following figures. Other specific simulation parameters are listed in Table 1.

In Fig. 1(a), we compare the performance obtained using the linear MF (or MRC), the linear MMSE and the non-linear partial-MLD demodulators, respectively, for QPSK modulation. The (rank-1) precoding matrix index (PMI) feedback is reported for each resource block. It is seen that the partial-MLD demodulator has much better performance than both MF and LMMSE demodulators. For example, at a BLER of 10^{-2} , the partial-MLD has 2dB and 2.5dB gains, respectively, over the LMMSE for $R=1/2$ and $R=2/3$.


In Fig. 1(b), we compare the performance obtained using the linear MMSE and the non-linear partial-MLD demodulators, respectively, for 16 QAM modulation. The PMI feedback is again reported for each resource block. It is seen that the partial-MLD demodulator yields an even larger gain over the LMMSE demodulator. For instance, the partial-MLD has 2dB and 4.0dB gains, respectively, over the LMMSE for $R=1/2$ and $R=2/3$.

In a practical scenario, each UE will be allowed to report only one (or a few) PMIs. We anticipate more gains from the partial-MLD demodulator over the linear demodulators in this case since more severe multi-user interference is expected, which is particularly detrimental to the performance of linear demodulators.

¹The UE uses the SU-MIMO rank-1 rule to determine its preferred PMI.



(a) Block error rate performance for QPSK



(b) Block error rate performance for 16 QAM

Figure 1: BLER performance with independent PMI per RB.

4 Conclusions

It is evident that the linear combiner which requires no information about other co-scheduled users results in the least amount of (feedforward) signaling overhead. Such combiners rely on a large extent on the precoder employed by the transmitter (eNodeB) to mitigate or remove the interference seen by them. If the eNodeB has perfect knowledge of the channel matrix ² of each user on each subcarrier, it can employ a zero-forcing based precoder to ensure that each scheduled user sees no interference from transmission to other co-scheduled users. In such a scenario the MRC combiner is optimal.

However, in practical FDD systems with limited feedback, providing such perfect channel knowledge about each user to the eNodeB is not possible, particularly in the wideband OFDMA based downlink, where each user's channel response matrix varies across subcarriers. Consequently, the users may need to employ more sophisticated demodulators to combat residual interference and help the system realize the benefit of multi-user MIMO. These sophisticated demodulators need the knowledge about some scheduling parameters of other co-scheduled users such as their precoding vectors, power levels and modulations. Fortunately, such parameters for each scheduled user are anyway transmitted in the user-specific part of the control channel. The signaling should be designed in an appropriate manner so that an MU-MIMO user can deduce such parameters of other co-scheduled MU-MIMO users.

5 Appendix

5.1 Linear Combiner: Match Filter Linear Combiner

A popular linear combiner is the match filter (a.k.a. maximum ratio combiner (MRC)) which is optimal in the absence of interference from the signals intended for the other co-scheduled

²As suggested in [1], each user can use a linear combiner to convert its channel matrix into an effective channel vector and report the latter to the eNodeB.

users. In order to employ this linear combiner, the user of interest (say user 1) does not need to know any information about the co-scheduled users and it can demodulate its own data by completely neglecting the co-channel interference resulting from the transmission intended for the other co-scheduled users. In particular, user 1 employs the unit norm combiner given by,

$$\mathbf{u} = \frac{\mathbf{H}_1 \mathbf{g}_1}{\|\mathbf{H}_1 \mathbf{g}_1\|}. \quad (5)$$

The received signal at user 1 post-combining can now be written as

$$\mathbf{u}_1^\dagger \mathbf{y}_1 = \mathbf{u}_1^\dagger \mathbf{H}_1 \mathbf{g}_1 s_1 + \sum_{k \in \mathcal{S}, k \neq 1} \mathbf{u}_1^\dagger \mathbf{H}_1 \mathbf{g}_k s_k + \tilde{v}_1 \quad (6)$$

and note that due to our normalization $E[|\tilde{v}_1|^2] = 1$. In order to compute the log-likelihood ratios (LLRs) for the coded bits corresponding to the symbol s_1 , the user can completely neglect the interference term $\sum_{k \in \mathcal{S}, k \neq 1} \mathbf{u}_1^\dagger \mathbf{H}_1 \mathbf{g}_k s_k$ and assume the SNR to be $\rho_1 \|\mathbf{H}_1 \mathbf{g}_1\|^2$, where $\rho_1 = E[|s_1|^2]$. Alternatively, an estimate of the true SINR can instead be determined. However, the accuracy of such an estimate depends on the number of sample observations available.

The MRC based demodulator can result in substantial performance degradation when the interference power is not negligible compared to that of the additive noise. This is particularly true at high SNR. In order to design a better linear combiner for such scenarios, a quantization error minimization approach is employed in [1]. In particular, assuming $N < M$, the linear combiner used by the UE is now given by

$$\mathbf{u}_1 = \frac{(\mathbf{g}_1^\dagger \mathbf{H}_1^+)^{\dagger}}{\|\mathbf{g}_1^\dagger \mathbf{H}_1^+\|} \quad (7)$$

where $\mathbf{H}_1^+ = \mathbf{H}_1^\dagger (\mathbf{H}_1 \mathbf{H}_1^\dagger)^{-1}$ denotes the pseudo-inverse. In general, the user can use any linear combiner \mathbf{u}_1 (which could have been pre-computed based only on the channel estimate \mathbf{H}_1). Upon using such a combiner, the resulting model is given by (6) and the LLRs can either

be computed by completely neglecting the interference and using the SNR $\rho_1 \|\mathbf{u}_1^\dagger \mathbf{H}_1 \mathbf{g}_1\|^2$ or by using an estimated SINR.

5.2 Linear Combiner: MMSE Linear Combiner

In some scenarios, each scheduled user can also deduce the precoding vectors and power levels used to serve the other co-scheduled users. In this case, assuming that the transmit power is equally split among all scheduled users, user 1 can determine the optimal minimum mean squared error (MMSE) linear combiner as

$$\mathbf{u}_1 = \left(\mathbf{I} + \tilde{\rho} \sum_{k \in \mathcal{S}, k \neq 1} \mathbf{H}_1 \mathbf{g}_k \mathbf{g}_k^\dagger \mathbf{H}_1^\dagger \right)^{-1} \mathbf{H}_1 \mathbf{g}_1, \quad (8)$$

where $\tilde{\rho} = \frac{\rho}{|\mathcal{S}|}$. The resulting SINR is determined to be

$$\tilde{\rho} \mathbf{g}_1^\dagger \mathbf{H}_1^\dagger \left(\mathbf{I} + \tilde{\rho} \sum_{k \in \mathcal{S}, k \neq 1} \mathbf{H}_1 \mathbf{g}_k \mathbf{g}_k^\dagger \mathbf{H}_1^\dagger \right)^{-1} \mathbf{H}_1 \mathbf{g}_1. \quad (9)$$

5.3 Partial-MLD

We next illustrate one non-linear demodulator, referred to as the partial-MLD. Suppose that $\mathcal{J} = \{1, 2\}$ and that user-1 has two receive antennas so that $\mathbf{B} = [\mathbf{b}_1, \mathbf{b}_2]$ is a 2×2 matrix. Denote $\tilde{\mathbf{b}}_i \triangleq \mathbf{b}_i / \|\mathbf{b}_i\|$, $i = 1, 2$, where $\|\mathbf{b}_i\| = \sqrt{\mathbf{b}_i^\dagger \mathbf{b}_i}$. Let $\mathbf{B} = \|\mathbf{b}_2\| \mathbf{U} \mathbf{L}$ be the modified QR decomposition of \mathbf{B} with $\mathbf{U} = [\mathbf{u}_1, \mathbf{u}_2]$ being a semi-unitary matrix such that $\mathbf{U}^\dagger \mathbf{U} = \mathbf{I}$ and \mathbf{L} being lower triangular with positive diagonal elements. In particular, we have

$$\mathbf{u}_1 = \frac{\tilde{\mathbf{b}}_1 - \rho \tilde{\mathbf{b}}_2}{\sqrt{1 - |\rho|^2}}, \quad \mathbf{u}_2 = \tilde{\mathbf{b}}_2, \quad \text{with } \rho \triangleq \tilde{\mathbf{b}}_2^\dagger \tilde{\mathbf{b}}_1, \quad (10)$$

$$\text{and } \mathbf{L} = \begin{bmatrix} l_{11} & 0 \\ l_{21} & 1 \end{bmatrix}, \quad \text{with } l_{11} = \frac{\|\mathbf{b}_1\|}{\|\mathbf{b}_2\|} \sqrt{1 - |\rho|^2}, \quad l_{21} = \frac{\|\mathbf{b}_1\|}{\|\mathbf{b}_2\|} \rho. \quad (11)$$

We then obtain

$$\mathbf{w} \triangleq \mathbf{U}^\dagger \mathbf{z} / \|\mathbf{b}_2\| = \mathbf{L} \mathbf{s}_{\mathcal{J}} + \hat{\mathbf{n}}, \quad (12)$$

where $\mathbf{w} = [w_1, w_2]^T$, $\mathbf{s}_{\mathcal{J}} = [s_1, s_2]^T$ and $E[\hat{\mathbf{n}}\hat{\mathbf{n}}^\dagger] = \|\mathbf{b}_2\|^{-2} \mathbf{I}$. Let s_i^{R} and s_i^{I} denote the real and imaginary parts of s_i , $i = 1, 2$, respectively. For the j -th possibility of symbol s_1 , denoted as $s_{1,j}$, we define the metric

$$Q(s_{1,j}) \triangleq |w_1 - l_{11}s_{1,j}|^2 + \min_{s_2 \in \mathcal{S}_2} |w_2 - l_{21}s_{1,j} - s_2|^2, \quad (13)$$

where \mathcal{S}_2 denotes the constellation (modulation-type) of user-2. Suppose the modulation \mathcal{S}_1 assigned to user-1 is M-QAM, Using (13) we determine the M metrics $\{Q(s_{1,j})\}$.

The QAM symbol s_1 , corresponds to $\log_2 M$ bits, i.e., is represented by a $\log_2 M$ length bit-vector. The M metrics $\{Q(s_{1,j})\}$ defined above are sufficient to determine the max-log LLR for each bit associated with s_1 . To see this, consider the $\log_2 M$ bits associated with s_1 . Then letting $\lambda_{1,\ell}$ denote the max-log LLR of the ℓ -th bit $b_{1,\ell}$ associated with s_1 and assuming equal *a priori* bit probabilities, we have

$$\lambda_{1,\ell} = \|\mathbf{b}_2\|^2 \min_{s_{1,j} \in \mathcal{S}_1: b_{1,\ell}=0} Q(s_{1,j}) - \|\mathbf{b}_2\|^2 \min_{s_{1,j} \in \mathcal{S}_1: b_{1,\ell}=1} Q(s_{1,j}), \quad 1 \leq \ell \leq \log_2 M. \quad (14)$$

References

- [1] N.Jindal, "Antenna Combining for the MIMO Downlink Channel," *IEEE Trans. Wireless Communications*, Vol. 7, No. 10, pp. 3834-3844, Oct. 2008.
- [2] B. M. Hochwald and S. ten Brink, "Achieving near-capacity on a multiple-antenna channel," *IEEE Trans. Commun.*, vol. 51, pp. 389-399, Mar. 2003.