

**TSG-RAN Meeting #9
Hawaii, U.S.A. , 20-22 September 2000**

RP-000348

Title: Agreed CRs to TS 25.225

Source: TSG-RAN WG1

Agenda item: 5.1.3

No.	R1 T-doc	Spec	CR	Rev	Subject	Cat	Current	New
1	R1-000922	25.225	012	1	Alignment of TDD measurements with FDD : GPS related measurements	F	3.3.0	3.4.0
2	R1-000911	25.225	013	1	Alignment of TDD measurements with FDD :SFN-CFN observed time difference	F	3.3.0	3.4.0
3	R1-000886	25.225	014	-	Clarification of the Timeslot ISCP measurements	F	3.3.0	3.4.0
4	R1-000940	25.225	015	-	Terminology regarding the beacon function	F	3.3.0	3.4.0
5	R1-000990	25.225	016	-	Removal of Physical Channel BER	F	3.3.0	3.4.0
6	R1-000998	25.225	017	-	Update of TS25.225 due to recent change for FDD: Reporting of UTRAN TX carrier power	F	3.3.0	3.4.0

CHANGE REQUEST

Please see embedded help file at the bottom of this page for instructions on how to fill in this form correctly.

25.225 CR 012r1

Current Version: 3.3.0

GSM (AA.BB) or 3G (AA.BBB) specification number ↑

↑ CR number as allocated by MCC support team

For submission to: RAN #9
 list expected approval meeting # here ↑

for approval
 for information

strategic
 non-strategic (for SMG use only)

Form: CR cover sheet, version 2 for 3GPP and SMG The latest version of this form is available from: ftp://ftp.3gpp.org/Information/CR-Form-v2.doc

Proposed change affects:
 (at least one should be marked with an X)

(U)SIM ME UTRAN / Radio Core Network

Source: TSG RAN WG1

Date: 28.06.2000

Subject: Alignment of TDD measurements with FDD: GPS related measurements

Work item:

Category:

(only one category shall be marked with an X)

F Correction
 A Corresponds to a correction in an earlier release
 B Addition of feature
 C Functional modification of feature
 D Editorial modification

Release: Phase 2
 Release 96
 Release 97
 Release 98
 Release 99
 Release 00

Reason for change:

Analogous to FDD it is proposed to introduce also GPS Timing measurements for LCS in the UE and the UTRAN.

Clauses affected: 5.1 and 5.2

Other specs affected:

Other 3G core specifications → List of CRs:
 Other GSM core specifications → List of CRs:
 MS test specifications → List of CRs:
 BSS test specifications → List of CRs:
 O&M specifications → List of CRs:

Other comments:

See introductory Tdoc about LCS for TDD R1-00-0866.



help.doc

<----- double-click here for help and instructions on how to create a CR.

5.1.9 UE transmitted power

Definition	The total UE transmitted power on one carrier measured in a timeslot. The reference point for the UE transmitted power shall be the UE antenna connector.
Applicable for	connected mode (intra-frequency).

5.1.10 SFN-SFN observed time difference

Definition	<p>SFN-SFN observed time difference is the time difference of the reception times of frames from two cells (serving and target) measured in the UE and expressed in chips. It is distinguished in two types. Type 2 applies if the serving and the target cell have the same frame timing.</p> <p>Type 1: SFN-SFN observed time difference = $OFF \times 38400 + T_m$ in chips, where: $T_m = T_{RxSFNi} - T_{RxSFNk}$, given in chip units with the range [0, 1, ..., 38399] chips T_{RxSFNi}: time of start of the received frame SFN_i of the serving TDD cell i. T_{RxSFNk}: time of start of the received frame SFN_k of the target UTRA cell k received most recent in time before the time instant T_{RxSFNi} in the UE. If this frame SFN_k of the target UTRA cell is received exactly at T_{RxSFNi} then $T_{RxSFNk} = T_{RxSFNi}$ (which leads to $T_m=0$). $OFF = (SFN_i - SFN_k) \bmod 256$, given in number of frames with the range [0, 1, ..., 255] frames SFN_i: system frame number for downlink frame from serving TDD cell i in the UE at the time T_{RxSFNi}. SFN_k: system frame number for downlink frame from target UTRA cell k received in the UE at the time T_{RxSFNk}. (for FDD: the P-CCPCH frame)</p> <p>Type 2: SFN-SFN observed time difference = $T_{RxTsk} - T_{RxTsi}$, in chips, where T_{RxTsi}: time of start of a timeslot received of the serving TDD cell i. T_{RxTsk}: time of start of a timeslot received from the target UTRA cell k that is closest in time to the start of the timeslot of the serving TDD cell i.</p>
Applicable for	idle mode, connected mode (intra-frequency), connected mode (inter-frequency)

5.1.11 Observed time difference to GSM cell

Definition	<p>Observed time difference to GSM cell is the time difference T_m in ms, where $T_m = T_{RxGSMk} - T_{RxSFNi}$ T_{RxSFNi}: time of start of the received frame SFN=0 of the serving TDD cell i T_{RxGSMk}: time of start of the GSM BCCH 51-multiframe of the considered target GSM frequency k received closest in time after the time T_{RxSFNi}. If the next GSM BCCH 51-multiframe is received exactly at T_{RxSFNi} then $T_{RxGSMk} = T_{RxSFNi}$ (which leads to $T_m=0$). The beginning of the GSM BCCH 51-multiframe is defined as the beginning of the first tail bit of the frequency correction burst in the first TDMA-frame of the GSM BCCH 51-multiframe, i.e. the TDMA-frame following the IDLE-frame.</p>
Applicable for	Idle mode, connected mode (inter-frequency)

5.1.1244 UE GPS Timing of Cell Frames for LCS

Definition	The timing between cell j and GPS Time Of Week. $T_{UE-GPSj}$ is defined as the time of occurrence of a specified UTRAN event according to GPS time. The specified UTRAN event is the beginning of a particular frame (identified through its SFN) in the first significant multipath of the cell j P-CCPCH measured in the UE.
Applicable for	idle mode, connected mode (intra-frequency, inter-frequency)

5.2.4 SIR

Definition	<p>Signal to Interference Ratio, defined as: $(RSCP/ISCP) \times SF$.</p> <p>Where:</p> <p>RSCP = Received Signal Code Power, the received power on the code of a specified DPCH, PRACH or PUSCH.</p> <p>ISCP = Interference Signal Code Power, the interference on the received signal in the same timeslot which can't be eliminated by the receiver.</p> <p>SF = The used spreading factor.</p> <p>The reference point for the SIR shall be the antenna connector.</p>
-------------------	--

5.2.5 Transport channel BER

Definition	<p>The transport channel BER is an estimation of the average bit error rate (BER) of DCH or USCH data. The transport channel (TrCH) BER is measured from the data considering only non-punctured bits at the input of the channel decoder in Node B.</p> <p>It shall be possible to report an estimate of the transport channel BER for a TrCH after the end of each TTI of the TrCH. The reported TrCH BER shall be an estimate of the BER during the latest TTI for that TrCH. Transport channel BER is only required to be reported for TrCHs that are channel coded.</p>
-------------------	--

5.2.6 Physical channel BER

Definition	The physical channel BER is an estimation of the average bit error rate (BER) of a DPCH or PUSCH.
-------------------	---

5.2.7 Transmitted carrier power

Definition	<p>Transmitted carrier power, is the ratio between the total transmitted power on one DL carrier [W] from one UTRAN access point measured in a timeslot and the maximum transmission power [W] that is possible to use on the same carrier during the measurement period.</p> <p>The maximum transmission power is the configured maximum transmission power for the cell. The measurement shall be possible on any carrier transmitted from the UTRAN access point. The reference point for the transmitted carrier power measurement shall be the antenna connector.</p> <p>In case of Tx diversity the transmitted carrier power for each branch shall be measured.</p>
-------------------	--

5.2.8 Transmitted code power

Definition	Transmitted Code Power, is the transmitted power on one carrier and one channelisation code in one timeslot. The reference point for the transmitted code power measurement shall be the antenna connector at the UTRAN access point cabinet.
-------------------	---

5.2.9 RX Timing Deviation

Definition	<p>'RX Timing Deviation' is the time difference $TRX_{dev} = TTS - TRX_{path}$ in chips, with</p> <p>TRX_{path}: time of the reception in the Node B of the first significant uplink path to be used in the detection process</p> <p>TTS: time of the beginning of the respective slot according to the Node B internal Timing</p>
-------------------	---

NOTE: This measurement can be used for timing advance calculation or location services.

5.2.10 UTRAN GPS Timing of Cell Frames for LCS

Definition	The time difference between the timing of the cell and GPS Time Of Week. $T_{\text{UTRAN-GPS}}$ is defined as the time of occurrence of a specified UTRAN event according to GPS time. The specified UTRAN event is the beginning of a particular frame (identified through its SFN) transmitted in the cell.
-------------------	---

CHANGE REQUEST

Please see embedded help file at the bottom of this page for instructions on how to fill in this form correctly.

25.225 CR 013r1

Current Version: 3.3.0

GSM (AA.BB) or 3G (AA.BBB) specification number ↑

↑ CR number as allocated by MCC support team

For submission to: RAN #9
 list expected approval meeting # here ↑

for approval
 for information

strategic
 non-strategic (for SMG use only)

Form: CR cover sheet, version 2 for 3GPP and SMG The latest version of this form is available from: ftp://ftp.3gpp.org/Information/CR-Form-v2.doc

Proposed change affects:
 (at least one should be marked with an X)

(U)SIM ME UTRAN / Radio Core Network

Source: TSG RAN WG1

Date: 28.06.2000

Subject: Alignment of TDD measurements with FDD: SFN-CFN observed time difference

Work item:

Category:

(only one category shall be marked with an X)

F Correction
 A Corresponds to a correction in an earlier release
 B Addition of feature
 C Functional modification of feature
 D Editorial modification

Release:

Phase 2
 Release 96
 Release 97
 Release 98
 Release 99
 Release 00

Reason for change:

Following CR 058r1 to TS 25.302 (R2-00-1151) approved on RAN #8 (RP-00-0215) this CR proposes to include the 'SFN-CFN observed time difference' (which is already present in 25.215 v.3.3.0 for FDD) also in the TDD specification 25.225.

Clauses affected:

Other specs affected:

Other 3G core specifications → List of CRs:
 Other GSM core specifications → List of CRs:
 MS test specifications → List of CRs:
 BSS test specifications → List of CRs:
 O&M specifications → List of CRs:

Other comments:



help.doc

<----- double-click here for help and instructions on how to create a CR.

5.1.9 UE transmitted power

Definition	The total UE transmitted power on one carrier measured in a timeslot. The reference point for the UE transmitted power shall be the UE antenna connector.
Applicable for	connected mode (intra-frequency).

5.1.10 SFN-SFN observed time difference

Definition	<p>SFN-SFN observed time difference is the time difference of the reception times of frames from two cells (serving and target) measured in the UE and expressed in chips. It is distinguished in two types. Type 2 applies if the serving and the target cell have the same frame timing.</p> <p>Type 1: SFN-SFN observed time difference = $OFF \times 38400 + T_m$ in chips, where: $T_m = T_{RxSFNi} - T_{RxSFNk}$, given in chip units with the range [0, 1, ..., 38399] chips T_{RxSFNi}: time of start of the received frame SFN_i of the serving TDD cell i. T_{RxSFNk}: time of start of the received frame SFN_k of the target UTRA cell k received most recent in time before the time instant T_{RxSFNi} in the UE. If this frame SFN_k of the target UTRA cell is received exactly at T_{RxSFNi} then $T_{RxSFNk} = T_{RxSFNi}$ (which leads to $T_m = 0$). $OFF = (SFN_i - SFN_k) \bmod 256$, given in number of frames with the range [0, 1, ..., 255] frames SFN_i: system frame number for downlink frame from serving TDD cell i in the UE at the time T_{RxSFNi}. SFN_k: system frame number for downlink frame from target UTRA cell k received in the UE at the time T_{RxSFNk}. (for FDD: the P-CCPCH frame)</p> <p>Type 2: SFN-SFN observed time difference = $T_{RxTSk} - T_{RxTSi}$, in chips, where T_{RxTSi}: time of start of a timeslot received of the serving TDD cell i. T_{RxTSk}: time of start of a timeslot received from the target UTRA cell k that is closest in time to the start of the timeslot of the serving TDD cell i.</p>
Applicable for	idle mode, connected mode (intra-frequency), connected mode (inter-frequency)

5.1.9 SFN-CFN observed time difference

Definition	<p>The SFN-CFN observed time difference is defined as: T_m for an FDD neighbour cell (i.e. the value is reported in chips), OFF for a TDD neighbour cell (i.e the value is reported in frames), where: $T_m = T_{UETx} - T_{RxSFN}$, given in chip units with the range [0, 1, ..., 38399] chips. T_{UETx} is the time at the beginning of the frame with the connection frame number CFN_{Tx} considering the transmission from the UE in the serving TDD cell. T_{RxSFN} is the time at the beginning of the frame with the system frame number SFN (for FDD neighbour cells: P-CCPCH frame is considered) received at the UE from a neighbour cell T_{RxSFN} is the time instant most recent in time before the time instant T_{UETx} $OFF = (SFN - CFN_{Tx}) \bmod 256$, given in number of frames with the range [0, 1, ..., 255] frames CFN_{Tx} is the connection frame number for the UE transmission. SFN is the system frame number for the neighbouring cell frame (for FDD neighbour cells: P-CCPCH frame) received in the UE at the time instant T_{RxSFN}.</p>
Applicable for	connected mode (inter-frequency), connected mode (intra-frequency)

5.1.11 Observed time difference to GSM cell

Definition	<p>Observed time difference to GSM cell is the time difference T_m in ms, where</p> $T_m = T_{RxGSMk} - T_{RxSFNOi}$ <p>$T_{RxSFNOi}$: time of start of the received frame SFN=0 of the serving TDD cell i</p> <p>T_{RxGSMk}: time of start of the GSM BCCH 51-multiframe of the considered target GSM frequency k received closest in time after the time $T_{RxSFNOi}$.</p> <p>If the next GSM BCCH 51-multiframe is received exactly at $T_{RxSFNOi}$ then $T_{RxGSMk} = T_{RxSFNOi}$ (which leads to $T_m=0$).</p> <p>The beginning of the GSM BCCH 51-multiframe is defined as the beginning of the first tail bit of the frequency correction burst in the first TDMA-frame of the GSM BCCH 51-multiframe, i.e. the TDMA-frame following the IDLE-frame.</p>
Applicable for	Idle mode, connected mode (inter-frequency)

CHANGE REQUEST

Please see embedded help file at the bottom of this page for instructions on how to fill in this form correctly.

25.225 CR 014

Current Version: 3.3.0

GSM (AA.BB) or 3G (AA.BBB) specification number ↑

↑ CR number as allocated by MCC support team

For submission to: RAN #9
list expected approval meeting # here ↑

for approval
for information

strategic
non-strategic (for SMG use only)

Form: CR cover sheet, version 2 for 3GPP and SMG The latest version of this form is available from: ftp://ftp.3gpp.org/Information/CR-Form-v2.doc

Proposed change affects:
(at least one should be marked with an X)

(U)SIM ME UTRAN / Radio Core Network

Source: TSG RAN WG1

Date: 28.06.2000

Subject: Clarification of the Timeslot ISCP measurements

Work item:

Category:

(only one category shall be marked with an X)

F Correction
A Corresponds to a correction in an earlier release
B Addition of feature
C Functional modification of feature
D Editorial modification

Release: Phase 2
Release 96
Release 97
Release 98
Release 99
Release 00

Reason for change:

Timeslot ISCP is a measurement to evaluate the interference situation in a specific timeslot for DCA. To avoid that in case of Joint Detection the Joint Detector must be started to determine Timeslot ISCP this CR proposes to measure Timeslot ISCP on the midamble.

Clauses affected:

Other specs affected:

Other 3G core specifications → List of CRs:
Other GSM core specifications → List of CRs:
MS test specifications → List of CRs:
BSS test specifications → List of CRs:
O&M specifications → List of CRs:

Other comments:



help.doc

<----- double-click here for help and instructions on how to create a CR.

5.1.3 Timeslot ISCP

Definition	Interference Signal Code Power, the interference on the received signal in a specified timeslot measured on the midamble. Only this part of the interference that is not eliminated by the receiver shall be included in the measurement. The reference point for the ISCP is the antenna connector at the UE.
Applicable for	connected mode (intra-frequency).

5.1.4 UTRA carrier RSSI

Definition	Received Signal Strength Indicator, the wide-band received power within the relevant channel bandwidth in a specified timeslot. Measurement shall be performed on a UTRAN DL carrier. The reference point for the RSSI is the antenna connector at the UE.
Applicable for	idle mode, connected mode (intra- & inter-frequency)

5.1.5 GSM carrier RSSI

Definition	Received Signal Strength Indicator, the wide-band received power within the relevant channel bandwidth in a specified timeslot. Measurement shall be performed on a GSM BCCH carrier. The reference point for the RSSI is the antenna connector at the UE.
Applicable for	idle mode, connected mode (inter-frequency)

5.1.6 SIR

Definition	Signal to Interference Ratio, defined as: $(RSCP/ISCP) \times SF$. Where: RSCP = Received Signal Code Power, the received power on the code of a specified DPCH or PDSCH. ISCP = Interference Signal Code Power, the interference on the received signal in the same timeslot which can't be eliminated by the receiver. SF = The used spreading factor. The reference point for the SIR is the antenna connector of the UE.
Applicable for	connected mode (intra-frequency)

5.1.7 CPICH Ec/No

Definition	The received energy per chip divided by the power density in the band. The Ec/No is identical to RSCP/RSSI. Measurement shall be performed on the Primary CPICH. The reference point for Ec/No is the antenna connector at the UE. (This measurement is used in TDD for monitoring FDD cells while camping on a TDD cell) If Tx diversity is applied on the Primary CPICH the received energy per chip (Ec) from each antenna shall be separately measured and summed together in [Ws] to a total received chip energy per chip on the Primary CPICH, before calculating the Ec/No.
Applicable for	idle mode, connected mode (inter-frequency)

5.1.8 Transport channel BLER

Definition	Estimation of the transport channel block error rate (BLER). The BLER estimation shall be based on evaluating the CRC on each transport block.
Applicable for	connected mode (intra-frequency)

5.1.9 UE transmitted power

Definition	The total UE transmitted power on one carrier measured in a timeslot. The reference point for the UE transmitted power shall be the UE antenna connector.
Applicable for	connected mode (intra-frequency).

5.2 UTRAN measurement abilities

NOTE 1: If the UTRAN supports multiple frequency bands then the measurements apply for each frequency band individually.

NOTE 2: The RSCP can either be measured on the data part or the midamble of a burst, since there is no power offset between both. However, in order to have a common reference, the measurement on the midamble is assumed.

5.2.1 RSCP

Definition	Received Signal Code Power, the received power on one DPCH, PRACH or PUSCH code. The reference point for the RSCP shall be the antenna connector.
-------------------	---

5.2.2 Timeslot ISCP

Definition	Interference Signal Code Power, the interference on the received signal in a specified timeslot measured on the midamble. Only this part of the interference that is not eliminated by the receiver shall be included in the measurement. The reference point for the ISCP shall be the antenna connector.
-------------------	---

5.2.3 RSSI

Definition	Received Signal Strength Indicator, the wide-band received power within the UTRAN UL carrier channel bandwidth in a specified timeslot. The reference point for the RSSI shall be the antenna connector.
-------------------	--

CHANGE REQUEST

Please see embedded help file at the bottom of this page for instructions on how to fill in this form correctly.

25.225 CR 015

Current Version: **3.3.0**

GSM (AA.BB) or 3G (AA.BBB) specification number ↑

↑ CR number as allocated by MCC support team

For submission to: **RAN#9**
list expected approval meeting # here
↑

for approval
for information

strategic
non-strategic (for SMG use only)

Form: CR cover sheet, version 2 for 3GPP and SMG The latest version of this form is available from: <ftp://ftp.3gpp.org/Information/CR-Form-v2.doc>

Proposed change affects: (U)SIM ME UTRAN / Radio Core Network
(at least one should be marked with an X)

Source: TSG RAN WG1 **Date:** 00-07-04

Subject: Terminology regarding the beacon function

Work item: _____

Category:	F Correction <input checked="" type="checkbox"/> A Corresponds to a correction in an earlier release <input type="checkbox"/> B Addition of feature <input type="checkbox"/> C Functional modification of feature <input type="checkbox"/> D Editorial modification <input type="checkbox"/>	Release:	Phase 2 <input type="checkbox"/> Release 96 <input type="checkbox"/> Release 97 <input type="checkbox"/> Release 98 <input type="checkbox"/> Release 99 <input checked="" type="checkbox"/> Release 00 <input type="checkbox"/>
------------------	--	-----------------	--

(only one category shall be marked with an X)

Reason for change: Currently, there are different terms in connection with the beacon function that may lead to some misunderstanding:

- ‚Physical Channels providing the Beacon Function‘
- ‚Physical Channels with Beacon Function‘
- ‚Beacon Channels‘

This CR tries to make the terminology more consistent in such a sense that

- Physical Channels have Beacon Characteristics
- Physical Channels with Beacon Characteristics are called Beacon Channels
- The ensemble of Beacon Channels provide the Beacon Function

Clauses affected: 5.1

Other specs affected:	Other 3G core specifications <input checked="" type="checkbox"/> Other GSM core specifications <input type="checkbox"/> MS test specifications <input type="checkbox"/> BSS test specifications <input type="checkbox"/> O&M specifications <input type="checkbox"/>	→ List of CRs: → List of CRs: → List of CRs: → List of CRs: → List of CRs:	CR221-028, CR224-025
------------------------------	--	--	----------------------

Other comments: _____



<----- double-click here for help and instructions on how to create a CR.

5.1 UE measurement abilities

NOTE 1: Measurements for TDD which are specified on the Primary CCPCH (P-CCPCH) are carried out on the P-CCPCH or on any other ~~beacon physical channels with beacon function~~, see [6].

NOTE 2: For ~~those beacon~~ channels ~~providing beacon function~~ [6], the received power measurements shall be based on the sum of the received powers for midambles $m^{(1)}$ and $m^{(2)}$ if Block-STTD is applied to the P-CCPCH.

NOTE 3: The UTRAN has to take into account the UE capabilities when specifying the timeslots to be measured in the measurement control message.

NOTE 4: The RSCP can either be measured on the data part or the midamble of a burst, since there is no power offset between both. However, in order to have a common reference, the measurement on the midamble is assumed.

NOTE 5: The line 'applicable for' indicates whether the measurement is applicable for inter-frequency and/or intra-frequency and furthermore for idle and/or connected mode.

CHANGE REQUEST

Please see embedded help file at the bottom of this page for instructions on how to fill in this form correctly.

25.225 CR 016

Current Version: **3.3.0**

GSM (AA.BB) or 3G (AA.BBB) specification number ↑

↑ CR number as allocated by MCC support team

For submission to: **RAN #9**
list expected approval meeting # here
↑

for approval
for information

strategic
non-strategic (for SMG use only)

Form: CR cover sheet, version 2 for 3GPP and SMG The latest version of this form is available from: ftp://ftp.3gpp.org/Information/CR-Form-v2.doc

Proposed change affects: (U)SIM ME UTRAN / Radio Core Network
(at least one should be marked with an X)

Source: TSG RAN WG1 **Date:** August 7, 2000

Subject: Removal of Physical Channel BER

Work item: TS 25.225

Category: F Correction **Release:** Phase 2
A Corresponds to a correction in an earlier release Release 96
B Addition of feature Release 97
C Functional modification of feature Release 98
D Editorial modification Release 99
Release 00
(only one category shall be marked with an X)

Reason for change: The Physical Channel BER measurement for FDD applies to the DPCCH. This channel does not exist in TDD.

Clauses affected: 5.2.6

Other specs affected: Other 3G core specifications → List of CRs: TS 25.407, TS 25.302, TS 25.WG4
Other GSM core specifications → List of CRs:
MS test specifications → List of CRs:
BSS test specifications → List of CRs:
O&M specifications → List of CRs:

Other comments:



help.doc

<----- double-click here for help and instructions on how to create a CR.

Contents

Foreword.....	3
1 Scope	4
2 References.....	4
3 Abbreviations.....	5
4 Control of UE/UTRAN measurements.....	5
4.1 General measurement concept.....	5
4.2 Measurements for cell selection/reselection	6
4.3 Measurements for Handover	6
4.4 Measurements for DCA.....	6
4.5 Measurements for timing advance.....	6
5 Measurement abilities for UTRA TDD	7
5.1 UE measurement abilities.....	7
5.1.1 P-CCPCH RSCP.....	7
5.1.2 CPICH RSCP.....	7
5.1.3 Timeslot ISCP.....	7
5.1.4 UTRA carrier RSSI.....	8
5.1.5 GSM carrier RSSI.....	8
5.1.6 SIR.....	8
5.1.7 CPICH Ec/No	8
5.1.8 Transport channel BLER	8
5.1.9 UE transmitted power	8
5.1.10 SFN-SFN observed time difference	9
5.1.11 Observed time difference to GSM cell.....	9
5.2 UTRAN measurement abilities.....	10
5.2.1 RSCP.....	10
5.2.2 Timeslot ISCP.....	10
5.2.3 RSSI.....	10
5.2.4 SIR.....	10
5.2.5 Transport channel BER.....	10
5.2.6 Physical channel BER.....	11
5.2.76 Transmitted carrier power.....	11
5.2.87 Transmitted code power.....	11
5.2.98 RX Timing Deviation.....	11

Annex A (informative): Monitoring GSM from TDD: Calculation Results..Error! Bookmark not defined.

A.1 Low data rate traffic using 1 uplink and 1 downlink slot.....**Error! Bookmark not defined.**

A.1.1 Higher data rate traffic using more than 1 uplink and/or 1 downlink TDD timeslot**Error! Bookmark not defined**

Annex B (informative): Change historyError! Bookmark not defined.

Foreword

This Technical Specification (TS) has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

1 Scope

The present document contains the description and definition of the measurements done at the UE and network in TDD mode in order to support operation in idle mode and connected mode.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies.

- [1] 3G TS 25.211: "Physical channels and mapping of transport channels onto physical channels (FDD)".
- [2] 3G TS 25.212: "Multiplexing and channel coding (FDD)".
- [3] 3G TS 25.213: "Spreading and modulation (FDD)".
- [4] 3G TS 25.214: "Physical layer procedures (FDD)".
- [5] 3G TS 25.215: "Physical layer measurements (FDD)".
- [6] 3G TS 25.221: "Physical channels and mapping of transport channels onto physical channels (TDD)".
- [7] 3G TS 25.222: "Multiplexing and channel coding (TDD)".
- [8] 3G TS 25.223: "Spreading and modulation (TDD)".
- [9] 3G TS 25.224: "Physical layer procedures (TDD)".
- [10] 3G TS 25.301: "Radio Interface Protocol Architecture".
- [11] 3G TS 25.302: "Services provided by the Physical layer".
- [12] 3G TS 25.303: "UE functions and interlayer procedures in connected mode".
- [13] 3G TS 25.304: "UE procedures in idle mode".
- [14] 3G TS 25.331: "RRC Protocol Specification".
- [15] 3G TR 25.922: "Radio Resource Management Strategies".
- [16] 3G TR 25.923: "Report on Location Services (LCS)".

3 Abbreviations

For the purposes of the present document, the following abbreviations apply:

BER	Bit Error Rate
BLER	Block Error Rate
DCH	Dedicated Channel
DPCH	Dedicated Physical Channel
E_c/N_0	Received energy per chip divided by the power density in the band
FACH	Forward Access Channel
ISCP	Interference Signal Code Power
P-CCPCH	Primary Common Control Physical Channel
PCH	Paging Channel
PRACH	Physical Random Access Channel
RACH	Random Access Channel
RSCP	Received Signal Code Power
RSSI	Received Signal Strength Indicator
S-CCPCH	Secondary Common Control Physical Channel
SCH	Synchronisation Channel
SIR	Signal-to-Interference Ratio
UE	User Equipment

4 Control of UE/UTRAN measurements

In this clause the general measurement control concept of the higher layers is briefly described to provide an understanding on how L1 measurements are initiated and controlled by higher layers.

4.1 General measurement concept

L1 provides with the measurement specifications a toolbox of measurement abilities for the UE and the UTRAN. These measurements can be differentiated in different measurement types: intra-frequency, inter-frequency, inter-system, traffic volume, quality and internal measurements (see [14]).

In the L1 measurement specifications the measurements are distinguished between measurements in the UE (the messages will be described in the RRC Protocol) and measurements in the UTRAN (the messages will be described in the NBAP and the Frame Protocol).

To initiate a specific measurement the UTRAN transmits a ‘measurement control message’ to the UE including a measurement ID and type, a command (setup, modify, release), the measurement objects and quantity, the reporting quantities, criteria (periodical/event-triggered) and mode (acknowledged/unacknowledged), see [14].

When the reporting criteria is fulfilled the UE shall answer with a ‘measurement report message’ to the UTRAN including the measurement ID and the results.

In idle mode the measurement control message is broadcast in a System Information. Intra-frequency reporting events, traffic volume reporting events and UE internal measurement reporting events described in [14] define events which trigger the UE to send a report to the UTRAN. This defines a toolbox from which the UTRAN can choose the needed reporting events.

4.2 Measurements for cell selection/reselection

Whenever a PLMN has been selected the UE shall start to find a suitable cell to camp on, this is 'cell selection'.

When camped on cell the UE regularly searches for a better cell depending on the cell reselection criteria, this is called 'cell reselection'. The procedures for cell selection and reselection are described in [13] and the measurements carried out by the UE are explained in this specification.

4.3 Measurements for Handover

For the handover preparation the UE receives from the UTRAN a list of cells (e.g. TDD, FDD or GSM), which the UE shall monitor (see 'monitored set' in [14]) in its idle timeslots.

At the beginning of the measurement process the UE shall find synchronization to the cell to measure using the synchronization channel. This is described under 'cell search' in [9] if the monitored cell is a TDD cell and in [4] if it is an FDD cell.

For a TDD cell to monitor after this procedure the exact timing of the midamble of the P-CCPCH is known and the measurements can be performed. Depending on the UE implementation and if timing information about the cell to monitor is available, the UE may perform the measurements on the P-CCPCH directly without prior SCH synchronisation.

4.4 Measurements for DCA

DCA is used to optimise the resource allocation by means of a channel quality criteria or traffic parameters. The DCA measurements are configured by the UTRAN. The UE reports the measurements to the UTRAN.

For DCA no measurements are performed in idle mode in the serving TDD cell.

When connecting with the initial access the UE immediately starts measuring the ISCP of time slots which are communicated on the BCH. The measurements and the preprocessing are done while the UTRAN assigns an UL channel for the UE for signalling and measurement reporting.

In connected mode the UE performs measurements according to a measurement control message from the UTRAN.

4.5 Measurements for timing advance

To update timing advance of a moving UE the UTRAN measures 'Received Timing Deviation', i.e. the time difference of the received UL transmission (PRACH, DPCH, PUSCH) in relation to its timeslot structure that means in relation to the ideal case where an UL transmission would have zero propagation delay. The measurements are reported to higher layers, where timing advance values are calculated and signalled to the UE.

5 Measurement abilities for UTRA TDD

In this clause the physical layer measurements reported to higher layers. (this may also include UE internal measurements not reported over the air-interface) are defined.

5.1 UE measurement abilities

NOTE 1: Measurements for TDD which are specified on the Primary CCPCH (P-CCPCH) are carried out on the P-CCPCH or other physical channels with beacon function, see [6].

NOTE 2: For those channels providing beacon function [6], the received power measurements shall be based on the sum of the received powers for midambles $m^{(1)}$ and $m^{(2)}$ if Block-STTD is applied to the P-CCPCH.

NOTE 3: The UTRAN has to take into account the UE capabilities when specifying the timeslots to be measured in the measurement control message.

NOTE 4: The RSCP can either be measured on the data part or the midamble of a burst, since there is no power offset between both. However, in order to have a common reference, the measurement on the midamble is assumed.

NOTE 5: The line 'applicable for' indicates whether the measurement is applicable for inter-frequency and/or intra-frequency and furthermore for idle and/or connected mode.

5.1.1 P-CCPCH RSCP

Definition	Received Signal Code Power, the received power on P-CCPCH of own or neighbour cell. The reference point for the RSCP is the antenna connector at the UE.
Applicable for	idle mode, connected mode (intra-frequency & inter-frequency)

5.1.2 CPICH RSCP

Definition	Received Signal Code Power, the received power on one code measured on the Primary CPICH. The reference point for the RSCP is the antenna connector at the UE. (This measurement is used in TDD for monitoring FDD cells while camping on a TDD cell). If Tx diversity is applied on the Primary CPICH the received code power from each antenna shall be separately measured and summed together in [W] to a total received code power on the Primary CPICH.
Applicable for	idle mode, connected mode (inter-frequency)

5.1.3 Timeslot ISCP

Definition	Interference Signal Code Power, the interference on the received signal in a specified timeslot. Only this part of the interference that is not eliminated by the receiver shall be included in the measurement. The reference point for the ISCP is the antenna connector at the UE.
Applicable for	connected mode (intra-frequency).

5.1.4 UTRA carrier RSSI

Definition	Received Signal Strength Indicator, the wide-band received power within the relevant channel bandwidth in a specified timeslot. Measurement shall be performed on a UTRAN DL carrier. The reference point for the RSSI is the antenna connector at the UE.
Applicable for	idle mode, connected mode (intra- & inter-frequency)

5.1.5 GSM carrier RSSI

Definition	Received Signal Strength Indicator, the wide-band received power within the relevant channel bandwidth in a specified timeslot. Measurement shall be performed on a GSM BCCH carrier. The reference point for the RSSI is the antenna connector at the UE.
Applicable for	idle mode, connected mode (inter-frequency)

5.1.6 SIR

Definition	Signal to Interference Ratio, defined as: $(RSCP/ISCP) \times SF$. Where: RSCP = Received Signal Code Power, the received power on the code of a specified DPCH or PDSCH. ISCP = Interference Signal Code Power, the interference on the received signal in the same timeslot which can't be eliminated by the receiver. SF = The used spreading factor. The reference point for the SIR is the antenna connector of the UE.
Applicable for	connected mode (intra-frequency)

5.1.7 CPICH E_c/N_0

Definition	The received energy per chip divided by the power density in the band. The E_c/N_0 is identical to RSCP/RSSI. Measurement shall be performed on the Primary CPICH. The reference point for E_c/N_0 is the antenna connector at the UE. (This measurement is used in TDD for monitoring FDD cells while camping on a TDD cell) If Tx diversity is applied on the Primary CPICH the received energy per chip (E_c) from each antenna shall be separately measured and summed together in [Ws] to a total received chip energy per chip on the Primary CPICH, before calculating the E_c/N_0 .
Applicable for	idle mode, connected mode (inter-frequency)

5.1.8 Transport channel BLER

Definition	Estimation of the transport channel block error rate (BLER). The BLER estimation shall be based on evaluating the CRC on each transport block.
Applicable for	connected mode (intra-frequency)

5.1.9 UE transmitted power

Definition	The total UE transmitted power on one carrier measured in a timeslot. The reference point for the UE transmitted power shall be the UE antenna connector.
Applicable for	connected mode (intra-frequency).

5.1.10 SFN-SFN observed time difference

Definition	<p>SFN-SFN observed time difference is the time difference of the reception times of frames from two cells (serving and target) measured in the UE and expressed in chips. It is distinguished in two types. Type 2 applies if the serving and the target cell have the same frame timing.</p> <p>Type 1: SFN-SFN observed time difference = $OFF \times 38400 + T_m$ in chips, where: $T_m = T_{RxSFNi} - T_{RxSFNk}$, given in chip units with the range [0, 1, ..., 38399] chips T_{RxSFNi} : time of start of the received frame SFN_i of the serving TDD cell i. T_{RxSFNk} : time of start of the received frame SFN_k of the target UTRA cell k received most recent in time before the time instant T_{RxSFNi} in the UE. If this frame SFN_k of the target UTRA cell is received exactly at T_{RxSFNi} then $T_{RxSFNk} = T_{RxSFNi}$ (which leads to $T_m = 0$). $OFF = (SFN_i - SFN_k) \bmod 256$, given in number of frames with the range [0, 1, ..., 255] frames SFN_i : system frame number for downlink frame from serving TDD cell i in the UE at the time T_{RxSFNi}. SFN_k : system frame number for downlink frame from target UTRA cell k received in the UE at the time T_{RxSFNk} (for FDD: the P-CCPCH frame)</p> <p>Type 2: SFN-SFN observed time difference = $T_{RxTSk} - T_{RxTSi}$, in chips, where T_{RxTSi} : time of start of a timeslot received of the serving TDD cell i. T_{RxTSk} : time of start of a timeslot received from the target UTRA cell k that is closest in time to the start of the timeslot of the serving TDD cell i.</p>
Applicable for	idle mode, connected mode (intra-frequency), connected mode (inter-frequency)

5.1.11 Observed time difference to GSM cell

Definition	<p>Observed time difference to GSM cell is the time difference T_m in ms, where $T_m = T_{RxGSMk} - T_{RxSFNi}$ T_{RxSFNi} : time of start of the received frame SFN=0 of the serving TDD cell i T_{RxGSMk} : time of start of the GSM BCCH 51-multiframe of the considered target GSM frequency k received closest in time after the time T_{RxSFNi}. If the next GSM BCCH 51-multiframe is received exactly at T_{RxSFNi} then $T_{RxGSMk} = T_{RxSFNi}$ (which leads to $T_m = 0$). The beginning of the GSM BCCH 51-multiframe is defined as the beginning of the first tail bit of the frequency correction burst in the first TDMA-frame of the GSM BCCH 51-multiframe, i.e. the TDMA-frame following the IDLE-frame.</p>
Applicable for	Idle mode, connected mode (inter-frequency)

5.2 UTRAN measurement abilities

NOTE 1: If the UTRAN supports multiple frequency bands then the measurements apply for each frequency band individually.

NOTE 2: The RSCP can either be measured on the data part or the midamble of a burst, since there is no power offset between both. However, in order to have a common reference, the measurement on the midamble is assumed.

5.2.1 RSCP

Definition	Received Signal Code Power, the received power on one DPCH, PRACH or PUSCH code. The reference point for the RSCP shall be the antenna connector.
-------------------	---

5.2.2 Timeslot ISCP

Definition	Interference Signal Code Power, the interference on the received signal in a specified timeslot. Only this part of the interference that is not eliminated by the receiver shall be included in the measurement. The reference point for the ISCP shall be the antenna connector.
-------------------	---

5.2.3 RSSI

Definition	Received Signal Strength Indicator, the wide-band received power within the UTRAN UL carrier channel bandwidth in a specified timeslot. The reference point for the RSSI shall be the antenna connector.
-------------------	--

5.2.4 SIR

Definition	Signal to Interference Ratio, defined as: $(RSCP/ISCP) \times SF$. Where: RSCP = Received Signal Code Power, the received power on the code of a specified DPCH, PRACH or PUSCH. ISCP = Interference Signal Code Power, the interference on the received signal in the same timeslot which can't be eliminated by the receiver. SF = The used spreading factor. The reference point for the SIR shall be the antenna connector.
-------------------	---

5.2.5 Transport channel BER

Definition	The transport channel BER is an estimation of the average bit error rate (BER) of DCH or USCH data. The transport channel (TrCH) BER is measured from the data considering only non-punctured bits at the input of the channel decoder in Node B. It shall be possible to report an estimate of the transport channel BER for a TrCH after the end of each TTI of the TrCH. The reported TrCH BER shall be an estimate of the BER during the latest TTI for that TrCH. Transport channel BER is only required to be reported for TrCHs that are channel coded.
-------------------	---

5.2.6 ~~Physical channel BER~~

Definition	The physical channel BER is an estimation of the average bit error rate (BER) of a DPCH or PUSCH.
-------------------	--

5.2.76 Transmitted carrier power

Definition	Transmitted carrier power, is the ratio between the total transmitted power on one DL carrier [W] from one UTRAN access point measured in a timeslot and the maximum transmission power [W] that is possible to use on the same carrier during the measurement period. The maximum transmission power is the configured maximum transmission power for the cell. The measurement shall be possible on any carrier transmitted from the UTRAN access point. The reference point for the transmitted carrier power measurement shall be the antenna connector. In case of Tx diversity the transmitted carrier power for each branch shall be measured.
-------------------	---

5.2.87 Transmitted code power

Definition	Transmitted Code Power, is the transmitted power on one carrier and one channelisation code in one timeslot. The reference point for the transmitted code power measurement shall be the antenna connector at the UTRAN access point cabinet.
-------------------	---

5.2.98 RX Timing Deviation

Definition	'RX Timing Deviation' is the time difference $TRX_{dev} = TTS - TRX_{path}$ in chips, with TRX _{path} : time of the reception in the Node B of the first significant uplink path to be used in the detection process TTS: time of the beginning of the respective slot according to the Node B internal timing
-------------------	---

NOTE: This measurement can be used for timing advance calculation or location services.

<h2 style="margin: 0;">CHANGE REQUEST</h2>		Please see embedded help file at the bottom of this page for instructions on how to fill in this form correctly.
25.225	CR 017	Current Version: <input style="width: 50px;" type="text"/>
GSM (AA.BB) or 3G (AA.BBB) specification number ↑	↑ CR number as allocated by MCC support team	
For submission to: <input style="width: 50px;" type="text"/> RAN #9 <i>list expected approval meeting # here ↑</i>	for approval <input checked="" type="checkbox"/> for information <input type="checkbox"/>	strategic <input type="checkbox"/> non-strategic <input type="checkbox"/> <i>(for SMG use only)</i>

Form: CR cover sheet, version 2 for 3GPP and SMG The latest version of this form is available from: <ftp://ftp.3gpp.org/Information/CR-Form-v2.doc>

Proposed change affects: (U)SIM ME UTRAN / Radio Core Network
(at least one should be marked with an X)

Source: TSG RAN WG1 **Date:** 18.08.2000

Subject: Update of TS25.225 due to recent change for FDD:
Reporting of UTRAN TX carrier power

Work item:

Category:	F Correction <input checked="" type="checkbox"/> A Corresponds to a correction in an earlier release <input type="checkbox"/> B Addition of feature <input type="checkbox"/> C Functional modification of feature <input type="checkbox"/> D Editorial modification <input type="checkbox"/>	Release:	Phase 2 <input type="checkbox"/> Release 96 <input type="checkbox"/> Release 97 <input type="checkbox"/> Release 98 <input type="checkbox"/> Release 99 <input checked="" type="checkbox"/> Release 00 <input type="checkbox"/>
------------------	--	-----------------	--

(only one category shall be marked with an X)

Reason for change: Since currently one value is reported for the UTRAN Transmitted carrier power over NBAP this CR clarifies that also in the case of TX diversity only one value is reported, i.e. the maximum of two values.

Clauses affected: 5.2.7

Other specs affected:	Other 3G core specifications <input type="checkbox"/> Other GSM core specifications <input type="checkbox"/> MS test specifications <input type="checkbox"/> BSS test specifications <input type="checkbox"/> O&M specifications <input type="checkbox"/>	→ List of CRs: <input style="width: 100%;" type="text"/> → List of CRs: <input style="width: 100%;" type="text"/> → List of CRs: <input style="width: 100%;" type="text"/> → List of CRs: <input style="width: 100%;" type="text"/> → List of CRs: <input style="width: 100%;" type="text"/>
------------------------------	---	--

Other comments: This CR adopts the changes already proposed for FDD for this measurement for TX diversity (see CR 068 to 25.215, R1-00-0900). Some editorial reordering of phrases is also included.



<----- double-click here for help and instructions on how to create a CR.

5.2.7 Transmitted carrier power

Definition	<p>Transmitted carrier power, is the ratio between the total transmitted power on one DL carrier [W] from one UTRAN access point measured in a timeslot and the maximum transmission power. <u>Total transmission power is the power [W] transmitted on one DL carrier in a specific timeslot from one UTRAN access point.</u></p> <p>[W] that is possible to use on the same carrier during the measurement period.</p> <p>The mMaximum transmission power is <u>the power [W] on the same carrier when transmitting at the configured maximum transmission power for the cell.</u></p> <p>The measurement shall be possible on any carrier transmitted from the UTRAN access point. The reference point for the transmitted carrier power measurement shall be the antenna connector.</p> <p>In case of Tx diversity the transmitted carrier power for each branch shall be measured <u>and the maximum of the two values shall be reported to higher layers, i.e. only one value will be reported to higher layers.</u></p>
-------------------	---

5.2.8 Transmitted code power

Definition	<p>Transmitted Code Power, is the transmitted power on one carrier and one channelisation code in one timeslot. The reference point for the transmitted code power measurement shall be the antenna connector at the UTRAN access point cabinet.</p>
-------------------	--

5.2.9 RX Timing Deviation

Definition	<p>'RX Timing Deviation' is the time difference $TRX_{dev} = TTS - TRX_{path}$ in chips, with</p> <p>TRX_{path}: time of the reception in the Node B of the first significant uplink path to be used in the detection process</p> <p>TTS: time of the beginning of the respective slot according to the Node B internal timing</p>
-------------------	---

NOTE: This measurement can be used for timing advance calculation or location services.