

Source: TSG-RAN WG2

Title: 25.331 CR to Rel-6 on Enhanced Uplink

Spec	CR	Rev	Phase	Subject	Cat	Version-Current	Version-New	Doc-2nd-Level	Workitem
25.331	2529	-	Rel-6	Minor E-DCH related corrections	F	6.4.0	6.5.0	R2-050673	EUDCH-L23
25.331	2534	-	Rel-6	Introduction of E-DCH in the ASN.1	B	6.4.0	6.5.0	R2-050707	EUDCH-L23

CHANGE REQUEST

⌘ 25.331 CR 2529 ⌘ rev - ⌘ Current version: 6.4.0 ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

Proposed change affects: UICC apps ⌘ ME Radio Access Network Core Network

Title:	⌘ Minor E-DCH related corrections	
Source:	⌘ RAN WG2	
Work item code:	⌘ EUDCH-L23	Date: ⌘ January 2005
Category:	⌘ F Use one of the following categories: F (correction) A (corresponds to a correction in an earlier release) B (addition of feature), C (functional modification of feature) D (editorial modification) Detailed explanations of the above categories can be found in 3GPP TR 21.900 .	Release: ⌘ Rel-6 Use one of the following releases: Ph2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) Rel-4 (Release 4) Rel-5 (Release 5) Rel-6 (Release 6) Rel-7 (Release 7)

Reason for change:	⌘ This CR intends to collect minor corrections related to E-DCH
Summary of change:	⌘ The minor errors are corrected.
Consequences if not approved:	⌘ The minor errors remain.

Clauses affected:	⌘ 8.5.21; 8.6.6.37; 10.3.4.23								
Other specs affected:	⌘ <table border="1" style="display: inline-table; vertical-align: middle;"><tr><td>Y</td><td>N</td></tr><tr><td><input checked="" type="checkbox"/></td><td><input type="checkbox"/></td></tr><tr><td><input type="checkbox"/></td><td><input checked="" type="checkbox"/></td></tr><tr><td><input type="checkbox"/></td><td><input checked="" type="checkbox"/></td></tr></table> Other core specifications ⌘ <input type="checkbox"/> Test specifications ⌘ <input type="checkbox"/> O&M Specifications ⌘ <input type="checkbox"/>	Y	N	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>
Y	N								
<input checked="" type="checkbox"/>	<input type="checkbox"/>								
<input type="checkbox"/>	<input checked="" type="checkbox"/>								
<input type="checkbox"/>	<input checked="" type="checkbox"/>								
Other comments:	⌘								

How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

8.5.21 Actions related to Radio Bearer mapping

When the UE receives the IE "RB mapping info" and/or the IE "Transport format set", when transport channels, MAC-d flows or E-DCH MAC-d flows are added or deleted, when the UE performs a cell reselection or a state transition, or when the UE releases a RB, the UE shall for each of the configured Radio Bearers:

- 1> upon moving to CELL_FACH state from CELL_DCH state to initiate a cell update procedure and upon subsequent cell reselections until the first successfully completed cell update procedure, perform the actions defined in the remainder of this subclause only for signalling radio bearers;
- 1> for FDD, select the multiplexing option according to the following:
 - 2> if the UE is in CELL_FACH state:
 - 3> if the RB has a multiplexing option with transport channel type "FACH" for the DL and transport channel type "RACH" for the UL:
 - 4> select this multiplexing option.
 - 2> if the UE is in CELL_DCH state:
 - 3> if the RB has a multiplexing option with transport channel type "DCH + HS-DSCH" for the DL, and both the corresponding DCH transport channel and MAC-d flow are configured, and with transport channel type "E-DCH" for the UL, and the corresponding E-DCH MAC-d flow is configured:
 - 4> select this multiplexing option; else
 - 3> if the RB has a multiplexing option with transport channel type "DCH + HS-DSCH" for the DL, and both the corresponding DCH transport channel and MAC-d flow are configured, and with transport channel type "DCH" for the UL, and the corresponding DCH transport channel is configured:
 - 4> select this multiplexing option; else
 - 3> if the RB has a multiplexing option with transport channel type "DCH + DSCH" for the DL, and both the corresponding DCH and DSCH transport channels are configured, and with transport channel type "E-DCH" for the UL, and the corresponding E-DCH MAC-d flow is configured:
 - 4> select this multiplexing option; else
 - 3> if the RB has a multiplexing option with transport channel type "DCH + DSCH" for the DL, and both the corresponding DCH and DSCH transport channels are configured, and with transport channel type "DCH" for the UL, and the corresponding DCH transport channel is configured:
 - 4> select this multiplexing option; else
 - 3> if the RB has a multiplexing option with transport channel type "HS-DSCH" for the DL, and the corresponding MAC-d flow is configured, and with transport channel type "E-DCH" for the UL, and the corresponding E-DCH MAC-d flow is configured:
 - 4> select this multiplexing option; else
 - 3> if the RB has a multiplexing option with transport channel type "HS-DSCH" for the DL, and the corresponding MAC-d flow is configured, and with transport channel type "DCH" for the UL, and the corresponding DCH transport channel is configured:
 - 4> select this multiplexing option; else
 - 3> if the RB has a multiplexing option with transport channel type "DSCH" for the DL, and the corresponding DSCH transport channel is configured, and with transport channel type "E-DCH" for the UL, and the corresponding E-DCH MAC-d flow is configured:
 - 4> select this multiplexing option; else
 - 3> if the RB has a multiplexing option with transport channel type "DSCH" for the DL, and the corresponding DSCH transport channel is configured, and with transport channel type "DCH" for the UL, and the corresponding DCH transport channel is configured:
 - 4> select this multiplexing option; else

3> if the RB has a multiplexing option with transport channel type "DCH" for the DL, and the corresponding DCH transport channel is configured, and with transport channel type "E-DCH" for the UL, and the corresponding E-DCH MAC-d flow is configured:

4> select this multiplexing option.

3> if the RB has a multiplexing option with transport channel type "DCH" for the DL, and the corresponding DCH transport channel is configured, and with transport channel type "DCH" for the UL, and the corresponding DCH transport channel is configured:

4> select this multiplexing option.

1> for TDD, select the multiplexing option according to the following:

2> if the UE is in CELL_FACH state:

3> if the RB has the multiplexing options with the transport channel types "FACH" and "DSCH" for the DL, and the corresponding FACH and DSCH transport channels are configured, and with the transport channel types "RACH" and "USCH" for the UL, and the corresponding RACH and USCH transport channels are configured:

4> if both PUSCH and PDSCH are allocated:

5> select the multiplexing option "DSCH" for DL and "USCH" for UL; else

4> if only PUSCH is allocated:

5> select the multiplexing option "FACH" for DL and "USCH" for UL; else

4> if only PDSCH is allocated:

5> select the multiplexing option "DSCH" for DL and "RACH" for UL; else

4> if neither PUSCH nor PDSCH is allocated:

5> select the multiplexing option "FACH" for DL and "RACH" for UL.

3> if the RB has a single multiplexing option with the transport channel type "FACH" for the DL and the transport channel type "RACH" for the UL:

4> select this multiplexing option; else

3> if the RB has a single multiplexing option with the transport channel type "DSCH" for the DL, and the corresponding DSCH transport channel is configured, and with the transport channel type "USCH" for the UL, and the corresponding USCH transport channel is configured:

4> select this multiplexing option; else

2> if the UE is in CELL_DCH state:

3> if the RB has a multiplexing option with transport channel type "DCH + HS-DSCH" for the DL, and both the corresponding DCH transport channel and MAC-d flow are configured, and with transport channel type "DCH" for the UL, and the corresponding DCH transport channel is configured:

4> select this multiplexing option; else

3> if the RB has a multiplexing option with transport channel type "DCH + DSCH" for the DL, and both the corresponding DCH and DSCH transport channels are configured, and with transport channel type "DCH" for the UL, and the corresponding DCH transport channel is configured:

4> select this multiplexing option; else

3> if the RB has a multiplexing option with transport channel type "HS-DSCH" for the DL, and the corresponding MAC-d flow is configured, and with transport channel type "DCH" for the UL, and the corresponding DCH transport channel is configured:

4> select this multiplexing option; else

3> if the RB has a multiplexing option with transport channel type "DCH" for the DL, and the corresponding DCH transport channel is configured, and with transport channel type "DCH" for the UL, and the corresponding DCH transport channel is configured:

4> select this multiplexing option; else

3> if the RB has a multiplexing option with transport channel type "DSCH" for the DL, and the corresponding DSCH transport channel is configured, and with transport channel "USCH" for the UL, and the corresponding USCH transport channel is configured:

4> select this multiplexing option.

1> configure the MAC with the appropriate transport format set (with computed transport block sizes) for the transport channel used by that RB;

1> in case the selected multiplexing option is a multiplexing option on E-DCH:

2> the set of RLC sizes that apply to the logical channel used by that RB consists of all RLC PDU sizes listed in the IE "RLC PDU size list" in the RB mapping info for E-DCH;

1> else

2> determine the sets of RLC sizes that apply to the logical channels used by that RB, based on the IEs "RLC size list" and/or the IEs "Logical Channel List" included in the applicable "Transport format set" (either the ones received in the same message or the ones stored if none were received);

1> in case the selected multiplexing option is a multiplexing option on RACH:

2> ignore the RLC size indexes that do not correspond to any RLC size within the Transport Format Set stored for RACH.

2> if there is no remaining RLC size index corresponding to an RLC size within the Transport Format Set stored for RACH:

3> set the variable INVALID_CONFIGURATION to TRUE.

1> if RACH is the transport channel to be used on the uplink, if that RB has a multiplexing option on RACH and if it is using AM:

2> apply the largest size amongst the ones derived according to the previous bullet for the RLC size (or RLC sizes in case the RB is realised using two logical channels) for the corresponding RLC entity.

NOTE: The IE "RB mapping info" is only included in the IE "Predefined RB configurations" in system information when used for Inter-RAT handover to UTRAN and there is no AM RLC size change involved in this case.

1> if that RB is using AM and the RLC size applicable to the uplink logical channel transporting data PDUs is different from the one derived from the previously stored configuration; and

1> none of the following conditions is met:

- the RLC size change is caused by a CELL UPDATE CONFIRM and the CELL UPDATE CONFIRM message includes the IE "Downlink counter synchronisation info".
- the RLC size change is caused by a reconfiguration message, and a cell update procedure occurs during the reconfiguration procedure and the CELL UPDATE CONFIRM message includes the IE "Downlink counter synchronisation info".
- the RLC size change is caused by a reconfiguration message, and a cell update procedure occurs during this reconfiguration procedure and the CELL UPDATE CONFIRM message includes the IE "RLC re-establish indicator" being set to TRUE for the corresponding radio bearer.

2> if the RLC size change is caused by a reconfiguration message or a CELL UPDATE CONFIRM; and

2> the IE "one sided RLC re-establishment" is included in that message and is set to TRUE:

3> re-establish the transmitting side of the corresponding RLC entity.

2> else:

- 3> re-establish the corresponding RLC entity.
- 2> configure the corresponding RLC entity with the new uplink RLC size;
- 2> for each AM RLC radio bearer in the CN domain as indicated in the IE "CN domain identity" in the IE "RAB info" in the variable ESTABLISHED_RABS whose RLC size is changed; and
- 2> for each AM RLC signalling radio bearer in the CN domain as indicated in the IE "CN domain identity" in the variable LATEST_CONFIGURED_CN_DOMAIN whose RLC size is changed:
- 3> if the IE "Status" in the variable CIPHERING_STATUS of this CN domain is set to "Started":
- 4> if the information causing the RLC re-establishment was included in system information:
 - 5> set the HFN values for the corresponding RLC entity equal to the value of the IE "START" for this CN domain that will be included in the CELL UPDATE message following cell reselection.

NOTE: Since the UE cannot predict the START value at the time of the next CELL UPDATE transmission in the future, UTRAN should desist from changing the RLC size for a signalling radio bearer within a cell. Other than this case the change in RLC size for a signalling radio bearer is known to the UE when reading system information following cell reselection.

- 4> if the RLC re-establishment is caused by a CELL UPDATE CONFIRM:
 - 5> if the whole RLC entity was re-established:
 - 6> set the HFN values for the corresponding RLC entity in uplink and downlink equal to the value of the IE "START" included in the latest transmitted CELL UPDATE message for this CN domain.
 - 5> if only the transmitting side of the RLC entity was re-established:
 - 6> set the HFN value for the corresponding RLC entity in the uplink equal to the value of the IE "START" included in the latest transmitted CELL UPDATE message for this CN domain.
- 4> if the RLC re-establishment is caused by a reconfiguration message:
 - 5> if the whole RLC entity was re-established:
 - 6> set the HFN values for the corresponding RLC entity in uplink and downlink equal to the value of the IE "START" that will be included in the reconfiguration complete message for this CN domain.
 - 5> if only the transmitting side of the RLC entity was re-established:
 - 6> set the HFN value for the corresponding RLC entity in the direction uplink equal to the value of the IE "START" that will be included in the reconfiguration complete message for this CN domain.

NOTE1: If the UTRAN modifies the RLC size for RB2 on any reconfiguration message or Cell Update Confirm message, the UE behaviour is unspecified in this version of the specification.

NOTE2: The UE cannot rely on the configured Transport Formats to determine the RLC sizes to be used in downlink for a particular logical channel. This size can be signalled explicitly in the RLC Info IE.

- 1> if that RB is using UM:
 - 2> indicate the largest RLC size applicable for uplink to the corresponding RLC entity.
- 1> configure MAC multiplexing according to the selected multiplexing option (MAC multiplexing shall only be configured for a logical channel if the transport channel it is mapped on according to the selected multiplexing option is the same as the transport channel another logical channel is mapped on according to the multiplexing option selected for it);
- 1> configure the MAC with the logical channel priorities according to selected multiplexing option;
- 1> configure the MAC with the set of applicable RLC Sizes for each of the logical channels used for that RB;

1> if there is no multiplexing option applicable for the transport channels and MAC-d flows to be used:

2> set the variable INVALID_CONFIGURATION to TRUE.

1> if there is more than one multiplexing option applicable for the transport channels or MAC-d flows to be used:

2> set the variable INVALID_CONFIGURATION to TRUE.

If upon cell re-selection or upon moving to CELL_FACH state from CELL_DCH state to initiate cell update procedure the UE sets variable INVALID_CONFIGURATION to TRUE as a result of the actions defined in this subclause, the UE should:

1> move to idle mode;

1> release (locally) the established signalling connections (as stored in the variable ESTABLISHED_SIGNALLING_CONNECTIONS) and the established radio access bearers (as stored in the variable ESTABLISHED_RABS) and indicate this to upper layers;

1> perform other actions when entering idle mode from connected mode as specified in subclause 8.5.2.

8.6.6.37 E-DCH Info

If the IE "E-DCH Info" is included and the UE will be in CELL_DCH state after completion of this procedure, the UE shall:

1> if the IE "E-DPCCH Info" is included:

2> store the newly received E-DPCCH configuration.

1> if the IE "E-DPDCH Info" is included:

2> store the newly received E-DPDCH configuration.

1> determine the value for the E_DCH_TRANSMISSION variable and take the corresponding actions as described in subclause 8.5.2⁸⁵.

When the variable E_DCH_TRANSMISSION is set to TRUE the UE shall:

1> configure the UL E-DPCCH in accordance with the stored IE "E-DPCCH" configuration;

1> configure the UL E-DPDCH in accordance with the stored IE "E-DPDCH" configuration.

10.3.4.23 RLC info

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
CHOICE Uplink RLC mode	OP			Indicates if Acknowledged, Unacknowledged or Transparent mode RLC shall be used.	
>AM RLC					
>>Transmission RLC discard	MP		Transmission RLC discard 10.3.4.25		
>>Transmission window size	MP		Integer(1,8,16,32,64,128,256,512,768,1024,1536,2048,2560,3072,3584,4096)	Maximum number of RLC PUs sent without getting them acknowledged. This parameter is needed if acknowledged mode is used. UE shall also assume that the UTRAN receiver window is equal to this value.	
>>Timer_RST	MP		Integer(50, 100, 150, 200, 250, 300, 350, 400, 450, 500, 550, 600, 700, 800, 900, 1000)	Elapsed time in milliseconds. It is used to trigger the retransmission of RESET PDU.	
>>Max_RST	MP		Integer(1, 4, 6, 8, 12, 16, 24, 32)	Defined in [16]	
>>Polling info	OP		Polling info 10.3.4.4		
>UM RLC					
>>Transmission RLC discard	OP		Transmission RLC discard 10.3.4.25		
>TM RLC					
>>Transmission RLC discard	OP		Transmission RLC discard 10.3.4.25		
>>Segmentation indication	MP		Boolean	TRUE indicates that segmentation is performed.	
CHOICE Downlink RLC mode	OP			Indicates if Acknowledged, Unacknowledged or Transparent mode RLC shall be used	
>AM RLC					
>>DL RLC PDU size	MP		Integer(0..4992 by step of 8)	Unit is bits	REL-5
>>In-sequence delivery	MP		Boolean	TRUE indicates that RLC shall preserve the order of higher layer PDUs when these are delivered. FALSE indicates that receiving RLC entity could allow SDUs to be delivered to the higher layer in different order than submitted to RLC sublayer at the transmitting side.	
>>Receiving window size	MP		Integer(1,8,16,32,64,128,256,512,768,1024,1536,2048,2560,3072,3584,4096)	Maximum number of RLC PUs allowed to be received. This parameter is needed if acknowledged mode is used.	

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
			047,2560,30 72,3584,409 5)	UE shall also assume that the UTRAN transmitter window is equal to this value	
>>Downlink RLC status Info	MP		Downlink RLC status info 10.3.4.1		
>UM RLC				(No data)	
>>DL UM RLC LI size	MP		Integer(7, 15)	Size in bits to use for the downlink RLC UM LI.	REL-5
>>DL Duplication Avoidance and Reordering info	OP		UM Duplication Avoidance and Reordering info 10.3.4.26		REL-6
>>DL Out of sequence delivery info	OP		UM Out of sequence delivery info 10.3.4.27		REL-6
>TM RLC					
>>Segmentation indication	MP		Boolean	TRUE indicates that segmentation is performed.	
One sided RLC re-establishment	MP		Boolean	TRUE indicates that only one side of the AM RLC entity is re-established.	REL-5

Condition	Explanation
<i>EDCH</i>	This IE is mandatory if the RB has a mapping option on E-DCH, otherwise it is not needed.

NOTE: This information element is included within IE "Predefined RB configuration".

CHANGE REQUEST

25.331 CR 2534 #rev - # Current version: 6.4.0

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the # symbols.

Proposed change affects: UICC apps # ME Radio Access Network Core Network

Title:	# Introduction of E-DCH in the ASN.1	
Source:	# RAN WG2	
Work item code:	# EUDCH-L23	Date: # 18/02/2005
Category:	# B Use <u>one</u> of the following categories: F (correction) A (corresponds to a correction in an earlier release) B (addition of feature), C (functional modification of feature) D (editorial modification) Detailed explanations of the above categories can be found in 3GPP TR 21.900 .	Release: # Rel-6 Use <u>one</u> of the following releases: Ph2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) Rel-4 (Release 4) Rel-5 (Release 5) Rel-6 (Release 6) Rel-7 (Release 7)

Reason for change:	# The E-DCH feature was introduced in the 25.331 v6.4.0 (December 2004) without updating the ASN.1.
Summary of change:	# Introducing E-DCH in the ASN.1 (refer to R2-050442 cover paper for details). Certain corrections of the tabular are done to align between the tabular and the proposed ASN.1.
Consequences if not approved:	# (Category B)

Clauses affected:	# 10.3.4.21, 10.3.4.23, 10.3.5.1b, 10.3.5.7d, 10.3.5.23, 10.3.6.27, 10.3.6.97, 10.3.6.98, 10.3.6.99, 10.3.6.100, 10.3.6.101, 10.3.6.102, 10.3.10, 11.2, 11.3, 11.4, 11.5 and 14.12.4.2																								
Other specs affected:	# <table border="1" style="display: inline-table; vertical-align: middle;"><tr><td>Y</td><td>N</td></tr><tr><td>X</td><td></td></tr><tr><td>X</td><td></td></tr><tr><td>X</td><td></td></tr></table> Other core specifications # <table border="1" style="display: inline-table; vertical-align: middle;"><tr><td>Y</td><td>N</td></tr><tr><td>X</td><td></td></tr><tr><td>X</td><td></td></tr><tr><td>X</td><td></td></tr></table> Test specifications # <table border="1" style="display: inline-table; vertical-align: middle;"><tr><td>Y</td><td>N</td></tr><tr><td>X</td><td></td></tr><tr><td>X</td><td></td></tr><tr><td>X</td><td></td></tr></table> O&M Specifications	Y	N	X		X		X		Y	N	X		X		X		Y	N	X		X		X	
Y	N																								
X																									
X																									
X																									
Y	N																								
X																									
X																									
X																									
Y	N																								
X																									
X																									
X																									
Other comments:	#																								

10.3.4 Radio Bearer Information elements

10.3.4.21 RB mapping info

A multiplexing option for each possible transport channel MAC-d flow or E-DCH MAC-d flow this RB can be multiplexed on.

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
Information for each multiplexing option	MP	1 to <maxRBMaxOptions>			
>RLC logical channel mapping indicator	CV-UL-RLCLogicalChannels		Boolean	TRUE indicates that the first logical channel shall be used for data PDUs and the second logical channel shall be used for control PDUs. FALSE indicates that control and data PDUs can be sent on either of the two logical channels. This parameter is not used in this release and shall be set to TRUE.	
>Number of uplink RLC logical channels	CV-UL-RLC info	1 to MaxLoCHperRLC		1 or 2 logical channels per RLC entity or radio bearer RLC [16]	
>>Uplink transport channel type	MP		Enumerated(DCH,RACH,CPCH,USCH, ,E-DCH)	CPCH is FDD only USCH is TDD only	REL-6
>>CHOICE Uplink transport channel type					REL-6
>>>DCH, RACH, CPCH, USCH					REL-6
>>>ULtransport channel identity	CV-UL-DCH/USCH		Transport channel identity 10.3.5.18	This is the ID of a DCH or USCH (TDD only) that this RB could be mapped onto.	
>>>Logical channel identity	OP		Integer(1..15)	This parameter is used to distinguish logical channels multiplexed by MAC on a transport channel.	
>>>CHOICE RLC size list	MP			The RLC sizes that are allowed for this logical channel.	
>>>>All			Null	All RLC sizes listed in the Transport Format Set. 10.3.5.23	

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
>>>>Configured			Null	The RLC sizes configured for this logical channel in the <i>Transport Format Set</i> . 10.3.5.23 if present in this message or in the previously stored configuration otherwise	
>>>>Explicit List		1 to <maxTF>		Lists the RLC sizes that are valid for the logical channel.	
>>>>>RLC size index	MP		Integer(1..maxTF)	The integer number is a reference to the RLC size which arrived at that position in the <i>Transport Format Set</i> 10.3.5.23	
>>>E-DCH					REL-6
>>>E-DCH MAC-d flow identity	MP		E-DCH MAC-d flow identity 10.3.5.7e		REL-6
>>>>DDI	MP		Integer (0..62)	If more than 1 UL RLC PDU size is configured for this RB, the different sizes will use subsequent DDI values starting from this DDI value. Value "0x3F" is reserved	REL-6
>>>RLC PDU size list	MP	1 to <MaxRL CPDUsize PerLogChan>			REL-6
>>>>RLC PDU size	MP		Integer_(016..49925 000 by step of 8)	Unit is bits	REL-6
>>MAC logical channel priority	MP		Integer(1..8)	This is priority between a user's different RBs (or logical channels). [15]	
>Downlink RLC logical channel info	CV-DL-RLC info				
>>Number of downlink RLC logical channels	MD	1 to MaxLoCHperRLC		1 or 2 logical channels per RLC entity or radio bearer RLC [16] Default value is that parameter values for DL are exactly the same as for corresponding UL	

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
				logical channel. In case two multiplexing options are specified for the UL, the first options shall be used as default for the DL. As regards to the IE "Channel type", rule is specified in 8.6.4.8.	
>>>Downlink transport channel type	MP		Enumerated(DCH,FACH, DSCH,DCH+ DSCH , HS-DSCH, DCH + HS- DSCH)	Note 1	REL-5
>>>DL DCH Transport channel identity	CV-DL- DCH		Transport channel identity 10.3.5.18		
>>>DL DSCH Transport channel identity	CV-DL- DSCH		Transport channel identity 10.3.5.18		
>>>DL HS-DSCH MAC-d flow identity	CV-DL-HS- DSCH		MAC-d flow identity 10.3.5.7c		REL-5
>>>Logical channel identity	OP		Integer(1..15)	16 is reserved	
Note 1: The IE "Downlink transport channel type" values "HS-DSCH" and "DCH + HS-DSCH" are not used in the RRC CONNECTION SETUP message.					
Note 2: The IE "Uplink transport channel type" value E-DCH is not used in the RRC CONNECTION SETUP message.					

Condition	Explanation
UL-RLC info	If "CHOICE Uplink RLC mode" in the IE "RLC info" that applies for that RB (i.e. either the one stored or received in the same message for the RB for which the "RB mapping info" was received, or the one stored or received in the same message for the RB pointed at in the IE "Same as RB" in the IE "RB information to setup" stored or received in the same message) is present this IE is mandatory present. Otherwise the IE is not needed.
DL-RLC info	If "CHOICE Downlink RLC mode" in the IE "RLC info" that applies for that RB (i.e. either the one stored or received in the same message for the RB for which the "RB mapping info" was received, or the one stored or received in the same message for the RB pointed at in the IE "Same as RB" in the IE "RB information to setup" stored or received in the same message) is present this IE is mandatory present. Otherwise the IE is not needed.
UL-RLCLogicalChannels	If "Number of uplink RLC logical channels" in IE "RB mapping info" is 2, then this IE is mandatory present. Otherwise this IE is not needed.
UL-DCH/USCH	If IE "Uplink transport channel type" is equal to "DCH" or "USCH" (TDD only) this IE is mandatory present. Otherwise the IE is not needed.
DL-DCH	If IE "Downlink transport channel type" is equal to "DCH", "DCH+DSCH" or "DCH + HS-DSCH" this IE is

		mandatory present. Otherwise the IE is not needed.
<i>DL-DSCH</i>		If IE "Downlink transport channel type" is equal to "DSCH" or "DCH+DSCH" this IE is mandatory present. Otherwise the IE is not needed.
<i>DL-HS-DSCH</i>		If IE "Downlink transport channel type" is equal to "HSDSCH" or "DCH + HS-DSCH" this IE is mandatory present. Otherwise the IE is not needed.

10.3.4.23 RLC info

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
<i>CHOICE Uplink RLC mode</i>	OP			Indicates if Acknowledged, Unacknowledged or Transparent mode RLC shall be used.	
>AM RLC					
>>Transmission RLC discard	MP		Transmission RLC discard 10.3.4.25		
>>Transmission window size	MP		Integer(1,8,16,32,64,128,256,512,768,1024,1536,2048,2560,3072,3584,4096)	Maximum number of RLC PUs sent without getting them acknowledged. This parameter is needed if acknowledged mode is used. UE shall also assume that the UTRAN receiver window is equal to this value.	
>>Timer_RST	MP		Integer(50, 100, 150, 200, 250, 300, 350, 400, 450, 500, 550, 600, 700, 800, 900, 1000)	Elapsed time in milliseconds. It is used to trigger the retransmission of RESET PDU.	
>>Max_RST	MP		Integer(1, 4, 6, 8, 12, 16, 24, 32)	Defined in [16]	
>>Polling info	OP		Polling info 10.3.4.4		
>UM RLC					
>>Transmission RLC discard	OP		Transmission RLC discard 10.3.4.25		
>TM RLC					
>>Transmission RLC discard	OP		Transmission RLC discard 10.3.4.25		
>>Segmentation indication	MP		Boolean	TRUE indicates that segmentation is performed.	
<i>CHOICE Downlink RLC mode</i>	OP			Indicates if Acknowledged, Unacknowledged or Transparent mode RLC shall be used	
>AM RLC					

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
>>DL RLC PDU size	MP		Integer_(016..4992_5000 by step of 8)	Unit is bits	REL-5
>>In-sequence delivery	MP		Boolean	TRUE indicates that RLC shall preserve the order of higher layer PDUs when these are delivered. FALSE indicates that receiving RLC entity could allow SDUs to be delivered to the higher layer in different order than submitted to RLC sublayer at the transmitting side.	
>>Receiving window size	MP		Integer(1,8,1 6,32,64,128, 256,512,768, 1024,1536,2 047,2560,30 72,3584,409 5)	Maximum number of RLC PUs allowed to be received. This parameter is needed if acknowledged mode is used. UE shall also assume that the UTRAN transmitter window is equal to this value	
>>Downlink RLC status Info	MP		Downlink RLC status info 10.3.4.1	(No data)	
>UM RLC					
>>DL UM RLC LI size	MP		Integer(7, 15)	Size in bits to use for the downlink RLC UM LI.	REL-5
>>DL Duplication Avoidance and Reordering info	OP		UM Duplication Avoidance and Reordering info 10.3.4.26		REL-6
>>DL Out of sequence delivery info	OP		UM Out of sequence delivery info 10.3.4.27		REL-6
>TM RLC					
>>Segmentation indication	MP		Boolean	TRUE indicates that segmentation is performed.	
One sided RLC re-establishment	MP		Boolean	TRUE indicates that only one side of the AM RLC entity is re-established.	REL-5

Condition	Explanation
EDCH	This IE is mandatory if the RB has a mapping option on E-DCH, otherwise it is not needed.

NOTE: This information element is included within IE "Predefined RB configuration".

10.3.5 Transport CH Information elements

10.3.5.1b Added or reconfigured E-DCH MAC-d flow

This IE is used in relation to MAC-d flows mapped to the E-DCH transport channel.

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
E-DCH MAC-d flow identity	MP		E-DCH MAC-d flow identity 10.3.5.7e		REL-6
E-DCH MAC-d flow power offset	OP		FFS	Only allowed to be absent when already defined for this E-DCH MAC-d flow	REL-6
E-DCH MAC-d flow maximum number of retransmissions	OP		Integer (0..FFS)	Only allowed to be absent when already defined for this E-DCH MAC-d flow	REL-6
E-DCH MAC-d flow multiplexing list	OP		Bitstring_(MaxEDCH MacdFlows maxE-DCHMACdFI ow-1)	Indicates whether information from this MAC-d flow can be multiplexed in the same MAC-e PDU with MAC-d PDU's belonging to other MAC-d flows. Bit 0 is for MAC-d flow 0, ... Only bits below "MAC-d flow identity" of this MAC-d flow shall be used. <u>TRUE Value '1'</u> means multiplexing is allowed.	REL-6

10.3.5.2 Added or Reconfigured UL TrCH information

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
Uplink transport channel type	MP		Enumerated(DCH,USCH ,E-DCH)	USCH is TDD only Note 1	
UL Transport channel identity	MP		Transport channel identity 10.3.5.18		
	CV-NotE-DCH				REL-6
CHOICE <i>UL parameters</i>					REL-6
>DCH,USCH					REL-6
>>TFS	MP		Transport Format Set 10.3.5.23		
>E-DCH				Note 1	REL-6
>>E-DCH Transmission Time Interval	OP		Integer(2,10)	Unit is ms.	REL-6
>>HARQ info for E-DCH	OP		10.3.5.7d		REL-6
>>Added or reconfigured E-DCH MAC-d flow	OP		10.3.5.1b		REL-6
Note 1: The IE "Uplink transport channel type" value "E-DCH" is not used in the RRC CONNECTION SETUP message, nor is the CHOICE <i>UL parameters</i> = "E-DCH".					

Condition	Explanation
NotE-DCH	If the uplink transport channel type is DCH or USCH then this IE is mandatory otherwise it is not needed.

NOTE: This information element is included within IE "Predefined RB configuration".

10.3.5.7d HARQ Info for E-DCH

This IE is used in relation to the E-DCH transport channel.

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
HARQ Round Trip Time	MP		Integer (1.. W maxHar qRTT)	A value "x" means that every x-th TTI the same HARQ process shall be scheduled.	REL-6

10.3.5.23 Transport Format Set

Information Element/Group name	Need	Multi	Type and reference	Semantics description
CHOICE <i>Transport channel type</i>	MP			
>Dedicated transport channels				The transport channel that is configured with this TFS is of type DCH
>>Dynamic Transport Format Information	MP	1 to <maxTF>		
>>>RLC Size	MP		Integer (0.. 4992 16.. 5000 by step of 8)	Unit is bits
>>>Number of TBs and TTI List	MP	1 to <maxTF>		Present for every valid number of TB's (and TTI) for this RLC

Information Element/Group name	Need	Multi	Type and reference	Semantics description
				Size.
>>>Transmission Time Interval	CV- <i>dynamicTTI</i>		Integer(10,2 0,40,80)	Unit is ms.
>>>Number of Transport blocks	MP		Integer(0..512)	
>>>CHOICE Logical Channel List	MP			The logical channels that are allowed to use this RLC Size
>>>ALL			Null	All logical channels mapped to this transport channel.
>>>Configured			Null	The logical channels configured to use this RLC size in the <i>RB mapping info</i> . 10.3.4.21 if present in this message or in the previously stored configuration otherwise
>>>Explicit List		1 to 15		Lists the logical channels that are allowed to use this RLC size.
>>>>RB Identity	MP		RB identity 10.3.4.16	
>>>>LogicalChannel	CH-UL- <i>RLCLogicalChannels</i>		Integer(0..1)	Indicates the relevant UL logical channel for this RB. "0" corresponds to the first, "1" corresponds to the second UL logical channel configured for this RB in the IE "RB mapping info".
>>Semi-static Transport Format Information	MP		Semi-static Transport Format Information 10.3.5.11	
>Common transport channels				The transport channel that is configured with this TFS is of a type not equal to DCH
>>Dynamic Transport Format Information	MP	1 to <maxTF>		Note
>>>RLC Size	MP		Integer (0..499216..5000 by step of 8)	Unit is bits
>>>Number of TBs and TTI List	MP	1 to <maxTF>		Present for every valid number of TB's (and TTI) for this RLC Size.
>>>Number of Transport blocks	MP		Integer(0..512)	
>>>CHOICE mode	MP			
>>>>FDD				(no data)
>>>>TDD				
>>>>>Transmission Time Interval	CV- <i>dynamicTTI</i>		Integer(10,2 0,40,80)	Unit is ms.
>>>CHOICE Logical Channel List	MP			The logical channels that are allowed to use this RLC Size.
>>>ALL			Null	All logical channels mapped to this transport channel.
>>>Configured			Null	The logical channels configured to use this RLC size in the <i>RB mapping info</i> . 10.3.4.21 if present in this message or in the previously stored configuration otherwise

Information Element/Group name	Need	Multi	Type and reference	Semantics description
>>>Explicit List		1 to 15		Lists the logical channels that are allowed to use this RLC size.
>>>>RB Identity	MP		RB identity 10.3.4.16	
>>>>LogicalChannel	CV-UL- <i>RLCLogicalChannels</i>		Integer(0..1)	Indicates the relevant UL logical channel for this RB. "0" corresponds to the first, "1" corresponds to the second UL logical channel configured for this RB in the IE "RB mapping info".
>>Semi-static Transport Format Information	MP		Semi-static Transport Format Information 10.3.5.11	

Condition	Explanation
<i>dynamicTTI</i>	This IE is mandatory present if dynamic TTI usage is indicated in IE Transmission Time Interval in Semi-static Transport Format Information. Otherwise it is not needed.
<i>UL-RLCLogicalChannels</i>	If "Number of uplink RLC logical channels" in IE "RB mapping info" in this message is 2 or the IE "RB mapping info" is not present in this message and 2 UL logical channels are configured for this RB, then this IE is mandatory present. Otherwise this IE is not needed.

10.3.6 Physical CH Information elements

10.3.6.27 Downlink information for each radio link

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
Choice mode	MP				
>FDD					
>>Primary CPICH info	MP		Primary CPICH info 10.3.6.60		
>>Cell ID	OP		Cell ID 10.3.2.2		REL-4
>>PDSCH with SHO DCH Info	OP		PDSCH with SHO DCH Info 10.3.6.47		
>>PDSCH code mapping	OP		PDSCH code mapping 10.3.6.43		
>>Serving HS-DSCH radio link indicator	CV- <i>not_rrcConnectionSetup</i>		Boolean	The value "TRUE" indicates that this radio link is the serving HS-DSCH radio link	REL-5
>> Serving E-DCH radio link	CV- <i>not_rrcConnectionSetup</i>		Boolean	The value "TRUE" indicates that this radio link is the serving E-DCH radio link	REL-6
>TDD					
>>Primary CCPCH info	MP		Primary CCPCH info 10.3.6.57		
Downlink DPCH info for each RL	OP		Downlink DPCH info for each RL 10.3.6.21		
SCCPCH Information for FACH	OP		SCCPCH Information for FACH 10.3.6.70		
E-AGCH Info	<u>OP CV- not_rrcConnectionSetup</u>		E-AGCH Info 10.3.6.100		REL-6
E-HICH Information	<u>OP CV- not_rrcConnectionSetup</u>		E-HICH Info 10.3.6.101		REL-6
E-RGCH Information	<u>OP CV- not_rrcConnectionSetup</u>		E-RGCH Info 10.3.6.102		REL-6

Condition	Explanation
<i>not_rrcConnectionSetup</i>	This IE is not needed in the RRC CONNECTION SETUP message. Otherwise it is mandatory present.

10.3.6.97 E-DCH Info

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
E-DPCCH info	OP		E-DPCCH Info 10.3.6.98		REL-6
E-DPDCH info	OP		E-DPDCH info 10.3.6.99		REL-6

10.3.6.98 E-DPCCH Info

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
E-DPCCH/DPCCH power offset	MP		FFS		REL-6

10.3.6.99 E-DPDCH Info

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
Reference E-TFCI power offset	MP		FFS		REL-6
E-TFCI table index	MP		Integer_(0..FFS)	Indicates which standardised E-TFCI TB size table shall be used	REL-6
Maximum number of channelisation codes	MP		Integer_(1,2,4)		REL-6

10.3.6.100 E-AGCH Info

Includes the configuration for the E-DCH related Absolute Grant Channel.

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
DL Scrambling Code	MD		Secondary scrambling code 10.3.6.74	[Default FFS]	REL-6
E-AGCH Channelisation Code	MP		Integer_(0..255)		REL-6

10.3.6.101 E-HICH Info

Includes the configuration for the E-DCH related HARQ Acknowledgement Indicator Channel.

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
DL Scrambling Code	MD		Secondary scrambling code 10.3.6.74	[Default FFS]	REL-6
Channelisation Code	MP		Integer_(0..127)		REL-6
Signature Sequence	MP		Integer_(0..39)		REL-6
Timing offset	MP		FFS	FFS whether this IE is really needed	REL-6

10.3.6.102 E-RGCH Info

Includes the configuration for the E-DCH related Relative Grant Channel.

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
DL Scrambling Code	MD		Secondary scrambling code 10.3.6.74	[Default FFS]	REL-6
Signature Sequence	MP		Integer_(0..39)		REL-6
Timing offset	MP		FFS	FFS whether this IE is really needed	REL-6
RG combination index	OP		Integer(0..5)	Radio links with the same index have RG commands, which for the UE are known to be the same. If no RG combination index is indicated, the RG commands from this RL cannot be combined with the RG commands from any other RL.	REL-6

10.3.10 Multiplicity values and type constraint values

The following table includes constants that are either used as multi bounds (name starting with "max") or as high or low value in a type specification (name starting with "lo" or "hi"). Constants are specified only for values appearing more than once in the RRC specification. In case a constant is related to one or more other constants, an expression is included in the "value" column instead of the actual value.

Constant	Explanation	Value	Version
CN information			
maxCNdomains	Maximum number of CN domains	4	
UTRAN mobility information			
maxRAT	Maximum number of Radio Access Technologies	maxOtherRAT + 1	
maxOtherRAT	Maximum number of other Radio Access Technologies	15	
maxURA	Maximum number of URAs in a cell	8	
maxInterSysMessages	Maximum number of Inter System Messages	4	
maxRABsetup	Maximum number of RABs to be established	16	
UE information			
maxtransactions	Maximum number of parallel RRC transactions in downlink	25	
maxPDCPAlgotype	Maximum number of PDCP algorithm types	8	
maxDRACclasses	Maximum number of UE classes which would require different DRAC parameters	8	
maxFreqBandsFDD	Maximum number of frequency bands supported by the UE as defined in [21]	8	
maxFreqBandsTDD	Maximum number of frequency bands supported by the UE as defined in [22]	4	
maxFreqBandsGSM	Maximum number of frequency bands supported by the UE as defined in [45]	16	
maxPage1	Number of UEs paged in the Paging Type 1 message	8	
maxSystemCapability	Maximum number of system specific capabilities that can be requested in one message.	16	
MaxURNTIgroup	Maximum number of U-RNTI groups in one message	8	REL-5
RB information			
maxPredefConfig	Maximum number of predefined configurations	16	
maxRB	Maximum number of RBs	32	
maxSRBsetup	Maximum number of signalling RBs to be established	8	
maxRBperRAB	Maximum number of RBs per RAB	8	
maxRBallRBs	Maximum number of non signalling RBs	27	
maxRBperTrCh	Maximum number of RB per TrCh	16	REL-6
maxRBMuxOptions	Maximum number of RB multiplexing options	8	
maxLoCHperRLC	Maximum number of logical channels per RLC entity	2	
maxRLCPDUsizesPerLogChan	Maximum number of RLC PDU sizes per logical channel	FFS	REL-6
MaxROHC-PacketSizes	Maximum number of packet sizes that are allowed to be produced by ROHC.	16	
MaxROHC-Profiles	Maximum number of profiles supported by ROHC on a given RB.	8	
maxRFC 3095-CID	Maximum number of available CID values per radio bearer	16384	REL-5
TrCH information			
maxE-DCHMACdFlow	Maximum number of E-DCH MAC-d flows	FFS	REL-6
maxHargRTT	Maximum number of E-DCH HARQ processes	FFS	REL-6
MaxHProcesses	Maximum number of H-ARQ processes	8	REL-5
MaxHSDSCH_TB_index	Maximum number of TB set size configurations for the HS-DSCH.	64 (FDD and 1.28 MCPS TDD); 512 (3.84 Mcps TDD)	REL-5

Constant	Explanation	Value	Version
maxMACdPDUSizes	Maximum number of MAC-d PDU sizes per queue permitted for MAC-hs	8	REL-5
maxTrCH	Maximum number of transport channels used in one direction (UL or DL)	32	
maxTrCHpreconf	Maximum number of preconfigured Transport channels, per direction	16	
maxCCTrCH	Maximum number of CCTrCHs	8	
maxQueueID	Maximum number of Mac-hs queues	8	REL-5
MaxTF	Maximum number of different transport formats that can be included in the Transport format set for one transport channel	32	
maxTF-CPCH	Maximum number of TFs in a CPCH set	16	
maxTFC	Maximum number of Transport Format Combinations	1024	
maxTFCsub	Maximum number of Transport Format Combinations Subset	1024	
maxTFCI-1-Combs	Maximum number of TFCI (field 1) combinations	512	
maxTFCI-2-Combs	Maximum number of TFCI (field 2) combinations	512	
maxCPCHsets	Maximum number of CPCH sets per cell	16	
maxSIBperMsg	Maximum number of complete system information blocks per SYSTEM INFORMATION message	16	
maxSIB	Maximum number of references to other system information blocks.	32	
maxSIB-FACH	Maximum number of references to system information blocks on the FACH	8	
PhyCH information			
maxHSSCCHs	Maximum number of HSSCCH codes that can be assigned to a UE	4	REL-5
maxPCPCH-APsubCH	Maximum number of available sub-channels for AP signature on PCPCH	12	
maxPCPCH-CDsubCH	Maximum number of available sub-channels for CD signature on PCPCH	12	
maxPCPCH-APsig	Maximum number of available signatures for AP on PCPCH	16	
maxPCPCH-CDsig	Maximum number of available signatures for CD on PCPCH	16	
maxAC	Maximum number of access classes	16	
maxASC	Maximum number of access service classes	8	
maxASCmap	Maximum number of access class to access service classes mappings	7	
maxASCpersist	Maximum number of access service classes for which persistence scaling factors are specified	6	
maxPRACH	Maximum number of PRACHs in a cell	16	
MaxPRACH_FPACH	Maximum number of PRACH / FPACH pairs in a cell (1.28 Mcps TDD)	8	REL-4
maxFACHPCH	Maximum number of FACHs and PCHs mapped onto one secondary CCPCHs	8	
maxTrChperSCCPCH	Maximum number of TrCh per S-CCPCH	8	REL-6
maxRL	Maximum number of radio links	8	
maxSCCPCH	Maximum number of secondary CCPCHs per cell	16	
maxDPDCH-UL	Maximum number of DPDCHs per cell	6	
maxDPCH-DLchan	Maximum number of channelisation codes used for DL DPCH	8	
maxPUSCH	Maximum number of PUSCHs	(8)	
maxPDSCH	Maximum number of PDSCHs	8	
maxPDSCHcodes	Maximum number of codes for PDSCH	16	
maxPDSCH-TFCIgroups	Maximum number of TFCI groups for PDSCH	256	
maxPDSCHcodeGroups	Maximum number of code groups for PDSCH	256	
maxPCPCHs	Maximum number of PCPCH channels in a CPCH Set	64	
maxPCPCH-SF	Maximum number of available SFs on PCPCH	7	
maxTS	Maximum number of timeslots used in one direction (UL or DL)	14 (3.84 Mcps TDD)	

Constant	Explanation	Value	Version
		6 (1.28 Mcps TDD)	REL-4
hiPUSCHidentities	Maximum number of PUSCH Identities	64	
hiPDSCHidentities	Maximum number of PDSCH Identities	64	
Measurement information			
maxTGPS	Maximum number of transmission gap pattern sequences	6	
maxAdditionalMeas	Maximum number of additional measurements for a given measurement identity	4	
maxMeasEvent	Maximum number of events that can be listed in measurement reporting criteria	8	
maxMeasParEvent	Maximum number of measurement parameters (e.g. thresholds) per event	2	
maxMeasIntervals	Maximum number of intervals that define the mapping function between the measurements for the cell quality Q of a cell and the representing quality value	1	
maxCellMeas	Maximum number of cells to measure	32	
maxReportedGSMCells	Maximum number of GSM cells to be reported	8	
maxFreq	Maximum number of frequencies to measure	8	
maxSat	Maximum number of satellites to measure	16	
maxSatAlmanacStorage	Maximum number of satellites for which to store GPS Almanac information	32	
HiRM	Maximum number that could be set as rate matching attribute for a transport channel	256	
Frequency information			
MaxFDDFreqList	Maximum number of FDD carrier frequencies to be stored in USIM	4	
MaxTDDFreqList	Maximum number of TDD carrier frequencies to be stored in USIM	4	
MaxFDDFreqCellList	Maximum number of neighbouring FDD cells to be stored in USIM	32	
MaxTDDFreqCellList	Maximum number of neighbouring TDD cells to be stored in USIM	32	
MaxGSMCellList	Maximum number of GSM cells to be stored in USIM	32	
Other information			
MaxGERANSI	Maximum number of GERAN SI blocks that can be provided as part of NACC information	8	REL-5
maxNumGSMFreqRanges	Maximum number of GSM Frequency Ranges to store	32	
MaxNumFDDFreqs	Maximum number of FDD centre frequencies to store	8	
MaxNumTDDFreqs	Maximum number of TDD centre frequencies to store	8	
maxNumCDMA200Freqs	Maximum number of CDMA2000 centre frequencies to store	8	
maxGSMTargetCells	Maximum number of GSM target cells	32	REL-6
MBMS information			
maxMBMS-CommonCCTrCh	Maximum number of CCTrCh configurations included in the MBMS COMMON P-T-M RB INFORMATION message	32	REL-6
maxMBMS-CommonPhyCh	Maximum number of PhyCh configurations included in the MBMS COMMON P-T-M RB INFORMATION message	32	REL-6
maxMBMS-CommonRB	Maximum number of RB configurations included in the MBMS COMMON P-T-M RB INFORMATION message	32	REL-6
maxMBMS-CommonTrCh	Maximum number of TrCh configurations included in the MBMS COMMON P-T-M RB INFORMATION message	32	REL-6
maxMBMS-Freq	Maximum number of MBMS preferred frequencies	4	REL-6

Constant	Explanation	Value	Version
maxMBMS-L1CP	Maximum number of periods in which layer 1 combining applies	FFS	REL-6
maxMBMSServCount	Maximum number of MBMS services in a Access Info message	4	REL-6
maxMBMSServDedic	Maximum number of MBMS services in a dedicated notification/ Paging type 2 message	4	REL-6
maxMBMSServModif	Maximum number of MBMS services in a MBMS MODIFIED SERVICES INFORMATION message	4	REL-6
maxMBMSServSched	Maximum number of MBMS services in a MBMS SCHEDULING INFORMATION message	16	REL-6
maxMBMSServUnmodif	Maximum number of MBMS services in a MBMS UNMODIFIED SERVICES INFORMATION message	32	REL-6
maxMBMSTransmis	Maximum number of transmissions for which scheduling information is provided within a scheduling period	FFS	REL-6

11 Message and Information element abstract syntax (with ASN.1)

11.1 General message structure

```
Class-definitions DEFINITIONS AUTOMATIC TAGS ::=
```

```
BEGIN
```

```
IMPORTS
```

```

ActiveSetUpdate,
ActiveSetUpdateComplete,
ActiveSetUpdateFailure,
AssistanceDataDelivery,
CellChangeOrderFromUTRAN,
CellChangeOrderFromUTRANFailure,
CellUpdate,
CellUpdateConfirm-CCCH,
CellUpdateConfirm,
CounterCheck,
CounterCheckResponse,
DownlinkDirectTransfer,
HandoverToUTRANComplete,
InitialDirectTransfer,
HandoverFromUTRANCommand-GERANIu,
HandoverFromUTRANCommand-GSM,
HandoverFromUTRANCommand-CDMA2000,
HandoverFromUTRANFailure,
MBMSAccessInformation,
MBMSCommonPTMRBInformation,
MBMSCurrentCellPTMRBInformation,
MBMSGeneralInformation,
MBMSModificationRequest,
MBMSModifiedServicesInformation,
MBMSNeighbouringCellPTMRBInformation,
MBMSSchedulingInformation,
MBMSUnmodifiedServicesInformation,
MeasurementControl,
MeasurementControlFailure,
MeasurementReport,
PagingType1,
PagingType2,
PhysicalChannelReconfiguration,
PhysicalChannelReconfigurationComplete,
PhysicalChannelReconfigurationFailure,
PhysicalSharedChannelAllocation,
PUSCHCapacityRequest,
RadioBearerReconfiguration,
RadioBearerReconfigurationComplete,
RadioBearerReconfigurationFailure,
RadioBearerRelease,
RadioBearerReleaseComplete,
RadioBearerReleaseFailure,
RadioBearerSetup,
RadioBearerSetupComplete,
RadioBearerSetupFailure,
RRCConnectionReject,
RRCConnectionRelease,
RRCConnectionRelease-CCCH,
RRCConnectionReleaseComplete,
RRCConnectionRequest,
RRCConnectionSetup,
RRCConnectionSetupComplete,
RRCStatus,
SecurityModeCommand,
SecurityModeComplete,
SecurityModeFailure,
SignallingConnectionRelease,
SignallingConnectionReleaseIndication,
```

```

SystemInformation-BCH,
SystemInformation-FACH,
SystemInformationChangeIndication,
TransportChannelReconfiguration,
TransportChannelReconfigurationComplete,
TransportChannelReconfigurationFailure,
TransportFormatCombinationControl,
TransportFormatCombinationControlFailure,
UECapabilityEnquiry,
UECapabilityInformation,
UECapabilityInformationConfirm,
UplinkDirectTransfer,
UplinkPhysicalChannelControl,
URAUpdate,
URAUpdateConfirm,
URAUpdateConfirm-CCCH,
UTRANMobilityInformation,
UTRANMobilityInformationConfirm,
UTRANMobilityInformationFailure
FROM PDU-definitions

-- User Equipment IEs :
  IntegrityCheckInfo
FROM InformationElements;

--***** --
-- Downlink DCCH messages
--***** --

DL-DCCH-Message ::= SEQUENCE {
  integrityCheckInfo      IntegrityCheckInfo      OPTIONAL,
  message                 DL-DCCH-MessageType
}

DL-DCCH-MessageType ::= CHOICE {
  activeSetUpdate           ActiveSetUpdate,
  assistanceDataDelivery    AssistanceDataDelivery,
  cellChangeOrderFromUTRAN   CellChangeOrderFromUTRAN,
  cellUpdateConfirm          CellUpdateConfirm,
  counterCheck               CounterCheck,
  downlinkDirectTransfer    DownlinkDirectTransfer,
  handoverFromUTRANCommand-GSM HandoverFromUTRANCommand-GSM,
  handoverFromUTRANCommand-CDMA2000 HandoverFromUTRANCommand-CDMA2000,
  measurementControl         MeasurementControl,
  pagingType2                PagingType2,
  physicalChannelReconfiguration PhysicalChannelReconfiguration,
  physicalSharedChannelAllocation PhysicalSharedChannelAllocation,
  radioBearerReconfiguration RadioBearerReconfiguration,
  radioBearerRelease          RadioBearerRelease,
  radioBearerSetup             RadioBearerSetup,
  rrcConnectionRelease        RRCConnectionRelease,
  securityModeCommand         SecurityModeCommand,
  signallingConnectionRelease SignallingConnectionRelease,
  transportChannelReconfiguration TransportChannelReconfiguration,
  transportFormatCombinationControl TransportFormatCombinationControl,
  ueCapabilityEnquiry          UECapabilityEnquiry,
  ueCapabilityInformationConfirm UECapabilityInformationConfirm,
  uplinkPhysicalChannelControl UplinkPhysicalChannelControl,
  uraUpdateConfirm            URAUpdateConfirm,
  utranMobilityInformation     UTRANMobilityInformation,
  handoverFromUTRANCommand-GERANIu HandoverFromUTRANCommand-GERANIu,
  mbmsModifiedServicesInformation MBMSModifiedServicesInformation,
  spare5                      NULL,
  spare4                      NULL,
  spare3                      NULL,
  spare2                      NULL,
  spare1                      NULL
}

--***** --
-- Uplink DCCH messages
--***** --

UL-DCCH-Message ::= SEQUENCE {

```

```

integrityCheckInfo      IntegrityCheckInfo      OPTIONAL,
message                UL-DCCH-MessageType
}

UL-DCCH-MessageType ::= CHOICE {
activeSetUpdateComplete      ActiveSetUpdateComplete,
activeSetUpdateFailure       ActiveSetUpdateFailure,
cellChangeOrderFromUTRANFailure CellChangeOrderFromUTRANFailure,
counterCheckResponse        CounterCheckResponse,
handoverToUTRANComplete     HandoverToUTRANComplete,
initialDirectTransfer      InitialDirectTransfer,
handoverFromUTRANFailure   HandoverFromUTRANFailure,
measurementControlFailure MeasurementControlFailure,
measurementReport          MeasurementReport,
physicalChannelReconfigurationComplete PhysicalChannelReconfigurationComplete,
physicalChannelReconfigurationFailure PhysicalChannelReconfigurationFailure,
radioBearerReconfigurationComplete RadioBearerReconfigurationComplete,
radioBearerReconfigurationFailure RadioBearerReconfigurationFailure,
radioBearerReleaseComplete   RadioBearerReleaseComplete,
radioBearerReleaseFailure    RadioBearerReleaseFailure,
radioBearerSetupComplete    RadioBearerSetupComplete,
radioBearerSetupFailure     RadioBearerSetupFailure,
rrcConnectionReleaseComplete RRCConnectionReleaseComplete,
rrcConnectionSetupComplete  RRCCConnectionSetupComplete,
rrcStatus                  RRCStatus,
securityModeComplete       SecurityModeComplete,
securityModeFailure        SecurityModeFailure,
signallingConnectionReleaseIndication SignallingConnectionReleaseIndication,
transportChannelReconfigurationComplete TransportChannelReconfigurationComplete,
transportChannelReconfigurationFailure TransportChannelReconfigurationFailure,
transportFormatCombinationControlFailure TransportFormatCombinationControlFailure,
ueCapabilityInformation    UECapabilityInformation,
uplinkDirectTransfer       UplinkDirectTransfer,
utranMobilityInformationConfirm UTRANMobilityInformationConfirm,
utranMobilityInformationFailure UTRANMobilityInformationFailure,
mbmsModificationRequest   MBMSModificationRequest,
spare1                     NULL
}

--*****--  

--  

-- Downlink CCCH messages  

--  

--*****--  

DL-CCCH-Message ::= SEQUENCE {
integrityCheckInfo      IntegrityCheckInfo      OPTIONAL,
message                DL-CCCH-MessageType
}

DL-CCCH-MessageType ::= CHOICE {
cellUpdateConfirm        CellUpdateConfirm-CCCH,
rrcConnectionReject      RRCConnectionReject,
rrcConnectionRelease     RRCConnectionRelease-CCCH,
rrcConnectionSetup       RRCConnectionSetup,
uraUpdateConfirm         URAUpdateConfirm-CCCH,
spare3                  NULL,
spare2                  NULL,
spare1                  NULL
}

--*****--  

--  

-- Uplink CCCH messages  

--  

--*****--  

UL-CCCH-Message ::= SEQUENCE {
integrityCheckInfo      IntegrityCheckInfo      OPTIONAL,
message                UL-CCCH-MessageType
}

```

```

UL-CCCH-MessageType ::= CHOICE {
    cellUpdate                               CellUpdate,
    rrcConnectionRequest                    RRCConnectionRequest,
    uraUpdate                                URAUpdate,
    spare                                     NULL
}

-- ****
-- PCCH messages
--
-- ****

PCCH-Message ::= SEQUENCE {
    message          PCCH-MessageType
}

PCCH-MessageType ::= CHOICE {
    pagingType1           PagingType1,
    spare                  NULL
}

-- ****
-- Downlink SHCCH messages
--
-- ****

DL-SHCCH-Message ::= SEQUENCE {
    message          DL-SHCCH-MessageType
}

DL-SHCCH-MessageType ::= CHOICE {
    physicalSharedChannelAllocation PhysicalSharedChannelAllocation,
    spare                           NULL
}

-- ****
-- Uplink SHCCH messages
--
-- ****

UL-SHCCH-Message ::= SEQUENCE {
    message          UL-SHCCH-MessageType
}

UL-SHCCH-MessageType ::= CHOICE {
    puschCapacityRequest      PUSCHCapacityRequest,
    spare                     NULL
}

-- ****
-- BCCH messages sent on FACH
--
-- ****

BCCH-FACH-Message ::= SEQUENCE {
    message          BCCH-FACH-MessageType
}

BCCH-FACH-MessageType ::= CHOICE {
    systemInformation        SystemInformation-FACH,
    systemInformationChangeIndication SystemInformationChangeIndication
    spare2                   NULL,
    spare1                   NULL
}

-- ****
-- BCCH messages sent on BCH
--
-- ****

BCCH-BCH-Message ::= SEQUENCE {
    message          SystemInformation-BCH
}

```

```

}

--*****
-- 
-- MCCH messages
-- 
--*****


MCCH-Message ::= SEQUENCE {
    message          MCCH-MessageType
}

MCCH-MessageType ::= CHOICE {
    mbmsAccessInformation      MBMSAccessInformation,
    mbmsCommonPTMRBInformation MBMSCommonPTMRBInformation,
    mbmsCurrentCellPTMRBInformation MBMSCurrentCellPTMRBInformation,
    mbmsGeneralInformation     MBMSGeneralInformation,
    mbmsModifiedServicesInformation MBMSModifiedServicesInformation,
    mbmsNeighbouringCellPTMRBInformation MBMSNeighbouringCellPTMRBInformation,
    mbmsUnmodifiedServicesInformation MBMSUnmodifiedServicesInformation,
    spare9                 NULL,
    spare8                 NULL,
    spare7                 NULL,
    spare6                 NULL,
    spare5                 NULL,
    spare4                 NULL,
    spare3                 NULL,
    spare2                 NULL,
    spare1                 NULL
}

--*****
-- 
-- MSCH messages
-- 
--*****


MSCH-Message ::= SEQUENCE {
    message          MSCH-MessageType
}

MSCH-MessageType ::= CHOICE {
    mbmsSchedulingInformation MBMSSchedulingInformation,
    spare3               NULL,
    spare2               NULL,
    spare1               NULL
}

}
END

```

11.2 PDU definitions

```

--***** 
-- 
-- TABULAR: The message type and integrity check info are not
-- visible in this module as they are defined in the class module.
-- Also, all FDD/TDD specific choices have the FDD option first
-- and TDD second, just for consistency.
-- 
--***** 

PDU-definitions DEFINITIONS AUTOMATIC TAGS :=

BEGIN

--***** 
-- 
-- IE parameter types from other modules
-- 
--***** 

IMPORTS

-- Core Network IEs :
CN-DomainIdentity,
CN-InformationInfo,

```

```

CN-InformationInfoFull,
NAS-Message,
PagingRecordTypeID,
PLMN-Identity,
-- UTRAN Mobility IEs :
CellIdentity,
CellIdentity-PerRL-List,
URA-Identity,
-- User Equipment IEs :
AccessStratumReleaseIndicator,
ActivationTime,
C-RNTI,
CapabilityUpdateRequirement,
CapabilityUpdateRequirement-r4,
CapabilityUpdateRequirement-r4-ext,
CapabilityUpdateRequirement-r5,
CellUpdateCause,
CellUpdateCause-ext,
CipheringAlgorithm,
CipheringModeInfo,
DSCH-RNTI,
E-RNTI,
EstablishmentCause,
FailureCauseWithProtErr,
FailureCauseWithProtErrTrId,
GroupReleaseInformation,
H-RNTI,
UESpecificBehaviourInformationIdle,
UESpecificBehaviourInformationInterRAT,
InitialUE-Identity,
IntegrityProtActivationInfo,
IntegrityProtectionModeInfo,
N-308,
PagingCause,
PagingRecordList,
PagingRecord2List-r5,
ProtocolErrorIndicator,
ProtocolErrorIndicatorWithMoreInfo,
RadioFrequencyBandTDDList,
Rb-timer-indicator,
RedirectionInfo,
RedirectionInfo-r6,
RejectionCause,
ReleaseCause,
RF-CapabilityComp,
RRC-StateIndicator,
RRC-TransactionIdentifier,
SecurityCapability,
START-Value,
STARTList,
SystemSpecificCapUpdateReq-v590ext,
U-RNTI,
U-RNTI-Short,
UE-RadioAccessCapability,
UE-RadioAccessCapability-v370ext,
UE-RadioAccessCapability-v380ext,
UE-RadioAccessCapability-v3a0ext,
UE-RadioAccessCapability-v3g0ext,
UE-RadioAccessCapability-v4b0ext,
UE-RadioAccessCapability-v590ext,
UE-RadioAccessCapabilityComp,
DL-PhysChCapabilityFDD-v380ext,
UE-ConnTimersAndConstants,
UE-ConnTimersAndConstants-v3a0ext,
UE-ConnTimersAndConstants-r5,
UE-SecurityInformation,
URA-UpdateCause,
UTRAN-DRX-CycleLengthCoefficient,
WaitTime,
-- Radio Bearer IEs :
DefaultConfigIdentity,
DefaultConfigIdentity-r4,
DefaultConfigIdentity-r5,
DefaultConfigMode,
DL-CounterSynchronisationInfo,
DL-CounterSynchronisationInfo-r5,
PredefinedConfigIdentity,
PredefinedConfigStatusList,

```

```

PredefinedConfigStatusListComp,
PredefinedConfigSetWithDifferentValueTag,
RAB-Info,
RAB-Info-Post,
RAB-InformationList,
RAB-InformationReconfigList,
RAB-InformationSetupList,
RAB-InformationSetupList-r4,
RAB-InformationSetupList-r5,
RAB-InformationSetupList-r6-ext,
RAB-InformationSetupList-r6,
RB-ActivationTimeInfoList,
RB-COUNT-C-InformationList,
RB-COUNT-C-MSB-InformationList,
RB-IdentityList,
RB-InformationAffectedList,
RB-InformationAffectedList-r5,
RB-InformationAffectedList-r6,
RB-InformationReconfigList,
RB-InformationReconfigList-r4,
RB-InformationReconfigList-r5,
RB-InformationReconfigList-r6,
RB-InformationReleaseList,
RB-PDCPContextRelocationList,
SRB-InformationSetupList,
SRB-InformationSetupList-r5,
SRB-InformationSetupList-r6,
SRB-InformationSetupList2,
UL-CounterSynchronisationInfo,
-- Transport Channel IEs:
CPCH-SetID,
DL-AddReconfTransChInfo2List,
DL-AddReconfTransChInfoList,
DL-AddReconfTransChInfoList-r4,
DL-AddReconfTransChInfoList-r5,
DL-CommonTransChInfo,
DL-CommonTransChInfo-r4,
DL-DeletedTransChInfoList,
DL-DeletedTransChInfoList-r5,
DRAC-StaticInformationList,
TFC-Subset,
TFCS-Identity,
UL-AddReconfTransChInfoList,
UL-AddReconfTransChInfoList-r6,
UL-CommonTransChInfo,
UL-CommonTransChInfo-r4,
UL-DeletedTransChInfoList,
UL-DeletedTransChInfoList-r6,
-- Physical Channel IEs :
Alpha,
CCTrCH-PowerControlInfo,
CCTrCH-PowerControlInfo-r4,
CCTrCH-PowerControlInfo-r5,
ConstantValue,
ConstantValueTdd,
CPCH-SetInfo,
DL-CommonInformation,
DL-CommonInformation-r4,
DL-CommonInformation-r5,
DL-CommonInformationPost,
DL-HSPDSCH-Information,
DL-InformationPerRL-List,
DL-InformationPerRL-List-r4,
DL-InformationPerRL-List-r5,
DL-InformationPerRL-List-r5bis,
DL-InformationPerRL-List-r6,
DL-InformationPerRL-ListPostFDD,
DL-InformationPerRL-PostTDD,
DL-InformationPerRL-PostTDD-LCR-r4,
DL-PDSCH-Information,
DL-TPC-PowerOffsetPerRL-List,
DPC-Mode,
DPCH-CompressedModeStatusInfo,
FrequencyInfo,
FrequencyInfoFDD,
FrequencyInfoTDD,
HARQ-Preamble-Mode,
HS-SICH-Power-Control-Info-TDD384,

```

```

MaxAllowedUL-TX-Power,
OpenLoopPowerControl-IPDL-TDD-r4,
PDSCH-CapacityAllocationInfo,
PDSCH-CapacityAllocationInfo-r4,
PDSCH-Identity,
PrimaryCPICH-Info,
PrimaryCCPCH-TX-Power,
PUSCH-CapacityAllocationInfo,
PUSCH-CapacityAllocationInfo-r4,
PUSCH-Identity,
PUSCH-SysInfoList-HCR-r5,
PDSCH-SysInfoList-HCR-r5,
RL-AdditionInformationList,
RL-RemovalInformationList,
SpecialBurstScheduling,
SSDT-Information,
TFC-ControlDuration,
SSDT-UL,
TimeslotList,
TimeslotList-r4,
TX-DiversityMode,
UL-ChannelRequirement,
UL-ChannelRequirement-r4,
UL-ChannelRequirement-r5,
UL-ChannelRequirement-r6,
UL-ChannelRequirementWithCPCH-SetID,
UL-ChannelRequirementWithCPCH-SetID-r4,
UL-ChannelRequirementWithCPCH-SetID-r5,
UL-ChannelRequirementWithCPCH-Set ID-r6,
UL-DPCH-Info,
UL-DPCH-Info-r4,
UL-DPCH-Info-r5,
UL-DPCH-Info-r6,
UL-DPCH-InfoPostFDD,
UL-DPCH-InfoPostTDD,
UL-DPCH-InfoPostTDD-LCR-r4,
UL-EDCH-Information-r6,
UL-SynchronisationParameters-r4,
UL-TimingAdvance,
UL-TimingAdvanceControl,
UL-TimingAdvanceControl-r4,
-- Measurement IEs :
AdditionalMeasurementID-List,
DeltaRSCP,
Frequency-Band,
EventResults,
Inter-FreqEventCriteriaList-v590ext,
Intra-FreqEventCriteriaList-v590ext,
IntraFreqReportingCriteria-1b-r5,
IntraFreqEvent-1d-r5,
InterFreqEventResults-LCR-r4-ext,
InterRATCellInfoIndicator,
InterRAT-TargetCellDescription,
MeasuredResults,
MeasuredResults-v390ext,
MeasuredResults-v590ext,
MeasuredResultsList,
MeasuredResultsList-LCR-r4-ext,
MeasuredResultsOnRACH,
MeasurementCommand,
MeasurementCommand-r4,
MeasurementIdentity,
MeasurementReportingMode,
PrimaryCCPCH-RSCP,
SFN-Offset-Validity,
TimeslotListWithISCP,
TrafficVolumeMeasuredResultsList,
UE-Positioning-GPS-AssistanceData,
UE-Positioning-Measurement-v390ext,
UE-Positioning-OTDOA-AssistanceData,
UE-Positioning-OTDOA-AssistanceData-r4ext,
UE-Positioning-OTDOA-AssistanceData-UEB,
-- Other IEs :
BCCH-ModificationInfo,
CDMA2000-MessageList,
GSM-TargetCellInfoList,
GERANIu-MessageList,
GERAN-SystemInformation,
GSM-MessageList,

```

```

InterRAT-ChangeFailureCause,
InterRAT-HO-FailureCause,
InterRAT-UE-RadioAccessCapabilityList,
InterRAT-UE-RadioAccessCapability-v590ext,
InterRAT-UE-SecurityCapList,
IntraDomainNasNodeSelector,
ProtocolErrorMoreInformation,
Rplmn-Information,
Rplmn-Information-r4,
SegCount,
SegmentIndex,
SFN-Prime,
SIB-Data-fixed,
SIB-Data-variable,
SIB-Type,
-- MBMS IEs:
MBMS-CellGroupIdentity-r6,
MBMS-CommonRBInformationList-r6,
MBMS-CurrentCell-SCCPCHList-r6,
MBMS-DefaultL1CombiningConfigInfo-r6,
MBMS-FLCAplicabilityInfo-r6,
MBMS-JoinedInformation-r6,
MBMS-MICHConfigurationInfo-r6,
MBMS-ModifiedServiceList-r6,
MBMS-MSCHConfigurationInfo-r6,
MBMS-NeighbouringCellsCCPCHList-r6,
MBMS-PhyChInformationList-r6,
MBMS-PreferredFreqRequest-r6,
MBMS-PreferredFrequencyList-r6,
MBMS-ServiceAccessInfoList-r6,
MBMS-ServiceSchedulingInfoList-r6,
MBMS-SIBType5-SCCPCHList-r6,
MBMS-TimersAndCounters-r6,
MBMS-TranspChInfoForEachCCTrCh-r6,
MBMS-TranspChInfoForEachTrCh-r6,
MBMS-UnmodifiedServiceList-r6
FROM InformationElements

maxSIBperMsg,
maxURNTI-Group
FROM Constant-definitions;

-- *****
-- ACTIVE SET UPDATE (FDD only)
-- *****
ActiveSetUpdate ::= CHOICE {
    r3
        SEQUENCE {
            activeSetUpdate-r3           ActiveSetUpdate-r3-IEs,
            laterNonCriticalExtensions   SEQUENCE {
                -- Container for additional R99 extensions
                activeSetUpdate-r3-add-ext  BIT STRING      OPTIONAL,
                v4b0NonCriticalExtensions  SEQUENCE {
                    activeSetUpdate-v4b0ext   ActiveSetUpdate-v4b0ext-IEs,
                    v590NonCriticalExtensions SEQUENCE {
                        activeSetUpdate-v590ext   ActiveSetUpdate-v590ext-IEs,
                        nonCriticalExtensions    SEQUENCE {} OPTIONAL
                    } OPTIONAL
                } OPTIONAL
            } OPTIONAL
        },
    later-than-r3
        SEQUENCE {
            rrc-TransactionIdentifier     RRC-TransactionIdentifier,
            criticalExtensions           SEQUENCE {}
        }
}
ActiveSetUpdate-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier     RRC-TransactionIdentifier,
    -- dummy and dummy2 are not used in this version of the specification, they should
    -- not be sent and if received they should be ignored.
    dummy                          IntegrityProtectionModeInfo      OPTIONAL,
    dummy2                         CipheringModeInfo          OPTIONAL,
    activationTime                 ActivationTime             OPTIONAL,
    newU-RNTI                      U-RNTI                   OPTIONAL,
    -- Core network IEs
}

```

```

    cn-InformationInfo          CN-InformationInfo          OPTIONAL,
-- Radio bearer IEs
    -- dummy3 is not used in this version of the specification, it should
    -- not be sent and if received it should be ignored.
    dummy3                      DL-CounterSynchronisationInfo   OPTIONAL,
-- Physical channel IEs
    maxAllowedUL-TX-Power      MaxAllowedUL-TX-Power      OPTIONAL,
    rl-AdditionInformationList RL-AdditionInformationList  OPTIONAL,
    rl-RemovalInformationList  RL-RemovalInformationList  OPTIONAL,
    tx-DiversityMode           TX-DiversityMode           OPTIONAL,
    ssdt-Information            SSDT-Information           OPTIONAL
}

ActiveSetUpdate-v4b0ext-IEs ::= SEQUENCE {
    -- Physical channel IEs
    -- ssdt-UL extends SSDT-Information. FDD only.
    ssdt-UL-r4                  SSDT-UL                           OPTIONAL,
    -- The order of the RLs in IE cell-id-PerRL-List is the same as
    -- in IE RL-AdditionInformationList included in this message
    cell-id-PerRL-List           CellIdentity-PerRL-List        OPTIONAL
}

ActiveSetUpdate-v590ext-IEs ::= SEQUENCE {
    -- Physical channel IEs
    dpc-Mode                     DPC-Mode,
    dl-TPC-PowerOffsetPerRL-List DL-TPC-PowerOffsetPerRL-List  OPTIONAL
}

-- *****
-- 
-- ACTIVE SET UPDATE COMPLETE (FDD only)
-- 
-- *****

ActiveSetUpdateComplete ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier    RRC-TransactionIdentifier,
    -- dummy is not used in this version of the specification, it should
    -- not be sent and if received it should be ignored.
    dummy                         IntegrityProtActivationInfo   OPTIONAL,
    -- Radio bearer IEs
    -- dummy2 and dummy3 are not used in this version of the specification, they should
    -- not be sent and if received they should be ignored.
    dummy2                        RB-ActivationTimeInfoList  OPTIONAL,
    dummy3                        UL-CounterSynchronisationInfo OPTIONAL,
    laterNonCriticalExtensions   SEQUENCE {
        -- Container for additional R99 extensions
        activeSetUpdateComplete-r3-add-ext BIT STRING        OPTIONAL,
        nonCriticalExtensions          SEQUENCE {} OPTIONAL
    } OPTIONAL
}

-- *****
-- 
-- ACTIVE SET UPDATE FAILURE (FDD only)
-- 
-- *****

ActiveSetUpdateFailure ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier    RRC-TransactionIdentifier,
    failureCause                 FailureCauseWithProtErr,
    laterNonCriticalExtensions   SEQUENCE {
        -- Container for additional R99 extensions
        activeSetUpdateFailure-r3-add-ext BIT STRING        OPTIONAL,
        nonCriticalExtensions          SEQUENCE {} OPTIONAL
    } OPTIONAL
}

-- *****
-- 
-- Assistance Data Delivery
-- 
-- *****

AssistanceDataDelivery ::= CHOICE {
    r3                          SEQUENCE {
        assistanceDataDelivery-r3      AssistanceDataDelivery-r3-IEs,
}

```

```

v3a0NonCriticalExtensions      SEQUENCE {
    assistanceDataDelivery-v3a0ext  AssistanceDataDelivery-v3a0ext,
    laterNonCriticalExtensions   SEQUENCE {
        -- Container for additional R99 extensions
        assistanceDataDelivery-r3-add-ext  BIT STRING      OPTIONAL,
        v4b0NonCriticalExtensions   SEQUENCE {
            assistanceDataDelivery-v4b0ext
                AssistanceDataDelivery-v4b0ext-IEs,
                nonCriticalExtensions  SEQUENCE {}          OPTIONAL
            } OPTIONAL
        } OPTIONAL
    } OPTIONAL
},
later-than-r3                  SEQUENCE {
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    criticalExtensions         SEQUENCE {}
}
}

AssistanceDataDelivery-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    -- Measurement Information Elements
    ue-positioning-GPS-AssistanceData      UE-Positioning-GPS-AssistanceData
    OPTIONAL,
    ue-positioning-OTDOA-AssistanceData-UEB  UE-Positioning-OTDOA-AssistanceData-UEB
    OPTIONAL
}

AssistanceDataDelivery-v3a0ext ::= SEQUENCE {
    sfn-Offset-Validity           SFN-Offset-Validity      OPTIONAL
}

AssistanceDataDelivery-v4b0ext-IEs ::= SEQUENCE {
    ue-Positioning-OTDOA-AssistanceData-r4ext  UE-Positioning-OTDOA-AssistanceData-r4ext  OPTIONAL
}

-- ****
-- CELL CHANGE ORDER FROM UTRAN
--
-- ****

CellChangeOrderFromUTRAN ::= CHOICE {
    r3           SEQUENCE {
        cellChangeOrderFromUTRAN-IEs      CellChangeOrderFromUTRAN-r3-IEs,
        laterNonCriticalExtensions   SEQUENCE {
            -- Container for additional R99 extensions
            cellChangeOrderFromUTRAN-r3-add-ext  BIT STRING      OPTIONAL,
            v590NonCriticalExtensions   SEQUENCE {
                cellChangeOrderFromUTRAN-v590ext  CellChangeOrderFromUTRAN-v590ext-IEs,
                nonCriticalExtensions  SEQUENCE {} OPTIONAL
            } OPTIONAL
        } OPTIONAL
    } OPTIONAL
},
later-than-r3                  SEQUENCE {
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    criticalExtensions         SEQUENCE {}
}
}

CellChangeOrderFromUTRAN-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    -- dummy is not used in this version of the specification, it should
    -- not be sent and if received it should be ignored.
    dummy                      IntegrityProtectionModeInfo      OPTIONAL,
    activationTime              ActivationTime                 OPTIONAL,
    -- the IE rab-InformationList is not used in this version of the specification, it should
    -- not be sent and if received it should be ignored. The IE may be used in a later
    -- version of the protocol and hence it is not changed into a dummy
    rab-InformationList        RAB-InformationList       OPTIONAL,
    interRAT-TargetCellDescription  InterRAT-TargetCellDescription
}

CellChangeOrderFromUTRAN-v590ext-IEs ::= SEQUENCE {
    geran-SystemInfoType        CHOICE {
        sI                         GERAN-SystemInformation,

```

```

    pSI                               GERAN-SystemInformation
}     OPTIONAL

}

-- ****
-- CELL CHANGE ORDER FROM UTRAN FAILURE
--
-- ****

CellChangeOrderFromUTRANFailure ::= CHOICE {
  r3      SEQUENCE {
    cellChangeOrderFromUTRANFailure-r3
          CellChangeOrderFromUTRANFailure-r3-IEs,
    laterNonCriticalExtensions   SEQUENCE {
      -- Container for additional R99 extensions
      cellChangeOrderFromUTRANFailure-r3-add-ext   BIT STRING OPTIONAL,
      nonCriticalExtensions        SEQUENCE {} OPTIONAL
    } OPTIONAL
  },
  -- dummy is not used in this version of the specification and it
  -- should be ignored.
  dummy      SEQUENCE {
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    criticalExtensions         SEQUENCE {}
  }
}

CellChangeOrderFromUTRANFailure-r3-IEs ::= SEQUENCE {
  -- User equipment IEs
  rrc-TransactionIdentifier   RRC-TransactionIdentifier,
  -- dummy is not used in this version of the specification, it should
  -- not be sent and if received it should be ignored.
  dummy      IntegrityProtectionModeInfo      OPTIONAL,
  interRAT-ChangeFailureCause InterRAT-ChangeFailureCause
}

-- ****
-- CELL UPDATE
--
-- ****

CellUpdate ::= SEQUENCE {
  -- User equipment IEs
  u-RNTI                  U-RNTI,
  startList     STARTList,
  am-RLC-ErrorIndicationRb2-3or4   BOOLEAN,
  am-RLC-ErrorIndicationRb5orAbove  BOOLEAN,
  cellUpdateCause           CellUpdateCause,
  -- TABULAR: RRC transaction identifier is nested in FailureCauseWithProtErrTrId
  failureCause              FailureCauseWithProtErrTrId      OPTIONAL,
  rb-timer-indicator        Rb-timer-indicator,
  -- Measurement IEs
  measuredResultsOnRACH     MeasuredResultsOnRACH      OPTIONAL,
  laterNonCriticalExtensions SEQUENCE {
    -- Container for additional R99 extensions
    cellUpdate-r3-add-ext    BIT STRING OPTIONAL,
    v590NonCriticalExtensions SEQUENCE {
      cellUpdate-v590ext     CellUpdate-v590ext,
      v6xyNonCriticalExtensions SEQUENCE {
        cellUpdate-v6xyext   CellUpdate-v6xyext-IEs,
        nonCriticalExtensions SEQUENCE {} OPTIONAL
      } OPTIONAL
    } OPTIONAL
  } OPTIONAL
}

CellUpdate-v590ext ::= SEQUENCE {
  establishmentCause       EstablishmentCause OPTIONAL
}

CellUpdate-v6xyext-IEs ::= SEQUENCE {
  -- User equipment IEs
  cellUpdateCause-ext     CellUpdateCause-ext      OPTIONAL
}

-- ****

```

```

-- CELL UPDATE CONFIRM
--
-- ****
CellUpdateConfirm ::= CHOICE {
    r3           SEQUENCE {
        cellUpdateConfirm-r3          CellUpdateConfirm-r3-IEs,
        v3a0NonCriticalExtensions     SEQUENCE {
            cellUpdateConfirm-v3a0ext   CellUpdateConfirm-v3a0ext,
            laterNonCriticalExtensions SEQUENCE {
                -- Container for additional R99 extensions
                cellUpdateConfirm-r3-add-ext BIT STRING OPTIONAL,
                v4b0NonCriticalExtensions   SEQUENCE {
                    cellUpdateConfirm-v4b0ext   CellUpdateConfirm-v4b0ext-IEs,
                    v590NonCriticalExtensions SEQUENCE {
                        cellUpdateConfirm-v590ext   CellUpdateConfirm-v590ext-IEs,
                        v6xyNonCriticalExtensions SEQUENCE {
                            cellUpdateConfirm-v6xyext   CellUpdateConfirm-v6xyext-IEs,
                            nonCriticalExtensions    SEQUENCE {} OPTIONAL
                        }
                    } OPTIONAL
                }
            } OPTIONAL
        }
    } OPTIONAL
},
later-than-r3           SEQUENCE {
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    criticalExtensions         CHOICE {
        r4           SEQUENCE {
            cellUpdateConfirm-r4          CellUpdateConfirm-r4-IEs,
            v4d0NonCriticalExtensions     SEQUENCE {
                -- Container for adding non critical extensions after freezing REL-5
                cellUpdateConfirm-r4-add-ext BIT STRING OPTIONAL,
                v590NonCriticalExtensions   SEQUENCE {
                    cellUpdateConfirm-v590ext   CellUpdateConfirm-v590ext-IEs,
                    v6xyNonCriticalExtensions SEQUENCE {
                        cellUpdateConfirm-v6xyext   CellUpdateConfirm-v6xyext-IEs,
                        nonCriticalExtensions    SEQUENCE {} OPTIONAL
                    }
                }
            } OPTIONAL
        }
    } OPTIONAL
},
criticalExtensions      CHOICE {
    r5           SEQUENCE {
        cellUpdateConfirm-r5          CellUpdateConfirm-r5-IEs,
        -- Container for adding non critical extensions after freezing REL-6
        cellUpdateConfirm-r5-add-ext BIT STRING OPTIONAL,
        v6xyNonCriticalExtensions   SEQUENCE {
            cellUpdateConfirm-v6xyext   CellUpdateConfirm-v6xyext-IEs,
            nonCriticalExtensions    SEQUENCE {} OPTIONAL
        }
    } OPTIONAL
},
criticalExtensions      CHOICE {
    r6           SEQUENCE {
        cellUpdateConfirm-r6          CellUpdateConfirm-r6-IEs,
        -- Container for adding non critical extensions after freezing REL-7
        cellUpdateConfirm-r6-add-ext BIT STRING OPTIONAL,
        nonCriticalExtensions       SEQUENCE {} OPTIONAL
    }
},
criticalExtensions      SEQUENCE {}
}
}

CellUpdateConfirm-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    integrityProtectionModeInfo IntegrityProtectionModeInfo OPTIONAL,
    cipheringModeInfo           CipheringModeInfo OPTIONAL,
    activationTime               ActivationTime OPTIONAL,
    new-U-RNTI                  U-RNTI OPTIONAL,
    new-C-RNTI                  C-RNTI OPTIONAL,
    rrc-StateIndicator           RRC-StateIndicator,
    utran-DRX-CycleLengthCoeff  UTRAN-DRX-CycleLengthCoefficient OPTIONAL,
    rlc-Re-establishIndicatorRb2-3or4 BOOLEAN,
}

```

```

    rlc-Re-establishIndicatorRb5orAbove      BOOLEAN,
-- CN information elements
    cn-InformationInfo          CN-InformationInfo      OPTIONAL,
-- UTRAN mobility IEs
    ura-Identity                URA-Identity          OPTIONAL,
-- Radio bearer IEs
    rb-InformationReleaseList   RB-InformationReleaseList OPTIONAL,
    rb-InformationReconfigList  RB-InformationReconfigList OPTIONAL,
    rb-InformationAffectedList RB-InformationAffectedList OPTIONAL,
    dl-CounterSynchronisationInfo DL-CounterSynchronisationInfo OPTIONAL,
-- Transport channel IEs
    ul-CommonTransChInfo        UL-CommonTransChInfo    OPTIONAL,
    ul-deletedTransChInfoList  UL-DeletedTransChInfoList OPTIONAL,
    ul-AddReconfTransChInfoList UL-AddReconfTransChInfoList OPTIONAL,
    modeSpecificTransChInfo     CHOICE {
        fdd                      SEQUENCE {
            cpch-SetID           CPCH-SetID          OPTIONAL,
            addReconfTransChDRAC-Info DRAC-StaticInformationList OPTIONAL
        },
        tdd                      NULL
    },
    dl-CommonTransChInfo        DL-CommonTransChInfo    OPTIONAL,
    dl-DeletedTransChInfoList  DL-DeletedTransChInfoList OPTIONAL,
    dl-AddReconfTransChInfoList DL-AddReconfTransChInfoList OPTIONAL,
-- Physical channel IEs
    frequencyInfo               FrequencyInfo          OPTIONAL,
    maxAllowedUL-TX-Power      MaxAllowedUL-TX-Power    OPTIONAL,
    ul-ChannelRequirement      UL-ChannelRequirement    OPTIONAL,
    modeSpecificPhysChInfo     CHOICE {
        fdd                      SEQUENCE {
            dl-PDSCH-Information DL-PDSCH-Information    OPTIONAL
        },
        tdd                      NULL
    },
    dl-CommonInformation        DL-CommonInformation    OPTIONAL,
    dl-InformationPerRL-List   DL-InformationPerRL-List  OPTIONAL
}

CellUpdateConfirm-v3a0ext ::= SEQUENCE {
    new-DSCH-RNTI             DSCH-RNTI           OPTIONAL
}

CellUpdateConfirm-v4b0ext-IEs ::= SEQUENCE {
-- Physical channel IEs
-- ssdt-UL extends SSDT-Information, which is included in
-- DL-CommonInformation. FDD only.
    ssdt-UL-r4                SSDT-UL             OPTIONAL,
-- The order of the RLs in IE cell-id-PerRL-List is the same as
-- in IE DL-InformationPerRL-List included in this message
    cell-id-PerRL-List         CellIdentity-PerRL-List    OPTIONAL
}

CellUpdateConfirm-v590ext-IEs ::= SEQUENCE {
-- Physical channel IEs
    dl-TPC-PowerOffsetPerRL-List DL-TPC-PowerOffsetPerRL-List    OPTIONAL
}

CellUpdateConfirm-r4-IEs ::= SEQUENCE {
-- User equipment IEs
    integrityProtectionModeInfo IntegrityProtectionModeInfo    OPTIONAL,
    cipheringModeInfo           CipheringModeInfo        OPTIONAL,
    activationTime              ActivationTime          OPTIONAL,
    new-U-RNTI                 U-RNTI                OPTIONAL,
    new-C-RNTI                 C-RNTI                OPTIONAL,
    new-DSCH-RNTI              DSCH-RNTI             OPTIONAL,
    rrc-StateIndicator          RRC-StateIndicator      OPTIONAL,
    utran-DRX-CycleLengthCoeff UTRAN-DRX-CycleLengthCoefficient    OPTIONAL,
    rlc-Re-establishIndicatorRb2-3or4  BOOLEAN,
    rlc-Re-establishIndicatorRb5orAbove  BOOLEAN,
-- CN information elements
    cn-InformationInfo          CN-InformationInfo      OPTIONAL,
-- UTRAN mobility IEs
    ura-Identity                URA-Identity          OPTIONAL,
-- Radio bearer IEs
    rb-InformationReleaseList   RB-InformationReleaseList OPTIONAL,
    rb-InformationReconfigList  RB-InformationReconfigList-r4    OPTIONAL,
    rb-InformationAffectedList RB-InformationAffectedList    OPTIONAL,
    dl-CounterSynchronisationInfo DL-CounterSynchronisationInfo    OPTIONAL
}

```

```

-- Transport channel IEs
    ul-CommonTransChInfo          UL-CommonTransChInfo-r4           OPTIONAL,
    ul-deletedTransChInfoList     UL-DeletedTransChInfoList        OPTIONAL,
    ul-AddReconfTransChInfoList   UL-AddReconfTransChInfoList      OPTIONAL,
    modeSpecificTransChInfo      CHOICE {
        fdd                         SEQUENCE {
            cpch-SetID                CPCH-SetID                  OPTIONAL,
            addReconfTransChDRAC-Info DRAC-StaticInformationList   OPTIONAL
        },
        tdd                         NULL
    },
    dl-CommonTransChInfo          DL-CommonTransChInfo-r4           OPTIONAL,
    dl-DeletedTransChInfoList     DL-DeletedTransChInfoList        OPTIONAL,
    dl-AddReconfTransChInfoList   DL-AddReconfTransChInfoList-r4  OPTIONAL,
-- Physical channel IEs
    frequencyInfo                FrequencyInfo               OPTIONAL,
    maxAllowedUL-TX-Power        MaxAllowedUL-TX-Power        OPTIONAL,
    ul-ChannelRequirement        UL-ChannelRequirement-r4       OPTIONAL,
    modeSpecificPhysChInfo      CHOICE {
        fdd                         SEQUENCE {
            dl-PDSCH-Information    DL-PDSCH-Information        OPTIONAL
        },
        tdd                         NULL
    },
    dl-CommonInformation         DL-CommonInformation-r4        OPTIONAL,
    dl-InformationPerRL-List     DL-InformationPerRL-List-r4   OPTIONAL
}

CellUpdateConfirm-r5-IEs ::= SEQUENCE {
    -- User equipment IEs
    integrityProtectionModeInfo IntegrityProtectionModeInfo OPTIONAL,
    cipheringModeInfo             CipheringModeInfo          OPTIONAL,
    activationTime                ActivationTime             OPTIONAL,
    new-U-RNTI                   U-RNTI                     OPTIONAL,
    new-C-RNTI                   C-RNTI                     OPTIONAL,
    new-DSCH-RNTI                DSCH-RNTI                 OPTIONAL,
    new-H-RNTI                   H-RNTI                     OPTIONAL,
    rrc-StateIndicator            RRC-StateIndicator         OPTIONAL,
    utran-DRX-CycleLengthCoeff   UTRAN-DRX-CycleLengthCoefficient OPTIONAL,
    rlc-Re-establishIndicatorRb2-3or4 BOOLEAN,
    rlc-Re-establishIndicatorRb5orAbove BOOLEAN,
    -- CN information elements
    cn-InformationInfo           CN-InformationInfo        OPTIONAL,
    -- UTRAN mobility IEs
    ura-Identity                 URA-Identity              OPTIONAL,
    -- Radio bearer IEs
    rb-InformationReleaseList    RB-InformationReleaseList  OPTIONAL,
    rb-InformationReconfigList    RB-InformationReconfigList-r5  OPTIONAL,
    rb-InformationAffectedList   RB-InformationAffectedList-r5  OPTIONAL,
    dl-CounterSynchronisationInfo DL-CounterSynchronisationInfo-r5 OPTIONAL,
    -- Transport channel IEs
    ul-CommonTransChInfo          UL-CommonTransChInfo-r4           OPTIONAL,
    ul-deletedTransChInfoList     UL-DeletedTransChInfoList        OPTIONAL,
    ul-AddReconfTransChInfoList   UL-AddReconfTransChInfoList      OPTIONAL,
    modeSpecificTransChInfo      CHOICE {
        fdd                         SEQUENCE {
            cpch-SetID                CPCH-SetID                  OPTIONAL,
            addReconfTransChDRAC-Info DRAC-StaticInformationList   OPTIONAL
        },
        tdd                         NULL
    },
    dl-CommonTransChInfo          DL-CommonTransChInfo-r4           OPTIONAL,
    dl-DeletedTransChInfoList     DL-DeletedTransChInfoList-r5      OPTIONAL,
    dl-AddReconfTransChInfoList   DL-AddReconfTransChInfoList-r5  OPTIONAL,
-- Physical channel IEs
    frequencyInfo                FrequencyInfo               OPTIONAL,
    maxAllowedUL-TX-Power        MaxAllowedUL-TX-Power        OPTIONAL,
    ul-ChannelRequirement        UL-ChannelRequirement-r5       OPTIONAL,
    modeSpecificPhysChInfo      CHOICE {
        fdd                         SEQUENCE {
            dl-PDSCH-Information    DL-PDSCH-Information        OPTIONAL
        },
        tdd                         NULL
    },
    dl-HSPDSCH-Information       DL-HSPDSCH-Information        OPTIONAL,
    dl-CommonInformation         DL-CommonInformation-r5        OPTIONAL,
    dl-InformationPerRL-List     DL-InformationPerRL-List-r5   OPTIONAL
}

```

```

CellUpdateConfirm-v6xyext-IEs ::= SEQUENCE {
    -- Physical channel IEs
        harq-Preamble-Mode          HARQ-Preamble-Mode           OPTIONAL,
    -- MBMS IEs
        mbms-FLCAplicabilityInfo   MBMS-FLCAplicabilityInfo-r6
}

CellUpdateConfirm-r6-IEs ::= SEQUENCE {
    -- User equipment IEs
        integrityProtectionModeInfo IntegrityProtectionModeInfo OPTIONAL,
        cipheringModeInfo            CipheringModeInfo           OPTIONAL,
        activationTime               ActivationTime             OPTIONAL,
        new-U-RNTI                  U-RNTI                     OPTIONAL,
        new-C-RNTI                  C-RNTI                     OPTIONAL,
        new-DSCH-RNTI               DSCH-RNTI                 OPTIONAL,
        new-H-RNTI                  H-RNTI                     OPTIONAL,
        new-E-RNTI                  E-RNTI                     OPTIONAL,
        rrc-StateIndicator          RRC-StateIndicator         OPTIONAL,
        utran-DRX-CycleLengthCoeff UTRAN-DRX-CycleLengthCoefficient OPTIONAL,
        rlc-Re-establishIndicatorRb2-3or4 BOOLEAN,
        rlc-Re-establishIndicatorRb5orAbove BOOLEAN,
    -- CN information elements
        cn-InformationInfo          CN-InformationInfo        OPTIONAL,
    -- UTRAN mobility IEs
        ura-Identity                URA-Identity              OPTIONAL,
    -- Radio bearer IEs
        rb-InformationReleaseList   RB-InformationReleaseList OPTIONAL,
        rb-InformationReconfigList  RB-InformationReconfigList-r6 OPTIONAL,
        rb-InformationAffectedList RB-InformationAffectedList-r6 OPTIONAL,
        dl-CounterSynchronisationInfo DL-CounterSynchronisationInfo-r5 OPTIONAL,
    -- Transport channel IEs
        ul-CommonTransChInfo        UL-CommonTransChInfo-r4   OPTIONAL,
        ul-deletedTransChInfoList   UL-DeletedTransChInfoList-r6 OPTIONAL,
        ul-AddReconfTransChInfoList UL-AddReconfTransChInfoList-r6 OPTIONAL,
        modeSpecificTransChInfo     CHOICE {
            fdd                      SEQUENCE {
                cpch-SetID            CPCH-SetID              OPTIONAL,
                addReconfTransChDRAC-Info DRAC-StaticInformationList OPTIONAL
            },
            tdd                      NULL
        },
        dl-CommonTransChInfo        DL-CommonTransChInfo-r4   OPTIONAL,
        dl-DeletedTransChInfoList  DL-DeletedTransChInfoList-r5 OPTIONAL,
        dl-AddReconfTransChInfoList DL-AddReconfTransChInfoList-r5 OPTIONAL,
    -- Physical channel IEs
        frequencyInfo               FrequencyInfo             OPTIONAL,
        maxAllowedUL-TX-Power      MaxAllowedUL-TX-Power       OPTIONAL,
        ul-ChannelRequirement      UL-ChannelRequirement-r6   OPTIONAL,
        ul-EDCH-Information        UL-EDCH-Information-r6   OPTIONAL,
        modeSpecificPhysChInfo     CHOICE {
            fdd                      SEQUENCE {
                dl-PDSCH-Information DL-PDSCH-Information        OPTIONAL
            },
            tdd                      NULL
        },
        dl-HSPDSCH-Information     DL-HSPDSCH-Information        OPTIONAL,
        dl-CommonInformation       DL-CommonInformation-r5   OPTIONAL,
        dl-InformationPerRL-List  DL-InformationPerRL-List-r6 OPTIONAL,
    -- MBMS IEs
        mbms-FLCAplicabilityInfo   MBMS-FLCAplicabilityInfo-r6
}

-- ****
-- CELL UPDATE CONFIRM for CCCH
-- ****

CellUpdateConfirm-CCCH ::= CHOICE {
    r3           SEQUENCE {
        -- User equipment IEs
            u-RNTI                  U-RNTI,
        -- The rest of the message is identical to the one sent on DCCH.
            cellUpdateConfirm-r3      CellUpdateConfirm-r3-IEs,
            laterNonCriticalExtensions SEQUENCE {
                -- Container for additional R99 extensions
                cellUpdateConfirm-CCCH-r3-add-ext BIT STRING OPTIONAL,
}

```

```

v4b0NonCriticalExtensions      SEQUENCE {
    cellUpdateConfirm-v4b0ext   CellUpdateConfirm-v4b0ext-IEs,
    v590NonCriticalExtensions  SEQUENCE {
        cellUpdateConfirm-v590ext   CellUpdateConfirm-v590ext-IEs,
        v6xyNonCriticalExtensions SEQUENCE {
            cellUpdateConfirm-v6xyext   CellUpdateConfirm-v6xyext-IEs,
            nonCriticalExtensions     SEQUENCE {} OPTIONAL
        } OPTIONAL
    } OPTIONAL
} OPTIONAL
},
later-than-r3                  SEQUENCE {
    u-RNTI                      U-RNTI,
    rrc-TransactionIdentifier    RRC-TransactionIdentifier,
    criticalExtensions           CHOICE {
        r4                         SEQUENCE {
            -- The rest of the message is identical to the one sent on DCCH.
            cellUpdateConfirm-r4       CellUpdateConfirm-r4-IEs,
            v4d0NonCriticalExtensions SEQUENCE {
                -- Container for adding non critical extensions after freezing REL-5
                cellUpdateConfirm-CCCH-r4-add-ext BIT STRING OPTIONAL,
                v590NonCriticalExtensions SEQUENCE {
                    cellUpdateConfirm-v590ext   CellUpdateConfirm-v590ext-IEs,
                    v6xyNonCriticalExtensions SEQUENCE {
                        cellUpdateConfirm-v6xyext   CellUpdateConfirm-v6xyext-IEs,
                        nonCriticalExtensions     SEQUENCE {} OPTIONAL
                    } OPTIONAL
                } OPTIONAL
            } OPTIONAL
        } OPTIONAL
    },
    criticalExtensions            CHOICE {
        r5                         SEQUENCE {
            cellUpdateConfirm-r5       CellUpdateConfirm-r5-IEs,
            cellUpdateConfirm-CCCH-r5-add-ext BIT STRING OPTIONAL,
            v6xyNonCriticalExtensions SEQUENCE {
                cellUpdateConfirm-v6xyext   CellUpdateConfirm-v6xyext-IEs,
                nonCriticalExtensions     SEQUENCE {} OPTIONAL
            } OPTIONAL
        } OPTIONAL
    },
    criticalExtensions            CHOICE {
        r6                         SEQUENCE {
            cellUpdateConfirm-r6       CellUpdateConfirm-r6-IEs,
            cellUpdateConfirm-r6-add-ext BIT STRING OPTIONAL,
            nonCriticalExtensions     SEQUENCE {} OPTIONAL
        },
        criticalExtensions          SEQUENCE {}
    }
}
},
criticalExtensions               SEQUENCE {
    r3                         CHOICE {
        r3                         SEQUENCE {
            counterCheck-r3         CounterCheck-r3-IEs,
            laterNonCriticalExtensions SEQUENCE {
                -- Container for additional R99 extensions
                counterCheck-r3-add-ext BIT STRING OPTIONAL,
                nonCriticalExtensions   SEQUENCE {} OPTIONAL
            } OPTIONAL
        },
        later-than-r3              SEQUENCE {
            rrc-TransactionIdentifier RRC-TransactionIdentifier,
            criticalExtensions       SEQUENCE {}
        }
    }
}
},
CounterCheck ::= CHOICE {
    r3                         SEQUENCE {
        counterCheck-r3         CounterCheck-r3-IEs,
        laterNonCriticalExtensions SEQUENCE {
            -- Container for additional R99 extensions
            counterCheck-r3-add-ext BIT STRING OPTIONAL,
            nonCriticalExtensions   SEQUENCE {} OPTIONAL
        } OPTIONAL
    },
    later-than-r3              SEQUENCE {
        rrc-TransactionIdentifier RRC-TransactionIdentifier,
        criticalExtensions       SEQUENCE {}
    }
}
},
CounterCheck-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier    RRC-TransactionIdentifier,
    -- Radio bearer IEs
}

```

```

rb-COUNT-C-MSB-InformationList RB-COUNT-C-MSB-InformationList
}

-- ****
-- COUNTER CHECK RESPONSE
--
-- ****

CounterCheckResponse ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    -- Radio bearer IEs
    rb-COUNT-C-InformationList    RB-COUNT-C-InformationList OPTIONAL,
    laterNonCriticalExtensions    SEQUENCE {
        -- Container for additional R99 extensions
        counterCheckResponse-r3-add-ext   BIT STRING OPTIONAL,
        nonCriticalExtensions           SEQUENCE {} OPTIONAL
    } OPTIONAL
}

-- ****
-- DOWNLINK DIRECT TRANSFER
--
-- ****

DownlinkDirectTransfer ::= CHOICE {
    r3          SEQUENCE {
        downlinkDirectTransfer-r3       DownlinkDirectTransfer-r3-IEs,
        laterNonCriticalExtensions    SEQUENCE {
            -- Container for additional R99 extensions
            downlinkDirectTransfer-r3-add-ext   BIT STRING OPTIONAL,
            nonCriticalExtensions           SEQUENCE {} OPTIONAL
        } OPTIONAL
    },
    later-than-r3           SEQUENCE {
        rrc-TransactionIdentifier      RRC-TransactionIdentifier,
        criticalExtensions            SEQUENCE {}
    }
}

DownlinkDirectTransfer-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    -- Core network IEs
    cn-DomainIdentity              CN-DomainIdentity,
    nas-Message                     NAS-Message
}

-- ****
-- HANOVER TO UTRAN COMMAND
--
-- ****

HandoverToUTRANCommand ::= CHOICE {
    r3          SEQUENCE {
        handoverToUTRANCommand-r3     HandoverToUTRANCommand-r3-IEs,
        nonCriticalExtensions         SEQUENCE {} OPTIONAL
    },
    criticalExtensions           CHOICE {
        r4          SEQUENCE {
            handoverToUTRANCommand-r4   HandoverToUTRANCommand-r4-IEs,
            nonCriticalExtensions     SEQUENCE {} OPTIONAL
        },
        criticalExtensions           CHOICE {
            r5          SEQUENCE {
                handoverToUTRANCommand-r5   HandoverToUTRANCommand-r5-IEs,
                nonCriticalExtensions     SEQUENCE {} OPTIONAL
            },
            criticalExtensions         CHOICE {
                r6          SEQUENCE {
                    handoverToUTRANCommand-r6   HandoverToUTRANCommand-r6-IEs,
                    nonCriticalExtensions     SEQUENCE {} OPTIONAL
                },
                criticalExtensions       SEQUENCE {}
            }
        }
    }
}

```

```

| _____ }
|
}

HandoverToUTRANCommand-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    new-U-RNTI                      U-RNTI-Short,
    -- dummy is not used in this version of specification, it should
    -- not be sent and if received it should be ignored.
    dummy                            ActivationTime           OPTIONAL,
    cipheringAlgorithm               CipheringAlgorithm      OPTIONAL,
    -- Radio bearer IEs
    -- Specification mode information
    specificationMode                CHOICE {
        complete                     SEQUENCE {
            srb-InformationSetupList SRB-InformationSetupList,
            rab-InformationSetupList RAB-InformationSetupList      OPTIONAL,
            ul-CommonTransChInfo     UL-CommonTransChInfo,
            ul-AddReconfTransChInfoList UL-AddReconfTransChInfoList,
            dl-CommonTransChInfo     DL-CommonTransChInfo,
            dl-AddReconfTransChInfoList DL-AddReconfTransChInfoList,
            ul-DPCH-Info             UL-DPCH-Info,
            modeSpecificInfo         CHOICE {
                fdd                  SEQUENCE {
                    dl-PDSCH-Information DL-PDSCH-Information OPTIONAL,
                    cpch-SetInfo          CPCH-SetInfo       OPTIONAL
                },
                tdd                  NULL
            },
            dl-CommonInformation   DL-CommonInformation,
            dl-InformationPerRL-List DL-InformationPerRL-List,
            frequencyInfo           FrequencyInfo
        },
        preconfiguration          SEQUENCE {
            -- All IEs that include an FDD/TDD choice are split in two IEs for this message,
            -- one for the FDD only elements and one for the TDD only elements, so that one
            -- FDD/TDD choice in this level is sufficient.
            preConfigMode            CHOICE {
                predefinedConfigIdentity PredefinedConfigIdentity,
                defaultConfig           SEQUENCE {
                    defaultConfigMode DefaultConfigMode,
                    defaultConfigIdentity DefaultConfigIdentity
                }
            },
            rab-Info                 RAB-Info-Post      OPTIONAL,
            modeSpecificInfo         CHOICE {
                fdd                  SEQUENCE {
                    ul-DPCH-Info       UL-DPCH-InfoPostFDD,
                    dl-CommonInformationPost DL-CommonInformationPost,
                    dl-InformationPerRL-List DL-InformationPerRL-ListPostFDD,
                    frequencyInfo        FrequencyInfoFDD
                },
                tdd                  SEQUENCE {
                    ul-DPCH-Info       UL-DPCH-InfoPostTDD,
                    dl-CommonInformationPost DL-CommonInformationPost,
                    dl-InformationPerRL-List DL-InformationPerRL-PostTDD,
                    frequencyInfo        FrequencyInfoTDD,
                    primaryCCPCH-TX-Power PrimaryCCPCH-TX-Power
                }
            }
        },
        -- Physical channel IEs
        maxAllowedUL-TX-Power    MaxAllowedUL-TX-Power
    }
}

HandoverToUTRANCommand-r4-IEs ::= SEQUENCE {
    -- User equipment IEs
    new-U-RNTI                      U-RNTI-Short,
    cipheringAlgorithm               CipheringAlgorithm      OPTIONAL,
    -- Radio bearer IEs
    -- Specification mode information
    specificationMode                CHOICE {
        complete                     SEQUENCE {
            srb-InformationSetupList SRB-InformationSetupList,
            rab-InformationSetupList RAB-InformationSetupList-r4      OPTIONAL,

```

```

    ul-CommonTransChInfo
    ul-AddReconfTransChInfoList
    dl-CommonTransChInfo
    dl-AddReconfTransChInfoList
    ul-DPCH-Info
    modeSpecificInfo
      fdd
        dl-PDSCH-Information
        cpch-SetInfo
      },
      tdd
    },
    dl-CommonInformation
    dl-InformationPerRL-List
    frequencyInfo
  },
  preconfiguration
-- All IEs that include an FDD/TDD choice are split in two IEs for this message,
-- one for the FDD only elements and one for the TDD only elements, so that one
-- FDD/TDD choice in this level is sufficient.
  preConfigMode
    predefinedConfigIdentity
    defaultConfig
      defaultConfigMode
      defaultConfigIdentity
    },
    rab-Info
    modeSpecificInfo
      fdd
        ul-DPCH-Info
        dl-CommonInformationPost
        dl-InformationPerRL-List
        frequencyInfo
      },
      tdd
        tdd384
          ul-DPCH-Info
          dl-InformationPerRL
          frequencyInfo
          primaryCCPCH-TX-Power
        },
        tdd128
          ul-DPCH-Info
          dl-InformationPerRL
          frequencyInfo
          primaryCCPCH-TX-Power
        }
      }
    },
    -- Physical channel IEs
    maxAllowedUL-TX-Power
  }

HandoverToUTRANCommand-r5-IEs ::= SEQUENCE {
  -- User equipment IEs
  new-U-RNTI
  cipheringAlgorithm
  -- Radio bearer IEs
  -- Specification mode information
  specificationMode
    CHOICE {
      complete
        SEQUENCE {
          srb-InformationSetupList
          rab-InformationSetupList
          ul-CommonTransChInfo
          ul-AddReconfTransChInfoList
          dl-CommonTransChInfo
          dl-AddReconfTransChInfoList
          ul-DPCH-Info
          modeSpecificInfo
            fdd
              dl-PDSCH-Information
              cpch-SetInfo
            },
            tdd
          },
        CHOICE {
          SEQUENCE {
            DL-PDSCH-Information OPTIONAL,
            CPCH-SetInfo OPTIONAL
          }
        }
      }
    }
  }
}

```

```

dl-CommonInformation          DL-CommonInformation-r4,
dl-InformationPerRL-List     DL-InformationPerRL-List-r5,
frequencyInfo                 FrequencyInfo

},
preconfiguration               SEQUENCE {
-- All IEs that include an FDD/TDD choice are split in two IEs for this message,
-- one for the FDD only elements and one for the TDD only elements, so that one
-- FDD/TDD choice in this level is sufficient.
    preConfigMode             CHOICE {
        predefinedConfigIdentity PredefinedConfigIdentity,
        defaultConfig           SEQUENCE {
            defaultConfigMode   DefaultConfigMode,
            defaultConfigIdentity DefaultConfigIdentity-r5
        }
    },
    rab-Info                  RAB-Info-Post      OPTIONAL,
    modeSpecificInfo          CHOICE {
        fdd                   SEQUENCE {
            ul-DPCH-Info       UL-DPCH-InfoPostFDD,
            dl-CommonInformationPost DL-CommonInformationPost,
            dl-InformationPerRL-List DL-InformationPerRL-ListPostFDD,
            frequencyInfo        FrequencyInfoFDD
        },
        tdd                   CHOICE {
            tdd384              SEQUENCE {
                ul-DPCH-Info       UL-DPCH-InfoPostTDD,
                dl-InformationPerRL DL-InformationPerRL-PostTDD,
                frequencyInfo        FrequencyInfoTDD,
                primaryCCPCH-TX-Power PrimaryCCPCH-TX-Power
            },
            tdd128              SEQUENCE {
                ul-DPCH-Info       UL-DPCH-InfoPostTDD-LCR-r4,
                dl-InformationPerRL DL-InformationPerRL-PostTDD-LCR-r4,
                frequencyInfo        FrequencyInfoTDD,
                primaryCCPCH-TX-Power PrimaryCCPCH-TX-Power
            }
        }
    }
},
-- Physical channel IEs
    maxAllowedUL-TX-Power      MaxAllowedUL-TX-Power
}

HandoverToUTRANCommand-r6-IEs ::= SEQUENCE {
-- User equipment IEs
    new-U-RNTI                 U-RNTI-Short,
    cipheringAlgorithm          CipheringAlgorithm      OPTIONAL,
-- Radio bearer IEs
-- Specification mode information
    specificationMode           CHOICE {
        complete                SEQUENCE {
            srb-InformationSetupList SRB-InformationSetupList-r6,
            rab-InformationSetupList RAB-InformationSetupList-r6      OPTIONAL,
            ul-CommonTransChInfo    UL-CommonTransChInfo-r4,
            ul-AddReconfTransChInfoList UL-AddReconfTransChInfoList-r6,
            dl-CommonTransChInfo    DL-CommonTransChInfo-r4,
            dl-AddReconfTransChInfoList DL-AddReconfTransChInfoList-r5,
            ul-DPCH-Info            UL-DPCH-Info-r6,
            modeSpecificInfo        CHOICE {
                fdd                  SEQUENCE {
                    dl-PDSCH-Information DL-PDSCH-Information      OPTIONAL,
                    cpch-SetInfo          CPCH-SetInfo      OPTIONAL
                },
                tdd                  NULL
            },
            dl-CommonInformation     DL-CommonInformation-r4,
            dl-InformationPerRL-List DL-InformationPerRL-List-r6,
            frequencyInfo            FrequencyInfo
        }
-- For the 'preconfiguration' specificationMode the r5 message is used.
    },
-- Physical channel IEs
    maxAllowedUL-TX-Power      MaxAllowedUL-TX-Power
}

-- ****
--
```

```

-- HANOVER TO UTRAN COMPLETE
--
-- ****
HandoverToUTRANComplete ::= SEQUENCE {
    --TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    -- TABULAR: startList is conditional on history.
    startList                      STARTList                                OPTIONAL,
    -- Radio bearer IEs
    count-C-ActivationTime          ActivationTime
    laterNonCriticalExtensions     SEQUENCE {
        -- Container for additional R99 extensions
        handoverToUTRANComplete-r3-add-ext   BIT STRING  OPTIONAL,
        nonCriticalExtensions      SEQUENCE {}    OPTIONAL
    }    OPTIONAL
}
-- ****
-- INITIAL DIRECT TRANSFER
--
-- ****

InitialDirectTransfer ::= SEQUENCE {
    -- Core network IEs
    cn-DomainIdentity           CN-DomainIdentity,
    intraDomainNasNodeSelector  IntraDomainNasNodeSelector,
    nas-Message                  NAS-Message,
    -- Measurement IEs
    measuredResultsOnRACH       MeasuredResultsOnRACH      OPTIONAL,
    v3a0NonCriticalExtensions   SEQUENCE {
        initialDirectTransfer-v3a0ext  InitialDirectTransfer-v3a0ext,
        laterNonCriticalExtensions   SEQUENCE {
            -- Container for additional R99 extensions
            initialDirectTransfer-r3-add-ext   BIT STRING  OPTIONAL,
            v590NonCriticalExtensions     SEQUENCE {
                initialDirectTransfer-v590ext  InitialDirectTransfer-v590ext,
                v6xyNonCriticalExtensions   SEQUENCE {
                    initialDirectTransfer-v6xyext  InitialDirectTransfer-v6xyext-IEs,
                    nonCriticalExtensions      SEQUENCE {}    OPTIONAL
                }    OPTIONAL
            }    OPTIONAL
        }    OPTIONAL
    }    OPTIONAL
}
InitialDirectTransfer-v3a0ext ::= SEQUENCE {
    -- start-value shall always be included in this version of the protocol
    start-Value                   START-Value                 OPTIONAL
}
InitialDirectTransfer-v590ext ::= SEQUENCE {
    establishmentCause           EstablishmentCause  OPTIONAL
}

InitialDirectTransfer-v6xyext-IEs ::= SEQUENCE {
    -- Core network IEs
    plmn-Identity               PLMN-Identity      OPTIONAL,
    -- MBMS IEs
    mbms-JoinedInformation     MBMS-JoinedInformation-r6  OPTIONAL
}

-- ****
-- HANOVER FROM UTRAN COMMAND
--
-- ****

HandoverFromUTRANCommand-GSM ::= CHOICE {
    r3
    r3                               SEQUENCE {
        handoverFromUTRANCommand-GSM-r3
            HandoverFromUTRANCommand-GSM-r3-IEs,
        -- UTRAN should not include the IE laterNonCriticalExtensions when it sets the IE
        -- gsm-message included in handoverFromUTRANCommand-GSM-r3 to single-GSM-Message. The UE
        -- behaviour upon receiving a message with this combination of IE values is unspecified.
        laterNonCriticalExtensions     SEQUENCE {
            -- Container for additional R99 extensions
            handoverFromUTRANCommand-GSM-r3-add-ext   BIT STRING  OPTIONAL,

```

```

        nonCriticalExtensions           SEQUENCE {} OPTIONAL
    }   OPTIONAL
},
later-than-r3           SEQUENCE {
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    criticalExtensions            SEQUENCE {}
}
}

HandoverFromUTRANCommand-GSM-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    activationTime                 ActivationTime
                                OPTIONAL,
    -- Radio bearer IEs
    toHandoverRAB-Info            RAB-Info
                                OPTIONAL,
    -- Measurement IEs
    frequency-band                Frequency-Band,
    -- Other IEs
    gsm-message                   CHOICE {
        -- In the single-GSM-Message case the following rules apply:
        -- 1> the GSM message directly follows the basic production; the final padding that
        --     results when PER encoding the abstract syntax value is removed prior to appending
        --     the GSM message.
        -- 2> the RRC message excluding the GSM part, does not contain a length determinant;
        --     there is no explicit parameter indicating the size of the included GSM message.
        -- 3> depending on need, final padding (all "0"s) is added to ensure the final result
        --     comprises a full number of octets
        single-GSM-Message          SEQUENCE {},
        gsm-MessageList              SEQUENCE {
            gsm-Messages             GSM-MessageList
        }
    }
}

HandoverFromUTRANCommand-GERANIu ::= SEQUENCE {
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    handoverFromUTRANCommand-GERANIu CHOICE {
        r5                      SEQUENCE {
            handoverFromUTRANCommand-GERANIu-r5
                HandoverFromUTRANCommand-GERANIu-r5-IEs,
                -- UTRAN should not include the IE nonCriticalExtensions when it sets
                -- the IE geraniu-message included in handoverFromUTRANCommand-GERANIu-r5 to
                -- single-GERANIu-Message
                -- The UE behaviour upon receiving a message including this combination of IE values is
                -- not specified
                nonCriticalExtensions    SEQUENCE {} OPTIONAL
        },
        later-than-r5               SEQUENCE {
            criticalExtensions      SEQUENCE {}
        }
    }
}

HandoverFromUTRANCommand-GERANIu-r5-IEs ::= SEQUENCE {
    -- User equipment IEs
    activationTime                 ActivationTime
                                OPTIONAL,
    -- Measurement IEs
    frequency-Band                Frequency-Band,
    -- Other IEs
    geraniu-Message               CHOICE {
        -- In the single-GERANIu-Message case the following rules apply:
        -- 1> the GERAN Iu message directly follows the basic production; the final padding that
        --     results when PER encoding the abstract syntax value is removed prior to appending
        --     the GERAN Iu message.
        -- 2> the RRC message excluding the GERAN Iu part does not contain a length determinant;
        --     there is no explicit parameter indicating the size of the included GERAN Iu
        --     message.
        -- 3> depending on need, final padding (all "0"s) is added to ensure the final result
        --     comprises a full number of octets.
        single-GERANIu-Message      SEQUENCE {},
        geraniu-MessageList          SEQUENCE {
            geraniu-Messages         GERANIu-MessageList
        }
    }
}

HandoverFromUTRANCommand-CDMA2000 ::= CHOICE {
    r3                      SEQUENCE {

```

```

handoverFromUTRANCommand-CDMA2000-r3
                                         HandoverFromUTRANCommand-CDMA2000-r3-IES,
laterNonCriticalExtensions      SEQUENCE {
    -- Container for additional R99 extensions
    handoverFromUTRANCommand-CDMA2000-r3-add-ext
                                         BIT STRING      OPTIONAL,
    nonCriticalExtensions          SEQUENCE {}      OPTIONAL
}
    OPTIONAL
},
later-than-r3           SEQUENCE {
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    criticalExtensions          SEQUENCE {}
}
}

HandoverFromUTRANCommand-CDMA2000-r3-IES ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    activationTime               ActivationTime
                                         OPTIONAL,
    -- Radio bearer IEs
    toHandoverRAB-Info          RAB-Info
                                         OPTIONAL,
    -- Other IEs
    cdma2000-MessageList        CDMA2000-MessageList
}

-- ****
-- 
-- HANOVER FROM UTRAN FAILURE
-- 
-- ****

HandoverFromUTRANFailure ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    -- Other IEs
    interRAT-HO-FailureCause    InterRAT-HO-FailureCause
                                         OPTIONAL,
    -- In case the interRATMessage to be transferred is for GERAN Iu mode, the
    -- message should be placed in the HandoverFromUtranFailure-v590ext-IES
    -- non-critical extension container.
    interRATMessage             CHOICE {
        gsm                   SEQUENCE {
            gsm-MessageList     GSM-MessageList
        },
        cdma2000              SEQUENCE {
            cdma2000-MessageList CDMA2000-MessageList
        }
    }
                                         OPTIONAL,
    laterNonCriticalExtensions   SEQUENCE {
        -- Container for additional R99 extensions
        handoverFromUTRANFailure-r3-add-ext   BIT STRING  OPTIONAL,
        v590NonCriticalExtensions          SEQUENCE {
            handoverFromUTRANFailure-v590ext   HandoverFromUtranFailure-v590ext-IES,
            nonCriticalExtensions            SEQUENCE {}      OPTIONAL
        }
    }
                                         OPTIONAL
}
                                         OPTIONAL
}

HandoverFromUtranFailure-v590ext-IES ::= SEQUENCE {
    geranIu-MessageList          GERANIu-MessageList
                                         OPTIONAL
}

-- ****
-- 
-- INTER RAT HANDOVER INFO
-- 
-- ****

InterRATHandoverInfo ::= SEQUENCE {
    -- This structure is defined for historical reasons, backward compatibility with 04.18
    predefinedConfigStatusList    CHOICE {
        absent                 NULL,
        present                PredefinedConfigStatusList
    },
    uE-SecurityInformation       CHOICE {
        absent                 NULL,
        present                UE-SecurityInformation
    },
    ue-CapabilityContainer       CHOICE {

```

```

absent NULL,
-- present is an octet aligned string containing IE UE-RadioAccessCapabilityInfo
present OCTET STRING (SIZE (0..63))
},
-- Non critical extensions
v390NonCriticalExtensions CHOICE {
absent NULL,
present SEQUENCE {
    interRATHandoverInfo-v390ext InterRATHandoverInfo-v390ext-IEs,
    v3a0NonCriticalExtensions SEQUENCE {
        interRATHandoverInfo-v3a0ext InterRATHandoverInfo-v3a0ext-IEs,
        laterNonCriticalExtensions SEQUENCE {
            interRATHandoverInfo-v3d0ext InterRATHandoverInfo-v3d0ext-IEs,
            -- Container for additional R99 extensions
            interRATHandoverInfo-r3-add-ext BIT STRING OPTIONAL,
            v3g0NonCriticalExtensions SEQUENCE {
                interRATHandoverInfo-v3g0ext InterRATHandoverInfo-v3g0ext-IEs,
                v4b0NonCriticalExtensions SEQUENCE {
                    interRATHandoverInfo-v4b0ext InterRATHandoverInfo-v4b0ext-IEs,
                    v4d0NonCriticalExtensions SEQUENCE {
                        interRATHandoverInfo-v4d0ext InterRATHandoverInfo-v4d0ext-IEs,
                        -- Reserved for future non critical extension
                        v590NonCriticalExtensions SEQUENCE {
                            interRATHandoverInfo-v590ext InterRATHandoverInfo-v590ext-IEs,
                            nonCriticalExtensions SEQUENCE {} OPTIONAL
                        }
                    }
                }
            }
        }
    }
}
InterRATHandoverInfo-v390ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v380ext     UE-RadioAccessCapability-v380ext     OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext      DL-PhysChCapabilityFDD-v380ext
}

InterRATHandoverInfo-v3a0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3a0ext     UE-RadioAccessCapability-v3a0ext     OPTIONAL
}

InterRATHandoverInfo-v3d0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    uESpecificBehaviourInformation1interRAT     UESpecificBehaviourInformation1interRAT
    OPTIONAL
}

InterRATHandoverInfo-v3g0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3g0ext     UE-RadioAccessCapability-v3g0ext     OPTIONAL
}

InterRATHandoverInfo-v4b0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    accessStratumReleaseIndicator     AccessStratumReleaseIndicator
}

InterRATHandoverInfo-v4d0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    tdd128-RF-Capability           RadioFrequencyBandTDDList     OPTIONAL
}

InterRATHandoverInfo-v590ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    predefinedConfigStatusListComp   PredefinedConfigStatusListComp   OPTIONAL,
    ue-RadioAccessCapabilityComp     UE-RadioAccessCapabilityComp   OPTIONAL
}

-- ****
-- 
-- MEASUREMENT CONTROL
-- 
```

```

-- ****
MeasurementControl ::= CHOICE {
    -- The Rel-4 functionality of UE Positioning OTDOA AssistanceData TDD is only available
    -- in the later-than-r3 branch of this message (i.e. through the use of the IE
    -- ue-Positioning-OTDOA-AssistanceData-r4)
    r3           SEQUENCE {
        measurementControl-r3          MeasurementControl-r3-IEs,
        v390nonCriticalExtensions     SEQUENCE {
            measurementControl-v390ext   MeasurementControl-v390ext,
            v3a0NonCriticalExtensions   SEQUENCE {
                measurementControl-v3a0ext   MeasurementControl-v3a0ext,
                laterNonCriticalExtensions SEQUENCE {
                    -- Container for additional R99 extensions
                    measurementControl-r3-add-ext BIT STRING OPTIONAL,
                    v4b0NonCriticalExtensions   SEQUENCE{
                        -- The content of the v4b0 non-critical extension has been removed. If sent
                        -- to a UE of AS release 4, the UE behaviour is unspecified. A UE of AS
                        -- release 5 onward shall comply with the v4b0 and later extensions in this
                        -- branch of the message.
                        v590NonCriticalExtensions   SEQUENCE {
                            measurementControl-v590ext   MeasurementControl-v590ext-IEs,
                            v5b0NonCriticalExtensions SEQUENCE {
                                measurementControl-v5b0ext   MeasurementControl-v5b0ext-IEs,
                                nonCriticalExtensions    SEQUENCE {} OPTIONAL
                            }
                        }
                    }
                }
            }
        }
    },
    later-than-r3      SEQUENCE {
        rrc-TransactionIdentifier   RRC-TransactionIdentifier,
        criticalExtensions         CHOICE {
            r4           SEQUENCE {
                measurementControl-r4          MeasurementControl-r4-IEs,
                v4d0NonCriticalExtensions     SEQUENCE {
                    -- Container for adding non critical extensions after freezing REL-5
                    measurementControl-r4-add-ext BIT STRING OPTIONAL,
                    v590NonCriticalExtensions   SEQUENCE{
                        measurementControl-v590ext   MeasurementControl-v590ext-IEs,
                        v5b0NonCriticalExtensions SEQUENCE {
                            measurementControl-v5b0ext   MeasurementControl-v5b0ext-IEs,
                            nonCriticalExtensions    SEQUENCE {} OPTIONAL
                        }
                    }
                }
            }
        }
    },
    criticalExtensions   SEQUENCE {}
}

MeasurementControl-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    -- Measurement IEs
    measurementIdentity       MeasurementIdentity,
    -- TABULAR: The measurement type is included in MeasurementCommand.
    measurementCommand        MeasurementCommand,
    measurementReportingMode  MeasurementReportingMode OPTIONAL,
    additionalMeasurementList  AdditionalMeasurementID-List OPTIONAL,
    -- Physical channel IEs
    dpch-CompressedModeStatusInfo DPCH-CompressedModeStatusInfo OPTIONAL
}

MeasurementControl-v390ext ::= SEQUENCE {
    ue-Positioning-Measurement-v390ext   UE-Positioning-Measurement-v390ext OPTIONAL
}

MeasurementControl-v3a0ext ::= SEQUENCE {
    sfn-Offset-Validity      SFN-Offset-Validity OPTIONAL
}

MeasurementControl-r4-IEs ::= SEQUENCE {
    -- Measurement IEs
    measurementIdentity       MeasurementIdentity,
}

```

```

-- TABULAR: The measurement type is included in measurementCommand.
measurementCommand          MeasurementCommand-r4,
measurementReportingMode    MeasurementReportingMode
additionalMeasurementList   AdditionalMeasurementID-List
                           OPTIONAL,
-- Physical channel IEs
dpch-CompressedModeStatusInfo DPCH-CompressedModeStatusInfo
                           OPTIONAL
}

MeasurementControl-v590ext-IEs ::= SEQUENCE {
  measurementCommand-v590ext      CHOICE {
    -- the choice "intra-frequency" shall be used for the case of intra-frequency measurement,
    -- as well as when intra-frequency events are configured for inter-frequency measurement
    intra-frequency                Intra-FreqEventCriteriaList-v590ext,
    inter-frequency                 Inter-FreqEventCriteriaList-v590ext
  }                                OPTIONAL,
  intraFreqReportingCriteria-1b-r5     IntraFreqReportingCriteria-1b-r5
  intraFreqEvent-1d-r5                  IntraFreqEvent-1d-r5
  -- most significant part of "RRC transaction identifier" (MSP),
  -- "RRC transaction identifier" = rrc-TransactionIdentifier-MSP-v590ext * 4 +
  -- rrc-TransactionIdentifier
  rrc-TransactionIdentifier-MSP-v590ext RRC-TransactionIdentifier
}
}

MeasurementControl-v5b0ext-IEs ::= SEQUENCE {
  interRATCellInfoIndicator        InterRATCellInfoIndicator
}                                OPTIONAL

-- ****
-- 
-- MEASUREMENT CONTROL FAILURE
-- 
-- ****

MeasurementControlFailure ::= SEQUENCE {
  -- User equipment IEs
  rrc-TransactionIdentifier      RRC-TransactionIdentifier,
  failureCause                   FailureCauseWithProtErr,
  laterNonCriticalExtensions    SEQUENCE {
    -- Container for additional R99 extensions
    measurementControlFailure-r3-add-ext BIT STRING
  }                                OPTIONAL,
  v590NonCriticalExtensions     SEQUENCE {
    measurementControlFailure-v590ext MeasurementControlFailure-v590ext-IEs,
    nonCriticalExtensions         SEQUENCE {}      OPTIONAL
  }                                OPTIONAL
}                                OPTIONAL
}

MeasurementControlFailure-v590ext-IEs ::= SEQUENCE {
  -- most significant part of "RRC transaction identifier" (MSP),
  -- "RRC transaction identifier" = rrc-TransactionIdentifier-MSP-v590ext * 4 +
  -- rrc-TransactionIdentifier
  -- If the rrc-TransactionIdentifier-MSP-v590ext was not received in the MEASUREMENT CONTROL
  -- message, then the rrc-TransactionIdentifier-MSP-v590ext shall be set to zero
  rrc-TransactionIdentifier-MSP-v590ext RRC-TransactionIdentifier
}
 

-- ****
-- 
-- MEASUREMENT REPORT
-- 
-- ****

MeasurementReport ::= SEQUENCE {
  -- Measurement IEs
  measurementIdentity            MeasurementIdentity,
  measuredResults                MeasuredResults
  measuredResultsOnRACH          MeasuredResultsOnRACH
  additionalMeasuredResults      MeasuredResultsList
  eventResults                   EventResults
  -- Non-critical extensions
  v390nonCriticalExtensions     SEQUENCE {
    measurementReport-v390ext     MeasurementReport-v390ext,
    laterNonCriticalExtensions   SEQUENCE {
      -- Container for additional R99 extensions
      measurementReport-r3-add-ext BIT STRING
    }                                OPTIONAL,
    v4b0NonCriticalExtensions    SEQUENCE {
      measurementReport-v4b0ext     MeasurementReport-v4b0ext-IEs,
      -- Extension mechanism for non-Rel4 information
    }
  }
}
```

```

        v590NonCriticalExtensions   SEQUENCE {
            measurementReport-v590ext      MeasurementReport-v590ext-IES,
            v5b0NonCriticalExtensions     SEQUENCE {
                measurementReport-v5b0ext      MeasurementReport-v5b0ext-IES,
                nonCriticalExtensions       SEQUENCE {}      OPTIONAL
            }      OPTIONAL
        }      OPTIONAL
    }      OPTIONAL
}      OPTIONAL

MeasurementReport-v390ext ::= SEQUENCE {
    measuredResults-v390ext      MeasuredResults-v390ext
}      OPTIONAL

MeasurementReport-v4b0ext-IES ::= SEQUENCE {
    interFreqEventResults-LCR      InterFreqEventResults-LCR-r4-ext      OPTIONAL,
    -- additionalMeasuredResults-LCR shall contain measurement results and additional measurement
    -- results list.
    additionalMeasuredResults-LCR    MeasuredResultsList-LCR-r4-ext      OPTIONAL,
    gsmOTDreferenceCell           PrimaryCPICH-Info      OPTIONAL
}

MeasurementReport-v590ext-IES ::= SEQUENCE {
    measuredResults-v590ext      MeasuredResults-v590ext
}      OPTIONAL

MeasurementReport-v5b0ext-IES ::= SEQUENCE {
    interRATCellInfoIndicator      InterRATCellInfoIndicator
}      OPTIONAL

-- ****
-- 
-- PAGING TYPE 1
-- 
-- ****

PagingType1 ::= SEQUENCE {
    -- User equipment IEs
    pagingRecordList          PagingRecordList
}      OPTIONAL,
    -- Other IEs
    bcch-ModificationInfo      BCCH-ModificationInfo
    laterNonCriticalExtensions SEQUENCE {
        -- Container for additional R99 extensions
        pagingType1-r3-add-ext      BIT STRING      OPTIONAL,
        v590NonCriticalExtensions   SEQUENCE {
            pagingType1-v590ext      PagingType1-v590ext-IES,
            nonCriticalExtensions   SEQUENCE {}      OPTIONAL
        }      OPTIONAL
    }      OPTIONAL
}

PagingType1-v590ext-IES ::= SEQUENCE {
    -- User equipment IEs
    pagingRecord2List          PagingRecord2List-r5
}      OPTIONAL

-- ****
-- 
-- PAGING TYPE 2
-- 
-- ****

PagingType2 ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier    RRC-TransactionIdentifier,
    pagingCause                  PagingCause,
    -- Core network IEs
    cn-DomainIdentity           CN-DomainIdentity,
    pagingRecordTypeID          PagingRecordTypeID,
    laterNonCriticalExtensions   SEQUENCE {
        -- Container for additional R99 extensions
        pagingType2-r3-add-ext      BIT STRING      OPTIONAL,
        nonCriticalExtensions       SEQUENCE {}      OPTIONAL
    }      OPTIONAL
}

```

```

-- ****
-- PHYSICAL CHANNEL RECONFIGURATION
-- ****

PhysicalChannelReconfiguration ::= CHOICE {
    r3
        physicalChannelReconfiguration-r3
            PhysicalChannelReconfiguration-r3-IEs,
            SEQUENCE {
                v3a0NonCriticalExtensions
                    physicalChannelReconfiguration-v3a0ext
                        PhysicalChannelReconfiguration-v3a0ext,
                laterNonCriticalExtensions
                    SEQUENCE {
                        -- Container for additional R99 extensions
                        physicalChannelReconfiguration-r3-add-ext
                            BIT STRING
                            OPTIONAL,
                        v4b0NonCriticalExtensios
                            SEQUENCE {
                                physicalChannelReconfiguration-v4b0ext
                                    PhysicalChannelReconfiguration-v4b0ext-IEs,
                                v590NonCriticalExtenstions
                                    SEQUENCE {
                                        physicalChannelReconfiguration-v590ext
                                            PhysicalChannelReconfiguration-v590ext-IEs,
                                        v6xyNonCriticalExtensions
                                            SEQUENCE {
                                                physicalChannelReconfiguration-v6xyext
                                                    PhysicalChannelReconfiguration-v6xyext-IEs,
                                                nonCriticalExtensions
                                                    SEQUENCE {} OPTIONAL
                                            } OPTIONAL
                                        } OPTIONAL
                                    } OPTIONAL
                                } OPTIONAL
                            } OPTIONAL
                        },
                    later-than-r3
                        SEQUENCE {
                            rrc-TransactionIdentifier
                                RRC-TransactionIdentifier,
                            criticalExtensions
                                CHOICE {
                                r4
                                    SEQUENCE {
                                        physicalChannelReconfiguration-r4
                                            PhysicalChannelReconfiguration-r4-IEs,
                                        v4d0NonCriticalExtensions
                                            SEQUENCE {
                                                -- Container for adding non critical extensions after freezing REL-5
                                                physicalChannelReconfiguration-r4-add-ext
                                                    BIT STRING
                                                    OPTIONAL,
                                                v590NonCriticalExtensios
                                                    SEQUENCE {
                                                        physicalChannelReconfiguration-v590ext
                                                            PhysicalChannelReconfiguration-v590ext-IEs,
                                                        v6xyNonCriticalExtensions
                                                            SEQUENCE {
                                                                physicalChannelReconfiguration-v6xyext
                                                                    PhysicalChannelReconfiguration-v6xyext-IEs,
                                                                nonCriticalExtensions
                                                                    SEQUENCE {} OPTIONAL
                                                            } OPTIONAL
                                                        } OPTIONAL
                                                    } OPTIONAL
                                                },
                                            criticalExtensions
                                                CHOICE {
                                                r5
                                                    SEQUENCE {
                                                        physicalChannelReconfiguration-r5
                                                            PhysicalChannelReconfiguration-r5-IEs,
                                                        -- Container for adding non critical extensions after freezing REL-6
                                                        physicalChannelReconfiguration-r5-add-ext
                                                            BIT STRING
                                                            OPTIONAL,
                                                        v6xyNonCriticalExtensions
                                                            SEQUENCE {
                                                                physicalChannelReconfiguration-v6xyext
                                                                    PhysicalChannelReconfiguration-v6xyext-IEs,
                                                                nonCriticalExtensions
                                                                    SEQUENCE {} OPTIONAL
                                                            } OPTIONAL
                                                        },
                                                    criticalExtensions
                                                        CHOICE {
                                                        r6
                                                            SEQUENCE {
                                                                physicalChannelReconfiguration-r6
                                                                    PhysicalChannelReconfiguration-r6-IEs,
                                                                -- Container for adding non critical extensions after freezing REL-7
                                                                physicalChannelReconfiguration-r6-add-ext
                                                                    BIT STRING
                                                                    OPTIONAL,
                                                                nonCriticalExtensions
                                                                    SEQUENCE {} OPTIONAL
                                                            },
                                                        criticalExtensions
                                                            SEQUENCE {}
                                                        }
                                                    } }
                                                }
                                            }
                                        }
                                    }
                                }
                            }
                        }
                    }
                }
            }
        }
    }
}

```

```

PhysicalChannelReconfiguration-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    integrityProtectionModeInfo   IntegrityProtectionModeInfo      OPTIONAL,
    cipheringModeInfo             CipheringModeInfo            OPTIONAL,
    activationTime                ActivationTime               OPTIONAL,
    new-U-RNTI                   U-RNTI                      OPTIONAL,
    new-C-RNTI                   C-RNTI                      OPTIONAL,
    rrc-StateIndicator            RRC-StateIndicator          OPTIONAL,
    utran-DRX-CycleLengthCoeff   UTRAN-DRX-CycleLengthCoefficient OPTIONAL,
    -- Core network IEs
    cn-InformationInfo           CN-InformationInfo        OPTIONAL,
    -- UTRAN mobility IEs
    ura-Identity                 URA-Identity               OPTIONAL,
    -- Radio bearer IEs
    dl-CounterSynchronisationInfo DL-CounterSynchronisationInfo OPTIONAL,
    -- Physical channel IEs
    frequencyInfo                FrequencyInfo              OPTIONAL,
    maxAllowedUL-TX-Power        MaxAllowedUL-TX-Power      OPTIONAL,
    -- TABULAR: UL-ChannelRequirementWithCPCH-SetID contains the choice
    -- between UL DPCH info, CPCH SET info and CPCH set ID.
    ul-ChannelRequirement         UL-ChannelRequirementWithCPCH-SetID OPTIONAL,
    modeSpecificInfo              CHOICE {
        fdd                      SEQUENCE {
            dl-PDSCH-Information   DL-PDSCH-Information        OPTIONAL
        },
        tdd                      NULL
    },
    dl-CommonInformation          DL-CommonInformation        OPTIONAL,
    dl-InformationPerRL-List     DL-InformationPerRL-List    OPTIONAL
}

PhysicalChannelReconfiguration-v3a0ext ::= SEQUENCE {
    new-DSCH-RNTI                DSCH-RNTI                  OPTIONAL
}

PhysicalChannelReconfiguration-v4b0ext-IEs ::= SEQUENCE {
    -- Physical channel IEs
    ssdt-UL                      SSDT-UL                  OPTIONAL,
    -- ssdt-UL extends SSDT-Information, which is included in
    -- DL-CommonInformation. FDD only.
    ssdt-UL-r4                   SSDT-UL                  OPTIONAL,
    -- The order of the RLs in IE cell-id-PerRL-List is the same as
    -- in IE DL-InformationPerRL-List included in this message
    cell-id-PerRL-List            CellIdentity-PerRL-List    OPTIONAL
}

PhysicalChannelReconfiguration-v590ext-IEs ::= SEQUENCE {
    -- Physical channel IEs
    dl-TPC-PowerOffsetPerRL-List  DL-TPC-PowerOffsetPerRL-List    OPTIONAL
}

PhysicalChannelReconfiguration-r4-IEs ::= SEQUENCE {
    -- User equipment IEs
    integrityProtectionModeInfo   IntegrityProtectionModeInfo      OPTIONAL,
    cipheringModeInfo             CipheringModeInfo            OPTIONAL,
    activationTime                ActivationTime               OPTIONAL,
    new-U-RNTI                   U-RNTI                      OPTIONAL,
    new-C-RNTI                   C-RNTI                      OPTIONAL,
    new-DSCH-RNTI                DSCH-RNTI                  OPTIONAL,
    rrc-StateIndicator            RRC-StateIndicator          OPTIONAL,
    utran-DRX-CycleLengthCoeff   UTRAN-DRX-CycleLengthCoefficient OPTIONAL,
    -- Core network IEs
    cn-InformationInfo           CN-InformationInfo        OPTIONAL,
    -- UTRAN mobility IEs
    ura-Identity                 URA-Identity               OPTIONAL,
    -- Radio bearer IEs
    dl-CounterSynchronisationInfo DL-CounterSynchronisationInfo OPTIONAL,
    -- Physical channel IEs
    frequencyInfo                FrequencyInfo              OPTIONAL,
    maxAllowedUL-TX-Power        MaxAllowedUL-TX-Power      OPTIONAL,
    -- TABULAR: UL-ChannelRequirementWithCPCH-SetID-r4 contains the choice
    -- between UL DPCH info, CPCH SET info and CPCH set ID.
    ul-ChannelRequirement         UL-ChannelRequirementWithCPCH-SetID-r4 OPTIONAL,
    modeSpecificInfo              CHOICE {
        fdd                      SEQUENCE {
            dl-PDSCH-Information   DL-PDSCH-Information        OPTIONAL
        },
        tdd                      NULL
    }
}

```

```

        },
        dl-CommonInformation          DL-CommonInformation-r4           OPTIONAL,
        dl-InformationPerRL-List     DL-InformationPerRL-List-r4        OPTIONAL
    }

PhysicalChannelReconfiguration-r5-IEs ::= SEQUENCE {
    -- User equipment IEs
    integrityProtectionModeInfo   IntegrityProtectionModeInfo      OPTIONAL,
    cipheringModeInfo             CipheringModeInfo            OPTIONAL,
    activationTime                ActivationTime                 OPTIONAL,
    new-U-RNTI                   U-RNTI                         OPTIONAL,
    new-C-RNTI                   C-RNTI                         OPTIONAL,
    new-DSCH-RNTI                DSCH-RNTI                     OPTIONAL,
    new-H-RNTI                   H-RNTI                         OPTIONAL,
    rrc-StateIndicator            RRC-StateIndicator           OPTIONAL,
    utran-DRX-CycleLengthCoeff   UTRAN-DRX-CycleLengthCoefficient OPTIONAL,
    -- Core network IEs
    cn-InformationInfo           CN-InformationInfo          OPTIONAL,
    -- UTRAN mobility IEs
    ura-Identity                  URA-Identity                    OPTIONAL,
    -- Radio bearer IEs
    dl-CounterSynchronisationInfo DL-CounterSynchronisationInfo-r5 OPTIONAL,
    -- Physical channel IEs
    frequencyInfo                 FrequencyInfo                 OPTIONAL,
    maxAllowedUL-TX-Power         MaxAllowedUL-TX-Power          OPTIONAL,
    -- TABULAR: UL-ChannelRequirementWithCPCH-SetID-r5 contains the choice
    -- between UL DPCH info, CPCH SET info and CPCH set ID.
    ul-ChannelRequirement         UL-ChannelRequirementWithCPCH-SetID-r5 OPTIONAL,
    modeSpecificInfo              CHOICE {
        fdd                      SEQUENCE {
            dl-PDSCH-Information  DL-PDSCH-Information          OPTIONAL
        },
        tdd                      NULL
    },
    dl-HSPDSCH-Information       DL-HSPDSCH-Information          OPTIONAL,
    dl-CommonInformation          DL-CommonInformation-r5          OPTIONAL,
    dl-InformationPerRL-List     DL-InformationPerRL-List-r5        OPTIONAL
}

PhysicalChannelReconfiguration-v6xyext-IEs ::= SEQUENCE {
    -- Core network IEs
    plmn-Identity                PLMN-Identity                  OPTIONAL,
    -- Physical channel IEs
    harq-Preamble-Mode           HARQ-Preamble-Mode          OPTIONAL,
    -- MBMS IEs
    mbms-FLCAplicabilityInfo    MBMS-FLCAplicabilityInfo-r6
}

PhysicalChannelReconfiguration-r6-IEs ::= SEQUENCE {
    -- User equipment IEs
    integrityProtectionModeInfo   IntegrityProtectionModeInfo      OPTIONAL,
    cipheringModeInfo             CipheringModeInfo            OPTIONAL,
    activationTime                ActivationTime                 OPTIONAL,
    new-U-RNTI                   U-RNTI                         OPTIONAL,
    new-C-RNTI                   C-RNTI                         OPTIONAL,
    new-DSCH-RNTI                DSCH-RNTI                     OPTIONAL,
    new-H-RNTI                   H-RNTI                         OPTIONAL,
    new-E-RNTI                   E-RNTI                         OPTIONAL,
    rrc-StateIndicator            RRC-StateIndicator           OPTIONAL,
    utran-DRX-CycleLengthCoeff   UTRAN-DRX-CycleLengthCoefficient OPTIONAL,
    -- Core network IEs
    cn-InformationInfo           CN-InformationInfo          OPTIONAL,
    plmn-Identity                PLMN-Identity                  OPTIONAL,
    -- UTRAN mobility IEs
    ura-Identity                  URA-Identity                    OPTIONAL,
    -- Radio bearer IEs
    dl-CounterSynchronisationInfo DL-CounterSynchronisationInfo-r5 OPTIONAL,
    -- Physical channel IEs
    frequencyInfo                 FrequencyInfo                 OPTIONAL,
    maxAllowedUL-TX-Power         MaxAllowedUL-TX-Power          OPTIONAL,
    -- TABULAR: UL-ChannelRequirementWithCPCH-SetID-r6 contains the choice
    -- between UL DPCH info, CPCH SET info and CPCH set ID.
    ul-ChannelRequirement         UL-ChannelRequirementWithCPCH-SetID-r6 OPTIONAL,
    ul-EDCH-Information          UL-EDCH-Information-r6          OPTIONAL,
    modeSpecificInfo              CHOICE {
        fdd                      SEQUENCE {
            dl-PDSCH-Information  DL-PDSCH-Information          OPTIONAL
        },
    }
}

```

```

    tdd           NULL
  },
  dl-HSPDSCH-Information      DL-HSPDSCH-Information      OPTIONAL,
  dl-CommonInformation        DL-CommonInformation-r5    OPTIONAL,
  dl-InformationPerRL-List   DL-InformationPerRL-List-r6  OPTIONAL,
  -- MBMS IEs
  mbms-FLCAplicabilityInfo  MBMS-FLCAplicabilityInfo-r6
}

-- ****
-- PHYSICAL CHANNEL RECONFIGURATION COMPLETE
-- ****

PhysicalChannelReconfigurationComplete ::= SEQUENCE {
  -- User equipment IEs
  rrc-TransactionIdentifier      RRC-TransactionIdentifier,
  ul-IntegProtActivationInfo    IntegrityProtActivationInfo    OPTIONAL,
  -- TABULAR: UL-TimingAdvance is applicable for TDD mode only.
  ul-TimingAdvance              UL-TimingAdvance            OPTIONAL,
  -- Radio bearer IEs
  count-C-ActivationTime        ActivationTime            OPTIONAL,
  -- dummy is not used in this version of the specification and
  -- it should be ignored by the receiver.
  dummy                         RB-ActivationTimeInfoList  OPTIONAL,
  ul-CounterSynchronisationInfo UL-CounterSynchronisationInfo  OPTIONAL,
  laterNonCriticalExtensions   SEQUENCE {
    -- Container for additional R99 extensions
    physicalChannelReconfigurationComplete-r3-add-ext   BIT STRING    OPTIONAL,
    nonCriticalExtensions        SEQUENCE {}             OPTIONAL
  }                           OPTIONAL
}

-- ****
-- PHYSICAL CHANNEL RECONFIGURATION FAILURE
-- ****

PhysicalChannelReconfigurationFailure ::= SEQUENCE {
  -- User equipment IEs
  rrc-TransactionIdentifier      RRC-TransactionIdentifier      OPTIONAL,
  failureCause                  FailureCauseWithProtErr,
  laterNonCriticalExtensions   SEQUENCE {
    -- Container for additional R99 extensions
    physicalChannelReconfigurationFailure-r3-add-ext   BIT STRING    OPTIONAL,
    nonCriticalExtensions        SEQUENCE {}             OPTIONAL
  }                           OPTIONAL
}

-- ****
-- PHYSICAL SHARED CHANNEL ALLOCATION (TDD only)
-- ****

PhysicalSharedChannelAllocation ::= CHOICE {
  r3           SEQUENCE {
    physicalSharedChannelAllocation-r3
      PhysicalSharedChannelAllocation-r3-IEs,
    laterNonCriticalExtensions SEQUENCE {
      -- Container for additional R99 extensions
      physicalSharedChannelAllocation-r3-add-ext   BIT STRING    OPTIONAL,
      nonCriticalExtensions        SEQUENCE {}             OPTIONAL
    }                           OPTIONAL
  },
  later-than-r3          SEQUENCE {
    dsch-RNTI                DSCH-RNTI                  OPTIONAL,
    rrc-TransactionIdentifier RRC-TransactionIdentifier,
    criticalExtensions       CHOICE {
      r4           SEQUENCE {
        physicalSharedChannelAllocation-r4
          PhysicalSharedChannelAllocation-r4-IEs,
        v4d0NonCriticalExtensions SEQUENCE {
          -- Container for adding non critical extensions after freezing REL-5
          physicalSharedChannelAllocation-r4-add-ext   BIT STRING    OPTIONAL,
          nonCriticalExtensions        SEQUENCE {}             OPTIONAL
        }
      }
    }
  }
}

```

```

        }
        OPTIONAL
    },
    criticalExtensions           SEQUENCE {}
}

PhysicalSharedChannelAllocation-r3-IEs ::= SEQUENCE {
-- TABULAR: Integrity protection shall not be performed on this message.
-- User equipment IEs
    dsch-RNTI                  DSCH-RNTI                      OPTIONAL,
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
-- Physical channel IEs
    ul-TimingAdvance           UL-TimingAdvanceControl      OPTIONAL,
    pusch-CapacityAllocationInfo PUSCH-CapacityAllocationInfo OPTIONAL,
    pdsch-CapacityAllocationInfo PDSCH-CapacityAllocationInfo OPTIONAL,
-- TABULAR: If confirmRequest is not present, the default value "No Confirm"
-- shall be used as specified in 10.2.25.
    confirmRequest              ENUMERATED {
                                confirmPDSCH, confirmPUSCH }    OPTIONAL,
    trafficVolumeReportRequest  INTEGER (0..255)          OPTIONAL,
    iscpTimeslotList            TimeslotList                  OPTIONAL,
    requestPCCPCHRSCP          BOOLEAN                     OPTIONAL
}

PhysicalSharedChannelAllocation-r4-IEs ::= SEQUENCE {
-- TABULAR: Integrity protection shall not be performed on this message.
-- Physical channel IEs
    ul-TimingAdvance           UL-TimingAdvanceControl-r4     OPTIONAL,
    pusch-CapacityAllocationInfo PUSCH-CapacityAllocationInfo-r4 OPTIONAL,
    pdsch-CapacityAllocationInfo PDSCH-CapacityAllocationInfo-r4 OPTIONAL,
-- TABULAR: If confirmRequest is not present, the default value "No Confirm"
-- shall be used as specified in 10.2.25.
    confirmRequest              ENUMERATED {
                                confirmPDSCH, confirmPUSCH }    OPTIONAL,
    trafficVolumeReportRequest  INTEGER (0..255)          OPTIONAL,
    iscpTimeslotList            TimeslotList-r4             OPTIONAL,
    requestPCCPCHRSCP          BOOLEAN                     OPTIONAL
}

-- ****
-- 
-- PUSCH CAPACITY REQUEST (TDD only)
-- 
-- ****

PUSCHCapacityRequest ::= SEQUENCE {
-- User equipment IEs
    dsch-RNTI                  DSCH-RNTI                      OPTIONAL,
-- Measurement IEs
    trafficVolume               TrafficVolumeMeasuredResultsList OPTIONAL,
    timeslotListWithISCP        TimeslotListWithISCP          OPTIONAL,
    primaryCCPCH-RSCP           PrimaryCCPCH-RSCP          OPTIONAL,
    allocationConfirmation      CHOICE {
        pdschConfirmation       PDSCH-Identity,
        puschConfirmation       PUSCH-Identity
    }                           OPTIONAL,
    protocolErrorIndicator      ProtocolErrorIndicatorWithMoreInfo,
    laterNonCriticalExtensions  SEQUENCE {
        -- Container for additional R99 extensions
        puschCapacityRequest-r3-add-ext  BIT STRING      OPTIONAL,
        v590NonCriticalExtensions      SEQUENCE {
            puschCapacityRequest-v590ext  PUSCHCapacityRequest-v590ext,
            nonCriticalExtensions       SEQUENCE {} OPTIONAL
        }                           OPTIONAL
    }                           OPTIONAL
}

PUSCHCapacityRequest-v590ext ::= SEQUENCE {
    primaryCCPCH-RSCP-delta     DeltaRSCP                     OPTIONAL
}

-- ****
-- 
-- RADIO BEARER RECONFIGURATION
-- 
-- ****

RadioBearerReconfiguration ::= CHOICE {

```

```

r3
    SEQUENCE {
        radioBearerReconfiguration-r3    RadioBearerReconfiguration-r3-IEs,
        -- Prefix "v3ao" is used (in one instance) to keep alignment with R99
        v3aoNonCriticalExtensions      SEQUENCE {
            radioBearerReconfiguration-v3a0ext  RadioBearerReconfiguration-v3a0ext,
            laterNonCriticalExtensions     SEQUENCE {
                -- Container for additional R99 extensions
                radioBearerReconfiguration-r3-add-ext   BIT STRING      OPTIONAL,
                v4b0NonCriticalExtensions       SEQUENCE {
                    radioBearerReconfiguration-v4b0ext
                        RadioBearerReconfiguration-v4b0ext-IEs,
                    v590NonCriticalExtensions     SEQUENCE {
                        radioBearerReconfiguration-v590ext
                            RadioBearerReconfiguration-v590ext-IEs,
                        v6xyNonCriticalExtensions   SEQUENCE {
                            radioBearerReconfiguration-v6xyext
                                RadioBearerReconfiguration-v6xyext-IEs,
                            nonCriticalExtensions     SEQUENCE {} OPTIONAL
                        } OPTIONAL
                    } OPTIONAL
                } OPTIONAL
            } OPTIONAL
        } OPTIONAL
    },
    later-than-r3
        SEQUENCE {
            rrc-TransactionIdentifier    RRC-TransactionIdentifier,
            criticalExtensions          CHOICE {
                r4
                    SEQUENCE {
                        radioBearerReconfiguration-r4    RadioBearerReconfiguration-r4-IEs,
                        v4d0NonCriticalExtensions     SEQUENCE {
                            -- Container for adding non critical extensions after freezing REL-5
                            radioBearerReconfiguration-r4-add-ext   BIT STRING      OPTIONAL,
                            v590NonCriticalExtensions       SEQUENCE {
                                radioBearerReconfiguration-v590ext
                                    RadioBearerReconfiguration-v590ext-IEs,
                                v6xyNonCriticalExtensions   SEQUENCE {
                                    radioBearerReconfiguration-v6xyext
                                        RadioBearerReconfiguration-v6xyext-IEs,
                                    nonCriticalExtensions     SEQUENCE {} OPTIONAL
                                } OPTIONAL
                            } OPTIONAL
                        } OPTIONAL
                    },
                    criticalExtensions          CHOICE {
                        r5
                            SEQUENCE {
                                radioBearerReconfiguration-r5    RadioBearerReconfiguration-r5-IEs,
                                -- Container for adding non critical extensions after freezing REL-6
                                radioBearerReconfiguration-r5-add-ext   BIT STRING      OPTIONAL,
                                v6xyNonCriticalExtensions       SEQUENCE {
                                    radioBearerReconfiguration-v6xyext
                                        RadioBearerReconfiguration-v6xyext-IEs,
                                    nonCriticalExtensions     SEQUENCE {} OPTIONAL
                                } OPTIONAL
                            },
                            criticalExtensions          CHOICE {
                                r6
                                    SEQUENCE {
                                        radioBearerReconfiguration-r6    RadioBearerReconfiguration-r6-IEs,
                                        -- Container for adding non critical extensions after freezing REL-7
                                        radioBearerReconfiguration-r6-add-ext   BIT STRING      OPTIONAL,
                                        nonCriticalExtensions     SEQUENCE {} OPTIONAL
                                    },
                                    criticalExtensions          SEQUENCE {}
                                }
                            }
                        }
                    }
                }
            }
        }
    }

RadioBearerReconfiguration-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier    RRC-TransactionIdentifier,
    integrityProtectionModeInfo IntegrityProtectionModeInfo      OPTIONAL,
    cipheringModeInfo            CipheringModeInfo           OPTIONAL,
    activationTime                ActivationTime             OPTIONAL,
    new-U-RNTI                  U-RNTI                   OPTIONAL,
    new-C-RNTI                  C-RNTI                   OPTIONAL,
    rrc-StateIndicator           RRC-StateIndicator        OPTIONAL,
    utran-DRX-CycleLengthCoeff  UTRAN-DRX-CycleLengthCoefficient  OPTIONAL,
}

```

```

-- Core network IEs
  cn-InformationInfo          CN-InformationInfo           OPTIONAL,
-- UTRAN mobility IEs
  ura-Identity                 URA-Identity                  OPTIONAL,
-- Radio bearer IEs
  rab-InformationReconfigList RAB-InformationReconfigList OPTIONAL,
  -- NOTE: IE rb-InformationReconfigList should be optional in later versions
  -- of this message
  rb-InformationReconfigList   RB-InformationReconfigList,
  rb-InformationAffectedList   RB-InformationAffectedList    OPTIONAL,
-- Transport channel IEs
  ul-CommonTransChInfo        UL-CommonTransChInfo         OPTIONAL,
  ul-deletedTransChInfoList   UL-DeletedTransChInfoList    OPTIONAL,
  ul-AddReconfTransChInfoList UL-AddReconfTransChInfoList  OPTIONAL,
  modeSpecificTransChInfo     CHOICE {
    fdd                         SEQUENCE {
      cpch-SetID                CPCH-SetID                 OPTIONAL,
      addReconfTransChDRAC-Info DRAC-StaticInformationList OPTIONAL
    },
    tdd                         NULL
  }
  dl-CommonTransChInfo        DL-CommonTransChInfo         OPTIONAL,
  dl-DeletedTransChInfoList   DL-DeletedTransChInfoList    OPTIONAL,
  dl-AddReconfTransChInfoList DL-AddReconfTransChInfoList  OPTIONAL,
-- Physical channel IEs
  frequencyInfo               FrequencyInfo              OPTIONAL,
  maxAllowedUL-TX-Power       MaxAllowedUL-TX-Power        OPTIONAL,
  ul-ChannelRequirement       UL-ChannelRequirement        OPTIONAL,
  modeSpecificPhysChInfo     CHOICE {
    fdd                         SEQUENCE {
      dl-PDSCH-Information     DL-PDSCH-Information        OPTIONAL
    },
    tdd                         NULL
  },
  dl-CommonInformation        DL-CommonInformation        OPTIONAL,
  -- NOTE: IE dl-InformationPerRL-List should be optional in later versions
  -- of this message
  dl-InformationPerRL-List    DL-InformationPerRL-List
}

RadioBearerReconfiguration-v3a0ext ::= SEQUENCE {
  new-DSCH-RNTI             DSCH-RNTI                  OPTIONAL
}

RadioBearerReconfiguration-v4b0ext-IEs ::= SEQUENCE {
  -- Physical channel IEs
  -- ssdt-UL extends SSDT-Information, which is included in
  -- DL-CommonInformation. FDD only.
  ssdt-UL-r4                 SSDT-UL                  OPTIONAL,
  -- The order of the RLs in IE cell-id-PerRL-List is the same as
  -- in IE DL-InformationPerRL-List included in this message
  cell-id-PerRL-List          CellIdentity-PerRL-List    OPTIONAL
}

RadioBearerReconfiguration-v590ext-IEs ::= SEQUENCE {
  -- Physical channel IEs
  dl-TPC-PowerOffsetPerRL-List DL-TPC-PowerOffsetPerRL-List  OPTIONAL
}

RadioBearerReconfiguration-r4-IEs ::= SEQUENCE {
  -- User equipment IEs
  integrityProtectionModeInfo IntegrityProtectionModeInfo OPTIONAL,
  cipheringModeInfo            CipheringModeInfo        OPTIONAL,
  activationTime                ActivationTime           OPTIONAL,
  new-U-RNTI                   U-RNTI                  OPTIONAL,
  new-C-RNTI                   C-RNTI                  OPTIONAL,
  new-DSCH-RNTI                DSCH-RNTI              OPTIONAL,
  rrc-StateIndicator            RRC-StateIndicator        OPTIONAL,
  utran-DRX-CycleLengthCoeff  UTRAN-DRX-CycleLengthCoefficient OPTIONAL,
  -- Core network IEs
  cn-InformationInfo          CN-InformationInfo           OPTIONAL,
  -- UTRAN mobility IEs
  ura-Identity                 URA-Identity                  OPTIONAL,
  -- Radio bearer IEs
  rab-InformationReconfigList RAB-InformationReconfigList OPTIONAL,
  rb-InformationReconfigList   RB-InformationReconfigList-r4 OPTIONAL,
  rb-InformationAffectedList   RB-InformationAffectedList  OPTIONAL,
  -- Transport channel IEs
}

```

```

ul-CommonTransChInfo          UL-CommonTransChInfo-r4           OPTIONAL,
ul-deletedTransChInfoList     UL-DeletedTransChInfoList        OPTIONAL,
ul-AddReconfTransChInfoList   UL-AddReconfTransChInfoList        OPTIONAL,
modeSpecificTransChInfo       CHOICE {
    fdd                      SEQUENCE {
        cpch-SetID            CPCH-SetID                OPTIONAL,
        addReconfTransChDRAC-Info DRAC-StaticInformationList OPTIONAL
    },
    tdd                      NULL
}
dl-CommonTransChInfo          DL-CommonTransChInfo-r4           OPTIONAL,
dl-DeletedTransChInfoList     DL-DeletedTransChInfoList        OPTIONAL,
dl-AddReconfTransChInfoList   DL-AddReconfTransChInfoList-r4      OPTIONAL,
-- Physical channel IEs
frequencyInfo                 FrequencyInfo               OPTIONAL,
maxAllowedUL-TX-Power        MaxAllowedUL-TX-Power        OPTIONAL,
ul-ChannelRequirement        UL-ChannelRequirement-r4        OPTIONAL,
modeSpecificPhysChInfo       CHOICE {
    fdd                      SEQUENCE {
        dl-PDSCH-Information DL-PDSCH-Information        OPTIONAL
    },
    tdd                      NULL
},
dl-CommonInformation          DL-CommonInformation-r4        OPTIONAL,
dl-InformationPerRL-List     DL-InformationPerRL-List-r4      OPTIONAL
}

RadioBearerReconfiguration-r5-IEs ::= SEQUENCE {
    -- User equipment IEs
    integrityProtectionModeInfo IntegrityProtectionModeInfo OPTIONAL,
    cipheringModeInfo             CipheringModeInfo          OPTIONAL,
    activationTime                ActivationTime            OPTIONAL,
    new-U-RNTI                   U-RNTI                    OPTIONAL,
    new-C-RNTI                   C-RNTI                    OPTIONAL,
    new-DSCH-RNTI                DSCH-RNTI                OPTIONAL,
    new-H-RNTI                   H-RNTI                    OPTIONAL,
    rrc-StateIndicator            RRC-StateIndicator        OPTIONAL,
    utran-DRX-CycleLengthCoeff  UTRAN-DRX-CycleLengthCoefficient OPTIONAL,
    -- Core network IEs
    cn-InformationInfo          CN-InformationInfo        OPTIONAL,
    -- UTRAN mobility IEs
    ura-Identity                 URA-Identity              OPTIONAL,
    -- Specification mode information
    specificationMode             CHOICE {
        complete                 SEQUENCE {
            -- Radio bearer IEs
            rab-InformationReconfigList RAB-InformationReconfigList OPTIONAL,
            rb-InformationReconfigList RB-InformationReconfigList-r5  OPTIONAL,
            rb-InformationAffectedList RB-InformationAffectedList-r5  OPTIONAL,
            rb-PDCPContextRelocationList RB-PDCPContextRelocationList OPTIONAL,
            -- Transport channel IEs
            ul-CommonTransChInfo        UL-CommonTransChInfo-r4           OPTIONAL,
            ul-deletedTransChInfoList   UL-DeletedTransChInfoList        OPTIONAL,
            ul-AddReconfTransChInfoList UL-AddReconfTransChInfoList        OPTIONAL,
            modeSpecificTransChInfo     CHOICE {
                fdd                      SEQUENCE {
                    cpch-SetID            CPCH-SetID                OPTIONAL,
                    addReconfTransChDRAC-Info DRAC-StaticInformationList OPTIONAL
                },
                tdd                      NULL
}
            dl-CommonTransChInfo        DL-CommonTransChInfo-r4           OPTIONAL,
            dl-DeletedTransChInfoList   DL-DeletedTransChInfoList-r5      OPTIONAL,
            dl-AddReconfTransChInfoList DL-AddReconfTransChInfoList-r5      OPTIONAL
},
        preconfiguration           SEQUENCE {
            -- All IEs that include an FDD/TDD choice are split in two IEs for this message,
            -- one for the FDD only elements and one for the TDD only elements, so that one
            -- FDD/TDD choice in this level is sufficient.
            preConfigMode              CHOICE {
                predefinedConfigIdentity PredefinedConfigIdentity,
                defaultConfig             SEQUENCE {
                    defaultConfigMode      DefaultConfigMode,
                    defaultConfigIdentity  DefaultConfigIdentity-r5
                }
            }
        }
    }
}

```

```

-- Physical channel IEs
frequencyInfo FrequencyInfo OPTIONAL,
maxAllowedUL-TX-Power MaxAllowedUL-TX-Power OPTIONAL,
ul-ChannelRequirement UL-ChannelRequirement-r5 OPTIONAL,
modeSpecificPhysChInfo CHOICE {
    fdd SEQUENCE {
        dl-PDSCH-Information DL-PDSCH-Information OPTIONAL
    },
    tdd NULL
},
dl-HSPDSCH-Information DL-HSPDSCH-Information OPTIONAL,
dl-CommonInformation DL-CommonInformation-r5 OPTIONAL,
dl-InformationPerRL-List DL-InformationPerRL-List-r5 OPTIONAL
}

RadioBearerReconfiguration-v6xyext-IEs ::= SEQUENCE {
    -- Core network IEs
    plmn-Identity PLMN-Identity OPTIONAL,
    -- Physical channel IEs
    harq-Preamble-Mode HARQ-Preamble-Mode OPTIONAL,
    -- MBMS IEs
    mbms-FLCAplicabilityInfo MBMS-FLCAplicabilityInfo-r6
}

RadioBearerReconfiguration-r6-IEs ::= SEQUENCE {
    -- User equipment IEs
    integrityProtectionModeInfo IntegrityProtectionModeInfo OPTIONAL,
    cipheringModeInfo CipheringModeInfo OPTIONAL,
    activationTime ActivationTime OPTIONAL,
    new-U-RNTI U-RNTI OPTIONAL,
    new-C-RNTI C-RNTI OPTIONAL,
    new-DSCH-RNTI DSCH-RNTI OPTIONAL,
    new-H-RNTI H-RNTI OPTIONAL,
    new-E-RNTI E-RNTI OPTIONAL,
    rrc-StateIndicator RRC-StateIndicator OPTIONAL,
    utran-DRX-CycleLengthCoeff UTRAN-DRX-CycleLengthCoefficient OPTIONAL,
    -- Core network IEs
    cn-InformationInfo CN-InformationInfo OPTIONAL,
    plmn-Identity PLMN-Identity OPTIONAL,
    -- UTRAN mobility IEs
    ura-Identity URA-Identity OPTIONAL,
    -- Specification mode information
    specificationMode CHOICE {
        complete SEQUENCE {
            -- Radio bearer IEs
            rab-InformationReconfigList RAB-InformationReconfigList OPTIONAL,
            rb-InformationReconfigList RB-InformationReconfigList-r6 OPTIONAL,
            rb-InformationAffectedList RB-InformationAffectedList-r6 OPTIONAL,
            rb-PDCPContextRelocationList RB-PDCPContextRelocationList OPTIONAL,
            -- Transport channel IEs
            ul-CommonTransChInfo UL-CommonTransChInfo-r4 OPTIONAL,
            ul-deletedTransChInfoList UL-DeletedTransChInfoList-r6 OPTIONAL,
            ul-AddReconfTransChInfoList UL-AddReconfTransChInfoList-r6 OPTIONAL,
            modeSpecificTransChInfo CHOICE {
                fdd SEQUENCE {
                    cpch-SetID CPCH-SetID OPTIONAL,
                    addReconfTransChDRAC-Info DRAC-StaticInformationList OPTIONAL
                },
                tdd NULL
            }
            dl-CommonTransChInfo DL-CommonTransChInfo-r4 OPTIONAL,
            dl-DeletedTransChInfoList DL-DeletedTransChInfoList-r5 OPTIONAL,
            dl-AddReconfTransChInfoList DL-AddReconfTransChInfoList-r5 OPTIONAL
        },
        preconfiguration SEQUENCE {
            -- All IEs that include an FDD/TDD choice are split in two IEs for this message,
            -- one for the FDD only elements and one for the TDD only elements, so that one
            -- FDD/TDD choice in this level is sufficient.
            preConfigMode CHOICE {
                predefinedConfigIdentity PredefinedConfigIdentity,
                defaultConfig SEQUENCE {
                    defaultConfigMode DefaultConfigMode,
                    defaultConfigIdentity DefaultConfigIdentity-r5
                }
            }
        }
    },
    -- Physical channel IEs
}

```

```

frequencyInfo FrequencyInfo OPTIONAL,
maxAllowedUL-TX-Power MaxAllowedUL-TX-Power OPTIONAL,
ul-ChannelRequirement UL-ChannelRequirement-r6 OPTIONAL,
ul-EDCH-Information UL-EDCH-Information-r6 OPTIONAL,
modeSpecificPhysChInfo CHOICE {
    fdd SEQUENCE {
        dl-PDSCH-Information DL-PDSCH-Information OPTIONAL
    },
    tdd NULL
},
dl-HSPDSCH-Information DL-HSPDSCH-Information OPTIONAL,
dl-CommonInformation DL-CommonInformation-r5 OPTIONAL,
dl-InformationPerRL-List DL-InformationPerRL-List-r6 OPTIONAL,
-- MBMS IEs
mbms-FLCAplicabilityInfo MBMS-FLCAplicabilityInfo-r6
}

-- *****
-- 
-- RADIO BEARER RECONFIGURATION COMPLETE
-- 
-- *****

RadioBearerReconfigurationComplete ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier RRC-TransactionIdentifier,
    ul-IntegProtActivationInfo IntegrityProtActivationInfo OPTIONAL,
    -- TABULAR: UL-TimingAdvance is applicable for TDD mode only.
    ul-TimingAdvance UL-TimingAdvance OPTIONAL,
    -- Radio bearer IEs
    count-C-ActivationTime ActivationTime OPTIONAL,
    -- dummy is not used in this version of the specification and
    -- it should be ignored by the receiver.
    dummy RB-ActivationTimeInfoList OPTIONAL,
    ul-CounterSynchronisationInfo UL-CounterSynchronisationInfo OPTIONAL,
    laterNonCriticalExtensions SEQUENCE {
        -- Container for additional R99 extensions
        radioBearerReconfigurationComplete-r3-add-ext BIT STRING OPTIONAL,
        nonCriticalExtensions SEQUENCE {} OPTIONAL
    } OPTIONAL
}

-- *****
-- 
-- RADIO BEARER RECONFIGURATION FAILURE
-- 
-- *****

RadioBearerReconfigurationFailure ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier RRC-TransactionIdentifier,
    failureCause FailureCauseWithProtErr,
    -- Radio bearer IEs
    potentiallySuccessfulBearerList RB-IdentityList OPTIONAL,
    laterNonCriticalExtensions SEQUENCE {
        -- Container for additional R99 extensions
        radioBearerReconfigurationFailure-r3-add-ext BIT STRING OPTIONAL,
        nonCriticalExtensions SEQUENCE {} OPTIONAL
    } OPTIONAL
}

-- *****
-- 
-- RADIO BEARER RELEASE
-- 
-- *****

RadioBearerRelease ::= CHOICE {
    r3 SEQUENCE {
        radioBearerRelease-r3 RadioBearerRelease-r3-IES,
        v3a0NonCriticalExtensions SEQUENCE {
            radioBearerRelease-v3a0ext RadioBearerRelease-v3a0ext,
        laterNonCriticalExtensions SEQUENCE {
            -- Container for additional R99 extensions
            radioBearerRelease-r3-add-ext BIT STRING OPTIONAL,
            v4b0NonCriticalExtensions SEQUENCE {
                radioBearerRelease-v4b0ext RadioBearerRelease-v4b0ext-IES,
                v590NonCriticalExtensions SEQUENCE {

```



```

        addReconfTransChDRAC-Info          DRAC-StaticInformationList  OPTIONAL
    },
    tdd                                NULL
}
dl-CommonTransChInfo                 DL-CommonTransChInfo         OPTIONAL,
dl-DeletedTransChInfoList           DL-DeletedTransChInfoList   OPTIONAL,
dl-AddReconfTransChInfoList         DL-AddReconfTransChInfo2List OPTIONAL,
-- Physical channel IEs
frequencyInfo                      FrequencyInfo             OPTIONAL,
maxAllowedUL-TX-Power              MaxAllowedUL-TX-Power     OPTIONAL,
ul-ChannelRequirement              UL-ChannelRequirement      OPTIONAL,
modeSpecificPhysChInfo
    fdd                           CHOICE {
        SEQUENCE {
            dl-PDSCH-Information
        },
        tdd
    },
    dl-CommonInformation             DL-CommonInformation       OPTIONAL,
    dl-InformationPerRL-List        DL-InformationPerRL-List   OPTIONAL
}

RadioBearerRelease-v3a0ext ::= SEQUENCE {
    new-DSCH-RNTI                  DSCH-RNTI
}                                         OPTIONAL

RadioBearerRelease-v4b0ext-IEs ::= SEQUENCE {
-- Physical channel IEs
    -- IE ssdt-UL extends SSDT-Information, which is included in
    -- DL-CommonInformation. FDD only.
    ssdt-UL-r4                     SSDT-UL
    -- The order of the RLs in IE cell-id-PerRL-List is the same as
    -- in IE DL-InformationPerRL-List included in this message
    cell-id-PerRL-List              CellIdentity-PerRL-List   OPTIONAL
}

RadioBearerRelease-v590ext-IEs ::= SEQUENCE {
-- Physical channel IEs
    dl-TPC-PowerOffsetPerRL-List   DL-TPC-PowerOffsetPerRL-List OPTIONAL
}

RadioBearerRelease-r4-IEs ::= SEQUENCE {
-- User equipment IEs
    integrityProtectionModeInfo   IntegrityProtectionModeInfo OPTIONAL,
    cipheringModeInfo              CipheringModeInfo        OPTIONAL,
    activationTime                 ActivationTime          OPTIONAL,
    new-U-RNTI                     U-RNTI
    new-C-RNTI                     C-RNTI
    new-DSCH-RNTI                  DSCH-RNTI
    rrc-StateIndicator              RRC-StateIndicator
    utran-DRX-CycleLengthCoeff    UTRAN-DRX-CycleLengthCoefficient OPTIONAL,
-- Core network IEs
    cn-InformationInfo             CN-InformationInfo      OPTIONAL,
    signallingConnectionRelIndication CN-DomainIdentity    OPTIONAL,
-- UTRAN mobility IEs
    ura-Identity                   URA-Identity          OPTIONAL,
-- Radio bearer IEs
    rab-InformationReconfigList   RAB-InformationReconfigList OPTIONAL,
    rb-InformationReleaseList     RB-InformationReleaseList OPTIONAL,
    rb-InformationAffectedList    RB-InformationAffectedList OPTIONAL,
    dl-CounterSynchronisationInfo DL-CounterSynchronisationInfo OPTIONAL,
-- Transport channel IEs
    ul-CommonTransChInfo          UL-CommonTransChInfo-r4  OPTIONAL,
    ul-deletedTransChInfoList     UL-DeletedTransChInfoList OPTIONAL,
    ul-AddReconfTransChInfoList   UL-AddReconfTransChInfoList OPTIONAL,
    modeSpecificTransChInfo
        fdd                         CHOICE {
            SEQUENCE {
                cpch-SetID            CPCH-SetID
                addReconfTransChDRAC-Info DRAC-StaticInformationList
            },
            tdd
        },
        dl-CommonTransChInfo       NULL
    },
    dl-DeletedTransChInfoList      DL-CommonTransChInfo-r4
    dl-AddReconfTransChInfoList   DL-DeletedTransChInfoList
    dl-AddReconfTransChInfoList   DL-AddReconfTransChInfoList-r4
-- Physical channel IEs
    frequencyInfo                 FrequencyInfo             OPTIONAL,
    maxAllowedUL-TX-Power         MaxAllowedUL-TX-Power     OPTIONAL,
    ul-ChannelRequirement         UL-ChannelRequirement-r4  OPTIONAL,
}

```

```

modeSpecificPhysChInfo          CHOICE {
    fdd                      SEQUENCE {
        dl-PDSCH-Information   DL-PDSCH-Information      OPTIONAL
    },
    tdd                      NULL
},
dl-CommonInformation           DL-CommonInformation-r4      OPTIONAL,
dl-InformationPerRL-List       DL-InformationPerRL-List-r4  OPTIONAL
}

RadioBearerRelease-r5-IEs ::= SEQUENCE {
-- User equipment IEs
    integrityProtectionModeInfo  IntegrityProtectionModeInfo  OPTIONAL,
    cipheringModeInfo            CipheringModeInfo         OPTIONAL,
    activationTime               ActivationTime             OPTIONAL,
    new-U-RNTI                  U-RNTI                     OPTIONAL,
    new-C-RNTI                  C-RNTI                     OPTIONAL,
    new-DSCH-RNTI               DSCH-RNTI                 OPTIONAL,
    new-H-RNTI                  H-RNTI                     OPTIONAL,
    rrc-StateIndicator           RRC-StateIndicator        OPTIONAL,
    utran-DRX-CycleLengthCoeff  UTRAN-DRX-CycleLengthCoefficient  OPTIONAL,
-- Core network IEs
    cn-InformationInfo          CN-InformationInfo        OPTIONAL,
    signallingConnectionRelIndication  CN-DomainIdentity  OPTIONAL,
-- UTRAN mobility IEs
    ura-Identity                URA-Identity              OPTIONAL,
-- Radio bearer IEs
    rab-InformationReconfigList RAB-InformationReconfigList OPTIONAL,
    rb-InformationReleaseList   RB-InformationReleaseList  OPTIONAL,
    rb-InformationAffectedList  RB-InformationAffectedList-r5  OPTIONAL,
    dl-CounterSynchronisationInfo DL-CounterSynchronisationInfo-r5  OPTIONAL,
-- Transport channel IEs
    ul-CommonTransChInfo        UL-CommonTransChInfo-r4  OPTIONAL,
    ul-deletedTransChInfoList   UL-DeletedTransChInfoList  OPTIONAL,
    ul-AddReconfTransChInfoList UL-AddReconfTransChInfoList  OPTIONAL,
    modeSpecificTransChInfo     CHOICE {
        fdd                      SEQUENCE {
            cpch-SetID            CPCH-SetID              OPTIONAL,
            addReconfTransChDRAC-Info DRAC-StaticInformationList  OPTIONAL
        },
        tdd                      NULL
    }
    dl-CommonTransChInfo        DL-CommonTransChInfo-r4  OPTIONAL,
    dl-DeletedTransChInfoList   DL-DeletedTransChInfoList-r5  OPTIONAL,
    dl-AddReconfTransChInfoList DL-AddReconfTransChInfoList-r5  OPTIONAL,
-- Physical channel IEs
    frequencyInfo               FrequencyInfo            OPTIONAL,
    maxAllowedUL-TX-Power      MaxAllowedUL-TX-Power      OPTIONAL,
    ul-ChannelRequirement      UL-ChannelRequirement-r5  OPTIONAL,
    modeSpecificPhysChInfo     CHOICE {
        fdd                      SEQUENCE {
            dl-PDSCH-Information   DL-PDSCH-Information      OPTIONAL
        },
        tdd                      NULL
    }
    dl-HSPDSCH-Information     DL-HSPDSCH-Information      OPTIONAL,
    dl-CommonInformation        DL-CommonInformation-r5  OPTIONAL,
    dl-InformationPerRL-List   DL-InformationPerRL-List-r5  OPTIONAL
}

RadioBearerRelease-v6xyext-IEs ::= SEQUENCE {
-- Core network IEs
    plmn-Identity              PLMN-Identity            OPTIONAL,
-- Physical channel IEs
    harq-Preamble-Mode         HARQ-Preamble-Mode        OPTIONAL,
-- MBMS IEs
    mbms-FLCAplicabilityInfo   MBMS-FLCAplicabilityInfo-r6,
    mbms-RB-ListReleasedToChangeTransferMode  RB-InformationReleaseList  OPTIONAL
}

RadioBearerRelease-r6-IEs ::= SEQUENCE {
-- User equipment IEs
    integrityProtectionModeInfo  IntegrityProtectionModeInfo  OPTIONAL,
    cipheringModeInfo            CipheringModeInfo         OPTIONAL,
    activationTime               ActivationTime             OPTIONAL,
    new-U-RNTI                  U-RNTI                     OPTIONAL,
    new-C-RNTI                  C-RNTI                     OPTIONAL,
}

```

new-DSCH-RNTI	DSCH-RNTI	OPTIONAL,
new-H-RNTI	H-RNTI	OPTIONAL,
new-E-RNTI	E-RNTI	OPTIONAL,
rrc-StateIndicator	RRC-StateIndicator,	
utran-DRX-CycleLengthCoeff	UTRAN-DRX-CycleLengthCoefficient	OPTIONAL,
-- Core network IEs		
cn-InformationInfo	CN-InformationInfo	OPTIONAL,
plmn-Identity	PLMN-Identity	OPTIONAL,
signallingConnectionRelIndication	CN-DomainIdentity	OPTIONAL,
-- UTRAN mobility IEs		
ura-Identity	URA-Identity	OPTIONAL,
-- Radio bearer IEs		
rab-InformationReconfigList	RAB-InformationReconfigList	OPTIONAL,
rb-InformationReleaseList	RB-InformationReleaseList,	
rb-InformationAffectedList	RB-InformationAffectedList-r6	OPTIONAL,
dl-CounterSynchronisationInfo	DL-CounterSynchronisationInfo-r5	OPTIONAL,
-- Transport channel IEs		
ul-CommonTransChInfo	UL-CommonTransChInfo-r4	OPTIONAL,
ul-deletedTransChInfoList	UL-DeletedTransChInfoList-r6	OPTIONAL,
ul-AddReconfTransChInfoList	UL-AddReconfTransChInfoList-r6	OPTIONAL,
modeSpecificTransChInfo	CHOICE {	
fdd	SEQUENCE {	
cpch-SetID	CPCH-SetID	OPTIONAL,
addReconfTransChDRAC-Info	DRAC-StaticInformationList	OPTIONAL
},		
tdd	NULL	
}		OPTIONAL,
dl-CommonTransChInfo	DL-CommonTransChInfo-r4	OPTIONAL,
dl-DeletedTransChInfoList	DL-DeletedTransChInfoList-r5	OPTIONAL,
dl-AddReconfTransChInfoList	DL-AddReconfTransChInfoList-r5	OPTIONAL,
-- Physical channel IEs		
frequencyInfo	FrequencyInfo	OPTIONAL,
maxAllowedUL-TX-Power	MaxAllowedUL-TX-Power	OPTIONAL,
ul-ChannelRequirement	UL-ChannelRequirement-r6	OPTIONAL,
ul-EDCH-Information	UL-EDCH-Information-r6	OPTIONAL,
modeSpecificPhysChInfo	CHOICE {	
fdd	SEQUENCE {	
dl-PDSCH-Information	DL-PDSCH-Information	OPTIONAL
},		
tdd	NULL	
},		
dl-HSPDSCH-Information	DL-HSPDSCH-Information	OPTIONAL,
dl-CommonInformation	DL-CommonInformation-r5	OPTIONAL,
dl-InformationPerRL-List	DL-InformationPerRL-List-r6	OPTIONAL,
-- MBMS IEs		
mbms-FLCAplicabilityInfo	MBMS-FLCAplicabilityInfo-r6,	
mbms-RB-ListReleasedToChangeTransferMode		
	RB-InformationReleaseList	OPTIONAL

}

-- ****

-- RADIO BEARER RELEASE COMPLETE

--

-- ****

RadioBearerReleaseComplete ::= SEQUENCE {

-- User equipment IEs		
rrc-TransactionIdentifier	RRC-TransactionIdentifier,	
ul-IntegProtActivationInfo	IntegrityProtActivationInfo	OPTIONAL,
-- TABULAR: UL-TimingAdvance is applicable for TDD mode only.		
ul-TimingAdvance	UL-TimingAdvance	OPTIONAL,
-- Radio bearer IEs		
count-C-ActivationTime	ActivationTime	OPTIONAL,
-- dummy is not used in this version of the specification and		
-- it should be ignored by the receiver.		
dummy	RB-ActivationTimeInfoList	OPTIONAL,
ul-CounterSynchronisationInfo	UL-CounterSynchronisationInfo	OPTIONAL,
laterNonCriticalExtensions	SEQUENCE {	
-- Container for additional R99 extensions		
radioBearerReleaseComplete-r3-add-ext	BIT STRING	OPTIONAL,
nonCriticalExtensions	SEQUENCE {}	OPTIONAL
}	OPTIONAL	

}

-- ****

-- RADIO BEARER RELEASE FAILURE

```

-- ****
-- RadioBearerReleaseFailure ::= SEQUENCE {
  -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    failureCause                  FailureCauseWithProtErr,
  -- Radio bearer IEs
    potentiallySuccessfulBearerList RB-IdentityList
    laterNonCriticalExtensions   SEQUENCE {
      -- Container for additional R99 extensions
      radioBearerReleaseFailure-r3-add-ext   BIT STRING      OPTIONAL,
      nonCriticalExtensions      SEQUENCE {}      OPTIONAL
    } OPTIONAL
}

-- ****
-- RADIO BEARER SETUP
-- ****

RadioBearerSetup ::= CHOICE {
  r3
    SEQUENCE {
      radioBearerSetup-r3           RadioBearerSetup-r3-IEs,
      v3a0NonCriticalExtensions   SEQUENCE {
        radioBearerSetup-v3a0ext     RadioBearerSetup-v3a0ext,
        laterNonCriticalExtensions SEQUENCE {
          -- Container for additional R99 extensions
          radioBearerSetup-r3-add-ext BIT STRING      OPTIONAL,
          v4b0NonCriticalExtensions  SEQUENCE {
            radioBearerSetup-v4b0ext     RadioBearerSetup-v4b0ext-IEs,
            v590NonCriticalExtensions  SEQUENCE {
              radioBearerSetup-v590ext     RadioBearerSetup-v590ext-IEs,
              v6xyNonCriticalExtensions  SEQUENCE {
                radioBearerSetup-v6xyext     RadioBearerSetup-v6xyext-IEs,
                nonCriticalExtensions      SEQUENCE {}      OPTIONAL
              } OPTIONAL
            } OPTIONAL
          } OPTIONAL
        } OPTIONAL
      } OPTIONAL
    } OPTIONAL
  },
  later-than-r3
    SEQUENCE {
      rrc-TransactionIdentifier      RRC-TransactionIdentifier,
      criticalExtensions            CHOICE {
        r4
          SEQUENCE {
            radioBearerSetup-r4           RadioBearerSetup-r4-IEs,
            v4d0NonCriticalExtensions   SEQUENCE {
              -- Container for adding non critical extensions after freezing REL-5
              radioBearerSetup-r4-add-ext  BIT STRING      OPTIONAL,
              v590NonCriticalExtensions  SEQUENCE {
                radioBearerSetup-v590ext     RadioBearerSetup-v590ext-IEs,
                v6xyNonCriticalExtensions  SEQUENCE {
                  radioBearerSetup-v6xyext     RadioBearerSetup-v6xyext-IEs,
                  nonCriticalExtensions      SEQUENCE {}      OPTIONAL
                } OPTIONAL
              } OPTIONAL
            } OPTIONAL
          } OPTIONAL
        },
        criticalExtensions            CHOICE {
          r5
            SEQUENCE {
              radioBearerSetup-r5           RadioBearerSetup-r5-IEs,
              -- Container for adding non critical extensions after freezing REL-6
              radioBearerSetup-r5-add-ext  BIT STRING      OPTIONAL,
              v6xyNonCriticalExtensions  SEQUENCE {
                radioBearerSetup-v6xyext     RadioBearerSetup-v6xyext-IEs,
                nonCriticalExtensions      SEQUENCE {}      OPTIONAL
              } OPTIONAL
            },
            criticalExtensions          CHOICE {
              r6
                SEQUENCE {
                  radioBearerSetup-r6           RadioBearerSetup-r6-IEs,
                  -- Container for adding non critical extensions after freezing REL-7
                  radioBearerSetup-r6-add-ext  BIT STRING      OPTIONAL,
                  nonCriticalExtensions      SEQUENCE {}      OPTIONAL
                },
                criticalExtensions          SEQUENCE {}
              }
            }
          }
        }
      }
    }
}

```

```

| _____ }
|
    }

}

RadioBearerSetup-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
        rrc-TransactionIdentifier          RRC-TransactionIdentifier,
        integrityProtectionModeInfo      IntegrityProtectionModeInfo
        cipheringModeInfo                CipheringModeInfo
        activationTime                   ActivationTime
        new-U-RNTI                      U-RNTI
        new-C-RNTI                      C-RNTI
        rrc-StateIndicator               RRC-StateIndicator,
        utran-DRX-CycleLengthCoeff      UTRAN-DRX-CycleLengthCoefficient
    -- UTRAN mobility IEs
        ura-Identity                    URA-Identity
    -- Core network IEs
        cn-InformationInfo              CN-InformationInfo
    -- Radio bearer IEs
        srb-InformationSetupList       SRB-InformationSetupList
        rab-InformationSetupList       RAB-InformationSetupList
        rb-InformationAffectedList     RB-InformationAffectedList
        dl-CounterSynchronisationInfo DL-CounterSynchronisationInfo
    -- Transport channel IEs
        ul-CommonTransChInfo           UL-CommonTransChInfo
        ul-deletedTransChInfoList      UL-DeletedTransChInfoList
        ul-AddReconfTransChInfoList    UL-AddReconfTransChInfoList
        modeSpecificTransChInfo
            fdd                         CHOICE {
                cpch-SetID                 SEQUENCE {
                    cpch-SetID               CPCH-SetID
                    addReconfTransChDRAC-Info DRAC-StaticInformationList
                },
                tdd                         NULL
            }
            dl-CommonTransChInfo         DL-CommonTransChInfo
            dl-DeletedTransChInfoList   DL-DeletedTransChInfoList
            dl-AddReconfTransChInfoList DL-AddReconfTransChInfoList
    -- Physical channel IEs
        frequencyInfo                 FrequencyInfo
        maxAllowedUL-TX-Power         MaxAllowedUL-TX-Power
        ul-ChannelRequirement         UL-ChannelRequirement
        modeSpecificPhysChInfo
            fdd                         CHOICE {
                dl-PDSCH-Information    SEQUENCE {
                    dl-PDSCH-Information
                },
                tdd                         NULL
            },
            dl-CommonInformation        DL-CommonInformation
            dl-InformationPerRL-List    DL-InformationPerRL-List
        }
    }

RadioBearerSetup-v3a0ext ::= SEQUENCE {
    new-DSCH-RNTI                  DSCH-RNTI
}                                         OPTIONAL

RadioBearerSetup-v4b0ext-IEs ::= SEQUENCE {
    -- Physical channel IEs
        -- ssdt-UL extends SSDT-Information, which is included in
        -- DL-CommonInformation. FDD only.
        ssdt-UL-r4                     SSDT-UL
        -- The order of the RLs in IE cell-id-PerRL-List is the same as
        -- in IE DL-InformationPerRL-List included in this message
        cell-id-PerRL-List              CellIdentity-PerRL-List
}                                         OPTIONAL

RadioBearerSetup-v590ext-IEs ::= SEQUENCE {
    -- Physical channel IEs
        dl-TPC-PowerOffsetPerRL-List  DL-TPC-PowerOffsetPerRL-List
}                                         OPTIONAL

RadioBearerSetup-r4-IEs ::= SEQUENCE {
    -- User equipment IEs
        integrityProtectionModeInfo  IntegrityProtectionModeInfo
        cipheringModeInfo             CipheringModeInfo
        activationTime                ActivationTime
        new-U-RNTI                   U-RNTI
}                                         OPTIONAL,

```

```

new-C-RNTI                               C-RNTI                           OPTIONAL,
new-DSCH-RNTI                            DSCH-RNTI                         OPTIONAL,
rrc-StateIndicator                      RRC-StateIndicator,                OPTIONAL,
utran-DRX-CycleLengthCoeff              UTRAN-DRX-CycleLengthCoefficient  OPTIONAL,
-- UTRAN mobility IEs                   URA-Identity                      OPTIONAL,
ura-Identity                            URA-Identity                      OPTIONAL,
-- Core network IEs                    cn-InformationInfo               OPTIONAL,
cn-InformationInfo                      CN-InformationInfo               OPTIONAL,
-- Radio bearer IEs                   srb-InformationSetupList          SRB-InformationSetupList        OPTIONAL,
rab-InformationSetupList                RAB-InformationSetupList-r4      OPTIONAL,
rb-InformationAffectedList             RB-InformationAffectedList       OPTIONAL,
dl-CounterSynchronisationInfo          DL-CounterSynchronisationInfo    OPTIONAL,
-- Transport channel IEs                ul-CommonTransChInfo-r4           UL-CommonTransChInfo-r4         OPTIONAL,
ul-deletedTransChInfoList              UL-DeletedTransChInfoList        OPTIONAL,
ul-AddReconfTransChInfoList            UL-AddReconfTransChInfoList      OPTIONAL,
modeSpecificTransChInfo                CHOICE {
    fdd                                SEQUENCE {
        cpch-SetID                     CPCH-SetID                      OPTIONAL,
        addReconfTransChDRAC-Info      DRAC-StaticInformationList     OPTIONAL
    },
    tdd                                NULL                            OPTIONAL
}
dl-CommonTransChInfo                  DL-CommonTransChInfo-r4           OPTIONAL,
dl-DeletedTransChInfoList             DL-DeletedTransChInfoList        OPTIONAL,
dl-AddReconfTransChInfoList           DL-AddReconfTransChInfoList-r4   OPTIONAL,
-- Physical channel IEs                frequencyInfo                  FrequencyInfo                  OPTIONAL,
maxAllowedUL-TX-Power                MaxAllowedUL-TX-Power           OPTIONAL,
ul-ChannelRequirement                UL-ChannelRequirement-r4        OPTIONAL,
modeSpecificPhysChInfo               CHOICE {
    fdd                                SEQUENCE {
        dl-PDSCH-Information          DL-PDSCH-Information            OPTIONAL
    },
    tdd                                NULL                            OPTIONAL
},
dl-CommonInformation                 DL-CommonInformation-r4          OPTIONAL,
dl-InformationPerRL-List             DL-InformationPerRL-List-r4     OPTIONAL
}

RadioBearerSetup-r5-IEs ::= SEQUENCE {
-- User equipment IEs
integrityProtectionModeInfo          IntegrityProtectionModeInfo      OPTIONAL,
cipheringModeInfo                   CipheringModeInfo               OPTIONAL,
activationTime                      ActivationTime                  OPTIONAL,
new-U-RNTI                           U-RNTI                          OPTIONAL,
new-C-RNTI                           C-RNTI                          OPTIONAL,
new-DSCH-RNTI                        DSCH-RNTI                      OPTIONAL,
new-H-RNTI                           H-RNTI                          OPTIONAL,
rrc-StateIndicator,                 RRC-StateIndicator,                OPTIONAL,
utran-DRX-CycleLengthCoeff          UTRAN-DRX-CycleLengthCoefficient  OPTIONAL,
-- UTRAN mobility IEs                   URA-Identity                      OPTIONAL,
ura-Identity                          URA-Identity                      OPTIONAL,
-- Core network IEs                    cn-InformationInfo               OPTIONAL,
cn-InformationInfo                  CN-InformationInfo               OPTIONAL,
-- Radio bearer IEs                   srb-InformationSetupList-r5      SRB-InformationSetupList-r5    OPTIONAL,
rab-InformationSetupList-r5          RAB-InformationSetupList-r5    OPTIONAL,
rb-InformationAffectedList-r5       RB-InformationAffectedList-r5   OPTIONAL,
dl-CounterSynchronisationInfo-r5    DL-CounterSynchronisationInfo-r5 OPTIONAL,
-- Transport channel IEs                ul-CommonTransChInfo-r4           UL-CommonTransChInfo-r4         OPTIONAL,
ul-deletedTransChInfoList-r5        UL-DeletedTransChInfoList-r5    OPTIONAL,
ul-AddReconfTransChInfoList-r5      UL-AddReconfTransChInfoList-r5   OPTIONAL,
modeSpecificTransChInfo             CHOICE {
    fdd                                SEQUENCE {
        cpch-SetID                     CPCH-SetID                      OPTIONAL,
        addReconfTransChDRAC-Info      DRAC-StaticInformationList     OPTIONAL
    },
    tdd                                NULL                            OPTIONAL
}
dl-CommonTransChInfo-r4              DL-CommonTransChInfo-r4           OPTIONAL,
dl-DeletedTransChInfoList-r5        DL-DeletedTransChInfoList-r5    OPTIONAL,
dl-AddReconfTransChInfoList-r5     DL-AddReconfTransChInfoList-r5   OPTIONAL,
-- Physical channel IEs                frequencyInfo                  FrequencyInfo                  OPTIONAL,
maxAllowedUL-TX-Power               MaxAllowedUL-TX-Power           OPTIONAL,

```

```

    ul-ChannelRequirement
    modeSpecificPhysChInfo
      fdd
        dl-PDSCH-Information
      },
      tdd
    },
    dl-HSPDSCH-Information
    dl-CommonInformation
    dl-InformationPerRL-List
}

RadioBearerSetup-v6xyext-IEs ::= SEQUENCE {
  -- Core network IEs
  plmn-Identity
  -- Physical channel IEs
  harq-Preamble-Mode
  -- Radio bearer IEs
  rab-InformationSetupList
  -- MBMS IEs
  mbms-FLCAplicabilityInfo
}

RadioBearerSetup-r6-IEs ::= SEQUENCE {
  -- User equipment IEs
  integrityProtectionModeInfo
  cipheringModeInfo
  activationTime
  new-U-RNTI
  new-C-RNTI
  new-DSCH-RNTI
  new-H-RNTI
  new-E-RNTI
  rrc-StateIndicator
  utran-DRX-CycleLengthCoeff
  -- UTRAN mobility IEs
  ura-Identity
  -- Core network IEs
  cn-InformationInfo
  plmn-Identity
  -- Radio bearer IEs
  srb-InformationSetupList
  rab-InformationSetupList
  rb-InformationAffectedList
  dl-CounterSynchronisationInfo
  -- Transport channel IEs
  ul-CommonTransChInfo
  ul-deletedTransChInfoList
  ul-AddReconfTransChInfoList
  modeSpecificTransChInfo
    CHOICE {
      fdd
        SEQUENCE {
          cpch-SetID
          addReconfTransChDRAC-Info
        },
      tdd
    }
    dl-CommonTransChInfo
    dl-DeletedTransChInfoList
    dl-AddReconfTransChInfoList
  -- Physical channel IEs
  frequencyInfo
  maxAllowedUL-TX-Power
  ul-ChannelRequirement
  ul-EDCH-Information
  modeSpecificPhysChInfo
    CHOICE {
      fdd
        SEQUENCE {
          dl-PDSCH-Information
        },
      tdd
    }
    dl-HSPDSCH-Information
    dl-CommonInformation
    dl-InformationPerRL-List
  -- MBMS IEs
  mbms-FLCAplicabilityInfo
}

```

-- ****

```

--  

-- RADIO BEARER SETUP COMPLETE  

--  

-- ****  

RadioBearerSetupComplete ::= SEQUENCE {  

    -- User equipment IEs  

        rrc-TransactionIdentifier      RRC-TransactionIdentifier,  

        ul-IntegProtActivationInfo   IntegrityProtActivationInfo      OPTIONAL,  

        -- TABULAR: UL-TimingAdvance is applicable for TDD mode only.  

        ul-TimingAdvance            UL-TimingAdvance      OPTIONAL,  

        start-Value                 START-Value      OPTIONAL,  

    -- Radio bearer IEs  

        count-C-ActivationTime       ActivationTime      OPTIONAL,  

        -- dummy is not used in this version of the specification and  

        -- it should be ignored by the receiver.  

        dummy                      RB-ActivationTimeInfoList      OPTIONAL,  

        ul-CounterSynchronisationInfo UL-CounterSynchronisationInfo      OPTIONAL,  

        laterNonCriticalExtensions  SEQUENCE {  

            -- Container for additional R99 extensions  

            radioBearerSetupComplete-r3-add-ext   BIT STRING      OPTIONAL,  

            nonCriticalExtensions           SEQUENCE {}      OPTIONAL  

        }  OPTIONAL  

}  

-- ****  

--  

-- RADIO BEARER SETUP FAILURE  

--  

-- ****  

RadioBearerSetupFailure ::= SEQUENCE {  

    -- User equipment IEs  

        rrc-TransactionIdentifier      RRC-TransactionIdentifier,  

        failureCause                  FailureCauseWithProtErr,  

    -- Radio bearer IEs  

        potentiallySuccessfulBearerList RB-IdentityList      OPTIONAL,  

        laterNonCriticalExtensions    SEQUENCE {  

            -- Container for additional R99 extensions  

            radioBearerSetupFailure-r3-add-ext   BIT STRING      OPTIONAL,  

            nonCriticalExtensions           SEQUENCE {}      OPTIONAL  

        }  OPTIONAL  

}  

-- ****  

--  

-- RRC CONNECTION REJECT  

--  

-- ****  

RRCConnectionReject ::= CHOICE {  

    r3                         SEQUENCE {  

        rrcConnectionReject-r3          RRCConnectionReject-r3-IES,  

        laterNonCriticalExtensions     SEQUENCE {  

            -- Container for additional R99 extensions  

            rrcConnectionReject-r3-add-ext   BIT STRING      OPTIONAL,  

            v6xyNonCriticalExtensions      SEQUENCE {  

                rrcConnectionReject-v6xyext   RRCConnectionReject-v6xyext-IES,  

                nonCriticalExtensions         SEQUENCE {}      OPTIONAL  

            }  OPTIONAL  

        }  OPTIONAL  

    },  

    later-than-r3               SEQUENCE {  

        initialUE-Identity           InitialUE-Identity,  

        rrc-TransactionIdentifier    RRC-TransactionIdentifier,  

        criticalExtensions           SEQUENCE {}  

    }  

}  

RRCConnectionReject-r3-IES ::= SEQUENCE {  

    -- TABULAR: Integrity protection shall not be performed on this message.  

    -- User equipment IEs  

        initialUE-Identity           InitialUE-Identity,  

        rrc-TransactionIdentifier    RRC-TransactionIdentifier,  

        rejectionCause               RejectionCause,  

        waitTime                     WaitTime,  

        redirectionInfo              RedirectionInfo      OPTIONAL  

}

```

```

RRCConnectionReject-v6xyext-IEs ::= SEQUENCE {
    redirectionInfo-v6xyext           GSM-TargetCellInfoList           OPTIONAL
}

-- ****
-- 
-- RRC CONNECTION RELEASE
-- 
-- ****

RRCConnectionRelease ::= CHOICE {
    r3          SEQUENCE {
        rrcConnectionRelease-r3           RRCConnectionRelease-r3-IEs,
        laterNonCriticalExtensions     SEQUENCE {
            -- Container for additional R99 extensions
            rrcConnectionRelease-r3-add-ext   BIT STRING      OPTIONAL,
            v6xyNonCriticalExtensions       SEQUENCE {
                rrcConnectionRelease-v6xyext   RRCConnectionRelease-v6xyext-IEs,
                nonCriticalExtensions        SEQUENCE {}      OPTIONAL
            } OPTIONAL
        } OPTIONAL
    } OPTIONAL
},
later-than-r3          SEQUENCE {
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    criticalExtensions            CHOICE {
        r4          SEQUENCE {
            rrcConnectionRelease-r4           RRCConnectionRelease-r4-IEs,
            v4d0NonCriticalExtensions       SEQUENCE {
                -- Container for adding non critical extensions after freezing REL-6
                rrcConnectionRelease-r4-add-ext   BIT STRING      OPTIONAL,
                v6xyNonCriticalExtensions       SEQUENCE {
                    rrcConnectionRelease-v6xyext   RRCConnectionRelease-v6xyext-IEs,
                    nonCriticalExtensions        SEQUENCE {}      OPTIONAL
                } OPTIONAL
            } OPTIONAL
        },
        criticalExtensions             SEQUENCE {}
    }
}
}

RRCConnectionRelease-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    -- n-308 is conditional on the UE state
    n-308                          N-308                         OPTIONAL,
    releaseCause                   ReleaseCause,
    rplmn-information              Rplmn-Information           OPTIONAL
}

RRCConnectionRelease-r4-IEs ::= SEQUENCE {
    -- User equipment IEs
    -- n-308 is conditional on the UE state.
    n-308                          N-308                         OPTIONAL,
    releaseCause                   ReleaseCause,
    rplmn-information              Rplmn-Information-r4           OPTIONAL
}

RRCConnectionRelease-v6xyext-IEs ::= SEQUENCE {
    redirectionInfo-v6xyext         RedirectionInfo-r6      OPTIONAL
}

-- ****
-- 
-- RRC CONNECTION RELEASE for CCCH
-- 
-- ****

RRCConnectionRelease-CCCH ::= CHOICE {
    r3          SEQUENCE {
        rrcConnectionRelease-CCCH-r3      RRCConnectionRelease-CCCH-r3-IEs,
        laterNonCriticalExtensions     SEQUENCE {
            -- Container for additional R99 extensions
            rrcConnectionRelease-CCCH-r3-add-ext   BIT STRING      OPTIONAL,
            nonCriticalExtensions        SEQUENCE {}      OPTIONAL
        } OPTIONAL
    } OPTIONAL
}

```

```

},
later-than-r3
    SEQUENCE {
        u-RNTI,
        rrc-TransactionIdentifier
        criticalExtensions
            CHOICE {
                r4
                    SEQUENCE {
                        rrcConnectionRelease-CCCH-r4    RRCCConnectionRelease-CCCH-r4-IEs,
                        v4d0NonCriticalExtensions     SEQUENCE {
                            -- Container for adding non critical extensions after freezing REL-5
                            rrcConnectionRelease-CCCH-r4-add-ext   BIT STRING      OPTIONAL,
                            nonCriticalExtensions      SEQUENCE {}      OPTIONAL
                        }
                    }
                },
                criticalExtensions      SEQUENCE {
                    -- TABULAR: CHOICE IdentityType (U-RNTI, GroupIdentity) is replaced with the
                    -- optional element groupIdentity, since the U-RNTI is mandatory in ASN.1.
                    -- In case CHOICE IdentityType is equal to GroupIdentity the value of the U-RNTI
                    -- shall be ignored by a UE complying with this version of the message.
                    groupIdentity      SEQUENCE ( SIZE (1 .. maxURNTI-Group) ) OF
                        GroupReleaseInformation      OPTIONAL,
                    criticalExtensions      CHOICE {
                        r5
                            SEQUENCE {
                                rrcConnectionRelease-CCCH-r5    RRCCConnectionRelease-CCCH-r5-IEs,
                                -- Container for adding non critical extensions after freezing REL-6
                                rrcConnectionRelease-CCCH-r5-add-ext   BIT STRING      OPTIONAL,
                                nonCriticalExtensions      SEQUENCE {} OPTIONAL
                            },
                            criticalExtensions      SEQUENCE {}
                        }
                    }
                }
            }
        }
    }

RRCConnectionRelease-CCCH-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    u-RNTI,
    -- The rest of the message is identical to the one sent on DCCH.
    rrcConnectionRelease      RRCCConnectionRelease-r3-IEs
}

RRCConnectionRelease-CCCH-r4-IEs ::= SEQUENCE {
    -- The rest of the message is identical to the one sent on DCCH.
    rrcConnectionRelease      RRCCConnectionRelease-r4-IEs
}

-- The R5 and R4 sequence of IEs are identical in this message
RRCConnectionRelease-CCCH-r5-IEs ::= RRCCConnectionRelease-CCCH-r4-IEs

-- ****
-- 
-- RRC CONNECTION RELEASE COMPLETE
-- 
-- ****

RRCCConnectionReleaseComplete ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    errorIndication      FailureCauseWithProtErr      OPTIONAL,
    laterNonCriticalExtensions      SEQUENCE {
        -- Container for additional R99 extensions
        rrcConnectionReleaseComplete-r3-add-ext   BIT STRING      OPTIONAL,
        nonCriticalExtensions      SEQUENCE {}      OPTIONAL
    }
}
-- ****
-- 
-- RRC CONNECTION REQUEST
-- 
-- ****

RRCCConnectionRequest ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    initialUE-Identity      InitialUE-Identity,
    establishmentCause      EstablishmentCause,
    -- protocolErrorIndicator is MD, but for compactness reasons no default value
}

```

```

-- has been assigned to it.
protocolErrorIndicator          ProtocolErrorIndicator,
-- Measurement IEs
measuredResultsOnRACH           MeasuredResultsOnRACH           OPTIONAL,
-- Non critical Extensions
v3d0NonCriticalExtensions       SEQUENCE {
    rRCConnectionRequest-v3d0ext   RRCConnectionRequest-v3d0ext-IEs,
-- Reserved for future non critical extension
v4b0NonCriticalExtensions       SEQUENCE {
    rrcConnectionRequest-v4b0ext  RRCConnectionRequest-v4b0ext-IEs,
    v590NonCriticalExtensions     SEQUENCE {
        rrcConnectionRequest-v590ext  RRCConnectionRequest-v590ext-IEs,
        -- Reserved for future non critical extension
        nonCriticalExtensions      SEQUENCE {}      OPTIONAL
    } OPTIONAL
} OPTIONAL
} OPTIONAL

RRCConnectionRequest-v3d0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    uESpecificBehaviourInformation1idle  UESpecificBehaviourInformation1idle  OPTIONAL
}

RRCConnectionRequest-v4b0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    accessStratumReleaseIndicator      AccessStratumReleaseIndicator
}

RRCConnectionRequest-v590ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    predefinedConfigStatusInfo        BOOLEAN
}

-- ****
-- 
-- RRC CONNECTION SETUP
-- 
-- ****

RRCConnectionSetup ::= CHOICE {
    r3                      SEQUENCE {
        rrcConnectionSetup-r3      RRCConnectionSetup-r3-IEs,
        laterNonCriticalExtensions SEQUENCE {
            -- Container for additional R99 extensions
            rrcConnectionSetup-r3-add-ext BIT STRING      OPTIONAL,
            v4b0NonCriticalExtensions SEQUENCE {
                rrcConnectionSetup-v4b0ext  RRCConnectionSetup-v4b0ext-IEs,
                v590NonCriticalExtensions SEQUENCE {
                    rrcConnectionSetup-v590ext  RRCConnectionSetup-v590ext-IEs,
                    nonCriticalExtensions    SEQUENCE {}      OPTIONAL
                } OPTIONAL
            } OPTIONAL
        } OPTIONAL
    } OPTIONAL
},
later-than-r3                  SEQUENCE {
    initialUE-Identity          InitialUE-Identity,
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    criticalExtensions          CHOICE {
        r4                      SEQUENCE {
            rrcConnectionSetup-r4  RRCConnectionSetup-r4-IEs,
            v4d0NonCriticalExtensions SEQUENCE {
                -- Container for adding non critical extensions after freezing REL-5
                rrcConnectionSetup-r4-add-ext BIT STRING      OPTIONAL,
                v590NonCriticalExtensions SEQUENCE {
                    rrcConnectionSetup-v590ext  RRCConnectionSetup-v590ext-IEs,
                    nonCriticalExtensions    SEQUENCE {}      OPTIONAL
                } OPTIONAL
            } OPTIONAL
        } OPTIONAL
    },
    criticalExtensions          CHOICE {
        r5                      SEQUENCE {
            rrcConnectionSetup-r5  RRCConnectionSetup-r5-IEs,
            -- Container for adding non critical extensions after freezing REL-6
            rrcConnectionSetup-r5-add-ext BIT STRING      OPTIONAL,
            nonCriticalExtensions    SEQUENCE {}      OPTIONAL
        },
        criticalExtensions        SEQUENCE {}
    }
}

```

```

        }
    }

RRCConnectionSetup-r3-IEs ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    initialUE-Identity           InitialUE-Identity,
    rrc-TransactionIdentifier     RRC-TransactionIdentifier,
    activationTime                ActivationTime           OPTIONAL,
    new-U-RNTI                   U-RNTI,
    new-c-RNTI                   C-RNTI                 OPTIONAL,
    rrc-StateIndicator            RRC-StateIndicator,
    utran-DRX-CycleLengthCoeff   UTRAN-DRX-CycleLengthCoefficient,
    -- TABULAR: If capabilityUpdateRequirement is not present, the default value
    -- defined in 10.3.3.2 shall be used.
    capabilityUpdateRequirement   CapabilityUpdateRequirement   OPTIONAL,
    -- Radio bearer IEs
    srb-InformationSetupList      SRB-InformationSetupList2,
    -- Transport channel IEs
    ul-CommonTransChInfo          UL-CommonTransChInfo       OPTIONAL,
    -- NOTE: ul-AddReconfTransChInfoList should be optional in later versions of
    -- this message
    ul-AddReconfTransChInfoList   UL-AddReconfTransChInfoList,
    dl-CommonTransChInfo          DL-CommonTransChInfo       OPTIONAL,
    -- NOTE: dl-AddReconfTransChInfoList should be optional in later versions
    -- of this message
    dl-AddReconfTransChInfoList   DL-AddReconfTransChInfoList,
    -- Physical channel IEs
    frequencyInfo                 FrequencyInfo           OPTIONAL,
    maxAllowedUL-TX-Power         MaxAllowedUL-TX-Power      OPTIONAL,
    ul-ChannelRequirement         UL-ChannelRequirement      OPTIONAL,
    dl-CommonInformation          DL-CommonInformation      OPTIONAL,
    dl-InformationPerRL-List      DL-InformationPerRL-List    OPTIONAL
}

RRCConnectionSetup-v4b0ext-IEs ::= SEQUENCE {
    capabilityUpdateRequirement-r4-ext  CapabilityUpdateRequirement-r4-ext  OPTIONAL,
    -- Physical channel IEs
    -- ssdt-UL extends SSDT-Information, which is included in
    -- DL-CommonInformation. FDD only.
    ssdt-UL-r4                    SSDT-UL                  OPTIONAL,
    -- The order of the RLs in IE cell-id-PerRL-List is the same as
    -- in IE DL-InformationPerRL-List included in this message
    cell-id-PerRL-List             CellIdentity-PerRL-List    OPTIONAL
}

RRCConnectionSetup-v590ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    systemSpecificCapUpdateReq    SystemSpecificCapUpdateReq-v590ext  OPTIONAL,
    -- Physical channel IEs
    dl-TPC-PowerOffsetPerRL-List  DL-TPC-PowerOffsetPerRL-List    OPTIONAL
}

RRCConnectionSetup-r4-IEs ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    activationTime                ActivationTime           OPTIONAL,
    new-U-RNTI                   U-RNTI,
    new-c-RNTI                   C-RNTI                 OPTIONAL,
    rrc-StateIndicator            RRC-StateIndicator,
    utran-DRX-CycleLengthCoeff   UTRAN-DRX-CycleLengthCoefficient,
    -- TABULAR: If capabilityUpdateRequirement is not present, the default value
    -- defined in 10.3.3.2 shall be used.
    capabilityUpdateRequirement   CapabilityUpdateRequirement-r4  OPTIONAL,
    -- Radio bearer IEs
    srb-InformationSetupList      SRB-InformationSetupList2,
    -- Transport channel IEs
    ul-CommonTransChInfo          UL-CommonTransChInfo-r4      OPTIONAL,
    ul-AddReconfTransChInfoList   UL-AddReconfTransChInfoList    OPTIONAL,
    dl-CommonTransChInfo          DL-CommonTransChInfo-r4      OPTIONAL,
    dl-AddReconfTransChInfoList   DL-AddReconfTransChInfoList-r4  OPTIONAL,
    -- Physical channel IEs
    frequencyInfo                 FrequencyInfo           OPTIONAL,
    maxAllowedUL-TX-Power         MaxAllowedUL-TX-Power      OPTIONAL,
    ul-ChannelRequirement         UL-ChannelRequirement-r4      OPTIONAL,
    dl-CommonInformation          DL-CommonInformation-r4      OPTIONAL,
    dl-InformationPerRL-List      DL-InformationPerRL-List-r4    OPTIONAL
}

```

```

}

RRCConnectionSetup-r5-IEs ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    activationTime          ActivationTime           OPTIONAL,
    new-U-RNTI              U-RNTI,                  OPTIONAL,
    new-c-RNTI              C-RNTI,                  OPTIONAL,
    rrc-StateIndicator       RRC-StateIndicator,
    utran-DRX-CycleLengthCoeff   UTRAN-DRX-CycleLengthCoefficient,
    -- TABULAR: If capabilityUpdateRequirement is not present, the default value
    -- defined in 10.3.3.2 shall be used.
    capabilityUpdateRequirement CapabilityUpdateRequirement-r5   OPTIONAL,
    -- Specification mode information
    specificationMode        CHOICE {
        complete             SEQUENCE {
            -- Radio bearer IEs
            srb-InformationSetupList SRB-InformationSetupList2,
            -- Transport channel IEs
            ul-CommonTransChInfo   UL-CommonTransChInfo-r4      OPTIONAL,
            ul-AddReconfTransChInfoList UL-AddReconfTransChInfoList OPTIONAL,
            dl-CommonTransChInfo   DL-CommonTransChInfo-r4      OPTIONAL,
            dl-AddReconfTransChInfoList DL-AddReconfTransChInfoList-r4  OPTIONAL
        },
        preconfiguration        SEQUENCE {
            -- All IEs that include an FDD/TDD choice are split in two IEs for this message,
            -- one for the FDD only elements and one for the TDD only elements, so that one
            -- FDD/TDD choice in this level is sufficient.
            preConfigMode         CHOICE {
                predefinedConfigIdentity PredefinedConfigIdentity,
                defaultConfig          SEQUENCE {
                    defaultConfigMode, DefaultConfigMode,
                    defaultConfigIdentity DefaultConfigIdentity-r5
                }
            }
        }
    },
    -- Physical channel IEs
    frequencyInfo           FrequencyInfo           OPTIONAL,
    maxAllowedUL-TX-Power MaxAllowedUL-TX-Power   OPTIONAL,
    ul-ChannelRequirement UL-ChannelRequirement-r4  OPTIONAL,
    dl-CommonInformation  DL-CommonInformation-r4  OPTIONAL,
    dl-InformationPerRL-List DL-InformationPerRL-List-r5bis OPTIONAL
}

-- ****
-- RRC CONNECTION SETUP COMPLETE
-- ****

RRCConnectionSetupComplete ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    startList                   STARTList,
    ue-RadioAccessCapability   UE-RadioAccessCapability   OPTIONAL,
    -- Other IEs
    ue-RATSpecificCapability  InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
    -- Non critical extensions
    v370NonCriticalExtensions SEQUENCE {
        rrcConnectionSetupComplete-v370ext RRCConnectionSetupComplete-v370ext,
        v380NonCriticalExtensions   SEQUENCE {
            rrcConnectionSetupComplete-v380ext RRCConnectionSetupComplete-v380ext-IEs,
            -- Reserved for future non critical extension
            v3a0NonCriticalExtensions  SEQUENCE {
                rrcConnectionSetupComplete-v3a0ext RRCConnectionSetupComplete-v3a0ext-IEs,
                laterNonCriticalExtensions SEQUENCE {
                    -- Container for additional R99 extensions
                    rrcConnectionSetupComplete-r3-add-ext   BIT STRING      OPTIONAL,
                    v3g0NonCriticalExtensions   SEQUENCE {
                        rrcConnectionSetupComplete-v3g0ext RRCConnectionSetupComplete-v3g0ext-IEs,
                        v4b0NonCriticalExtensions   SEQUENCE {
                            rrcConnectionSetupComplete-v4b0ext RRCConnectionSetupComplete-v4b0ext-IEs,
                            v590NonCriticalExtensions   SEQUENCE {
                                rrcConnectionSetupComplete-v590ext RRCConnectionSetupComplete-v590ext-IEs,
                                nonCriticalExtensions     SEQUENCE {}      OPTIONAL
                            }
                        }
                    }
                }
            }
        }
    }
}

```

```

        }
    }
}
}

RRCConnectionSetupComplete-v370ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v370ext     UE-RadioAccessCapability-v370ext     OPTIONAL
}

RRCConnectionSetupComplete-v380ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v380ext     UE-RadioAccessCapability-v380ext     OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext      DL-PhysChCapabilityFDD-v380ext
}

RRCConnectionSetupComplete-v3a0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3a0ext     UE-RadioAccessCapability-v3a0ext     OPTIONAL
}

RRCConnectionSetupComplete-v3g0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3g0ext     UE-RadioAccessCapability-v3g0ext     OPTIONAL
}

RRCConnectionSetupComplete-v4b0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v4b0ext     UE-RadioAccessCapability-v4b0ext     OPTIONAL
}

RRCConnectionSetupComplete-v590ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v590ext     UE-RadioAccessCapability-v590ext     OPTIONAL,
    -- Other IEs
    ue-RATSpecificCapability-v590ext   InterRAT-UE-RadioAccessCapability-v590ext   OPTIONAL
}

-- ****
-- 
-- RRC FAILURE INFO
-- 
-- ****

RRC-FailureInfo ::= CHOICE {
    r3                               SEQUENCE {
        rRC-FailureInfo-r3            RRC-FailureInfo-r3-IEs,
        laterNonCriticalExtensions   SEQUENCE {
            -- Container for additional R99 extensions
            rrc-FailureInfo-r3-add-ext BIT STRING     OPTIONAL,
            nonCriticalExtensions       SEQUENCE {} OPTIONAL
        } OPTIONAL
    },
    criticalExtensions                SEQUENCE {}
}

RRC-FailureInfo-r3-IEs ::= SEQUENCE {
    -- Non-RRC IEs
    failureCauseWithProtErr        FailureCauseWithProtErr
}

-- ****
-- 
-- RRC STATUS
-- 
-- ****

RRCStatus ::= SEQUENCE {
    -- Other IEs
    -- TABULAR: Identification of received message is nested in
    -- ProtocolErrorMoreInformation
    protocolErrorInformation         ProtocolErrorMoreInformation,
    laterNonCriticalExtensions      SEQUENCE {
        -- Container for additional R99 extensions
    }
}

```

```

        rrcStatus-r3-add-ext      BIT STRING      OPTIONAL,
        nonCriticalExtensions    SEQUENCE { }      OPTIONAL
    }
}

-- ****
-- SECURITY MODE COMMAND
-- ****

SecurityModeCommand ::= CHOICE {
    r3                      SEQUENCE {
        securityModeCommand-r3          SecurityModeCommand-r3-IEs,
        laterNonCriticalExtensions     SEQUENCE {
            -- Container for additional R99 extensions
            securityModeCommand-r3-add-ext   BIT STRING      OPTIONAL,
            nonCriticalExtensions         SEQUENCE { }      OPTIONAL
        }
        OPTIONAL
    },
    later-than-r3             SEQUENCE {
        rrc-TransactionIdentifier      RRC-TransactionIdentifier,
        criticalExtensions            SEQUENCE { }
    }
}

SecurityModeCommand-r3-IEs ::= SEQUENCE {
-- TABULAR: Integrity protection shall always be performed on this message.
-- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    securityCapability             SecurityCapability,
    cipheringModeInfo              CipheringModeInfo      OPTIONAL,
    integrityProtectionModeInfo   IntegrityProtectionModeInfo      OPTIONAL,
-- Core network IEs
    cn-DomainIdentity             CN-DomainIdentity,
-- Other IEs
    ue-SystemSpecificSecurityCap InterRAT-UE-SecurityCapList      OPTIONAL
}
}

-- ****
-- SECURITY MODE COMPLETE
-- ****

SecurityModeComplete ::= SEQUENCE {
-- TABULAR: Integrity protection shall always be performed on this message.

-- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    ul-IntegProtActivationInfo    IntegrityProtActivationInfo      OPTIONAL,
-- Radio bearer IEs
    rb-UL-CiphActivationTimeInfo RB-ActivationTimeInfoList      OPTIONAL,
    laterNonCriticalExtensions    SEQUENCE {
        -- Container for additional R99 extensions
        securityModeComplete-r3-add-ext   BIT STRING      OPTIONAL,
        nonCriticalExtensions         SEQUENCE { }      OPTIONAL
    }
    OPTIONAL
}

-- ****
-- SECURITY MODE FAILURE
-- ****

SecurityModeFailure ::= SEQUENCE {
-- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    failureCause                  FailureCauseWithProtErr,
    laterNonCriticalExtensions    SEQUENCE {
        -- Container for additional R99 extensions
        securityModeFailure-r3-add-ext   BIT STRING      OPTIONAL,
        nonCriticalExtensions         SEQUENCE { }      OPTIONAL
    }
    OPTIONAL
}
}

```

```

--  

-- SIGNALLING CONNECTION RELEASE  

--  

-- ****  

SignallingConnectionRelease ::= CHOICE {
    r3
        SEQUENCE {
            signallingConnectionRelease-r3    SignallingConnectionRelease-r3-IEs,
            laterNonCriticalExtensions      SEQUENCE {
                -- Container for additional R99 extensions
                signallingConnectionRelease-r3-add-ext   BIT STRING      OPTIONAL,
                nonCriticalExtensions           SEQUENCE {}      OPTIONAL
            } OPTIONAL
        },
        later-than-r3                  SEQUENCE {
            rrc-TransactionIdentifier     RRC-TransactionIdentifier,
            criticalExtensions           SEQUENCE {}
        }
}
SignallingConnectionRelease-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier     RRC-TransactionIdentifier,
    -- Core network IEs
    cn-DomainIdentity             CN-DomainIdentity
}

-- ****  

--  

-- SIGNALLING CONNECTION RELEASE INDICATION  

--  

-- ****  

SignallingConnectionReleaseIndication ::= SEQUENCE {
    -- Core network IEs
    cn-DomainIdentity             CN-DomainIdentity,
    laterNonCriticalExtensions    SEQUENCE {
        -- Container for additional R99 extensions
        signallingConnectionReleaseIndication-r3-add-ext   BIT STRING      OPTIONAL,
        nonCriticalExtensions         SEQUENCE {}      OPTIONAL
    } OPTIONAL
}

-- ****  

--  

-- SYSTEM INFORMATION for BCH  

--  

-- ****  

SystemInformation-BCH ::= SEQUENCE {
    -- Other information elements
    sfn-Prime                      SFN-Prime,
    payload                         CHOICE {
        noSegment                   NULL,
        firstSegment                 FirstSegment,
        subsequentSegment           SubsequentSegment,
        lastSegmentShort             LastSegmentShort,
        lastAndFirst                 SEQUENCE {
            lastSegmentShort          LastSegmentShort,
            firstSegment               FirstSegmentShort
        },
        lastAndComplete               SEQUENCE {
            lastSegmentShort          LastSegmentShort,
            completeSIB-List           CompleteSIB-List
        },
        lastAndCompleteAndFirst       SEQUENCE {
            lastSegmentShort          LastSegmentShort,
            completeSIB-List           CompleteSIB-List,
            firstSegment               FirstSegmentShort
        },
        completeSIB-List              CompleteSIB-List,
        completeAndFirst              SEQUENCE {
            completeSIB-List           CompleteSIB-List,
            firstSegment               FirstSegmentShort
        },
        completeSIB                  CompleteSIB,
        lastSegment                  LastSegment,
        spare5                       NULL,
    }
}

```

```

        spare4                  NULL,
        spare3                  NULL,
        spare2                  NULL,
        spare1                  NULL
    }
}

-- ****
-- SYSTEM INFORMATION for FACH
--
-- ****

SystemInformation-FACH ::= SEQUENCE {
    -- Other information elements
    payload                 CHOICE {
        noSegment             NULL,
        firstSegment          FirstSegment,
        subsequentSegment     SubsequentSegment,
        lastSegmentShort      LastSegmentShort,
        lastAndFirst           SEQUENCE {
            lastSegmentShort  LastSegmentShort,
            firstSegment       FirstSegmentShort
        },
        lastAndComplete         SEQUENCE {
            lastSegmentShort  LastSegmentShort,
            completeSIB-List   CompleteSIB-List
        },
        lastAndCompleteAndFirst SEQUENCE {
            lastSegmentShort  LastSegmentShort,
            completeSIB-List   CompleteSIB-List,
            firstSegment        FirstSegmentShort
        },
        completeSIB-List        CompleteSIB-List,
        completeAndFirst         SEQUENCE {
            completeSIB-List   CompleteSIB-List,
            firstSegment        FirstSegmentShort
        },
        completeSIB              CompleteSIB,
        lastSegment              LastSegment,
        spare5                  NULL,
        spare4                  NULL,
        spare3                  NULL,
        spare2                  NULL,
        spare1                  NULL
    }
}

-- ****
-- First segment
--
-- ****

FirstSegment ::= SEQUENCE {
    -- Other information elements
    sib-Type                SIB-Type,
    seg-Count               SegCount,
    sib-Data-fixed           SIB-Data-fixed
}

-- ****
-- First segment (short)
--
-- ****

FirstSegmentShort ::= SEQUENCE {
    -- Other information elements
    sib-Type                SIB-Type,
    seg-Count               SegCount,
    sib-Data-variable        SIB-Data-variable
}

-- ****
-- Subsequent segment
--

```

```

-- ****
SubsequentSegment ::=          SEQUENCE {
    -- Other information elements
    sib-Type                  SIB-Type,
    segmentIndex               SegmentIndex,
    sib-Data-fixed             SIB-Data-fixed
}

-- ****
-- Last segment
--
-- ****

LastSegment ::=          SEQUENCE {
    -- Other information elements
    sib-Type                  SIB-Type,
    segmentIndex               SegmentIndex,
    -- For sib-Data-fixed, in case the SIB data is less than 222 bits, padding
    -- shall be used. The same padding bits shall be used as defined in clause 12.1
    sib-Data-fixed             SIB-Data-fixed
}

LastSegmentShort ::=          SEQUENCE {
    -- Other information elements
    sib-Type                  SIB-Type,
    segmentIndex               SegmentIndex,
    sib-Data-variable          SIB-Data-variable
}

-- ****
-- Complete SIB
--
-- ****

CompleteSIB-List ::=          SEQUENCE (SIZE (1..maxSIBperMsg)) OF
                                CompleteSIBshort

CompleteSIB ::=          SEQUENCE {
    -- Other information elements
    sib-Type                  SIB-Type,
    -- For sib-Data-fixed, in case the SIB data is less than 226 bits, padding
    -- shall be used. The same padding bits shall be used as defined in clause 12.1
    sib-Data-fixed             BIT STRING (SIZE (226))
}

CompleteSIBshort ::=          SEQUENCE {
    -- Other information elements
    sib-Type                  SIB-Type,
    sib-Data-variable          SIB-Data-variable
}

-- ****
-- SYSTEM INFORMATION CHANGE INDICATION
--
-- ****

SystemInformationChangeIndication ::=      SEQUENCE {
    -- Other IEs
    bcch-ModificationInfo      BCCH-ModificationInfo,
    laterNonCriticalExtensions SEQUENCE {
        -- Container for additional R99 extensions
        systemInformationChangeIndication-r3-add-ext   BIT STRING      OPTIONAL,
        nonCriticalExtensions       SEQUENCE {}           OPTIONAL
    }                           OPTIONAL
}

-- ****
-- TRANSPORT CHANNEL RECONFIGURATION
--
-- ****

TransportChannelReconfiguration ::= CHOICE {
    r3                         SEQUENCE {

```

```

transportChannelReconfiguration-r3
    TransportChannelReconfiguration-r3-IEs,
v3a0NonCriticalExtensions      SEQUENCE {
    transportChannelReconfiguration-v3a0ext
        TransportChannelReconfiguration-v3a0ext,
    laterNonCriticalExtensions     SEQUENCE {
        -- Container for additional R99 extensions
        transportChannelReconfiguration-r3-add-ext      BIT STRING      OPTIONAL,
v4b0NonCriticalExtensions      SEQUENCE {
        transportChannelReconfiguration-v4b0ext
            TransportChannelReconfiguration-v4b0ext-IEs,
v590NonCriticalExtensions      SEQUENCE {
        transportChannelReconfiguration-v590ext
            TransportChannelReconfiguration-v590ext-IEs,
v6xyNonCriticalExtensions      SEQUENCE {
        transportChannelReconfiguration-v6xyext
            TransportChannelReconfiguration-v6xyext-IEs,
        nonCriticalExtensions      SEQUENCE {}      OPTIONAL
    }      OPTIONAL
}      OPTIONAL
}      OPTIONAL
},
later-than-r3      SEQUENCE {
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    criticalExtensions      CHOICE {
        r4      SEQUENCE {
            transportChannelReconfiguration-r4
                TransportChannelReconfiguration-r4-IEs,
v4d0NonCriticalExtensions      SEQUENCE {
        -- Container for adding non critical extensions after freezing REL-5
        transportChannelReconfiguration-r4-add-ext      BIT STRING      OPTIONAL,
v590NonCriticalExtensions      SEQUENCE {
            transportChannelReconfiguration-v590ext
                TransportChannelReconfiguration-v590ext-IEs,
v6xyNonCriticalExtensions      SEQUENCE {
            transportChannelReconfiguration-v6xyext
                TransportChannelReconfiguration-v6xyext-IEs,
        nonCriticalExtensions      SEQUENCE {}      OPTIONAL
    }      OPTIONAL
}      OPTIONAL
}      OPTIONAL
},
criticalExtensions      CHOICE {
    r5      SEQUENCE {
        transportChannelReconfiguration-r5
            TransportChannelReconfiguration-r5-IEs,
        -- Container for adding non critical extensions after freezing REL-6
        transportChannelReconfiguration-r5-add-ext      BIT STRING      OPTIONAL,
v6xyNonCriticalExtensions      SEQUENCE {
            transportChannelReconfiguration-v6xyext
                TransportChannelReconfiguration-v6xyext-IEs,
        nonCriticalExtensions      SEQUENCE {}      OPTIONAL
    }      OPTIONAL
},
criticalExtensions      CHOICE {
    r6      SEQUENCE {
        transportChannelReconfiguration-r6
            TransportChannelReconfiguration-r6-IEs,
        -- Container for adding non critical extensions after freezing REL-7
        transportChannelReconfiguration-r6-add-ext      BIT STRING      OPTIONAL,
        nonCriticalExtensions      SEQUENCE {}      OPTIONAL
    },
    criticalExtensions      SEQUENCE {}
},
}
}

TransportChannelReconfiguration-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    integrityProtectionModeInfo      IntegrityProtectionModeInfo      OPTIONAL,
    cipheringModeInfo      CipheringModeInfo      OPTIONAL,
    activationTime      ActivationTime      OPTIONAL,
    new-U-RNTI      U-RNTI      OPTIONAL,
}

```

```

new-C-RNTI                               C-RNTI                                OPTIONAL,
rrc-StateIndicator                         RRC-StateIndicator,                      OPTIONAL,
utran-DRX-CycleLengthCoeff               UTRAN-DRX-CycleLengthCoefficient        OPTIONAL,
-- Core network IEs
cn-InformationInfo                      CN-InformationInfo                     OPTIONAL,
-- UTRAN mobility IEs
ura-Identity                             URA-Identity                           OPTIONAL,
-- Radio bearer IEs
dl-CounterSynchronisationInfo           DL-CounterSynchronisationInfo          OPTIONAL,
-- Transport channel IEs
ul-CommonTransChInfo                    UL-CommonTransChInfo                  OPTIONAL,
ul-AddReconfTransChInfoList             UL-AddReconfTransChInfoList            OPTIONAL,
modeSpecificTransChInfo                 CHOICE {
    fdd                                SEQUENCE {
        cpch-SetID                      CPCH-SetID                            OPTIONAL,
        addReconfTransChDRAC-Info       DRAC-StaticInformationList           OPTIONAL
    },
    tdd                                NULL
}
dl-CommonTransChInfo                    DL-CommonTransChInfo                  OPTIONAL,
dl-AddReconfTransChInfoList             DL-AddReconfTransChInfoList            OPTIONAL,
-- Physical channel IEs
frequencyInfo                           FrequencyInfo                          OPTIONAL,
maxAllowedUL-TX-Power                 MaxAllowedUL-TX-Power                OPTIONAL,
ul-ChannelRequirement                 UL-ChannelRequirement                 OPTIONAL,
modeSpecificPhysChInfo                 CHOICE {
    fdd                                SEQUENCE {
        dl-PDSCH-Information          DL-PDSCH-Information                 OPTIONAL
    },
    tdd                                NULL
},
dl-CommonInformation                   DL-CommonInformation                  OPTIONAL,
dl-InformationPerRL-List              DL-InformationPerRL-List              OPTIONAL
}

TransportChannelReconfiguration-v3a0ext ::= SEQUENCE {
    new-DSCH-RNTI                      DSCH-RNTI                            OPTIONAL
}

TransportChannelReconfiguration-v4b0ext-IEs ::= SEQUENCE {
-- Physical channel IEs
    -- ssdt-UL extends SSDT-Information, which is included in
    -- DL-CommonInformation. FDD only.
    ssdt-UL-r4                          SSDT-UL                              OPTIONAL,
    -- The order of the RLs in IE cell-id-PerRL-List is the same as
    -- in IE DL-InformationPerRL-List included in this message
    cell-id-PerRL-List                  CellIdentity-PerRL-List             OPTIONAL
}

TransportChannelReconfiguration-v590ext-IEs ::= SEQUENCE {
-- Physical channel IEs
    dl-TPC-PowerOffsetPerRL-List      DL-TPC-PowerOffsetPerRL-List          OPTIONAL
}

TransportChannelReconfiguration-r4-IEs ::= SEQUENCE {
-- User equipment IEs
    integrityProtectionModeInfo       IntegrityProtectionModeInfo           OPTIONAL,
    cipheringModeInfo                 CipheringModeInfo                   OPTIONAL,
    activationTime                   ActivationTime                        OPTIONAL,
    new-U-RNTI                       U-RNTI                                OPTIONAL,
    new-C-RNTI                       C-RNTI                                OPTIONAL,
    new-DSCH-RNTI                    DSCH-RNTI                            OPTIONAL,
    rrc-StateIndicator               RRC-StateIndicator,                      OPTIONAL,
    utran-DRX-CycleLengthCoeff       UTRAN-DRX-CycleLengthCoefficient        OPTIONAL,
-- Core network IEs
    cn-InformationInfo              CN-InformationInfo                     OPTIONAL,
-- UTRAN mobility IEs
    ura-Identity                     URA-Identity                           OPTIONAL,
-- Radio bearer IEs
    dl-CounterSynchronisationInfo   DL-CounterSynchronisationInfo          OPTIONAL,
-- Transport channel IEs
    ul-CommonTransChInfo-r4          UL-CommonTransChInfo-r4              OPTIONAL,
    ul-AddReconfTransChInfoList     UL-AddReconfTransChInfoList            OPTIONAL,
    modeSpecificTransChInfo         CHOICE {
        fdd                                SEQUENCE {
            cpch-SetID                      CPCH-SetID                            OPTIONAL,
            addReconfTransChDRAC-Info       DRAC-StaticInformationList           OPTIONAL
        },
    }
}

```

```

        tdd                         NULL
    }
    dl-CommonTransChInfo          DL-CommonTransChInfo-r4           OPTIONAL,
    dl-AddReconfTransChInfoList   DL-AddReconfTransChInfoList-r4      OPTIONAL,
-- Physical channel IEs
    frequencyInfo                FrequencyInfo                  OPTIONAL,
    maxAllowedUL-TX-Power       MaxAllowedUL-TX-Power            OPTIONAL,
    ul-ChannelRequirement       UL-ChannelRequirement-r4         OPTIONAL,
    modeSpecificPhysChInfo
        fdd
            dl-PDSCH-Information DL-PDSCH-Information            OPTIONAL
        },
        tdd
    },
    dl-CommonInformation          DL-CommonInformation-r4           OPTIONAL,
    dl-InformationPerRL-List     DL-InformationPerRL-List-r4      OPTIONAL
}

TransportChannelReconfiguration-r5-IEs ::= SEQUENCE {
-- User equipment IEs
    integrityProtectionModeInfo IntegrityProtectionModeInfo    OPTIONAL,
    cipheringModeInfo             CipheringModeInfo           OPTIONAL,
    activationTime                ActivationTime              OPTIONAL,
    new-U-RNTI                   U-RNTI                      OPTIONAL,
    new-C-RNTI                   C-RNTI                      OPTIONAL,
    new-DSCH-RNTI                DSCH-RNTI                  OPTIONAL,
    new-H-RNTI                   H-RNTI                      OPTIONAL,
    rrc-StateIndicator            RRC-StateIndicator         OPTIONAL,
    utran-DRX-CycleLengthCoeff  UTRAN-DRX-CycleLengthCoefficient OPTIONAL,
-- Core network IEs
    cn-InformationInfo           CN-InformationInfo        OPTIONAL,
-- UTRAN mobility IEs
    ura-Identity                 URA-Identity               OPTIONAL,
-- Radio bearer IEs
    dl-CounterSynchronisationInfo DL-CounterSynchronisationInfo-r5 OPTIONAL,
-- Transport channel IEs
    ul-CommonTransChInfo          UL-CommonTransChInfo-r4           OPTIONAL,
    ul-AddReconfTransChInfoList   UL-AddReconfTransChInfoList      OPTIONAL,
    modeSpecificTransChInfo
        fdd
            cpch-SetID             CPCH-SetID                 OPTIONAL,
            addReconfTransChDRAC-Info DRAC-StaticInformationList OPTIONAL
        },
        tdd
    },
    dl-CommonTransChInfo          DL-CommonTransChInfo-r4           OPTIONAL,
    dl-AddReconfTransChInfoList   DL-AddReconfTransChInfoList-r5      OPTIONAL,
-- Physical channel IEs
    frequencyInfo                FrequencyInfo                  OPTIONAL,
    maxAllowedUL-TX-Power       MaxAllowedUL-TX-Power            OPTIONAL,
    ul-ChannelRequirement       UL-ChannelRequirement-r5         OPTIONAL,
    modeSpecificPhysChInfo
        fdd
            dl-PDSCH-Information DL-PDSCH-Information            OPTIONAL
        },
        tdd
    },
    dl-HSPDSCH-Information        DL-HSPDSCH-Information        OPTIONAL,
    dl-CommonInformation          DL-CommonInformation-r5           OPTIONAL,
    dl-InformationPerRL-List     DL-InformationPerRL-List-r5      OPTIONAL
}

TransportChannelReconfiguration-v6xyext-IEs ::= SEQUENCE {
-- Core network IEs
    plmn-Identity                PLMN-Identity               OPTIONAL,
-- Physical channel IEs
    harq-Preamble-Mode           HARQ-Preamble-Mode          OPTIONAL,
-- MBMS IEs
    mbms-FLCAplicabilityInfo     MBMS-FLCAplicabilityInfo-r6
}

TransportChannelReconfiguration-r6-IEs ::= SEQUENCE {
-- User equipment IEs
    integrityProtectionModeInfo IntegrityProtectionModeInfo    OPTIONAL,
    cipheringModeInfo             CipheringModeInfo           OPTIONAL,
    activationTime                ActivationTime              OPTIONAL,
    new-U-RNTI                   U-RNTI                      OPTIONAL,
    new-C-RNTI                   C-RNTI                      OPTIONAL,
}

```

```

new-DSCH-RNTI           DSCH-RNTI           OPTIONAL,
new-H-RNTI              H-RNTI             OPTIONAL,
new-E-RNTI              E-RNTI             OPTIONAL,
rrc-StateIndicator       RRC-StateIndicator,
utran-DRX-CycleLengthCoeff UTRAN-DRX-CycleLengthCoefficient OPTIONAL,
-- Core network IEs
cn-InformationInfo     CN-InformationInfo OPTIONAL,
plmn-Identity          PLMN-Identity      OPTIONAL,
-- UTRAN mobility IEs
ura-Identity            URA-Identity      OPTIONAL,
-- Radio bearer IEs
dl-CounterSynchronisationInfo DL-CounterSynchronisationInfo-r5 OPTIONAL,
-- Transport channel IEs
ul-CommonTransChInfo    UL-CommonTransChInfo-r4 OPTIONAL,
ul-AddReconfTransChInfoList UL-AddReconfTransChInfoList-r6 OPTIONAL,
modeSpecificTransChInfo CHOICE {
    fdd                SEQUENCE {
        cpch-SetID      CPCH-SetID      OPTIONAL,
        addReconfTransChDRAC-Info DRAC-StaticInformationList OPTIONAL
    },
    tdd                NULL
},
dl-CommonTransChInfo    DL-CommonTransChInfo-r4 OPTIONAL,
dl-AddReconfTransChInfoList DL-AddReconfTransChInfoList-r5 OPTIONAL,
-- Physical channel IEs
frequencyInfo           FrequencyInfo      OPTIONAL,
maxAllowedUL-TX-Power   MaxAllowedUL-TX-Power OPTIONAL,
ul-ChannelRequirement   UL-ChannelRequirement-r6 OPTIONAL,
ul-EDCH-Information    UL-EDCH-Information-r6 OPTIONAL,
modeSpecificPhysChInfo CHOICE {
    fdd                SEQUENCE {
        dl-PDSCH-Information DL-PDSCH-Information OPTIONAL
    },
    tdd                NULL
},
dl-HSPDSCH-Information  DL-HSPDSCH-Information OPTIONAL,
dl-CommonInformation    DL-CommonInformation-r5 OPTIONAL,
dl-InformationPerRL-List DL-InformationPerRL-List-r6 OPTIONAL,
-- MBMS IEs
mbms-FLCAplicabilityInfo MBMS-FLCAplicabilityInfo-r6
}

-- *****
-- TRANSPORT CHANNEL RECONFIGURATION COMPLETE
-- *****
TransportChannelReconfigurationComplete ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    ul-IntegProtActivationInfo    IntegrityProtActivationInfo OPTIONAL,
    -- TABULAR: UL-TimingAdvance is applicable for TDD mode only.
    ul-TimingAdvance               UL-TimingAdvance           OPTIONAL,
    -- Radio bearer IEs
    count-C-ActivationTime        ActivationTime           OPTIONAL,
    -- dummy is not used in this version of the specification and
    -- it should be ignored by the receiver.
    dummy                         RB-ActivationTimeInfoList OPTIONAL,
    ul-CounterSynchronisationInfo UL-CounterSynchronisationInfo OPTIONAL,
    laterNonCriticalExtensions    SEQUENCE {
        -- Container for additional R99 extensions
        transportChannelReconfigurationComplete-r3-add-ext   BIT STRING    OPTIONAL,
        nonCriticalExtensions          SEQUENCE {}           OPTIONAL
    } OPTIONAL
}
-- *****
-- TRANSPORT CHANNEL RECONFIGURATION FAILURE
-- *****
TransportChannelReconfigurationFailure ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    failureCause                  FailureCauseWithProtErr,
    laterNonCriticalExtensions    SEQUENCE {

```

```

-- Container for additional R99 extensions
transportChannelReconfigurationFailure-r3-add-ext      BIT STRING      OPTIONAL,
nonCriticalExtensions          SEQUENCE {}           OPTIONAL
} OPTIONAL

}

-- ****
-- TRANSPORT FORMAT COMBINATION CONTROL in AM or UM RLC mode
--
-- ****

TransportFormatCombinationControl ::= SEQUENCE {
    -- rrc-TransactionIdentifier is always included in this version of the specification
    rrc-TransactionIdentifier      RRC-TransactionIdentifier      OPTIONAL,
    modeSpecificInfo               CHOICE {
        fdd                         NULL,
        tdd                         SEQUENCE {
            tfcs-ID                  TFCS-Identity      OPTIONAL
        }
    },
    dpch-TFCS-InUplink             TFC-Subset,
    activationTimeForTFCSubset     ActivationTime           OPTIONAL,
    tfc-ControlDuration           TFC-ControlDuration      OPTIONAL,
    laterNonCriticalExtensions    SEQUENCE {
        -- Container for additional R99 extensions
        transportFormatCombinationControl-r3-add-ext      BIT STRING      OPTIONAL,
        nonCriticalExtensions          SEQUENCE {}           OPTIONAL
    } OPTIONAL
}

-- ****
-- TRANSPORT FORMAT COMBINATION CONTROL FAILURE
--
-- ****

TransportFormatCombinationControlFailure ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    failureCause                   FailureCauseWithProtErr,
    laterNonCriticalExtensions    SEQUENCE {
        -- Container for additional R99 extensions
        transportFormatCombinationControlFailure-r3-add-ext      BIT STRING      OPTIONAL,
        nonCriticalExtensions          SEQUENCE {}           OPTIONAL
    } OPTIONAL
}

-- ****
-- UE CAPABILITY ENQUIRY
--
-- ****

UECapabilityEnquiry ::= CHOICE {
    r3                         SEQUENCE {
        ueCapabilityEnquiry-r3          UECapabilityEnquiry-r3-IEs,
        laterNonCriticalExtensions     SEQUENCE {
            -- Container for additional R99 extensions
            ueCapabilityEnquiry-r3-add-ext      BIT STRING      OPTIONAL,
            v4b0NonCriticalExtensions       SEQUENCE {
                ueCapabilityEnquiry-v4b0ext      UECapabilityEnquiry-v4b0ext-IEs,
                v590NonCriticalExtensions       SEQUENCE {
                    ueCapabilityEnquiry-v590ext      UECapabilityEnquiry-v590ext-IEs,
                    nonCriticalExtensions         SEQUENCE {}           OPTIONAL
                }
            } OPTIONAL
        } OPTIONAL
    } OPTIONAL
},
later-than-r3           SEQUENCE {
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    criticalExtensions            SEQUENCE {}
}

UECapabilityEnquiry-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,

```

```

        capabilityUpdateRequirement      CapabilityUpdateRequirement
    }

UECapabilityEnquiry-v4b0ext-IEs ::= SEQUENCE {
    capabilityUpdateRequirement-r4-ext  CapabilityUpdateRequirement-r4-ext
}

UECapabilityEnquiry-v590ext-IEs ::= SEQUENCE {
    systemSpecificCapUpdateReq      SystemSpecificCapUpdateReq-v590ext
}

-- ****
-- 
-- UE CAPABILITY INFORMATION
-- 
-- ****

UECapabilityInformation ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier           OPTIONAL,
    ue-RadioAccessCapability       UE-RadioAccessCapability           OPTIONAL,
    -- Other IEs
    ue-RATSpecificCapability      InterRAT-UE-RadioAccessCapabilityList
    OPTIONAL,
    v370NonCriticalExtensions     SEQUENCE {
        ueCapabilityInformation-v370ext UECapabilityInformation-v370ext,
        v380NonCriticalExtensions     SEQUENCE {
            ueCapabilityInformation-v380ext      UECapabilityInformation-v380ext-IEs,
            v3a0NonCriticalExtensions          SEQUENCE {
                ueCapabilityInformation-v3a0ext      UECapabilityInformation-v3a0ext-IEs,
                laterNonCriticalExtensions        SEQUENCE {
                    -- Container for additional R99 extensions
                    ueCapabilityInformation-r3-add-ext   BIT STRING           OPTIONAL,
                    -- Reserved for future non critical extension
                    v4b0NonCriticalExtensions         SEQUENCE {
                        ueCapabilityInformation-v4b0ext      UECapabilityInformation-v4b0ext,
                        v590NonCriticalExtensions          SEQUENCE {
                            ueCapabilityInformation-v590ext      UECapabilityInformation-v590ext,
                            nonCriticalExtensions           SEQUENCE {}           OPTIONAL
                        }
                    }
                }
            }
        }
    }
    OPTIONAL
}
    OPTIONAL
}

UECapabilityInformation-v370ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v370ext      UE-RadioAccessCapability-v370ext           OPTIONAL
}

UECapabilityInformation-v380ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v380ext      UE-RadioAccessCapability-v380ext           OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext       DL-PhysChCapabilityFDD-v380ext
}

UECapabilityInformation-v3a0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3a0ext      UE-RadioAccessCapability-v3a0ext           OPTIONAL
}

UECapabilityInformation-v4b0ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v4b0ext      UE-RadioAccessCapability-v4b0ext           OPTIONAL
}

UECapabilityInformation-v590ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3g0ext      UE-RadioAccessCapability-v3g0ext           OPTIONAL,
    ue-RadioAccessCapability-v590ext      UE-RadioAccessCapability-v590ext           OPTIONAL,
    -- Other IEs
    ue-RATSpecificCapability-v590ext     InterRAT-UE-RadioAccessCapability-v590ext  OPTIONAL
}

-- ****

```

```

-- UE CAPABILITY INFORMATION CONFIRM
--
-- ****
UECapabilityInformationConfirm ::= CHOICE {
    r3           SEQUENCE {
        ueCapabilityInformationConfirm-r3
            UECapabilityInformationConfirm-r3-IEs,
        laterNonCriticalExtensions   SEQUENCE {
            -- Container for additional R99 extensions
            ueCapabilityInformationConfirm-r3-add-ext   BIT STRING      OPTIONAL,
            nonCriticalExtensions       SEQUENCE {}      OPTIONAL
        } OPTIONAL
    },
    later-than-r3          SEQUENCE {
        rrc-TransactionIdentifier   RRC-TransactionIdentifier,
        criticalExtensions         SEQUENCE {}
    }
}

UECapabilityInformationConfirm-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier   RRC-TransactionIdentifier
}

-- ****
-- UPLINK DIRECT TRANSFER
--
-- ****

UplinkDirectTransfer ::= SEQUENCE {
    -- Core network IEs
    cn-DomainIdentity           CN-DomainIdentity,
    nas-Message                  NAS-Message,
    -- Measurement IEs
    measuredResultsOnRACH        MeasuredResultsOnRACH      OPTIONAL,
    laterNonCriticalExtensions   SEQUENCE {
        -- Container for additional R99 extensions
        uplinkDirectTransfer-r3-add-ext   BIT STRING      OPTIONAL,
        nonCriticalExtensions       SEQUENCE {}      OPTIONAL
    } OPTIONAL
}

-- ****
-- UPLINK PHYSICAL CHANNEL CONTROL
--
-- ****

UplinkPhysicalChannelControl ::= CHOICE {
    r3           SEQUENCE {
        uplinkPhysicalChannelControl-r3 UplinkPhysicalChannelControl-r3-IEs,
        laterNonCriticalExtensions   SEQUENCE {
            -- Container for additional R99 extensions
            uplinkPhysicalChannelControl-r3-add-ext   BIT STRING      OPTIONAL,
            v4b0NonCriticalExtensions     SEQUENCE {
                uplinkPhysicalChannelControl-v4b0ext   UplinkPhysicalChannelControl-v4b0ext-IEs,
                -- Extension mechanism for non-release4 information
                noncriticalExtensions       SEQUENCE {}      OPTIONAL
            } OPTIONAL
        } OPTIONAL
    },
    later-than-r3          SEQUENCE {
        rrc-TransactionIdentifier   RRC-TransactionIdentifier,
        criticalExtensions         CHOICE {
            r4           SEQUENCE {
                uplinkPhysicalChannelControl-r4 UplinkPhysicalChannelControl-r4-IEs,
                v4d0NonCriticalExtensions     SEQUENCE {
                    -- Container for adding non critical extensions after freezing REL-5
                    uplinkPhysicalChannelControl-r4-add-ext   BIT STRING      OPTIONAL,
                    nonCriticalExtensions       SEQUENCE {}      OPTIONAL
                } OPTIONAL
            },
            criticalExtensions         CHOICE {
                r5           SEQUENCE {
                    uplinkPhysicalChannelControl-r5 UplinkPhysicalChannelControl-r5-IEs,

```

```

        -- Container for adding non critical extensions after freezing REL-6
        uplinkPhysicalChannelControl-r5-add-ext      BIT STRING      OPTIONAL,
        nonCriticalExtensions           SEQUENCE {} OPTIONAL
    },
    criticalExtensions           SEQUENCE {}
}
}

UplinkPhysicalChannelControl-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    -- Physical channel IEs
    ccTrCH-PowerControlInfo       CCTrCH-PowerControlInfo      OPTIONAL,
    timingAdvance                  UL-TimingAdvanceControl      OPTIONAL,
    alpha                         Alpha      OPTIONAL,
    specialBurstScheduling         SpecialBurstScheduling      OPTIONAL,
    prach-ConstantValue            ConstantValueTdd      OPTIONAL,
    pusch-ConstantValue            ConstantValueTdd      OPTIONAL
}

UplinkPhysicalChannelControl-v4b0ext-IEs ::= SEQUENCE {
    -- In case of TDD, openLoopPowerControl-IPDL-TDD is included instead of IE
    -- up-IPDL-Parameters in up-OTDOA-AssistanceData
    openLoopPowerControl-IPDL-TDD   OpenLoopPowerControl-IPDL-TDD-r4      OPTIONAL
}

UplinkPhysicalChannelControl-r4-IEs ::= SEQUENCE {
    -- Physical channel IEs
    ccTrCH-PowerControlInfo       CCTrCH-PowerControlInfo-r4      OPTIONAL,
    specialBurstScheduling         SpecialBurstScheduling      OPTIONAL,
    tddOption                      CHOICE {
        tdd384                   SEQUENCE {
            timingAdvance          UL-TimingAdvanceControl-r4      OPTIONAL,
            alpha                  Alpha      OPTIONAL,
            prach-ConstantValue     ConstantValueTdd      OPTIONAL,
            pusch-ConstantValue     ConstantValueTdd      OPTIONAL,
            openLoopPowerControl-IPDL-TDD   OpenLoopPowerControl-IPDL-TDD-r4      OPTIONAL
        },
        tdd128                   SEQUENCE {
            ul-SynchronisationParameters   UL-SynchronisationParameters-r4 OPTIONAL
        }
    }
}

UplinkPhysicalChannelControl-r5-IEs ::= SEQUENCE {
    -- Physical channel IEs
    ccTrCH-PowerControlInfo       CCTrCH-PowerControlInfo-r5      OPTIONAL,
    specialBurstScheduling         SpecialBurstScheduling      OPTIONAL,
    tddOption                      CHOICE {
        tdd384                   SEQUENCE {
            timingAdvance          UL-TimingAdvanceControl-r4      OPTIONAL,
            alpha                  Alpha      OPTIONAL,
            prach-ConstantValue     ConstantValueTdd      OPTIONAL,
            pusch-ConstantValue     ConstantValueTdd      OPTIONAL,
            openLoopPowerControl-IPDL-TDD   OpenLoopPowerControl-IPDL-TDD-r4      OPTIONAL,
            hs-SICH-PowerControl     HS-SICH-Power-Control-Info-TDD384      OPTIONAL
        },
        tdd128                   SEQUENCE {
            ul-SynchronisationParameters   UL-SynchronisationParameters-r4 OPTIONAL
        }
    }
}

-- ****
-- 
-- URA UPDATE
-- 
-- ****

URAUpdate ::= SEQUENCE {
    -- User equipment IEs
    u-RNTI                      U-RNTI,
    ura-UpdateCause                URA-UpdateCause,
    protocolErrorIndicator         ProtocolErrorIndicatorWithMoreInfo,
    laterNonCriticalExtensions     SEQUENCE {
        -- Container for additional R99 extensions
    }
}

```

```

        uraUpdate-r3-add-ext      BIT STRING      OPTIONAL,
        nonCriticalExtensions    SEQUENCE {}     OPTIONAL
    }

-- ****
-- 
-- URA UPDATE CONFIRM
-- 
-- ****

URAUpdateConfirm ::= CHOICE {
    r3           SEQUENCE {
        uraUpdateConfirm-r3          URAUpdateConfirm-r3-IEs,
        laterNonCriticalExtensions   SEQUENCE {
            -- Container for additional R99 extensions
            uraUpdateConfirm-r3-add-ext BIT STRING      OPTIONAL,
            nonCriticalExtensions     SEQUENCE {}     OPTIONAL
        } OPTIONAL
    },
    later-than-r3       SEQUENCE {
        rrc-TransactionIdentifier   RRC-TransactionIdentifier,
        criticalExtensions         CHOICE {
            r5           SEQUENCE {
                uraUpdateConfirm-r5          URAUpdateConfirm-r5-IEs,
                nonCriticalExtensions     SEQUENCE {}     OPTIONAL
            },
            criticalExtensions         SEQUENCE {}
        }
    }
}

URAUpdateConfirm-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    integrityProtectionModeInfo IntegrityProtectionModeInfo      OPTIONAL,
    cipheringModeInfo           CipheringModeInfo             OPTIONAL,
    new-U-RNTI                  U-RNTI                      OPTIONAL,
    new-C-RNTI                  C-RNTI                      OPTIONAL,
    rrc-StateIndicator          RRC-StateIndicator,
    utran-DRX-CycleLengthCoeff UTRAN-DRX-CycleLengthCoefficient  OPTIONAL,
    -- CN information elements
    cn-InformationInfo          CN-InformationInfo        OPTIONAL,
    -- UTRAN mobility IEs
    ura-Identity                 URA-Identity               OPTIONAL,
    -- Radio bearer IEs
    dl-CounterSynchronisationInfo DL-CounterSynchronisationInfo  OPTIONAL
}

URAUpdateConfirm-r5-IEs ::= SEQUENCE {
    -- User equipment IEs
    integrityProtectionModeInfo IntegrityProtectionModeInfo      OPTIONAL,
    cipheringModeInfo           CipheringModeInfo             OPTIONAL,
    new-U-RNTI                  U-RNTI                      OPTIONAL,
    new-C-RNTI                  C-RNTI                      OPTIONAL,
    rrc-StateIndicator          RRC-StateIndicator,
    utran-DRX-CycleLengthCoeff UTRAN-DRX-CycleLengthCoefficient  OPTIONAL,
    -- CN information elements
    cn-InformationInfo          CN-InformationInfo        OPTIONAL,
    -- UTRAN mobility IEs
    ura-Identity                 URA-Identity               OPTIONAL,
    -- Radio bearer IEs
    dl-CounterSynchronisationInfo DL-CounterSynchronisationInfo-r5  OPTIONAL
}

-- ****
-- 
-- URA UPDATE CONFIRM for CCCH
-- 
-- ****

URAUpdateConfirm-CCCH ::= CHOICE {
    r3           SEQUENCE {
        uraUpdateConfirm-CCCH-r3          URAUpdateConfirm-CCCH-r3-IEs,
        laterNonCriticalExtensions       SEQUENCE {
            -- Container for additional R99 extensions
            uraUpdateConfirm-CCCH-r3-add-ext BIT STRING      OPTIONAL,
            nonCriticalExtensions         SEQUENCE {}     OPTIONAL
        }
    }
}

```

```

        }   OPTIONAL
},
later-than-r3
    u-RNTI
    rrc-TransactionIdentifier
    criticalExtensions
}
}

URAUpdateConfirm-CCCH-r3-IEs ::= SEQUENCE {
-- User equipment IEs
    u-RNTI
-- The rest of the message is identical to the one sent on DCCH.
    uraUpdateConfirm
}
URAUpdateConfirm-r3-IEs

-- ****
-- UTRAN MOBILITY INFORMATION
-- ****

UTRANMobilityInformation ::= CHOICE {
r3
    SEQUENCE {
        utranMobilityInformation-r3      UTRANMobilityInformation-r3-IEs,
        v3a0NonCriticalExtensions      SEQUENCE {
            utranMobilityInformation-v3a0ext      UTRANMobilityInformation-v3a0ext-IEs,
            laterNonCriticalExtensions      SEQUENCE {
                -- Container for additional R99 extensions
                utranMobilityInformation-r3-add-ext    BIT STRING      OPTIONAL,
                v6xyNonCriticalExtensions      SEQUENCE {
                    utranMobilityInformation-v6xyext      UtranMobilityInformation-v6xyext-IEs,
                    nonCriticalExtensions      SEQUENCE {}      OPTIONAL
                }
                OPTIONAL
            }
            OPTIONAL
        }
        OPTIONAL
    }
},
later-than-r3
    SEQUENCE {
        rrc-TransactionIdentifier      RRC-TransactionIdentifier,
        criticalExtensions      CHOICE {
            r5
                SEQUENCE {
                    utranMobilityInformation-r5      UTRANMobilityInformation-r5-IEs,
                    v6xyNonCriticalExtensions      SEQUENCE {
                        utranMobilityInformation-v6xyext      UtranMobilityInformation-v6xyext-IEs,
                        nonCriticalExtensions      SEQUENCE {}      OPTIONAL
                    }
                    OPTIONAL
                },
                criticalExtensions      SEQUENCE {}
            }
        }
    }
}

UTRANMobilityInformation-r3-IEs ::= SEQUENCE {
-- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    integrityProtectionModeInfo      IntegrityProtectionModeInfo      OPTIONAL,
    cipheringModeInfo      CipheringModeInfo      OPTIONAL,
    new-U-RNTI
    new-C-RNTI
    ue-ConnTimersAndConstants
-- CN information elements
    cn-InformationInfo      CN-InformationInfoFull      OPTIONAL,
-- UTRAN mobility IEs
    ura-Identity      URA-Identity      OPTIONAL,
-- Radio bearer IEs
    dl-CounterSynchronisationInfo      DL-CounterSynchronisationInfo      OPTIONAL,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions      SEQUENCE {}      OPTIONAL
}

UTRANMobilityInformation-v3a0ext-IEs ::= SEQUENCE {
    ue-ConnTimersAndConstants-v3a0ext      UE-ConnTimersAndConstants-v3a0ext
}

UTRANMobilityInformation-r5-IEs ::= SEQUENCE {
-- User equipment IEs
    integrityProtectionModeInfo      IntegrityProtectionModeInfo      OPTIONAL,
    cipheringModeInfo      CipheringModeInfo      OPTIONAL,
}

```

```

        new-U-RNTI           U-RNTI           OPTIONAL,
        new-C-RNTI           C-RNTI           OPTIONAL,
        ue-ConnTimersAndConstants UE-ConnTimersAndConstants-r5 OPTIONAL,
-- CN information elements
        cn-InformationInfo   CN-InformationInfoFull OPTIONAL,
-- UTRAN mobility IEs
        ura-Identity         URA-Identity    OPTIONAL,
-- Radio bearer IEs
        dl-CounterSynchronisationInfo DL-CounterSynchronisationInfo-r5 OPTIONAL
}

UtranMobilityInformation-v6xyext-IEs ::= SEQUENCE {
    plmn-Identity          PLMN-Identity    OPTIONAL
}

-- *****
-- 
-- UTRAN MOBILITY INFORMATION CONFIRM
-- 
-- *****

UTRANMobilityInformationConfirm ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    ul-IntegProtActivationInfo     IntegrityProtActivationInfo    OPTIONAL,
    -- Radio bearer IEs
    count-C-ActivationTime         ActivationTime    OPTIONAL,
    -- dummy is not used in this version of the specification and
    -- it should be ignored by the receiver.
    dummy                          RB-ActivationTimeInfoList    OPTIONAL,
    ul-CounterSynchronisationInfo UL-CounterSynchronisationInfo    OPTIONAL,
    laterNonCriticalExtensions    SEQUENCE {
        -- Container for additional R99 extensions
        utranMobilityInformationConfirm-r3-add-ext   BIT STRING    OPTIONAL,
        nonCriticalExtensions       SEQUENCE {}    OPTIONAL
    }    OPTIONAL
}

-- *****
-- 
-- UTRAN MOBILITY INFORMATION FAILURE
-- 
-- *****

UTRANMobilityInformationFailure ::= SEQUENCE {
    -- UE information elements
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    failureCause                  FailureCauseWithProtErr,
    laterNonCriticalExtensions    SEQUENCE {
        -- Container for additional R99 extensions
        utranMobilityInformationFailure-r3-add-ext   BIT STRING    OPTIONAL,
        nonCriticalExtensions       SEQUENCE {}    OPTIONAL
    }    OPTIONAL
}

-- *****
-- 
-- MBMS ACCESS INFORMATION
-- 
-- *****

MBMSAccessInformation ::= SEQUENCE {
    -- Access Information IEs
    mbms-ServiceAccessInfoList    MBMS-ServiceAccessInfoList-r6,
    -- Non critical extensions
    nonCriticalExtensions        SEQUENCE {}    OPTIONAL
}

-- *****
-- 
-- MBMS COMMON PTM RB INFORMATION
-- 
-- *****

MBMSCommonPTMRBInformation ::= SEQUENCE {
    -- Common PTM RB Information IEs
    mbms-CommonRBInformationList MBMS-CommonRBInformationList-r6,
    mbms-TranspChInfoForEachTrCh MBMS-TranspChInfoForEachTrCh-r6,
}

```

```

        mbms-TranspChInfoForEachCCTrCh    MBMS-TranspChInfoForEachCCTrCh-r6,
        mbms-PhyChInformationList         MBMS-PhyChInformationList-r6,
-- Non critical extensions           nonCriticalExtensions      SEQUENCE {}      OPTIONAL
}

-- ****
--
-- MBMS CURRENT CELL PTM RB INFORMATION
--
-- ****

MBMSCurrentCellPTMRBInformation ::= SEQUENCE {
  -- Current Cell PTM RB Information IEs
  mbms-CurrentCell-SCCPCHList      MBMS-CurrentCell-SCCPCHList-r6      OPTIONAL,
  mbms-SIBType5-SCCPCHList         MBMS-SIBType5-SCCPCHList-r6      OPTIONAL,
  -- Non critical extensions         nonCriticalExtensions      SEQUENCE {}      OPTIONAL
}

-- ****
--
-- MBMS GENERAL INFORMATION
--
-- ****

MBMSGeneralInformation ::= SEQUENCE {
  -- MBMS General Information IEs
  mbms-PreferredFrequencyInfo     MBMS-PreferredFrequencyList-r6      OPTIONAL,
  mbms-TimersAndCounters          MBMS-TimersAndCounters-r6,
  michConfigurationInfo           MBMS-MICHConfigurationInfo-r6,
  cellGroupIdentity                MBMS-CellGroupIdentity-r6,
  mschDefaultConfigurationInfo    MBMS-MSCHConfigurationInfo-r6      OPTIONAL,
  defaultLlCombiningConfigInfo   MBMS-DefaultLlCombiningConfigInfo-r6  OPTIONAL,
  -- Non critical extensions         nonCriticalExtensions      SEQUENCE {}      OPTIONAL
}

-- ****
--
-- MBMS MODIFICATION REQUEST
--
-- ****

MBMSModificationRequest ::= SEQUENCE {
  -- MBMS Modification Request IEs
  mbms-PreferredFreqRequest       MBMS-PreferredFreqRequest-r6      OPTIONAL,
  rb-InformationReleaseList       RB-InformationReleaseList      OPTIONAL,
  -- Non critical extensions         nonCriticalExtensions      SEQUENCE {}      OPTIONAL
}

-- ****
--
-- MBMS MODIFIED SERVICES INFORMATION
--
-- ****

MBMSModifiedServicesInformation ::= SEQUENCE {
  -- MBMS Modified Services Information IEs
  modifiedServiceList             MBMS-ModifiedServiceList-r6      OPTIONAL,
  endOfModifiedMCCHInformation    INTEGER (0)                      OPTIONAL, -- FFS
  -- Non critical extensions         nonCriticalExtensions      SEQUENCE {}      OPTIONAL
}

-- ****
--
-- MBMS NEIGHBOURING CELL PTM RB INFORMATION
--
-- ****

MBMSNeighbouringCellPTMRBInformation ::= SEQUENCE {
  -- MBMS Neighbouring Cell PTM RB Information IEs
  neighbouringCellIdentity         INTEGER (1), -- FFS
  neighbouringCellSCCPCHList       MBMS-NeighbouringCellSCCPCHList-r6,
  -- Non critical extensions         nonCriticalExtensions      SEQUENCE {}      OPTIONAL
}

```

```

}

-- ****
-- MBMS SCHEDULING INFORMATION
--
-- ****

MBMSSchedulingInformation ::= SEQUENCE {
    -- MBMS Scheduling Information IEs
    serviceSchedulingInfoList      MBMS-ServiceSchedulingInfoList-r6,
    -- Non critical extensions
    nonCriticalExtensions         SEQUENCE {}      OPTIONAL
}

-- ****
-- MBMS UNMODIFIED SERVICES INFORMATION
--
-- ****

MBMSUnmodifiedServicesInformation ::= SEQUENCE {
    -- IEs
    unmodifiedServiceList          MBMS-UnmodifiedServiceList-r6      OPTIONAL,
    -- Non critical extensions
    nonCriticalExtensions         SEQUENCE {}      OPTIONAL
}

END

```

11.3 Information element definitions

InformationElements DEFINITIONS AUTOMATIC TAGS ::=

BEGIN

IMPORTS

```

    hipDSCHidentities,
    hipUSCHidentities,
    hIRM,
    maxAC,
    maxAdditionalMeas,
    maxASC,
    maxASCmap,
    maxASCpersist,
    maxCCTrCH,
    maxCellMeas,
    maxCellMeas-1,
    maxCNdomains,
    maxCPCHsets,
    maxDPCH-DLchan,
    maxDPDCH-UL,
    maxDRACclasses,
    maxE-DCHMACdFlow,
    maxE-DCHMACdFlow-1,
    maxFACHPCH,
    maxFreq,
    maxFreqBandsFDD,
    maxFreqBandsTDD,
    maxFreqBandsGSM,
    maxGERAN-SI,
    maxHarqRTT,
    maxHProcesses,
    maxHSDSCHTBIndex,
    maxHSDSCHTBIndex-tdd384,
    maxHSSCCHs,
    maxInterSysMessages,
    maxLoCHperRLC,
    maxMAC-d-PDUsizes,
    maxMBMS-CommonCCTrCh,
    maxMBMS-CommonPhyCh,
    maxMBMS-CommonRB,
    maxMBMS-CommonTrCh,
    maxMBMS-Freq,
    maxMBMS-L1CP,
    maxMBMSservCount,

```

```

maxMBMSServDedic,
maxMBMSServModif,
maxMBMSServSched,
maxMBMSServUnmodif,
maxMBMSTransmis,
maxMeasEvent,
maxMeasIntervals,
maxMeasParEvent,
maxNumCDMA2000Freqs,
maxNumFDDFreqs,
maxNumGSMFreqRanges,
maxGSMTargetCells,
maxNumTDDFreqs,
maxOtherRAT,
maxOtherRAT-16,
maxPage1,
maxPCPCH-APsig,
maxPCPCH-APsubCh,
maxPCPCH-CDsig,
maxPCPCH-CDsubCh,
maxPCPCH-SF,
maxPCPCHs,
maxPDCPAlgoType,
maxPDSCH,
maxPDSCH-TFCIgroups,
maxPRACH,
maxPRACH-FPACH,
maxPredefConfig,
maxPUSCH,
maxQueueIDs,
maxRABsetup,
maxRAT,
maxRB,
maxRBallRABs,
maxRBperTrCh,
maxRBMuxOptions,
maxRBperRAB,
maxReportedGSMCells,
maxRLCPDUsizePerLogChan,
maxSRBsetup,
maxRL,
maxRL-1,
maxROHC-PacketSizes-r4,
maxROHC-Profile-r4,
maxSCCPCH,
maxSat,
maxSIB,
maxSIB-FACH,
maxSystemCapability,
maxTF,
maxTF-CPCH,
maxTFC,
maxTFCsub,
maxTFCI-2-Combs,
maxTGPS,
maxTrCH,
maxTrChperSCCPCH,
maxTrCHpreconf,
maxTS,
maxTS-1,
maxTS-2,
maxTS-LCR,
maxTS-LCR-1,
maxURA,
maxURNTI-Group
FROM Constant-definitions;

-- *****
-- CORE NETWORK INFORMATION ELEMENTS (10.3.1)
-- *****

Ansi-41-IDNNS ::=                               BIT STRING (SIZE (14))

CN-DomainIdentity ::=                           ENUMERATED {
                                                cs-domain,
                                                ps-domain }

```

```

CN-DomainInformation ::=          SEQUENCE {
    cn-DomainIdentity           CN-DomainIdentity,
    cn-DomainSpecificNAS-Info   NAS-SystemInformationGSM-MAP
}

CN-DomainInformationFull ::=      SEQUENCE {
    cn-DomainIdentity,
    cn-DomainSpecificNAS-Info,
    cn-DRX-CycleLengthCoeff
}

CN-DomainInformationList ::=      SEQUENCE (SIZE (1..maxCNdomains)) OF
    CN-DomainInformation

CN-DomainInformationListFull ::=  SEQUENCE (SIZE (1..maxCNdomains)) OF
    CN-DomainInformationFull

CN-DomainSysInfo ::=             SEQUENCE {
    cn-DomainIdentity,
    cn-Type
        gsm-MAP
        ansi-41
    },
    cn-DRX-CycleLengthCoeff
}

CN-DomainSysInfoList ::=         SEQUENCE (SIZE (1..maxCNdomains)) OF
    CN-DomainSysInfo

CN-InformationInfo ::=           SEQUENCE {
    plmn-Identity
    cn-CommonGSM-MAP-NAS-SysInfo
    cn-DomainInformationList
}

CN-InformationInfoFull ::=        SEQUENCE {
    plmn-Identity
    cn-CommonGSM-MAP-NAS-SysInfo
    cn-DomainInformationListFull
}

Digit ::=                         INTEGER (0..9)

Gsm-map-IDNNS ::=                SEQUENCE {
    routingbasis
        localPTMSI
            routingparameter
    },
    tMSIofsamePLMN
        routingparameter
    },
    tMSIofdifferentPLMN
        routingparameter
    },
    iMSIresponsetopaging
        routingparameter
    },
    iMSIcauseUEinitiatedEvent
        routingparameter
    },
    iMEI
        routingparameter
    },
    spare2
        routingparameter
    },
    spare1
        routingparameter
    }
},
-- dummy is not used in this version of the specification and
-- it should be ignored by the receiver.
dummy                                BOOLEAN
}

IMEI ::=                           SEQUENCE (SIZE (15)) OF
    IMEI-Digit

```

```

IMEI-Digit ::= INTEGER (0..15)

IMSI-GSM-MAP ::= SEQUENCE (SIZE (6..21)) OF
Digit

IntraDomainNasNodeSelector ::= SEQUENCE {
version CHOICE {
release99 SEQUENCE {
cn-Type CHOICE {
gsm-Map-IDNNS Gsm-map-IDNNS,
ansi-41-IDNNS Ansi-41-IDNNS
}
},
later SEQUENCE {
futurecoding BIT STRING (SIZE (15))
}
}
}

LAI ::= SEQUENCE {
plmn-Identity,
lac
}

MCC ::= SEQUENCE (SIZE (3)) OF
Digit

MNC ::= SEQUENCE (SIZE (2..3)) OF
Digit

MultiplePLMN-List-r6 ::= SEQUENCE {
mibPLMN-Identity,
multiplePLMNs
PLMN-IdentityWithOptionalMCC-r6
}

NAS-Message ::= OCTET STRING (SIZE (1..4095))

NAS-Synchronisation-Indicator ::= BIT STRING(SIZE(4))

NAS-SystemInformationGSM-MAP ::= OCTET STRING (SIZE (1..8))

P-TMSI-GSM-MAP ::= BIT STRING (SIZE (32))

PagingRecordTypeID ::= ENUMERATED {
imsi-GSM-MAP,
tmsi-GSM-MAP-P-TMSI,
imsi-DS-41,
tmsi-DS-41
}

PLMN-Identity ::= SEQUENCE {
mcc,
mnc
MCC,
MNC
}

PLMN-IdentityWithOptionalMCC-r6 ::= SEQUENCE {
mcc OPTIONAL,
mnc
MCC
MNC
}

PLMN-Type ::= CHOICE {
gsm-MAP SEQUENCE {
plmn-Identity PLMN-Identity
},
ansi-41 SEQUENCE {
p-REV,
min-P-REV,
sid,
nid
P-REV,
Min-P-REV,
SID,
NID
},
gsm-MAP-and-ANSI-41 SEQUENCE {
plmn-Identity,
p-REV,
min-P-REV,
sid,
nid
PLMN-Identity,
P-REV,
Min-P-REV,
SID,
NID
},
spare NULL
}

```

```

}

RAB-Identity ::= CHOICE {
    gsm-MAP-RAB-Identity
    ansi-41-RAB-Identity
}

RAI ::= SEQUENCE {
    lai,
    rac
}

RoutingAreaCode ::= BIT STRING (SIZE (8))

RoutingParameter ::= BIT STRING (SIZE (10))

TMSI-GSM-MAP ::= BIT STRING (SIZE (32))

-- ****
-- UTRAN MOBILITY INFORMATION ELEMENTS (10.3.2)
-- ****

AccessClassBarred ::= ENUMERATED {
    barred, notBarred }

AccessClassBarredList ::= SEQUENCE (SIZE (maxAC)) OF
    AccessClassBarred

AllowedIndicator ::= ENUMERATED {
    allowed, notAllowed }

CellAccessRestriction ::= SEQUENCE {
    cellBarred,
    cellReservedForOperatorUse,
    cellReservationExtension,
    -- NOTE: IE accessClassBarredList should not be included if the IE CellAccessRestriction
    -- is included in the IE SysInfoType4
    accessClassBarredList OPTIONAL
}

CellBarred ::= CHOICE {
    barred SEQUENCE {
        intraFreqCellReselectionInd,
        t-Barred
    },
    notBarred NULL
}

CellIdentity ::= BIT STRING (SIZE (28))

CellIdentity-PerRL-List ::= SEQUENCE (SIZE (1..maxRL)) OF CellIdentity

CellSelectReselectInfoSIB-3-4 ::= SEQUENCE {
    mappingInfo OPTIONAL,
    cellSelectQualityMeasure CHOICE {
        cpich-Ec-N0 SEQUENCE {
            -- Default value for q-HYST-2-S is q-HYST-1-S
            q-HYST-2-S Q-Hyst-S
            -- Default value for q-HYST-2-S is q-HYST-1-S
        },
        cpich-RSCP NULL
    },
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            s-Intrasearch S-SearchQual OPTIONAL,
            s-Intersearch S-SearchQual OPTIONAL,
            s-SearchHCS S-SearchRXLEV OPTIONAL,
            rat-List RAT-FDD-InfoList OPTIONAL,
            q-QualMin Q-QualMin,
            q-RxlevMin Q-RxlevMin
        },
        tdd SEQUENCE {
            s-Intrasearch S-SearchRXLEV OPTIONAL,
            s-Intersearch S-SearchRXLEV OPTIONAL,
            s-SearchHCS S-SearchRXLEV OPTIONAL,
            rat-List RAT-TDD-InfoList OPTIONAL,
        }
    }
}

```

```

        q-RxlevMin
    }
},
q-Hyst-1-S,
t-Reselection-S
hcs-ServingCellInformation
maxAllowedUL-TX-Power
}

MapParameter ::= INTEGER (0..99)

Mapping ::= SEQUENCE {
    rat,
    mappingFunctionParameterList
}

Mapping-LCR-r4 ::= SEQUENCE {
    mappingFunctionParameterList
}

MappingFunctionParameter ::= SEQUENCE {
    functionType,
    mapParameter1
    mapParameter2
    -- The presence of upperLimit is conditional on the number of repetition
    upperLimit
}
OPTIONAL,
OPTIONAL

MappingFunctionParameterList ::= SEQUENCE (SIZE (1..maxMeasIntervals)) OF
    MappingFunctionParameter

MappingFunctionType ::= ENUMERATED {
    linear,
    functionType2,
    functionType3,
    functionType4 }

-- In MappingInfo list, mapping for FDD and 3.84Mcps TDD is defined.
-- For 1.28Mcps TDD, Mapping-LCR-r4 is used instead.
MappingInfo ::= SEQUENCE (SIZE (1..maxRAT)) OF
    Mapping

-- Actual value Q-Hyst-S = IE value * 2
Q-Hyst-S ::= INTEGER (0..20)

Q-Hyst-S-Fine ::= INTEGER (0..40)

RAT ::= ENUMERATED {
    utra-FDD,
    utra-TDD,
    gsm,
    cdma2000 }

RAT-FDD-Info ::= SEQUENCE {
    rat-Identifier,
    s-SearchRAT
    s-HCS-RAT
    s-Limit-SearchRAT
}
OPTIONAL,

RAT-FDD-InfoList ::= SEQUENCE (SIZE (1..maxOtherRAT)) OF
    RAT-FDD-Info

RAT-Identifier ::= ENUMERATED {
    gsm, cdma2000 }

RAT-TDD-Info ::= SEQUENCE {
    rat-Identifier,
    s-SearchRAT
    s-HCS-RAT
    s-Limit-SearchRAT
}
OPTIONAL,

RAT-TDD-InfoList ::= SEQUENCE (SIZE (1..maxOtherRAT)) OF
    RAT-TDD-Info

ReservedIndicator ::= ENUMERATED {
    reserved,
}
OPTIONAL,
OPTIONAL

```

```

                                notReserved }

-- Actual value S-SearchQual = IE value * 2
S-SearchQual ::=           INTEGER (-16..10)

-- Actual value S-SearchRXLEV = (IE value * 2) + 1
S-SearchRXLEV ::=          INTEGER (-53..45)

T-Barred ::=                ENUMERATED {
                            s10, s20, s40, s80,
                            s160, s320, s640, s1280 }

T-Reselection-S ::=        INTEGER (0..31)

-- Actual value T-Reselection-S-Fine = IE value * 0.2
T-Reselection-S-Fine ::=   INTEGER (0..31)

-- For UpperLimit, the used range depends on the RAT used.
UpperLimit ::=              INTEGER (1..91)

URA-Identity ::=            BIT STRING (SIZE (16))

URA-IdentityList ::=       SEQUENCE (SIZE (1..maxURA)) OF
                           URA-Identity

-- ****
-- 
--      USER EQUIPMENT INFORMATION ELEMENTS (10.3.3)
-- 
-- ****

AccessStratumReleaseIndicator ::=  ENUMERATED {
                                    rel-4, rel-5, rel-6, spare13,
                                    spare12, spare11, spare10, spare9, spare8,
                                    spare7, spare6, spare5, spare4, spare3,
                                    spare2, spare1 }

-- TABULAR : for ActivationTime, value 'now' always appear as default, and is encoded
-- by absence of the field
ActivationTime ::=           INTEGER (0..255)

BackoffControlParams ::=     SEQUENCE {
                            n-AP-RetransMax,
                            n-AccessFails,
                            nf-BO-NoAICH,
                            ns-BO-Busy,
                            nf-BO-AllBusy,
                            nf-BO-Mismatch,
                            t-CPCH
                          }

C-RNTI ::=                  BIT STRING (SIZE (16))

CapabilityUpdateRequirement ::= SEQUENCE {
                                ue-RadioCapabilityFDDUpdateRequirement BOOLEAN,
                                -- ue-RadioCapabilityTDDUpdateRequirement is for 3.84Mcps TDD update requirement
                                ue-RadioCapabilityTDDUpdateRequirement BOOLEAN,
                                systemSpecificCapUpdateReqList     SystemSpecificCapUpdateReqList     OPTIONAL
                              }

CapabilityUpdateRequirement-r4-ext ::= SEQUENCE {
                                       ue-RadioCapabilityUpdateRequirement-TDD128  BOOLEAN
                                     }

CapabilityUpdateRequirement-r4 ::=  SEQUENCE {
                                       ue-RadioCapabilityFDDUpdateRequirement-FDD  BOOLEAN,
                                       ue-RadioCapabilityTDDUpdateRequirement-TDD384  BOOLEAN,
                                       ue-RadioCapabilityTDDUpdateRequirement-TDD128  BOOLEAN,
                                       systemSpecificCapUpdateReqList     SystemSpecificCapUpdateReqList     OPTIONAL
                                     }

-- If the IE CellUpdateCause has the value 'cellUpdateCause-ext', the actual value is
-- defined in the IE CellUpdateCause-ext.
CellUpdateCause ::=          ENUMERATED {
                            cellReselection,
                            periodicalCellUpdate,
                            uplinkDataTransmission,
                            utran-pagingResponse,

```

```

                                re-enteredServiceArea,
                                radiolinkFailure,
                                rlc-unrecoverableError,
                                cellUpdateCause-ext }

-- The IE CellUpdateCause-ext shall be present, if the IE CellUpdateCause has the
-- value 'cellUpdateCause-ext'.
CellUpdateCause-ext ::= ENUMERATED {
                           mbms-Reception,
                           spare3, spare2, spare1 }

ChipRateCapability ::= ENUMERATED {
                           mcps3-84, mcps1-28 }

CipheringAlgorithm ::= ENUMERATED {
                           uea0, uea1 }

CipheringModeCommand ::= CHOICE {
                           startRestart,
                           dummy
                           NULL
                           }

CipheringModeInfo ::= SEQUENCE {
                           -- TABULAR: The ciphering algorithm is included in the CipheringModeCommand.
                           cipheringModeCommand CipheringModeCommand,
                           activationTimeForDPCH ActivationTime OPTIONAL,
                           rb-DL-CiphActivationTimeInfo RB-ActivationTimeInfoList OPTIONAL
                           }

CN-DRX-CycleLengthCoefficient ::= INTEGER (6..9)

CN-PagedUE-Identity ::= CHOICE {
                           imsi-GSM-MAP,
                           tmsi-GSM-MAP,
                           p-TMSI-GSM-MAP,
                           imsi-DS-41,
                           tmsi-DS-41,
                           spare3,
                           spare2,
                           spare1
                           }

CompressedModeMeasCapability ::= SEQUENCE {
                           fdd-Measurements BOOLEAN,
                           -- TABULAR: The IEs tdd-Measurements, gsm-Measurements and multiCarrierMeasurements
                           -- are made optional since they are conditional based on another information element.
                           -- Their absence corresponds to the case where the condition is not true.
                           tdd-Measurements BOOLEAN OPTIONAL,
                           gsm-Measurements GSM-Measurements OPTIONAL,
                           multiCarrierMeasurements BOOLEAN OPTIONAL
                           }

CompressedModeMeasCapability-LCR-r4 ::= SEQUENCE {
                           tdd128-Measurements BOOLEAN OPTIONAL
                           }

CompressedModeMeasCapabFDDList ::= SEQUENCE (SIZE (1..maxFreqBandsFDD)) OF
                           CompressedModeMeasCapabFDD

CompressedModeMeasCapabFDD ::= SEQUENCE {
                           radioFrequencyBandFDD RadioFrequencyBandFDD OPTIONAL,
                           dl-MeasurementsFDD BOOLEAN,
                           ul-MeasurementsFDD BOOLEAN
                           }

CompressedModeMeasCapabTDDList ::= SEQUENCE (SIZE (1..maxFreqBandsTDD)) OF
                           CompressedModeMeasCapabTDD

CompressedModeMeasCapabTDD ::= SEQUENCE {
                           radioFrequencyBandTDD RadioFrequencyBandTDD,
                           dl-MeasurementsTDD BOOLEAN,
                           ul-MeasurementsTDD BOOLEAN
                           }

CompressedModeMeasCapabGSMList ::= SEQUENCE (SIZE (1..maxFreqBandsGSM)) OF
                           CompressedModeMeasCapabGSM

CompressedModeMeasCapabGSM ::= SEQUENCE {

```

```

radioFrequencyBandGSM           RadioFrequencyBandGSM,
dl-MeasurementsGSM            BOOLEAN,
ul-MeasurementsGSM            BOOLEAN
}

CompressedModeMeasCapabMC ::= SEQUENCE {
    dl-MeasurementsMC        BOOLEAN,
    ul-MeasurementsMC        BOOLEAN
}

CPCH-Parameters ::= SEQUENCE {
    initialPriorityDelayList   InitialPriorityDelayList      OPTIONAL,
    backoffControlParams       BackoffControlParams,
    -- TABULAR: TPC step size nested inside PowerControlAlgorithm
    powerControlAlgorithm     PowerControlAlgorithm,
    dl-DPCCH-BER              DL-DPCCH-BER
}

DL-CapabilityWithSimultaneousHS-DSCHConfig ::= ENUMERATED{kbps32, kbps64, kbps128, kbps384}

DL-DPCCH-BER ::= INTEGER (0..63)

DL-PhysChCapabilityFDD ::= SEQUENCE {
    maxNoDPCH-PDSCH-Codes     INTEGER (1..8),
    maxNoPhysChBitsReceived   MaxNoPhysChBitsReceived,
    supportForSF-512           BOOLEAN,
    supportOfPDSCH             BOOLEAN,
    simultaneousSCCPCH-DPCH-Reception SimultaneousSCCPCH-DPCH-Reception
}

DL-PhysChCapabilityFDD-v380ext ::= SEQUENCE {
    supportOfDedicatedPilotsForChEstimation SupportOfDedicatedPilotsForChEstimation      OPTIONAL
}

SupportOfDedicatedPilotsForChEstimation ::= ENUMERATED { true }

DL-PhysChCapabilityTDD ::= SEQUENCE {
    maxTS-PerFrame             MaxTS-PerFrame,
    maxPhysChPerFrame          MaxPhysChPerFrame,
    minimumSF                  MinimumSF-DL,
    supportOfPDSCH             BOOLEAN,
    maxPhysChPerTS              MaxPhysChPerTS
}

DL-PhysChCapabilityTDD-LCR-r4 ::= SEQUENCE {
    maxTS-PerSubFrame          MaxTS-PerSubFrame-r4,
    maxPhysChPerFrame          MaxPhysChPerSubFrame-r4,
    minimumSF                  MinimumSF-DL,
    supportOfPDSCH             BOOLEAN,
    maxPhysChPerTS              MaxPhysChPerTS,
    supportOf8PSK               BOOLEAN
}

DL-TransChCapability ::= SEQUENCE {
    maxNoBitsReceived          MaxNoBits,
    maxConvCodeBitsReceived     MaxNoBits,
    turboDecodingSupport       TurboSupport,
    maxSimultaneousTransChs    MaxSimultaneousTransChsDL,
    maxSimultaneousCCTrCH-Count MaxSimultaneousCCTrCH-Count,
    maxReceivedTransportBlocks MaxTransportBlocksDL,
    maxNumberOfTFC              MaxNumberOfTFC-DL,
    maxNumberOfTF                MaxNumberOfTF
}

DRAC-SysInfo ::= SEQUENCE {
    transmissionProbability     TransmissionProbability,
    maximumBitRate              MaximumBitRate
}

DRAC-SysInfoList ::= SEQUENCE (SIZE (1..maxDRACclasses)) OF
    DRAC-SysInfo

DSCH-RNTI ::= BIT STRING (SIZE (16))

E-RNTI ::= BIT STRING (SIZE (16))

ESN-DS-41 ::= BIT STRING (SIZE (32))

```

```

EstablishmentCause ::= ENUMERATED {
    originatingConversationalCall,
    originatingStreamingCall,
    originatingInteractiveCall,
    originatingBackgroundCall,
    originatingSubscribedTrafficCall,
    terminatingConversationalCall,
    terminatingStreamingCall,
    terminatingInteractiveCall,
    terminatingBackgroundCall,
    emergencyCall,
    interRAT-CellReselection,
    interRAT-CellChangeOrder,
    registration,
    detach,
    originatingHighPrioritySignalling,
    originatingLowPrioritySignalling,
    callRe-establishment,
    terminatingHighPrioritySignalling,
    terminatingLowPrioritySignalling,
    terminatingCauseUnknown,
    mbms-Reception,
    spare11,
    spare10,
    spare9,
    spare8,
    spare7,
    spare6,
    spare5,
    spare4,
    spare3,
    spare2,
    spare1 }

FailureCauseWithProtErr ::= CHOICE {
    configurationUnsupported      NULL,
    physicalChannelFailure       NULL,
    incompatibleSimultaneousReconfiguration   NULL,
    compressedModeRuntimeError   TGPSI,
    protocolError                ProtocolErrorInformation,
    cellUpdateOccurred           NULL,
    invalidConfiguration          NULL,
    configurationIncomplete      NULL,
    unsupportedMeasurement        NULL,
    mbmsSessionAlreadyReceivedCorrectly  NULL,
    lowerPriorityMBMSService     NULL,
    spare5                      NULL,
    spare4                      NULL,
    spare3                      NULL,
    spare2                      NULL,
    spare1                      NULL
}

FailureCauseWithProtErrTrId ::= SEQUENCE {
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    failureCause                FailureCauseWithProtErr
}

GroupIdentityWithReleaseInformation ::= SEQUENCE {
    rrc-ConnectionReleaseInformation RRC-ConnectionReleaseInformation,
    groupReleaseInformation         GroupReleaseInformation
}

GroupReleaseInformation ::= SEQUENCE {
    uRNTI-Group                  U-RNTI-Group
}

GSM-Measurements ::= SEQUENCE {
    gsm900                       BOOLEAN,
    dcs1800                       BOOLEAN,
    gsm1900                       BOOLEAN
}

H-RNTI ::= BIT STRING (SIZE (16))

HSDSCH-physical-layer-category ::= INTEGER (1..64)

```

```

UESpecificBehaviourInformationlidle ::= BIT STRING (SIZE (4))

UESpecificBehaviourInformationlinterRAT ::= BIT STRING (SIZE (8))

IMSI-and-ESN-DS-41 ::=          SEQUENCE {
    imsi-DS-41,
    esn-DS-41
}

IMSI-DS-41 ::=                  OCTET STRING (SIZE (5..7))

InitialPriorityDelayList ::=      SEQUENCE (SIZE (1..maxASC)) OF
                                    NS-IP

InitialUE-Identity ::=          CHOICE {
    imsi
    tmsi-and-LAI
    p-TMSI-and-RAI
    imei
    esn-DS-41
    imsi-DS-41
    imsi-and-ESN-DS-41
    tmsi-DS-41
}

IntegrityCheckInfo ::=           SEQUENCE {
    messageAuthenticationCode,
    rrc-MessageSequenceNumber
}

IntegrityProtActivationInfo ::=   SEQUENCE {
    rrc-MessageSequenceNumberList
}

IntegrityProtectionAlgorithm ::= ENUMERATED {
    uial
}

IntegrityProtectionModeCommand ::= CHOICE {
    startIntegrityProtection
        SEQUENCE {
            integrityProtInitNumber
        },
    modify
        SEQUENCE {
            dl-IntegrityProtActivationInfo
            IntegrityProtActivationInfo
        }
}

IntegrityProtectionModeInfo ::=    SEQUENCE {
    -- TABULAR: DL integrity protection activation info and Integrity
    -- protection intialisation number have been nested inside
    -- IntegrityProtectionModeCommand.
    integrityProtectionModeCommand
    integrityProtectionAlgorithm
    OPTIONAL
}

IntegrityProtInitNumber ::=       BIT STRING (SIZE (32))

-- dummy is not used in this version of the specification, it should
-- not be sent and if received it should be ignored.
MaxHcContextSpace ::=           ENUMERATED {
    dummy, by1024, by2048, by4096,
    by8192 }

MaxHcContextSpace-r5-ext ::=     ENUMERATED {
    by16384, by32768, by65536, by131072 }

MaxROHC-ContextSessions-r4 ::=   ENUMERATED {
    s2, s4, s8, s12, s16, s24, s32, s48,
    s64, s128, s256, s512, s1024, s16384 }

MaximumAM-EntityNumberRLC-Cap ::= ENUMERATED {
    dummy, am4, am5, am6,
    am8, am16, am30 }

-- Actual value MaximumBitRate = IE value * 16
MaximumBitRate ::=              INTEGER (0..32)

```

```

MaximumRLC-WindowSize ::= ENUMERATED { mws2047, mws4095 }

MaxNoDPDCH-BitsTransmitted ::= ENUMERATED {
    b600, b1200, b2400, b4800,
    b9600, b19200, b28800, b38400,
    b48000, b57600 }

MaxNoBits ::= ENUMERATED {
    b640, b1280, b2560, b3840, b5120,
    b6400, b7680, b8960, b10240,
    b20480, b40960, b81920, b163840 }

MaxNoPhysChBitsReceived ::= ENUMERATED {
    dummy, b1200, b2400, b3600,
    b4800, b7200, b9600, b14400,
    b19200, b28800, b38400, b48000,
    b57600, b67200, b76800 }

MaxNoSCCPCH-RL ::= ENUMERATED {
    r11 }

MaxNumberOfTF ::= ENUMERATED {
    tf32, tf64, tf128, tf256,
    tf512, tf1024 }

MaxNumberOfTFC-DL ::= ENUMERATED {
    tfc16, tfc32, tfc48, tfc64, tfc96,
    tfc128, tfc256, tfc512, tfc1024 }

MaxNumberOfTFC-UL ::= ENUMERATED {
    dummy1, dummy2, tfc16, tfc32, tfc48, tfc64,
    tfc96, tfc128, tfc256, tfc512, tfc1024 }

-- the values 1 ...4 for MaxPhysChPerFrame are not used in this version of the protocol
MaxPhysChPerFrame ::= INTEGER (1..224)

MaxPhysChPerSubFrame-r4 ::= INTEGER (1..96)

MaxPhysChPerTimeslot ::= ENUMERATED {
    ts1, ts2 }

-- the values 1 ...4 for MaxPhysChPerTS are not used in this version of the protocol
MaxPhysChPerTS ::= INTEGER (1..16)

MaxSimultaneousCCTrCH-Count ::= INTEGER (1..8)

MaxSimultaneousTransChsDL ::= ENUMERATED {
    e4, e8, e16, e32 }

MaxSimultaneousTransChsUL ::= ENUMERATED {
    dummy, e4, e8, e16, e32 }

MaxTransportBlocksDL ::= ENUMERATED {
    tb4, tb8, tb16, tb32, tb48,
    tb64, tb96, tb128, tb256, tb512 }

MaxTransportBlocksUL ::= ENUMERATED {
    dummy, tb4, tb8, tb16, tb32, tb48,
    tb64, tb96, tb128, tb256, tb512 }

MaxTS-PerFrame ::= INTEGER (1..14)

MaxTS-PerSubFrame-r4 ::= INTEGER (1..6)

-- TABULAR: MeasurementCapability contains dependencies to UE-MultiModeRAT-Capability,
-- the conditional fields have been left mandatory for now.
MeasurementCapability ::= SEQUENCE {
    downlinkCompressedMode           CompressedModeMeasCapability,
    uplinkCompressedMode             CompressedModeMeasCapability
}

MeasurementCapabilityExt ::= SEQUENCE {
    compressedModeMeasCapabFDDList   CompressedModeMeasCapabFDDList,
    compressedModeMeasCapabTDDList   CompressedModeMeasCapabTDDList OPTIONAL,
    compressedModeMeasCapabGSMList   CompressedModeMeasCapabGSMList OPTIONAL,
    compressedModeMeasCapabMC        CompressedModeMeasCapabMC OPTIONAL
}

```

```

MeasurementCapability-r4-ext ::=      SEQUENCE {
    downlinkCompressedMode-LCR          CompressedModeMeasCapability-LCR-r4,
    uplinkCompressedMode-LCR          CompressedModeMeasCapability-LCR-r4
}

MessageAuthenticationCode ::=           BIT STRING (SIZE (32))

MinimumSF-DL ::=                      ENUMERATED {
    sf1, sf16 }

MinimumSF-UL ::=                      ENUMERATED {
    sf1, sf2, sf4, sf8, dummy }

MultiModeCapability ::=                ENUMERATED {
    tdd, fdd, fdd-tdd }

MultiRAT-Capability ::=              SEQUENCE {
    supportOfGSM                      BOOLEAN,
    supportOfMulticarrier             BOOLEAN
}

MultiModeRAT-Capability-v590ext ::=   SEQUENCE {
    supportOfUTRAN-ToGERAN-NACC      BOOLEAN
}

N-300 ::=                            INTEGER (0..7)

N-301 ::=                            INTEGER (0..7)

N-302 ::=                            INTEGER (0..7)

N-304 ::=                            INTEGER (0..7)

N-308 ::=                            INTEGER (1..8)

N-310 ::=                            INTEGER (0..7)

N-312 ::=                ENUMERATED {
    s1, s50, s100, s200, s400,
    s600, s800, s1000 }

N-312ext ::=               ENUMERATED {
    s2, s4, s10, s20 }

N-312-r5 ::=               ENUMERATED {
    s1, s2, s4, s10, s20,
    s50, s100, s200, s400,
    s600, s800, s1000 }

N-313 ::=                ENUMERATED {
    s1, s2, s4, s10, s20,
    s50, s100, s200 }

N-315 ::=                ENUMERATED {
    s1, s50, s100, s200, s400,
    s600, s800, s1000 }

N-315ext ::=               ENUMERATED {
    s2, s4, s10, s20 }

N-315-r5 ::=               ENUMERATED {
    s1, s2, s4, s10, s20,
    s50, s100, s200, s400,
    s600, s800, s1000 }

N-AccessFails ::=                  INTEGER (1..64)

N-AP-RetransMax ::=                INTEGER (1..64)

NetworkAssistedGPS-Supported ::=   ENUMERATED {
    networkBased,
    ue-Based,
    bothNetworkAndUE-Based,
    noNetworkAssistedGPS }

NF-BO-AllBusy ::=                  INTEGER (0..31)

```

```

NF-BO-NoAICH ::= INTEGER (0..31)
NF-BO-Mismatch ::= INTEGER (0..127)
NS-BO-Busy ::= INTEGER (0..63)
NS-IP ::= INTEGER (0..28)
P-TMSI-and-RAI-GSM-MAP ::= SEQUENCE {
    p-TMSI
    rai
}
PagingCause ::= ENUMERATED {
    terminatingConversationalCall,
    terminatingStreamingCall,
    terminatingInteractiveCall,
    terminatingBackgroundCall,
    terminatingHighPrioritySignalling,
    terminatingLowPrioritySignalling,
    terminatingCauseUnknown,
    spare
}
PagingRecord ::= CHOICE {
    cn-Identity
        pagingCause
        cn-DomainIdentity
        cn-pagedUE-Identity
    },
    utran-Identity
        u-RNTI
        cn-OriginatedPage-connectedMode-UE
            sequencing {
                pagingCause
                cn-DomainIdentity
                pagingRecordTypeID
            }
        }
    OPTIONAL
}
PagingRecord2-r5 ::= CHOICE {
    utran-SingleUE-Identity
        u-RNTI
        cn-OriginatedPage-connectedMode-UE
            sequencing {
                pagingCause
                cn-DomainIdentity
                pagingRecordTypeID
            }
        }
    rrc-ConnectionReleaseInformation
        RRC-ConnectionReleaseInformation
    },
    utran-GroupIdentity
        sequence (SIZE (1 .. maxURNTI-Group)) OF
        GroupIdentityWithReleaseInformation
}
PagingRecordList ::= sequence (SIZE (1..maxPage1)) OF
    PagingRecord
PagingRecord2List-r5 ::= sequence (SIZE (1..maxPage1)) OF
    PagingRecord2-r5
PDCP-Capability ::= sequence {
    losslessSRNS-RelocationSupport BOOLEAN,
    -- If present, the "maxHcContextSpace" in the IE "PDCP-Capability-r5-ext" overrides the
    -- "supported" value in this IE. The value in this IE may be used by a pre-REL-5 UTRAN.
    supportForRfc2507 CHOICE {
        notSupported NULL,
        supported MaxHcContextSpace
    }
}
PDCP-Capability-r4-ext ::= sequence {
    supportForRfc3095 CHOICE {
        notSupported NULL,
        supported sequence {
            maxROHC-ContextSessions MaxROHC-ContextSessions-r4 DEFAULT s16,
            reverseCompressionDepth INTEGER (0..65535) DEFAULT 0
        }
    }
}

```

```

        }
    }

PDCP-Capability-r5-ext ::=          SEQUENCE {
    supportForRfc3095ContextRelocation      BOOLEAN,
    maxHcContextSpace                      MaxHcContextSpace-r5-ext   OPTIONAL
}

PhysicalChannelCapability ::=          SEQUENCE {
    fddPhysChCapability           SEQUENCE {
        downlinkPhysChCapability      DL-PhysChCapabilityFDD,
        uplinkPhysChCapability        UL-PhysChCapabilityFDD
    }
    -- tddPhysChCapability describes the 3.84Mcps TDD physical channel capability
    tddPhysChCapability           SEQUENCE {
        downlinkPhysChCapability      DL-PhysChCapabilityTDD,
        uplinkPhysChCapability        UL-PhysChCapabilityTDD
    }
}
-- PhysicalChannelCapability-LCR-r4 describes the 1.28Mcps TDD physical channel capability
PhysicalChannelCapability-LCR-r4 ::=      SEQUENCE {
    tdd128-PhysChCapability        SEQUENCE {
        downlinkPhysChCapability      DL-PhysChCapabilityTDD-LCR-r4,
        uplinkPhysChCapability        UL-PhysChCapabilityTDD-LCR-r4
    }
}
-- PhysicalChannelCapability-hspdsch-r5 describes the HS-PDSCH physical channel capability
PhysicalChannelCapability-hspdsch-r5 ::=      SEQUENCE {
    fdd-hspdsch                  CHOICE {
        supported                 SEQUENCE {
            hdsch-physical-layer-category      HSDSCH-physical-layer-category,
            supportOfDedicatedPilotsForChannelEstimationOfHSDSCH  BOOLEAN,
            -- simultaneousSCCPCH-DPCH-HSDSCH-Reception shall be true only if the
            -- IE SimultaneousSCCPCH-DPCH-Reception indicates support of simultaneous
            -- reception of S-CCPCH and DPCH
            simultaneousSCCPCH-DPCH-HSDSCH-Reception      BOOLEAN
        },
        unsupported                NULL
    },
    tdd384-hspdsch               CHOICE {
        supported                 HSDSCH-physical-layer-category,
        unsupported               NULL
    },
    tdd128-hspdsch               CHOICE {
        supported                 HSDSCH-physical-layer-category,
        unsupported               NULL
    }
}

PNBSCH-Allocation-r4 ::=          SEQUENCE {
    numberOfRepetitionsPerSFNPeriod ENUMERATED {
        c2, c3, c4, c5, c6, c7, c8, c9, c10,
        c12, c14, c16, c18, c20, c24, c28, c32,
        c36, c40, c48, c56, c64, c72, c80
    }
}

ProtocolErrorCause ::=          ENUMERATED {
    asnl-ViolationOrEncodingException,
    messageTypeNonexistent,
    messageNotCompatibleWithReceiverState,
    ie-ValueNotComprehended,
    informationElementMissing,
    messageExtensionNotComprehended,
    spare2, spare1
}

ProtocolErrorIndicator ::=          ENUMERATED {
    noError, errorOccurred
}

ProtocolErrorIndicatorWithMoreInfo ::=      CHOICE {
    noError                    NULL,
    errorOccurred              SEQUENCE {
        rrc-TransactionIdentifier      RRC-TransactionIdentifier,
        protocolErrorInformation     ProtocolErrorInformation
    }
}

```

```

ProtocolErrorMoreInformation ::= SEQUENCE {
    diagnosticsType CHOICE {
        type1 CHOICE {
            asn1-ViolationOrEncodingError NULL,
            messageTypeNonexistent NULL,
            messageNotCompatibleWithReceiverState IdentificationOfReceivedMessage,
            ie-ValueNotComprehended IdentificationOfReceivedMessage,
            conditionalInformationElementError IdentificationOfReceivedMessage,
            messageExtensionNotComprehended IdentificationOfReceivedMessage,
            spare1 NULL,
            spare2 NULL
        },
        spare NULL
    }
}

RadioFrequencyBandFDD ::= ENUMERATED {
    -- fdd2100, fdd1900, fdd1800 correspond to Band I, Band II and Band III respectively
    fdd2100,
    fdd1900,
    fdd1800,
    bandVI,
    bandIV,
    bandV, spare2, spare1 }

RadioFrequencyBandTDDList ::= ENUMERATED {
    a, b, c, ab, ac, bc, abc, spare }

RadioFrequencyBandTDD ::= ENUMERATED {a, b, c, spare}

RadioFrequencyBandGSM ::= ENUMERATED {
    gsm450,
    gsm480,
    gsm850,
    gsm900P,
    gsm900E,
    gsm1800,
    gsm1900,
    spare9, spare8, spare7, spare6, spare5,
    spare4, spare3, spare2, spare1}

Rb-timer-indicator ::= SEQUENCE {
    t314-expired BOOLEAN,
    t315-expired BOOLEAN }

Re-EstablishmentTimer ::= ENUMERATED {
    useT314, useT315
}

RedirectionInfo ::= CHOICE {
    frequencyInfo FrequencyInfo,
    interRATInfo InterRATInfo
}

RedirectionInfo-r6 ::= CHOICE {
    frequencyInfo FrequencyInfo,
    interRATInfo InterRATInfo-r6
}

RejectionCause ::= ENUMERATED {
    congestion,
    unspecified }

ReleaseCause ::= ENUMERATED {
    normalEvent,
    unspecified,
    pre-emptiveRelease,
    congestion,
    re-establishmentReject,
    directedsignallingconnectionre-establishment,
    userInactivity,
    spare }

RF-Capability ::= SEQUENCE {
    fddRF-Capability
    ue-PowerClass
        SEQUENCE {
            UE-PowerClass,
}
}

```

```

        txRxFrequencySeparation
    }
    tddRF-Capability
        ue-PowerClass
        radioFrequencyTDDBandList
        chipRateCapability
    }
}

RF-Capability-r4-ext ::= SEQUENCE {
    tddRF-Capability
        ue-PowerClass
        radioFrequencyBandTDDList
        chipRateCapability
    }
}

RLC-Capability ::= SEQUENCE {
    -- If present, the "totalRLC-AM-BufferSize" in the IE "RLC-Capability-r5-ext" overrides the
    -- corresponding value in this IE. The value in this IE may be used by a pre-REL-5 UTRAN.
    totalRLC-AM-BufferSize
    maximumRLC-WindowSize
    maximumAM-EntityNumber
}
}

RLC-Capability-r5-ext ::= SEQUENCE {
    totalRLC-AM-BufferSize
        TotalRLC-AM-BufferSize-r5-ext OPTIONAL
}

RRC-ConnectionReleaseInformation ::= CHOICE {
    noRelease
    release
        releaseCause
}
}

RRC-MessageSequenceNumber ::= INTEGER (0..15)

RRC-MessageSequenceNumberList ::= SEQUENCE (SIZE (4..5)) OF
    RRC-MessageSequenceNumber

RRC-StateIndicator ::= ENUMERATED {
    cell-DCH, cell-FACH, cell-PCH, ura-PCH }

RRC-TransactionIdentifier ::= INTEGER (0..3)

S-RNTI ::= BIT STRING (SIZE (20))

S-RNTI-2 ::= BIT STRING (SIZE (10))

SecurityCapability ::= SEQUENCE {
    cipheringAlgorithmCap
        BIT STRING {
            -- For each bit value "0" means false/ not supported
            spare15(0),
            spare14(1),
            spare13(2),
            spare12(3),
            spare11(4),
            spare10(5),
            spare9(6),
            spare8(7),
            spare7(8),
            spare6(9),
            spare5(10),
            spare4(11),
            spare3(12),
            spare2(13),
            ueal(14),
            uea0(15)
        } (SIZE (16)),
    integrityProtectionAlgorithmCap
        BIT STRING {
            -- For each bit value "0" means false/ not supported
            spare15(0),
            spare14(1),
            spare13(2),
            spare12(3),
            spare11(4),
}

```

```

                spare10(5),
                spare9(6),
                spare8(7),
                spare7(8),
                spare6(9),
                spare5(10),
                spare4(11),
                spare3(12),
                spare2(13),
                uial1(14),
                spare0(15)
            }      (SIZE (16))
}

SimultaneousSCCPCH-DPCH-Reception ::= CHOICE {
    notSupported                  NULL,
    supported                     SEQUENCE {
        maxNoSCCPCH-RL           MaxNoSCCPCH-RL,
        -- simultaneousSCCPCH-DPCH-DPDCH-Reception is applicable only if
        -- the IE Support of PDSCH = TRUE
        -- Note: the reference to DPDCH in the element name below is incorrect (see tabular). The
        -- name is not changed, to keep it aligned with R99.
        simultaneousSCCPCH-DPCH-DPDCH-Reception   BOOLEAN
    }
}

SRNC-Identity ::=          BIT STRING (SIZE (12))

START-Value ::=             BIT STRING (SIZE (20))

STARTList ::=               SEQUENCE (SIZE (1..maxCNdomains)) OF
                            STARTSingle

STARTSingle ::=              SEQUENCE {
    cn-DomainIdentity,
    start-Value
}

CapabilityUpdateRequirement-r5 ::= SEQUENCE {
    ue-RadioCapabilityFDDUpdateRequirement-FDD   BOOLEAN,
    ue-RadioCapabilityTDDUpdateRequirement-TDD384  BOOLEAN,
    ue-RadioCapabilityTDDUpdateRequirement-TDD128  BOOLEAN,
    systemSpecificCapUpdateReqList      SystemSpecificCapUpdateReqList-r5      OPTIONAL
}

SystemSpecificCapUpdateReq ::=      ENUMERATED {
    gsm
}

SystemSpecificCapUpdateReq-v590ext ::=      ENUMERATED {
    geranIu
}

SystemSpecificCapUpdateReq-r5 ::=      ENUMERATED {
    gsm, geranIu
}

SystemSpecificCapUpdateReqList ::= SEQUENCE (SIZE (1..maxSystemCapability)) OF
                                    SystemSpecificCapUpdateReq

SystemSpecificCapUpdateReqList-r5 ::= SEQUENCE (SIZE (1..maxSystemCapability)) OF
                                    SystemSpecificCapUpdateReq-r5

T-300 ::=                   ENUMERATED {
    ms100, ms200, ms400, ms600, ms800,
    ms1000, ms1200, ms1400, ms1600,
    ms1800, ms2000, ms3000, ms4000,
    ms6000, ms8000
}

T-301 ::=                   ENUMERATED {
    ms100, ms200, ms400, ms600, ms800,
    ms1000, ms1200, ms1400, ms1600,
    ms1800, ms2000, ms3000, ms4000,
    ms6000, ms8000, spare
}

T-302 ::=                   ENUMERATED {
    ms100, ms200, ms400, ms600, ms800,
    ms1000, ms1200, ms1400, ms1600,
    ms1800, ms2000, ms3000, ms4000,
    ms6000, ms8000, spare
}

```

```

T-304 ::= ENUMERATED {
    ms100, ms200, ms400,
    ms1000, ms2000, spare3, spare2, spare1 }

T-305 ::= ENUMERATED {
    noUpdate, m5, m10, m30,
    m60, m120, m360, m720 }

T-307 ::= ENUMERATED {
    s5, s10, s15, s20,
    s30, s40, s50, spare }

T-308 ::= ENUMERATED {
    ms40, ms80, ms160, ms320 }

T-309 ::= INTEGER (1..8)

T-310 ::= ENUMERATED {
    ms40, ms80, ms120, ms160,
    ms200, ms240, ms280, ms320 }

T-311 ::= ENUMERATED {
    ms250, ms500, ms750, ms1000,
    ms1250, ms1500, ms1750, ms2000 }

-- The value 0 for T-312 is not used in this version of the specification
T-312 ::= INTEGER (0..15)

T-313 ::= INTEGER (0..15)

T-314 ::= ENUMERATED {
    s0, s2, s4, s6, s8,
    s12, s16, s20 }

T-315 ::= ENUMERATED {
    s0, s10, s30, s60, s180,
    s600, s1200, s1800 }

T-316 ::= ENUMERATED {
    s0, s10, s20, s30, s40,
    s50, s-inf, spare }

-- All the values are changed to "infinity" in Rel-5
T-317 ::= ENUMERATED {
    infinity0, infinity1, infinity2, infinity3, infinity4,
    infinity5, infinity6, infinity7 }

T-318 ::= ENUMERATED {
    ms250, ms500, ms750, ms1000, ms1250, ms1500,
    ms1750, ms2000, ms3000, ms4000, ms6000, ms8000,
    ms10000, ms12000, ms16000 }

T-CPCH ::= ENUMERATED {
    ct0, ct1 }

TMSI-and-LAI-GSM-MAP ::= SEQUENCE {
    tmsi,
    lai
}

TMSI-DS-41 ::= OCTET STRING (SIZE (2..17))

TotalRLC-AM-BufferSize ::= ENUMERATED {
    dummy, kb10, kb50, kb100,
    kb150, kb500, kb1000, spare }

TotalRLC-AM-BufferSize-r5-ext ::= ENUMERATED {
    kb200, kb300, kb400, kb750 }

-- Actual value TransmissionProbability = IE value * 0.125
TransmissionProbability ::= INTEGER (1..8)

TransportChannelCapability ::= SEQUENCE {
    dl-TransChCapability,
    ul-TransChCapability
}

```

```

TurboSupport ::= CHOICE {
    notSupported
    supported
}

TxRxFrequencySeparation ::= ENUMERATED {
    mhz190, mhz174-8-205-2,
    mhz134-8-245-2
}

U-RNTI ::= SEQUENCE {
    srnc-Identity,
    s-RNTI
}

U-RNTI-Group ::= CHOICE {
-- TABULAR: not following the tabular strictly, but this will most likely save bits
    all
    u-RNTI-BitMaskIndex-b1
    u-RNTI-BitMaskIndex-b2
    u-RNTI-BitMaskIndex-b3
    u-RNTI-BitMaskIndex-b4
    u-RNTI-BitMaskIndex-b5
    u-RNTI-BitMaskIndex-b6
    u-RNTI-BitMaskIndex-b7
    u-RNTI-BitMaskIndex-b8
    u-RNTI-BitMaskIndex-b9
    u-RNTI-BitMaskIndex-b10
    u-RNTI-BitMaskIndex-b11
    u-RNTI-BitMaskIndex-b12
    u-RNTI-BitMaskIndex-b13
    u-RNTI-BitMaskIndex-b14
    u-RNTI-BitMaskIndex-b15
    u-RNTI-BitMaskIndex-b16
    u-RNTI-BitMaskIndex-b17
    u-RNTI-BitMaskIndex-b18
    u-RNTI-BitMaskIndex-b19
    u-RNTI-BitMaskIndex-b20
    u-RNTI-BitMaskIndex-b21
    u-RNTI-BitMaskIndex-b22
    u-RNTI-BitMaskIndex-b23
    u-RNTI-BitMaskIndex-b24
    u-RNTI-BitMaskIndex-b25
    u-RNTI-BitMaskIndex-b26
    u-RNTI-BitMaskIndex-b27
    u-RNTI-BitMaskIndex-b28
    u-RNTI-BitMaskIndex-b29
    u-RNTI-BitMaskIndex-b30
    u-RNTI-BitMaskIndex-b31
}
}

U-RNTI-Short ::= SEQUENCE {
    srnc-Identity,
    s-RNTI-2
}

UE-ConnTimersAndConstants ::= SEQUENCE {
-- Optional is used also for parameters for which the default value is the last one read in SIB1
-- t-301 and n-301 should not be used by the UE in this version of the specification
    t-301
    n-301
    t-302
    n-302
    t-304
    n-304
    t-305
    t-307
    t-308
    t-309
    t-310
    n-310
    t-311
    t-312
-- n-312 shall be ignored if n-312 in UE-ConnTimersAndConstants-v3a0ext is present, and the
-- value of that element shall be used instead.
    n-312
    t-313
    n-313
    t-314
}

```

```

t-315                               T-315                               DEFAULT s180,
-- n-315 shall be ignored if n-315 in UE-ConnTimersAndConstants-v3a0ext is present, and the
-- value of that element shall be used instead.
n-315                               N-315                               DEFAULT s1,
t-316                               T-316                               DEFAULT s30,
t-317                               T-317                               DEFAULT infinity4
}

UE-ConnTimersAndConstants-v3a0ext ::=      SEQUENCE {
    n-312                           N-312ext                         OPTIONAL,
    n-315                           N-315ext                         OPTIONAL
}

UE-ConnTimersAndConstants-r5 ::=      SEQUENCE {
-- Optional is used also for parameters for which the default value is the last one read in SIB1
-- t-301 and n-301 should not be used by the UE in this version of the specification
    t-301                           T-301                               DEFAULT ms2000,
    n-301                           N-301                               DEFAULT 2,
    t-302                           T-302                               DEFAULT ms4000,
    n-302                           N-302                               DEFAULT 3,
    t-304                           T-304                               DEFAULT ms2000,
    n-304                           N-304                               DEFAULT 2,
    t-305                           T-305                               DEFAULT m30,
    t-307                           T-307                               DEFAULT s30,
    t-308                           T-308                               DEFAULT ms160,
    t-309                           T-309                               DEFAULT 5,
    t-310                           T-310                               DEFAULT ms160,
    n-310                           N-310                               DEFAULT 4,
    t-311                           T-311                               DEFAULT ms2000,
    t-312                           T-312                               DEFAULT 1,
    n-312                           N-312-r5                          DEFAULT s1,
    t-313                           T-313                               DEFAULT 3,
    n-313                           N-313                               DEFAULT s20,
    t-314                           T-314                               DEFAULT s12,
    t-315                           T-315                               DEFAULT s180,
    n-315                           N-315-r5                          DEFAULT s1,
    t-316                           T-316                               DEFAULT s30,
    t-317                           T-317                               DEFAULT infinity4
}

UE-IdleTimersAndConstants ::=      SEQUENCE {
    t-300                           T-300,
    n-300                           N-300,
    t-312                           T-312,
-- n-312 shall be ignored if n-312 in UE-IdleTimersAndConstants-v3a0ext is present, and the
-- value of that element shall be used instead.
    n-312                           N-312
}

UE-IdleTimersAndConstants-v3a0ext ::=      SEQUENCE {
    n-312                           N-312ext                         OPTIONAL
}

UE-MultiModeRAT-Capability ::=      SEQUENCE {
    multiRAT-CapabilityList        MultiRAT-Capability,
    multiModeCapability            MultiModeCapability
}

UE-PowerClass ::=                  INTEGER (1..4)

UE-PowerClassExt ::=             ENUMERATED {class1, class2, class3, class4,
                                             spare4, spare3, spare2, spare1 }

UE-RadioAccessCapability ::=      SEQUENCE {
-- UE-RadioAccessCapability is compatible with R99, although accessStratumReleaseIndicator
-- is removed from this IE, since its encoding did not does in bits. The
-- accessStratumReleaseIndicator is provided in the relevant REL-4 extension IEs.
    pdcp-Capability                PDCP-Capability,
    rlc-Capability                 RLC-Capability,
    transportChannelCapability     TransportChannelCapability,
    rf-Capability                  RF-Capability,
    physicalChannelCapability     PhysicalChannelCapability,
    ue-MultiModeRAT-Capability    UE-MultiModeRAT-Capability,
    securityCapability              SecurityCapability,
    ue-positioning-Capability     UE-Positioning-Capability,
    measurementCapability          MeasurementCapability   OPTIONAL
}

```

```

UE-RadioAccessCapabilityInfo ::= SEQUENCE {
    ue-RadioAccessCapability,
    ue-RadioAccessCapability-v370ext
}

UE-RadioAccessCapability-v370ext ::= SEQUENCE {
    ue-RadioAccessCapabBandFDDList
}

UE-RadioAccessCapability-v380ext ::= SEQUENCE {
    ue-PositioningCapabilityExt-v380
}

UE-RadioAccessCapability-v3a0ext ::= SEQUENCE {
    ue-PositioningCapabilityExt-v3a0
}

UE-RadioAccessCapability-v3g0ext ::= SEQUENCE {
    ue-PositioningCapabilityExt-v3g0
}

UE-PositioningCapabilityExt-v380 ::= SEQUENCE {
    rx-tx-TimeDifferenceType2Capable
    BOOLEAN
}

UE-PositioningCapabilityExt-v3a0 ::= SEQUENCE {
    validity-CellPCH-UraPCH
    ENUMERATED { true }
}

UE-PositioningCapabilityExt-v3g0 ::= SEQUENCE {
    sfn-sfnType2Capability
    ENUMERATED { true }
}

UE-RadioAccessCapabBandFDDList ::= SEQUENCE (SIZE (1..maxFreqBandsFDD)) OF
    UE-RadioAccessCapabBandFDD

UE-RadioAccessCapabBandFDD ::= SEQUENCE{
    radioFrequencyBandFDD
    RadioFrequencyBandFDD,
    fddRF-Capability
    SEQUENCE {
        ue-PowerClass
        UE-PowerClassExt,
        txRxFrequencySeparation
        TxRxFrequencySeparation
    }
    measurementCapability
    MeasurementCapabilityExt
    OPTIONAL,
}
}

UE-RadioAccessCapability-v4b0ext ::= SEQUENCE {
    pdcp-Capability-r4-ext
    PDCP-Capability-r4-ext,
    tdd-CapabilityExt
    SEQUENCE {
        rf-Capability
        RF-Capability-r4-ext,
        physicalChannelCapability-LCR
        PhysicalChannelCapability-LCR-r4,
        measurementCapability-r4-ext
        MeasurementCapability-r4-ext
    }
    OPTIONAL,
    -- IE "AccessStratumReleaseIndicator" is not needed in RRC CONNECTION SETUP COMPLETE
    accessStratumReleaseIndicator
    AccessStratumReleaseIndicator OPTIONAL
}

UE-RadioAccessCapabilityComp ::= SEQUENCE {
    totalAM-RLCMemoryExceeds10kB
    BOOLEAN,
    rf-CapabilityComp
    RF-CapabilityComp
}

RF-CapabilityComp ::= SEQUENCE {
    fdd
    CHOICE {
        notSupported
        NULL,
        supported
        RF-CapabBandListFDDComp
    },
    tdd384-RF-Capability
    CHOICE {
        notSupported
        NULL,
        supported
        RadioFrequencyBandTDDList
    },
    tdd128-RF-Capability
    CHOICE {
        notSupported
        NULL,
        supported
        RadioFrequencyBandTDDList
    }
}

-- NOTE: This IE is the frequency separation in MHz
RF-CapabBandFDDComp ::= ENUMERATED { notSupported, mhz190,

```

```
    mhz174-8-205-2, mhz134-8-245-2 }
```

```
RF-CapabBandListFDDComp ::= SEQUENCE (SIZE (1..maxFreqBandsFDD)) OF
  -- the first entry corresponds with the first value of IE RadioFrequencyBandFDD,
  -- fdd2100, and so on
  RF-CapabBandFDDComp
```

```
UE-RadioAccessCapability-v590ext ::= SEQUENCE {
  dl-CapabilityWithSimultaneousHS-DSCHConfig  DL-CapabilityWithSimultaneousHS-DSCHConfig
  OPTIONAL,
  pdcp-Capability-r5-ext                    PDCP-Capability-r5-ext,
  rlc-Capability-r5-ext                     RLC-Capability-r5-ext,
  physicalChannelCapability                PhysicalChannelCapability-hspdsch-r5,
  multiModeRAT-Capability-v590ext          MultiModeRAT-Capability-v590ext
}
```

```
UL-PhysChCapabilityFDD ::= SEQUENCE {
  maxNoDPDCH-BitsTransmitted
  supportOfPCPCH
}
```

```
UL-PhysChCapabilityTDD ::= SEQUENCE {
  maxTS-PerFrame
  maxPhysChPerTimeslot
  minimumSF
  supportOfPUSCH
}
```

```
UL-PhysChCapabilityTDD-LCR-r4 ::= SEQUENCE {
  maxTS-PerSubFrame
  maxPhysChPerTimeslot
  minimumSF
  supportOfPUSCH
  supportOf8PSK
}
```

```
UL-TransChCapability ::= SEQUENCE {
  maxNoBitsTransmitted
  maxConvCodeBitsTransmitted
  turboEncodingSupport
  maxSimultaneousTransChs
  modeSpecificInfo
    fdd
    tdd
      maxSimultaneousCCTrCH-Count
    }
  },
  maxTransmittedBlocks
  maxNumberOfTFC
  maxNumberOfTF
}
```

```
UE-Positioning-Capability ::= SEQUENCE {
  standaloneLocMethodsSupported
  ue-BasedOTDOA-Supported
  networkAssistedGPS-Supported
  supportForUE-GPS-TimingOfCellFrames
  supportForIPDL
}
```

```
UE-SecurityInformation ::= SEQUENCE {
  start-CS
}
```

```
URA-UpdateCause ::= ENUMERATED {
  changeOfURA,
  periodicURAUUpdate,
  dummy,
  spare1 }
```

```
UTRAN-DRX-CycleLengthCoefficient ::= INTEGER (3..9)
```

```
WaitTime ::= INTEGER (0..15)
```

```
-- ****
--      RADIO BEARER INFORMATION ELEMENTS (10.3.4)
--
```

```

-- ****
AlgorithmSpecificInfo ::= CHOICE {
    rfc2507-Info
}

AlgorithmSpecificInfo-r4 ::= CHOICE {
    rfc2507-Info,
    rfc3095-Info
}

CID-InclusionInfo-r4 ::= ENUMERATED {
    pdcp-Header,
    rfc3095-PacketFormat
}

-- Upper limit of COUNT-C is 2^32 - 1
COUNT-C ::= INTEGER (0..4294967295)

-- Upper limit of COUNT-C-MSB is 2^25 - 1
COUNT-C-MSB ::= INTEGER (0..33554431)

DefaultConfigIdentity ::= INTEGER (0..10)

DefaultConfigIdentity-r4 ::= INTEGER (0..12)

DefaultConfigIdentity-r5 ::= INTEGER (0..13)

DefaultConfigMode ::= ENUMERATED {
    fdd,
    tdd
}

DDI ::= INTEGER (0..62)

DL-AM-RLC-Mode ::= SEQUENCE {
    inSequenceDelivery,
    receivingWindowSize,
    dl-RLC-StatusInfo
}

DL-AM-RLC-Mode-r5 ::= SEQUENCE {
    dl-RLC-PDU-size,
    inSequenceDelivery,
    receivingWindowSize,
    dl-RLC-StatusInfo
}

DL-CounterSynchronisationInfo ::= SEQUENCE {
    rB-WithPDCP-InfoList
        OPTIONAL
}

DL-CounterSynchronisationInfo-r5 ::= SEQUENCE {
    rb-WithPDCP-InfoList
        OPTIONAL,
    rb-PDCPContextRelocationList
        OPTIONAL
}

DL-LogicalChannelMapping ::= SEQUENCE {
    -- TABULAR: DL-TransportChannelType contains TransportChannelIdentity as well.
    dl-TransportChannelType,
    logicalChannelIdentity
        OPTIONAL
}

DL-LogicalChannelMapping-r5 ::= SEQUENCE {
    -- TABULAR: DL-TransportChannelType contains TransportChannelIdentity as well.
    dl-TransportChannelType,
    logicalChannelIdentity
        OPTIONAL
}

DL-LogicalChannelMappingList ::= SEQUENCE (SIZE (1..maxLoCHperRLC)) OF
    DL-LogicalChannelMapping

DL-LogicalChannelMappingList-r5 ::= SEQUENCE (SIZE (1..maxLoCHperRLC)) OF
    DL-LogicalChannelMapping-r5

DL-RFC3095-r4 ::= SEQUENCE {
    cid-InclusionInfo
        DEFAULT 15,
    max-CID
        DEFAULT 0
    reverseDecompressionDepth
}

```

```

DL-RLC-Mode ::= CHOICE {
    dl-AM-RLC-Mode,
    dl-UM-RLC-Mode,
    dl-TM-RLC-Mode
}

DL-RLC-Mode-r5 ::= CHOICE {
    dl-AM-RLC-Mode-r5,
    dl-UM-RLC-Mode-r5,
    dl-TM-RLC-Mode
}

DL-RLC-Mode-r6 ::= CHOICE {
    dl-AM-RLC-Mode-r5,
    dl-UM-RLC-Mode-r5,
    dl-TM-RLC-Mode
}

DL-RLC-StatusInfo ::= SEQUENCE {
    timerStatusProhibit           OPTIONAL,
    -- dummy is not used in this version of the specification, it should not be sent
    -- and if received they should be ignored.
    dummy                          OPTIONAL,
    missingPDU-Indicator          BOOLEAN,
    timerStatusPeriodic           OPTIONAL
}

DL-TM-RLC-Mode ::= SEQUENCE {
    segmentationIndication        BOOLEAN
}

DL-TransportChannelType ::= CHOICE {
    dch                           TransportChannelIdentity,
    fach                          NULL,
    dsch                          TransportChannelIdentity,
    dch-and-dsch                 TransportChannelIdentityDCHandDSCH
}

DL-TransportChannelType-r5 ::= CHOICE {
    dch                           TransportChannelIdentity,
    fach                          NULL,
    dsch                          TransportChannelIdentity,
    dch-and-dsch                 TransportChannelIdentityDCHandDSCH,
    hsd sch                      MAC-d-FlowIdentity,
    dch-and-hsd sch              MAC-d-FlowIdentityDCHandHSDSCH
}

DL-UM-RLC-LI-size ::= ENUMERATED {
    size7, size15
}

DL-UM-RLC-Mode-r5 ::= SEQUENCE {
    dl-UM-RLC-LI-size
}

DL-UM-RLC-Mode-r6 ::= SEQUENCE {
    dl-UM-RLC-LI-size,
    dl-UM-RLC-Dup1Avoid-Reord-Info   OPTIONAL,
    dl-UM-RLC-OutOSeqDelivery-Info  OPTIONAL
}

ExpectReordering ::= ENUMERATED {
    reorderingNotExpected,
    reorderingExpected
}

ExplicitDiscard ::= SEQUENCE {
    timerMRW,
    timerDiscard,
    maxMRW
}

HeaderCompressionInfo ::= SEQUENCE {
    algorithmSpecificInfo
}

HeaderCompressionInfoList ::= SEQUENCE (SIZE (1..maxPDCPAlgoType)) OF
                                HeaderCompressionInfo

```

```

HeaderCompressionInfo-r4 ::=          SEQUENCE {
    algorithmSpecificInfo           AlgorithmSpecificInfo-r4
}

HeaderCompressionInfoList-r4 ::=       SEQUENCE (SIZE (1..maxPDCPAlgoType)) OF
                                         HeaderCompressionInfo-r4

LogicalChannelIdentity ::=            INTEGER (1..15)

LosslessSRNS-RelocSupport ::=         CHOICE {
    supported                      MaxPDCP-SN-WindowSize,
    notSupported                   NULL
}

MAC-d-HFN-initial-value ::=          BIT STRING (SIZE (24))

MAC-LogicalChannelPriority ::=        INTEGER (1..8)

MaxDAT ::=                           ENUMERATED {
    dat1, dat2, dat3, dat4, dat5, dat6,
    dat7, dat8, dat9, dat10, dat15, dat20,
    dat25, dat30, dat35, dat40 }

MaxDAT-Retransmissions ::=          SEQUENCE {
    maxDAT,
    timerMRW,
    maxMRW
}

MaxMRW ::=                           ENUMERATED {
    mm1, mm4, mm6, mm8, mm12, mm16,
    mm24, mm32 }

MaxPDCP-SN-WindowSize ::=           ENUMERATED {
    sn255, sn65535 }

MaxRST ::=                           ENUMERATED {
    rst1, rst4, rst6, rst8, rst12,
    rst16, rst24, rst32 }

NoExplicitDiscard ::=               ENUMERATED {
    dt10, dt20, dt30, dt40, dt50,
    dt60, dt70, dt80, dt90, dt100 }

PDCP-Info ::=                         SEQUENCE {
    losslessSRNS-RelocSupport      LosslessSRNS-RelocSupport      OPTIONAL,
    -- TABULAR: pdcp-PDU-Header is MD in the tabular format and it can be encoded
    -- in one bit, so the OPTIONAL is removed for compactness.
    pdcp-PDU-Header                PDCP-PDU-Header,
    headerCompressionInfoList       HeaderCompressionInfoList      OPTIONAL
}

PDCP-Info-r4 ::=                     SEQUENCE {
    losslessSRNS-RelocSupport      LosslessSRNS-RelocSupport      OPTIONAL,
    -- TABULAR: pdcp-PDU-Header is MD in the tabular format and it can be encoded
    -- in one bit, so the OPTIONAL is removed for compactness.
    pdcp-PDU-Header                PDCP-PDU-Header,
    headerCompressionInfoList       HeaderCompressionInfoList-r4     OPTIONAL
}

PDCP-InfoReconfig ::=               SEQUENCE {
    pdcp-Info                      PDCP-Info,
    -- dummy is not used in this version of the specification and
    -- it should be ignored.
    dummy                           INTEGER (0..65535)
}

PDCP-InfoReconfig-r4 ::=            SEQUENCE {
    pdcp-Info                      PDCP-Info-r4
}

PDCP-PDU-Header ::=                 ENUMERATED {
    present, absent }

PDCP-SN-Info ::=                   INTEGER (0..65535)

Poll-PDU ::=                        ENUMERATED {
    pdu1, pdu2, pdu4, pdu8, pdu16,

```

```

                                pdu32, pdu64, pdu128 }

Poll-SDU ::=          ENUMERATED {
                      sdu1, sdu4, sdu16, sdu64 }

PollingInfo ::=        SEQUENCE {
                      timerPollProhibit           OPTIONAL,
                      timerPoll                   OPTIONAL,
                      poll-PDU                    OPTIONAL,
                      poll-SDU                    OPTIONAL,
                      lastTransmissionPDU-Poll    BOOLEAN,
                      lastRetransmissionPDU-Poll  BOOLEAN,
                      pollWindow                  OPTIONAL,
                      timerPollPeriodic           OPTIONAL
}

PollWindow ::=          ENUMERATED {
                        pw50, pw60, pw70, pw80, pw85,
                        pw90, pw95, pw99 }

PredefinedConfigIdentity ::=      INTEGER (0..15)

PredefinedConfigValueTag ::=      INTEGER (0..15)

PredefinedRB-Configuration ::=    SEQUENCE {
                      re-EstablishmentTimer,
                      srb-InformationList,
                      rb-InformationList
}

PreDefRadioConfiguration ::=      SEQUENCE {
                      -- Radio bearer IEs
                      predefinedRB-Configuration,
                      -- Transport channel IEs
                      preDefTransChConfiguration,
                      -- Physical channel IEs
                      preDefPhyChConfiguration
}

PredefinedConfigStatusList ::=    SEQUENCE (SIZE (maxPredefConfig)) OF
                                  PredefinedConfigStatusInfo

PredefinedConfigStatusInfo ::=    CHOICE {
                      storedWithValueTagSameAsPrevious NULL,
                      other                         CHOICE {
                        notStored                     NULL,
                        storedWithValueTag            PredefinedConfigValueTag
}
}

PredefinedConfigStatusListComp ::= SEQUENCE {
                      setsWithDifferentValueTag     PredefinedConfigSetsWithDifferentValueTag,
                      otherEntries                  PredefinedConfigStatusListVarSz   OPTIONAL
}

PredefinedConfigSetsWithDifferentValueTag ::= SEQUENCE (SIZE (1..2)) OF
                                              PredefinedConfigSetWithDifferentValueTag

PredefinedConfigSetWithDifferentValueTag ::= SEQUENCE {
                      startPosition                 INTEGER (0..10)      DEFAULT 0,
                      -- numberOfEntries             INTEGER (6..16),
                      -- numberOfEntries is covered by the size of the list in IE PredefinedConfigValueTagList
                      valueTagList                 PredefinedConfigValueTagList
}

PredefinedConfigValueTagList ::=    SEQUENCE (SIZE (1..maxPredefConfig)) OF
                                    PredefinedConfigValueTag

PredefinedConfigStatusListVarSz ::= SEQUENCE (SIZE (1..maxPredefConfig)) OF
                                    PredefinedConfigStatusInfo

RAB-Info ::=          SEQUENCE {
                      rab-Identity,
                      cn-DomainIdentity,
                      nas-Synchronisation-Indicator OPTIONAL,
                      re-EstablishmentTimer
}

```

```

RAB-Info-r6-ext ::= SEQUENCE {
    mbms-SessionIdentity
} OPTIONAL

RAB-Info-r6 ::= SEQUENCE {
    rab-Identity,
    mbms-SessionIdentity MBMS-SessionIdentity OPTIONAL,
    cn-DomainIdentity CN-DomainIdentity,
    nas-Synchronisation-Indicator NAS-Synchronisation-Indicator OPTIONAL,
    re-EstablishmentTimer Re-EstablishmentTimer
}

RAB-InformationList ::= SEQUENCE (SIZE (1..maxRABsetup)) OF
    RAB-Info

RAB-InformationReconfigList ::= SEQUENCE (SIZE (1.. maxRABsetup)) OF
    RAB-InformationReconfig

RAB-InformationReconfig ::= SEQUENCE {
    rab-Identity,
    cn-DomainIdentity,
    nas-Synchronisation-Indicator
}

RAB-Info-Post ::= SEQUENCE {
    rab-Identity,
    cn-DomainIdentity,
    nas-Synchronisation-Indicator
} OPTIONAL

RAB-InformationSetup ::= SEQUENCE {
    rab-Info,
    rb-InformationSetupList
}

RAB-InformationSetup-r4 ::= SEQUENCE {
    rab-Info,
    rb-InformationSetupList-r4
}

RAB-InformationSetup-r5 ::= SEQUENCE {
    rab-Info,
    rb-InformationSetupList
}

RAB-InformationSetup-r6-ext ::= SEQUENCE {
    rab-Info-r6-ext
}

RAB-InformationSetup-r6 ::= SEQUENCE {
    rab-Info RAB-Info-r6,
    rb-InformationSetupList RB-InformationSetupList-r6
}

RAB-InformationSetupList ::= SEQUENCE (SIZE (1..maxRABsetup)) OF
    RAB-InformationSetup

RAB-InformationSetupList-r4 ::= SEQUENCE (SIZE (1..maxRABsetup)) OF
    RAB-InformationSetup-r4

RAB-InformationSetupList-r5 ::= SEQUENCE (SIZE (1..maxRABsetup)) OF
    RAB-InformationSetup-r5

RAB-InformationSetupList-r6 ::= SEQUENCE (SIZE (1..maxRABsetup)) OF
    RAB-InformationSetup-r6

-- The IE 'RAB-InformationSetupList-r6-ext' provides elements of extension information, which
-- are added to the corresponding elements of the IE 'RAB-InformationSetupList/-r4/-r5'.
RAB-InformationSetupList-r6-ext ::= SEQUENCE (SIZE (1..maxRABsetup)) OF
    RAB-InformationSetup-r6-ext

RB-ActivationTimeInfo ::= SEQUENCE {
    rb-Identity,
    rlc-SequenceNumber
}

RB-ActivationTimeInfoList ::= SEQUENCE (SIZE (1..maxRB)) OF

```

```

RB-ActivationTimeInfo

RB-COUNT-C-Information ::=      SEQUENCE {
    rb-Identity,
    count-C-UL,
    count-C-DL
}

RB-COUNT-C-InformationList ::=   SEQUENCE (SIZE (1..maxRBallRABs)) OF
                                RB-COUNT-C-Information

RB-COUNT-C-MSB-Information ::=  SEQUENCE {
    rb-Identity,
    count-C-MSB-UL,
    count-C-MSB-DL
}

RB-COUNT-C-MSB-InformationList ::= SEQUENCE (SIZE (1..maxRBallRABs)) OF
                                    RB-COUNT-C-MSB-Information

RB-Identity ::=                  INTEGER (1..32)

RB-IdentityList ::=             SEQUENCE (SIZE (1..maxRB)) OF
                                RB-Identity

RB-InformationAffected ::=      SEQUENCE {
    rb-Identity,
    rb-MappingInfo
}

RB-InformationAffected-r5 ::=   SEQUENCE {
    rb-Identity,
    rb-MappingInfo
}

RB-InformationAffected-r6 ::=   SEQUENCE {
    rb-Identity,
    rb-MappingInfo
}

RB-InformationAffectedList ::=  SEQUENCE (SIZE (1..maxRB)) OF
                                RB-InformationAffected

RB-InformationAffectedList-r5 ::= SEQUENCE (SIZE (1..maxRB)) OF
                                RB-InformationAffected-r5

RB-InformationAffectedList-r6 ::= SEQUENCE (SIZE (1..maxRB)) OF
                                RB-InformationAffected-r6

RB-InformationReconfig ::=      SEQUENCE {
    rb-Identity,
    pdcp-Info,
    pdcp-SN-Info,
    rlc-Info,
    rb-MappingInfo,
    rb-StopContinue
}

RB-InformationReconfig-r4 ::=   SEQUENCE {
    rb-Identity,
    pdcp-Info,
    pdcp-SN-Info,
    rlc-Info,
    rb-MappingInfo,
    rb-StopContinue
}

RB-InformationReconfig-r5 ::=   SEQUENCE {
    rb-Identity,
    pdcp-Info,
    pdcp-SN-Info,
    rlc-Info,
    rb-MappingInfo,
    rb-StopContinue
}

RB-InformationReconfig-r6 ::=   SEQUENCE {
    rb-Identity,
    RB-Identity,
    RB-Identity,
    COUNT-C-MSB,
    COUNT-C-MSB
}

```

```

pdcp-Info          PDCP-InfoReconfig-r4      OPTIONAL,
pdcp-SN-Info       PDCP-SN-Info           OPTIONAL,
rlc-Info           RLC-Info-r5            OPTIONAL,
rb-MappingInfo     RB-MappingInfo-r6      OPTIONAL,
rb-StopContinue    RB-StopContinue        OPTIONAL
}

RB-InformationReconfigList ::= SEQUENCE (SIZE (1..maxRB)) OF
                               RB-InformationReconfig

RB-InformationReconfigList-r4 ::= SEQUENCE (SIZE (1..maxRB)) OF
                                 RB-InformationReconfig-r4

RB-InformationReconfigList-r5 ::= SEQUENCE (SIZE (1..maxRB)) OF
                                 RB-InformationReconfig-r5

RB-InformationReconfigList-r6 ::= SEQUENCE (SIZE (1..maxRB)) OF
                                 RB-InformationReconfig-r6

RB-InformationReleaseList ::= SEQUENCE (SIZE (1..maxRB)) OF
                               RB-Identity

RB-InformationSetup ::= SEQUENCE {
                           rb-Identity,
                           pdcp-Info,
                           rlc-InfoChoice,
                           rb-MappingInfo
                         }
                               OPTIONAL,

RB-InformationSetup-r4 ::= SEQUENCE {
                           rb-Identity,
                           pdcp-Info,
                           rlc-InfoChoice,
                           rb-MappingInfo
                         }
                               OPTIONAL,

RB-InformationSetup-r5 ::= SEQUENCE {
                           rb-Identity,
                           pdcp-Info,
                           rlc-InfoChoice,
                           rb-MappingInfo
                         }
                               OPTIONAL,

RB-InformationSetup-r6 ::= SEQUENCE {
                           rb-Identity,
                           pdcp-Info,
                           rlc-InfoChoice,
                           rb-MappingInfo
                         }
                               OPTIONAL,
}

RB-InformationSetupList ::= SEQUENCE (SIZE (1..maxRBperRAB)) OF
                            RB-InformationSetup

RB-InformationSetupList-r4 ::= SEQUENCE (SIZE (1..maxRBperRAB)) OF
                            RB-InformationSetup-r4

RB-InformationSetupList-r5 ::= SEQUENCE (SIZE (1..maxRBperRAB)) OF
                            RB-InformationSetup-r5

RB-InformationSetupList-r6 ::= SEQUENCE (SIZE (1..maxRBperRAB)) OF
                            RB-InformationSetup-r6

RB-MappingInfo ::= SEQUENCE (SIZE (1..maxRBMuxOptions)) OF
                     RB-MappingOption

RB-MappingInfo-r5 ::= SEQUENCE (SIZE (1..maxRBMuxOptions)) OF
                     RB-MappingOption-r5

RB-MappingInfo-r6 ::= SEQUENCE (SIZE (1..maxRBMuxOptions)) OF
                     RB-MappingOption-r6

RB-MappingOption ::= SEQUENCE {
                     ul-LogicalChannelMappings,
                     dl-LogicalChannelMappingList
                   }
                     OPTIONAL,
                     OPTIONAL

RB-MappingOption-r5 ::= SEQUENCE {
                     ul-LogicalChannelMappings
                   }
                     OPTIONAL,

```

```

dl-Layer2-LogicalChannelMappingList      DL-Layer2-LogicalChannelMappingList-r5      OPTIONAL
}

RB-MappingOption-r6 ::=          SEQUENCE {
  ul-Layer2-LogicalChannelMappings      UL-Layer2-LogicalChannelMappings      OPTIONAL,
  dl-Layer2-LogicalChannelMappingList    DL-Layer2-LogicalChannelMappingList-r5    OPTIONAL
}

RB-PDCPContextRelocation ::=          SEQUENCE {
  rb-Identity                         RB-Identity,
  dl-RFC3095-Context-Relocation       BOOLEAN,
  ul-RFC3095-Context-Relocation       BOOLEAN
}

RB-PDCPContextRelocationList ::=          SEQUENCE (SIZE (1..maxRBallRABs)) OF
                                          RB-PDCPContextRelocation

RB-StopContinue ::=          ENUMERATED {
  stopRB, continueRB }

RB-WithPDCP-Info ::=          SEQUENCE {
  rb-Identity,
  pdcp-SN-Info
}

RB-WithPDCP-InfoList ::=          SEQUENCE (SIZE (1..maxRBallRABs)) OF
                                   RB-WithPDCP-Info

ReceivingWindowSize ::=          ENUMERATED {
  rw1, rw8, rw16, rw32, rw64, rw128, rw256,
  rw512, rw768, rw1024, rw1536, rw2047,
  rw2560, rw3072, rw3584, rw4095 }

RFC2507-Info ::=          SEQUENCE {
  f-MAX-PERIOD                      INTEGER (1..65535)                      DEFAULT 256,
  f-MAX-TIME                         INTEGER (1..255)                        DEFAULT 5,
  max-HEADER                          INTEGER (60..65535)                     DEFAULT 168,
  tcp-SPACE                           INTEGER (3..255)                        DEFAULT 15,
  non-TCP-SPACE                       INTEGER (3..65535)                     DEFAULT 15,
  -- TABULAR: expectReordering has only two possible values, so using Optional or Default
  -- would be wasteful
  expectReordering                    ExpectReordering
}

RFC3095-Info-r4 ::=          SEQUENCE {
  rohcProfileList                    ROHC-ProfileList-r4,
  ul-RFC3095                        UL-RFC3095-r4                         OPTIONAL,
  dl-RFC3095                        DL-RFC3095-r4                         OPTIONAL
}

RLC-Info ::=          SEQUENCE {
  ul-RLC-Mode                        UL-RLC-Mode,
  dl-RLC-Mode                        DL-RLC-Mode
}

RLC-Info-r5 ::=          SEQUENCE {
  ul-RLC-Mode                        UL-RLC-Mode,
  dl-RLC-Mode-r5                     DL-RLC-Mode-r5                         OPTIONAL,
  rlc-OneSidedReEst                  BOOLEAN
}

RLC-Info-r6 ::=          SEQUENCE {
  ul-RLC-Mode                        UL-RLC-Mode,
  dl-RLC-Mode-r5                     DL-RLC-Mode-r6                         OPTIONAL,
  rlc-OneSidedReEst                  BOOLEAN
}

RLC-InfoChoice ::=          CHOICE {
  rlc-Info                           RLC-Info,
  same-as-RB                         RB-Identity
}

RLC-InfoChoice-r5 ::=          CHOICE {
  rlc-Info-r5                        RLC-Info-r5,
  same-as-RB                         RB-Identity
}

RLC-PDU-Size ::=          OctetModeRLC-SizeInfoType1

```

```

RLC-PDU-SizeList ::= SEQUENCE (SIZE (1..maxRLCPDUsizePerLogChan)) OF
                  RLC-PDU-Size

RLC-SequenceNumber ::= INTEGER (0..4095)

RLC-SizeInfo ::= SEQUENCE {
   rlc-SizeIndex
}

RLC-SizeExplicitList ::= SEQUENCE (SIZE (1..maxTF)) OF
   RLC-SizeInfo

ROHC-Profile-r4 ::= INTEGER (1..3)

ROHC-ProfileList-r4 ::= SEQUENCE (SIZE (1..maxROHC-Profile-r4)) OF
   ROHC-Profile-r4

ROHC-PacketSize-r4 ::= INTEGER (2..1500)

ROHC-PacketSizeList-r4 ::= SEQUENCE (SIZE (1..maxROHC-PacketSizes-r4)) OF
   ROHC-PacketSize-r4

SRB-InformationSetup ::= SEQUENCE {
   -- The default value for rb-Identity is the smallest value not used yet.
   rb-Identity
   rlc-InfoChoice
   rb-MappingInfo
}
OPTIONAL,
   RB-Identity
   RLC-InfoChoice,
   RB-MappingInfo

SRB-InformationSetup-r5 ::= SEQUENCE {
   -- The default value for rb-Identity is the smallest value not used yet.
   rb-Identity
   rlc-InfoChoice
   rb-MappingInfo
}
OPTIONAL,
   RB-Identity
   RLC-InfoChoice-r5,
   RB-MappingInfo-r5

SRB-InformationSetup-r6 ::= SEQUENCE {
   -- The default value for rb-Identity is the smallest value not used yet.
   rb-Identity
   rlc-InfoChoice
   rb-MappingInfo
}
OPTIONAL,
   RB-Identity
   RLC-InfoChoice-r6,
   RB-MappingInfo-r6

SRB-InformationSetupList ::= SEQUENCE (SIZE (1..maxSRBsetup)) OF
   SRB-InformationSetup

SRB-InformationSetupList-r5 ::= SEQUENCE (SIZE (1..maxSRBsetup)) OF
   SRB-InformationSetup-r5

SRB-InformationSetupList-r6 ::= SEQUENCE (SIZE (1..maxSRBsetup)) OF
   SRB-InformationSetup-r6

SRB-InformationSetupList2 ::= SEQUENCE (SIZE (3..4)) OF
   SRB-InformationSetup

TimerDAR-r6 ::= ENUMERATED {
   ms40, ms80, ms160, ms320, ms640,
   ms1280, ms2560, ms5120
}

TimerDiscard ::= ENUMERATED {
   td0-1, td0-25, td0-5, td0-75,
   td1, td1-25, td1-5, td1-75,
   td2, td2-5, td3, td3-5, td4,
   td4-5, td5, td7-5
}

TimerEPC ::= ENUMERATED {
   te50, te60, te70, te80, te90,
   te100, te120, te140, te160, te180,
   te200, te300, te400, te500, te700,
   te900
}

TimerMRW ::= ENUMERATED {
   te50, te60, te70, te80, te90, te100,
   te120, te140, te160, te180, te200,
   te300, te400, te500, te700, te900
}

TimerPoll ::= ENUMERATED {
}

```

```

tp10, tp20, tp30, tp40, tp50,
tp60, tp70, tp80, tp90, tp100,
tp110, tp120, tp130, tp140, tp150,
tp160, tp170, tp180, tp190, tp200,
tp210, tp220, tp230, tp240, tp250,
tp260, tp270, tp280, tp290, tp300,
tp310, tp320, tp330, tp340, tp350,
tp360, tp370, tp380, tp390, tp400,
tp410, tp420, tp430, tp440, tp450,
tp460, tp470, tp480, tp490, tp500,
tp510, tp520, tp530, tp540, tp550,
tp600, tp650, tp700, tp750, tp800,
tp850, tp900, tp950, tp1000 }

TimerPollPeriodic ::= ENUMERATED {
    tper100, tper200, tper300, tper400,
    tper500, tper750, tper1000, tper2000 }

TimerPollProhibit ::= ENUMERATED {
    tpp10, tpp20, tpp30, tpp40, tpp50,
    tpp60, tpp70, tpp80, tpp90, tpp100,
    tpp110, tpp120, tpp130, tpp140, tpp150,
    tpp160, tpp170, tpp180, tpp190, tpp200,
    tpp210, tpp220, tpp230, tpp240, tpp250,
    tpp260, tpp270, tpp280, tpp290, tpp300,
    tpp310, tpp320, tpp330, tpp340, tpp350,
    tpp360, tpp370, tpp380, tpp390, tpp400,
    tpp410, tpp420, tpp430, tpp440, tpp450,
    tpp460, tpp470, tpp480, tpp490, tpp500,
    tpp510, tpp520, tpp530, tpp540, tpp550,
    tpp600, tpp650, tpp700, tpp750, tpp800,
    tpp850, tpp900, tpp950, tpp1000 }

TimerRST ::= ENUMERATED {
    tr50, tr100, tr150, tr200, tr250, tr300,
    tr350, tr400, tr450, tr500, tr550,
    tr600, tr700, tr800, tr900, tr1000 }

TimerStatusPeriodic ::= ENUMERATED {
    tsp100, tsp200, tsp300, tsp400, tsp500,
    tsp750, tsp1000, tsp2000 }

TimerStatusProhibit ::= ENUMERATED {
    tsp10,tsp20,tsp30,tsp40,tsp50,
    tsp60,tsp70,tsp80,tsp90,tsp100,
    tsp110,tsp120,tsp130,tsp140,tsp150,
    tsp160,tsp170,tsp180,tsp190,tsp200,
    tsp210,tsp220,tsp230,tsp240,tsp250,
    tsp260,tsp270,tsp280,tsp290,tsp300,
    tsp310,tsp320,tsp330,tsp340,tsp350,
    tsp360,tsp370,tsp380,tsp390,tsp400,
    tsp410,tsp420,tsp430,tsp440,tsp450,
    tsp460,tsp470,tsp480,tsp490,tsp500,
    tsp510,tsp520,tsp530,tsp540,tsp550,
    tsp600,tsp650,tsp700,tsp750,tsp800,
    tsp850,tsp900,tsp950,tsp1000 }

TransmissionRLC-Discard ::= CHOICE {
    timerBasedExplicit,
    timerBasedNoExplicit,
    maxDAT-Retransmissions,
    noDiscard
}

TransmissionWindowSize ::= ENUMERATED {
    tw1, tw8, tw16, tw32, tw64, tw128, tw256,
    tw512, tw768, tw1024, tw1536, tw2047,
    tw2560, tw3072, tw3584, tw4095 }

UL-AM-RLC-Mode ::= SEQUENCE {
    transmissionRLC-Discard,
    transmissionWindowSize,
    timerRST,
    max-RST,
    pollingInfo
} OPTIONAL

UL-CounterSynchronisationInfo ::= SEQUENCE {
}

```

```

rb-WithPDCP-InfoList           RB-WithPDCP-InfoList   OPTIONAL,
startList                      STARTList
}

UL-LogicalChannelMapping ::=      SEQUENCE {
-- TABULAR: UL-TransportChannelType contains TransportChannelIdentity as well.
ul-TransportChannelType        UL-TransportChannelType,
logicalChannelIdentity         LogicalChannelIdentity   OPTIONAL,
rlc-SizeList                   CHOICE {
  allSizes                     NULL,
  configured                  NULL,
  explicitList                RLC-SizeExplicitList
},
mac-LogicalChannelPriority     MAC-LogicalChannelPriority
}

UL-LogicalChannelMapping-r6 ::=   SEQUENCE {
ul-TrCH-Type                  CHOICE {
  dch-rach-cpch-usch          SEQUENCE {
-- TABULAR: UL-TransportChannelType contains TransportChannelIdentity as well.
  ul-TransportChannelType      UL-TransportChannelType,
  logicalChannelIdentity       LogicalChannelIdentity   OPTIONAL,
  rlc-SizeList                 CHOICE {
    allSizes                   NULL,
    configured                NULL,
    explicitList              RLC-SizeExplicitList
  },
  e-dch                       SEQUENCE {
    e-DCH-MAC-d-FlowIdentity  E-DCH-MAC-d-FlowIdentity,
    ddi                        DDI,
    rlc-PDU-SizeList          RLC-PDU-SizeList
  }
},
mac-LogicalChannelPriority     MAC-LogicalChannelPriority
}

UL-LogicalChannelMappingList ::=  SEQUENCE {
-- rlc-LogicalChannelMappingIndicator shall be set to TRUE in this version
-- of the specification
rlc-LogicalChannelMappingIndicator BOOLEAN,
ul-LogicalChannelMapping        SEQUENCE (SIZE (maxLoCHperRLC)) OF
                                  UL-LogicalChannelMapping
}
}

UL-LogicalChannelMappingList-r6 ::= SEQUENCE {
-- rlc-LogicalChannelMappingIndicator shall be set to TRUE in this version
-- of the specification
rlc-LogicalChannelMappingIndicator BOOLEAN,
ul-LogicalChannelMapping        SEQUENCE (SIZE (maxLoCHperRLC)) OF
                                  UL-LogicalChannelMapping-r6
}

UL-LogicalChannelMappings ::=    CHOICE {
  oneLogicalChannel             UL-LogicalChannelMapping,
  twoLogicalChannels            UL-LogicalChannelMappingList
}
}

UL-LogicalChannelMappings-r6 ::=  CHOICE {
  oneLogicalChannel             UL-LogicalChannelMapping-r6,
  twoLogicalChannels            UL-LogicalChannelMappingList-r6
}

UL-RFC3095-r4 ::=               SEQUENCE {
  cid-InclusionInfo            CID-InclusionInfo-r4,
  max-CID                      INTEGER (1..16383)           DEFAULT 15,
  rohcPacketSizeList            ROHC-PacketSizeList-r4
}

UL-RLC-Mode ::=                 CHOICE {
  ul-AM-RLC-Mode               UL-AM-RLC-Mode,
  ul-UM-RLC-Mode               UL-UM-RLC-Mode,
  ul-TM-RLC-Mode               UL-TM-RLC-Mode,
  spare                         NULL
}

UL-TM-RLC-Mode ::=              SEQUENCE {
  transmissionRLC-Discard     TransmissionRLC-Discard
}                               OPTIONAL,

```

```

    segmentationIndication           BOOLEAN
}

UL-UM-RLC-Mode ::= SEQUENCE {
    transmissionRLC-Discard
} OPTIONAL

|_ 1  
_ 2

UL-TransportChannelType ::= CHOICE {
    dch
    rach
    cpch
    usch
    TransportChannelIdentity
}

UM-RLC-DuplAvoid-Reord-Info-r6 ::= SEQUENCE {
    windowSize-OSSD
    WindowSizeOSSD-r6
}

UM-RLC-OutOfSeqDelivery-Info-r6 ::= SEQUENCE {
    timer-DAR
    widowSize-DAR
    TimerDAR-r6,
    WindowSizeDAR-r6
}

WindowSizeDAR-r6 ::= ENUMERATED {
    ws32, ws64, ws128, spare1
}

WindowSizeOSSD-r6 ::= ENUMERATED {
    ws32, ws64, ws128, spare1
}

-- *****
-- TRANSPORT CHANNEL INFORMATION ELEMENTS (10.3.5)
-- *****

AddOrReconfMAC-dFlow ::= SEQUENCE {
    mac-hs-AddReconfQueue-List
    mac-hs-DelQueue-List
    MAC-hs-AddReconfQueue-List OPTIONAL,
    MAC-hs-DelQueue-List OPTIONAL
}

AllowedTFC-List ::= SEQUENCE (SIZE (1..maxTFC)) OF
    TFC-Value

AllowedTFI-List ::= SEQUENCE (SIZE (1..maxTF)) OF
    INTEGER (0..31)

BitModeRLC-SizeInfo ::= CHOICE {
    sizeType1
        INTEGER (0..127),
    -- Actual value sizeType2 = (part1 * 8) + 128 + part2
    sizeType2
        SEQUENCE {
            part1
                INTEGER (0..15),
            part2
                INTEGER (1..7)
        },
    -- Actual value sizeType3 = (part1 * 16) + 256 + part2
    sizeType3
        SEQUENCE {
            part1
                INTEGER (0..47),
            part2
                INTEGER (1..15)
        },
    -- Actual value sizeType4 = (part1 * 64) + 1024 + part2
    sizeType4
        SEQUENCE {
            part1
                INTEGER (0..62),
            part2
                INTEGER (1..63)
        }
    }

-- Actual value BLER-QualityValue = IE value * 0.1
BLER-QualityValue ::= INTEGER (-63..0)

ChannelCodingType ::= CHOICE {
    -- noCoding is only used for TDD in this version of the specification,
    -- otherwise it should be ignored
    noCoding
        NULL,
    convolutional
        CodingRate,
    turbo
        NULL
}

CodingRate ::= ENUMERATED {

```

```

half,
third }

CommonDynamicTF-Info ::= SEQUENCE {
    rlc-Size
        CHOICE {
            fdd
                OctetModeRLC-SizeInfoType2
            },
            tdd
                CHOICE {
                    commonTDD-Choice
                        bitModeRLC-SizeInfo
                        OctetModeRLC-SizeInfoType1
                    }
                },
            numberOfTbSizeList
                SEQUENCE (SIZE (1..maxTF)) OF
                    NumberOfTransportBlocks,
            logicalChannelList
        }
}

CommonDynamicTF-Info-DynamicTTI ::= SEQUENCE {
    commonTDD-Choice
        CHOICE {
            bitModeRLC-SizeInfo
                BitModeRLC-SizeInfo,
            octetModeRLC-SizeInfoType1
                OctetModeRLC-SizeInfoType1
        },
    numberOfTbSizeAndTTIList
        NumberOfTbSizeAndTTIList,
    logicalChannelList
}

CommonDynamicTF-InfoList ::= SEQUENCE (SIZE (1..maxTF)) OF
    CommonDynamicTF-Info

CommonDynamicTF-InfoList-DynamicTTI ::= SEQUENCE (SIZE (1..maxTF)) OF
    CommonDynamicTF-Info-DynamicTTI

CommonTransChTFS ::= SEQUENCE {
    tti
        CHOICE {
            tti10
                CommonDynamicTF-InfoList,
            tti20
                CommonDynamicTF-InfoList,
            tti40
                CommonDynamicTF-InfoList,
            tti80
                CommonDynamicTF-InfoList,
            dynamic
                CommonDynamicTF-InfoList-DynamicTTI
        },
    semistaticTF-Information
        SemistaticTF-Information
}

CommonTransChTFS-LCR ::= SEQUENCE {
    tti
        CHOICE {
            tti5
                CommonDynamicTF-InfoList,
            tti10
                CommonDynamicTF-InfoList,
            tti20
                CommonDynamicTF-InfoList,
            tti40
                CommonDynamicTF-InfoList,
            tti80
                CommonDynamicTF-InfoList,
            dynamic
                CommonDynamicTF-InfoList-DynamicTTI
        },
    semistaticTF-Information
        SemistaticTF-Information
}

CPCH-SetID ::= INTEGER (1..maxCPCHsets)

CRC-Size ::= ENUMERATED {
    crc0, crc8, crc12, crc16, crc24 }

DedicatedDynamicTF-Info ::= SEQUENCE {
    rlc-Size
        CHOICE {
            bitMode
                BitModeRLC-SizeInfo,
            octetModeType1
                OctetModeRLC-SizeInfoType1
        },
    numberOfTbSizeList
        SEQUENCE (SIZE (1..maxTF)) OF
            NumberOfTransportBlocks,
    logicalChannelList
        LogicalChannelList
}

DedicatedDynamicTF-Info-DynamicTTI ::= SEQUENCE {
    rlc-Size
        CHOICE {
            bitMode
                BitModeRLC-SizeInfo,
            octetModeType1
                OctetModeRLC-SizeInfoType1
        },
}

```

```

numberOfTbSizeAndTTIList           NumberOfTbSizeAndTTIList,
logicalChannelList                LogicalChannelList
}

DedicatedDynamicTF-InfoList ::=      SEQUENCE (SIZE (1..maxTF)) OF
                                         DedicatedDynamicTF-Info

DedicatedDynamicTF-InfoList-DynamicTTI ::= SEQUENCE (SIZE (1..maxTF)) OF
                                         DedicatedDynamicTF-Info-DynamicTTI

DedicatedTransChTFS ::=             SEQUENCE {
                                         CHOICE {
                                             tti10
                                             tti20
                                             tti40
                                             tti80
                                             dynamic
                                         },
                                         semistaticTF-Information
                                         SemistaticTF-Information
}

-- The maximum allowed size of DL-AddReconfTransChInfo2List sequence is 16
DL-AddReconfTransChInfo2List ::=      SEQUENCE (SIZE (1..maxTrCHpreconf)) OF
                                         DL-AddReconfTransChInformation2

-- The maximum allowed size of DL-AddReconfTransChInfoList sequence is 16
DL-AddReconfTransChInfoList ::=      SEQUENCE (SIZE (1..maxTrCHpreconf)) OF
                                         DL-AddReconfTransChInformation

-- The maximum allowed size of DL-AddReconfTransChInfoList-r4 sequence is 16
DL-AddReconfTransChInfoList-r4 ::=   SEQUENCE (SIZE (1..maxTrCHpreconf)) OF
                                         DL-AddReconfTransChInformation-r4

-- The maximum allowed size of DL-AddReconfTransChInfoList-r5 sequence is 16
DL-AddReconfTransChInfoList-r5 ::=   SEQUENCE (SIZE (1..maxTrCHpreconf)) OF
                                         DL-AddReconfTransChInformation-r5

-- ASN.1 for IE "Added or Reconfigured DL TrCH information"
-- in case of messages other than: Radio Bearer Release message and
-- RadioBearer Reconfiguration message
DL-AddReconfTransChInformation ::=  SEQUENCE {
                                         dl-TransportChannelType          DL-TrCH-Type,
                                         dl-transportChannelIdentity       TransportChannelIdentity,
                                         tfs-SignallingMode               CHOICE {
                                             explicit-config
                                             sameAsULTrCH
                                         },
                                         dch-QualityTarget                QualityTarget
                                         OPTIONAL,
                                         -- dummy is not used in this version of the specification, it should
                                         -- not be sent and if received it should be ignored.
                                         dummy                           TM-SignallingInfo
                                         OPTIONAL
}

DL-AddReconfTransChInformation-r4 ::= SEQUENCE {
                                         dl-TransportChannelType          DL-TrCH-Type,
                                         dl-transportChannelIdentity       TransportChannelIdentity,
                                         tfs-SignallingMode               CHOICE {
                                             explicit-config
                                             sameAsULTrCH
                                         },
                                         dch-QualityTarget                QualityTarget
                                         OPTIONAL
}

DL-AddReconfTransChInformation-r5 ::= SEQUENCE {
                                         dl-TransportChannelType          DL-TrCH-TypeId1-r5,
                                         tfs-SignallingMode               CHOICE {
                                             explicit-config
                                             sameAsULTrCH
                                             hdsch
                                         },
                                         dch-QualityTarget                QualityTarget
                                         OPTIONAL
}

-- ASN.1 for IE "Added or Reconfigured DL TrCH information"
-- in case of Radio Bearer Release message and
-- RadioBearer Reconfiguration message
DL-AddReconfTransChInformation2 ::= SEQUENCE {
                                         dl-TransportChannelType          DL-TrCH-Type,
                                         ...
}

```

```

transportChannelIdentity
tfs-SignallingMode
  explicit-config
  sameAsULTrCH
},
qualityTarget
}
}

DL-CommonTransChInfo ::= SEQUENCE {
  sccpch-TFCS
  modeSpecificInfo
}
-- modeSpecificInfo should be optional. A new version of this IE should be defined
-- to be used in later versions of messages using this IE
  CHOICE {
    fdd
      dl-Parameters
        dl-DCH-TFCS
        sameAsUL
    },
    tdd
      individualDL-CCTrCH-InfoList
}
}
}

DL-CommonTransChInfo-r4 ::= SEQUENCE {
  sccpch-TFCS
  modeSpecificInfo
}
-- modeSpecificInfo should be optional. A new version of this IE should be defined
-- to be used in later versions of messages using this IE
  CHOICE {
    fdd
      dl-Parameters
        dl-DCH-TFCS
        tfcs
    },
    sameAsUL
  },
  tdd
    individualDL-CCTrCH-InfoList
}
}
}

DL-DeletedTransChInfoList ::= SEQUENCE (SIZE (1..maxTrCH)) OF
  DL-TransportChannelIdentity

DL-DeletedTransChInfoList-r5 ::= SEQUENCE (SIZE (1..maxTrCH)) OF
  DL-TransportChannelIdentity-r5

DL-TransportChannelIdentity ::= SEQUENCE {
  dl-TransportChannelType
  dl-TransportChannelIdentity
}
}

DL-TransportChannelIdentity-r5 ::= SEQUENCE {
  dl-TransportChannelType
}
}

| DL-TrCH-Type ::= ENUMERATED {dch, dsch}

DL-TrCH-TypeId1-r5 ::= CHOICE {
  dch
  dsch
  hsdsch
}
}

DL-TrCH-TypeId2-r5 ::= CHOICE {
  dch
  dsch
  hsdsch
}
}

DRAC-ClassIdentity ::= INTEGER (1..maxDRACclasses)

DRAC-StaticInformation ::= SEQUENCE {
  transmissionTimeValidity
  timeDurationBeforeRetry
}

```

```

drac-ClassIdentity          DRAC-ClassIdentity
}

DRAC-StaticInformationList ::= SEQUENCE (SIZE (1..maxTrCH)) OF
                               DRAC-StaticInformation

E-DCH-AddReconf-MAC-d-Flow ::= SEQUENCE {
  mac-d-FlowIdentity           E-DCH-MAC-d-FlowIdentity,
  mac-d-FlowPowerOffset         E-DCH-MAC-d-FlowPowerOffset OPTIONAL,
  mac-d-FlowMaxRetrans          E-DCH-MAC-d-FlowMaxRetrans OPTIONAL,
  mac-d-FlowMultiplexingList   E-DCH-MAC-d-FlowMultiplexingList OPTIONAL
}

E-DCH-Harq-Info ::= INTEGER (1..maxHarqRTT)

E-DCH-MAC-d-FlowIdentity ::= INTEGER (0..maxE-DCHMACdFlow)

E-DCH-MAC-d-FlowMaxRetrans ::= INTEGER (0)                                -- FFS

E-DCH-MAC-d-FlowMultiplexingList ::= BIT STRING (SIZE (maxE-DCHMACdFlow-1))

E-DCH-MAC-d-FlowPowerOffset ::= INTEGER (0)                                -- FFS

E-DCH-TTI ::= ENUMERATED { tti2, tti10 }

ExplicitTFCS-Configuration ::= CHOICE {
  complete                   TFCS-ReconfAdd,
  addition                   TFCS-ReconfAdd,
  removal                    TFCS-RemovalList,
  replacement                SEQUENCE {
    tfcsRemoval              TFCS-RemovalList,
    tfcsAdd                  TFCS-ReconfAdd
  }
}

GainFactor ::= INTEGER (0..15)

GainFactorInformation ::= CHOICE {
  signalledGainFactors      SignalledGainFactors,
  computedGainFactors       ReferenceTFC-ID
}

HSDSCH-Info ::= SEQUENCE {
  harqInfo                  HARQ-Info          OPTIONAL,
  addOrReconfMAC-dFlow      AddOrReconfMAC-dFlow OPTIONAL
}

HARQ-Info ::= SEQUENCE {
  numberOfProcesses          INTEGER (1..8),
  memoryPartitioning        CHOICE {
    implicit                 NULL,
    explicit                 SEQUENCE (SIZE (1..maxHProcesses)) OF
                                HARQMemorySize
  }
}

HARQMemorySize ::= ENUMERATED {
  hms800, hms1600, hms2400, hms3200, hms4000,
  hms4800, hms5600, hms6400, hms7200, hms8000,
  hms8800, hms9600, hms10400, hms11200, hms12000,
  hms12800, hms13600, hms14400, hms15200, hms16000,
  hms17600, hms19200, hms20800, hms22400, hms24000,
  hms25600, hms27200, hms28800, hms30400, hms32000,
  hms36000, hms40000, hms44000, hms48000, hms52000,
  hms56000, hms60000, hms64000, hms68000, hms72000,
  hms76000, hms80000, hms88000, hms96000, hms104000,
  hms112000, hms120000, hms128000, hms136000, hms144000,
  hms152000, hms160000, hms176000, hms192000, hms208000,
  hms224000, hms240000, hms256000, hms272000, hms288000,
  hms304000
}

IndividualDL-CCTrCH-Info ::= SEQUENCE {
  dl-TFCS-Identity,
  tfcs-SignallingMode,
  explicit-config,
  sameAsUL
}

```

```

IndividualDL-CCTrCH-InfoList ::=      SEQUENCE (SIZE (1..maxCCTrCH)) OF
                                         IndividualDL-CCTrCH-Info

IndividualUL-CCTrCH-Info ::=          SEQUENCE {
                                         ul-TFCS-Identity,
                                         ul-TFCS,
                                         tfc-Subset
                                         }

IndividualUL-CCTrCH-InfoList ::=     SEQUENCE (SIZE (1..maxCCTrCH)) OF
                                         IndividualUL-CCTrCH-Info

LogicalChannelByRB ::=               SEQUENCE {
                                         rb-Identity,
                                         logChOfRb
                                         }

LogicalChannelList ::=               CHOICE {
                                         allSizes
                                         NULL,
                                         configured
                                         NULL,
                                         explicitList
                                         SEQUENCE (SIZE (1..15)) OF
                                         LogicalChannelByRB
                                         }

MAC-d-FlowIdentityDCHandHSDSCH ::=   SEQUENCE {
                                         dch-transport-ch-id
                                         hsd sch-mac-d-flow-id
                                         }

MAC-d-FlowIdentity ::=                INTEGER (0..7)

MAC-d-PDU-SizeInfo-List ::=         SEQUENCE (SIZE(1.. maxMAC-d-PDUsizes)) OF
                                         MAC-d-PDUSizeInfo

--MAC-d-Pdu sizes need to be defined
MAC-d-PDUSizeInfo ::=               SEQUENCE{
                                         mac-d-PDU-Size
                                         INTEGER (1..5000),
                                         mac-d-PDU-Index
                                         INTEGER(0..7)
                                         }

MAC-hs-AddReconfQueue-List ::=       SEQUENCE (SIZE(1..maxQueueIDs)) OF
                                         MAC-hs-AddReconfQueue

MAC-hs-AddReconfQueue ::=            SEQUENCE {
                                         mac-hsQueueId
                                         mac-dFlowId
                                         reorderingReleaseTimer
                                         mac-hsWindowSize
                                         mac-d-PDU-SizeInfo-List
                                         }

MAC-hs-DelQueue-List ::=             SEQUENCE (SIZE(1..maxQueueIDs)) OF
                                         MAC-hs-DelQueue

MAC-hs-DelQueue ::=                 SEQUENCE {
                                         mac-hsQueueId
                                         INTEGER(0..7)
                                         }

MAC-hs-WindowSize ::=                ENUMERATED {
                                         mws4, mws6, mws8, mws12, mws16, mws24, mws32
                                         }

NumberOfTbSizeAndTTIList ::=        SEQUENCE (SIZE (1..maxTF)) OF SEQUENCE {
                                         numberOfTransportBlocks,
                                         transmissionTimeInterval
                                         }

MessType ::=                         ENUMERATED {
                                         transportFormatCombinationControl
                                         }

Non-allowedTFC-List ::=             SEQUENCE (SIZE (1..maxTFC)) OF
                                         TFC-Value

NumberOfTransportBlocks ::=          CHOICE {
                                         zero
                                         NULL,
                                         one
                                         NULL,
                                         small
                                         INTEGER (2..17),
                                         large
                                         INTEGER (18..512)
                                         }

```

```

}

OctetModeRLC-SizeInfoType1 ::=      CHOICE {
  -- Actual size = (8 * sizeType1) + 16
  sizeType1                  INTEGER (0..31),
  sizeType2                  SEQUENCE {
    -- Actual size = (32 * part1) + 272 + (part2 * 8)
    part1                    INTEGER (0..23),
    part2                    INTEGER (1..3)
  },
  sizeType3                  SEQUENCE {
    -- Actual size = (64 * part1) + 1040 + (part2 * 8)
    part1                    INTEGER (0..61),
    part2                    INTEGER (1..7)
  }
}

OctetModeRLC-SizeInfoType2 ::=      CHOICE {
  -- Actual size = (sizeType1 * 8) + 48
  sizeType1                  INTEGER (0..31),
  -- Actual size = (sizeType2 * 16) + 312
  sizeType2                  INTEGER (0..63),
  -- Actual size = (sizeType3 * 64) + 1384
  sizeType3                  INTEGER (0..56)
}

PowerOffsetInformation ::=          SEQUENCE {
  gainFactorInformation      GainFactorInformation,
  -- PowerOffsetPp-m is always absent in TDD
  powerOffsetPp-m            PowerOffsetPp-m
}                                     OPTIONAL

PowerOffsetPp-m ::=                 INTEGER (-5..10)

PreDefTransChConfiguration ::=     SEQUENCE {
  ul-CommonTransChInfo       UL-CommonTransChInfo,
  ul-AddReconfTrChInfoList  UL-AddReconfTransChInfoList,
  dl-CommonTransChInfo       DL-CommonTransChInfo,
  dl-TrChInfoList            DL-AddReconfTransChInfoList
}

QualityTarget ::=                 SEQUENCE {
  bler-QualityValue          BLER-QualityValue
}

RateMatchingAttribute ::=          INTEGER (1..hiRM)

ReferenceTFC-ID ::=                INTEGER (0..3)

RestrictedTrChInfo ::=           SEQUENCE {
  ul-TransportChannelType   UL-TrCH-Type,
  restrictedTrChIdentity   TransportChannelIdentity,
  allowedTFI-List           AllowedTFI-List
}                                     OPTIONAL

RestrictedTrChInfoList ::=        SEQUENCE (SIZE (1..maxTrCH)) OF
                                  RestrictedTrChInfo

SemistaticTF-Information ::=      SEQUENCE {
  -- TABULAR: Transmission time interval has been included in the IE CommonTransChTFS.
  channelCodingType          ChannelCodingType,
  rateMatchingAttribute      RateMatchingAttribute,
  crc-Size                   CRC-Size
}

SignalledGainFactors ::=          SEQUENCE {
  modeSpecificInfo           CHOICE {
    fdd                      SEQUENCE {
      gainFactorBetaC         GainFactor
    },
    tdd                      NULL
  },
  gainFactorBetaD            GainFactor,
  referenceTFC-ID            ReferenceTFC-ID
}                                     OPTIONAL

SplitTFCI-Signalling ::=         SEQUENCE {
}

```

```

splitType                                SplitType           OPTIONAL,
tfci-Field2-Length                      INTEGER (1..10)    OPTIONAL,
tfci-Field1-Information                 ExplicitTFCS-Configuration OPTIONAL,
tfci-Field2-Information                 TFCI-Field2-Information  OPTIONAL
}

SplitType ::= ENUMERATED {
    hardSplit, logicalSplit }

T1-ReleaseTimer ::= ENUMERATED {
    rt10, rt20, rt30, rt40, rt50,
    rt60, rt70, rt80, rt90, rt100,
    rt120, rt140, rt160, rt200, rt300,
    rt400 }

TFC-Subset ::= CHOICE {
    minimumAllowedTFC-Number,
    allowedTFC-List,
    non-allowedTFC-List,
    restrictedTrChInfoList,
    fullTFCS
}

TFC-Subset-ID-With3b ::= INTEGER (0..7)

TFC-Subset-ID-With5b ::= INTEGER (0..31)

TFC-Subset-ID-With10b ::= INTEGER (0..1023)

TFC-SubsetList ::= SEQUENCE (SIZE (1.. maxTFCsub)) OF SEQUENCE {
    modeSpecificInfo
        fdd
        tdd
            tfcs-ID
        }
    },
    tfc-Subset
}

TFC-Value ::= INTEGER (0..1023)

TFCI-Field2-Information ::= CHOICE {
    tfci-Range
    explicit-config
}

TFCI-Range ::= SEQUENCE {
    maxTFCIField2Value
    tfcs-InfoForDSCH
}

TFCI-RangeList ::= SEQUENCE (SIZE (1..maxPDSCH-TFCIgroups)) OF
    TFCI-Range

TFCS ::= CHOICE {
    normalTFCI-Signalling
    splitTFCI-Signalling
}

TFCS-Identity ::= SEQUENCE {
    tfcs-ID
    sharedChannelIndicator
}

TFCS-IdentityPlain ::= INTEGER (1..8)

TFCS-InfoForDSCH ::= CHOICE {
    ctfc2bit
    ctfc4bit
    ctfc6bit
    ctfc8bit
    ctfc12bit
    ctfc16bit
    ctfc24bit
}

TFCS-ReconfAdd ::= SEQUENCE{
    ctfcSize
    CHOICE{
}
}

```

```

ctfc2Bit
  ctfc2
  powerOffsetInformation
},
ctfc4Bit
  ctfc4
  powerOffsetInformation
},
ctfc6Bit
  ctfc6
  powerOffsetInformation
},
ctfc8Bit
  ctfc8
  powerOffsetInformation
},
ctfc12Bit
  ctfc12
  powerOffsetInformation
},
ctfc16Bit
  ctfc16
  powerOffsetInformation
},
ctfc24Bit
  ctfc24
  powerOffsetInformation
}
}

TFCS-Removal ::= SEQUENCE {
  tfci
}

TFCS-RemovalList ::= SEQUENCE (SIZE (1..maxTFC)) OF
  TFCS-Removal

TimeDurationBeforeRetry ::= INTEGER (1..256)

TM-SignallingInfo ::= SEQUENCE {
  messType
  tm-SignallingMode
    mode1
    mode2
      -- in ul-controlledTrChList, TrCH-Type is always DCH
      ul-controlledTrChList
        UL-ControlledTrChList
}
}

TransmissionTimeInterval ::= ENUMERATED {
  tti10, tti20, tti40, tti80 }

TransmissionTimeValidity ::= INTEGER (1..256)

TransportChannelIdentity ::= INTEGER (1..32)

TransportChannelIdentityDCHandDSCH ::= SEQUENCE {
  dch-transport-ch-id
  dsch-transport-ch-id
}

TransportFormatSet ::= CHOICE {
  dedicatedTransChTFS
  commonTransChTFS
}

TransportFormatSet-LCR ::= CHOICE {
  dedicatedTransChTFS,
  commonTransChTFS-LCR
}

-- The maximum allowed size of UL-AddReconfTransChInfoList sequence is 16
UL-AddReconfTransChInfoList ::= SEQUENCE (SIZE (1..maxTrCHpreconf)) OF
  UL-AddReconfTransChInformation
|

```

```

-- The maximum allowed size of UL-AddReconfTransChInfoList-r6 sequence is 32
UL-AddReconfTransChInfoList-r6 ::= SEQUENCE (SIZE (1..maxTrCH)) OF
    UL-AddReconfTransChInformation-r6

UL-AddReconfTransChInformation ::= SEQUENCE {
    ul-TransportChannelType           UL-TrCH-Type,
    transportChannelIdentity          TransportChannelIdentity,
    transportFormatSet                TransportFormatSet
}

UL-AddReconfTransChInformation-r6 ::= CHOICE {
    dch-usch                         SEQUENCE {
        ul-TransportChannelType       UL-TrCH-Type,
        transportChannelIdentity     TransportChannelIdentity,
        transportFormatSet           TransportFormatSet
    },
    e-dch                            SEQUENCE {
        tti                           E-DCH-TTI,
        harq-Info                     E-DCH-Harq-Info,
        addReconf-MAC-d-Flow          E-DCH-AddReconf-MAC-d-Flow
    }
}

UL-CommonTransChInfo ::= SEQUENCE {
    -- TABULAR: tfc-subset is applicable to FDD only, TDD specifies tfc-subset in individual
    -- CCTrCH Info.
    tfc-Subset                      TFC-Subset                  OPTIONAL,
    prach-TFCS                      TFCS                      OPTIONAL,
    modeSpecificInfo                 CHOICE {
        fdd                          SEQUENCE {
            ul-TFCS                   TFCS
        },
        tdd                          SEQUENCE {
            individualUL-CCTrCH-InfoList IndividualUL-CCTrCH-InfoList
        }
    }
}

UL-CommonTransChInfo-r4 ::= SEQUENCE {
    -- TABULAR: tfc-subset is applicable to FDD only, TDD specifies tfc-subset in individual
    -- CCTrCH Info.
    tfc-Subset                      TFC-Subset                  OPTIONAL,
    prach-TFCS                      TFCS                      OPTIONAL,
    modeSpecificInfo                 CHOICE {
        fdd                          SEQUENCE {
            ul-TFCS                   TFCS
        },
        tdd                          SEQUENCE {
            individualUL-CCTrCH-InfoList IndividualUL-CCTrCH-InfoList
        }
    }
    tfc-SubsetList                   TFC-SubsetList             OPTIONAL
}

-- In UL-ControlledTrChList, TrCH-Type is always DCH
UL-ControlledTrChList ::= SEQUENCE (SIZE (1..maxTrCH)) OF
    TransportChannelIdentity

UL-DeletedTransChInfoList ::= SEQUENCE (SIZE (1..maxTrCH)) OF
    UL-TransportChannelIdentity

UL-DeletedTransChInfoList-r6 ::= SEQUENCE (SIZE (1..maxTrCH)) OF
    UL-TransportChannelIdentity-r6

UL-TransportChannelIdentity ::= SEQUENCE {
    ul-TransportChannelType           UL-TrCH-Type,
    ul-TransportChannelIdentity      TransportChannelIdentity
}

UL-TransportChannelIdentity-r6 ::= CHOICE {
    dch-usch                         SEQUENCE {
        ul-TransportChannelType       UL-TrCH-Type,
        ul-TransportChannelIdentity   TransportChannelIdentity
    },
    e-dch                            E-DCH-MAC-d-FlowIdentity
}

```

```

| UL-TrCH-Type ::=-- ENUMERATED {dch, usch}
USCH-TransportChannelsInfo ::= SEQUENCE (SIZE (1..maxTrCH)) OF
  usch-TransportChannelIdentity
  usch-TFS
}
-- ****
-- PHYSICAL CHANNEL INFORMATION ELEMENTS (10.3.6)
-- ****

ACK-NACK-repetitionFactor ::= INTEGER(1..4)
AC-To-ASC-Mapping ::= INTEGER (0..7)
AC-To-ASC-MappingTable ::= SEQUENCE (SIZE (maxASCMAP)) OF
  AC-To-ASC-Mapping

AccessServiceClass-FDD ::= SEQUENCE {
  availableSignaturestartIndex
  availableSignature endIndex
  assignedSubChannelNumber
  }
}

AccessServiceClass-TDD ::= SEQUENCE {
  channelisationCodeIndices
  subchannelSize
    size1
    size2
      -- subch0 means bitstring '01' in the tabular, subch1 means bitstring '10'
      subchannels
    },
  size4
    subchannels
  },
  size8
    subchannels
  }
}

AccessServiceClass-TDD-LCR-r4 ::= SEQUENCE {
  availableSYNC-UlCodesIndics
  BIT STRING {
    sulCodeIndex7(0),
    sulCodeIndex6(1),
    sulCodeIndex5(2),
  }
}

```

```

                                sulCodeIndex4(3),
                                sulCodeIndex3(4),
                                sulCodeIndex2(5),
                                sulCodeIndex1(6),
                                sulCodeIndex0(7)
                                } (SIZE(8))           OPTIONAL,
subchannelSize
size1
size2
-- subch0 means bitstring '01' in the tabular, subch1 means bitsring '10'.
subchannels
                                CHOICE {
                                NULL,
                                SEQUENCE {
                                -- subch0 means bitstring '01' in the tabular, subch1 means bitsring '10'.
                                ENUMERATED { subch0, subch1 } OPTIONAL
                                },
                                size4
                                subchannels
                                SEQUENCE {
                                BIT STRING {
                                subCh3(0),
                                subCh2(1),
                                subCh1(2),
                                subCh0(3)
                                } (SIZE(4))           OPTIONAL
                                },
                                size8
                                subchannels
                                SEQUENCE {
                                BIT STRING {
                                subCh7(0),
                                subCh6(1),
                                subCh5(2),
                                subCh4(3),
                                subCh3(4),
                                subCh2(5),
                                subCh1(6),
                                subCh0(7)
                                } (SIZE(8))           OPTIONAL
                                }
                                }
}
}

AICH-Info ::= SEQUENCE {
    channelisationCode256
    sttd-Indicator
    aich-TransmissionTiming
}

AICH-PowerOffset ::= INTEGER (-22..5)

AICH-TransmissionTiming ::= ENUMERATED {
    e0, e1
}

AllocationPeriodInfo ::= SEQUENCE {
    allocationActivationTime
    allocationDuration
    INTEGER (0..255),
    INTEGER (1..256)
}

-- Actual value Alpha = IE value * 0.125
Alpha ::= INTEGER (0..8)

AP-AICH-ChannelisationCode ::= INTEGER (0..255)

AP-PreambleScramblingCode ::= INTEGER (0..79)

AP-Signature ::= INTEGER (0..15)

AP-Signature-VCAM ::= SEQUENCE {
    ap-Signature
    availableAP-SubchannelList
    AP-Signature,
    AvailableAP-SubchannelList OPTIONAL
}

AP-Subchannel ::= INTEGER (0..11)

ASCSetting-FDD ::= SEQUENCE {
    -- TABULAR: accessServiceClass-FDD is MD in tabular description
    -- Default value is previous ASC
    -- If this is the first ASC, the default value is all available signature and sub-channels
    accessServiceClass-FDD
    AccessServiceClass-FDD OPTIONAL
}

ASCSetting-TDD ::= SEQUENCE {
    -- TABULAR: accessServiceClass-TDD is MD in tabular description
    -- Default value is previous ASC
}

```

```

-- If this is the first ASC, the default value is all available channelisation codes and
-- all available sub-channels with subchannelSize=size1.
accessServiceClass-TDD                               AccessServiceClass-TDD  OPTIONAL
}

ASCSetting-TDD-LCR-r4 ::=          SEQUENCE {
-- TABULAR: accessServiceClass-TDD-LCR is MD in tabular description
-- Default value is previous ASC
-- If this is the first ASC, the default value is all available SYNC_UL codes and
-- all available sub-channels with subchannelSize=size1.
accessServiceClass-TDD-LCR                         AccessServiceClass-TDD-LCR-r4  OPTIONAL
}

AvailableAP-Signature-VCAMList ::=  SEQUENCE (SIZE (1..maxPCPCH-APsig)) OF
                                    AP-Signature-VCAM

AvailableAP-SignatureList ::=        SEQUENCE (SIZE (1..maxPCPCH-APsig)) OF
                                    AP-Signature

AvailableAP-SubchannelList ::=       SEQUENCE (SIZE (1..maxPCPCH-APsubCh)) OF
                                    AP-Subchannel

AvailableMinimumSF-ListVCAM ::=     SEQUENCE (SIZE (1..maxPCPCH-SF)) OF
                                    AvailableMinimumSF-VCAM

AvailableMinimumSF-VCAM ::=         SEQUENCE {
                                    minimumSpreadingFactor,
                                    nf-Max,
                                    maxAvailablePCPCH-Number,
                                    availableAP-Signature-VCAMList
}

AvailableSignatures ::=           BIT STRING {
                                    signature15(0),
                                    signature14(1),
                                    signature13(2),
                                    signature12(3),
                                    signature11(4),
                                    signature10(5),
                                    signature9(6),
                                    signature8(7),
                                    signature7(8),
                                    signature6(9),
                                    signature5(10),
                                    signature4(11),
                                    signature3(12),
                                    signature2(13),
                                    signature1(14),
                                    signature0(15)
}      (SIZE(16))

AvailableSubChannelNumbers ::=    BIT STRING {
                                    subCh11(0),
                                    subCh10(1),
                                    subCh9(2),
                                    subCh8(3),
                                    subCh7(4),
                                    subCh6(5),
                                    subCh5(6),
                                    subCh4(7),
                                    subCh3(8),
                                    subCh2(9),
                                    subCh1(10),
                                    subCh0(11)
}      (SIZE(12))

BurstType ::=                     ENUMERATED {
                                    type1, type2 }

-- Actual value Bler-Target = IE value * 0.05
Bler-Target ::=                   INTEGER (-63..0)

CCTrCH-PowerControlInfo ::=      SEQUENCE {
                                    tfcs-Identity,
                                    ul-DPCH-PowerControlInfo
}                                     OPTIONAL,

CCTrCH-PowerControlInfo-r4 ::=   SEQUENCE {

```

```

tfcs-Identity
ul-DPCH-PowerControlInfo
}

CCTrCH-PowerControlInfo-r5 ::= SEQUENCE {
    tfcs-Identity
    ul-DPCH-PowerControlInfo
}
OPTIONAL,
UL-DPCH-PowerControlInfo-r4

CD-AccessSlotSubchannel ::= INTEGER (0..11)

CD-AccessSlotSubchannelList ::= SEQUENCE (SIZE (1..maxPCPCH-CDsubCh)) OF
CD-AccessSlotSubchannel

CD-CA-ICH-ChannelisationCode ::= INTEGER (0..255)

CD-PreambleScramblingCode ::= INTEGER (0..79)

CD-SignatureCode ::= INTEGER (0..15)

CD-SignatureCodeList ::= SEQUENCE (SIZE (1..maxPCPCH-CDSig)) OF
CD-SignatureCode

CellAndChannelIdentity ::= SEQUENCE {
    burstType,
    midambleShift,
    timeslot,
    cellParametersID
}
OPTIONAL,
BurstType,
MidambleShiftLong,
TimeslotNumber,
CellParametersID

CellParametersID ::= INTEGER (0..127)

Cfntargetsfnframeoffset ::= INTEGER(0..255)

ChannelAssignmentActive ::= CHOICE {
    notActive
    isActive
}
NULL,
AvailableMinimumSF-ListVCAM

ChannelisationCode256 ::= INTEGER (0..255)

ChannelReqParamsForUCSM ::= SEQUENCE {
    availableAP-SignatureList,
    availableAP-SubchannelList
}
OPTIONAL,
AvailableAP-SignatureList,
AvailableAP-SubchannelList

ClosedLoopTimingAdjMode ::= ENUMERATED {
    slot1, slot2
}

CodeNumberDSCH ::= INTEGER (0..255)

CodeRange ::= SEQUENCE {
    pdsch-CodeMapList
}
PDSCH-CodeMapList

CodeWordSet ::= ENUMERATED {
    longCWS,
    mediumCWS,
    shortCWS,
    ssdtOff
}

CommonTimeslotInfo ::= SEQUENCE {
    -- TABULAR: secondInterleavingMode is MD, but since it can be encoded in a single
    -- bit it is not defined as OPTIONAL.
    secondInterleavingMode
    SecondInterleavingMode,
    tfci-Coding
    TFCI-Coding
    puncturingLimit
    PuncturingLimit
    repetitionPeriodAndLength
    RepetitionPeriodAndLength
}
OPTIONAL,
TFCI-Coding
PuncturingLimit
RepetitionPeriodAndLength

CommonTimeslotInfoSCCPCH ::= SEQUENCE {
    -- TABULAR: secondInterleavingMode is MD, but since it can be encoded in a single
    -- bit it is not defined as OPTIONAL.
    secondInterleavingMode
    SecondInterleavingMode,
    tfci-Coding
    TFCI-Coding
    puncturingLimit
    PuncturingLimit
    repetitionPeriodLengthAndOffset
    RepetitionPeriodLengthAndOffset
}
OPTIONAL,
TFCI-Coding
PuncturingLimit
RepetitionPeriodLengthAndOffset

```

```

ConstantValue ::= INTEGER (-35..-10)

ConstantValueTdd ::= INTEGER (-35..10)

CPCH-PersistenceLevels ::= SEQUENCE {
    cpch-SetID,
    dynamicPersistenceLevelTF-List
}

CPCH-PersistenceLevelsList ::= SEQUENCE (SIZE (1..maxCPCHsets)) OF
    CPCH-PersistenceLevels

CPCH-SetInfo ::= SEQUENCE {
    cpch-SetID,
    transportFormatSet,
    tfcs,
    ap-PreambleScramblingCode,
    ap-AICH-ChannelisationCode,
    cd-PreambleScramblingCode,
    cd-CA-ICH-ChannelisationCode,
    cd-AccessSlotSubchannelList,
    cd-SignatureCodeList,
    deltaPp-m,
    ul-DPCCH-SlotFormat,
    n-StartMessage,
    n-EOT,
    -- TABULAR: VCAM info has been nested inside ChannelAssignmentActive,
    -- which in turn is mandatory since it's only a binary choice.
    channelAssignmentActive,
    cpch-StatusIndicationMode,
    pcpch-ChannelInfoList
}

CPCH-SetInfoList ::= SEQUENCE (SIZE (1..maxCPCHsets)) OF
    CPCH-SetInfo

CPCH-StatusIndicationMode ::= ENUMERATED {
    pa-mode,
    pamsf-mode
}

CQI-RepetitionFactor ::= INTEGER(1..4)

CSICH-PowerOffset ::= INTEGER (-10..5)

-- DefaultDPCH-OffsetValueFDD and DefaultDPCH-OffsetValueTDD corresponds to
-- IE "Default DPCH Offset Value" depending on the mode.
-- Actual value DefaultDPCH-OffsetValueFDD = IE value * 512
DefaultDPCH-OffsetValueFDD ::= INTEGER (0..599)

DefaultDPCH-OffsetValueTDD ::= INTEGER (0..7)

DeltaPp-m ::= INTEGER (-10..10)

DeltaCQI ::= INTEGER (0..8)

DeltaNACK ::= INTEGER (0..8)

DeltaACK ::= INTEGER (0..8)

-- Actual value DeltaSIR = IE value * 0.1
DeltaSIR ::= INTEGER (0..30)

DL-CCTrCh ::= SEQUENCE {
    tfcs-ID,
    timeInfo,
    commonTimeslotInfo,
    dl-CCTrCH-TimeslotsCodes,
    ul-CCTrChTPCList
}

DL-CCTrCh-r4 ::= SEQUENCE {
    tfcs-ID,
    timeInfo,
    commonTimeslotInfo,
    tddOption,
    tdd384,
    dl-CCTrCH-TimeslotsCodes
}

    CHOICE {
        SEQUENCE {
            TFCS-IdentityPlain,
            TimeInfo,
            CommonTimeslotInfo,
            DownlinkTimeslotsCodes
        }
        DOWNLINKTIMESLOTSOPTIONAL
    }
}

```

```

},
tdd128
    dl-CCTrCH-TimeslotsCodes
}
},
ul-CCTrChTPCList
}
}

DL-CCTrChList ::= SEQUENCE (SIZE (1..maxCCTrCH)) OF DL-CCTrCh

DL-CCTrChList-r4 ::= SEQUENCE (SIZE (1..maxCCTrCH)) OF DL-CCTrCh-r4

DL-CCTrChListToRemove ::= SEQUENCE (SIZE (1..maxCCTrCH)) OF TFCS-IdentityPlain

DL-CCTrChTPCList ::= SEQUENCE (SIZE (0..maxCCTrCH)) OF TFCS-Identity

DL-ChannelisationCode ::= SEQUENCE {
    secondaryScramblingCode OPTIONAL,
    sf-AndCodeNumber,
    scramblingCodeChange OPTIONAL
}

DL-ChannelisationCodeList ::= SEQUENCE (SIZE (1..maxDPCH-DLchan)) OF DL-ChannelisationCode

DL-CommonInformation ::= SEQUENCE {
    dl-DPCH-InfoCommon OPTIONAL,
    modeSpecificInfo CHOICE {
        fdd {
            defaultDPCH-OffsetValue OPTIONAL,
            dpch-CompressedModeInfo OPTIONAL,
            tx-DiversityMode OPTIONAL,
            ssdt-Information OPTIONAL
        },
        tdd {
            defaultDPCH-OffsetValue OPTIONAL
        }
    }
}

DL-CommonInformation-r4 ::= SEQUENCE {
    dl-DPCH-InfoCommon OPTIONAL,
    modeSpecificInfo CHOICE {
        fdd {
            defaultDPCH-OffsetValue OPTIONAL,
            dpch-CompressedModeInfo OPTIONAL,
            tx-DiversityMode OPTIONAL,
            ssdt-Information OPTIONAL
        },
        tdd {
            tddOption {
                tdd384,
                tdd128
                    tstd-Indicator
            }
        },
        defaultDPCH-OffsetValue OPTIONAL
    }
}

DL-CommonInformation-r5 ::= SEQUENCE {
    dl-DPCH-InfoCommon OPTIONAL,
    modeSpecificInfo CHOICE {
        fdd {
            defaultDPCH-OffsetValue OPTIONAL,
            dpch-CompressedModeInfo OPTIONAL,
            tx-DiversityMode OPTIONAL,
            ssdt-Information OPTIONAL
        },
        tdd {
            tddOption {
                tdd384
            }
        }
    }
}

```

```

        tdd128
          tstd-Indicator
        }
      },
      defaultDPCH-OffsetValue
      DefaultDPCH-OffsetValueTDD OPTIONAL
    }
  },
  mac-hsResetIndicator
  ENUMERATED { true } OPTIONAL
}

DL-CommonInformationPost ::= SEQUENCE {
  dl-DPCH-InfoCommon
}

DL-CommonInformationPredef ::= SEQUENCE {
  dl-DPCH-InfoCommon
  DL-DPCH-InfoCommonPredef OPTIONAL
}

DL-CompressedModeMethod ::= ENUMERATED {
  puncturing, sf-2,
  higherLayerScheduling }

DL-DPCH-InfoCommon ::= SEQUENCE {
  cfnHandling
    CHOICE {
      maintain
        NULL,
      initialise
        SEQUENCE {
          Cfntargetsfnframeoffset
          Cfntargetsfnframeoffset
        }
      },
      modeSpecificInfo
        CHOICE {
          fdd
            SEQUENCE {
              dl-DPCH-PowerControlInfo
              PowerOffsetPilot-pdpdch,
              dl-rate-matching-restriction
              Dl-rate-matching-restriction
              -- TABULAR: The number of pilot bits is nested inside the spreading factor.
              spreadingFactorAndPilot
              SF512-AndPilot,
              positionFixedOrFlexible
              PositionFixedOrFlexible,
              tfci-Existence
              BOOLEAN
            },
          tdd
            SEQUENCE {
              dl-DPCH-PowerControlInfo
              DL-DPCH-PowerControlInfo
            }
        }
    }
}

DL-DPCH-InfoCommon-r4 ::= SEQUENCE {
  cfnHandling
    CHOICE {
      maintain
        NULL,
      initialise
        SEQUENCE {
          Cfntargetsfnframeoffset
          Cfntargetsfnframeoffset
        }
      },
      modeSpecificInfo
        CHOICE {
          fdd
            SEQUENCE {
              dl-DPCH-PowerControlInfo
              PowerOffsetPilot-pdpdch,
              dl-rate-matching-restriction
              Dl-rate-matching-restriction
              -- TABULAR: The number of pilot bits is nested inside the spreading factor.
              spreadingFactorAndPilot
              SF512-AndPilot,
              positionFixedOrFlexible
              PositionFixedOrFlexible,
              tfci-Existence
              BOOLEAN
            },
          tdd
            SEQUENCE {
              dl-DPCH-PowerControlInfo
              DL-DPCH-PowerControlInfo
            }
        }
    },
    -- The IE mac-d-HFN-initial-value should be absent in the RRCConnectionSetup-r4-IEs or
    -- RRCConnectionSetup-r5-IEs or HandoverToUTRANCommand-r4-IEs or HandoverToUTRANCommand-r5-IEs and
    -- if the IE is included, the general error handling for conditional IEs applies.
    mac-d-HFN-initial-value
      MAC-d-HFN-initial-value OPTIONAL
}

DL-DPCH-InfoCommonPost ::= SEQUENCE {
  dl-DPCH-PowerControlInfo
  DL-DPCH-PowerControlInfo
}

```

```

DL-DPCH-InfoCommonPredef ::= SEQUENCE {
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            -- TABULAR: The number of pilot bits is nested inside the spreading factor.
            spreadingFactorAndPilot SF512-AndPilot,
            positionFixedOrFlexible PositionFixedOrFlexible,
            tfci-Existence BOOLEAN
        },
        tdd SEQUENCE {
            commonTimeslotInfo CommonTimeslotInfo
        }
    }
}

DL-DPCH-InfoPerRL ::= CHOICE {
    fdd SEQUENCE {
        pCPICH-UsageForChannelEst,
        dpch-FrameOffset,
        secondaryCPICH-Info OPTIONAL,
        dl-ChannelisationCodeList,
        tpc-CombinationIndex,
        ssdt-CellIdentity OPTIONAL,
        closedLoopTimingAdjMode OPTIONAL
    },
    tdd SEQUENCE {
        dl-CCTrChListToEstablish,
        dl-CCTrChListToRemove OPTIONAL,
        dl-CCTrChListToEstablish OPTIONAL
    }
}

DL-DPCH-InfoPerRL-r4 ::= CHOICE {
    fdd SEQUENCE {
        pCPICH-UsageForChannelEst,
        dpch-FrameOffset,
        secondaryCPICH-Info OPTIONAL,
        dl-ChannelisationCodeList,
        tpc-CombinationIndex,
        ssdt-CellIdentity OPTIONAL,
        closedLoopTimingAdjMode OPTIONAL
    },
    tdd SEQUENCE {
        dl-CCTrChListToEstablish,
        dl-CCTrChListToRemove OPTIONAL,
        dl-CCTrChListToEstablish OPTIONAL
    }
}

DL-DPCH-InfoPerRL-r5 ::= CHOICE {
    fdd SEQUENCE {
        pCPICH-UsageForChannelEst,
        dpch-FrameOffset,
        secondaryCPICH-Info OPTIONAL,
        dl-ChannelisationCodeList,
        tpc-CombinationIndex,
        powerOffsetTPC-pdpdch OPTIONAL,
        ssdt-CellIdentity OPTIONAL,
        closedLoopTimingAdjMode OPTIONAL
    },
    tdd SEQUENCE {
        dl-CCTrChListToEstablish,
        dl-CCTrChListToRemove OPTIONAL,
        dl-CCTrChListToEstablish OPTIONAL
    }
}

DL-DPCH-InfoPerRL-PostFDD ::= SEQUENCE {
    pCPICH-UsageForChannelEst,
    dl-ChannelisationCode,
    tpc-CombinationIndex
}

DL-DPCH-InfoPerRL-PostTDD ::= SEQUENCE {
    dl-DPCH-TimeslotsCodes
}

DL-DPCH-InfoPerRL-PostTDD-LCR-r4 ::= SEQUENCE {
    dl-CCTrCH-TimeslotsCodes
}

DL-DPCH-PowerControlInfo ::= SEQUENCE {

```

```

modeSpecificInfo
  fdd
    dpc-Mode
  },
  tdd
    tpc-StepSizeTDD
  }
}

DL-FrameType ::= ENUMERATED {
  dl-FrameTypeA, dl-FrameTypeB }

DL-HSPDSCH-Information ::= SEQUENCE {
  hs-scch-Info OPTIONAL,
  measurement-feedback-Info OPTIONAL,
  modeSpecificInfo CHOICE {
    tdd CHOICE {
      tdd384 SEQUENCE {
        dl-HSPDSCH-TS-Configuration DL-HSPDSCH-TS-Configuration OPTIONAL
      },
      tdd128 SEQUENCE {
        hs-PDSCH-Midamble-Configuration-TDD128
          HS-PDSCH-Midamble-Configuration-TDD128 OPTIONAL
      }
    },
    fdd NULL
  }
}

-- The IE 'DL-HSPDSCH-TS-Configuration' applies to tdd-384 REL-5 onward
DL-HSPDSCH-TS-Configuration ::= SEQUENCE (SIZE (1..maxTS-2)) OF
  SEQUENCE {
    timeslot TimeslotNumber,
    midambleShiftAndBurstType MidambleShiftAndBurstType-DL
  }

DL-InformationPerRL ::= SEQUENCE {
  modeSpecificInfo CHOICE {
    fdd SEQUENCE {
      primaryCPICH-Info,
      pdsch-SHO-DCH-Info OPTIONAL,
      pdsch-CodeMapping OPTIONAL
    },
    tdd PrimaryCCPCH-Info
  },
  dl-DPCH-InfoPerRL OPTIONAL,
  sccpch-InfoforFACH OPTIONAL
}

DL-InformationPerRL-r4 ::= SEQUENCE {
  modeSpecificInfo CHOICE {
    fdd SEQUENCE {
      primaryCPICH-Info,
      pdsch-SHO-DCH-Info OPTIONAL,
      pdsch-CodeMapping OPTIONAL
    },
    tdd PrimaryCCPCH-Info-r4
  },
  dl-DPCH-InfoPerRL OPTIONAL,
  sccpch-InfoforFACH OPTIONAL,
  cell-id OPTIONAL
}

DL-InformationPerRL-r5 ::= SEQUENCE {
  modeSpecificInfo CHOICE {
    fdd SEQUENCE {
      primaryCPICH-Info,
      pdsch-SHO-DCH-Info OPTIONAL,
      pdsch-CodeMapping OPTIONAL,
      servingHSDSCH-RL-indicator BOOLEAN
    },
    tdd PrimaryCCPCH-Info-r4
  },
  dl-DPCH-InfoPerRL OPTIONAL,
  sccpch-InfoforFACH OPTIONAL,
  cell-id OPTIONAL
}

```

```

DL-InformationPerRL-r5bis ::=      SEQUENCE {
    modeSpecificInfo          CHOICE {
        fdd                   SEQUENCE {
            primaryCPICH-Info   PrimaryCPICH-Info,
            pdsch-SHO-DCH-Info   PDSCH-SHO-DCH-Info
            pdsch-CodeMapping    PDSCH-CodeMapping
        },
        tdd                   PrimaryCCPCH-Info-r4
    },
    dl-DPCH-InfoPerRL         DL-DPCH-InfoPerRL-r5
    sccpch-InfoforFACH       SCCPCH-InfoForFACH-r4
    cell-id                  CellIdentity
}

DL-InformationPerRL-r6 ::=      SEQUENCE {
    modeSpecificInfo          CHOICE {
        fdd                   SEQUENCE {
            primaryCPICH-Info   PrimaryCPICH-Info,
            pdsch-SHO-DCH-Info   PDSCH-SHO-DCH-Info
            pdsch-CodeMapping    PDSCH-CodeMapping
            servingHSDSCH-RL-indicator BOOLEAN,
            servingEDCH-RL-indicator BOOLEAN
        },
        tdd                   PrimaryCCPCH-Info-r4
    },
    dl-DPCH-InfoPerRL         DL-DPCH-InfoPerRL-r5
    sccpch-InfoforFACH       SCCPCH-InfoForFACH-r4
    e-AGCH-Information       E-AGCH-Information
    e-HICH-Information       E-HICH-Information
    e-RGCH-Information       E-RGCH-Information
    cell-id                  CellIdentity
}

DL-InformationPerRL-List ::=      SEQUENCE (SIZE (1..maxRL)) OF
                                    DL-InformationPerRL

DL-InformationPerRL-List-r4 ::=      SEQUENCE (SIZE (1..maxRL)) OF
                                    DL-InformationPerRL-r4

DL-InformationPerRL-List-r5 ::=      SEQUENCE (SIZE (1..maxRL)) OF
                                    DL-InformationPerRL-r5

DL-InformationPerRL-List-r6 ::=      SEQUENCE (SIZE (1..maxRL)) OF
                                    DL-InformationPerRL-r6

DL-InformationPerRL-List-r5bis ::=     SEQUENCE (SIZE (1..maxRL)) OF
                                         DL-InformationPerRL-r5bis

DL-InformationPerRL-ListPostFDD ::=    SEQUENCE (SIZE (1..maxRL)) OF
                                         DL-InformationPerRL-PostFDD

DL-InformationPerRL-PostFDD ::=      SEQUENCE {
    primaryCPICH-Info          PrimaryCPICH-Info,
    dl-DPCH-InfoPerRL          DL-DPCH-InfoPerRL-PostFDD
}

DL-InformationPerRL-PostTDD ::=      SEQUENCE {
    primaryCCPCH-Info          PrimaryCCPCH-InfoPost,
    dl-DPCH-InfoPerRL          DL-DPCH-InfoPerRL-PostTDD
}

DL-InformationPerRL-PostTDD-LCR-r4 ::= SEQUENCE {
    primaryCCPCH-Info          PrimaryCCPCH-InfoPostTDD-LCR-r4,
    dl-DPCH-InfoPerRL          DL-DPCH-InfoPerRL-PostTDD-LCR-r4
}

DL-PDSCH-Information ::=      SEQUENCE {
    pdsch-SHO-DCH-Info          PDSCH-SHO-DCH-Info
    pdsch-CodeMapping           PDSCH-CodeMapping
}

Dl-rate-matching-restriction ::= SEQUENCE {
    restrictedTrCH-InfoList    RestrictedTrCH-InfoList
}

DL-TPC-PowerOffsetPerRL ::=      SEQUENCE {
    powerOffsetTPC-pdpdch      PowerOffsetTPC-pdpdch
}

```

```

}

-- NOTE: The radio links in the following list have a one-to-one mapping with the
-- radio links in the message.
DL-TPC-PowerOffsetPerRL-List ::= SEQUENCE (SIZE (1..maxRL)) OF
                                DL-TPC-PowerOffsetPerRL

DL-TS-ChannelisationCode ::= ENUMERATED {
                                cc16-1, cc16-2, cc16-3, cc16-4,
                                cc16-5, cc16-6, cc16-7, cc16-8,
                                cc16-9, cc16-10, cc16-11, cc16-12,
                                cc16-13, cc16-14, cc16-15, cc16-16 }

DL-TS-ChannelisationCodesShort ::= SEQUENCE {
    codesRepresentation CHOICE {
        consecutive      SEQUENCE {
            firstChannelisationCode
            lastChannelisationCode
        },
        bitmap           BIT STRING {
            chCode16-SF16(0),
            chCode15-SF16(1),
            chCode14-SF16(2),
            chCode13-SF16(3),
            chCode12-SF16(4),
            chCode11-SF16(5),
            chCode10-SF16(6),
            chCode9-SF16(7),
            chCode8-SF16(8),
            chCode7-SF16(9),
            chCode6-SF16(10),
            chCode5-SF16(11),
            chCode4-SF16(12),
            chCode3-SF16(13),
            chCode2-SF16(14),
            chCode1-SF16(15)
        } (SIZE (16))
    }
}

DownlinkAdditionalTimeslots ::= SEQUENCE {
    parameters CHOICE {
        sameAsLast      SEQUENCE {
            timeslotNumber
        },
        newParameters   SEQUENCE {
            individualTimeslotInfo
            dl-TS-ChannelisationCodesShort
        }
    }
}

DownlinkAdditionalTimeslots-LCR-r4 ::= SEQUENCE {
    parameters CHOICE {
        sameAsLast      SEQUENCE {
            timeslotNumber
        },
        newParameters   SEQUENCE {
            individualTimeslotInfo
            dl-TS-ChannelisationCodesShort
        }
    }
}

DownlinkTimeslotsCodes ::= SEQUENCE {
    firstIndividualTimeslotInfo IndividualTimeslotInfo,
    dl-TS-ChannelisationCodesShort DL-TS-ChannelisationCodesShort,
    moreTimeslots   CHOICE {
        noMore          NULL,
        additionalTimeslots CHOICE {
            consecutive      INTEGER (1..maxTS-1),
            timeslotList     SEQUENCE (SIZE (1..maxTS-1)) OF
                                DownlinkAdditionalTimeslots
        }
    }
}

DownlinkTimeslotsCodes-LCR-r4 ::= SEQUENCE {

```

```

firstIndividualTimeslotInfo          IndividualTimeslotInfo-LCR-r4,
dl-TS-ChannelisationCodesShort      DL-TS-ChannelisationCodesShort,
moreTimeslots                         CHOICE {
    noMore                           NULL,
    additionalTimeslots               CHOICE {
        consecutive                   INTEGER (1..maxTS-LCR-1),
        timeslotList                  SEQUENCE (SIZE (1..maxTS-LCR-1)) OF
                                         DownlinkAdditionalTimeslots-LCR-r4
    }
}
}

DPC-Mode ::= ENUMERATED {
    singleTPC,
    tpcTripletInSoft }

-- Actual value DPCCH-PowerOffset = IE value * 2
DPCCH-PowerOffset ::= INTEGER (-82..-3)

-- Actual value DPCCH-PowerOffset2 = 2 + (IE value * 4)
DPCCH-PowerOffset2 ::= INTEGER (-28..-13)

DPCH-CompressedModeInfo ::= SEQUENCE {
    tgp-SequenceList                TGP-SequenceList
}

DPCH-CompressedModeStatusInfo ::= SEQUENCE {
    tgps-Reconfiguration-CFN       TGPS-Reconfiguration-CFN,
    tgp-SequenceShortList          SEQUENCE (SIZE (1..maxTGPS)) OF
                                    TGP-SequenceShort
}

-- Actual value DPCH-FrameOffset = IE value * 256
DPCH-FrameOffset ::= INTEGER (0..149)

DSCH-Mapping ::= SEQUENCE {
    maxTFCI-Field2Value,
    spreadingFactor,
    codeNumber,
    multiCodeInfo
}

DSCH-MappingList ::= SEQUENCE (SIZE (1..maxPDSCH-TFCIgroups)) OF
                      DSCH-Mapping

DSCH-RadioLinkIdentifier ::= INTEGER (0..511)

DSCH-TransportChannelsInfo ::= SEQUENCE (SIZE (1..maxTrCH)) OF
                                SEQUENCE {
        dsch-transport-channel-identity TransportChannelIdentity,
        dsch-TFS                          TransportFormatSet
    }

DurationTimeInfo ::= INTEGER (1..4096)

DynamicPersistenceLevel ::= INTEGER (1..8)

DynamicPersistenceLevelList ::= SEQUENCE (SIZE (1..maxPRACH)) OF
                               DynamicPersistenceLevel

DynamicPersistenceLevelTF-List ::= SEQUENCE (SIZE (1..maxTF-CPCH)) OF
                                 DynamicPersistenceLevel

E-AGCH-ChannelisationCode ::= INTEGER (0..255)

E-AGCH-Information ::= SEQUENCE {
    dl-ScramblingCode             SecondaryScramblingCode OPTIONAL,
    e-AGCH-ChannelisationCode     E-AGCH-ChannelisationCode
}

E-DPCCH-Info ::= SEQUENCE {
    e-DPCCH-DPCCH-PowerOffset    E-DPCCH-DPCCH-PowerOffset
}

E-DPCCH-DPCCH-PowerOffset ::= INTEGER (0) -- FFS

E-DPDCH-Info ::= SEQUENCE {
    e-TFCI-ReferencePowerOffset  E-TFCI-ReferencePowerOffset,
    e-TFCI-TableIndex            E-TFCI-TableIndex,
}

```

```

e-DPDCH-MaxNChannelisationCodes      E-DPDCH-MaxNChannelisationCodes
1

E-DPDCH-MaxNChannelisationCodes ::= INTEGER (0)      -- FFS

E-HICH-ChannelisationCode ::=      INTEGER (0..127)

E-HICH-Information ::=      SEQUENCE {
    dl-ScramblingCode      SecondaryScramblingCode      OPTIONAL,
    channelisationCode      E-HICH-ChannelisationCode,
    signatureSequence      E-HICH-RGCH-SignatureSequence,
    timingOffset      E-HICH-RGCH-TimingOffset
}

E-HICH-RGCH-SignatureSequence ::=      INTEGER (0..39)

E-HICH-RGCH-TimingOffset ::=      INTEGER (0)      -- FFS

E-RGCH-CombinationIndex ::=      INTEGER (0..5)

E-RGCH-Information ::=      SEQUENCE {
    dl-ScramblingCode      SecondaryScramblingCode      OPTIONAL,
    signatureSequence      E-HICH-RGCH-SignatureSequence,
    timingOffset      E-HICH-RGCH-TimingOffset,
    rg-CombinationIndex      E-RGCH-CombinationIndex      OPTIONAL
}

E-TFCI-ReferencePowerOffset ::=      INTEGER (0)      -- FFS

E-TFCI-TableIndex ::=      ENUMERATED { ncc1, ncc2, ncc4 }

FACH-PCH-Information ::=      SEQUENCE {
    transportFormatSet      TransportFormatSet,
    transportChannelIdentity      TransportChannelIdentity,
    ctch-Indicator      BOOLEAN
}

FACH-PCH-InformationList ::=      SEQUENCE (SIZE (1..maxFACHPCH)) OF
                                FACH-PCH-Information

Feedback-cycle ::=      ENUMERATED {
    fc0, fc2, fc4, fc8, fc10, fc20, fc40, fc80, fc160
}

FPACH-Info-r4 ::=      SEQUENCE {
    timeslot      TimeslotNumber-LCR-r4,
    channelisationCode      TDD-FPACH-CCode16-r4,
    midambleShiftAndBurstType      MidambleShiftAndBurstType-LCR-r4,
    wi      Wi-LCR
}

FrequencyInfo ::=      SEQUENCE {
    modeSpecificInfo      CHOICE {
        fdd      FrequencyInfoFDD,
        tdd      FrequencyInfoTDD
    }
}

FrequencyInfoFDD ::=      SEQUENCE {
    uarfcn-UL      UARFCN      OPTIONAL,
    uarfcn-DL      UARFCN
}

FrequencyInfoTDD ::=      SEQUENCE {
    uarfcn-Nt      UARFCN
}

HARQ-Preamble-Mode ::=      INTEGER (0..1)

HS-ChannelisationCode-LCR ::=      ENUMERATED {
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
    cc16-9, cc16-10, cc16-11, cc16-12,
    cc16-13, cc16-14, cc16-15, cc16-16
}

HS-PDSCH-Midamble-Configuration-TDD128 ::=      SEQUENCE {
    midambleAllocationMode      CHOICE{
        defaultMidamble      NULL,
        commonMidamble      NULL,
        ueSpecificMidamble      INTEGER (0..15)
    }
}

```

```

},
-- Actual value midambleConfiguration = IE value * 2
midambleConfiguration           INTEGER (1..8)
}

HS-SCCH-Info ::=          SEQUENCE {
    modeSpecificInfo      CHOICE {
        fdd               SEQUENCE {
            hS-SCCHChannelisationCodeInfo   SEQUENCE (SIZE (1..maxHSSCCHs)) OF
                                            HS-SCCH-Codes,
            dl-ScramblingCode           SecondaryScramblingCode   OPTIONAL
        },
        tdd               CHOICE {
            tdd384           SEQUENCE {
                nack-ack-power-offset    INTEGER (-7..8),
                hs-SICH-PowerControl-Info HS-SICH-Power-Control-Info-TDD384,
                hs-SCCH-SetConfiguration  SEQUENCE (SIZE (1..maxHSSCCHs)) OF
                                            HS-SCCH-TDD384
            },
            tdd128           SEQUENCE (SIZE (1..maxHSSCCHs)) OF
                                            HS-SCCH-TDD128
        }
    }
}

HS-SCCH-Codes ::=          INTEGER (0..127)

HS-SCCH-TDD128 ::=          SEQUENCE {
    timeslotNumber        TimeslotNumber-LCR-r4,
    firstChannelisationCode HS-ChannelisationCode-LCR,
    secondChannelisationCode HS-ChannelisationCode-LCR,
    midambleAllocationMode CHOICE {
        defaultMidamble     NULL,
        commonMidamble       NULL,
        ueSpecificMidamble  INTEGER(0..15)
    },
    -- Actual value midambleConfiguration = IE value * 2
    midambleConfiguration   INTEGER (1..8),
   bler-target             Bler-Target,
    hs-sich-configuration  HS-SICH-Configuration-TDD128
}

HS-SICH-Configuration-TDD128 ::=  SEQUENCE {
    timeslotNumber        TimeslotNumber-LCR-r4,
    channelisationCode    HS-ChannelisationCode-LCR,
    midambleAllocationMode CHOICE {
        defaultMidamble     NULL,
        ueSpecificMidamble  SEQUENCE {
            midambleShift      MidambleShiftLong
        }
    },
    -- Actual value midambleConfiguration = IE value * 2
    midambleConfiguration   INTEGER (1..8),
    nack-ack-power-offset  INTEGER (-7..8),
    power-level-HSSICH     INTEGER (-120..-58),
    tpc-step-size           ENUMERATED { s1, s2, s3 , spare1}
}

HS-SCCH-TDD384 ::=          SEQUENCE {
    timeslotNumber        TimeslotNumber,
    channelisationCode    DL-TS-ChannelisationCode,
    midambleAllocationMode CHOICE {
        defaultMidamble     NULL,
        commonMidamble       NULL,
        ueSpecificMidamble  SEQUENCE {
            midambleShift      MidambleShiftLong
        }
    },
    midambleConfiguration  MidambleConfigurationBurstType1and3,
    bler-target             Bler-Target,
    hs-sich-configuration  HS-SICH-Configuration-TDD384
}

HS-SICH-Configuration-TDD384 ::=  SEQUENCE {
    timeslotNumber        TimeslotNumber,
    channelisationCode    DL-TS-ChannelisationCode,

```

```

midambleAllocationMode          CHOICE {
    defaultMidamble           NULL,
    ueSpecificMidamble        SEQUENCE {
        midambleShift          MidambleShiftLong
    }
},
midambleconfiguration          MidambleConfigurationBurstType1and3
}

HS-SICH-Power-Control-Info-TDD384 ::= SEQUENCE {
    -- Actual value ul-target-SIR = IE value * 0.5
    ul-target-SIR              INTEGER (-22..40),
    hs-sich-ConstantValue      ConstantValue
}

IndividualTimeslotInfo ::= SEQUENCE {
    timeslotNumber            TimeslotNumber,
    tfci-Existence            BOOLEAN,
    midambleShiftAndBurstType MidambleShiftAndBurstType
}

IndividualTimeslotInfo-LCR-r4 ::= SEQUENCE {
    timeslotNumber             TimeslotNumber-LCR-r4,
    tfci-Existence              BOOLEAN,
    midambleShiftAndBurstType   MidambleShiftAndBurstType-LCR-r4,
    modulation                  ENUMERATED { mod-QPSK, mod-8PSK },
    ss-TPC-Symbols               ENUMERATED { zero, one, sixteenOverSF },
    additionalSS-TPC-Symbols     INTEGER(1..15) OPTIONAL
}

IndividualTimeslotInfo-LCR-r4-ext ::= SEQUENCE {
    -- timeslotNumber and tfci-Existence is taken from IndividualTimeslotInfo.
    -- midambleShiftAndBurstType in IndividualTimeslotInfo shall be ignored.
    midambleShiftAndBurstType   MidambleShiftAndBurstType-LCR-r4,
    modulation                  ENUMERATED { mod-QPSK, mod-8PSK },
    ss-TPC-Symbols               ENUMERATED { zero, one, sixteenOverSF }
}

IndividualTS-Interference ::= SEQUENCE {
    timeslot                  TimeslotNumber,
    ul-TimeslotInterference    TDD-UL-Interference
}

IndividualTS-InterferenceList ::= SEQUENCE (SIZE (1..maxTS)) OF
    IndividualTS-Interference

ITP ::= ENUMERATED {
    mode0, mode1
}

NidentifyAbort ::= INTEGER (1..128)

MaxAllowedUL-TX-Power ::= INTEGER (-50..33)

MaxAvailablePCPCH-Number ::= INTEGER (1..64)

MaxPowerIncrease-r4 ::= INTEGER (0..3)

MaxTFCI-Field2Value ::= INTEGER (1..1023)

Measurement-Feedback-Info ::= SEQUENCE {
    modeSpecificInfo           CHOICE {
        fdd                     SEQUENCE {
            measurementPowerOffset MeasurementPowerOffset,
            feedback-cycle          Feedback-cycle,
            cqi-RepetitionFactor    CQI-RepetitionFactor,
            deltaCQI                 DeltacQI
        },
        tdd                     NULL
    }
}

MidambleConfigurationBurstType1and3 ::= ENUMERATED {ms4, ms8, ms16}

MidambleConfigurationBurstType2 ::= ENUMERATED {ms3, ms6}

MidambleShiftAndBurstType ::= SEQUENCE {

```

```

burstType                               CHOICE {
  type1                                SEQUENCE {
    midambleConfigurationBurstType1and3 MidambleConfigurationBurstType1and3,
    midambleAllocationMode           CHOICE {
      defaultMidamble               NULL,
      commonMidamble                NULL,
      ueSpecificMidamble          SEQUENCE {
        midambleShift              MidambleShiftLong
      }
    }
  },
  type2                                SEQUENCE {
    midambleConfigurationBurstType2 MidambleConfigurationBurstType2,
    midambleAllocationMode           CHOICE {
      defaultMidamble               NULL,
      commonMidamble                NULL,
      ueSpecificMidamble          SEQUENCE {
        midambleShift              MidambleShiftShort
      }
    }
  },
  type3                                SEQUENCE {
    midambleConfigurationBurstType1and3 MidambleConfigurationBurstType1and3,
    midambleAllocationMode           CHOICE {
      defaultMidamble               NULL,
      ueSpecificMidamble          SEQUENCE {
        midambleShift              MidambleShiftLong
      }
    }
  }
}

MidambleShiftAndBurstType-DL ::=      SEQUENCE {
  burstType                               CHOICE {
    type1                                SEQUENCE {
      midambleConfigurationBurstType1and3 MidambleConfigurationBurstType1and3,
      midambleAllocationMode           CHOICE {
        defaultMidamble               NULL,
        commonMidamble                NULL,
        ueSpecificMidamble          SEQUENCE {
          midambleShift              MidambleShiftLong
        }
      }
    },
    type2                                SEQUENCE {
      midambleConfigurationBurstType2 MidambleConfigurationBurstType2,
      midambleAllocationMode           CHOICE {
        defaultMidamble               NULL,
        commonMidamble                NULL,
        ueSpecificMidamble          SEQUENCE {
          midambleShift              MidambleShiftShort
        }
      }
    }
  }
}

MidambleShiftAndBurstType-LCR-r4 ::=  SEQUENCE {
  midambleAllocationMode           CHOICE {
    defaultMidamble               NULL,
    commonMidamble                NULL,
    ueSpecificMidamble          SEQUENCE {
      midambleShift              INTEGER (0..15)
    }
  },
  -- Actual value midambleConfiguration = IE value * 2
  midambleConfiguration          INTEGER (1..8)
}

MidambleShiftLong ::=                  INTEGER (0..15)

MidambleShiftShort ::=                INTEGER (0..5)

MinimumSpreadingFactor ::=          ENUMERATED {
  sf4, sf8, sf16, sf32,
  sf64, sf128, sf256 }

```

```

MultiCodeInfo ::= INTEGER (1..16)

N-EOT ::= INTEGER (0..7)

N-GAP ::= ENUMERATED {
    f2, f4, f8 }

N-PCH ::= INTEGER (1..8)

N-StartMessage ::= INTEGER (1..8)

NB01 ::= INTEGER (0..50)

NF-Max ::= INTEGER (1..64)

NumberOfDPDCH ::= INTEGER (1..maxDPDCH-UL)

NumberOfFBI-Bits ::= INTEGER (1..2)

OpenLoopPowerControl-TDD ::= SEQUENCE {
    primaryCCPCH-TX-Power          PrimaryCCPCH-TX-Power,
    -- alpha, prach-ConstantValue, dpch-ConstantValue and pusch-ConstantValue
    -- shall be ignored in 1.28Mcps TDD mode.
    alpha                          Alpha                      OPTIONAL,
    prach-ConstantValue            ConstantValueTdd,
    dpch-ConstantValue            ConstantValueTdd,
    pusch-ConstantValue           ConstantValueTdd          OPTIONAL
}

OpenLoopPowerControl-IPDL-TDD-r4 ::= SEQUENCE {
    ipdl-alpha                    Alpha,
    maxPowerIncrease              MaxPowerIncrease-r4
}

PagingIndicatorLength ::= ENUMERATED {
    pi4, pi8, pi16 }

PC-Preamble ::= INTEGER (0..7)

PCP-Length ::= ENUMERATED {
    as0, as8 }

PCPCH-ChannelInfo ::= SEQUENCE {
    pcpch-UL-ScramblingCode      INTEGER (0..79),
    pcpch-DL-ChannelisationCode  INTEGER (0..511),
    pcpch-DL-ScramblingCode      SecondaryScramblingCode   OPTIONAL,
    pcp-Length                   PCP-Length,
    ucsm-Info                     UCSR-Info                OPTIONAL
}

PCPCH-ChannelInfoList ::= SEQUENCE (SIZE (1..maxPCPCHs)) OF
    PCPCH-ChannelInfo

PCPICH-UsageForChannelEst ::= ENUMERATED {
    maybeUsed,
    shallNotBeUsed }

PDSCH-CapacityAllocationInfo ::= SEQUENCE {
    -- pdsch-PowerControlInfo is conditional on new-configuration branch below, if this
    -- selected the IE is OPTIONAL otherwise it should not be sent
    pdsch-PowerControlInfo        PDSCH-PowerControlInfo          OPTIONAL,
    pdsch-AllocationPeriodInfo    AllocationPeriodInfo,
    configuration                 CHOICE {
        old-Configuration       SEQUENCE {
            tfcs-ID             TFCS-IdentityPlain,
            pdsch-Identity       PDSCH-Identity                  DEFAULT 1,
        },
        new-Configuration       SEQUENCE {
            pdsch-Info           PDSCH-Info,
            pdsch-Identity       PDSCH-Identity                OPTIONAL
    }
}

PDSCH-CapacityAllocationInfo-r4 ::= SEQUENCE {
    pdsch-AllocationPeriodInfo   AllocationPeriodInfo,

```

```

configuration
  old-Configuration
    tfcs-ID
    pdsch-Identity
  },
  new-Configuration
    pdsch-Info
    pdsch-Identity
    pdsch-PowerControlInfo
  }
}
}

PDSCH-CodeInfo ::= CHOICE {
  old-Configuration
    TFCS-IdentityPlain
    PDSCH-Identity
  },
  new-Configuration
    PDSCH-Info-r4,
    PDSCH-Identity
    PDSCH-PowerControlInfo
  }
}

PDSCH-CodeInfoList ::= SEQUENCE {
  spreadingFactor
  codeNumber
  multiCodeInfo
}

PDSCH-CodeMap ::= SEQUENCE {
  spreadingFactor
  multiCodeInfo
  codeNumberStart
  codeNumberStop
}

PDSCH-CodeMapList ::= SEQUENCE (SIZE (1..maxTFCI-2-Combs)) OF
  PDSCH-CodeMap

PDSCH-CodeMapping ::= SEQUENCE {
  d1-ScramblingCode
  signallingMethod
    codeRange
    tfci-Range
    explicit-config
    replace
}
}

PDSCH-Identity ::= INTEGER (1..hiPDSCHidentities)

PDSCH-Info ::= SEQUENCE {
  tfcs-ID
  commonTimeslotInfo
  pdsch-TimeslotsCodes
}
}

PDSCH-Info-r4 ::= SEQUENCE {
  tfcs-ID
  commonTimeslotInfo
  tddOption
    tdd384
      pdsch-TimeslotsCodes
    },
    tdd128
      pdsch-TimeslotsCodes
}
}

PDSCH-Info-LCR-r4 ::= SEQUENCE {
  tfcs-ID
  commonTimeslotInfo
  pdsch-TimeslotsCodes
}
}

PDSCH-PowerControlInfo ::= SEQUENCE {
  tpc-StepSizeTDD
  ul-CCTrChTPCList
}
}

PDSCH-SHO-DCH-Info ::= SEQUENCE {
  dsch-RadioLinkIdentifier
  rl-IdentifierList
}

```

```

PDSCH-SysInfo ::= SEQUENCE {
    pdsch-Identity,
    pdsch-Info,
    dsch-TFS,
    dsch-TFCS
} OPTIONAL, OPTIONAL

PDSCH-SysInfo-HCR-r5 ::= SEQUENCE {
    pdsch-Identity,
    pdsch-Info,
    dsch-TransportChannelsInfo
    dsch-TFCS
} OPTIONAL, OPTIONAL

PDSCH-SysInfo-LCR-r4 ::= SEQUENCE {
    pdsch-Identity,
    pdsch-Info,
    dsch-TFS,
    dsch-TFCS
} OPTIONAL, OPTIONAL

PDSCH-SysInfoList ::= SEQUENCE (SIZE (1..maxPDSCH)) OF PDSCH-SysInfo

PDSCH-SysInfoList-HCR-r5 ::= SEQUENCE (SIZE (1..maxPDSCH)) OF PDSCH-SysInfo-HCR-r5

PDSCH-SysInfoList-LCR-r4 ::= SEQUENCE (SIZE (1..maxPDSCH)) OF PDSCH-SysInfo-LCR-r4

PDSCH-SysInfoList-SFN ::= SEQUENCE (SIZE (1..maxPDSCH)) OF
SEQUENCE {
    pdsch-SysInfo,
    sfn-TimeInfo
} OPTIONAL

PDSCH-SysInfoList-SFN-HCR-r5 ::= SEQUENCE (SIZE (1..maxPDSCH)) OF
SEQUENCE {
    pdsch-SysInfo-HCR-r5,
    SFN-TimeInfo
} OPTIONAL

PDSCH-SysInfoList-SFN-LCR-r4 ::= SEQUENCE (SIZE (1..maxPDSCH)) OF
SEQUENCE {
    PDSCH-SysInfo-LCR-r4,
    SFN-TimeInfo
} OPTIONAL

PersistenceScalingFactor ::= ENUMERATED {
    psf0-9, psf0-8, psf0-7, psf0-6,
    psf0-5, psf0-4, psf0-3, psf0-2
}

PersistenceScalingFactorList ::= SEQUENCE (SIZE (1..maxASCpersist)) OF PersistenceScalingFactor

PI-CountPerFrame ::= ENUMERATED {
    e18, e36, e72, e144
}

PichChannelisationCodeList-LCR-r4 ::= SEQUENCE (SIZE (1..2)) OF DL-TS-ChannelisationCode

PICH-Info ::= CHOICE {
    fdd
        channelisationCode256
    pi-CountPerFrame
    sttd-Indicator
},
    tdd
        channelisationCode
    timeslot
    midambleShiftAndBurstType
    repetitionPeriodLengthOffset
    pagingIndicatorLength
    n-GAP
    n-PCH
} OPTIONAL, OPTIONAL, OPTIONAL, DEFAULT pi4, DEFAULT f4, DEFAULT 2
}

```

```

PICH-Info-LCR-r4 ::= SEQUENCE {
    timeslot                                TimeslotNumber-LCR-r4           OPTIONAL,
    pitchChannelisationCodeList-LCR-r4        PitchChannelisationCodeList-LCR-r4,
    midambleShiftAndBurstType                MidambleShiftAndBurstType-LCR-r4,
    repetitionPeriodLengthOffset             RepPerLengthOffset-PICH          OPTIONAL,
    pagingIndicatorLength                   PagingIndicatorLength            DEFAULT pi4,
    n-GAP                                    N-GAP                           DEFAULT f4,
    n-PCH                                    N-PCH                           DEFAULT 2
}

PICH-PowerOffset ::= INTEGER (-10..5)

PilotBits128 ::= ENUMERATED {
    pb4, pb8 }

PilotBits256 ::= ENUMERATED {
    pb2, pb4, pb8 }

-- Actual measurement power offset value = IE value * 0.5
MeasurementPowerOffset ::= INTEGER (-12..26)

PositionFixedOrFlexible ::= ENUMERATED {
    fixed,
    flexible }

PowerControlAlgorithm ::= CHOICE {
    algorithm1                            TPC-StepSizeFDD,
    algorithm2                            NULL
}

PowerOffsetPilot-pdpdch ::= INTEGER (0..24)

PowerOffsetTPC-pdpdch ::= INTEGER (0..24)

PowerRampStep ::= INTEGER (1..8)

PRACH-ChanCodes-LCR-r4 ::= SEQUENCE (SIZE (1..4)) OF
    TDD-PRACH-CCode-LCR-r4

PRACH-Definition-LCR-r4 ::= SEQUENCE {
    timeslot                                TimeslotNumber-PRACH-LCR-r4,
    prach-ChanCodes-LCR                     PRACH-ChanCodes-LCR-r4,
    midambleShiftAndBurstType              MidambleShiftAndBurstType-LCR-r4,
    fpach-Info                             FPACH-Info-r4
}

PRACH-Midamble ::= ENUMERATED {
    direct,
    direct-Inverted }

PRACH-Partitioning ::= CHOICE {
    fdd                                     SEQUENCE (SIZE (1..maxASC)) OF
    -- TABULAR: If only "NumASC+1" (with, NumASC+1 < maxASC) ASCSetting-FDD are listed,
    -- the remaining (NumASC+2 through maxASC) ASCs are unspecified.
    -- ASCSetting-FDD,
    tdd                                     SEQUENCE (SIZE (1..maxASC)) OF
    -- TABULAR: If only "NumASC+1" (with, NumASC+1 < maxASC) ASCSetting-TDD are listed,
    -- the remaining (NumASC+2 through maxASC) ASCs are unspecified.
    -- ASCSetting-TDD
}

PRACH-Partitioning-LCR-r4 ::= SEQUENCE (SIZE (1..maxASC)) OF
    -- TABULAR: If only "NumASC+1" (with, NumASC+1 < maxASC) ASCSetting-TDD-LCR-r4 are listed,
    -- the remaining (NumASC+2 through maxASC) ASCs are unspecified.
    -- ASCSetting-TDD-LCR-r4

PRACH-PowerOffset ::= SEQUENCE {
    powerRampStep,
    preambleRetransMax
}

PRACH-RACH-Info ::= SEQUENCE {
    modeSpecificInfo
    fdd
    availableSignatures
    availableSF
    preambleScramblingCodeWordNumber
    CHOICE {
        SEQUENCE {
            AvailableSignatures,
            SF-PRACH,
            PreambleScramblingCodeWordNumber,
        }
    }
}

```

```

        puncturingLimit,
        availableSubChannelNumbers
    },
    tdd
        timeslot
        channelisationCodeList
        prach-Midamble
    }
}

PRACH-RACH-Info-LCR-r4 ::= SEQUENCE {
    sync-UL-Info,
    prach-DefinitionList
}

PRACH-SystemInformation ::= SEQUENCE {
    prach-RACH-Info
    transportChannelIdentity
    rach-TransportFormatSet
    rach-TFCS
    prach-Partitioning
    persistenceScalingFactorList
    ac-To-ASC-MappingTable
    modeSpecificInfo
        fdd
            primaryCPICH-TX-Power
            constantValue
            prach-PowerOffset
            rach-TransmissionParameters
            aich-Info
        },
    tdd
}
}

PRACH-SystemInformation-LCR-r4 ::= SEQUENCE {
    prach-RACH-Info-LCR
    rach-TransportFormatSet-LCR
    prach-Partitioning-LCR
}

PRACH-SystemInformationList ::= SEQUENCE (SIZE (1..maxPRACH)) OF
    PRACH-SystemInformation

PRACH-SystemInformationList-LCR-r4 ::= SEQUENCE (SIZE (1..maxPRACH)) OF
    PRACH-SystemInformation-LCR-r4

PreambleRetransMax ::= INTEGER (1..64)

PreambleScramblingCodeWordNumber ::= INTEGER (0..15)

PreDefPhyChConfiguration ::= SEQUENCE {
    ul-DPCH-InfoPredef
    dl-CommonInformationPredef
}

PrimaryCCPCH-Info ::= CHOICE {
    fdd
        tx-DiversityIndicator
    },
    tdd
        -- syncCase should be ignored for 1.28Mcps TDD mode
        syncCase
            syncCase1
                timeslot
            },
            syncCase2
                timeslotSync2
            }
    },
    cellParametersID
    sctd-Indicator
}

PrimaryCCPCH-Info-r4 ::= CHOICE {
    PuncturingLimit,
    AvailableSubChannelNumbers
}
SEQUENCE {
    TimeslotNumber,
    TDD-PRACH-CCodeList,
    PRACH-Midamble
}

SEQUENCE {
    SYNC-UL-Info-r4,
    SEQUENCE (SIZE (1..maxPRACH)) OF
        PRACH-Definition-LCR-r4
}

SEQUENCE {
    PRACH-RACH-Info,
    TransportChannelIdentity,
    TransportFormatSet OPTIONAL,
    TFCS OPTIONAL,
    PRACH-Partitioning OPTIONAL,
    PersistenceScalingFactorList OPTIONAL,
    AC-To-ASC-MappingTable OPTIONAL,
    CHOICE {
        SEQUENCE {
            PrimaryCPICH-TX-Power OPTIONAL,
            ConstantValue OPTIONAL,
            PRACH-PowerOffset OPTIONAL,
            RACH-TransmissionParameters OPTIONAL,
            AICH-Info OPTIONAL
        },
        NULL
    }
}

SEQUENCE {
    PRACH-RACH-Info-LCR-r4,
    TransportFormatSet-LCR OPTIONAL,
    PRACH-Partitioning-LCR-r4 OPTIONAL
}

SEQUENCE (SIZE (1..maxPRACH)) OF
    PRACH-SystemInformation

```

```

    fdd                                SEQUENCE {
        tx-DiversityIndicator          BOOLEAN
    },
    tdd                                SEQUENCE {
        tddOption                      CHOICE {
            tdd384                         SEQUENCE {
                syncCase                     CHOICE {
                    syncCase1                  SEQUENCE {
                        timeslot                   TimeslotNumber
                    },
                    syncCase2                  SEQUENCE {
                        timeslotSync2             TimeslotSync2
                    }
                }
            },
            OPTIONAL
        },
        tdd128                          SEQUENCE {
            tstd-Indicator               BOOLEAN
        }
    },
    cellParametersID                  CellParametersID
    sctd-Indicator                   BOOLEAN
}

PrimaryCCPCH-Info-LCR-r4 ::=      SEQUENCE {
    tstd-Indicator                 BOOLEAN,
    cellParametersID              CellParametersID
    sctd-Indicator                OPTIONAL,
}
-- For 1.28Mcps TDD, the following IE includes elements for the PCCPCH Info additional to those
-- in PrimaryCCPCH-Info
PrimaryCCPCH-Info-LCR-r4-ext ::=   SEQUENCE {
    tstd-Indicator                 BOOLEAN
}

PrimaryCCPCH-InfoPost ::=         SEQUENCE {
    syncCase                      CHOICE {
        syncCase1                  SEQUENCE {
            timeslot                   TimeslotNumber
        },
        syncCase2                  SEQUENCE {
            timeslotSync2             TimeslotSync2
        }
    },
    cellParametersID              CellParametersID,
    sctd-Indicator                BOOLEAN
}

PrimaryCCPCH-InfoPostTDD-LCR-r4 ::= SEQUENCE {
    tstd-Indicator                 BOOLEAN,
    cellParametersID              CellParametersID,
    sctd-Indicator                BOOLEAN
}

PrimaryCCPCH-TX-Power ::=          INTEGER (6..43)

PrimaryCPICH-Info ::=             SEQUENCE {
    primaryScramblingCode        PrimaryScramblingCode
}

PrimaryCPICH-TX-Power ::=          INTEGER (-10..50)

PrimaryScramblingCode ::=          INTEGER (0..511)

PuncturingLimit ::=               ENUMERATED {
    p10-40, p10-44, p10-48, p10-52, p10-56,
    p10-60, p10-64, p10-68, p10-72, p10-76,
    p10-80, p10-84, p10-88, p10-92, p10-96, p11 }

PUSCH-CapacityAllocationInfo ::=  SEQUENCE {
    pusch-Allocation              CHOICE {
        pusch-AllocationPending      NULL,
        pusch-AllocationAssignment   SEQUENCE {
            pusch-AllocationPeriodInfo AllocationPeriodInfo,
            pusch-PowerControlInfo     UL-TargetSIR
        },
        configuration                CHOICE {
            old-Configuration          SEQUENCE {
        }
    }
}

```

```

        tfcs-ID
        pusch-Identity
    },
    new-Configuration
        pusch-Info
        pusch-Identity
    }
}
}

PUSCH-CapacityAllocationInfo-r4 ::= SEQUENCE {
    pusch-Allocation
        CHOICE {
            pusch-AllocationPending
                NULL,
            pusch-AllocationAssignment
                SEQUENCE {
                    pusch-AllocationPeriodInfo,
                    PUSCH-PowerControlInfo-r4 OPTIONAL,
                    configuration
                        CHOICE {
                            old-Configuration
                                tfcs-ID
                                pusch-Identity
                            },
                            new-Configuration
                                pusch-Info
                                pusch-Identity
                        }
                    }
    }
}

PUSCH-Identity ::= INTEGER (1..hiPUSCHidentities)

PUSCH-Info ::= SEQUENCE {
    tfcs-ID
    commonTimeslotInfo
    pusch-TimeslotsCodes
}
}

PUSCH-Info-r4 ::= SEQUENCE {
    tfcs-ID
    commonTimeslotInfo
    tddOption
        CHOICE {
            tdd384
                pusch-TimeslotsCodes
            },
            tdd128
                pusch-TimeslotsCodes
        }
}
}

PUSCH-Info-LCR-r4 ::= SEQUENCE {
    tfcs-ID
    commonTimeslotInfo
    pusch-TimeslotsCodes
}
}

PUSCH-PowerControlInfo-r4 ::= SEQUENCE {
    -- The IE ul-TargetSIR corresponds to PRX-PUSCHdes for 1.28Mcps TDD
    -- Actual value PRX-PUSCHdes = (value of IE "ul-TargetSIR" - 120)
    ul-TargetSIR
        UL-TargetSIR,
    tddOption
        CHOICE {
            tdd384
            tdd128
                tpc-StepSize
        }
}
}

PUSCH-SysInfo ::= SEQUENCE {
    pusch-Identity
    pusch-Info
    usch-TFS
    usch-TFCS
}
}

```

```

PUSCH-SysInfo-HCR-r5 ::=          SEQUENCE {
    pusch-Identity,
    pusch-Info,
    usch-TransportChannelsInfo      USCH-TransportChannelsInfo
    usch-TFCS                      OPTIONAL,
}                                     TFCS                         OPTIONAL

PUSCH-SysInfo-LCR-r4 ::=          SEQUENCE {
    pusch-Identity,
    pusch-Info,
    usch-TFS                        TransportFormatSet
    usch-TFCS                      OPTIONAL,
}                                     TFCS                         OPTIONAL

PUSCH-SysInfoList ::=             SEQUENCE (SIZE (1..maxPUSCH)) OF
}                                     PUSCH-SysInfo

PUSCH-SysInfoList-HCR-r5 ::=       SEQUENCE (SIZE (1..maxPUSCH)) OF PUSCH-SysInfo-HCR-r5

PUSCH-SysInfoList-LCR-r4 ::=       SEQUENCE (SIZE (1..maxPUSCH)) OF
}                                     PUSCH-SysInfo-LCR-r4

PUSCH-SysInfoList-SFN ::=         SEQUENCE (SIZE (1..maxPUSCH)) OF
}                                     SEQUENCE {
    pusch-SysInfo,
    sfn-TimeInfo                  SFN-TimeInfo
}                                     OPTIONAL

PUSCH-SysInfoList-SFN-HCR-r5 ::=  SEQUENCE (SIZE (1..maxPUSCH)) OF
}                                     SEQUENCE {
    pusch-SysInfo-HCR-r5,
    SFN-TimeInfo                  OPTIONAL
}

PUSCH-SysInfoList-SFN-LCR-r4 ::=  SEQUENCE (SIZE (1..maxPUSCH)) OF
}                                     SEQUENCE {
    pusch-SysInfo-LCR-r4,
    SFN-TimeInfo                  OPTIONAL
}

RACH-TransmissionParameters ::=   SEQUENCE {
    mmax                         INTEGER (1..32),
    nb01Min                      NB01,
    nb01Max                      NB01
}

ReducedScramblingCodeNumber ::=    INTEGER (0..8191)

RepetitionPeriodAndLength ::=     CHOICE {
    repetitionPeriod1            NULL,
    -- repetitionPeriod2 could just as well be NULL also.
    repetitionPeriod2            INTEGER (1..1),
    repetitionPeriod4            INTEGER (1..3),
    repetitionPeriod8            INTEGER (1..7),
    repetitionPeriod16           INTEGER (1..15),
    repetitionPeriod32           INTEGER (1..31),
    repetitionPeriod64           INTEGER (1..63)
}

RepetitionPeriodLengthAndOffset ::= CHOICE {
    repetitionPeriod1            NULL,
    repetitionPeriod2            SEQUENCE {
        length                    NULL,
        offset                     INTEGER (0..1)
    },
    repetitionPeriod4            SEQUENCE {
        length                    INTEGER (1..3),
        offset                     INTEGER (0..3)
    },
    repetitionPeriod8            SEQUENCE {
        length                    INTEGER (1..7),
        offset                     INTEGER (0..7)
    },
    repetitionPeriod16           SEQUENCE {
        length                    INTEGER (1..15),
        offset                     INTEGER (0..15)
    },
}

```

```

repetitionPeriod32           SEQUENCE {
    length                  INTEGER (1..31),
    offset                  INTEGER (0..31)
},
repetitionPeriod64           SEQUENCE {
    length                  INTEGER (1..63),
    offset                  INTEGER (0..63)
}
}

ReplacedPDSCH-CodeInfo ::= SEQUENCE {
    tfci-Field2              MaxTFCI-Field2Value,
    spreadingFactor           SF-PDSCH,
    codeNumber                CodeNumberDSCH,
    multiCodeInfo             MultiCodeInfo
}

ReplacedPDSCH-CodeInfoList ::= SEQUENCE (SIZE (1..maxTFCI-2-Combs)) OF
                                ReplacedPDSCH-CodeInfo

RepPerLengthOffset-PICH ::= CHOICE {
    rpp4-2                   INTEGER (0..3),
    rpp8-2                   INTEGER (0..7),
    rpp8-4                   INTEGER (0..7),
    rpp16-2                  INTEGER (0..15),
    rpp16-4                  INTEGER (0..15),
    rpp32-2                  INTEGER (0..31),
    rpp32-4                  INTEGER (0..31),
    rpp64-2                  INTEGER (0..63),
    rpp64-4                  INTEGER (0..63)
}

RepPerLengthOffset-MICH ::= CHOICE {
    rpp4-2                   INTEGER (0..3),
    rpp8-2                   INTEGER (0..7),
    rpp8-4                   INTEGER (0..7),
    rpp16-2                  INTEGER (0..15),
    rpp16-4                  INTEGER (0..15),
    rpp32-2                  INTEGER (0..31),
    rpp32-4                  INTEGER (0..31),
    rpp64-2                  INTEGER (0..63),
    rpp64-4                  INTEGER (0..63)
}

RestrictedTrCH ::= SEQUENCE {
    dl-restrictedTrCh-Type   DL-TrCH-Type,
    restrictedDL-TrCH-Identity TransportChannelIdentity,
    allowedTFIList            AllowedTFI-List
}

RestrictedTrCH-InfoList ::= SEQUENCE (SIZE(1..maxTrCH)) OF
                                RestrictedTrCH

RL-AdditionInformation ::= SEQUENCE {
    primaryCPICH-Info        PrimaryCPICH-Info,
    dl-DPCH-InfoPerRL         DL-DPCH-InfoPerRL,
    tfci-CombiningIndicator  BOOLEAN,
    sccpch-InfoForFACH        SCCPCH-InfoForFACH
                                OPTIONAL
}

RL-AdditionInformationList ::= SEQUENCE (SIZE (1..maxRL-1)) OF
                                RL-AdditionInformation

RL-IdentifierList ::= SEQUENCE (SIZE (1..maxRL)) OF
                                PrimaryCPICH-Info

RL-RemovalInformationList ::= SEQUENCE (SIZE (1..maxRL)) OF
                                PrimaryCPICH-Info

RPP ::= ENUMERATED {
    mode0, mode1
}

S-Field ::= ENUMERATED {
    elbit, e2bits
}

SCCPCH-ChannelisationCode ::= ENUMERATED {
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
}

```

```

cc16-9, cc16-10, cc16-11, cc16-12,
cc16-13, cc16-14, cc16-15, cc16-16 }

SCCPCH-ChannelisationCodeList ::= SEQUENCE (SIZE (1..16)) OF
SCCPCH-ChannelisationCode

SCCPCH-InfoForFACH ::= SEQUENCE {
    secondaryCCPCH-Info,
    tfcs,
    modeSpecificInfo CHOICE {
        fdd {
            fach-PCH-InformationList
            sib-ReferenceListFACH
        },
        tdd {
            fach-PCH-InformationList
        }
    }
}

SCCPCH-InfoForFACH-r4 ::= SEQUENCE {
    secondaryCCPCH-Info,
    tfcs,
    fach-PCH-InformationList,
    modeSpecificInfo CHOICE {
        fdd {
            sib-ReferenceListFACH
        },
        tdd NULL
    }
}

SCCPCH-SystemInformation ::= SEQUENCE {
    secondaryCCPCH-Info,
    tfcs,
    fach-PCH-InformationList OPTIONAL,
    pich-Info OPTIONAL
}

SCCPCH-SystemInformation-LCR-r4-ext ::= SEQUENCE {
    secondaryCCPCH-LCR-Extensions SecondaryCCPCH-Info-LCR-r4-ext,
    -- pich-Info in the SCCPCH-SystemInformation IE shall be absent,
    -- and instead the following used.
    pich-Info PICH-Info-LCR-r4 OPTIONAL
}

SCCPCH-SystemInformation-MBMS-r6-ext ::= SEQUENCE {
    mcch-ConfigurationInfo MBMS-MCCH-ConfigurationInfo-r6 OPTIONAL
}

SCCPCH-SystemInformationList ::= SEQUENCE (SIZE (1..maxSCCPCH)) OF
SCCPCH-SystemInformation

-- SCCPCH-SystemInformationList-LCR-r4-ext includes elements additional to those in
-- SCCPCH-SystemInformationList for the 1.28Mcps TDD. The order of the IEs
-- indicates which SCCPCH-SystemInformation-LCR-r4-ext IE extends which
-- SCCPCH-SystemInformation IE.

SCCPCH-SystemInformationList-LCR-r4-ext ::= SEQUENCE (SIZE (1..maxSCCPCH)) OF
SCCPCH-SystemInformation-LCR-r4-ext

-- The SCCPCH-SystemInformationList-MBMS-r6-ext includes elements additional to those in the
-- SCCPCH-SystemInformationList for the mapping of MCCH onto an S-CCPCH common for both MBMS
-- and non-MBMS purposes. The order of the IEs indicates which SCCPCH-SystemInformation-MBMS-r6-ext
-- IE extends which SCCPCH-SystemInformation IE.

SCCPCH-SystemInformationList-MBMS-r6-ext ::= SEQUENCE (SIZE (1..maxSCCPCH)) OF
SCCPCH-SystemInformation-MBMS-r6-ext

-- The SCCPCH-SystemInformation-MBMS-r6 is used for an S-CCPCH dedicated for MBMS purposes.

SCCPCH-SystemInformation-MBMS-r6 ::= SEQUENCE {
    secondaryCCPCHInfo-MBMS SecondaryCCPCHInfo-MBMS-r6,
    transportFormatCombinationSet TFCS,
    fachCarryingMCCH SEQUENCE {
        transportFormatSet,
        mcch-ConfigurationInfo MBMS-MCCH-ConfigurationInfo-r6
    },
    fachCarryingMTCH-List SEQUENCE (SIZE (1..maxFACHPCH)) OF
        TransportFormatSet,
    schedulingInformation SEQUENCE {

```

```

fachCarryingMSCH
mschConfigurationInfo
    OPTIONAL
}

ScramblingCodeChange ::= ENUMERATED {
    codeChange, noCodeChange }

ScramblingCodeType ::= ENUMERATED {
    shortSC,
    longSC }

SecondaryCCPCH-Info ::= SEQUENCE {
    modeSpecificInfo
        CHOICE {
            fdd
                SEQUENCE {
                    -- dummy1 is not used in this version of the specification and should be ignored.
                    dummy1
                        PCPICH-UsageForChannelEst,
                    -- dummy2 is not used in this version of the specification. It should not
                    -- be sent and if received it should be ignored.
                    dummy2
                        SecondaryCPICH-Info
                            OPTIONAL,
                    secondaryScramblingCode
                        SecondaryScramblingCode
                            OPTIONAL,
                    stdt-Indicator
                        BOOLEAN,
                    sf-AndCodeNumber
                        SF256-AndCodeNumber,
                    pilotSymbolExistence
                        BOOLEAN,
                    tfci-Existence
                        BOOLEAN,
                    positionFixedOrFlexible
                        PositionFixedOrFlexible,
                    timingOffset
                        TimingOffset
                            DEFAULT 0
                },
            tdd
                SEQUENCE {
                    -- TABULAR: the offset is included in CommonTimeslotInfoSCCPCH
                    commonTimeslotInfo
                        CommonTimeslotInfoSCCPCH,
                    individualTimeslotInfo
                        IndividualTimeslotInfo,
                    channelisationCode
                        SCCPCH-ChannelisationCodeList
                }
        }
    }

SecondaryCCPCH-Info-r4 ::= SEQUENCE {
    modeSpecificInfo
        CHOICE {
            fdd
                SEQUENCE {
                    secondaryScramblingCode
                        SecondaryScramblingCode
                            OPTIONAL,
                    stdt-Indicator
                        BOOLEAN,
                    sf-AndCodeNumber
                        SF256-AndCodeNumber,
                    pilotSymbolExistence
                        BOOLEAN,
                    tfci-Existence
                        BOOLEAN,
                    positionFixedOrFlexible
                        PositionFixedOrFlexible,
                    timingOffset
                        TimingOffset
                            DEFAULT 0
                },
            tdd
                SEQUENCE {
                    -- TABULAR: the offset is included in CommonTimeslotInfoSCCPCH
                    commonTimeslotInfo
                        CommonTimeslotInfoSCCPCH,
                    tddOption
                        CHOICE {
                            tdd384
                                individualTimeslotInfo
                            },
                            tdd128
                                individualTimeslotInfo
                            }
                },
            channelisationCode
                SCCPCH-ChannelisationCodeList
        }
    }

SecondaryCCPCH-Info-LCR-r4-ext ::= SEQUENCE {
    individualTimeslotLCR-Ext
        IndividualTimeslotInfo-LCR-r4-ext
}

SecondaryCCPCHInfo-MBMS-r6 ::= SEQUENCE {
    modeSpecificInfo
        CHOICE {
            fdd
                SEQUENCE {
                    secondaryScramblingCode
                        SecondaryScramblingCode
                            OPTIONAL,
                    stdt-Indicator
                        BOOLEAN,
                    sf-AndCodeNumber
                        SF256-AndCodeNumber,
                    tfci-Existence
                        BOOLEAN,
                    positionFixedOrFlexible
                        PositionFixedOrFlexible,
                    timingOffset
                        TimingOffset
                            DEFAULT 0
                },
            tdd
                SEQUENCE {
                    secondaryScramblingCode
                        SecondaryScramblingCode
                            OPTIONAL,
                    stdt-Indicator
                        BOOLEAN,
                    sf-AndCodeNumber
                        SF256-AndCodeNumber,
                    tfci-Existence
                        BOOLEAN,
                    positionFixedOrFlexible
                        PositionFixedOrFlexible,
                    timingOffset
                        TimingOffset
                            DEFAULT 0
                }
        }
}

```

```

    tdd384
    tdd128
}
}

SecondaryCPICH-Info ::= SEQUENCE {
    secondaryDL-ScramblingCode
    channelisationCode
}
OPTIONAL,
ChannelisationCode256

SecondaryScramblingCode ::= INTEGER (1..15)

SecondInterleavingMode ::= ENUMERATED {
    frameRelated, timeslotRelated }

-- SF256-AndCodeNumber encodes both "Spreading factor" and "Code Number"
SF256-AndCodeNumber ::= CHOICE {
    sf4
    sf8
    sf16
    sf32
    sf64
    sf128
    sf256
}
INTEGER (0..3),
INTEGER (0..7),
INTEGER (0..15),
INTEGER (0..31),
INTEGER (0..63),
INTEGER (0..127),
INTEGER (0..255)

-- SF512-AndCodeNumber encodes both "Spreading factor" and "Code Number"
SF512-AndCodeNumber ::= CHOICE {
    sf4
    sf8
    sf16
    sf32
    sf64
    sf128
    sf256
    sf512
}
INTEGER (0..3),
INTEGER (0..7),
INTEGER (0..15),
INTEGER (0..31),
INTEGER (0..63),
INTEGER (0..127),
INTEGER (0..255),
INTEGER (0..511)

-- SF512-AndPilot encodes both "Spreading factor" and "Number of bits for Pilot bits"
SF512-AndPilot ::= CHOICE {
    sfd4
    sfd8
    sfd16
    sfd32
    sfd64
    sfd128
    sfd256
    sfd512
}
NULL,
NULL,
NULL,
NULL,
NULL,
PilotBits128,
PilotBits256,
NULL

}
SF-PDSCH ::= ENUMERATED {
    sfp4, sfp8, sfp16, sfp32,
    sfp64, sfp128, sfp256 }

SF-PRACH ::= ENUMERATED {
    sfpr32, sfpr64, sfpr128, sfpr256 }

SFN-TimeInfo ::= SEQUENCE {
    activationTimeSFN
    physChDuration
}
INTEGER (0..4095),
DurationTimeInfo

-- actual scheduling value = 2^(signalled value +1) and is the periodicity of sending special burst frames
SpecialBurstScheduling ::= INTEGER (0..7)

SpreadingFactor ::= ENUMERATED {
    sf4, sf8, sf16, sf32,
    sf64, sf128, sf256 }

SRB-delay ::= INTEGER (0..7)

SSDT-CellIdentity ::= ENUMERATED {
    ssdt-id-a, ssdt-id-b, ssdt-id-c,
    ssdt-id-d, ssdt-id-e, ssdt-id-f,
    ssdt-id-g, ssdt-id-h }

SSDT-Information ::= SEQUENCE {
    s-Field
    codeWordSet
}
S-Field,
CodeWordSet

```

```

}

SSDT-Information-r4 ::= SEQUENCE {
    s-Field,
    codeWordSet,
    ssdt-UL-r4
} OPTIONAL

SSDT-UL ::= ENUMERATED {
    ul, ul-AndDL }

SynchronisationParameters-r4 ::= SEQUENCE {
    sync-UL-CodesBitmap
    BIT STRING {
        code7(0),
        code6(1),
        code5(2),
        code4(3),
        code3(4),
        code2(5),
        code1(6),
        code0(7)
    } (SIZE (8)),
    fpach-Info FPACH-Info-r4,
    -- Actual value prxUpPCHdes = IE value - 120
    prxUpPCHdes INTEGER (0..62),
    sync-UL-Procedure SYNC-UL-Procedure-r4
} OPTIONAL

SYNC-UL-Procedure-r4 ::= SEQUENCE {
    max-SYNC-UL-Transmissions
    powerRampStep
} INTEGER (0..3)

SYNC-UL-Info-r4 ::= SEQUENCE {
    sync-UL-Codes-Bitmap
    BIT STRING {
        code7(0),
        code6(1),
        code5(2),
        code4(3),
        code3(4),
        code2(5),
        code1(6),
        code0(7)
    } (SIZE (8)),
    -- Actual value prxUpPCHdes = IE value - 120
    prxUpPCHdes INTEGER (0..62),
    powerRampStep INTEGER (0..3),
    max-SYNC-UL-Transmissions
    mmax
} ENUMERATED { tr1, tr2, tr4, tr8 },
    INTEGER(1..32)

TDD-FPACH-CCode16-r4 ::= ENUMERATED {
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
    cc16-9, cc16-10, cc16-11, cc16-12,
    cc16-13, cc16-14, cc16-15, cc16-16 }

TDD-UL-Interference ::= INTEGER (-110...-52)

TDD-PICH-CCode ::= ENUMERATED {
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
    cc16-9, cc16-10, cc16-11, cc16-12,
    cc16-13, cc16-14, cc16-15, cc16-16 }

TDD-PRACH-CCode8 ::= ENUMERATED {
    cc8-1, cc8-2, cc8-3, cc8-4,
    cc8-5, cc8-6, cc8-7, cc8-8 }

TDD-PRACH-CCode16 ::= ENUMERATED {
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
    cc16-9, cc16-10, cc16-11, cc16-12,
    cc16-13, cc16-14, cc16-15, cc16-16 }

TDD-PRACH-CCode-LCR-r4 ::= ENUMERATED {
    cc4-1, cc4-2, cc4-3, cc4-4,
    cc8-1, cc8-2, cc8-3, cc8-4,
}

```

```

cc8-5, cc8-6, cc8-7, cc8-8,
cc16-1, cc16-2, cc16-3, cc16-4,
cc16-5, cc16-6, cc16-7, cc16-8,
cc16-9, cc16-10, cc16-11, cc16-12,
cc16-13, cc16-14, cc16-15, cc16-16 }

TDD-PRACH-CCodeList ::= CHOICE {
    sf8           SEQUENCE (SIZE (1..8)) OF
                  TDD-PRACH-CCode8,
-- Channelisation codes cc16-9, cc16-10, cc16-11, cc16-12, cc16-13, cc16-14,
-- cc16-15 and cc16-16 shall not be used
    sf16          SEQUENCE (SIZE (1..8)) OF
                  TDD-PRACH-CCode16
}

TFC-ControlDuration ::= ENUMERATED {
    tfc-cd1, tfc-cd2, tfc-cd4, tfc-cd8,
    tfc-cd16, tfc-cd24, tfc-cd32,
    tfc-cd48, tfc-cd64, tfc-cd128,
    tfc-cd192, tfc-cd256, tfc-cd512 }

TFCI-Coding ::= ENUMERATED {
    tfci-bits-4, tfci-bits-8,
    tfci-bits-16, tfci-bits-32 }

TGCFN ::= INTEGER (0..255)

-- In TGD, value 270 represents "undefined" in the tabular description.
TGD ::= INTEGER (15..270)

TGL ::= INTEGER (1..14)

TGMP ::= ENUMERATED {
    tdd-Measurement, fdd-Measurement,
    gsm-CarrierRSSIMeasurement,
    gsm-initialBSICIdentification, gsmBSICReconfirmation,
    multi-carrier }

TGP-Sequence ::= SEQUENCE {
    tgpsi,
    TGPSI,
    CHOICE {
        SEQUENCE {
            TGCFN
        },
        deactivate
    },
    TGPS-ConfigurationParams OPTIONAL
}

TGPS-Reconfiguration-CFN ::= INTEGER (0..255)

TGP-SequenceList ::= SEQUENCE (SIZE (1..maxTGPS)) OF
                     TGP-Sequence

TGP-SequenceShort ::= SEQUENCE {
    tgpsi,
    TGPSI,
    CHOICE {
        SEQUENCE {
            TGCFN
        },
        deactivate
    },
    NULL
}

TGPL ::= INTEGER (1..144)

-- TABULAR: In TGPRC, value 0 represents "infinity" in the tabular description.
TGPRC ::= INTEGER (0..511)

TGPS-ConfigurationParams ::= SEQUENCE {
    tgmp,
    TGMP,
    tgprc,
    TGPRC,
    tgsn,
    TGSN,
    tgl1,
    TGL,
    tgl2,
    TGL,
    tgd,
    TGD,
    tgpl1,
    TGPL,
    tgpl2,
    TGPL
}

```

```

rpp                                RPP,
itp                                ITP,
-- TABULAR: Compressed mode method is nested inside UL-DL-Mode
ul-DL-Mode                          UL-DL-Mode,
dl-FrameType                        DL-FrameType,
deltaSIR1                            DeltaSIR1,
deltaSIRAAfter1                     DeltaSIR1,
deltaSIR2                            DeltaSIR2,
deltaSIRAAfter2                     DeltaSIR2,
nIdentifyAbort                      NIdentifyAbort
treconfirmAbort                      TreconfirmAbort
}

TGPSI ::= INTEGER (1..maxTGPS)

TGSN ::= INTEGER (0..14)

TimeInfo ::= SEQUENCE {
    activationTime                  ActivationTime
    durationTimeInfo                DurationTimeInfo
}
OPTIONAL,
OPTIONAL

TimeslotList ::= SEQUENCE (SIZE (1..maxTS)) OF
    TimeslotNumber

TimeslotList-r4 ::= CHOICE {
    tdd384                           SEQUENCE (SIZE (1..maxTS)) OF
        TimeslotNumber,
    tdd128                           SEQUENCE (SIZE (1..maxTS-LCR)) OF
        TimeslotNumber-LCR-r4
}
OPTIONAL,
OPTIONAL

-- If TimeslotNumber is included for a 1.28Mcps TDD description, it shall take values from 0..6
TimeslotNumber ::= INTEGER (0..14)

TimeslotNumber-LCR-r4 ::= INTEGER (0..6)

TimeslotNumber-PRACH-LCR-r4 ::= INTEGER (1..6)

TimeslotSync2 ::= INTEGER (0..6)

-- Actual value TimingOffset = IE value * 256
TimingOffset ::= INTEGER (0..149)

TPC-CombinationIndex ::= INTEGER (0..5)

-- Actual value TPC-StepSizeFDD = IE value + 1
TPC-StepSizeFDD ::= INTEGER (0..1)

TPC-StepSizeTDD ::= INTEGER (1..3)

-- Actual value TreconfirmAbort = IE value * 0.5 seconds
TreconfirmAbort ::= INTEGER (1..20)

TX-DiversityMode ::= ENUMERATED {
    noDiversity,
    sttd,
    closedLoopMode1,
    closedLoopMode2
}

UARFCN ::= INTEGER (0..16383)

UCSM-Info ::= SEQUENCE {
    minimumSpreadingFactor          MinimumSpreadingFactor,
    nf-Max                           NF-Max,
    channelReqParamsForUCSM         ChannelReqParamsForUCSM
}
OPTIONAL,
OPTIONAL

UL-CCTrCH ::= SEQUENCE {
    tfcs-ID                          TFCS-IdentityPlain
    ul-TargetSIR                      UL-TargetSIR,
    timeInfo                          TimeInfo,
    commonTimeslotInfo                CommonTimeslotInfo
    ul-CCTrCH-TimeslotsCodes          UplinkTimeslotsCodes
}
OPTIONAL,
OPTIONAL

UL-CCTrCH-r4 ::= SEQUENCE {
    tfcs-ID                          TFCS-IdentityPlain
}
OPTIONAL,
OPTIONAL

```

```

-- The IE ul-TargetSIR corresponds to PRX-DPCHdes for 1.28Mcps TDD
-- Actual value PRX-DPCHdes = (value of IE "ul-TargetSIR" - 120)
ul-TargetSIR
timeInfo
commonTimeslotInfo
tddOption
  tdd384
    ul-CCTrCH-TimeslotsCodes
  },
  tdd128
    ul-CCTrCH-TimeslotsCodes
  }
}
}

UL-CCTrCHList ::= SEQUENCE (SIZE (1..maxCCTrCH)) OF
  UL-CCTrCH

UL-CCTrCHList-r4 ::= SEQUENCE (SIZE (1..maxCCTrCH)) OF
  UL-CCTrCH-r4

UL-CCTrCHListToRemove ::= SEQUENCE (SIZE (1..maxCCTrCH)) OF
  TFCS-IdentityPlain

UL-CCTrChTPCList ::= SEQUENCE (SIZE (0..maxCCTrCH)) OF
  TFCS-Identity

UL-ChannelRequirement ::= CHOICE {
  ul-DPCH-Info,
  cpch-SetInfo
}

UL-ChannelRequirement-r4 ::= CHOICE {
  ul-DPCH-Info,
  cpch-SetInfo
}

UL-ChannelRequirement-r5 ::= CHOICE {
  ul-DPCH-Info
  cpch-SetInfo
}

UL-ChannelRequirement-r6 ::= CHOICE {
  ul-DPCH-Info
  cpch-SetInfo
}

UL-ChannelRequirementWithCPCH-SetID ::= CHOICE {
  ul-DPCH-Info
  cpch-SetInfo
  cpch-SetID
}

UL-ChannelRequirementWithCPCH-SetID-r4 ::= CHOICE {
  ul-DPCH-Info
  cpch-SetInfo
  cpch-SetID
}

UL-ChannelRequirementWithCPCH-SetID-r5 ::= CHOICE {
  ul-DPCH-Info
  cpch-SetInfo
  cpch-SetID
}

UL-ChannelRequirementWithCPCH-SetID-r6 ::= CHOICE {
  ul-DPCH-Info
  cpch-SetInfo
  cpch-SetID
}

UL-CompressedModeMethod ::= ENUMERATED {
  sf-2,
  higherLayerScheduling }

UL-DL-Mode ::= CHOICE {
  ul
  dl
}

```

```

ul-and-dl          SEQUENCE {
    ul           UL-CompressedModeMethod,
    dl           DL-CompressedModeMethod
} }

UL-DPCCH-SlotFormat ::= ENUMERATED {
    slf0, slf1, slf2 }

UL-DPCH-Info ::= SEQUENCE {
    ul-DPCH-PowerControlInfo OPTIONAL,
    modeSpecificInfo CHOICE {
        fdd          SEQUENCE {
            scramblingCodeType ScramblingCodeType,
            scramblingCode   UL-ScramblingCode,
            numberDPDCH     NumberOfDPDCH
            spreadingFactor SpreadingFactor,
            tfci-Existence BOOLEAN,
            -- numberOffBI-Bits is conditional based on history
            numberOffBI-Bits NumberOfFBI-Bits
            puncturingLimit PuncturingLimit
        },
        tdd          SEQUENCE {
            ul-TimingAdvanceControl OPTIONAL,
            ul-CCTrCHList      OPTIONAL,
            ul-CCTrCHListToRemove OPTIONAL
        }
    }
}

UL-DPCH-Info-r4 ::= SEQUENCE {
    ul-DPCH-PowerControlInfo-r4 OPTIONAL,
    modeSpecificInfo CHOICE {
        fdd          SEQUENCE {
            scramblingCodeType ScramblingCodeType,
            scramblingCode   UL-ScramblingCode,
            numberDPDCH     NumberOfDPDCH
            spreadingFactor SpreadingFactor,
            tfci-Existence BOOLEAN,
            -- numberOffBI-Bits is conditional based on history
            numberOffBI-Bits NumberOfFBI-Bits
            puncturingLimit PuncturingLimit
        },
        tdd          SEQUENCE {
            ul-TimingAdvanceControl-r4 OPTIONAL,
            ul-CCTrCHList-r4      OPTIONAL,
            ul-CCTrCHListToRemove OPTIONAL
        }
    }
}

UL-DPCH-Info-r5 ::= SEQUENCE {
    ul-DPCH-PowerControlInfo-r5 OPTIONAL,
    modeSpecificInfo CHOICE {
        fdd          SEQUENCE {
            scramblingCodeType ScramblingCodeType,
            scramblingCode   UL-ScramblingCode,
            numberDPDCH     NumberOfDPDCH
            spreadingFactor SpreadingFactor,
            tfci-Existence BOOLEAN,
            -- numberOffBI-Bits is conditional based on history
            numberOffBI-Bits NumberOfFBI-Bits
            puncturingLimit PuncturingLimit
        },
        tdd          SEQUENCE {
            ul-TimingAdvanceControl-r4 OPTIONAL,
            ul-CCTrCHList-r4      OPTIONAL,
            ul-CCTrCHListToRemove OPTIONAL
        }
    }
}

UL-DPCH-Info-r6 ::= SEQUENCE {
    ul-DPCH-PowerControlInfo-r6 OPTIONAL,
    modeSpecificInfo CHOICE {
        fdd          SEQUENCE {
            scramblingCodeType ScramblingCodeType,
            scramblingCode   UL-ScramblingCode,
            numberDPDCH     NumberOfDPDCH
        }
    }
}

```

```

spreadingFactor           SpreadingFactor,
tfci-Existence           BOOLEAN,
-- numberOfFBI-Bits is conditional based on history
numberOfFBI-Bits          NumberOfFBI-Bits
puncturingLimit           PuncturingLimit
OPTIONAL,
},
tdd                         SEQUENCE {
    ul-TimingAdvance        UL-TimingAdvanceControl-r4 OPTIONAL,
    ul-CCTrCHList            UL-CCTrCHList-r4   OPTIONAL,
    ul-CCTrCHListToRemove    UL-CCTrCHListToRemove OPTIONAL
}
}

UL-DPCH-InfoPostFDD ::=      SEQUENCE {
    ul-DPCH-PowerControlInfo   UL-DPCH-PowerControlInfoPostFDD,
    scramblingCodeType          ScramblingCodeType,
    reducedScramblingCodeNumber ReducedScramblingCodeNumber,
    spreadingFactor             SpreadingFactor
}

UL-DPCH-InfoPostTDD ::=      SEQUENCE {
    ul-DPCH-PowerControlInfo   UL-DPCH-PowerControlInfoPostTDD,
    ul-TimingAdvance           UL-TimingAdvanceControl
                                OPTIONAL,
    ul-CCTrCH-TimeslotsCodes  UplinkTimeslotsCodes
}

UL-DPCH-InfoPostTDD-LCR-r4 ::= SEQUENCE {
    ul-DPCH-PowerControlInfo   UL-DPCH-PowerControlInfoPostTDD-LCR-r4,
    ul-TimingAdvance           UL-TimingAdvanceControl-LCR-r4
                                OPTIONAL,
    ul-CCTrCH-TimeslotsCodes  UplinkTimeslotsCodes-LCR-r4
}

UL-DPCH-InfoPredef ::=       SEQUENCE {
    ul-DPCH-PowerControlInfo   UL-DPCH-PowerControlInfoPredef,
    modeSpecificInfo           CHOICE {
        fdd                     SEQUENCE {
            tfci-Existence        BOOLEAN,
            puncturingLimit       PuncturingLimit
        },
        tdd                     SEQUENCE {
            commonTimeslotInfo   CommonTimeslotInfo
        }
    }
}

UL-DPCH-PowerControlInfo ::=  CHOICE {
    fdd                     SEQUENCE {
        dpcch-PowerOffset      DPCCH-PowerOffset,
        pc-Preamble             PC-Preamble,
        sRB-delay                SRB-delay,
        -- TABULAR: TPC step size nested inside PowerControlAlgorithm
        powerControlAlgorithm    PowerControlAlgorithm
    },
    tdd                     SEQUENCE {
        ul-TargetSIR            UL-TargetSIR
                                OPTIONAL,
        ul-OL-PC-Signalling     CHOICE {
            broadcast-UL-OL-PC-info NULL,
            individuallySignalled  SEQUENCE {
                individualTS-InterferenceList IndividualTS-InterferenceList,
                dpch-ConstantValue      ConstantValueTdd,
                primaryCCPCH-TX-Power   PrimaryCCPCH-TX-Power
            }
        }
    }
}

UL-DPCH-PowerControlInfo-r4 ::= CHOICE {
    fdd                     SEQUENCE {
        dpcch-PowerOffset      DPCCH-PowerOffset,
        pc-Preamble             PC-Preamble,
        sRB-delay                SRB-delay,
        -- TABULAR: TPC step size nested inside PowerControlAlgorithm
        powerControlAlgorithm    PowerControlAlgorithm
    },
    tdd                     SEQUENCE {
        -- The IE ul-TargetSIR corresponds to PRX-DPCHdes for 1.28Mcps TDD
    }
}

```

```

-- Actual value PRX-DPCHdes = (value of IE "ul-TargetSIR" - 120)
ul-TargetSIR                                UL-TargetSIR           OPTIONAL,
ul-OL-PC-Signalling                          CHOICE {
    broadcast-UL-OL-PC-info                 NULL,
    individuallySignalled                  SEQUENCE {
        tddOption                           CHOICE {
            tdd384                            SEQUENCE {
                individualTS-InterferenceList IndividualTS-InterferenceList,
                dpch-ConstantValue          ConstantValue
            },
            tdd128                            SEQUENCE {
                tpc-StepSize              TPC-StepSizeTDD
            }
        },
        primaryCCPCH-TX-Power          PrimaryCCPCH-TX-Power
    }
}
}

UL-DPCH-PowerControlInfo-r5 ::=      CHOICE {
    fdd                                SEQUENCE {
        dpcch-PowerOffset             DPCCH-PowerOffset,
        pc-Preamble                  PC-Preamble,
        SRB-delay                   SRB-delay,
        -- TABULAR: TPC step size nested inside PowerControlAlgorithm
        powerControlAlgorithm        PowerControlAlgorithm,
        deltaACK                     DeltaACK   OPTIONAL,
        deltaNACK                     DeltaNACK   OPTIONAL,
        ack-NACK-repetition-factor ACK-NACK-repetitionFactor OPTIONAL
    },
    tdd                                SEQUENCE {
        -- The IE ul-TargetSIR corresponds to PRX-DPCHdes for 1.28Mcps TDD
        -- Actual value PRX-DPCHdes = (value of IE "ul-TargetSIR" - 120)
        ul-TargetSIR                  UL-TargetSIR           OPTIONAL,
        ul-OL-PC-Signalling          CHOICE {
            broadcast-UL-OL-PC-info     NULL,
            individuallySignalled      SEQUENCE {
                tddOption                           CHOICE {
                    tdd384                            SEQUENCE {
                        individualTS-InterferenceList IndividualTS-InterferenceList,
                        dpch-ConstantValue          ConstantValue
                    },
                    tdd128                            SEQUENCE {
                        tpc-StepSize              TPC-StepSizeTDD
                    }
                },
                primaryCCPCH-TX-Power          PrimaryCCPCH-TX-Power
            }
        }
    }
}

UL-DPCH-PowerControlInfo-r6 ::=      CHOICE {
    fdd                                SEQUENCE {
        dpcch-PowerOffset             DPCCH-PowerOffset,
        pc-Preamble                  PC-Preamble,
        SRB-delay                   SRB-delay,
        -- TABULAR: TPC step size nested inside PowerControlAlgorithm
        powerControlAlgorithm        PowerControlAlgorithm,
        deltaACK                     DeltaACK   OPTIONAL,
        deltaNACK                     DeltaNACK   OPTIONAL,
        ack-NACK-repetition-factor ACK-NACK-repetitionFactor OPTIONAL,
        harq-Preamble-Mode          HARQ-Preamble-Mode OPTIONAL
    },
    tdd                                SEQUENCE {
        -- The IE ul-TargetSIR corresponds to PRX-DPCHdes for 1.28Mcps TDD
        -- Actual value PRX-DPCHdes = (value of IE "ul-TargetSIR" - 120)
        ul-TargetSIR                  UL-TargetSIR           OPTIONAL,
        ul-OL-PC-Signalling          CHOICE {
            broadcast-UL-OL-PC-info     NULL,
            individuallySignalled      SEQUENCE {
                tddOption                           CHOICE {
                    tdd384                            SEQUENCE {
                        individualTS-InterferenceList IndividualTS-InterferenceList,
                        dpch-ConstantValue          ConstantValue
                    },
                    tdd128                            SEQUENCE {
                        tpc-StepSize              TPC-StepSizeTDD
                    }
                }
            }
        }
    }
}

```

```

tpc-StepSize
}
},
primaryCCPCH-TX-Power
}
}
}

UL-DPCH-PowerControlInfoPostFDD ::= SEQUENCE {
-- DPCCH-PowerOffset2 has a smaller range to save bits
dpcch-PowerOffset          DPCCH-PowerOffset2,
pc-Preamble                 PC-Preamble,
sRB-delay                   SRB-delay
}

UL-DPCH-PowerControlInfoPostTDD ::= SEQUENCE {
ul-TargetSIR                UL-TargetSIR,
ul-TimeslotInterference     TDD-UL-Interference
}

UL-DPCH-PowerControlInfoPostTDD-LCR-r4 ::= SEQUENCE {
-- The IE ul-TargetSIR corresponds to PRX-DPCHdes for 1.28Mcps TDD
-- Actual value PRX-DPCHdes = (value of IE "ul-TargetSIR" - 120)
ul-TargetSIR                UL-TargetSIR
}

UL-DPCH-PowerControlInfoPredef ::= CHOICE {
fdd                         SEQUENCE {
-- TABULAR: TPC step size nested inside PowerControlAlgorithm
powerControlAlgorithm       PowerControlAlgorithm
},
tdd                         SEQUENCE {
-- dpch-ConstantValue shall be ignored if in 1.28Mcps TDD mode.
dpch-ConstantValue          ConstantValueTdd
}
}

UL-EDCH-Information-r6 ::= SEQUENCE {
e-DPCCH-Info                E-DPCCH-Info           OPTIONAL,
e-DPDCH-Info                 E-DPDCH-Info           OPTIONAL
}

UL-Interference ::= INTEGER (-110..-70)

UL-ScramblingCode ::= INTEGER (0..16777215)

UL-SynchronisationParameters-r4 ::= SEQUENCE {
stepSize                     INTEGER (1..8),
frequency                    INTEGER (1..8)
}

-- Actual value UL-TargetSIR = (IE value * 0.5) - 11
UL-TargetSIR ::= INTEGER (0..62)

UL-TimingAdvance ::= INTEGER (0..63)

UL-TimingAdvanceControl ::= CHOICE {
disabled                     NULL,
enabled                      SEQUENCE {
ul-TimingAdvance             UL-TimingAdvance
activationTime               ActivationTime
}
}

UL-TimingAdvanceControl-r4 ::= CHOICE {
disabled                     NULL,
enabled                      SEQUENCE {
tddOption                    CHOICE {
SEQUENCE {
ul-TimingAdvance             UL-TimingAdvance           OPTIONAL,
activationTime               ActivationTime            OPTIONAL
},
tdd128                      SEQUENCE {
ul-SynchronisationParameters UL-SynchronisationParameters-r4 OPTIONAL,
synchronisationParameters   SynchronisationParameters-r4 OPTIONAL
}
}
}

```

```

        }
    }

UL-TimingAdvanceControl-LCR-r4 ::= CHOICE {
    disabled
    NULL,
    enabled
    SEQUENCE {
        ul-SynchronisationParameters
        UL-SynchronisationParameters-r4 OPTIONAL,
        synchronisationParameters
        SynchronisationParameters-r4 OPTIONAL
    }
}

UL-TS-ChannelisationCode ::= ENUMERATED {
    cc1-1, cc2-1, cc2-2,
    cc4-1, cc4-2, cc4-3, cc4-4,
    cc8-1, cc8-2, cc8-3, cc8-4,
    cc8-5, cc8-6, cc8-7, cc8-8,
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
    cc16-9, cc16-10, cc16-11, cc16-12,
    cc16-13, cc16-14, cc16-15, cc16-16
}

UL-TS-ChannelisationCodeList ::= SEQUENCE (SIZE (1..2)) OF
    UL-TS-ChannelisationCode

UplinkAdditionalTimeslots ::= SEQUENCE {
    parameters
    CHOICE {
        sameAsLast
        SEQUENCE {
            timeslotNumber
        },
        newParameters
        SEQUENCE {
            individualTimeslotInfo
            IndividualTimeslotInfo,
            ul-TS-ChannelisationCodeList
            UL-TS-ChannelisationCodeList
        }
    }
}

UplinkAdditionalTimeslots-LCR-r4 ::= SEQUENCE {
    parameters
    CHOICE {
        sameAsLast
        SEQUENCE {
            timeslotNumber
        },
        newParameters
        SEQUENCE {
            individualTimeslotInfo
            IndividualTimeslotInfo-LCR-r4,
            ul-TS-ChannelisationCodeList
            UL-TS-ChannelisationCodeList
        }
    }
}

UplinkTimeslotsCodes ::= SEQUENCE {
    dynamicSFUsage
    BOOLEAN,
    firstIndividualTimeslotInfo
    IndividualTimeslotInfo,
    ul-TS-ChannelisationCodeList
    UL-TS-ChannelisationCodeList,
    moreTimeslots
    CHOICE {
        noMore
        NULL,
        additionalTimeslots
        CHOICE {
            consecutive
            SEQUENCE {
                numAdditionalTimeslots
                INTEGER (1..maxTS-1)
            },
            timeslotList
            SEQUENCE (SIZE (1..maxTS-1)) OF
                UplinkAdditionalTimeslots
        }
    }
}

UplinkTimeslotsCodes-LCR-r4 ::= SEQUENCE {
    dynamicSFUsage
    BOOLEAN,
    firstIndividualTimeslotInfo
    IndividualTimeslotInfo-LCR-r4,
    ul-TS-ChannelisationCodeList
    UL-TS-ChannelisationCodeList,
    moreTimeslots
    CHOICE {
        noMore
        NULL,
        additionalTimeslots
        CHOICE {
            consecutive
            SEQUENCE {
                numAdditionalTimeslots
                INTEGER (1..maxTS-LCR-1)
            },
            timeslotList
            SEQUENCE (SIZE (1..maxTS-LCR-1)) OF
                UplinkAdditionalTimeslots-LCR-r4
    }
}

```

```

        }
}

Wi-LCR ::= INTEGER(1..4)

-- ****
-- MEASUREMENT INFORMATION ELEMENTS (10.3.7)
-- ****

AcquisitionSatInfo ::= SEQUENCE {
    satID                               SatID,
    -- Actual value doppler0thOrder = IE value * 2.5
    doppler0thOrder                     INTEGER (-2048..2047),
    extraDopplerInfo                   ExtraDopplerInfo OPTIONAL,
    codePhase                           INTEGER (0..1022),
    integerCodePhase                   INTEGER (0..19),
    gps-BitNumber                      INTEGER (0..3),
    codePhaseSearchWindow              CodePhaseSearchWindow,
    azimuthAndElevation                AzimuthAndElevation OPTIONAL
}

AcquisitionSatInfoList ::= SEQUENCE (SIZE (1..maxSat)) OF
                            AcquisitionSatInfo

AdditionalMeasurementID-List ::= SEQUENCE (SIZE (1..maxAdditionalMeas)) OF
                                MeasurementIdentity

AlmanacSatInfo ::= SEQUENCE {
    dataID                             INTEGER (0..3),
    satID                               SatID,
    e                                   BIT STRING (SIZE (16)),
    t-oa                               BIT STRING (SIZE (8)),
    deltaI                            BIT STRING (SIZE (16)),
    omegaDot                          BIT STRING (SIZE (16)),
    satHealth                         BIT STRING (SIZE (8)),
    a-Sqrt                            BIT STRING (SIZE (24)),
    omega0                            BIT STRING (SIZE (24)),
    m0                                 BIT STRING (SIZE (24)),
    omega                            BIT STRING (SIZE (24)),
    af0                               BIT STRING (SIZE (11)),
    af1                               BIT STRING (SIZE (11))
}

AlmanacSatInfoList ::= SEQUENCE (SIZE (1..maxSat)) OF
                            AlmanacSatInfo

AverageRLC-BufferPayload ::= ENUMERATED {
    pla0, pla4, pla8, pla16, pla32,
    pla64, pla128, pla256, pla512,
    pla1024, pla2k, pla4k, pla8k, pla16k,
    pla32k, pla64k, pla128k, pla256k,
    pla512k, pla1024k, spare12, spare11,
    spare10, spare9, spare8, spare7, spare6,
    spare5, spare4, spare3, spare2, spare1 }

AzimuthAndElevation ::= SEQUENCE {
    -- Actual value azimuth = IE value * 11.25
    azimuth                           INTEGER (0..31),
    -- Actual value elevation = IE value * 11.25
    elevation                          INTEGER (0..7)
}

BadSatList ::= SEQUENCE (SIZE (1..maxSat)) OF
                  INTEGER (0..63)

Frequency-Band ::= ENUMERATED {
    dcs1800BandUsed, pcs1900BandUsed }

BCCH-ARFCN ::= INTEGER (0..1023)

BLER-MeasurementResults ::= SEQUENCE {
    transportChannelIdentity,
    dl-TransportChannelBLER           OPTIONAL
}

```

```

BLER-MeasurementResultsList ::= SEQUENCE (SIZE (1..maxTrCH)) OF
                                BLER-MeasurementResults

BLER-TransChIdList ::= SEQUENCE (SIZE (1..maxTrCH)) OF
                                TransportChannelIdentity

BSIC-VerificationRequired ::= ENUMERATED {
                                required, notRequired }

BSICReported ::= CHOICE {
-- Value maxCellMeas is not allowed for verifiedBSIC
    verifiedBSIC           INTEGER (0..maxCellMeas),
    nonVerifiedBSIC        BCCH-ARFCN
}

BurstModeParameters ::= SEQUENCE {
    burstStart             INTEGER (0..15),
    burstLength            INTEGER (10..25),
    burstFreq              INTEGER (1..16)
}

CellDCH-ReportCriteria ::= CHOICE {
    intraFreqReportingCriteria   IntraFreqReportingCriteria,
    periodicalReportingCriteria  PeriodicalReportingCriteria
}

CellDCH-ReportCriteria-LCR-r4 ::= CHOICE {
    intraFreqReportingCriteria   IntraFreqReportingCriteria-LCR-r4,
    periodicalReportingCriteria  PeriodicalReportingCriteria
}

-- Actual value CellIndividualOffset = IE value * 0.5
CellIndividualOffset ::= INTEGER (-20..20)

CellInfo ::= SEQUENCE {
    cellIndividualOffset          CellIndividualOffset                               DEFAULT 0,
    referenceTimeDifferenceToCell ReferenceTimeDifferenceToCell                  OPTIONAL,
    modeSpecificInfo               CHOICE {
        fdd                         SEQUENCE {
            primaryCPICH-Info          PrimaryCPICH-Info                           OPTIONAL,
            primaryCPICH-TX-Power       PrimaryCPICH-TX-Power                      OPTIONAL,
            readSFN-Indicator          BOOLEAN,                                     OPTIONAL,
            tx-DiversityIndicator     BOOLEAN,                                     OPTIONAL
        },
        tdd                         SEQUENCE {
            primaryCCPCH-Info          PrimaryCCPCH-Info                           OPTIONAL,
            primaryCCPCH-TX-Power       PrimaryCCPCH-TX-Power                      OPTIONAL,
            timeslotInfoList           TimeslotInfoList                          OPTIONAL,
            readSFN-Indicator          BOOLEAN,                                     OPTIONAL
        }
    }
}

CellInfo-r4 ::= SEQUENCE {
    cellIndividualOffset          CellIndividualOffset                               DEFAULT 0,
    referenceTimeDifferenceToCell ReferenceTimeDifferenceToCell                 OPTIONAL,
    modeSpecificInfo               CHOICE {
        fdd                         SEQUENCE {
            primaryCPICH-Info          PrimaryCPICH-Info                           OPTIONAL,
            primaryCPICH-TX-Power       PrimaryCPICH-TX-Power                      OPTIONAL,
            readSFN-Indicator          BOOLEAN,                                     OPTIONAL,
            tx-DiversityIndicator     BOOLEAN,                                     OPTIONAL
        },
        tdd                         SEQUENCE {
            primaryCCPCH-Info          PrimaryCCPCH-Info-r4                     OPTIONAL,
            primaryCCPCH-TX-Power       PrimaryCCPCH-TX-Power                      OPTIONAL,
            timeslotInfoList           TimeslotInfoList-r4                      OPTIONAL,
            readSFN-Indicator          BOOLEAN,                                     OPTIONAL
        }
    }
}

CellInfoSI-RSCP ::= SEQUENCE {
    cellIndividualOffset          CellIndividualOffset                               DEFAULT 0,
    referenceTimeDifferenceToCell ReferenceTimeDifferenceToCell                 OPTIONAL,
    modeSpecificInfo               CHOICE {

```

```

fdd
    primaryCPICH-Info
    primaryCPICH-TX-Power
    readSFN-Indicator
    tx-DiversityIndicator
},
tdd
    primaryCCPCH-Info
    primaryCCPCH-TX-Power
    timeslotInfoList
    readSFN-Indicator
}
},
cellSelectionReselectionInfo
}

CellInfoSI-RSCP-LCR-r4 ::=

    cellIndividualOffset
    referenceTimeDifferenceToCell
    primaryCCPCH-Info
    primaryCCPCH-TX-Power
    timeslotInfoList
    readSFN-Indicator
    cellSelectionReselectionInfo
}

CellInfoSI-ECNO ::=

    cellIndividualOffset
    referenceTimeDifferenceToCell
    modeSpecificInfo
        fdd
            primaryCPICH-Info
            primaryCPICH-TX-Power
            readSFN-Indicator
            tx-DiversityIndicator
        },
        tdd
            primaryCCPCH-Info
            primaryCCPCH-TX-Power
            timeslotInfoList
            readSFN-Indicator
        }
    },
    cellSelectionReselectionInfo
}

CellInfoSI-ECNO-LCR-r4 ::=

    cellIndividualOffset
    referenceTimeDifferenceToCell
    primaryCCPCH-Info
    primaryCCPCH-TX-Power
    timeslotInfoList
    readSFN-Indicator
    cellSelectionReselectionInfo
}

CellInfoSI-HCS-RSCP ::=

    cellIndividualOffset
    referenceTimeDifferenceToCell
    modeSpecificInfo
        fdd
            primaryCPICH-Info
            primaryCPICH-TX-Power
            readSFN-Indicator
            tx-DiversityIndicator
        },
        tdd
            primaryCCPCH-Info
            primaryCCPCH-TX-Power
            timeslotInfoList
            readSFN-Indicator
        }
    },
    cellSelectionReselectionInfo
}

CellInfoSI-HCS-RSCP-LCR-r4 ::=

    cellIndividualOffset
}

```

SEQUENCE {

PrimaryCPICH-Info	OPTIONAL,
PrimaryCPICH-TX-Power	OPTIONAL,
BOOLEAN,	
BOOLEAN	

SEQUENCE {

PrimaryCCPCH-Info,	
PrimaryCCPCH-TX-Power	OPTIONAL,
TimeslotInfoList	OPTIONAL,
BOOLEAN	

CellSelectReselectInfoSIB-11-12-RSCP OPTIONAL

SEQUENCE {

CellIndividualOffset	DEFAULT 0,
ReferenceTimeDifferenceToCell	OPTIONAL,
PrimaryCCPCH-Info-LCR-r4,	
PrimaryCCPCH-TX-Power	OPTIONAL,
TimeslotInfoList-LCR-r4	OPTIONAL,
BOOLEAN,	
CellSelectReselectInfoSIB-11-12-RSCP	OPTIONAL

SEQUENCE {

CellIndividualOffset	DEFAULT 0,
ReferenceTimeDifferenceToCell	OPTIONAL,
CHOICE {	
SEQUENCE {	
PrimaryCPICH-Info	OPTIONAL,
PrimaryCPICH-TX-Power	OPTIONAL,
BOOLEAN,	
BOOLEAN	
SEQUENCE {	
PrimaryCCPCH-Info,	
PrimaryCCPCH-TX-Power	OPTIONAL,
TimeslotInfoList	OPTIONAL,
BOOLEAN	

CellSelectReselectInfoSIB-11-12-ECNO OPTIONAL

SEQUENCE {

CellIndividualOffset	DEFAULT 0,
ReferenceTimeDifferenceToCell	OPTIONAL,
PrimaryCCPCH-Info-LCR-r4,	
PrimaryCCPCH-TX-Power	OPTIONAL,
TimeslotInfoList-LCR-r4	OPTIONAL,
BOOLEAN,	
CellSelectReselectInfoSIB-11-12-ECNO	OPTIONAL

SEQUENCE {

CellIndividualOffset	DEFAULT 0,
ReferenceTimeDifferenceToCell	OPTIONAL,
CHOICE {	
SEQUENCE {	
PrimaryCPICH-Info	OPTIONAL,
PrimaryCPICH-TX-Power	OPTIONAL,
BOOLEAN,	
BOOLEAN	
SEQUENCE {	
PrimaryCCPCH-Info,	
PrimaryCCPCH-TX-Power	OPTIONAL,
TimeslotInfoList	OPTIONAL,
BOOLEAN	

CellSelectReselectInfoSIB-11-12-HCS-RSCP OPTIONAL

SEQUENCE {

CellIndividualOffset	OPTIONAL,
----------------------	-----------

```

referenceTimeDifferenceToCell           ReferenceTimeDifferenceToCell           OPTIONAL,
primaryCCPCH-Info                     PrimaryCCPCH-Info-LCR-r4,             OPTIONAL,
primaryCCPCH-TX-Power                 PrimaryCCPCH-TX-Power,               OPTIONAL,
timeslotInfoList                      TimeslotInfoList-LCR-r4,             OPTIONAL,
readSFN-Indicator                     BOOLEAN,                                OPTIONAL,
cellSelectionReselectionInfo          CellSelectReselectInfoSIB-11-12-HCS-RSCP   OPTIONAL
}

CellInfoSI-HCS-ECNO ::=           SEQUENCE {
  cellIndividualOffset                CellIndividualOffset                  DEFAULT 0,
  referenceTimeDifferenceToCell       ReferenceTimeDifferenceToCell      OPTIONAL,
  modeSpecificInfo                   CHOICE {
    fdd                           SEQUENCE {
      primaryCPICH-Info            PrimaryCPICH-Info,                  OPTIONAL,
      primaryCPICH-TX-Power        PrimaryCPICH-TX-Power,             OPTIONAL,
      readSFN-Indicator           BOOLEAN,                                OPTIONAL,
      tx-DiversityIndicator       BOOLEAN
    },
    tdd                           SEQUENCE {
      primaryCCPCH-Info           PrimaryCCPCH-Info,                  OPTIONAL,
      primaryCCPCH-TX-Power        PrimaryCCPCH-TX-Power,             OPTIONAL,
      timeslotInfoList            TimeslotInfoList,                OPTIONAL,
      readSFN-Indicator           BOOLEAN
    }
  },
  cellSelectionReselectionInfo        CellSelectReselectInfoSIB-11-12-HCS-ECNO   OPTIONAL
}

CellInfoSI-HCS-ECNO-LCR-r4 ::=     SEQUENCE {
  cellIndividualOffset                CellIndividualOffset                  DEFAULT 0,
  referenceTimeDifferenceToCell       ReferenceTimeDifferenceToCell      OPTIONAL,
  primaryCCPCH-Info                 PrimaryCCPCH-Info-LCR-r4,             OPTIONAL,
  primaryCCPCH-TX-Power              PrimaryCCPCH-TX-Power,             OPTIONAL,
  timeslotInfoList                  TimeslotInfoList-LCR-r4,             OPTIONAL,
  readSFN-Indicator                 BOOLEAN,                                OPTIONAL,
  cellSelectionReselectionInfo       CellSelectReselectInfoSIB-11-12-HCS-ECNO   OPTIONAL
}

CellMeasuredResults ::=           SEQUENCE {
  cellIdentity                      CellIdentity,                         OPTIONAL,
  -- dummy is not used in this version of the specification, it should
  -- not be sent and if received it should be ignored.
  dummy                            SFN-SFN-ObsTimeDifference,          OPTIONAL,
  cellSynchronisationInfo           CellSynchronisationInfo,           OPTIONAL,
  modeSpecificInfo                  CHOICE {
    fdd                           SEQUENCE {
      primaryCPICH-Info            PrimaryCPICH-Info,                  OPTIONAL,
      cpich-Ec-N0                  CPICH-Ec-N0,                      OPTIONAL,
      cpich-RSCP                   CPICH-RSCP,                      OPTIONAL,
      pathloss                     Pathloss
    },
    tdd                           SEQUENCE {
      cellParametersID            CellParametersID,                 OPTIONAL,
      proposedTGSN                TGSN,                               OPTIONAL,
      primaryCCPCH-RSCP            PrimaryCCPCH-RSCP,                OPTIONAL,
      pathloss                     Pathloss,                         OPTIONAL,
      timeslotISCP-List           TimeslotISCP-List,              OPTIONAL
    }
  }
}

CellMeasurementEventResults ::=      CHOICE {
  fdd                           SEQUENCE (SIZE (1..maxCellMeas)) OF
                                PrimaryCPICH-Info,
  tdd                           SEQUENCE (SIZE (1..maxCellMeas)) OF
                                PrimaryCCPCH-Info
}

CellMeasurementEventResults-LCR-r4 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
                                         PrimaryCCPCH-Info-LCR-r4

CellReportingQuantities ::=         SEQUENCE {
  -- dummy is not used in this version of the specification, it should
  -- not be sent and if received it should be ignored.
  dummy                          SFN-SFN-OTD-Type,
  cellIdentity-reportingIndicator BOOLEAN,                                OPTIONAL,
  cellSynchronisationInfoReportingIndicator BOOLEAN,                  OPTIONAL,
  modeSpecificInfo                 CHOICE {

```

```

fdd                                SEQUENCE {
    cpich-Ec-N0-reportingIndicator      BOOLEAN,
    cpich-RSCP-reportingIndicator      BOOLEAN,
    pathloss-reportingIndicator       BOOLEAN
},
tdd                                SEQUENCE {
    timeslotISCP-reportingIndicator   BOOLEAN,
    proposedTGSN-ReportingRequired    BOOLEAN,
    primaryCCPCH-RSCP-reportingIndicator  BOOLEAN,
    pathloss-reportingIndicator       BOOLEAN
}
}

CellSelectReselectInfoSIB-11-12 ::= SEQUENCE {
    q-Offset1S-N                      Q-OffsetS-N                               DEFAULT 0,
    q-Offset2S-N                      Q-OffsetS-N                               OPTIONAL,
    maxAllowedUL-TX-Power             MaxAllowedUL-TX-Power                         OPTIONAL,
    hcs-NeighbouringCellInformation-RSCP   HCS-NeighbouringCellInformation-RSCP
    OPTIONAL,
    modeSpecificInfo                  CHOICE {
        fdd                            SEQUENCE {
            q-QualMin                   Q-QualMin
            q-RxlevMin                 Q-RxlevMin
        },
        tdd                            SEQUENCE {
            q-RxlevMin                 Q-RxlevMin
        },
        gsm                            SEQUENCE {
            q-RxlevMin                 Q-RxlevMin
        }
    }
}

CellSelectReselectInfoSIB-11-12-RSCP ::= SEQUENCE {
    q-OffsetS-N                      Q-OffsetS-N                               DEFAULT 0,
    maxAllowedUL-TX-Power             MaxAllowedUL-TX-Power                         OPTIONAL,
    modeSpecificInfo                  CHOICE {
        fdd                            SEQUENCE {
            q-QualMin                   Q-QualMin
            q-RxlevMin                 Q-RxlevMin
        },
        tdd                            SEQUENCE {
            q-RxlevMin                 Q-RxlevMin
        },
        gsm                            SEQUENCE {
            q-RxlevMin                 Q-RxlevMin
        }
    }
}

CellSelectReselectInfoSIB-11-12-ECN0 ::= SEQUENCE {
    q-Offset1S-N                      Q-OffsetS-N                               DEFAULT 0,
    q-Offset2S-N                      Q-OffsetS-N                               DEFAULT 0,
    maxAllowedUL-TX-Power             MaxAllowedUL-TX-Power                         OPTIONAL,
    modeSpecificInfo                  CHOICE {
        fdd                            SEQUENCE {
            q-QualMin                   Q-QualMin
            q-RxlevMin                 Q-RxlevMin
        },
        tdd                            SEQUENCE {
            q-RxlevMin                 Q-RxlevMin
        },
        gsm                            SEQUENCE {
            q-RxlevMin                 Q-RxlevMin
        }
    }
}

CellSelectReselectInfoSIB-11-12-HCS-RSCP ::= SEQUENCE {
    q-OffsetS-N                      Q-OffsetS-N                               DEFAULT 0,
    maxAllowedUL-TX-Power             MaxAllowedUL-TX-Power                         OPTIONAL,
    hcs-NeighbouringCellInformation-RSCP   HCS-NeighbouringCellInformation-RSCP
    OPTIONAL,
    modeSpecificInfo                  CHOICE {
        fdd                            SEQUENCE {
            q-QualMin                   Q-QualMin
            q-RxlevMin                 Q-RxlevMin
        }
    }
}

```

```

        },
        tdd          q-RxlevMin           SEQUENCE {
                                Q-RxlevMin           OPTIONAL
        },
        gsm          q-RxlevMin           SEQUENCE {
                                Q-RxlevMin           OPTIONAL
        }
    }

CellSelectReselectInfoSIB-11-12-HCS-ECN0 ::= SEQUENCE {
    q-Offset1S-N             Q-OffsetS-N           DEFAULT 0,
    q-Offset2S-N             Q-OffsetS-N           DEFAULT 0,
    maxAllowedUL-TX-Power   MaxAllowedUL-TX-Power   OPTIONAL,
    hcs-NeighbouringCellInformation-ECN0   HCS-NeighbouringCellInformation-ECN0
    OPTIONAL,
    modeSpecificInfo         CHOICE {
        fdd          q-QualMin            SEQUENCE {
                                Q-QualMin           OPTIONAL,
                                Q-RxlevMin          OPTIONAL
        },
        tdd          q-RxlevMin          SEQUENCE {
                                Q-RxlevMin          OPTIONAL
        },
        gsm          q-RxlevMin          SEQUENCE {
                                Q-RxlevMin          OPTIONAL
        }
    }
}

CellSelectReselectInfo-v590ext ::= SEQUENCE {
    deltaQrxlevmin          DeltaQrxlevmin      OPTIONAL,
    deltaQhcs                DeltaRSCP           OPTIONAL
}

CellSelectReselectInfoPCHFACH-v5b0ext ::= SEQUENCE {
    q-Hyst-1-S-PCH           Q-Hyst-S-Fine       OPTIONAL,
    q-Hyst-1-S-FACH          Q-Hyst-S-Fine       OPTIONAL,
    q-Hyst-2-S-PCH           Q-Hyst-S-Fine       OPTIONAL,
    q-Hyst-2-S-FACH          Q-Hyst-S-Fine       OPTIONAL,
    t-Reselection-S-PCH     T-Reselection-S       OPTIONAL,
    t-Reselection-S-FACH    T-Reselection-S-Fine  OPTIONAL
}

CellsForInterFreqMeasList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    InterFreqCellID
CellsForInterRATMeasList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    InterRATCellID
CellsForIntraFreqMeasList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    IntraFreqCellID

CellSynchronisationInfo ::= SEQUENCE {
    modeSpecificInfo         CHOICE {
        fdd          countC-SFN-Frame-difference SEQUENCE {
                                CountC-SFN-Frame-difference OPTIONAL,
                                INTEGER(0..38399)
        },
        tdd          countC-SFN-Frame-difference SEQUENCE {
                                CountC-SFN-Frame-difference OPTIONAL
        }
    }
}

CellToReport ::= SEQUENCE {
    bsicReported             BSICReported
}

CellToReportList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    CellToReport

CodePhaseSearchWindow ::= ENUMERATED {
    w1023, w1, w2, w3, w4, w6, w8,
    w12, w16, w24, w32, w48, w64,
    w96, w128, w192
}

CountC-SFN-Frame-difference ::= SEQUENCE {
    -- Actual value countC-SFN-High = IE value * 256
    countC-SFN-High           INTEGER(0..15),
}

```

```

    off                                INTEGER(0..255)
}

-- SPARE: CPICH-Ec-No, Max = 49
-- Values above Max are spare
CPICH-Ec-N0 ::= INTEGER (0..63)

-- SPARE: CPICH- RSCP, Max = 91
-- Values above Max are spare
CPICH-RSCP ::= INTEGER (0..127)

DeltaPRC ::= INTEGER (-127..127)

--Actual value DeltaQrxlevmin = IE value * 2
DeltaQrxlevmin ::= INTEGER (-2..-1)

DeltaRSCP ::= INTEGER (-5..-1)

DeltaRSCPPerCell ::= SEQUENCE {
    deltaRSCP          DeltaRSCP OPTIONAL
}

-- Actual value DeltaRRC = IE value * 0.032
DeltaRRC ::= INTEGER (-7..7)

DGPS-CorrectionSatInfo ::= SEQUENCE {
    satID                SatID,
    iode                 IODE,
    udre                 UDRE,
    prc                  PRC,
    rrc                  RRC,
}
-- dummy1 and dummy2 are not used in this version of the specification and should be ignored.
dummy1              DeltaPRC,
dummy2              DeltaRRC,
-- dummy3 and dummy4 are not used in this version of the specification. They should not
-- be sent and if received they should be ignored.
dummy3              DeltaPRC OPTIONAL,
dummy4              DeltaRRC OPTIONAL
}

DGPS-CorrectionSatInfoList ::= SEQUENCE (SIZE (1..maxSat)) OF
                               DGPS-CorrectionSatInfo

DiffCorrectionStatus ::= ENUMERATED {
    udre-1-0, udre-0-75, udre-0-5, udre-0-3,
    udre-0-2, udre-0-1, noData, invalidData }

DL-TransportChannelBLER ::= INTEGER (0..63)

DopplerUncertainty ::= ENUMERATED {
    hz12-5, hz25, hz50, hz100, hz200,
    spare3, spare2, spare1 }

EllipsoidPoint ::= SEQUENCE {
    latitudeSign        ENUMERATED { north, south },
    latitude             INTEGER (0..8388607),
    longitude            INTEGER (-8388608..8388607)
}

EllipsoidPointAltitude ::= SEQUENCE {
    latitudeSign        ENUMERATED { north, south },
    latitude             INTEGER (0..8388607),
    longitude            INTEGER (-8388608..8388607),
    altitudeDirection   ENUMERATED {height, depth},
    altitude             INTEGER (0..32767)
}

EllipsoidPointAltitudeEllipsoide ::= SEQUENCE {
    latitudeSign        ENUMERATED { north, south },
    latitude             INTEGER (0..8388607),
    longitude            INTEGER (-8388608..8388607),
    altitudeDirection   ENUMERATED {height, depth},
    altitude             INTEGER (0..32767),
    uncertaintySemiMajor INTEGER (0..127),
    uncertaintySemiMinor INTEGER (0..127),
}

```

```

-- Actual value orientationMajorAxis = IE value * 2
orientationMajorAxis      INTEGER (0..89),
uncertaintyAltitude      INTEGER (0..127),
confidence                INTEGER (0..100)
}

EllipsoidPointUncertCircle ::=      SEQUENCE {
    latitudeSign           ENUMERATED { north, south },
    latitude                 INTEGER (0..8388607),
    longitude                INTEGER (-8388608..8388607),
    uncertaintyCode          INTEGER (0..127)
}

EllipsoidPointUncertEllipse ::=      SEQUENCE {
    latitudeSign           ENUMERATED { north, south },
    latitude                 INTEGER (0..8388607),
    longitude                INTEGER (-8388608..8388607),
    uncertaintySemiMajor     INTEGER (0..127),
    uncertaintySemiMinor     INTEGER (0..127),
    -- Actual value orientationMajorAxis = IE value * 2
    orientationMajorAxis      INTEGER (0..89),
    confidence                INTEGER (0..100)
}

EnvironmentCharacterisation ::=      ENUMERATED {
    possibleHeavyMultipathNLOS,
    lightMultipathLOS,
    notDefined,
    spare }

Eventla ::=      SEQUENCE {
    triggeringCondition,
    reportingRange,
    forbiddenAffectCellList OPTIONAL,
    w,
    reportDeactivationThreshold,
    reportingAmount,
    reportingInterval }

Eventla-r4 ::=      SEQUENCE {
    triggeringCondition,
    reportingRange,
    forbiddenAffectCellList OPTIONAL,
    w,
    reportDeactivationThreshold,
    reportingAmount,
    reportingInterval }

Eventla-LCR-r4 ::=      SEQUENCE {
    triggeringCondition,
    reportingRange,
    forbiddenAffectCellList OPTIONAL,
    w,
    reportDeactivationThreshold,
    reportingAmount,
    reportingInterval }

Eventlb ::=      SEQUENCE {
    triggeringCondition,
    reportingRange,
    forbiddenAffectCellList OPTIONAL,
    w }

Eventlb-r4 ::=      SEQUENCE {
    triggeringCondition,
    reportingRange,
    forbiddenAffectCellList OPTIONAL,
    w }

Eventlb-LCR-r4 ::=      SEQUENCE {

```

```

triggeringCondition           TriggeringCondition1,
reportingRange                 ReportingRange,
forbiddenAffectCellList       ForbiddenAffectCellList-LCR-r4      OPTIONAL,
w                               W
}

Event1c ::= SEQUENCE {
    replacementActivationThreshold ReplacementActivationThreshold,
    reportingAmount                ReportingAmount,
    reportingInterval              ReportingInterval
}

Event1e ::= SEQUENCE {
    triggeringCondition           TriggeringCondition2,
    thresholdUsedFrequency        ThresholdUsedFrequency
}

Event1f ::= SEQUENCE {
    triggeringCondition           TriggeringCondition1,
    thresholdUsedFrequency        ThresholdUsedFrequency
}

Event2a ::= SEQUENCE {
    -- dummy is not used in this version of the specification and should be ignored
    dummy                         Threshold,
    usedFreqW                      W,
    hysteresis                     HysteresisInterFreq,
    timeToTrigger                  TimeToTrigger,
    reportingCellStatus            ReportingCellStatus
    nonUsedFreqParameterList      NonUsedFreqParameterList      OPTIONAL,
}                                         OPTIONAL

Event2b ::= SEQUENCE {
    usedFreqThreshold             Threshold,
    usedFreqW                     W,
    hysteresis                   HysteresisInterFreq,
    timeToTrigger                TimeToTrigger,
    reportingCellStatus          ReportingCellStatus
    nonUsedFreqParameterList    NonUsedFreqParameterList      OPTIONAL,
}                                         OPTIONAL

Event2c ::= SEQUENCE {
    hysteresis                   HysteresisInterFreq,
    timeToTrigger                TimeToTrigger,
    reportingCellStatus          ReportingCellStatus
    nonUsedFreqParameterList    NonUsedFreqParameterList      OPTIONAL,
}                                         OPTIONAL

Event2d ::= SEQUENCE {
    usedFreqThreshold             Threshold,
    usedFreqW                     W,
    hysteresis                   HysteresisInterFreq,
    timeToTrigger                TimeToTrigger,
    reportingCellStatus          ReportingCellStatus
}                                         OPTIONAL

Event2e ::= SEQUENCE {
    hysteresis                   HysteresisInterFreq,
    timeToTrigger                TimeToTrigger,
    reportingCellStatus          ReportingCellStatus
    nonUsedFreqParameterList    NonUsedFreqParameterList      OPTIONAL,
}                                         OPTIONAL

Event2f ::= SEQUENCE {
    usedFreqThreshold             Threshold,
    usedFreqW                     W,
    hysteresis                   HysteresisInterFreq,
    timeToTrigger                TimeToTrigger,
    reportingCellStatus          ReportingCellStatus
}                                         OPTIONAL

Event3a ::= SEQUENCE {
    thresholdOwnSystem            Threshold,
    w                             W,
    thresholdOtherSystem          Threshold,
    hysteresis                   Hysteresis,
    timeToTrigger                TimeToTrigger,
    reportingCellStatus          ReportingCellStatus
}                                         OPTIONAL

```

```

}

Event3b ::= SEQUENCE {
    thresholdOtherSystem,
    hysteresis,
    timeToTrigger,
    reportingCellStatus
} OPTIONAL

Event3c ::= SEQUENCE {
    thresholdOtherSystem,
    hysteresis,
    timeToTrigger,
    reportingCellStatus
} OPTIONAL

Event3d ::= SEQUENCE {
    hysteresis,
    timeToTrigger,
    reportingCellStatus
} OPTIONAL

EventIDInterFreq ::= ENUMERATED {
    e2a, e2b, e2c, e2d, e2e, e2f, spare2, spare1 }

EventIDInterRAT ::= ENUMERATED {
    e3a, e3b, e3c, e3d }

EventIDIntraFreq ::= ENUMERATED {
    ela, elb, elc, eld, ele,
    elf, elg, elh, eli, spare7,
    spare6, spare5, spare4, spare3, spare2,
    spare1 }

EventResults ::= CHOICE {
    intraFreqEventResults,
    interFreqEventResults,
    interRATEventResults,
    trafficVolumeEventResults,
    qualityEventResults,
    ue-InternalEventResults,
    ue-positioning-MeasurementEventResults,
    spare
} NULL

ExtraDopplerInfo ::= SEQUENCE {
    -- Actual value doppler1stOrder = IE value * 0.023
    doppler1stOrder INTEGER (-42..21),
    dopplerUncertainty DopplerUncertainty
}

FACH-MeasurementOccasionInfo ::= SEQUENCE {
    fACH-meas-occasion-coeff INTEGER (1..12) OPTIONAL,
    inter-freq-FDD-meas-ind BOOLEAN,
    -- inter-freq-TDD-meas-ind is for 3.84Mcps TDD. For 1.28Mcps TDD, the IE in
    -- FACH-MeasurementOccasionInfo-LCR-r4-ext is used.
    inter-freq-TDD-meas-ind BOOLEAN,
    inter-RAT-meas-ind SEQUENCE (SIZE (1..maxOtherRAT)) OF
        RAT-Type OPTIONAL
}

FACH-MeasurementOccasionInfo-LCR-r4-ext ::= SEQUENCE {
    inter-freq-TDD128-meas-ind BOOLEAN
}

FilterCoefficient ::= ENUMERATED {
    fc0, fc1, fc2, fc3, fc4, fc5,
    fc6, fc7, fc8, fc9, fc11, fc13,
    fc15, fc17, fc19, spare1 }

-- Actual value FineSFN-SFN = IE value * 0.0625
FineSFN-SFN ::= INTEGER (0..15)

ForbiddenAffectCell ::= CHOICE {
    fdd PrimaryCPICH-Info,
    tdd PrimaryCCPCH-Info
}

```

```

ForbiddenAffectCell-r4 ::= CHOICE {
    fdd
    tdd
}
PrimaryCPICH-Info,
PrimaryCCPCH-Info-r4

ForbiddenAffectCell-LCR-r4 ::= SEQUENCE {
    tdd
}
PrimaryCCPCH-Info-LCR-r4

ForbiddenAffectCellList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    ForbiddenAffectCell

ForbiddenAffectCellList-r4 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    ForbiddenAffectCell-r4

ForbiddenAffectCellList-LCR-r4 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    ForbiddenAffectCell-LCR-r4

FreqQualityEstimateQuantity-FDD ::= ENUMERATED {
    cpich-Ec-N0,
    cpich-RSCP
}

FreqQualityEstimateQuantity-TDD ::= ENUMERATED {
    primaryCCPCH-RSCP
}

GPS-MeasurementParam ::= SEQUENCE {
    satelliteID
    INTEGER (0..63),
    c-N0
    INTEGER (0..63),
    doppler
    INTEGER (-32768..32768),
    wholeGPS-Chips
    INTEGER (0..1022),
    fractionalGPS-Chips
    INTEGER (0..1023),
    multipathIndicator
    MultipathIndicator,
    pseudorangeRMS-Error
    INTEGER (0..63)
}

GPS-MeasurementParamList ::= SEQUENCE (SIZE (1..maxSat)) OF
    GPS-MeasurementParam

GSM-CarrierRSSI ::= BIT STRING (SIZE (6))

GSM-MeasuredResults ::= SEQUENCE {
    gsm-CarrierRSSI
        GSM-CarrierRSSI
        OPTIONAL,
    -- dummy is not used in this version of the specification, it should
    -- not be sent and if received it should be ignored.
    dummy
        INTEGER (46..173)
        OPTIONAL,
    bsicReported
        BSICReported,
    observedTimeDifferenceToGSM
        ObservedTimeDifferenceToGSM
        OPTIONAL
}
GSM-MeasuredResultsList ::= SEQUENCE (SIZE (1..maxReportedGSMCells)) OF
    GSM-MeasuredResults

GPS-TOW-1msec ::= INTEGER (0..604799999)

GPS-TOW-Assist ::= SEQUENCE {
    satID
    SatID,
    tlm-Message
    BIT STRING (SIZE (14)),
    tlm-Reserved
    BIT STRING (SIZE (2)),
    alert
    BOOLEAN,
    antiSpoof
    BOOLEAN
}

GPS-TOW-AssistList ::= SEQUENCE (SIZE (1..maxSat)) OF
    GPS-TOW-Assist

HCS-CellReselectInformation-RSCP ::= SEQUENCE {
    -- TABULAR: The default value for penaltyTime is "notUsed"
    -- Temporary offset is nested inside PenaltyTime-RSCP
    penaltyTime
        PenaltyTime-RSCP
}
HCS-CellReselectInformation-ECNO ::= SEQUENCE {
    -- TABULAR: The default value for penaltyTime is "notUsed"
    -- Temporary offset is nested inside PenaltyTime-ECNO
    penaltyTime
        PenaltyTime-ECNO
}

```

```

HCS-NeighbouringCellInformation-RSCP ::= SEQUENCE {
    hcs-PRI0                               HCS-PRI0                               DEFAULT 0,
    q-HCS                                    Q-HCS                                 DEFAULT 0,
    hcs-CellReselectInformation             HCS-CellReselectInformation-RSCP
}

HCS-NeighbouringCellInformation-ECNO ::= SEQUENCE {
    hcs-PRI0                               HCS-PRI0                               DEFAULT 0,
    q-HCS                                    Q-HCS                                 DEFAULT 0,
    hcs-CellReselectInformation             HCS-CellReselectInformation-ECNO
}

HCS-PRI0 ::= INTEGER (0..7)

HCS-ServingCellInformation ::= SEQUENCE {
    hcs-PRI0                               HCS-PRI0                               DEFAULT 0,
    q-HCS                                    Q-HCS                                 DEFAULT 0,
    t-CR-Max                                T-CRMax                               OPTIONAL
}

-- Actual value Hysteresis = IE value * 0.5
Hysteresis ::= INTEGER (0..15)

-- Actual value HysteresisInterFreq = IE value * 0.5
HysteresisInterFreq ::= INTEGER (0..29)

InterFreqCell ::= SEQUENCE {
    frequencyInfo                           FrequencyInfo,
    nonFreqRelatedEventResults            CellMeasurementEventResults
}

InterFreqCell-LCR-r4 ::= SEQUENCE {
    frequencyInfo                           FrequencyInfo,
    nonFreqRelatedEventResults            CellMeasurementEventResults-LCR-r4
}

InterFreqCellID ::= INTEGER (0..maxCellMeas-1)

InterFreqCellInfoList ::= SEQUENCE {
    removedInterFreqCellList              RemovedInterFreqCellList           OPTIONAL,
    newInterFreqCellList                 NewInterFreqCellList              OPTIONAL,
    cellsForInterFreqMeasList            CellsForInterFreqMeasList         OPTIONAL
}

InterFreqCellInfoList-r4 ::= SEQUENCE {
    removedInterFreqCellList              RemovedInterFreqCellList           OPTIONAL,
    newInterFreqCellList                 NewInterFreqCellList-r4            OPTIONAL,
    cellsForInterFreqMeasList            CellsForInterFreqMeasList         OPTIONAL
}

InterFreqCellInfoSI-List-RSCP ::= SEQUENCE {
    removedInterFreqCellList              RemovedInterFreqCellList           OPTIONAL,
    newInterFreqCellList                 NewInterFreqCellList              OPTIONAL
}

InterFreqCellInfoSI-List-ECNO ::= SEQUENCE {
    removedInterFreqCellList              RemovedInterFreqCellList           OPTIONAL,
    newInterFreqCellList                 NewInterFreqCellListSI-List-ECNO   OPTIONAL
}

InterFreqCellInfoSI-List-HCS-RSCP ::= SEQUENCE {
    removedInterFreqCellList              RemovedInterFreqCellList           OPTIONAL,
    newInterFreqCellList                 NewInterFreqCellListSI-List-HCS-RSCP OPTIONAL
}

InterFreqCellInfoSI-List-HCS-ECNO ::= SEQUENCE {
    removedInterFreqCellList              RemovedInterFreqCellList           OPTIONAL,
    newInterFreqCellList                 NewInterFreqCellListSI-List-HCS-ECNO OPTIONAL
}

InterFreqCellInfoSI-List-RSCP-LCR ::= SEQUENCE {
    removedInterFreqCellList              RemovedInterFreqCellList           OPTIONAL,
    newInterFreqCellList                 NewInterFreqCellListSI-List-RSCP-LCR-r4 OPTIONAL
}

InterFreqCellInfoSI-List-ECNO-LCR ::= SEQUENCE {
    removedInterFreqCellList              RemovedInterFreqCellList           OPTIONAL,
    newInterFreqCellList                 NewInterFreqCellListSI-List-ECNO-LCR-r4 OPTIONAL
}

```

```

}

InterFreqCellInfoSI-List-HCS-RSCP-LCR ::= SEQUENCE {
    removedInterFreqCellList           OPTIONAL,
    newInterFreqCellList              NewInterFreqCellSI-List-HCS-RSCP-LCR-r4 OPTIONAL
}
InterFreqCellInfoSI-List-HCS-ECN0-LCR ::= SEQUENCE {
    removedInterFreqCellList           OPTIONAL,
    newInterFreqCellList              NewInterFreqCellSI-List-HCS-ECN0-LCR-r4 OPTIONAL
}

InterFreqCellList ::= SEQUENCE (SIZE (1..maxFreq)) OF
    InterFreqCell

InterFreqCellList-LCR-r4-ext ::= SEQUENCE (SIZE (1..maxFreq)) OF
    InterFreqCell-LCR-r4

InterFreqCellMeasuredResultsList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    CellMeasuredResults

InterFreqEvent ::= CHOICE {
    event2a,
    event2b,
    event2c,
    event2d,
    event2e,
    event2f
}

InterFreqEventList ::= SEQUENCE (SIZE (1..maxMeasEvent)) OF
    InterFreqEvent

--Following IE shall be used regardless of CPICH RSCP(FDD) or Primary CCPCH RSCP(TDD)
--The order of the list corresponds to the order of the cells in Inter-FrequencyMeasuredResultsList
InterFrequencyMeasuredResultsList-v590ext ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    DeltaRSCPPerCell

Inter-FreqEventCriteria-v590ext ::= SEQUENCE {
    thresholdUsedFrequency-delta      DeltaRSCP,
    thresholdNonUsedFrequency-deltaList ThresholdNonUsedFrequency-deltaList OPTIONAL
}

--The order of the list corresponds to the order of the events in Inter-FreqEventList
Inter-FreqEventCriteriaList-v590ext ::= SEQUENCE (SIZE (1..maxMeasEvent)) OF
    Inter-FreqEventCriteria-v590ext

--The order of the list corresponds to the order of relevant events in Intra-FreqEventCriteriaList
--i.e. the first element of the list corresponds to the first occurrence of event 1e, 1f, 1h, 1i,
--the second element of the list corresponds to the second occurrence of event 1e, 1f, 1h, 1i
Intra-FreqEventCriteriaList-v590ext ::= SEQUENCE (SIZE (1..maxMeasEvent)) OF
    DeltaRSCP

--Following IE shall be used regardless of CPICH RSCP(FDD) or Primary CCPCH RSCP(TDD)
--The order of the list corresponds to the order of the cells in Intra-FrequencyMeasuredResultsList
IntraFrequencyMeasuredResultsList-v590ext ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    DeltaRSCPPerCell

IntraFreqReportingCriteria-1b-r5 ::= SEQUENCE {
    periodicReportingInfo-1b          PeriodicReportingInfo-1b
}

PeriodicReportingInfo-1b ::= SEQUENCE {
    reportingAmount                  ReportingAmount,
    reportingInterval                ReportingInterval
}

InterFreqEventResults ::= SEQUENCE {
    eventID                         EventIDInterFreq,
    interFreqCellList                InterFreqCellList OPTIONAL
}

InterFreqEventResults-LCR-r4-ext ::= SEQUENCE {
    eventID                         EventIDInterFreq,
    interFreqCellList                InterFreqCellList-LCR-r4-ext OPTIONAL
}

InterFreqMeasQuantity ::= SEQUENCE {
    reportingCriteria                CHOICE {

```

```

intraFreqReportingCriteria      SEQUENCE {
    intraFreqMeasQuantity      IntraFreqMeasQuantity
},
interFreqReportingCriteria      SEQUENCE {
    filterCoefficient          FilterCoefficient           DEFAULT fc0,
    modeSpecificInfo           CHOICE {
        fdd                      SEQUENCE {
            freqQualityEstimateQuantity-FDD   FreqQualityEstimateQuantity-FDD
        },
        tdd                      SEQUENCE {
            freqQualityEstimateQuantity-TDD   FreqQualityEstimateQuantity-TDD
        }
    }
}
}

InterFreqMeasuredResults ::=      SEQUENCE {
    frequencyInfo               FrequencyInfo             OPTIONAL,
    ultra-CarrierRSSI           UTRA-CarrierRSSI         OPTIONAL,
    interFreqCellMeasuredResultsList InterFreqCellMeasuredResultsList OPTIONAL
}

InterFreqMeasuredResultsList ::=   SEQUENCE (SIZE (1..maxFreq)) OF
                                    InterFreqMeasuredResults

InterFreqMeasurementSysInfo-RSCP ::= SEQUENCE {
    interFreqCellInfoSI-List     InterFreqCellInfoSI-List-RSCP   OPTIONAL
}

InterFreqMeasurementSysInfo-ECNO ::= SEQUENCE {
    interFreqCellInfoSI-List     InterFreqCellInfoSI-List-ECNO   OPTIONAL
}

InterFreqMeasurementSysInfo-HCS-RSCP ::= SEQUENCE {
    interFreqCellInfoSI-List     InterFreqCellInfoSI-List-HCS-RSCP   OPTIONAL
}

InterFreqMeasurementSysInfo-HCS-ECNO ::= SEQUENCE {
    interFreqCellInfoSI-List     InterFreqCellInfoSI-List-HCS-ECNO   OPTIONAL
}

InterFreqMeasurementSysInfo-RSCP-LCR-r4 ::= SEQUENCE {
    interFreqCellInfoSI-List     InterFreqCellInfoSI-List-RSCP-LCR   OPTIONAL
}

InterFreqMeasurementSysInfo-ECNO-LCR-r4 ::= SEQUENCE {
    interFreqCellInfoSI-List     InterFreqCellInfoSI-List-ECNO-LCR   OPTIONAL
}

InterFreqMeasurementSysInfo-HCS-RSCP-LCR-r4 ::= SEQUENCE {
    interFreqCellInfoSI-List     InterFreqCellInfoSI-List-HCS-RSCP-LCR   OPTIONAL
}

InterFreqMeasurementSysInfo-HCS-ECNO-LCR-r4 ::= SEQUENCE {
    interFreqCellInfoSI-List     InterFreqCellInfoSI-List-HCS-ECNO-LCR   OPTIONAL
}

InterFreqReportCriteria ::=       CHOICE {
    intraFreqReportingCriteria  IntraFreqReportingCriteria,
    interFreqReportingCriteria  InterFreqReportingCriteria,
    periodicalReportingCriteria PeriodicalWithReportingCellStatus,
    noReporting                 ReportingCellStatusOpt
}

InterFreqReportCriteria-r4 ::=     CHOICE {
    intraFreqReportingCriteria  IntraFreqReportingCriteria-r4,
    interFreqReportingCriteria  InterFreqReportingCriteria,
    periodicalReportingCriteria PeriodicalWithReportingCellStatus,
    noReporting                 ReportingCellStatusOpt
}

InterFreqReportingCriteria ::=     SEQUENCE {
    interFreqEventList           InterFreqEventList           OPTIONAL
}

InterFreqReportingQuantity ::=    SEQUENCE {

```

```

 ultra-Carrier-RSSI                                BOOLEAN,
 frequencyQualityEstimate                         BOOLEAN,
 nonFreqRelatedQuantities                        CellReportingQuantities
}

InterFrequencyMeasurement ::=      SEQUENCE {
    interFreqCellInfoList,
    interFreqMeasQuantity          OPTIONAL,
    interFreqReportingQuantity     OPTIONAL,
    measurementValidity           OPTIONAL,
    interFreqSetUpdate             OPTIONAL,
    reportCriteria                InterFreqReportCriteria
}

InterFrequencyMeasurement-r4 ::=      SEQUENCE {
    interFreqCellInfoList-r4,
    interFreqMeasQuantity          OPTIONAL,
    interFreqReportingQuantity     OPTIONAL,
    measurementValidity           OPTIONAL,
    interFreqSetUpdate             OPTIONAL,
    reportCriteria                InterFreqReportCriteria-r4
}

InterRAT-TargetCellDescription ::=   SEQUENCE {
    technologySpecificInfo        CHOICE {
        gsm                      SEQUENCE {
            bsic                   BSIC,
            frequency-band         Frequency-Band,
            bcch-ARFCN              BCCH-ARFCN,
            ncMode                  NC-Mode
                                         OPTIONAL
        },
        is-2000                  NULL,
        spare2                  NULL,
        spare1                  NULL
    }
}

InterRATCellID ::=                  INTEGER (0..maxCellMeas-1)

InterRATCellInfoIndicator ::=       INTEGER (0..3)

InterRATCellInfoList ::=          SEQUENCE {
    removedInterRATCellList      RemovedInterRATCellList,
    -- NOTE: Future revisions of dedicated messages including IE newInterRATCellList
    -- should use a corrected version of this IE
    newInterRATCellList          NewInterRATCellList,
    cellsForInterRATMeasList     CellsForInterRATMeasList
                                         OPTIONAL
}

InterRATCellInfoList-B ::=         SEQUENCE {
    removedInterRATCellList      RemovedInterRATCellList,
    -- NOTE: IE newInterRATCellList should be optional. However, system information
    -- does not support message versions. Hence, this can not be corrected
    newInterRATCellList          NewInterRATCellList-B
}

InterRATCellInfoList-r4 ::=        SEQUENCE {
    removedInterRATCellList      RemovedInterRATCellList,
    newInterRATCellList          NewInterRATCellList
                                         OPTIONAL,
    cellsForInterRATMeasList     CellsForInterRATMeasList
                                         OPTIONAL
}

InterRATCellIndividualOffset ::=    INTEGER (-50..50)

InterRATEvent ::=                  CHOICE {
    event3a                    Event3a,
    event3b                    Event3b,
    event3c                    Event3c,
    event3d                    Event3d
}

InterRATEventList ::=             SEQUENCE (SIZE (1..maxMeasEvent)) OF
                                    InterRATEvent

InterRATEventResults ::=          SEQUENCE {
    eventID                    EventIDInterRAT,
    cellToReportList            CellToReportList
}

```

```

InterRATInfo ::= ENUMERATED {
    gsm
}

InterRATInfo-r6 ::= SEQUENCE {
    rat,
    gsm-TargetCellInfoList
} OPTIONAL

InterRATMeasQuantity ::= CHOICE {
    measQuantityUTRAN-QualityEstimate OPTIONAL,
    ratSpecificInfo
    gsm
        measurementQuantity
        filterCoefficient
        bsic-VerificationRequired
    },
    is-2000
        tadd-EcIo
        tcomp-EcIo
        softSlope
        addIntercept
} OPTIONAL

InterRATMeasuredResults ::= CHOICE {
    gsm
    spare
} NULL

InterRATMeasuredResultsList ::= SEQUENCE (SIZE (1..maxOtherRAT-16)) OF
    InterRATMeasuredResults

InterRATMeasurement ::= SEQUENCE {
    interRATCellInfoList OPTIONAL,
    interRATMeasQuantity OPTIONAL,
    interRATReportingQuantity OPTIONAL,
    reportCriteria
}

InterRATMeasurement-r4 ::= SEQUENCE {
    interRATCellInfoList OPTIONAL,
    interRATMeasQuantity OPTIONAL,
    interRATReportingQuantity OPTIONAL,
    reportCriteria
}

InterRATMeasurementSysInfo ::= SEQUENCE {
    interRATCellInfoList
} InterRATCellInfoList OPTIONAL

InterRATMeasurementSysInfo-B ::= SEQUENCE {
    interRATCellInfoList
} InterRATCellInfoList-B OPTIONAL

InterRATReportCriteria ::= CHOICE {
    interRATReportingCriteria
    periodicalReportingCriteria
    noReporting
} InterRATReportingCriteria,
    PeriodicalWithReportingCellStatus,
    ReportingCellStatusOpt

InterRATReportingCriteria ::= SEQUENCE {
    interRATEventList
} InterRATEventList OPTIONAL

InterRATReportingQuantity ::= SEQUENCE {
    utran-EstimatedQuality
    ratSpecificInfo
    gsm
        dummy
        observedTimeDifferenceGSM
        gsm-Carrier-RSSI
} BOOLEAN,
    CHOICE {
        SEQUENCE {
            dummy
            observedTimeDifferenceGSM
            gsm-Carrier-RSSI
        }
    }
}

IntraFreqCellID ::= INTEGER (0..maxCellMeas-1)

```

```

IntraFreqCellInfoList ::=          SEQUENCE {
    removedIntraFreqCellList           RemovedIntraFreqCellList      OPTIONAL,
    newIntraFreqCellList              NewIntraFreqCellList        OPTIONAL,
    cellsForIntraFreqMeasList        CellsForIntraFreqMeasList   OPTIONAL
}

IntraFreqCellInfoList-r4 ::=        SEQUENCE {
    removedIntraFreqCellList           RemovedIntraFreqCellList      OPTIONAL,
    newIntraFreqCellList              NewIntraFreqCellList-r4       OPTIONAL,
    cellsForIntraFreqMeasList        CellsForIntraFreqMeasList   OPTIONAL
}

IntraFreqCellInfoSI-List-RSCP ::=   SEQUENCE {
    removedIntraFreqCellList           RemovedIntraFreqCellList      OPTIONAL,
    newIntraFreqCellList              NewIntraFreqCellsSI-List-RSCP
}

IntraFreqCellInfoSI-List-ECN0 ::=   SEQUENCE {
    removedIntraFreqCellList           RemovedIntraFreqCellList      OPTIONAL,
    newIntraFreqCellList              NewIntraFreqCellsSI-List-ECN0
}

IntraFreqCellInfoSI-List-HCS-RSCP ::= SEQUENCE {
    removedIntraFreqCellList           RemovedIntraFreqCellList      OPTIONAL,
    newIntraFreqCellList              NewIntraFreqCellsSI-List-HCS-RSCP
}

IntraFreqCellInfoSI-List-HCS-ECN0 ::= SEQUENCE {
    removedIntraFreqCellList           RemovedIntraFreqCellList      OPTIONAL,
    newIntraFreqCellList              NewIntraFreqCellsSI-List-HCS-ECN0
}

IntraFreqCellInfoSI-List-RSCP-LCR-r4 ::= SEQUENCE {
    removedIntraFreqCellList           RemovedIntraFreqCellList      OPTIONAL,
    newIntraFreqCellList              NewIntraFreqCellsSI-List-RSCP-LCR-r4
}

IntraFreqCellInfoSI-List-ECN0-LCR-r4 ::= SEQUENCE {
    removedIntraFreqCellList           RemovedIntraFreqCellList      OPTIONAL,
    newIntraFreqCellList              NewIntraFreqCellsSI-List-ECN0-LCR-r4
}

IntraFreqCellInfoSI-List-HCS-RSCP-LCR-r4 ::= SEQUENCE {
    removedIntraFreqCellList           RemovedIntraFreqCellList      OPTIONAL,
    newIntraFreqCellList              NewIntraFreqCellsSI-List-HCS-RSCP-LCR-r4
}

IntraFreqCellInfoSI-List-HCS-ECN0-LCR-r4 ::= SEQUENCE {
    removedIntraFreqCellList           RemovedIntraFreqCellList      OPTIONAL,
    newIntraFreqCellList              NewIntraFreqCellsSI-List-HCS-ECN0-LCR-r4
}

IntraFreqEvent ::=                 CHOICE {
    ela                           Event1a,
    elb                           Event1b,
    elc                           Event1c,
    eld                           NULL,
    ele                           Event1e,
    elf                           Event1f,
    elg                           NULL,
    elh                           ThresholdUsedFrequency,
    eli                           ThresholdUsedFrequency
}

IntraFreqEvent-r4 ::=              CHOICE {
    ela                           Event1a-r4,
    elb                           Event1b-r4,
    elc                           Event1c,
    eld                           NULL,
    ele                           Event1e,
    elf                           Event1f,
    elg                           NULL,
    elh                           ThresholdUsedFrequency,
    eli                           ThresholdUsedFrequency
}

IntraFreqEvent-LCR-r4 ::=         CHOICE {

```

```

ela                                Event1a-LCR-r4,
elb                                Event1b-LCR-r4,
elc                                Event1c,
eld                                NULL,
ele                                Event1e,
elf                                Event1f,
elg                                NULL,
elh                                ThresholdUsedFrequency,
eli                                ThresholdUsedFrequency
}

IntraFreqEvent-1d-r5 ::=          SEQUENCE {
    triggeringCondition           TriggeringCondition2      OPTIONAL,
    useCIO                         BOOLEAN                  OPTIONAL
}

IntraFreqEventCriteria ::=         SEQUENCE {
    event                           IntraFreqEvent,
    hysteresis                     Hysteresis,
    timeToTrigger                   TimeToTrigger,
    reportingCellStatus            ReportingCellStatus      OPTIONAL
}

IntraFreqEventCriteria-r4 ::=       SEQUENCE {
    event                           IntraFreqEvent-r4,
    hysteresis                     Hysteresis,
    timeToTrigger                   TimeToTrigger,
    reportingCellStatus            ReportingCellStatus      OPTIONAL
}

IntraFreqEventCriteria-LCR-r4 ::=  SEQUENCE {
    event                           IntraFreqEvent-LCR-r4,
    hysteresis                     Hysteresis,
    timeToTrigger                   TimeToTrigger,
    reportingCellStatus            ReportingCellStatus      OPTIONAL
}

IntraFreqEventCriteriaList ::=     SEQUENCE (SIZE (1..maxMeasEvent)) OF
                                    IntraFreqEventCriteria

IntraFreqEventCriteriaList-r4 ::=   SEQUENCE (SIZE (1..maxMeasEvent)) OF
                                    IntraFreqEventCriteria-r4

IntraFreqEventCriteriaList-LCR-r4 ::= SEQUENCE (SIZE (1..maxMeasEvent)) OF
                                      IntraFreqEventCriteria-LCR-r4

IntraFreqEventResults ::=          SEQUENCE {
    eventID                        EventIDIntraFreq,
    cellMeasurementEventResults    CellMeasurementEventResults
}

IntraFreqMeasQuantity ::=          SEQUENCE {
    filterCoefficient               FilterCoefficient          DEFAULT fc0,
    modeSpecificInfo                CHOICE {
        fdd                            SEQUENCE {
            intraFreqMeasQuantity-FDD  IntraFreqMeasQuantity-FDD
        },
        tdd                            SEQUENCE {
            intraFreqMeasQuantity-TDDList  IntraFreqMeasQuantity-TDDList
        }
    }
}

-- If IntraFreqMeasQuantity-FDD is used in InterRATMeasQuantity, then only
-- cpich-Ec-N0 and cpich-RSCP are allowed.
-- dummy is not used in this version of the specification, it should
-- not be sent and if received it should be ignored.
IntraFreqMeasQuantity-FDD ::=      ENUMERATED {
    cpich-Ec-N0,
    cpich-RSCP,
    pathloss,
    dummy }

-- dummy is not used in this version of the specification, it should
-- not be sent and if received it should be ignored.
IntraFreqMeasQuantity-TDD ::=     ENUMERATED {
    primaryCCPCH-RSCP,
    pathloss,
}

```

```

timeslotISCP,
dummy }

IntraFreqMeasQuantity-TDDList ::= SEQUENCE (SIZE (1..4)) OF
IntraFreqMeasQuantity-TDD

IntraFreqMeasuredResultsList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
CellMeasuredResults

IntraFreqMeasurementSysInfo-RSCP ::= SEQUENCE {
intraFreqMeasurementID MeasurementIdentity DEFAULT 1,
intraFreqCellInfoSI-List IntraFreqCellInfoSI-List-RSCP OPTIONAL,
intraFreqMeasQuantity IntraFreqMeasQuantity OPTIONAL,
intraFreqReportingQuantityForRACH IntraFreqReportingQuantityForRACH OPTIONAL,
maxReportedCellsOnRACH MaxReportedCellsOnRACH OPTIONAL,
reportingInfoForCellDCH ReportingInfoForCellDCH OPTIONAL
}

IntraFreqMeasurementSysInfo-ECNO ::= SEQUENCE {
intraFreqMeasurementID MeasurementIdentity DEFAULT 1,
intraFreqCellInfoSI-List IntraFreqCellInfoSI-List-ECNO OPTIONAL,
intraFreqMeasQuantity IntraFreqMeasQuantity OPTIONAL,
intraFreqReportingQuantityForRACH IntraFreqReportingQuantityForRACH OPTIONAL,
maxReportedCellsOnRACH MaxReportedCellsOnRACH OPTIONAL,
reportingInfoForCellDCH ReportingInfoForCellDCH OPTIONAL
}

IntraFreqMeasurementSysInfo-HCS-RSCP ::= SEQUENCE {
intraFreqMeasurementID MeasurementIdentity DEFAULT 1,
intraFreqCellInfoSI-List IntraFreqCellInfoSI-List-HCS-RSCP OPTIONAL,
intraFreqMeasQuantity IntraFreqMeasQuantity OPTIONAL,
intraFreqReportingQuantityForRACH IntraFreqReportingQuantityForRACH OPTIONAL,
maxReportedCellsOnRACH MaxReportedCellsOnRACH OPTIONAL,
reportingInfoForCellDCH ReportingInfoForCellDCH OPTIONAL
}

IntraFreqMeasurementSysInfo-HCS-ECNO ::= SEQUENCE {
intraFreqMeasurementID MeasurementIdentity DEFAULT 1,
intraFreqCellInfoSI-List IntraFreqCellInfoSI-List-HCS-ECNO OPTIONAL,
intraFreqMeasQuantity IntraFreqMeasQuantity OPTIONAL,
intraFreqReportingQuantityForRACH IntraFreqReportingQuantityForRACH OPTIONAL,
maxReportedCellsOnRACH MaxReportedCellsOnRACH OPTIONAL,
reportingInfoForCellDCH ReportingInfoForCellDCH OPTIONAL
}

IntraFreqMeasurementSysInfo-RSCP-LCR-r4 ::= SEQUENCE {
intraFreqMeasurementID MeasurementIdentity DEFAULT 1,
intraFreqCellInfoSI-List IntraFreqCellInfoSI-List-RSCP-LCR-r4 OPTIONAL,
intraFreqMeasQuantity IntraFreqMeasQuantity OPTIONAL,
intraFreqReportingQuantityForRACH IntraFreqReportingQuantityForRACH OPTIONAL,
maxReportedCellsOnRACH MaxReportedCellsOnRACH OPTIONAL,
reportingInfoForCellDCH ReportingInfoForCellDCH-LCR-r4 OPTIONAL
}

IntraFreqMeasurementSysInfo-ECNO-LCR-r4 ::= SEQUENCE {
intraFreqMeasurementID MeasurementIdentity DEFAULT 1,
intraFreqCellInfoSI-List IntraFreqCellInfoSI-List-ECNO-LCR-r4 OPTIONAL,
intraFreqMeasQuantity IntraFreqMeasQuantity OPTIONAL,
intraFreqReportingQuantityForRACH IntraFreqReportingQuantityForRACH OPTIONAL,
maxReportedCellsOnRACH MaxReportedCellsOnRACH OPTIONAL,
reportingInfoForCellDCH ReportingInfoForCellDCH-LCR-r4 OPTIONAL
}

IntraFreqMeasurementSysInfo-HCS-RSCP-LCR-r4 ::= SEQUENCE {
intraFreqMeasurementID MeasurementIdentity DEFAULT 1,
intraFreqCellInfoSI-List IntraFreqCellInfoSI-List-HCS-RSCP-LCR-r4 OPTIONAL,
intraFreqMeasQuantity IntraFreqMeasQuantity OPTIONAL,
intraFreqReportingQuantityForRACH IntraFreqReportingQuantityForRACH OPTIONAL,
maxReportedCellsOnRACH MaxReportedCellsOnRACH OPTIONAL,
reportingInfoForCellDCH ReportingInfoForCellDCH-LCR-r4 OPTIONAL
}

IntraFreqMeasurementSysInfo-HCS-ECNO-LCR-r4 ::= SEQUENCE {
intraFreqMeasurementID MeasurementIdentity DEFAULT 1,
intraFreqCellInfoSI-List IntraFreqCellInfoSI-List-HCS-ECNO-LCR-r4 OPTIONAL,
intraFreqMeasQuantity IntraFreqMeasQuantity OPTIONAL,
intraFreqReportingQuantityForRACH IntraFreqReportingQuantityForRACH OPTIONAL,
maxReportedCellsOnRACH MaxReportedCellsOnRACH OPTIONAL,
reportingInfoForCellDCH ReportingInfoForCellDCH-LCR-r4 OPTIONAL
}

```

```

reportingInfoForCellDCH           ReportingInfoForCellDCH-LCR-r4      OPTIONAL
}

IntraFreqReportCriteria ::= CHOICE {
    intraFreqReportingCriteria,
    periodicalReportingCriteria,
    noReporting
}

IntraFreqReportCriteria-r4 ::= CHOICE {
    intraFreqReportingCriteria,
    periodicalReportingCriteria,
    noReporting
}

IntraFreqReportingCriteria ::= SEQUENCE {
    eventCriteriaList
}
IntraFreqReportingCriteria-r4 ::= SEQUENCE {
    eventCriteriaList
}

IntraFreqReportingCriteria-LCR-r4 ::= SEQUENCE {
    eventCriteriaList
}

IntraFreqReportingQuantity ::= SEQUENCE {
    activeSetReportingQuantities   CellReportingQuantities,
    monitoredSetReportingQuantities CellReportingQuantities,
    detectedSetReportingQuantities CellReportingQuantities
}
IntraFreqReportingQuantityForRACH ::= SEQUENCE {
    sfn-SFN-OTD-Type             SFN-SFN-OTD-Type,
    modeSpecificInfo              CHOICE {
        fdd                      SEQUENCE {
            intraFreqRepQuantityRACH-FDD   IntraFreqRepQuantityRACH-FDD
        },
        tdd                      SEQUENCE {
            intraFreqRepQuantityRACH-TDDList IntraFreqRepQuantityRACH-TDDList
        }
    }
}
IntraFreqRepQuantityRACH-FDD ::= ENUMERATED {
    cpich-EcNo, cpich-RSCP,
    pathloss, noReport
}
IntraFreqRepQuantityRACH-TDD ::= ENUMERATED {
    timeslotISCP,
    primaryCCPCH-RSCP,
    noReport
}
IntraFreqRepQuantityRACH-TDDList ::= SEQUENCE (SIZE (1..2)) OF
    IntraFreqRepQuantityRACH-TDD

IntraFrequencyMeasurement ::= SEQUENCE {
    intraFreqCellInfoList          IntraFreqCellInfoList      OPTIONAL,
    intraFreqMeasQuantity          IntraFreqMeasQuantity    OPTIONAL,
    intraFreqReportingQuantity     IntraFreqReportingQuantity OPTIONAL,
    measurementValidity           MeasurementValidity      OPTIONAL,
    reportCriteria                 IntraFreqReportCriteria  OPTIONAL
}

IntraFrequencyMeasurement-r4 ::= SEQUENCE {
    intraFreqCellInfoList          IntraFreqCellInfoList-r4  OPTIONAL,
    intraFreqMeasQuantity          IntraFreqMeasQuantity    OPTIONAL,
    intraFreqReportingQuantity     IntraFreqReportingQuantity OPTIONAL,
    measurementValidity           MeasurementValidity      OPTIONAL,
    reportCriteria                 IntraFreqReportCriteria-r4 OPTIONAL
}

IODE ::= INTEGER (0..255)

IP-Length ::= ENUMERATED {
    ip15, ip10
}

```

```

IP-PCCPCH-r4 ::= BOOLEAN

IP-Spacing ::= ENUMERATED {
    e5, e7, e10, e15, e20,
    e30, e40, e50 }

IP-Spacing-TDD ::= ENUMERATED {
    e30, e40, e50, e70, e100}

IS-2000SpecificMeasInfo ::= ENUMERATED {
    frequency, timeslot, colourcode,
    outputpower, pn-Offset }

MaxNumberOfReportingCellsType1 ::= ENUMERATED {
    e1, e2, e3, e4, e5, e6}

MaxNumberOfReportingCellsType2 ::= ENUMERATED {
    e1, e2, e3, e4, e5, e6, e7, e8, e9, e10, e11, e12}

MaxNumberOfReportingCellsType3 ::= ENUMERATED {
    viactCellsPlus1,
    viactCellsPlus2,
    viactCellsPlus3,
    viactCellsPlus4,
    viactCellsPlus5,
    viactCellsPlus6 }

MaxReportedCellsOnRACH ::= ENUMERATED {
    noReport,
    currentCell,
    currentAnd-1-BestNeighbour,
    currentAnd-2-BestNeighbour,
    currentAnd-3-BestNeighbour,
    currentAnd-4-BestNeighbour,
    currentAnd-5-BestNeighbour,
    currentAnd-6-BestNeighbour }

MeasuredResults ::= CHOICE {
    intraFreqMeasuredResultsList,
    interFreqMeasuredResultsList,
    interRATMeasuredResultsList,
    trafficVolumeMeasuredResultsList,
    qualityMeasuredResults,
    ue-InternalMeasuredResults,
    ue-positioning-MeasuredResults,
    spare
}

MeasuredResults-v390ext ::= SEQUENCE {
    ue-positioning-MeasuredResults-v390ext
}                               UE-Positioning-MeasuredResults-v390ext

MeasuredResults-v590ext ::= CHOICE {
    intraFrequencyMeasuredResultsList,
    interFrequencyMeasuredResultsList
}                               IntraFrequencyMeasuredResultsList-v590ext,
                                InterFrequencyMeasuredResultsList-v590ext

MeasuredResults-LCR-r4 ::= CHOICE {
    intraFreqMeasuredResultsList,
    interFreqMeasuredResultsList,
    interRATMeasuredResultsList,
    trafficVolumeMeasuredResultsList,
    qualityMeasuredResults,
    ue-InternalMeasuredResults,
    ue-positioning-MeasuredResults,
    spare
}

MeasuredResultsList ::= SEQUENCE (SIZE (1..maxAdditionalMeas)) OF
                           MeasuredResults

MeasuredResultsList-LCR-r4-ext ::= SEQUENCE (SIZE (1..maxAdditionalMeas)) OF
                                   MeasuredResults-LCR-r4

MeasuredResultsOnRACH ::= SEQUENCE {
    currentCell
    modeSpecificInfo
        CHOICE {
}

```

```

    fdd
      measurementQuantity
        cpich-Ec-N0
        cpich-RSCP
        pathloss
        spare
      }
    },
    tdd
      timeslotISCP
      primaryCCPCH-RSCP
    }
  },
  monitoredCells
}
}

MeasurementCommand ::= CHOICE {
  setup
  modify
    measurementType
  },
  release
}
}

MeasurementCommand-r4 ::= CHOICE {
  setup
  modify
    measurementType
  },
  release
}
}

MeasurementControlSysInfo ::= SEQUENCE {
  -- CHOICE cellSelectQualityMeasure represents PCCPCH-RSCP in TDD mode.
  use-of-HCS
    CHOICE {
      hcs-not-used
        cellSelectQualityMeasure
          CHOICE {
            cpich-RSCP
              intraFreqMeasurementSysInfo
            OPTIONAL,
              interFreqMeasurementSysInfo
            },
            cpich-Ec-N0
              intraFreqMeasurementSysInfo
            OPTIONAL,
              interFreqMeasurementSysInfo
            },
            interRATMeasurementSysInfo
              InterRATMeasurementSysInfo-B
            OPTIONAL,
            hcs-used
              cellSelectQualityMeasure
                CHOICE {
                  cpich-RSCP
                    intraFreqMeasurementSysInfo
                  OPTIONAL,
                    interFreqMeasurementSysInfo
                  OPTIONAL,
                  cpich-Ec-N0
                    intraFreqMeasurementSysInfo
                  OPTIONAL,
                    interFreqMeasurementSysInfo
                  OPTIONAL,
                  interRATMeasurementSysInfo
                    InterRATMeasurementSysInfo
                  OPTIONAL
                }
            },
            trafficVolumeMeasSysInfo
              TrafficVolumeMeasSysInfo
            OPTIONAL,
  -- dummy is not used in this version of specification and it shall be ignored by the UE.
  dummy
    UE-InternalMeasurementSysInfo
  OPTIONAL
}

MeasurementControlSysInfo-LCR-r4-ext ::= SEQUENCE {
  -- CHOICE use-of-HCS shall have the same value as the use-of-HCS
  -- in MeasurementControlSysInfo
  -- CHOICE cellSelectQualityMeasure represents PCCPCH-RSCP in TDD mode.
}

```

```

use-of-HCS                               CHOICE {
  hcs-not-used                         SEQUENCE {
    -- CHOICE cellSelectQualityMeasure shall have the same value as the
    -- cellSelectQualityMeasure in MeasurementControlSysInfo
    cellSelectQualityMeasure      CHOICE {
      cpich-RSCP                  SEQUENCE {
        intraFreqMeasurementSysInfo IntraFreqMeasurementSysInfo-RSCP-LCR-r4 OPTIONAL,
        interFreqMeasurementSysInfo InterFreqMeasurementSysInfo-RSCP-LCR-r4 OPTIONAL
      },
      cpich-Ec-N0                 SEQUENCE {
        intraFreqMeasurementSysInfo IntraFreqMeasurementSysInfo-ECN0-LCR-r4 OPTIONAL,
        interFreqMeasurementSysInfo InterFreqMeasurementSysInfo-ECN0-LCR-r4 OPTIONAL
      }
    }
  },
  hcs-used                                SEQUENCE {
    -- CHOICE cellSelectQualityMeasure shall have the same value as the
    -- cellSelectQualityMeasure in MeasurementControlSysInfo
    cellSelectQualityMeasure      CHOICE {
      cpich-RSCP                  SEQUENCE {
        intraFreqMeasurementSysInfo IntraFreqMeasurementSysInfo-HCS-RSCP-LCR-r4
OPTIONAL,
        interFreqMeasurementSysInfo InterFreqMeasurementSysInfo-HCS-RSCP-LCR-r4 OPTIONAL
      },
      cpich-Ec-N0                 SEQUENCE {
        intraFreqMeasurementSysInfo IntraFreqMeasurementSysInfo-HCS-ECN0-LCR-r4
OPTIONAL,
        interFreqMeasurementSysInfo InterFreqMeasurementSysInfo-HCS-ECN0-LCR-r4 OPTIONAL
      }
    }
  }
}

MeasurementIdentity ::=      INTEGER (1..16)

MeasurementQuantityGSM ::=      ENUMERATED {
  gsm-CarrierRSSI,
  dummy
}

MeasurementReportingMode ::=      SEQUENCE {
  measurementReportTransferMode,
  periodicalOrEventTrigger
}

MeasurementType ::=      CHOICE {
  intraFrequencyMeasurement,
  interFrequencyMeasurement,
  interRATMeasurement,
  ue-positioning-Measurement,
  trafficVolumeMeasurement,
  qualityMeasurement,
  ue-InternalMeasurement
}

MeasurementType-r4 ::=      CHOICE {
  intraFrequencyMeasurement,
  interFrequencyMeasurement,
  interRATMeasurement,
  up-Measurement,
  trafficVolumeMeasurement,
  qualityMeasurement,
  ue-InternalMeasurement
}

MeasurementValidity ::=      SEQUENCE {
  ue-State
    ENUMERATED {
      cell-DCH, all-But-Cell-DCH, all-States
    }
}

MonitoredCellRACH-List ::=      SEQUENCE (SIZE (1..8)) OF
  MonitoredCellRACH-Result

MonitoredCellRACH-Result ::=      SEQUENCE {
  sfn-SFN-ObsTimeDifference
  modeSpecificInfo
  fdd
    primaryCPICH-Info
}

```

```

measurementQuantity CHOICE {
    cpich-Ec-N0,
    cpich-RSCP,
    pathloss,
    spare
}
},
tdd CHOICE {
    cellParametersID,
    primaryCCPCH-RSCP
}
}

MultipathIndicator ::= ENUMERATED {
    nm,
    low,
    medium,
    high }

N-CR-T-CRMaxHyst ::= SEQUENCE {
    n-CR,
    t-CRMaxHyst
} DEFAULT 8,

NavigationModelSatInfo ::= SEQUENCE {
    satID,
    satelliteStatus,
    ephemerisParameter OPTIONAL
}

NavigationModelSatInfoList ::= SEQUENCE (SIZE (1..maxSat)) OF
    NavigationModelSatInfo

EphemerisParameter ::= SEQUENCE {
    codeOnL2,
    uraIndex,
    satHealth,
    iodc,
    l2Pflag,
    sf1Revd,
    t-GD,
    t-oc,
    af2,
    af1,
    af0,
    c-rs,
    delta-n,
    m0,
    c-uc,
    e,
    c-us,
    a-Sqrt,
    t-oe,
    fitInterval,
    aodo,
    c-ic,
    omega0,
    c-is,
    i0,
    c-rc,
    omega,
    omegaDot,
    iDot
}
}

NC-Mode ::= BIT STRING (SIZE (3))

Neighbour ::= SEQUENCE {
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            neighbourIdentity PrimaryCPICH-Info OPTIONAL,
            uE-RX-TX-TimeDifferenceType2Info UE-RX-TX-TimeDifferenceType2Info OPTIONAL
        },
        tdd SEQUENCE {
            neighbourAndChannelIdentity CellAndChannelIdentity OPTIONAL
        }
    },
    neighbourQuality NeighbourQuality,
}

```

```

sfn-SFN-ObsTimeDifference2           SFN-SFN-ObsTimeDifference2}

Neighbour-v390ext ::=          SEQUENCE {
    modeSpecificInfo
    fdd
    frequencyInfo
},
    tdd
    NULL
}

NeighbourList ::=             SEQUENCE (SIZE (1..maxCellMeas)) OF
                                Neighbour

-- The order of the cells in IE NeighbourList-v390ext shall be the
-- same as the order in IE NeighbourList
NeighbourList-v390ext ::=        SEQUENCE (SIZE (1..maxCellMeas)) OF
                                Neighbour-v390ext

NeighbourQuality ::=           SEQUENCE {
    ue-Positioning-OTDOA-Quality
}

NewInterFreqCell ::=           SEQUENCE {
    interFreqCellID
    frequencyInfo
    cellInfo
}
                                OPTIONAL,
                                OPTIONAL,
                                CellInfo

NewInterFreqCell-r4 ::=         SEQUENCE {
    interFreqCellID
    frequencyInfo
    cellInfo
}
                                OPTIONAL,
                                OPTIONAL,
                                CellInfo-r4

NewInterFreqCellList ::=        SEQUENCE (SIZE (1..maxCellMeas)) OF
                                NewInterFreqCell

NewInterFreqCellList-r4 ::=      SEQUENCE (SIZE (1..maxCellMeas)) OF
                                NewInterFreqCell-r4

NewInterFreqCellSI-RSCP ::=     SEQUENCE {
    interFreqCellID
    frequencyInfo
    cellInfo
}
                                OPTIONAL,
                                OPTIONAL,
                                CellInfoSI-RSCP

NewInterFreqCellSI-ECN0 ::=     SEQUENCE {
    interFreqCellID
    frequencyInfo
    cellInfo
}
                                OPTIONAL,
                                OPTIONAL,
                                CellInfoSI-ECN0

NewInterFreqCellSI-HCS-RSCP ::= SEQUENCE {
    interFreqCellID
    frequencyInfo
    cellInfo
}
                                OPTIONAL,
                                OPTIONAL,
                                CellInfoSI-HCS-RSCP

NewInterFreqCellSI-HCS-ECN0 ::= SEQUENCE {
    interFreqCellID
    frequencyInfo
    cellInfo
}
                                OPTIONAL,
                                OPTIONAL,
                                CellInfoSI-HCS-ECN0

NewInterFreqCellSI-RSCP-LCR-r4 ::= SEQUENCE {
    interFreqCellID
    frequencyInfo
    cellInfo
}
                                OPTIONAL,
                                OPTIONAL,
                                CellInfoSI-RSCP-LCR-r4

NewInterFreqCellSI-ECN0-LCR-r4 ::= SEQUENCE {
    interFreqCellID
    frequencyInfo
    cellInfo
}
                                OPTIONAL,
                                OPTIONAL,
                                CellInfoSI-ECN0-LCR-r4

NewInterFreqCellSI-HCS-RSCP-LCR-r4 ::= SEQUENCE {
}

```

```

interFreqCellID           InterFreqCellID           OPTIONAL,
frequencyInfo             FrequencyInfo            OPTIONAL,
cellInfo                  CellInfoSI-HCS-RSCP-LCR-r4

}

NewInterFreqCellsSI-HCS-ECN0-LCR-r4 ::=   SEQUENCE {
    interFreqCellID           InterFreqCellID           OPTIONAL,
    frequencyInfo             FrequencyInfo            OPTIONAL,
    cellInfo                  CellInfoSI-HCS-ECN0-LCR-r4
}

NewInterFreqCellsSI-List-ECN0 ::=          SEQUENCE (SIZE (1..maxCellMeas)) OF
                                         NewInterFreqCellsSI-ECN0

NewInterFreqCellsSI-List-HCS-RSCP ::=       SEQUENCE (SIZE (1..maxCellMeas)) OF
                                         NewInterFreqCellsSI-HCS-RSCP

NewInterFreqCellsSI-List-HCS-ECN0 ::=       SEQUENCE (SIZE (1..maxCellMeas)) OF
                                         NewInterFreqCellsSI-HCS-ECN0

NewInterFreqCellsSI-List-RSCP ::=          SEQUENCE (SIZE (1..maxCellMeas)) OF
                                         NewInterFreqCellsSI-RSCP

NewInterFreqCellsSI-List-ECN0-LCR-r4 ::=  SEQUENCE (SIZE (1..maxCellMeas)) OF
                                         NewInterFreqCellsSI-ECN0-LCR-r4

NewInterFreqCellsSI-List-HCS-RSCP-LCR-r4 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
                                         NewInterFreqCellsSI-HCS-RSCP-LCR-r4

NewInterFreqCellsSI-List-HCS-ECN0-LCR-r4 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
                                         NewInterFreqCellsSI-HCS-ECN0-LCR-r4

NewInterFreqCellsSI-List-RSCP-LCR-r4 ::=  SEQUENCE (SIZE (1..maxCellMeas)) OF
                                         NewInterFreqCellsSI-RSCP-LCR-r4

NewInterRATCell ::=           SEQUENCE {
    interRATCellID           InterRATCellID           OPTIONAL,
    technologySpecificInfo   CHOICE {
        gsm                  SEQUENCE {
            cellSelectionReselectionInfo   CellSelectReselectInfoSIB-11-12   OPTIONAL,
            interRATCellIndividualOffset   InterRATCellIndividualOffset,
            bsic                   BSIC,
            frequency-band           Frequency-Band,
            bcch-ARFCN              BCCH-ARFCN,
            -- dummy is not used in this version of the specification, it should
            -- not be sent and if received it should be ignored.
            dummy                  NULL                                     OPTIONAL
        },
        is-2000                SEQUENCE {
            is-2000SpecificMeasInfo     IS-2000SpecificMeasInfo
        },
        -- ASN.1 inconsistency: NewInterRATCellList should be optional within
        -- InterRATCellInfoList. The UE shall consider IE NewInterRATCell with
        -- technologySpecificInfo set to "absent" as valid and handle the
        -- message as if the IE NewInterRATCell was absent
        absent                 NULL,
        spare1                NULL
    }
}

NewInterRATCell-B ::=          SEQUENCE {
    interRATCellID           InterRATCellID           OPTIONAL,
    technologySpecificInfo   CHOICE {
        gsm                  SEQUENCE {
            cellSelectionReselectionInfo   CellSelectReselectInfoSIB-11-12   OPTIONAL,
            interRATCellIndividualOffset   InterRATCellIndividualOffset,
            bsic                   BSIC,
            frequency-band           Frequency-Band,
            bcch-ARFCN              BCCH-ARFCN,
            -- dummy is not used in this version of the specification, it should
            -- not be sent and if received it should be ignored.
            dummy                  NULL                                     OPTIONAL
        },
        is-2000                SEQUENCE {
            is-2000SpecificMeasInfo     IS-2000SpecificMeasInfo
        },
        -- ASN.1 inconsistency: NewInterRATCellList-B should be optional within
        -- InterRATCellInfoList-B. The UE shall consider IE NewInterRATCell-B with

```

```

-- technologySpecificInfo set to "absent" as valid and handle the
-- message as if the IE NewInterRATCell-B was absent
absent
    NULL,
spare1
    NULL
}

NewInterRATCellList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewInterRATCell

NewInterRATCellList-B ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewInterRATCell-B

NewIntraFreqCell ::= SEQUENCE {
    intraFreqCellID
    cellInfo
} OPTIONAL,

NewIntraFreqCell-r4 ::= SEQUENCE {
    intraFreqCellID
    cellInfo
} OPTIONAL,

NewIntraFreqCellList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewIntraFreqCell

NewIntraFreqCellList-r4 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewIntraFreqCell-r4

NewIntraFreqCellsSI-RSCP ::= SEQUENCE {
    intraFreqCellID
    cellInfo
} OPTIONAL,

NewIntraFreqCellsSI-ECN0 ::= SEQUENCE {
    intraFreqCellID
    cellInfo
} OPTIONAL,

NewIntraFreqCellsSI-HCS-RSCP ::= SEQUENCE {
    intraFreqCellID
    cellInfo
} OPTIONAL,

NewIntraFreqCellsSI-HCS-ECN0 ::= SEQUENCE {
    intraFreqCellID
    cellInfo
} OPTIONAL,

NewIntraFreqCellsSI-RSCP-LCR-r4 ::= SEQUENCE {
    intraFreqCellID
    cellInfo
} OPTIONAL,

NewIntraFreqCellsSI-ECN0-LCR-r4 ::= SEQUENCE {
    intraFreqCellID
    cellInfo
} OPTIONAL,

NewIntraFreqCellsSI-HCS-RSCP-LCR-r4 ::= SEQUENCE {
    intraFreqCellID
    cellInfo
} OPTIONAL,

NewIntraFreqCellsSI-HCS-ECN0-LCR-r4 ::= SEQUENCE {
    intraFreqCellID
    cellInfo
} OPTIONAL,

NewIntraFreqCellsSI-List-RSCP ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewIntraFreqCellsSI-RSCP

NewIntraFreqCellsSI-List-ECN0 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewIntraFreqCellsSI-ECN0

NewIntraFreqCellsSI-List-HCS-RSCP ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewIntraFreqCellsSI-HCS-RSCP

NewIntraFreqCellsSI-List-HCS-ECN0 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewIntraFreqCellsSI-HCS-ECN0

```

```

NewIntraFreqCellsSI-List-RSCP-LCR-r4 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
                                         NewIntraFreqCellsSI-RSCP-LCR-r4

NewIntraFreqCellsSI-List-ECN0-LCR-r4 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
                                         NewIntraFreqCellsSI-ECN0-LCR-r4

NewIntraFreqCellsSI-List-HCS-RSCP-LCR-r4 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
                                         NewIntraFreqCellsSI-HCS-RSCP-LCR-r4

NewIntraFreqCellsSI-List-HCS-ECN0-LCR-r4 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
                                         NewIntraFreqCellsSI-HCS-ECN0-LCR-r4

-- IE "nonUsedFreqThreshold" is not needed in case of event 2a
-- In case of event 2a UTRAN should include value 0 within IE "nonUsedFreqThreshold"
-- In case of event 2a, the UE shall ignore IE "nonUsedFreqThreshold"
-- In later versions of the message including this IE, a special version of
-- IE "NonUsedFreqParameterList" may be defined for event 2a, namely a
-- version not including IE "nonUsedFreqThreshold"
NonUsedFreqParameter ::= SEQUENCE {
    nonUsedFreqThreshold,
    Threshold,
    W
}

NonUsedFreqParameterList ::= SEQUENCE (SIZE (1..maxFreq)) OF
                           NonUsedFreqParameter

ObservedTimeDifferenceToGSM ::= INTEGER (0..4095)

OTDOA-SearchWindowSize ::= ENUMERATED {
    c20, c40, c80, c160, c320,
    c640, c1280, moreThan1280 }

-- SPARE: Pathloss, Max = 158
-- Values above Max are spare
Pathloss ::= INTEGER (46..173)

PenaltyTime-RSCP ::= CHOICE {
    notUsed,
    pt10,
    pt20,
    pt30,
    pt40,
    pt50,
    pt60
}

PenaltyTime-ECN0 ::= CHOICE {
    notUsed,
    pt10,
    pt20,
    pt30,
    pt40,
    pt50,
    pt60
}

PendingTimeAfterTrigger ::= ENUMERATED {
    ptat0-25, ptat0-5, ptat1,
    ptat2, ptat4, ptat8, ptat16 }

PeriodicalOrEventTrigger ::= ENUMERATED {
    periodical,
    eventTrigger }

PeriodicalReportingCriteria ::= SEQUENCE {
    reportingAmount,
    reportingInterval }
                                         ReportingAmount                               DEFAULT ra-Infinity,
                                         ReportingIntervalLong

PeriodicalWithReportingCellStatus ::= SEQUENCE {
    periodicalReportingCriteria,
    reportingCellStatus }
                                         PeriodicalReportingCriteria,
                                         ReportingCellStatus                         OPTIONAL

PLMNIdentitiesOfNeighbourCells ::= SEQUENCE {
    plmnsOfIntraFreqCellsList,
    plmnsOfInterFreqCellsList }
                                         PLMNsOfIntraFreqCellsList,
                                         PLMNsOfInterFreqCellsList                   OPTIONAL,
                                         OPTIONAL

```

```

    plmnsOfInterRATCellsList          PLMNsOfInterRATCellsList      OPTIONAL
}

PLMNsOfInterFreqCellsList ::=           SEQUENCE (SIZE (1..maxCellMeas)) OF
                                         SEQUENCE {
                                         plmn-Identity          PLMN-Identity        OPTIONAL
                                         }

PLMNsOfIntraFreqCellsList ::=          SEQUENCE (SIZE (1..maxCellMeas)) OF
                                         SEQUENCE {
                                         plmn-Identity          PLMN-Identity        OPTIONAL
                                         }

PLMNsOfInterRATCellsList ::=          SEQUENCE (SIZE (1..maxCellMeas)) OF
                                         SEQUENCE {
                                         plmn-Identity          PLMN-Identity        OPTIONAL
                                         }

PositionEstimate ::=                  CHOICE {
                                         ellipsoidPoint          EllipsoidPoint,
                                         ellipsoidPointUncertCircle EllipsoidPointUncertCircle,
                                         ellipsoidPointUncertEllipse EllipsoidPointUncertEllipse,
                                         ellipsoidPointAltitude   EllipsoidPointAltitude,
                                         ellipsoidPointAltitudeEllipse EllipsoidPointAltitudeEllipsoide
                                         }

PositioningMethod ::=                ENUMERATED {
                                         otdoa,
                                         gps,
                                         otdoaOrGPS, cellID }

-- Actual value PRC = IE value * 0.32
PRC ::=                                INTEGER (-2047..2047)

-- SPARE: PrimaryCCPCH-RSCP, Max = 91
-- Values above Max are spare
PrimaryCCPCH-RSCP ::=                 INTEGER (0..127)

Q-HCS ::=                               INTEGER (0..99)

Q-OffsetS-N ::=                         INTEGER (-50..50)

Q-QualMin ::=                           INTEGER (-24..0)

-- Actual value Q-RxlevMin = (IE value * 2) + 1
Q-RxlevMin ::=                          INTEGER (-58..-13)

QualityEventResults ::=                SEQUENCE (SIZE (1..maxTrCH)) OF
                                         TransportChannelIdentity

QualityMeasuredResults ::=             SEQUENCE {
                                         blerMeasurementResultsList      OPTIONAL,
                                         modeSpecificInfo
                                         CHOICE {
                                         fdd
                                         tdd
                                         sir-MeasurementResults       SIR-MeasurementList      OPTIONAL
                                         }
                                         }

QualityMeasurement ::=                SEQUENCE {
                                         qualityReportingQuantity      OPTIONAL,
                                         reportCriteria
                                         }

QualityReportCriteria ::=             CHOICE {
                                         qualityReportingCriteria,
                                         periodicalReportingCriteria,
                                         noReporting
                                         }

QualityReportingCriteria ::=          SEQUENCE (SIZE (1..maxTrCH)) OF
                                         QualityReportingCriteriaSingle

QualityReportingCriteriaSingle ::=     SEQUENCE {
                                         transportChannelIdentity,
                                         totalCRC (1..512),
                                         badCRC (1..512),
                                         }

```

```

    pendingAfterTrigger           INTEGER (1..512)
}

QualityReportingQuantity ::= SEQUENCE {
    dl-TransChBLER             BOOLEAN,
    bler-dl-TransChIdList      OPTIONAL,
    modeSpecificInfo           CHOICE {
        fdd                   NULL,
        tdd                   SEQUENCE {
            sir-TFCS-List     SIR-TFCS-List
        }
    }
}

RAT-Type ::= ENUMERATED {
    gsm, is2000
}

ReferenceCellPosition ::= CHOICE {
    ellipsoidPoint             EllipsoidPoint,
    ellipsoidPointWithAltitude EllipsoidPointAltitude
}

-- ReferenceLocation, as defined in 23.032
ReferenceLocation ::= SEQUENCE {
    ellipsoidPointAltitudeEllipsoide   EllipsoidPointAltitudeEllipsoide
}

ReferenceTimeDifferenceToCell ::= CHOICE {
    -- Actual value accuracy40 = IE value * 40
    accuracy40                 INTEGER (0..960),
    -- Actual value accuracy256 = IE value * 256
    accuracy256                 INTEGER (0..150),
    -- Actual value accuracy2560 = IE value * 2560
    accuracy2560                INTEGER (0..15)
}

RemovedInterFreqCellList ::= CHOICE {
    removeAllInterFreqCells    NULL,
    removeSomeInterFreqCells   SEQUENCE (SIZE (1..maxCellMeas)) OF
                                InterFreqCellID,
    removeNoInterFreqCells     NULL
}

RemovedInterRATCellList ::= CHOICE {
    removeAllInterRATCells     NULL,
    removeSomeInterRATCells    SEQUENCE (SIZE (1..maxCellMeas)) OF
                                InterRATCellID,
    removeNoInterRATCells      NULL
}

RemovedIntraFreqCellList ::= CHOICE {
    removeAllIntraFreqCells   NULL,
    removeSomeIntraFreqCells  SEQUENCE (SIZE (1..maxCellMeas)) OF
                                IntraFreqCellID,
    removeNoIntraFreqCells    NULL
}

ReplacementActivationThreshold ::= ENUMERATED {
    notApplicable, t1, t2,
    t3, t4, t5, t6, t7
}

ReportDeactivationThreshold ::= ENUMERATED {
    notApplicable, t1, t2,
    t3, t4, t5, t6, t7
}

ReportingAmount ::= ENUMERATED {
    ral, ra2, ra4, ra8, ra16, ra32,
    ra64, ra-Infinity
}

ReportingCellStatus ::= CHOICE{
    withinActiveSet              MaxNumberOfReportingCellsType1,
    withinMonitoredSetUsedFreq   MaxNumberOfReportingCellsType1,
    withinActiveAndOrMonitoredUsedFreq MaxNumberOfReportingCellsType1,
    withinDetectedSetUsedFreq    MaxNumberOfReportingCellsType1,
    withinMonitoredAndOrDetectedUsedFreq MaxNumberOfReportingCellsType1,
    allActiveplusMonitoredSet    MaxNumberOfReportingCellsType3,
    allActivePlusDetectedSet     MaxNumberOfReportingCellsType3,
}

```

```

allActivePlusMonitoredAndOrDetectedSet
    MaxNumberOfReportingCellsType3,
withinVirtualActSet           MaxNumberOfReportingCellsType1,
withinMonitoredSetNonUsedFreq MaxNumberOfReportingCellsType1,
withinMonitoredAndOrVirtualActiveSetNonUsedFreq
    MaxNumberOfReportingCellsType1,
allVirtualActSetplusMonitoredSetNonUsedFreq
    MaxNumberOfReportingCellsType3,
withinActSetOrVirtualActSet-InterRATcells
    MaxNumberOfReportingCellsType2,
withinActSetAndOrMonitoredUsedFreqOrVirtualActSetAndOrMonitoredNonUsedFreq
    MaxNumberOfReportingCellsType2
}

ReportingCellStatusOpt ::=          SEQUENCE {
    reportingCellStatus           ReportingCellStatus           OPTIONAL
}

ReportingInfoForCellDCH ::=          SEQUENCE {
    intraFreqReportingQuantity   IntraFreqReportingQuantity,
    measurementReportingMode    MeasurementReportingMode,
    reportCriteria               CellDCH-ReportCriteria
}

ReportingInfoForCellDCH-LCR-r4 ::=  SEQUENCE {
    intraFreqReportingQuantity   IntraFreqReportingQuantity,
    measurementReportingMode    MeasurementReportingMode,
    reportCriteria               CellDCH-ReportCriteria-LCR-r4
}

ReportingInterval ::=                ENUMERATED {
    noPeriodicalreporting, ri0-25,
    ri0-5, ril1, ri2, ri4, ri8, ril16 }

ReportingIntervalLong ::=           ENUMERATED {
    ril0, ril0-25, ril0-5, ril1,
    ril2, ril3, ril4, ril6, ril8,
    ril12, ril16, ril20, ril24,
    ril28, ril32, ril64 }
-- When the value "ril0" is used, the UE behaviour is not
-- defined.

-- Actual value ReportingRange = IE value * 0.5
ReportingRange ::=                  INTEGER (0..29)

RL-AdditionInfoList ::=            SEQUENCE (SIZE (1..maxRL)) OF
                                    PrimaryCPICH-Info

RL-InformationLists ::=           SEQUENCE {
    rl-AdditionInfoList         RL-AdditionInfoList           OPTIONAL,
    rL-RemovalInformationList   RL-RemovalInformationList   OPTIONAL
}

RLC-BuffersPayload ::=             ENUMERATED {
    p10, p14, p18, p116, p132,
    p164, p1128, p1256, p1512, p11024,
    p12k, p14k, p18k, p116k, p132k,
    p164k, p1128k, p1256k, p1512k, p11024k,
    spare12, spare11, spare10, spare9, spare8,
    spare7, spare6, spare5, spare4, spare3,
    spare2, spare1 }

-- Actual value RRC = IE value * 0.032
RRC ::=                           INTEGER (-127..127)

SatData ::=                         SEQUENCE{
    satID                      SatID,
    iode                        IODE
}

SatDataList ::=                     SEQUENCE (SIZE (0..maxSat)) OF
                                    SatData

SatelliteStatus ::=                ENUMERATED {
    ns-NN-U,
    es-SN,
    es-NN-U,

```

```

        rev2,
        rev }

-- Identifies the satellite and is equal to (SV ID No - 1) where SV ID No is defined in [12].
SatID ::= INTEGER (0..63)

SFN-Offset-Validity ::= ENUMERATED { false }

SFN-SFN-Drift ::= ENUMERATED {
    sfnsfndrift0, sfnsfndrift1, sfnsfndrift2,
    sfnsfndrift3, sfnsfndrift4, sfnsfndrift5,
    sfnsfndrift8, sfnsfndrift10, sfnsfndrift15,
    sfnsfndrift25, sfnsfndrift35, sfnsfndrift50,
    sfnsfndrift65, sfnsfndrift80, sfnsfndrift100,
    sfnsfndrift-1, sfnsfndrift-2, sfnsfndrift-3,
    sfnsfndrift-4, sfnsfndrift-5, sfnsfndrift-8,
    sfnsfndrift-10, sfnsfndrift-15, sfnsfndrift-25,
    sfnsfndrift-35, sfnsfndrift-50, sfnsfndrift-65,
    sfnsfndrift-80, sfnsfndrift-100}

SFN-SFN-ObsTimeDifference ::= CHOICE {
    type1
    type2
}

-- SPARE: SFN-SFN-ObsTimeDifference1, Max = 9830399
-- For 1.28Mcps TDD, Max value of SFN-SFN-ObsTimeDifference1 is 3276799.
-- Values above Max are spare
SFN-SFN-ObsTimeDifference1 ::= INTEGER (0..16777215)

-- SPARE: SFN-SFN-ObsTimeDifference2, Max = 40961
-- For 1.28Mcps TDD, Max value of SFN-SFN-ObsTimeDifference2 is 27649.
-- Values above Max are spare
SFN-SFN-ObsTimeDifference2 ::= INTEGER (0..65535)

SFN-SFN-OTD-Type ::= ENUMERATED {
    noReport,
    type1,
    type2 }

SFN-SFN-RelTimeDifference1 ::= SEQUENCE {
    sfn-Offset
    sfn-sfn-Reltimedifference
}

SFN-TOW-Uncertainty ::= ENUMERATED {
    lessThan10,
    moreThan10 }

SIR ::= INTEGER (0..63)

SIR-MeasurementList ::= SEQUENCE (SIZE (1..maxCCTrCH)) OF
    SIR-MeasurementResults

SIR-MeasurementResults ::= SEQUENCE {
    tfcs-ID
    sir-TimeslotList
}

SIR-TFCS ::= TFCS-IdentityPlain

SIR-TFCS-List ::= SEQUENCE (SIZE (1..maxCCTrCH)) OF
    SIR-TFCS

SIR-TimeslotList ::= SEQUENCE (SIZE (1..maxTS)) OF
    SIR

-- SubFrame1Reserved, reserved bits in subframe 1 of the GPS navigation message
SubFrame1Reserved ::= SEQUENCE {
    reserved1
    reserved2
    reserved3
    reserved4
}

```

```

T-ADVinfo ::=          SEQUENCE {
                         t-ADV
                         sfn
                     }

T-CRMax ::=           CHOICE {
                         notUsed,
                         t30,
                         t60,
                         t120,
                         t180,
                         t240
                     }

T-CRMaxHyst ::=        ENUMERATED {
                         notUsed, t10, t20, t30,
                         t40, t50, t60, t70
                     }

TemporaryOffset1 ::=   ENUMERATED {
                         to3, to6, to9, to12, to15,
                         to18, to21, infinite
                     }

TemporaryOffset2 ::=   ENUMERATED {
                         to2, to3, to4, to6, to8,
                         to10, to12, infinite
                     }

TemporaryOffsetList ::= SEQUENCE {
                         temporaryOffset1,
                         temporaryOffset2
                     }

Threshold ::=          INTEGER (-115..0)

-- The order of the list corresponds to the order of frequency defined in Inter-FreqEventCriteria
ThresholdNonUsedFrequency-deltaList ::= SEQUENCE (SIZE (1..maxFreq)) OF
                                         DeltaRSCPPerCell

ThresholdPositionChange ::= ENUMERATED {
                            pc10, pc20, pc30, pc40, pc50,
                            pc100, pc200, pc300, pc500,
                            pc1000, pc2000, pc5000, pc10000,
                            pc20000, pc50000, pc100000
                           }

ThresholdSFN-GPS-TOW ::= ENUMERATED {
                           ms1, ms2, ms3, ms5, ms10,
                           ms20, ms50, ms100
                          }

ThresholdSFN-SFN-Change ::= ENUMERATED {
                            c0-25, c0-5, c1, c2, c3, c4, c5,
                            c10, c20, c50, c100, c200, c500,
                            c1000, c2000, c5000
                           }

ThresholdUsedFrequency ::= INTEGER (-115..165)

-- Actual value TimeInterval = IE value * 20.
TimeInterval ::=          INTEGER (1..13)

TimeslotInfo ::=          SEQUENCE {
                           timeslotNumber,
                           burstType
                         }

TimeslotInfo-LCR-r4 ::=   SEQUENCE {
                           timeslotNumber
                         }

TimeslotInfoList ::=       SEQUENCE (SIZE (1..maxTS)) OF
                           TimeslotInfo

TimeslotInfoList-LCR-r4 ::= SEQUENCE (SIZE (1..maxTS-LCR)) OF
                           TimeslotInfo-LCR-r4

TimeslotInfoList-r4 ::=    CHOICE {
                           tdd384
                           SEQUENCE (SIZE (1..maxTS)) OF
                           TimeslotInfo,
                         }

```

```

tdd128                               SEQUENCE (SIZE (1..maxTS-LCR)) OF
                                         TimeslotInfo-LCR-r4
}

-- SPARE: TimeslotISCP, Max = 91
-- Values above Max are spare
TimeslotISCP ::=                  INTEGER (0..127)

-- TimeslotISCP-List shall not include more than 6 elements in 1.28Mcps TDD mode.
TimeslotISCP-List ::=             SEQUENCE (SIZE (1..maxTS)) OF
                                         TimeslotISCP

TimeslotListWithISCP ::=           SEQUENCE (SIZE (1..maxTS)) OF
                                         TimeslotWithISCP

TimeslotWithISCP ::=               SEQUENCE {
                                         timeslot,
                                         timeslotISCP
}

TimeToTrigger ::=                  ENUMERATED {
                                         ttt0, ttt10, ttt20, ttt40, ttt60,
                                         ttt80, ttt100, ttt120, ttt160,
                                         ttt200, ttt240, ttt320, ttt640,
                                         ttt1280, ttt2560, ttt5000 }

TrafficVolumeEventParam ::=        SEQUENCE {
                                         eventID,
                                         reportingThreshold,
                                         timeToTrigger,
                                         pendingTimeAfterTrigger
                                         OPTIONAL,
                                         tx-InterruptionAfterTrigger
                                         OPTIONAL
}

TrafficVolumeEventResults ::=      SEQUENCE {
                                         ul-transportChannelCausingEvent
                                         UL-TrCH-Identity,
                                         trafficVolumeEventIdentity
                                         TrafficVolumeEventType
}

TrafficVolumeEventType ::=         ENUMERATED {
                                         e4a,
                                         e4b }

TrafficVolumeMeasQuantity ::=     CHOICE {
                                         rlc-BufferPayload
                                         NULL,
                                         averageRLC-BufferPayload
                                         TimeInterval,
                                         varianceOfRLC-BufferPayload
                                         TimeInterval
}

TrafficVolumeMeasSysInfo ::=       SEQUENCE {
                                         trafficVolumeMeasurementID
                                         MeasurementIdentity      DEFAULT 4,
                                         trafficVolumeMeasurementObjectList
                                         TrafficVolumeMeasurementObjectList
                                         OPTIONAL,
                                         trafficVolumeMeasQuantity
                                         TrafficVolumeMeasQuantity
                                         OPTIONAL,
                                         trafficVolumeReportingQuantity
                                         TrafficVolumeReportingQuantity
                                         OPTIONAL,
                                         -- dummy is not used in this version of specification, it should
                                         -- not be sent and if received it should be ignored.
                                         dummy
                                         TrafficVolumeReportingCriteria
                                         OPTIONAL,
                                         measurementValidity
                                         MeasurementValidity
                                         OPTIONAL,
                                         measurementReportingMode
                                         MeasurementReportingMode,
                                         reportCriteriaSysInf
                                         TrafficVolumeReportCriteriaSysInfo
}

TrafficVolumeMeasuredResults ::=   SEQUENCE {
                                         rb-Identity
                                         RB-Identity,
                                         rlc-BuffersPayload
                                         RLC-BuffersPayload
                                         OPTIONAL,
                                         averageRLC-BufferPayload
                                         AverageRLC-BufferPayload
                                         OPTIONAL,
                                         varianceOfRLC-BufferPayload
                                         VarianceOfRLC-BufferPayload
                                         OPTIONAL
}

TrafficVolumeMeasuredResultsList ::= SEQUENCE (SIZE (1..maxRB)) OF
                                         TrafficVolumeMeasuredResults

TrafficVolumeMeasurement ::=       SEQUENCE {
                                         trafficVolumeMeasurementObjectList
                                         TrafficVolumeMeasurementObjectList
                                         OPTIONAL,
                                         trafficVolumeMeasQuantity
                                         TrafficVolumeMeasQuantity
                                         OPTIONAL,
                                         trafficVolumeReportingQuantity
                                         TrafficVolumeReportingQuantity
                                         OPTIONAL,

```

```

measurementValidity           MeasurementValidity          OPTIONAL,
reportCriteria                TrafficVolumeReportCriteria
}

TrafficVolumeMeasurementObjectList ::= SEQUENCE (SIZE (1..maxTrCH)) OF
                                         UL-TrCH-Identity

TrafficVolumeReportCriteria ::= CHOICE {
    trafficVolumeReportingCriteria   TrafficVolumeReportingCriteria,
    periodicalReportingCriteria     PeriodicalReportingCriteria,
    noReporting                     NULL
}

TrafficVolumeReportCriteriaSysInfo ::= CHOICE {
    trafficVolumeReportingCriteria   TrafficVolumeReportingCriteria,
    periodicalReportingCriteria     PeriodicalReportingCriteria
}

TrafficVolumeReportingCriteria ::= SEQUENCE {
    -- NOTE: transChCriteriaList should be mandatory in later versions of this message
    transChCriteriaList             TransChCriteriaList          OPTIONAL
}

TrafficVolumeReportingQuantity ::= SEQUENCE {
    rlc-RB-BufferPayload           BOOLEAN,
    rlc-RB-BufferPayloadAverage    BOOLEAN,
    rlc-RB-BufferPayloadVariance   BOOLEAN
}

TrafficVolumeThreshold ::= ENUMERATED {
    th8, th16, th32, th64, th128,
    th256, th512, th1024, th2k, th3k,
    th4k, th6k, th8k, th12k, th16k,
    th24k, th32k, th48k, th64k, th96k,
    th128k, th192k, th256k, th384k,
    th512k, th768k
}

TransChCriteria ::= SEQUENCE {
    ul-transportChannelID          OPTIONAL,
    eventSpecificParameters        OPTIONAL
}

TransChCriteriaList ::= SEQUENCE (SIZE (1..maxTrCH)) OF
                           TransChCriteria

TransferMode ::= ENUMERATED {
    acknowledgedModeRLC,
    unacknowledgedModeRLC
}

TransmittedPowerThreshold ::= INTEGER (-50..33)

TriggeringCondition1 ::= ENUMERATED {
    activeSetCellsOnly,
    monitoredSetCellsOnly,
    activeSetAndMonitoredSetCells
}

TriggeringCondition2 ::= ENUMERATED {
    activeSetCellsOnly,
    monitoredSetCellsOnly,
    activeSetAndMonitoredSetCells,
    detectedSetCellsOnly,
    detectedSetAndMonitoredSetCells
}

TX-InterruptionAfterTrigger ::= ENUMERATED {
    txiat0-25, txiat0-5, txiat1,
    txiat2, txiat4, txiat8, txiat16
}

UDRE ::= ENUMERATED {
    lessThan1,
    between1-and-4,
    between4-and-8,
    over8
}

UE-6AB-Event ::= SEQUENCE {
    timeToTrigger,
    transmittedPowerThreshold
}

```

```

UE-6FG-Event ::=          SEQUENCE {
    timeToTrigger           TimeToTrigger,
    -- in 1.28 Mcps TDD ue-RX-TX-TimeDifferenceThreshold corresponds to TADV Threshold
    ue-RX-TX-TimeDifferenceThreshold   UE-RX-TX-TimeDifferenceThreshold
}

-- dummy and dummy2 are not used in this version of the specification, they should
-- not be sent and if received the UE behaviour is not specified.
UE-AutonomousUpdateMode ::=      CHOICE {
    dummy                  NULL,
    onWithNoReporting      NULL,
    dummy2                 RL-InformationLists
}

UE-InternalEventParam ::=       CHOICE {
    event6a                UE-6AB-Event,
    event6b                UE-6AB-Event,
    event6c                TimeToTrigger,
    event6d                TimeToTrigger,
    event6e                TimeToTrigger,
    event6f                UE-6FG-Event,
    event6g                UE-6FG-Event
}

UE-InternalEventParamList ::=    SEQUENCE (SIZE (1..maxMeasEvent)) OF
                                UE-InternalEventParam

UE-InternalEventResults ::=     CHOICE {
    event6a                NULL,
    event6b                NULL,
    event6c                NULL,
    event6d                NULL,
    event6e                NULL,
    event6f                PrimaryCPICH-Info,
    event6g                PrimaryCPICH-Info,
    spare                  NULL
}

UE-InternalMeasQuantity ::=     SEQUENCE {
    measurementQuantity     UE-MeasurementQuantity,
    filterCoefficient        FilterCoefficient
                                DEFAULT fc0
}

UE-InternalMeasuredResults ::=  SEQUENCE {
    modeSpecificInfo         CHOICE {
        fdd                   SEQUENCE {
            ue-TransmittedPowerFDD    UE-TransmittedPower    OPTIONAL,
            ue-RX-TX-ReportEntryList  UE-RX-TX-ReportEntryList  OPTIONAL
        },
        tdd                   SEQUENCE {
            ue-TransmittedPowerTDD-List  UE-TransmittedPowerTDD-List  OPTIONAL,
            appliedTA                UL-TimingAdvance    OPTIONAL
        }
    }
}

UE-InternalMeasuredResults-LCR-r4 ::= SEQUENCE {
    ue-TransmittedPowerTDD-List    UE-TransmittedPowerTDD-List  OPTIONAL,
    t-ADVinfo                      T-ADVinfo                OPTIONAL
}

UE-InternalMeasurement ::=      SEQUENCE {
    ue-InternalMeasQuantity      UE-InternalMeasQuantity    OPTIONAL,
    ue-InternalReportingQuantity UE-InternalReportingQuantity  OPTIONAL,
    reportCriteria               UE-InternalReportCriteria
}

UE-InternalMeasurement-r4 ::=    SEQUENCE {
    ue-InternalMeasQuantity      UE-InternalMeasQuantity    OPTIONAL,
    ue-InternalReportingQuantity UE-InternalReportingQuantity-r4  OPTIONAL,
    reportCriteria               UE-InternalReportCriteria
}

UE-InternalMeasurementSysInfo ::= SEQUENCE {
    ue-InternalMeasurementID     MeasurementIdentity      DEFAULT 5,
    ue-InternalMeasQuantity      UE-InternalMeasQuantity
}

```

```

UE-InternalReportCriteria ::= CHOICE {
    ue-InternalReportingCriteria,
    periodicalReportingCriteria,
    noReporting
}

UE-InternalReportingCriteria ::= SEQUENCE {
    ue-InternalEventParamList
} OPTIONAL

UE-InternalReportingQuantity ::= SEQUENCE {
    ue-TransmittedPower
    modeSpecificInfo
    fdd
        ue-RX-TX-TimeDifference
    },
    tdd
        appliedTA
}
}

UE-InternalReportingQuantity-r4 ::= SEQUENCE {
    ue-TransmittedPower
    modeSpecificInfo
    fdd
        ue-RX-TX-TimeDifference
    },
    tdd
        tddOption
            tdd384
                appliedTA
            },
            tdd128
                t-ADVinfo
}
}

-- TABULAR: UE-MeasurementQuantity, for 3.84 Mcps TDD only the first two values
-- ue-TransmittedPower and utra-Carrier-RSSI are used.
-- For 1.28 Mcps TDD ue-RX-TX-TimeDifference corresponds to T-ADV in the tabular
UE-MeasurementQuantity ::= ENUMERATED {
    ue-TransmittedPower,
    utra-Carrier-RSSI,
    ue-RX-TX-TimeDifference }

UE-RX-TX-ReportEntry ::= SEQUENCE {
    primaryCPICH-Info,
    ue-RX-TX-TimeDifferenceType1
}

UE-RX-TX-ReportEntryList ::= SEQUENCE (SIZE (1..maxRL)) OF
    UE-RX-TX-ReportEntry

-- SPARE: UE-RX-TX-TimeDifferenceType1, Max = 1280
-- Values above Max are spare
UE-RX-TX-TimeDifferenceType1 ::= INTEGER (768..1791)

UE-RX-TX-TimeDifferenceType2 ::= INTEGER (0..8191)

UE-RX-TX-TimeDifferenceType2Info ::= SEQUENCE {
    ue-RX-TX-TimeDifferenceType2
    neighbourQuality
}

-- In 1.28 Mcps TDD, actual value for
-- T-ADV Threshold = (UE-RX-TX-TimeDifferenceThreshold - 768) * 0.125
UE-RX-TX-TimeDifferenceThreshold ::= INTEGER (768..1280)

UE-TransmittedPower ::= INTEGER (0..104)

UE-TransmittedPowerTDD-List ::= SEQUENCE (SIZE (1..maxTS)) OF
    UE-TransmittedPower

```

```

UL-TrCH-Identity ::= CHOICE{
    dch
    -- Default transport channel in the UL is either RACH or CPCH, but not both.
    rachOrCPCH
    usch
}
}

UE-Positioning-Accuracy ::= BIT STRING (SIZE (7))

UE-Positioning-CipherParameters ::= SEQUENCE {
    cipheringKeyFlag
    cipheringSerialNumber
}
}

UE-Positioning-Error ::= SEQUENCE {
    errorReason
    ue-positioning-GPS-additionalAssistanceDataRequest
    ue-positioning-GPS-AdditionalAssistanceDataRequest OPTIONAL
}
}

UE-Positioning-ErrorCause ::= ENUMERATED {
    notEnoughOTDOA-Cells,
    notEnoughGPS-Satellites,
    assistanceDataMissing,
    notAccomplishedGPS-TimingOfCellFrames,
    undefinedError,
    requestDeniedByUser,
    notProcessedAndTimeout,
    referenceCellNotServingCell
}

UE-Positioning-EventParam ::= SEQUENCE {
    reportingAmount
    reportFirstFix
    measurementInterval
    eventSpecificInfo
}
}

UE-Positioning-EventParamList ::= SEQUENCE (SIZE (1..maxMeasEvent)) OF
UE-Positioning-EventParam

UE-Positioning-EventSpecificInfo ::= CHOICE {
    e7a
    e7b
    e7c
}
}

UE-Positioning-GPS-AcquisitionAssistance ::= SEQUENCE {
    gps-ReferenceTime
    INTEGER (0..604799999),
    utran-GPSReferenceTime
    UTRAN-GPSReferenceTime
    satelliteInformationList
    AcquisitionSatInfoList
}
}

UE-Positioning-GPS-AdditionalAssistanceDataRequest ::= SEQUENCE {
    almanacRequest
    BOOLEAN,
    utcModelRequest
    BOOLEAN,
    ionosphericModelRequest
    BOOLEAN,
    navigationModelRequest
    BOOLEAN,
    dgpsCorrectionsRequest
    BOOLEAN,
    referenceLocationRequest
    BOOLEAN,
    referenceTimeRequest
    BOOLEAN,
    acquisitionAssistanceRequest
    BOOLEAN,
    realTimeIntegrityRequest
    BOOLEAN,
    navModelAddDataRequest
    UE-Positioning-GPS-NavModelAddDataReq
    OPTIONAL
}
}

UE-Positioning-GPS-Almanac ::= SEQUENCE {
    wn-a
    BIT STRING (SIZE (8)),
    almanacSatInfoList
    AlmanacSatInfoList,
    sv-GlobalHealth
    BIT STRING (SIZE (364))
    OPTIONAL
}
}

UE-Positioning-GPS-AssistanceData ::= SEQUENCE {
    ue-positioning-GPS-ReferenceTime
    UE-Positioning-GPS-ReferenceTime
    OPTIONAL,
    ue-positioning-GPS-ReferenceLocation
    ReferenceLocation
    OPTIONAL,
}

```

```

ue-positioning-GPS-DGPS-Corrections
OPTIONAL,
ue-positioning-GPS-NavigationModel
OPTIONAL,
ue-positioning-GPS-IonosphericModel
OPTIONAL,
ue-positioning-GPS-UTC-Model
OPTIONAL,
ue-positioning-GPS-Almanac
OPTIONAL,
ue-positioning-GPS-AcquisitionAssistance
OPTIONAL,
ue-positioning-GPS-Real-timeIntegrity           BadSatList
-- dummy is not used in this version of the specification, it should
-- not be sent and if received it should be ignored.
dummy          UE-Positioning-GPS-ReferenceCellInfo   OPTIONAL
}

UE-Positioning-GPS-DGPS-Corrections ::=      SEQUENCE {
  gps-TOW                      INTEGER (0..604799),
  statusHealth                  DiffCorrectionStatus,
  dgps-CorrectionSatInfoList    DGPS-CorrectionSatInfoList
}

UE-Positioning-GPS-IonosphericModel ::=      SEQUENCE {
  alfa0                        BIT STRING (SIZE (8)),
  alfa1                        BIT STRING (SIZE (8)),
  alfa2                        BIT STRING (SIZE (8)),
  alfa3                        BIT STRING (SIZE (8)),
  beta0                         BIT STRING (SIZE (8)),
  beta1                         BIT STRING (SIZE (8)),
  beta2                         BIT STRING (SIZE (8)),
  beta3                         BIT STRING (SIZE (8))
}

UE-Positioning-GPS-MeasurementResults ::=      SEQUENCE {
  referenceTime                 CHOICE {
    utran-GPSReferenceTimeResult UTRAN-GPSReferenceTimeResult,
    gps-ReferenceTimeOnly        INTEGER (0..604799999)
  },
  gps-MeasurementParamList      GPS-MeasurementParamList
}

UE-Positioning-GPS-NavigationModel ::=      SEQUENCE {
  navigationModelSatInfoList    NavigationModelSatInfoList
}

UE-Positioning-GPS-NavModelAddDataReq ::=      SEQUENCE {
  gps-Week                      INTEGER (0..1023),
  -- SPARE: gps-Toe, Max = 167
  -- Values above Max are spare
  gps-Toe                       INTEGER (0..255),
  -- SPARE: tToeLimit, Max = 10
  -- Values above Max are spare
  tToeLimit                     INTEGER (0..15),
  satDataList                   SatDataList
}

UE-Positioning-GPS-ReferenceCellInfo ::=      SEQUENCE{
  modeSpecificInfo               CHOICE {
    fdd                           SEQUENCE {
      referenceIdentity            PrimaryCPICH-Info
    },
    tdd                           SEQUENCE {
      referenceIdentity            CellParametersID
    }
  }
}

UE-Positioning-GPS-ReferenceTime ::=      SEQUENCE {
  gps-Week                      INTEGER (0..1023),
  gps-tow-1msec                  GPS-TOW-1msec,   utran-GPSReferenceTime
  GPSReferenceTime                OPTIONAL,
  sfn-tow-Uncertainty            SFN-TOW-Uncertainty
  utran-GPS-DriftRate             UTRAN-GPS-DriftRate
  gps-TOW-AssistList              GPS-TOW-AssistList
}

```

```

UE-Positioning-GPS-UTC-Model ::=          SEQUENCE {
  a1                                BIT STRING (SIZE (24)),
  a0                                BIT STRING (SIZE (32)),
  t-ot                               BIT STRING (SIZE (8)),
  wn-t                               BIT STRING (SIZE (8)),
  delta-t-LS                          BIT STRING (SIZE (8)),
  wn-lsf                             BIT STRING (SIZE (8)),
  dn                                 BIT STRING (SIZE (8)),
  delta-t-LSF                         BIT STRING (SIZE (8))
}

UE-Positioning-IPDL-Parameters ::=          SEQUENCE {
  ip-Spacing,
  ip-Length,
  ip-Offset,
  seed,
  burstModeParameters                 BurstModeParameters OPTIONAL
}

UE-Positioning-IPDL-Parameters-r4 ::=         SEQUENCE {
  modeSpecificInfo                   CHOICE {
    fdd                                SEQUENCE {
      ip-Spacing,
      ip-Length,
      ip-Offset,
      seed
    },
    tdd                                SEQUENCE {
      ip-Spacing-TDD,
      ip-slot,
      ip-Start,
      ip-PCCPCG                         IP-PCCPCH-r4 OPTIONAL
    }
  },
  burstModeParameters                BurstModeParameters OPTIONAL
}

UE-Positioning-IPDL-Parameters-TDD-r4-ext ::= SEQUENCE {
  ip-Spacing,
  ip-slot,
  ip-Start,
  ip-PCCPCG                         IP-PCCPCH-r4 OPTIONAL,
  burstModeParameters                BurstModeParameters
}

UE-Positioning-MeasuredResults ::=          SEQUENCE {
  ue-positioning-OTDOA-Measurement   UE-Positioning-OTDOA-Measurement
  OPTIONAL,
  ue-positioning-PositionEstimateInfo UE-Positioning-PositionEstimateInfo
  OPTIONAL,
  ue-positioning-GPS-Measurement     UE-Positioning-GPS-MeasurementResults
  OPTIONAL,
  ue-positioning-Error               UE-Positioning-Error
  OPTIONAL
}

UE-Positioning-MeasuredResults-v390ext ::= SEQUENCE {
  ue-Positioning-OTDOA-Measurement-v390ext UE-Positioning-OTDOA-Measurement-v390ext
}

UE-Positioning-Measurement ::=             SEQUENCE {
  ue-positioning-ReportingQuantity    UE-Positioning-ReportingQuantity,
  reportCriteria                     UE-Positioning-ReportCriteria,
  ue-positioning-OTDOA-AssistanceData UE-Positioning-OTDOA-AssistanceData
  OPTIONAL,
  ue-positioning-GPS-AssistanceData  UE-Positioning-GPS-AssistanceData
  OPTIONAL
}

UE-Positioning-Measurement-v390ext ::= SEQUENCE {
  ue-positioning-ReportingQuantity-v390ext UE-Positioning-ReportingQuantity-v390ext
  OPTIONAL,
  measurementValidity                MeasurementValidity OPTIONAL,
  ue-positioning-OTDOA-AssistanceData-UEB UE-Positioning-OTDOA-AssistanceData-UEB
  OPTIONAL
}

UE-Positioning-Measurement-r4 ::=          SEQUENCE {
}

```

```

ue-positioning-ReportingQuantity
measurementValidity
OPTIONAL,
reportCriteria
ue-positioning-OTDOA-AssistanceData
OPTIONAL,
ue-positioning-GPS-AssistanceData
OPTIONAL
}

UE-Positioning-MeasurementEventResults ::= CHOICE {
    event7a                  UE-Positioning-PositionEstimateInfo,
    event7b                  UE-Positioning-OTDOA-Measurement,
    event7c                  UE-Positioning-GPS-MeasurementResults,
    spare                     NULL
}

UE-Positioning-MeasurementInterval ::= ENUMERATED {
    e5, e15, e60, e300,
    e900, e1800, e3600, e7200 }

UE-Positioning-MethodType ::= ENUMERATED {
    ue-Assisted,
    ue-Based,
    ue-BasedPreferred,
    ue-AssistedPreferred }

UE-Positioning-OTDOA-AssistanceData ::= SEQUENCE {
    ue-positioning-OTDOA-ReferenceCellInfo           UE-Positioning-OTDOA-ReferenceCellInfo
    OPTIONAL,
    ue-positioning-OTDOA-NeighbourCellList          UE-Positioning-OTDOA-NeighbourCellList
    OPTIONAL
}

UE-Positioning-OTDOA-AssistanceData-r4 ::= SEQUENCE {
    ue-positioning-OTDOA-ReferenceCellInfo           UE-Positioning-OTDOA-ReferenceCellInfo-r4
    OPTIONAL,
    ue-positioning-OTDOA-NeighbourCellList          UE-Positioning-OTDOA-NeighbourCellList-r4
    OPTIONAL
}

UE-Positioning-OTDOA-AssistanceData-r4ext ::= SEQUENCE {
    -- In case of TDD these IPDL parameters shall be used for the reference cell instead of
    -- IPDL Parameters in IE UE-Positioning-OTDOA-ReferenceCellInfo
    ue-Positioning-IPDL-Parameters-TDD-r4-ext        UE-Positioning-IPDL-Parameters-TDD-r4-ext
    OPTIONAL,
    -- These IPDL parameters shall be used for the neighbour cells in case of TDD instead of
    -- IPDL Parameters in IE UE-Positioning-OTDOA-NeighbourCellInfoList. The cells shall be
    -- listed in the same order as in IE UE-Positioning-OTDOA-NeighbourCellInfoList
    ue-Positioning-IPDL-Parameters-TDDList-r4-ext    UE-Positioning-IPDL-Parameters-TDDList-r4-ext
    OPTIONAL
}

UE-Positioning-OTDOA-AssistanceData-UEB ::= SEQUENCE {
    ue-positioning-OTDOA-ReferenceCellInfo-UEB       UE-Positioning-OTDOA-ReferenceCellInfo-UEB
    OPTIONAL,
    ue-positioning-OTDOA-NeighbourCellList-UEB      UE-Positioning-OTDOA-NeighbourCellList-
    UEB                                              OPTIONAL
}

UE-Positioning-IPDL-Parameters-TDDList-r4-ext ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
                                                UE-Positioning-IPDL-Parameters-TDD-r4-ext

UE-Positioning-OTDOA-Measurement ::= SEQUENCE {
    sfn                      INTEGER (0..4095),
    modeSpecificInfo          CHOICE {
        fdd                     SEQUENCE {
            referenceCellIDentity PrimaryCPICH-Info,
            ue-RX-TX-TimeDifferenceType2Info   UE-RX-TX-TimeDifferenceType2Info
        },
        tdd                     SEQUENCE {
            referenceCellIdentity     CellParametersID
        }
    },
    neighbourList              NeighbourList
    OPTIONAL
}

UE-Positioning-OTDOA-Measurement-v390ext ::= SEQUENCE {

```

```

neighbourList-v390ext                               NeighbourList-v390ext
}

UE-Positioning-OTDOA-NeighbourCellInfo ::= SEQUENCE {
    modeSpecificInfo CHOICE {
        fdd           SEQUENCE {
            primaryCPICH-Info
        },
        tdd           SEQUENCE{
            cellAndChannelIdentity
        }
    },
    frequencyInfo FrequencyInfo
    ue-positioning-IPDL-Parameters OPTIONAL,
    OPTIONAL,
    sfn-SFN-RelTimeDifference SFN-SFN-RelTimeDifference1,
    sfn-SFN-Drift SFN-SFN-Drift
    searchWindowSize OTDOA-SearchWindowSize,
    positioningMode CHOICE{
        ueBased
        ueAssisted
    }
}

UE-Positioning-OTDOA-NeighbourCellInfo-r4 ::= SEQUENCE {
    modeSpecificInfo CHOICE {
        fdd           SEQUENCE {
            primaryCPICH-Info
        },
        tdd           SEQUENCE{
            cellAndChannelIdentity
        }
    },
    frequencyInfo FrequencyInfo
    ue-positioning-IPDL-Parameters UE-Positioning-IPDL-Parameters-r4
    OPTIONAL,
    OPTIONAL,
    sfn-SFN-RelTimeDifference SFN-SFN-RelTimeDifference1,
    sfn-Offset-Validity SFN-Offset-Validity
    OPTIONAL,
    sfn-SFN-Drift SFN-SFN-Drift
    OPTIONAL,
    searchWindowSize OTDOA-SearchWindowSize,
    positioningMode CHOICE {
        ueBased
            relativeNorth
            relativeEast
            relativeAltitude
            fineSFN-SFN
            -- actual value roundTripTime = (IE value * 0.0625) + 876
            roundTripTime
            INTEGER (-20000..20000)
            INTEGER (-20000..20000)
            INTEGER (-4000..4000)
            FineSFN-SFN
            INTEGER (0.. 32766)
        },
        ueAssisted
            SEQUENCE {}
    }
}

UE-Positioning-OTDOA-NeighbourCellInfo-UEB ::= SEQUENCE {
    modeSpecificInfo CHOICE {
        fdd           SEQUENCE {
            primaryCPICH-Info
        },
        tdd           SEQUENCE{
            cellAndChannelIdentity
        }
    },
    frequencyInfo FrequencyInfo
    ue-positioning-IPDL-Parameters UE-Positioning-IPDL-Parameters
    OPTIONAL,
    OPTIONAL,
    sfn-SFN-RelTimeDifference SFN-SFN-RelTimeDifference1,
    sfn-SFN-Drift SFN-SFN-Drift
    OPTIONAL,
    searchWindowSize OTDOA-SearchWindowSize,
    relativeNorth
    relativeEast
    relativeAltitude
    fineSFN-SFN
    -- actual value roundTripTime = (IE value * 0.0625) + 876
    roundTripTime
    INTEGER (-20000..20000)
    INTEGER (-20000..20000)
    INTEGER (-4000..4000)
    FineSFN-SFN,
    INTEGER (0..32766)
    OPTIONAL
}

UE-Positioning-OTDOA-NeighbourCellList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    UE-Positioning-OTDOA-NeighbourCellInfo

UE-Positioning-OTDOA-NeighbourCellList-r4 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF

```

UE-Positioning-OTDOA-NeighbourCellInfo-r4

```

UE-Positioning-OTDOA-NeighbourCellList-UEB ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
                                              UE-Positioning-OTDOA-NeighbourCellInfo-UEB

UE-Positioning-OTDOA-Quality ::=           SEQUENCE {
  stdResolution                      BIT STRING (SIZE (2)),
  numberOFOTDOA-Measurements         BIT STRING (SIZE (3)),
  stdOfOTDOA-Measurements            BIT STRING (SIZE (5))
}

UE-Positioning-OTDOA-ReferenceCellInfo ::=      SEQUENCE {
  sfn                                INTEGER (0..4095)
  OPTIONAL,
  modeSpecificInfo CHOICE {
    fdd                               SEQUENCE {
      primaryCPICH-Info             PrimaryCPICH-Info
    },
    tdd                               SEQUENCE{
      cellAndChannelIdentity        CellAndChannelIdentity
    }
  },
  frequencyInfo                      FrequencyInfo
  OPTIONAL,
  positioningMode CHOICE {
    ueBased                           SEQUENCE {},
    ueAssisted                        SEQUENCE {}
  },
  ue-positioning-IPDL-Parameters    UE-Positioning-IPDL-Parameters OPTIONAL
}

UE-Positioning-OTDOA-ReferenceCellInfo-r4 ::=   SEQUENCE {
  sfn                                INTEGER (0..4095)
  OPTIONAL,
  modeSpecificInfo CHOICE {
    fdd                               SEQUENCE {
      primaryCPICH-Info             PrimaryCPICH-Info
    },
    tdd                               SEQUENCE{
      cellAndChannelIdentity        CellAndChannelIdentity
    }
  },
  frequencyInfo                      FrequencyInfo
  OPTIONAL,
  positioningMode CHOICE {
    ueBased                           SEQUENCE {
      cellPosition                  ReferenceCellPosition OPTIONAL,
      -- actual value roundTripTime = (IE value * 0.0625) + 876
      roundTripTime                 INTEGER (0..32766)          OPTIONAL
    },
    ueAssisted                        SEQUENCE {}
  },
  ue-positioning-IPDL-Parameters    UE-Positioning-IPDL-Parameters-r4 OPTIONAL
}

UE-Positioning-OTDOA-ReferenceCellInfo-UEB ::=      SEQUENCE {
  sfn                                INTEGER (0..4095)
  OPTIONAL,
  modeSpecificInfo CHOICE {
    fdd                               SEQUENCE {
      primaryCPICH-Info             PrimaryCPICH-Info
    },
    tdd                               SEQUENCE{
      cellAndChannelIdentity        CellAndChannelIdentity
    }
  },
  frequencyInfo                      FrequencyInfo
  OPTIONAL,
  cellPosition                       ReferenceCellPosition
  OPTIONAL,
  -- actual value roundTripTime = (IE value * 0.0625) + 876
  roundTripTime                     INTEGER (0..32766)          OPTIONAL,
  ue-positioning-IPDL-Parameters    UE-Positioning-IPDL-Parameters OPTIONAL
}

UE-Positioning-PositionEstimateInfo ::=           SEQUENCE {
  referenceTime                      CHOICE {
    utran-GPSReferenceTimeResult    UTRAN-GPSReferenceTimeResult,
    INTEGER (0..604799999),
    gps-ReferenceTimeOnly           SEQUENCE {
      sfn                            INTEGER (0..4095),
      modeSpecificInfo               CHOICE {
        fdd                           SEQUENCE {

```



```

}

UTRAN-GPSReferenceTimeResult ::=          SEQUENCE {
  -- For ue-GPSTimingOfCell values above 37158911999999 are not
  -- used in this version of the specification
  -- Actual value ue-GPSTimingOfCell = (ms-part * 4294967296) + ls-part
  ue-GPSTimingOfCell           SEQUENCE {
    ms-part                  INTEGER (0.. 16383),
    ls-part                  INTEGER (0..4294967295)
  },
  modeSpecificInfo           CHOICE {
    fdd                      SEQUENCE {
      referenceIdentity      PrimaryCPICH-Info
    },
    tdd                      SEQUENCE {
      referenceIdentity      CellParametersID
    }
  },
  sfn                      INTEGER (0..4095)
}

VarianceOfRLC-BufferPayload ::=      ENUMERATED {
  plv0, plv4, plv8, plv16, plv32, plv64,
  plv128, plv256, plv512, plv1024,
  plv2k, plv4k, plv8k, plv16k, spare2, spare1 }

-- Actual value W = IE value * 0.1
W ::=          INTEGER (0..20)

-- ****
-- OTHER INFORMATION ELEMENTS (10.3.8)
--

BCC ::=          INTEGER (0..7)

BCCH-ModificationInfo ::=          SEQUENCE {
  mib-ValueTag              MIB-ValueTag,
  bcch-ModificationTime     BCCH-ModificationTime
}                                         OPTIONAL

-- Actual value BCCH-ModificationTime = IE value * 8
BCCH-ModificationTime ::=          INTEGER (0..511)

BSIC ::=          SEQUENCE {
  ncc                      NCC,
  bcc                      BCC
}

CBS-DRX-Level1Information ::=        SEQUENCE {
  ctch-AllocationPeriod    INTEGER (1..256),
  cbs-FrameOffset          INTEGER (0..255)
}

CDMA2000-Message ::=          SEQUENCE {
  msg-Type                 BIT STRING (SIZE (8)),
  payload                  BIT STRING (SIZE (1..512))
}

CDMA2000-MessageList ::=        SEQUENCE (SIZE (1..maxInterSysMessages)) OF
                                CDMA2000-Message

CDMA2000-UMTS-Frequency-List ::=  SEQUENCE (SIZE (1..maxNumCDMA2000Freqs)) OF
                                FrequencyInfoCDMA2000

CellValueTag ::=          INTEGER (1..4)

--Actual value = 2^(IE value)
ExpirationTimeFactor ::=          INTEGER (1..8)

FDD-UMTS-Frequency-List ::=        SEQUENCE (SIZE (1..maxNumFDDFreqs)) OF
                                FrequencyInfoFDD

FrequencyInfoCDMA2000 ::=        SEQUENCE {
  band-Class               BIT STRING (SIZE (5)),
  cdma-Freq                BIT STRING (SIZE(11))
}

```

```

GERAN-SystemInfoBlock ::= OCTET STRING (SIZE (1..23))

GERAN-SystemInformation ::= SEQUENCE (SIZE (1..maxGERAN-SI)) OF GERAN-SystemInfoBlock

GSM-BA-Range ::= SEQUENCE {
    gsmLowRangeUARFCN      UARFCN,
    gsmUpRangeUARFCN       UARFCN
}

GSM-BA-Range-List ::= SEQUENCE (SIZE (1..maxNumGSMFreqRanges)) OF
                      GSM-BA-Range

-- This IE is formatted as 'TLV' and is coded in the same way as the Mobile Station Classmark 2
-- information element in [5]. The first octet is the Mobile station classmark 2 IEI and its value
-- shall be set to 33H. The second octet is the Length of mobile station classmark 2 and its value
-- shall be set to 3. The octet 3 contains the first octet of the value part of the Mobile Station
-- Classmark 2 information element, the octet 4 contains the second octet of the value part of the
-- Mobile Station Classmark 2 information element and so on. For each of these octets, the first/
-- leftmost/ most significant bit of the octet contains b8 of the corresponding octet of the Mobile
-- Station Classmark 2.
GSM-Classmark2 ::= OCTET STRING (SIZE (5))

-- This IE is formatted as 'V' and is coded in the same way as the value part in the Mobile station
-- classmark 3 information element in [5]
-- The value part is specified by means of CSN.1, which encoding results in a bit string, to which
-- final padding may be appended upto the next octet boundary [5]. The first/ leftmost bit of the
-- CSN.1 bit string is placed in the first/ leftmost/ most significant bit of the first
-- octet. This continues until the last bit of the CSN.1 bit string, which is placed in the last/
-- rightmost/ least significant bit of the last octet.
GSM-Classmark3 ::= OCTET STRING (SIZE (1..32))

GSM-MessageList ::= SEQUENCE (SIZE (1..maxInterSysMessages)) OF
                      BIT STRING (SIZE (1..512))

GsmSecurityCapability ::= BIT STRING {
    -- For each bit value "0" means false/ not supported
    a5-7(0),
    a5-6(1),
    a5-5(2),
    a5-4(3),
    a5-3(4),
    a5-2(5),
    a5-1(6)
} (SIZE (7))

GSM-TargetCellInfoList ::= SEQUENCE (SIZE (1..maxGSMTargetCells)) OF
                           GSM-TargetCellInfo

GSM-TargetCellInfo ::= SEQUENCE {
    bcch-ARFCN,
    frequency-band,
    bsic
} OPTIONAL

IdentificationOfReceivedMessage ::= SEQUENCE {
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    receivedMessageType           ReceivedMessageType
}

InterRAT-ChangeFailureCause ::= CHOICE {
    configurationUnacceptable   NULL,
    physicalChannelFailure     NULL,
    protocolError               ProtocolErrorInformation,
    unspecified                 NULL,
    spare4                     NULL,
    spare3                     NULL,
    spare2                     NULL,
    spare1                     NULL
}

GERANIu-MessageList ::= SEQUENCE (SIZE (1..maxInterSysMessages)) OF
                           BIT STRING (SIZE (1..32768))

GERANIu-RadioAccessCapability ::= BIT STRING (SIZE (1..170))

```

```

InterRAT-UE-RadioAccessCapability ::= CHOICE {
    gsm
        SEQUENCE {
            gsm-Classmark2
                GSM-Classmark2,
            gsm-Classmark3
                GSM-Classmark3
        },
    cdma2000
        SEQUENCE {
            cdma2000-MessageList
                CDMA2000-MessageList
        }
}

InterRAT-UE-RadioAccessCapabilityList ::= SEQUENCE (SIZE(1..maxInterSysMessages)) OF
                                         InterRAT-UE-RadioAccessCapability

InterRAT-UE-RadioAccessCapability-v590ext ::= SEQUENCE {
    geranIu-RadioAccessCapability      GERANIu-RadioAccessCapability
}

InterRAT-UE-SecurityCapability ::= CHOICE {
    gsm
        SEQUENCE {
            gsmSecurityCapability
                GsmSecurityCapability
        }
}

InterRAT-UE-SecurityCapList ::= SEQUENCE (SIZE(1..maxInterSysMessages)) OF
                                         InterRAT-UE-SecurityCapability

InterRAT-HO-FailureCause ::= CHOICE {
    configurationUnacceptable
        NULL,
    physicalChannelFailure
        NULL,
    protocolError
        ProtocolErrorInformation,
    interRAT-ProtocolError
        NULL,
    unspecified
        NULL,
    spare11
        NULL,
    spare10
        NULL,
    spare9
        NULL,
    spare8
        NULL,
    spare7
        NULL,
    spare6
        NULL,
    spare5
        NULL,
    spare4
        NULL,
    spare3
        NULL,
    spare2
        NULL,
    spare1
        NULL
}

MasterInformationBlock ::= SEQUENCE {
    mib-ValueTag
        MIB-ValueTag,
    -- TABULAR: The PLMN identity and ANSI-41 core network information
    -- are included in PLMN-Type.
    plmn-Type
        PLMN-Type,
    sibSb-ReferenceList
        SIBSb-ReferenceList,
    -- Extension mechanism for non- release99 information
    v6xyNonCriticalExtensions
        SEQUENCE {
            masterInformationBlock-v6xyext      MasterInformationBlock-v6xyext
            nonCriticalExtensions
                SEQUENCE {}                      OPTIONAL,
        }                                     OPTIONAL
}

MasterInformationBlock-v6xyext ::= SEQUENCE {
    multiplePLMN-List
        MultiplePLMN-List-r6
}

MIB-ValueTag ::= INTEGER (1..8)

NCC ::= INTEGER (0..7)

PLMN-ValueTag ::= INTEGER (1..256)

PredefinedConfigIdentityAndValueTag ::= SEQUENCE {
    predefinedConfigIdentity
        PredefinedConfigIdentity,
    predefinedConfigValueTag
        PredefinedConfigValueTag
}

ProtocolErrorInformation ::= SEQUENCE {
    diagnosticsType
        CHOICE {
            type1
                SEQUENCE {

```

```

    protocolErrorCause
  },
  spare
}
}

ReceivedMessageType ::=

  ENUMERATED {
    activeSetUpdate,
    cellChangeOrderFromUTRAN,
    cellUpdateConfirm,
    counterCheck,
    downlinkDirectTransfer,
    interRATHandoverCommand,
    measurementControl,
    pagingType2,
    physicalChannelReconfiguration,
    physicalSharedChannelAllocation,
    radioBearerReconfiguration,
    radioBearerRelease,
    radioBearerSetup,
    rrcConnectionRelease,
    rrcConnectionReject,
    rrcConnectionSetup,
    securityModeCommand,
    signallingConnectionRelease,
    transportChannelReconfiguration,
    transportFormatCombinationControl,
    ueCapabilityEnquiry,
    ueCapabilityInformationConfirm,
    uplinkPhysicalChannelControl,
    uraUpdateConfirm,
    utranMobilityInformation,
    assistanceDataDelivery,
    spare6, spare5, spare4, spare3, spare2,
    spare1
  }

Rplmn-Information ::=

  SEQUENCE {
    gsm-BA-Range-List      GSM-BA-Range-List   OPTIONAL,
    fdd-UMTS-Frequency-List FDD-UMTS-Frequency-List
  OPTIONAL,
  tdd-UMTS-Frequency-List TDD-UMTS-Frequency-List
  OPTIONAL,
  cdma2000-UMTS-Frequency-List CDMA2000-UMTS-Frequency-
List  OPTIONAL
}

Rplmn-Information-r4 ::=

  SEQUENCE {
    gsm-BA-Range-List      GSM-BA-Range-List   OPTIONAL,
    fdd-UMTS-Frequency-List FDD-UMTS-Frequency-List
  OPTIONAL,
    tdd384-UMTS-Frequency-List TDD-UMTS-Frequency-List
  OPTIONAL,
    tdd128-UMTS-Frequency-List TDD-UMTS-Frequency-List
  OPTIONAL,
    cdma2000-UMTS-Frequency-List CDMA2000-UMTS-Frequency-List
  }

SchedulingInformation ::=

  SEQUENCE {
    scheduling
      SEQUENCE {
        segCount
          SegCount
          DEFAULT 1,
        sib-Pos
          CHOICE {
            -- The element name indicates the repetition period and the value
            -- (multiplied by two) indicates the position of the first segment.
            rep4
              INTEGER (0..1),
            rep8
              INTEGER (0..3),
            rep16
              INTEGER (0..7),
            rep32
              INTEGER (0..15),
            rep64
              INTEGER (0..31),
            rep128
              INTEGER (0..63),
            rep256
              INTEGER (0..127),
            rep512
              INTEGER (0..255),
            rep1024
              INTEGER (0..511),
            rep2048
              INTEGER (0..1023),
            rep4096
              INTEGER (0..2047)
          },
        sib-PosOffsetInfo
          SibOFF-List
          OPTIONAL
      }
  }

SchedulingInformationSIB ::=

  SEQUENCE {

```

```

sib-Type
  scheduling
}

SchedulingInformationSIBSb ::=          SIB-TypeAndTag,
                                         SchedulingInformation
{
  sibSb-Type
  scheduling
}

SegCount ::=                         INTEGER (1..16)

SegmentIndex ::=                      INTEGER (1..15)

-- Actual value SFN-Prime = 2 * IE value
SFN-Prime ::=                         INTEGER (0..2047)

SIB-Data-fixed ::=                   BIT STRING (SIZE (222))

SIB-Data-variable ::=                BIT STRING (SIZE (1..214))

SIBOccurIdentity ::=                INTEGER (0..15)

SIBOccurrenceIdentityAndValueTag ::= SEQUENCE {
  sibOccurIdentity
  sibOccurValueTag
}

SIBOccurValueTag ::=                 INTEGER (0..15)

SIB-ReferenceList ::=                SEQUENCE (SIZE (1..maxSIB)) OF
                                         SchedulingInformationSIB

SIBSb-ReferenceList ::=              SEQUENCE (SIZE (1..maxSIB)) OF
                                         SchedulingInformationSIBSb

SIB-ReferenceListFACH ::=            SEQUENCE (SIZE (1..maxSIB-FACH)) OF
                                         SchedulingInformationSIB

SIB-Type ::=                         ENUMERATED {
  masterInformationBlock,
  systemInformationBlockType1,
  systemInformationBlockType2,
  systemInformationBlockType3,
  systemInformationBlockType4,
  systemInformationBlockType5,
  systemInformationBlockType6,
  systemInformationBlockType7,
  systemInformationBlockType8,
  systemInformationBlockType9,
  systemInformationBlockType10,
  systemInformationBlockType11,
  systemInformationBlockType12,
  systemInformationBlockType13,
  systemInformationBlockType13-1,
  systemInformationBlockType13-2,
  systemInformationBlockType13-3,
  systemInformationBlockType13-4,
  systemInformationBlockType14,
  systemInformationBlockType15,
  systemInformationBlockType15-1,
  systemInformationBlockType15-2,
  systemInformationBlockType15-3,
  systemInformationBlockType16,
  systemInformationBlockType17,
  systemInformationBlockType15-4,
  systemInformationBlockType18,
  schedulingBlock1,
  schedulingBlock2,
  systemInformationBlockType15-5,
  systemInformationBlockType5bis,
  spare1
}

SIB-TypeAndTag ::=                  CHOICE {
  sysInfoType1
  sysInfoType2
  sysInfoType3
  sysInfoType4
}

```

```

sysInfoType4           CellValueTag,
sysInfoType5           CellValueTag,
sysInfoType6           CellValueTag,
sysInfoType7           NULL,
sysInfoType8           CellValueTag,
sysInfoType9           NULL,
sysInfoType10          NULL,
sysInfoType11          CellValueTag,
sysInfoType12          CellValueTag,
sysInfoType13          CellValueTag,
sysInfoType13-1         CellValueTag,
sysInfoType13-2         CellValueTag,
sysInfoType13-3         CellValueTag,
sysInfoType13-4         CellValueTag,
sysInfoType14          NULL,
sysInfoType15          CellValueTag,
sysInfoType16          PredefinedConfigIdentityAndValueTag,
sysInfoType17          NULL,
sysInfoType15-1         CellValueTag,
sysInfoType15-2         SIBOccurrenceIdentityAndValueTag,
sysInfoType15-3         SIBOccurrenceIdentityAndValueTag,
sysInfoType15-4         CellValueTag,
sysInfoType18          CellValueTag,
sysInfoType15-5         CellValueTag,
sysInfoType5bis        CellValueTag,
spare4                NULL,
spare3                NULL,
spare2                NULL,
spare1                NULL
}

SIBSb-TypeAndTag ::= CHOICE {
    sysInfoType1   PLMN-ValueTag,
    sysInfoType2   CellValueTag,
    sysInfoType3   CellValueTag,
    sysInfoType4   CellValueTag,
    sysInfoType5   CellValueTag,
    sysInfoType6   CellValueTag,
    sysInfoType7   NULL,
    sysInfoType8   CellValueTag,
    sysInfoType9   NULL,
    sysInfoType10  NULL,
    sysInfoType11  CellValueTag,
    sysInfoType12  CellValueTag,
    sysInfoType13  CellValueTag,
    sysInfoType13-1 CellValueTag,
    sysInfoType13-2 CellValueTag,
    sysInfoType13-3 CellValueTag,
    sysInfoType13-4 CellValueTag,
    sysInfoType14  NULL,
    sysInfoType15  CellValueTag,
    sysInfoType16  PredefinedConfigIdentityAndValueTag,
    sysInfoType17  NULL,
    sysInfoTypeSB1 CellValueTag,
    sysInfoTypeSB2 CellValueTag,
    sysInfoType15-1 CellValueTag,
    sysInfoType15-2 SIBOccurrenceIdentityAndValueTag,
    sysInfoType15-3 SIBOccurrenceIdentityAndValueTag,
    sysInfoType15-4 CellValueTag,
    sysInfoType18  CellValueTag,
    sysInfoType15-5 CellValueTag,
    sysInfoType5bis CellValueTag,
    spare2        NULL,
    spare1        NULL
}

SibOFF ::= ENUMERATED {
    so2, so4, so6, so8, so10,
    so12, so14, so16, so18,
    so20, so22, so24, so26,
    so28, so30, so32 }

SibOFF-List ::= SEQUENCE (SIZE (1..15)) OF
                  SibOFF

SysInfoType1 ::= SEQUENCE {
    -- Core network IEs
    cn-CommonGSM-MAP-NAS-SysInfo      NAS-SystemInformationGSM-MAP,

```

```

cn-DomainSysInfoList           CN-DomainSysInfoList,
-- User equipment IEs
    ue-ConnTimersAndConstants   UE-ConnTimersAndConstants           OPTIONAL,
    ue-IDleTimersAndConstants   UE-IDleTimersAndConstants           OPTIONAL,
-- Extension mechanism for non- release99 information
    v3a0NonCriticalExtensions  SEQUENCE {
        sysInfoType1-v3a0ext     SysInfoType1-v3a0ext-IEs,
        nonCriticalExtensions   SEQUENCE {} OPTIONAL
    }
}                               OPTIONAL

SysInfoType1-v3a0ext-IEs ::= SEQUENCE {
    ue-ConnTimersAndConstants-v3a0ext   UE-ConnTimersAndConstants-v3a0ext,
    ue-IDleTimersAndConstants-v3a0ext   UE-IDleTimersAndConstants-v3a0ext
}

SysInfoType2 ::=          SEQUENCE {
    -- UTRAN mobility IEs
        ura-IdentityList       URA-IdentityList,
    -- Extension mechanism for non- release99 information
        nonCriticalExtensions  SEQUENCE {}           OPTIONAL
}

SysInfoType3 ::=          SEQUENCE {
    sib4Indicator            BOOLEAN,
    -- UTRAN mobility IEs
        cellIdentity          CellIdentity,
        cellSelectReselectInfo CellSelectReselectInfoSIB-3-4,
        cellAccessRestriction  CellAccessRestriction,
    -- Extension mechanism for non- release99 information
        v4b0NonCriticalExtensions  SEQUENCE {
            sysInfoType3-v4b0ext   SysInfoType3-v4b0ext-IEs,
            v590NonCriticalExtension SEQUENCE {
                sysInfoType3-v590ext   SysInfoType3-v590ext,
                nonCriticalExtensions SEQUENCE {}           OPTIONAL
            }
        }
}                               OPTIONAL

SysInfoType3-v4b0ext-IEs ::= SEQUENCE {
    mapping-LCR               Mapping-LCR-r4           OPTIONAL
}

SysInfoType3-v590ext ::= SEQUENCE {
    cellSelectReselectInfo-v590ext   CellSelectReselectInfo-v590ext           OPTIONAL
}

SysInfoType4 ::=          SEQUENCE {
    -- UTRAN mobility IEs
        cellIdentity          CellIdentity,
        cellSelectReselectInfo CellSelectReselectInfoSIB-3-4,
        cellAccessRestriction  CellAccessRestriction,
    -- Extension mechanism for non- release99 information
        v4b0NonCriticalExtensions  SEQUENCE {
            sysInfoType4-v4b0ext   SysInfoType4-v4b0ext-IEs,
            v590NonCriticalExtension SEQUENCE {
                sysInfoType4-v590ext   SysInfoType4-v590ext,
                v5b0NonCriticalExtension SEQUENCE {
                    sysInfoType4-v5b0ext   SysInfoType4-v5b0ext-IEs,
                    nonCriticalExtensions SEQUENCE {}           OPTIONAL
                }
            }
        }
}                               OPTIONAL

SysInfoType4-v4b0ext-IEs ::= SEQUENCE {
    mapping-LCR               Mapping-LCR-r4           OPTIONAL
}

SysInfoType4-v590ext ::= SEQUENCE {
    cellSelectReselectInfo-v590ext   CellSelectReselectInfo-v590ext           OPTIONAL
}

SysInfoType4-v5b0ext-IEs ::= SEQUENCE {
    cellSelectReselectInfoPCHFACH-v5b0ext   CellSelectReselectInfoPCHFACH-v5b0ext           OPTIONAL
}

```

```

SysInfoType5 ::= SEQUENCE {
    sib6Indicator BOOLEAN,
    -- Physical channel IEs
    pich-PowerOffset PICH-PowerOffset,
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            aich-PowerOffset AICH-PowerOffset
        },
        tdd SEQUENCE {
        }
    },
    -- If PDSCH/PUSCH is configured for 1.28Mcps TDD, the following IEs should be absent
    -- and the info included in the tdd128SpecificInfo instead.
    -- If PDSCH/PUSCH is configured for 3.84Mcps TDD in R5, HCR-r5-SpecificInfo should also be
    -- included.
    pusch-SysInfoList-SFN PUSCH-SysInfoList-SFN OPTIONAL,
    pdsch-SysInfoList-SFN PDSCH-SysInfoList-SFN OPTIONAL,
    openLoopPowerControl-TDD OpenLoopPowerControl-TDD
},
primaryCCPCH-Info PrimaryCCPCH-Info OPTIONAL,
prach-SystemInformationList PRACH-SystemInformationList,
sCCPCH-SystemInformationList SCCPCH-SystemInformationList,
-- cbs-DRX-Level1Information is conditional on any of the CTCH indicator IEs in
-- sCCPCH-SystemInformationList
cbs-DRX-Level1Information CBS-DRX-Level1Information OPTIONAL,
-- Extension mechanism for non- release99 information
v4b0NonCriticalExtensions SEQUENCE {
    sysInfoType5-v4b0ext SysInfoType5-v4b0ext-IES OPTIONAL,
-- Extension mechanism for non- rel-4 information
    v590NonCriticalExtensions SEQUENCE {
        sysInfoType5-v590ext SysInfoType5-v590ext-IES OPTIONAL,
        v6xyNonCriticalExtensions SEQUENCE {
            sysInfoType5-v6xyext SysInfoType5-v6xyext-IES,
            nonCriticalExtensions SEQUENCE {} OPTIONAL
        } OPTIONAL
    } OPTIONAL
} OPTIONAL
}

SysInfoType5-v4b0ext-IES ::= SEQUENCE {
    --The following IE PNBSCH-Allocation-r4 shall be used for 3.84Mcps TDD only.
    pnBSCH-Allocation-r4 PNBSCH-Allocation-r4 OPTIONAL,
    -- In case of TDD, the following IE is included instead of the
    -- IE up-IPDL-Parameter in up-OTDOA-AssistanceData.
    openLoopPowerControl-IPDL-TDD OpenLoopPowerControl-IPDL-TDD-r4 OPTIONAL,
-- If SysInfoType5 is sent to describe a 1.28Mcps TDD cell, the IE PRACH-RACH-Info included in
-- PRACH-SystemInformationList shall be ignored, the IE PRACH-Partitioning and the
-- IE rach-TransportFormatSet shall be absent and the corresponding IE in the following
-- PRACH-SystemInformationList-LCR-r4 shall be used
    prach-SystemInformationList-LCR-r4 PRACH-SystemInformationList-LCR-r4 OPTIONAL,
    tdd128SpecificInfo SEQUENCE {
        pusch-SysInfoList-SFN PUSCH-SysInfoList-SFN-LCR-r4 OPTIONAL,
        pdsch-SysInfoList-SFN PDSCH-SysInfoList-SFN-LCR-r4 OPTIONAL,
        pCCPCH-LCR-Extensions PrimaryCCPCH-Info-LCR-r4-ext OPTIONAL,
        sCCPCH-LCR-ExtensionsList SCCPCH-SystemInformationList-LCR-r4-ext
    } OPTIONAL,
    frequencyBandIndicator RadioFrequencyBandFDD OPTIONAL
}

SysInfoType5-v590ext-IES ::= SEQUENCE {
    hcr-r5-SpecificInfo SEQUENCE {
        pusch-SysInfoList-SFN PUSCH-SysInfoList-SFN-HCR-r5 OPTIONAL,
        pdsch-SysInfoList-SFN PDSCH-SysInfoList-SFN-HCR-r5 OPTIONAL
    } OPTIONAL
}

SysInfoType5-v6xyext-IES ::= SEQUENCE {
    sccpch-SystemInformation-MBMS CHOICE {
        sccpch-CommonForMBMSAndNonMBMS SCCPCH-SystemInformationList-MBMS-r6-ext,
        sccpch-DedicatedForMBMS SCCPCH-SystemInformation-MBMS-r6
    } OPTIONAL
}

-- SysInfoType5bis uses the same structure as SysInfoType5
SysInfoType5bis ::= SysInfoType5

SysInfoType6 ::= SEQUENCE {
    -- Physical channel IEs
    pich-PowerOffset PICH-PowerOffset,
}

```

```

modeSpecificInfo          CHOICE {
  fdd                 SEQUENCE {
    aich-PowerOffset      AICH-PowerOffset,
    -- dummy is not used in this version of specification, it should
    -- not be sent and if received it should be ignored.
    dummy                CSICH-PowerOffset      OPTIONAL
  },
  tdd                 SEQUENCE {
    -- If PDSCH/PUSCH is configured for 1.28Mcps TDD, pusch-SysInfoList-SFN,
    -- pdsch-SysInfoList-SFN and openLoopPowerControl-TDD should be absent
    -- and the info included in the tdd128SpecificInfo instead.
    -- If PDSCH/PUSCH is configured for 3.84Mcps TDD in R5, HCR-r5-SpecificInfo should
    -- also be included.
    pusch-SysInfoList-SFN      PUSCH-SysInfoList-SFN      OPTIONAL,
    pdsch-SysInfoList-SFN      PDSCH-SysInfoList-SFN      OPTIONAL,
    openLoopPowerControl-TDD  OpenLoopPowerControl-TDD
  }
},
primaryCCPCH-Info        PrimaryCCPCH-Info      OPTIONAL,
prach-SystemInformationList PRACH-SystemInformationList OPTIONAL,
sCCPCH-SystemInformationList SCCPCH-SystemInformationList OPTIONAL,
cbs-DRX-Level1Information CBS-DRX-Level1Information OPTIONAL,
-- Conditional on any of the CTCH indicator IEs in
-- sCCPCH-SystemInformationList
-- Extension mechanism for non- release99 information
v4b0NonCriticalExtensions SEQUENCE {
  sysInfoType6-v4b0ext      SysInfoType6-v4b0ext-IES      OPTIONAL,
-- Extension mechanism for non- rel-4 information
  v590NonCriticalExtensions SEQUENCE {
    sysInfoType6-v590ext      SysInfoType6-v590ext-IES      OPTIONAL,
    nonCriticalExtensions    SEQUENCE {}
  }
}
},
SysInfoType6-v4b0ext-IES ::= SEQUENCE {
  -- openLoopPowerControl-IPDL-TDD is present only if IPDLs are applied for TDD
  openLoopPowerControl-IPDL-TDD  OpenLoopPowerControl-IPDL-TDD-r4      OPTIONAL,
  -- If SysInfoType6 is sent to describe a 1.28Mcps TDD cell, the IE PRACH-RACH-Info included
  -- in PRACH-SystemInformationList shall be ignored, the IE PRACH-Partitioning and the
  -- IE rach-TransportFormatSet shall be absent and the corresponding IEs in the following
  -- PRACH-SystemInformationList-LCR-r4 shall be used
  prach-SystemInformationList-LCR-r4  PRACH-SystemInformationList-LCR-r4  OPTIONAL,
  tdd128SpecificInfo          SEQUENCE {
    pusch-SysInfoList-SFN      PUSCH-SysInfoList-SFN-LCR-r4      OPTIONAL,
    pdsch-SysInfoList-SFN      PDSCH-SysInfoList-SFN-LCR-r4      OPTIONAL,
    pCCPCH-LCR-Extensions     PrimaryCCPCH-Info-LCR-r4-ext      OPTIONAL,
    sCCPCH-LCR-ExtensionsList SCCPCH-SystemInformationList-LCR-r4-ext OPTIONAL
  }
  frequencyBandIndicator      RadioFrequencyBandFDD      OPTIONAL
}
},
SysInfoType6-v590ext-IES ::= SEQUENCE {
  hcr-r5-SpecificInfo        SEQUENCE {
    pusch-SysInfoList-SFN      PUSCH-SysInfoList-SFN-HCR-r5      OPTIONAL,
    pdsch-SysInfoList-SFN      PDSCH-SysInfoList-SFN-HCR-r5      OPTIONAL
  }
}
},
SysInfoType7 ::=          SEQUENCE {
  -- Physical channel IEs
  modeSpecificInfo          CHOICE {
    fdd                 SEQUENCE {
      ul-Interference      UL-Interference
    },
    tdd                 NULL
  },
  prach-Information-SIB5-List DynamicPersistenceLevelList,
  prach-Information-SIB6-List DynamicPersistenceLevelList      OPTIONAL,
  expirationTimeFactor       ExpirationTimeFactor      OPTIONAL,
  -- Extension mechanism for non- release99 information
  nonCriticalExtensions     SEQUENCE {}      OPTIONAL
}
},
SysInfoType8 ::=          SEQUENCE {
  -- User equipment IEs
  cpch-Parameters           CPCH-Parameters,
  -- Physical channel IEs
}

```

```

cpch-SetInfoList          CPCH-SetInfoList,
csich-PowerOffset         CSICH-PowerOffset,
-- Extension mechanism for non- release99 information
nonCriticalExtensions     SEQUENCE {}
}                                         OPTIONAL

SysInfoType9 ::= SEQUENCE {
  -- Physical channel IEs
  cpch-PersistenceLevelsList   CPCH-PersistenceLevelsList,
  -- Extension mechanism for non- release99 information
  nonCriticalExtensions        SEQUENCE {}
}                                         OPTIONAL

SysInfoType10 ::= SEQUENCE {
  -- User equipment IEs
  drac-SysInfoList            DRAC-SysInfoList,
  -- Extension mechanism for non- release99 information
  nonCriticalExtensions        SEQUENCE {}
}                                         OPTIONAL

SysInfoType11 ::= SEQUENCE {
  sib12Indicator              BOOLEAN,
  -- Measurement IEs
  fach-MeasurementOccasionInfo FACH-MeasurementOccasionInfo      OPTIONAL,
  measurementControlSysInfo   MeasurementControlSysInfo,
  -- Extension mechanism for non- release99 information
  v4b0NonCriticalExtensions   SEQUENCE {
    sysInfoType11-v4b0ext       SysInfoType11-v4b0ext-IEs      OPTIONAL,
    v590NonCriticalExtension   SEQUENCE {
      sysInfoType11-v590ext     SysInfoType11-v590ext-IEs,
      nonCriticalExtensions     SEQUENCE {}                      OPTIONAL
    }                           OPTIONAL
  }                           OPTIONAL
}                                         OPTIONAL

SysInfoType11-v4b0ext-IEs ::= SEQUENCE {
  fach-MeasurementOccasionInfo-LCR-Ext  FACH-MeasurementOccasionInfo-LCR-r4-ext OPTIONAL,
  measurementControlSysInfo-LCR         MeasurementControlSysInfo-LCR-r4-ext
}

SysInfoType11-v590ext-IEs ::= SEQUENCE {
  --The order of the list corresponds to the order of cell in newIntraFrequencyCellInfoList
  newIntraFrequencyCellInfoList-v590ext  SEQUENCE (SIZE (1..maxCellMeas)) OF
    CellSelectReselectInfo-v590ext    OPTIONAL,
  --The order of the list corresponds to the order of cell in newInterFrequencyCellInfoList
  newInterFrequencyCellInfoList-v590ext SEQUENCE (SIZE (1..maxCellMeas)) OF
    CellSelectReselectInfo-v590ext    OPTIONAL,
  --The order of the list corresponds to the order of cell in newInterRATCellInfoList
  newInterRATCellInfoList-v590ext      SEQUENCE (SIZE (1..maxCellMeas)) OF
    CellSelectReselectInfo-v590ext    OPTIONAL,
  intraFreqEventCriteriaList-v590ext   Intra-FreqEventCriteriaList-v590ext  OPTIONAL,
  intraFreqReportingCriteria-1b-r5    IntraFreqReportingCriteria-1b-r5    OPTIONAL,
  intraFreqEvent-1d-r5                IntraFreqEvent-1d-r5                 OPTIONAL
}

SysInfoType12 ::= SEQUENCE {
  -- Measurement IEs
  fach-MeasurementOccasionInfo      FACH-MeasurementOccasionInfo      OPTIONAL,
  measurementControlSysInfo         MeasurementControlSysInfo,
  -- Extension mechanism for non- release99 information
  v4b0NonCriticalExtensions        SEQUENCE {
    sysInfoType12-v4b0ext          SysInfoType12-v4b0ext-IEs      OPTIONAL,
    v590NonCriticalExtension      SEQUENCE {
      sysInfoType12-v590ext        SysInfoType12-v590ext-IEs,
      nonCriticalExtensions       SEQUENCE {}                      OPTIONAL
    }                           OPTIONAL
  }                           OPTIONAL
}                                         OPTIONAL

SysInfoType12-v4b0ext-IEs ::= SEQUENCE {
  fach-MeasurementOccasionInfo-LCR-Ext  FACH-MeasurementOccasionInfo-LCR-r4-ext OPTIONAL,
  measurementControlSysInfo-LCR         MeasurementControlSysInfo-LCR-r4-ext
}

SysInfoType12-v590ext-IEs ::= SEQUENCE {
  --The order of the list corresponds to the order of cell in newIntraFrequencyCellInfoList
  newIntraFrequencyCellInfoList-v590ext SEQUENCE (SIZE (1..maxCellMeas)) OF
    CellSelectReselectInfo-v590ext  OPTIONAL,

```

```

--The order of the list corresponds to the order of cell in newInterFrequencyCellInfoList
newInterFrequencyCellInfoList-v590ext      SEQUENCE (SIZE (1..maxCellMeas)) OF
                                                CellSelectReselectInfo-v590ext    OPTIONAL,
--The order of the list corresponds to the order of cell in newInterRATCellInfoList
newInterRATCellInfoList-v590ext           SEQUENCE (SIZE (1..maxCellMeas)) OF
                                                CellSelectReselectInfo-v590ext    OPTIONAL,
                                                Intra-FreqEventCriteriaList-v590ext   OPTIONAL,
intraFreqEventCriteriaList-v590ext        IntraFreqReportingCriteria-1b-r5      OPTIONAL,
intraFreqReportingCriteria-1b-r5          intraFreqEvent-1d-r5                  OPTIONAL
}
}

SysInfoType13 ::=          SEQUENCE {
  -- Core network IEs
  cn-DomainSysInfoList            CN-DomainSysInfoList,
  -- User equipment IEs
  ue-IDLETimersAndConstants       UE-IDLETimersAndConstants           OPTIONAL,
  capabilityUpdateRequirement     CapabilityUpdateRequirement           OPTIONAL,
  -- Extension mechanism for non- release99 information
  v3a0NonCriticalExtensions      SEQUENCE {
    sysInfoType13-v3a0ext         SysInfoType13-v3a0ext-IEs,
    v4b0NonCriticalExtensions     SEQUENCE {
      sysInfoType13-v4b0ext       SysInfoType13-v4b0ext-IEs,
      -- Extension mechanism for non- release99 information
      nonCriticalExtensions      SEQUENCE {}           OPTIONAL
    }
  }
}

SysInfoType13-v3a0ext-IEs ::= SEQUENCE {
  ue-IDLETimersAndConstants-v3a0ext      UE-IDLETimersAndConstants-v3a0ext
}

SysInfoType13-v4b0ext-IEs ::= SEQUENCE {
  capabilityUpdateRequirement-r4Ext     CapabilityUpdateRequirement-r4-ext  OPTIONAL
}

SysInfoType13-1 ::=          SEQUENCE {
  -- ANSI-41 IEs
  ansi-41-RAND-Information          ANSI-41-RAND-Information,
  -- Extension mechanism for non- release99 information
  nonCriticalExtensions            SEQUENCE {}           OPTIONAL
}

SysInfoType13-2 ::=          SEQUENCE {
  -- ANSI-41 IEs
  ansi-41-UserZoneID-Information    ANSI-41-UserZoneID-Information,
  -- Extension mechanism for non- release99 information
  nonCriticalExtensions            SEQUENCE {}           OPTIONAL
}

SysInfoType13-3 ::=          SEQUENCE {
  -- ANSI-41 IEs
  ansi-41-PrivateNeighbourListInfo  ANSI-41-PrivateNeighbourListInfo,
  -- Extension mechanism for non- release99 information
  nonCriticalExtensions            SEQUENCE {}           OPTIONAL
}

SysInfoType13-4 ::=          SEQUENCE {
  -- ANSI-41 IEs
  ansi-41-GlobalServiceRedirectInfo ANSI-41-GlobalServiceRedirectInfo,
  -- Extension mechanism for non- release99 information
  nonCriticalExtensions            SEQUENCE {}           OPTIONAL
}

SysInfoType14 ::=          SEQUENCE {
  -- Physical channel IEs
  individualTS-InterferenceList    IndividualTS-InterferenceList,
  expirationTimeFactor             ExpirationTimeFactor           OPTIONAL,
  -- Extension mechanism for non- release99 information
  nonCriticalExtensions            SEQUENCE {}           OPTIONAL
}

SysInfoType15 ::=          SEQUENCE {
  -- Measurement IEs
  ue-positioning-GPS-CipherParameters  UE-Positioning-CipherParameters   OPTIONAL,
  ue-positioning-GPS-ReferenceLocation ReferenceLocation,
}

```

```

ue-positioning-GPS-ReferenceTime           UE-Positioning-GPS-ReferenceTime,
                                         BadSatList                               OPTIONAL,
-- Extension mechanism for non- release99 information
v4b0NonCriticalExtensions      SEQUENCE {
    sysInfoType15-v4b0ext          SysInfoType15-v4b0ext-IEs,
-- Extension mechanism for non- release4 information
    nonCriticalExtensions        SEQUENCE {}                                OPTIONAL
}   OPTIONAL
}

SysInfoType15-v4b0ext-IEs ::= SEQUENCE {
    up-Ipdl-Parameters-TDD          UE-Positioning-IPDL-Parameters-TDD-r4-ext   OPTIONAL
}

SysInfoType15-1 ::=           SEQUENCE {
    -- DGPS corrections
    ue-positioning-GPS-DGPS-Corrections     UE-Positioning-GPS-DGPS-Corrections,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions        SEQUENCE {}                                OPTIONAL
}

SysInfoType15-2 ::=           SEQUENCE {
    -- Ephemeris and clock corrections
    transmissionTOW                INTEGER (0..604799),
    satID                         SatID,
    ephemerisParameter            EphemericParameter,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions        SEQUENCE {}                                OPTIONAL
}

SysInfoType15-3 ::=           SEQUENCE {
    -- Almanac and other data
    transmissionTOW                INTEGER (0.. 604799),
    ue-positioning-GPS-Almanac       UE-Positioning-GPS-Almanac
} OPTIONAL,
    ue-positioning-GPS-IonosphericModel     UE-Positioning-GPS-IonosphericModel
OPTIONAL,
    ue-positioning-GPS-UTC-Model         UE-Positioning-GPS-UTC-Model
OPTIONAL,
    satMask                          BIT STRING (SIZE (1..32))   OPTIONAL,
    lsbTOW                           BIT STRING (SIZE (8))     OPTIONAL,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions        SEQUENCE {}                                OPTIONAL
}

SysInfoType15-4 ::=           SEQUENCE {
    -- Measurement IEs
    ue-positioning-OTDOA-CipherParameters  UE-Positioning-CipherParameters      OPTIONAL,
    ue-positioning-OTDOA-AssistanceData    UE-Positioning-OTDOA-AssistanceData,
    v3a0NonCriticalExtensions      SEQUENCE {
        sysInfoType15-4-v3a0ext          SysInfoType15-4-v3a0ext,
-- Extension mechanism for non- release99 information
        v4b0NonCriticalExtensions      SEQUENCE {
            sysInfoType15-4-v4b0ext          SysInfoType15-4-v4b0ext,
            nonCriticalExtensions        SEQUENCE {}                                OPTIONAL
        }   OPTIONAL
    }   OPTIONAL
}

SysInfoType15-4-v3a0ext ::= SEQUENCE {
    sfn-Offset-Validity             SFN-Offset-Validity      OPTIONAL
}

SysInfoType15-4-v4b0ext ::= SEQUENCE {
    ue-Positioning-OTDOA-AssistanceData-r4ext  UE-Positioning-OTDOA-AssistanceData-r4ext   OPTIONAL
}

SysInfoType15-5 ::=           SEQUENCE {
    -- Measurement IEs
    ue-positioning-OTDOA-AssistanceData-UEB    UE-Positioning-OTDOA-AssistanceData-UEB,
    v3a0NonCriticalExtensions      SEQUENCE {
        sysInfoType15-5-v3a0ext          SysInfoType15-5-v3a0ext,
-- Extension mechanism for non- release99 information
        nonCriticalExtensions        SEQUENCE {}                                OPTIONAL
    }   OPTIONAL
}

```

```

}

SysInfoType15-5-v3a0ext ::= SEQUENCE {
    sfn-Offset-Validity           SFN-Offset-Validity      OPTIONAL
}

SysInfoType16 ::= SEQUENCE {
    -- Radio bearer IEs
    preDefinedRadioConfiguration PreDefRadioConfiguration,
    -- Extension mechanism for non- release99 information
    nonCriticalExtensions       SEQUENCE {}                  OPTIONAL
}

SysInfoType17 ::= SEQUENCE {
    -- Physical channel IEs
    -- If PDSCH/PUSCH is configured for 1.28Mcps TDD, pusch-SysInfoList and
    -- pdsch-SysInfoList should be absent and the info included in the
    -- tdd128SpecificInfo instead.
    -- If PDSCH/PUSCH is configured for 3.84Mcps TDD in R5, HCR-r5-SpecificInfo should also be
    -- included.
    pusch-SysInfoList            PUSCH-SysInfoList        OPTIONAL,
    pdsch-SysInfoList            PDSCH-SysInfoList        OPTIONAL,
    -- Extension mechanism for non- release99 information
    v4b0NonCriticalExtensions   SEQUENCE {
        sysInfoType17-v4b0ext      SysInfoType17-v4b0ext-IEs,
        v590NonCriticalExtensions SEQUENCE {
            sysInfoType17-v590ext      SysInfoType17-v590ext-IEs        OPTIONAL,
            nonCriticalExtensions     SEQUENCE {}                      OPTIONAL
        }
    }
}

SysInfoType17-v4b0ext-IEs ::= SEQUENCE {
    tdd128SpecificInfo          SEQUENCE {
        pusch-SysInfoList        PUSCH-SysInfoList-LCR-r4        OPTIONAL,
        pdsch-SysInfoList        PDSCH-SysInfoList-LCR-r4        OPTIONAL
    }
}

SysInfoType17-v590ext-IEs ::= SEQUENCE {
    hcr-r5-SpecificInfo         SEQUENCE {
        pusch-SysInfoList        PUSCH-SysInfoList-HCR-r5        OPTIONAL,
        pdsch-SysInfoList        PDSCH-SysInfoList-HCR-r5        OPTIONAL
    }
}

SysInfoType18 ::= SEQUENCE {
    idleModePLMNIentities       PLMNIentitiesOfNeighbourCells  OPTIONAL,
    connectedModePLMNIentities  PLMNIentitiesOfNeighbourCells  OPTIONAL,
    -- Extension mechanism for non- release99 information
    nonCriticalExtensions       SEQUENCE {}                  OPTIONAL
}

SysInfoTypeSB1 ::= SEQUENCE {
    -- Other IEs
    sib-ReferenceList           SIB-ReferenceList,
    -- Extension mechanism for non- release99 information
    nonCriticalExtensions       SEQUENCE {}                  OPTIONAL
}

SysInfoTypeSB2 ::= SEQUENCE {
    -- Other IEs
    sib-ReferenceList           SIB-ReferenceList,
    -- Extension mechanism for non- release99 information
    nonCriticalExtensions       SEQUENCE {}                  OPTIONAL
}

TDD-UMTS-Frequency-List ::= SEQUENCE (SIZE (1..maxNumTDDFreqs)) OF
    FrequencyInfoTDD

-- ****
-- ANSI-41 INFORMATION ELEMENTS (10.3.9)
-- ****

ANSI-41-GlobalServiceRedirectInfo ::= ANSI-41-NAS-Parameter
ANSI-41-PrivateNeighbourListInfo ::= ANSI-41-NAS-Parameter

```

```

ANSI-41-RAND-Information ::=      ANSI-41-NAS-Parameter
ANSI-41-UserZoneID-Information ::=      ANSI-41-NAS-Parameter
ANSI-41-NAS-Parameter ::=          BIT STRING (SIZE (1..2048))

Min-P-REV ::=                  BIT STRING (SIZE (8))

NAS-SystemInformationANSI-41 ::=      ANSI-41-NAS-Parameter
NID ::=                      BIT STRING (SIZE (16))

P-REV ::=                  BIT STRING (SIZE (8))

SID ::=                  BIT STRING (SIZE (15))

-- ****
-- MBMS INFORMATION ELEMENTS (10.3.9a)
-- ****

MBMS-AccessProbabilityFactor ::=      ENUMERATED {
                                         apf0, apf32, apf64, apf96, apf128, apf160, apf192,
                                         apf224, apf256, apf288, apf320, apf352, apf384, apf416,
                                         apf448, apf480, apf512, apf544, apf576, apf608, apf640,
                                         apf672, apf704, apf736, apf768, apf800, apf832, apf864,
                                         apf896, apf928, apf960, apf1000 }

MBMS-CellGroupIdentity-r6 ::=      BIT STRING (SIZE (12))

MBMS-CommonCCTrChIdentity ::=      INTEGER (1..32)

MBMS-CommonPhyChIdentity ::=      INTEGER (1..32)

MBMS-CommonRBIdentity ::=      INTEGER (1..32)

MBMS-CommonTrChIdentity ::=      INTEGER (1..32)

MBMS-CommonRBInformation-r6 ::=      SEQUENCE {
                                         commonRBIdentity,
                                         pdcp-Info,
                                         rlc-Info
                                         }

MBMS-CommonRBInformationList-r6 ::= SEQUENCE (SIZE (1..maxMBMS-CommonRB)) OF
                                         MBMS-CommonRBInformation-r6

MBMS-CurrentCell-SCCPCH-r6 ::=      SEQUENCE {
                                         sccpchIdentity
                                         secondaryCCPCH-Info
                                         transpCh-InfoCommonForAllTrCh
                                         facchCarryingMTCH
                                         schedulingInfo
                                         facchCarryingMSCH
                                         mschConfigurationInfo
                                         }
                                         OPTIONAL
                                         }

MBMS-CurrentCell-SCCPCHList-r6 ::= SEQUENCE (SIZE (1..maxSCCPCH)) OF
                                         MBMS-CurrentCell-SCCPCH-r6

MBMS-SCCPCHIdentity ::=      INTEGER (1..maxSCCPCH)

MBMS-DefaultL1CombiningConfigInfo-r6 ::= SEQUENCE {
                                         mbms-L1CombiningSchedCycleLength      MBMS-L1CombiningSchedCycleLength
                                         }

MBMS-FACCHCarryingMTCH-Comm ::=      SEQUENCE {
                                         transpCh-Info
                                         rbInformation
                                         }

MBMS-FACCHCarryingMTCH-CommList ::= SEQUENCE (SIZE (1..maxTrChperSCCPCH)) OF
                                         MBMS-FACCHCarryingMTCH-Comm

MBMS-FACCHCarryingMTCH-Neighb ::=      SEQUENCE {
                                         transpCh-Info
                                         transpCh-CombiningStatus
                                         rbInformation
                                         }
                                         OPTIONAL
                                         }


```

```

MBMS-FACCHCarryingMTCH-NeighbList ::= SEQUENCE (SIZE (1..maxFACHPCH)) OF
                                         MBMS-FACCHCarryingMTCH-Neighb

MBMS-FACCHCarryingMTCH-SIB5 ::=      SEQUENCE {
    transpCh-Identity           INTEGER (1..maxFACHPCH),
    rbInformation                MBMS-RBInformation-SList
}

MBMS-FACCHCarryingMTCH-SIB5List ::= SEQUENCE (SIZE (1..maxTrChperSCCPCH)) OF
                                         MBMS-FACCHCarryingMTCH-SIB5

MBMS-FLCApPLICABILITYInfo-r6 ::=      SEQUENCE {
    mbms-FLCApPLICABILITY        ENUMERATED { false }                                OPTIONAL
}

MBMS-JoinedInformation-r6 ::=          SEQUENCE {
    p-TMSI                         P-TMSI-GSM-MAP                                OPTIONAL
}

MBMS-L1CombiningSchedCycleLength ::= ENUMERATED { spare1 } -- FFS
MBMS-L1CombiningSchedCycleOffset ::= ENUMERATED { spare1 } -- FFS

MBMS-L1CombiningSchedule ::=          SEQUENCE {
    layer1CombiningSchedCycleLength   MBMS-L1CombiningSchedCycleLength      OPTIONAL,
    layer1CombiningSchedCycleOffset   MBMS-L1CombiningSchedCycleOffset      OPTIONAL,
    layer1CombiningTransmTimeDiff     MBMS-L1CombiningTransmTimeDiff,
    mtch-L1CombiningperiodList       MBMS-MTCH-L1CombiningPeriodList
}

MBMS-L1CombiningTransmTimeDiff ::= ENUMERATED { spare1 } -- FFS

MBMS-L2Configuration ::=             CHOICE {
    sameAsCurrent                  MBMS-SCCPCHIdentity,
    different                      SEQUENCE {
        transpCh-InfoCommonForAllTrCh   MBMS-CommonCCTrChIdentity,
        facchCarryingMTCH              MBMS-FACCHCarryingMTCH-NeighbList,
        schedulingInfo                 SEQUENCE {
            facchCarryingMSCH           MBMS-CommonTrChIdentity,
            mschConfigurationInfo       MBMS-MSCHConfigurationInfo-r6
        }                                OPTIONAL
    }
}

MBMS-LogicalChIdentity ::=          INTEGER (1..16)

MBMS-MCCH-ConfigurationInfo-r6 ::= SEQUENCE {
    accessInfoPeriod               INTEGER (1),      -- FFS
    repetitionPeriod                INTEGER (1),      -- FFS
    modificationPeriod              INTEGER (1),      -- FFS
    rlc-Info                        RLC-Info-r6
}

MBMS-MICHConfigurationInfo-r6 ::= SEQUENCE {
    michPowerOffset                 MBMS-MICHPowerOffset,
    mode                            CHOICE {
        fdd                            SEQUENCE {
            channelisationCode256       ChannelisationCode256,
            ni-CountPerFrame           MBMS-NI-CountPerFrame,
            stdt-Indicator              BOOLEAN
        },
        tdd384                          SEQUENCE {
            timeslot                   TimeslotNumber,
            midambleShiftAndBurstType  MidambleShiftAndBurstType,
            channelisationCode          DL-TS-ChannelisationCode,
            repetitionPeriodLengthOffset RepPerLengthOffset-MICH      OPTIONAL,
            mbmsNotificationIndLength   MBMS-MICHNotificationIndLength DEFAULT mn4
        },
        tdd128                          SEQUENCE {
            timeslot                   TimeslotNumber-LCR-r4,
            midambleShiftAndBurstType  MidambleShiftAndBurstType-LCR-r4,
            channelisationCodeList      SEQUENCE (SIZE (1..2)) OF
                                         DL-TS-ChannelisationCode,
                                         RepPerLengthOffset-MICH      OPTIONAL,
                                         MBMS-MICHNotificationIndLength DEFAULT mn4
        }
    }
}

```

```

}

MBMS-MICHNotificationIndLength ::= ENUMERATED { mn4, mn8, mn16 }

MBMS-MICHPowerOffset ::= INTEGER (-10..5)

MBMS-ModifiedService-r6 ::= SEQUENCE {
    mbms-TransmissionIdentity,
    mbms-RequiredUEAction,
    mbms-PreferredFrequency
        mcch
        dcch
    } OPTIONAL,
    continueMCCHReading
} BOOLEAN

MBMS-ModifiedServiceList-r6 ::= SEQUENCE (SIZE (1..maxMBMSservModif)) OF
    MBMS-ModifiedService-r6

MBMS-MTCH-L1CombiningPeriod ::= SEQUENCE {
    start
    duration
}
SEQUENCE (SIZE (1..maxMBMS-L1CP)) OF
    MBMS-MTCH-L1CombiningPeriod

MBMS-MSCHConfigurationInfo-r6 ::= SEQUENCE {
    mschSchedulingInfo
    rlc-Info
}
OPTIONAL,
OPTIONAL

MBMS-MSCHSchedulingInfo ::= CHOICE {
    schedulingPeriod-32-Offset
    schedulingPeriod-64-Offset
    schedulingPeriod-128-Offset
    schedulingPeriod-256-Offset
    schedulingPeriod-512-Offset
    schedulingPeriod-1024-Offset
}
INTEGER (0..31),
INTEGER (0..63),
INTEGER (0..127),
INTEGER (0..255),
INTEGER (0..511),
INTEGER (0..1023)

MBMS-NeighbouringCellSCCPCH-r6 ::= SEQUENCE {
    secondaryCCPCH-Info
    combiningMethod
        fullL1Combining
        currentCellsCCPCH
        typeOfL1Combining
    },
    otherCombining
        mbms-L1CombSchedule
        mbms-L2Configuration
}
SEQUENCE {
    MBMS-L1CombiningSchedule
    MBMS-L2Configuration
}
OPTIONAL,

MBMS-NeighbouringCellSCCPCHList-r6 ::= SEQUENCE (SIZE (1..maxSCCPCH)) OF
    MBMS-NeighbouringCellSCCPCH-r6

MBMS-NI-CountPerFrame ::= ENUMERATED { ni18, ni36, ni72, ni144 }

MBMS-PFLIndex ::= INTEGER (1..maxMBMS-Freq)

MBMS-PFLInfo ::= FrequencyInfo

MBMS-PhyChInformation-r6 ::= SEQUENCE {
    mbms-CommonPhyChIdentity,
    SecondaryCCPCHInfo-MBMS
}
SEQUENCE {
    MBMS-CommonPhyChIdentity,
    SecondaryCCPCHInfo-MBMS-r6
}

MBMS-PhyChInformationList-r6 ::= SEQUENCE (SIZE (1..maxMBMS-CommonPhyCh)) OF
    MBMS-PhyChInformation-r6

MBMS-PreferredFreqRequest-r6 ::= SEQUENCE {
    dl-UARFCN
}
SEQUENCE {
    UARFCN
}

MBMS-PreferredFrequencyInfo-r6 ::= SEQUENCE {
    mbmsPreferredFrequency
        INTEGER (1..maxMBMS-Freq),
}
SEQUENCE {
    INTEGER (1..maxMBMS-Freq),
}

```

```

layerConvergenceInformation      SEQUENCE {
    mbms-Qoffset                INTEGER (0..7),
    mbms-HCSoftset               INTEGER (0..7)
}

MBMS-PreferredFrequencyList-r6 ::= SEQUENCE (SIZE (1..maxMBMS-Freq)) OF
                                MBMS-PreferredFrequencyInfo-r6

MBMS-RBInformation-C ::=      SEQUENCE {
    rbInformation                MBMS-CommonRBIdentity,
    shortTransmissionID          MBMS-ShortTransmissionID,
    logicalChIdentity             MBMS-LogicalChIdentity,
    layer1-CombiningStatus       BOOLEAN
}

MBMS-RBInformation-CList ::=   SEQUENCE (SIZE (1..maxRBperTrCh)) OF
                                MBMS-RBInformation-C

MBMS-RBInformation-N ::=      SEQUENCE {
    shortTransmissionID          MBMS-ShortTransmissionID,
    logicalChIdentity             MBMS-LogicalChIdentity,
    layer1-CombiningStatus       BOOLEAN
}

MBMS-RBInformation-NList ::=   SEQUENCE (SIZE (1..maxRBperTrCh)) OF
                                MBMS-RBInformation-N

MBMS-RBInformation-S ::=      SEQUENCE {
    rbInformation                MBMS-CommonRBIdentity,
    shortTransmissionID          MBMS-ShortTransmissionID,
    logicalChIdentity             MBMS-LogicalChIdentity
}

MBMS-RBInformation-SList ::=   SEQUENCE (SIZE (1..maxRBperTrCh)) OF
                                MBMS-RBInformation-S

MBMS-RequiredUEAction ::=     ENUMERATED {
    none,
    acquireCountingInfo,
    acquirePTM-RBInfo,
    establishPMMConnection,
    releasePTM-RB,
    acquireMCCH
}

MBMS-ServiceAccessInfo-r6 ::=  SEQUENCE {
    shortTransmissionID          MBMS-ShortTransmissionID,
    accessprobabilityFactor-Idle  MBMS-AccessProbabilityFactor,
    accessprobabilityFactor-UraPCH MBMS-AccessProbabilityFactor OPTIONAL
}

MBMS-ServiceAccessInfoList-r6 ::= SEQUENCE (SIZE (1..maxMBMSServCount)) OF
                                MBMS-ServiceAccessInfo-r6

MBMS-ServiceIdentity ::=       SEQUENCE {
    plmn-Identity                PLMN-Identity OPTIONAL,
    serviceIdentity               OCTET STRING (SIZE (3))
}

MBMS-ServiceSchedulingInfo-r6 ::= SEQUENCE {
    mbms-ServiceIdentity          MBMS-ServiceIdentity,
    mbms-ServiceTransmInfoList    MBMS-ServiceTransmInfoList OPTIONAL,
    nextSchedulingperiod          INTEGER (1..32)
}

MBMS-ServiceSchedulingInfoList-r6 ::= SEQUENCE (SIZE (1..maxMBMSServSched)) OF
                                         MBMS-ServiceSchedulingInfo-r6

MBMS-ServiceTransmInfo ::=     SEQUENCE {
    start                        INTEGER (1),      -- FFS
    duration                      INTEGER (1)       -- FFS
}

MBMS-ServiceTransmInfoList ::=  SEQUENCE (SIZE (1..maxMBMSTransmis)) OF
                                MBMS-ServiceTransmInfo

MBMS-SessionIdentity ::=      OCTET STRING (SIZE (1))

```

```

MBMS-ShortTransmissionID ::= INTEGER (1..32)

MBMS-SIBType5-SCCPCH-r6 ::= SEQUENCE {
    sccpchIdentity,
    facchCarryingMTCH,
    schedulingInfo {
        facchCarryingMSCH,
        mschConfigurationInfo
    } OPTIONAL
}

MBMS-SIBType5-SCCPCHList-r6 ::= SEQUENCE (SIZE (1..maxSCCPCH)) OF
    MBMS-SIBType5-SCCPCH-r6

MBMS-TimersAndCounters-r6 ::= SEQUENCE {
    t-318
} DEFAULT ms1000

MBMS-TransmissionIdentity ::= SEQUENCE {
    mbms-ServiceIdentity,
    mbms-SessionIdentity
} OPTIONAL

MBMS-TranspChInfoForCCTrCh-r6 ::= SEQUENCE {
    commonCCTrChIdentity,
    transportFormatCombinationSet
}

MBMS-TranspChInfoForEachCCTrCh-r6 ::= SEQUENCE (SIZE (1..maxMBMS-CommonCCTrCh)) OF
    MBMS-TranspChInfoForCCTrCh-r6

MBMS-TranspChInfoForEachTrCh-r6 ::= SEQUENCE (SIZE (1..maxMBMS-CommonTrCh)) OF
    MBMS-TranspChInfoForTrCh-r6

MBMS-TranspChInfoForTrCh-r6 ::= SEQUENCE {
    commonTrChIdentity,
    transportFormatSet
}

MBMS-TypeOfL1Combining ::= ENUMERATED { rake, soft }

MBMS-UnmodifiedService-r6 ::= SEQUENCE {
    mbms-TransmissionIdentity,
    mbms-RequiredUEAction,
    mbms-PreferredFrequency
} OPTIONAL

MBMS-UnmodifiedServiceList-r6 ::= SEQUENCE (SIZE (1..maxMBMSservUnmodif)) OF
    MBMS-UnmodifiedService-r6

END

```

11.4 Constant definitions

Constant-definitions DEFINITIONS AUTOMATIC TAGS ::=

BEGIN

hiPDSCHidentities	INTEGER ::= 64
hiPUSCHidentities	INTEGER ::= 64
hiRM	INTEGER ::= 256
maxAC	INTEGER ::= 16
maxAdditionalMeas	INTEGER ::= 4
maxASC	INTEGER ::= 8
maxASCMmap	INTEGER ::= 7
maxASCPersist	INTEGER ::= 6
maxCCTrCH	INTEGER ::= 8
maxCellMeas	INTEGER ::= 32
maxCellMeas-1	INTEGER ::= 31
maxCNdomains	INTEGER ::= 4
maxCPCHsets	INTEGER ::= 16
maxDPCH-DLchan	INTEGER ::= 8
maxDPDCH-UL	INTEGER ::= 6
maxDRAcclasses	INTEGER ::= 8
<u>maxE-DCHMACdFlow</u>	<u>INTEGER ::= 1 -- FFS</u>
<u>maxE-DCHMACdFlow-1</u>	<u>INTEGER ::= 0 -- FFS</u>
maxFACHPCH	INTEGER ::= 8

```

maxFreq                      INTEGER ::= 8
maxFreqBandsFDD              INTEGER ::= 8
maxFreqBandsTDD              INTEGER ::= 4
maxFreqBandsGSM              INTEGER ::= 16
maxGERAN-SI                  INTEGER ::= 8
maxGSMTargetCells            INTEGER ::= 32
| maxHarqRTT                INTEGER ::= 1    -- FFS
maxHPprocesses               INTEGER ::= 8
maxHSDSCHTBIndex             INTEGER ::= 64
maxHSDSCHTBIndex-tdd384      INTEGER ::= 512
maxHSSCHs                     INTEGER ::= 4
maxInterSysMessages           INTEGER ::= 4
maxLoCHperRLC                INTEGER ::= 2
maxMAC-d-PDUsizes            INTEGER ::= 8
maxMBMS-CommonCCTrCh         INTEGER ::= 32
maxMBMS-CommonPhyCh          INTEGER ::= 32
maxMBMS-CommonRB              INTEGER ::= 32
maxMBMS-CommonTrCh           INTEGER ::= 32
maxMBMS-Freq                 INTEGER ::= 4
maxMBMS-L1CP                 INTEGER ::= 1    -- FFS
maxMBMSServCount             INTEGER ::= 4
maxMBMSServDedic             INTEGER ::= 4
maxMBMSServModif             INTEGER ::= 4
maxMBMSServSched             INTEGER ::= 16
maxMBMSServUnmodif           INTEGER ::= 32
maxMBMSTransmis              INTEGER ::= 1    -- FFS
maxMeasEvent                 INTEGER ::= 8
maxMeasIntervals              INTEGER ::= 3
maxMeasParEvent               INTEGER ::= 2
maxNumCDMA2000Freqs          INTEGER ::= 8
maxNumGSMFreqRanges          INTEGER ::= 32
maxNumFDDFreqs               INTEGER ::= 8
maxNumTDDFreqs               INTEGER ::= 8
maxNoOfMeas                  INTEGER ::= 16
maxOtherRAT                  INTEGER ::= 15
maxOtherRAT-16                INTEGER ::= 16
maxPage1                      INTEGER ::= 8
maxPCPCH-APsig                INTEGER ::= 16
maxPCPCH-APsubCh              INTEGER ::= 12
maxPCPCH-CDsig                INTEGER ::= 16
maxPCPCH-CDsubCh              INTEGER ::= 12
maxPCPCH-SF                  INTEGER ::= 7
maxPCPCHs                     INTEGER ::= 64
maxPDCPAlgoType              INTEGER ::= 8
maxPDSCH                      INTEGER ::= 8
maxPDSCH-TFCIgroups           INTEGER ::= 256
maxPRACH                      INTEGER ::= 16
maxPRACH-FPACH                INTEGER ::= 8
maxPredefConfig               INTEGER ::= 16
maxPUSCH                      INTEGER ::= 8
maxQueueIDs                   INTEGER ::= 8
maxRABsetup                    INTEGER ::= 16
maxRAT                         INTEGER ::= 16
maxRB                          INTEGER ::= 32
maxRBallRABs                  INTEGER ::= 27
maxRB_muxOptions               INTEGER ::= 8
maxRBperRAB                   INTEGER ::= 8
maxRBperTrCh                  INTEGER ::= 16
maxReportedGSMCells           INTEGER ::= 8
maxRL                          INTEGER ::= 8
maxRL-1                        INTEGER ::= 7
| maxRLCPDUsizePerLogChan   INTEGER ::= 1    -- FFS
maxRFC3095-CID                INTEGER ::= 16384
maxROHC-PacketSizes-r4         INTEGER ::= 16
maxROHC-Profile-r4             INTEGER ::= 8
maxSat                         INTEGER ::= 16
maxSCCPCH                      INTEGER ::= 16
maxSIB                         INTEGER ::= 32
maxSIB-FACH                     INTEGER ::= 8
maxSIBperMsg                    INTEGER ::= 16
maxSRBsetup                     INTEGER ::= 8
maxSystemCapability             INTEGER ::= 16
maxTF                          INTEGER ::= 32
maxTF-CPCH                      INTEGER ::= 16
maxTFC                         INTEGER ::= 1024
maxTFCsub                       INTEGER ::= 1024
maxTFCI-2-Combs                INTEGER ::= 512
maxTGPS                         INTEGER ::= 6

```

```

maxTrCH           INTEGER ::= 32
maxTrChperSCCPCH INTEGER ::= 8
-- maxTrCHpreconf should be 16 but has been set to 32 for compatibility
maxTrCHpreconf   INTEGER ::= 32
maxTS            INTEGER ::= 14
maxTS-1          INTEGER ::= 13
maxTS-2          INTEGER ::= 12
maxTS-LCR        INTEGER ::= 6
maxTS-LCR-1      INTEGER ::= 5
maxURA           INTEGER ::= 8
maxURNTI-Group   INTEGER ::= 8

END

```

11.5 RRC information between network nodes

```
Internode-definitions DEFINITIONS AUTOMATIC TAGS ::=
```

```
BEGIN
```

```
IMPORTS
```

```

HandoverToUTRANCommand,
MeasurementReport,
PhysicalChannelReconfiguration,
RadioBearerReconfiguration,
RadioBearerRelease,
RadioBearerSetup,
RRC-FailureInfo,
TransportChannelReconfiguration
FROM PDU-definitions

-- Core Network IEs :
CN-DomainIdentity,
CN-DomainInformationList,
CN-DomainInformationListFull,
CN-DRX-CycleLengthCoefficient,
NAS-SystemInformationGSM-MAP,
-- UTRAN Mobility IEs :
CellIdentity,
URA-Identity,
-- User Equipment IEs :
AccessStratumReleaseIndicator,
C-RNTI,
ChipRateCapability,
DL-CapabilityWithSimultaneousHS-DSCHConfig,
DL-PhysChCapabilityFDD-v380ext,
DL-PhysChCapabilityTDD,
DL-PhysChCapabilityTDD-LCR-r4,
GSM-Measurements,
HSDSCH-physical-layer-category,
FailureCauseWithProtErr,
MaxHcContextSpace,
MaximumAM-EntityNumberRLC-Cap,
MaximumRLC-WindowSize,
MaxNoPhysChBitsReceived,
MaxPhysChPerFrame,
MaxPhysChPerSubFrame-r4,
MaxPhysChPerTS,
MaxROHC-ContextSessions-r4,
MaxTS-PerFrame,
MaxTS-PerSubFrame-r4,
MinimumSF-DL,
MultiModeCapability,
MultiRAT-Capability,
NetworkAssistedGPS-Supported,
RadioFrequencyBandTDDList,
RLC-Capability,
RRC-MessageSequenceNumber,
SecurityCapability,
SimultaneousSCCPCH-DPCH-Reception,
STARTList,
STARTSingle,
START-Value,
SupportOfDedicatedPilotsForChEstimation,
TransportChannelCapability,
TxRxFrequencySeparation,

```

```

U-RNTI,
UE-MultiModeRAT-Capability,
UE-PowerClassExt,
UE-RadioAccessCapabBandFDDList,
UE-RadioAccessCapability,
UE-RadioAccessCapability-v370ext,
UE-RadioAccessCapability-v380ext,
UE-RadioAccessCapability-v3a0ext,
UE-RadioAccessCapability-v3g0ext,
UE-RadioAccessCapability-v4b0ext,
UE-RadioAccessCapability-v590ext,
UL-PhysChCapabilityFDD,
UL-PhysChCapabilityTDD,
UL-PhysChCapabilityTDD-LCR-r4,
-- Radio Bearer IEs :
PredefinedConfigStatusList,
PredefinedConfigValueTag,
RAB-InformationSetupList,
RAB-InformationSetupList-r4,
RAB-InformationSetupList-r5,
RAB-InformationSetupList-r6-ext,
RAB-InformationSetupList-r6,
RB-Identity,
SRB-InformationSetupList,
SRB-InformationSetupList-r5,
SRB-InformationSetupList-r6,
-- Transport Channel IEs :
CPCH-SetID,
DL-CommonTransChInfo,
DL-CommonTransChInfo-r4,
DL-AddReconfTransChInfoList,
DL-AddReconfTransChInfoList-r4,
DL-AddReconfTransChInfoList-r5,
DRAC-StaticInformationList,
UL-CommonTransChInfo,
UL-CommonTransChInfo-r4,
UL-AddReconfTransChInfoList,
UL-AddReconfTransChInfoList-r6,
-- Physical Channel IEs :
PrimaryCPICH-Info,
TPC-CombinationIndex,
ScramblingCodeChange,
TGCFN,
TGPSI,
TGPS-ConfigurationParams,
-- Measurement IEs :
Inter-FreqEventCriteriaList-v590ext,
Intra-FreqEventCriteriaList-v590ext,
IntraFreqEvent-1d-r5,
IntraFreqReportingCriteria-1b-r5,
InterRATCellInfoIndicator,
MeasurementIdentity,
MeasurementReportingMode,
MeasurementType,
MeasurementType-r4,
AdditionalMeasurementID-List,
PositionEstimate,
-- MBMS IEs :
MBMS-JoinedInformation-r6,
-- Other IEs :
GERANIu-RadioAccessCapability,
InterRAT-UE-RadioAccessCapabilityList,
InterRAT-UE-RadioAccessCapability-v590ext,
UESpecificBehaviourInformationIdle,
UESpecificBehaviourInformationInterRAT

```

FROM InformationElements

```

maxCNdomains,
maxNoOfMeas,

maxRB,
maxRBallRABs,
maxRFC3095-CID,
maxSRBsetup,
maxRL,
maxTGPS

```

FROM Constant-definitions

```

;

-- Part 1: Class definitions similar to what has been defined in 11.1 for RRC messages
-- Information that is transferred in the same direction and across the same path is grouped

-- ****
-- 
-- RRC information, to target RNC
-- 
-- ****
-- RRC Information to target RNC sent either from source RNC or from another RAT

ToTargetRNC-Container ::= CHOICE {
    interRATHandoverInfo           InterRATHandoverInfoWithInterRATCapabilities-r3,
    srncRelocation                 SRNC-RelocationInfo-r3,
    rfc3095-ContextInfo            RFC3095-ContextInfo-r5,
    extension                       NULL
}

-- ****
-- 
-- RRC information, target RNC to source RNC
-- 
-- ****

TargetRNC-ToSourceRNC-Container ::= CHOICE {
    radioBearerSetup                RadioBearerSetup,
    radioBearerReconfiguration       RadioBearerReconfiguration,
    radioBearerRelease               RadioBearerRelease,
    transportChannelReconfiguration TransportChannelReconfiguration,
    physicalChannelReconfiguration PhysicalChannelReconfiguration,
    rrc-FailureInfo                RRC-FailureInfo,
    -- IE dl-DCCHmessage consists of an octet string that includes the IE DL-DCCH-Message
    dL-DCCHmessage                  OCTET STRING,
    extension                        NULL
}

-- Part 2: Container definitions, similar to the PDU definitions in 11.2 for RRC messages
-- In alphabetical order

-- ****
-- 
-- Handover to UTRAN information
-- 
-- ****

InterRATHandoverInfoWithInterRATCapabilities-r3 ::= CHOICE {
    r3                           SEQUENCE {
        -- IE InterRATHandoverInfoWithInterRATCapabilities-r3-IEs also
        -- includes non critical extensions
        interRATHandoverInfo-r3           InterRATHandoverInfoWithInterRATCapabilities-r3-IEs,
        v390NonCriticalExtensions        SEQUENCE {
            interRATHandoverInfoWithInterRATCapabilities-v390ext
        },
        InterRATHandoverInfoWithInterRATCapabilities-v390ext-IEs,
        -- Reserved for future non critical extension
        nonCriticalExtensions          SEQUENCE {} OPTIONAL
    },
    criticalExtensions             SEQUENCE {}
}

InterRATHandoverInfoWithInterRATCapabilities-r3-IEs ::= SEQUENCE {
    -- The order of the IE's may not reflect the tabular format
    -- but has been chosen to simplify the handling of the information in the BSC
    -- Other IE's
    ue-RATSpecificCapability        InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
    -- interRATHandoverInfo, Octet string is used to obtain 8 bit length field prior to
    -- actual information. This makes it possible for BSS to transparently handle information
    -- received via GSM air interface even when it includes non critical extensions.
    -- The octet string shall include the InterRATHandoverInfo information
    -- The BSS can re-use the 04.18 length field received from the MS
    interRATHandoverInfo           OCTET STRING (SIZE (0..255))
}

InterRATHandoverInfoWithInterRATCapabilities-v390ext-IEs ::= SEQUENCE {
    -- User equipment IE's
}

```

```

failureCauseWithProtErr           FailureCauseWithProtErr          OPTIONAL
}

-- *****
-- RFC3095 context, source RNC to target RNC
-- *****
RFC3095-ContextInfo-r5 ::= CHOICE {
    r5
        SEQUENCE {
            RFC3095-ContextInfoList-r5      RFC3095-ContextInfoList-r5,
            -- Reserved for future non critical extension
            nonCriticalExtensions         SEQUENCE {} OPTIONAL
        },
        criticalExtensions             SEQUENCE {}
}
RFC3095-ContextInfoList-r5 ::= SEQUENCE (SIZE (1..maxRBallRABs)) OF
                                RFC3095-ContextInfo

-- *****
-- SRNC Relocation information
-- *****
SRNC-RelocationInfo-r3 ::= CHOICE {
    r3
        SEQUENCE {
            sRNC-RelocationInfo-r3          SRNC-RelocationInfo-r3-IES,
            v380NonCriticalExtensions       SEQUENCE {
                SRNC-RelocationInfo-v380ext SRNC-RelocationInfo-v380ext-IES,
                -- Reserved for future non critical extension
                v390NonCriticalExtensions     SEQUENCE {
                    SRNC-RelocationInfo-v390ext      SRNC-RelocationInfo-v390ext-IES,
                    v3a0NonCriticalExtensions       SEQUENCE {
                        SRNC-RelocationInfo-v3a0ext      SRNC-RelocationInfo-v3a0ext-IES,
                        v3b0NonCriticalExtensions       SEQUENCE {
                            SRNC-RelocationInfo-v3b0ext      SRNC-RelocationInfo-v3b0ext-IES,
                            v3c0NonCriticalExtensions       SEQUENCE {
                                SRNC-RelocationInfo-v3c0ext      SRNC-RelocationInfo-v3c0ext-IES,
                                laterNonCriticalExtensions     SEQUENCE {
                                    SRNC-RelocationInfo-v3d0ext      SRNC-RelocationInfo-v3d0ext-IES,
                                    -- Container for additional R99 extensions
                                    SRNC-RelocationInfo-r3-add-ext   BIT STRING
                                        (CONTAINING SRNC-RelocationInfo-v3h0ext-IES)      OPTIONAL,
                                    v3g0NonCriticalExtensions       SEQUENCE {
                                        SRNC-RelocationInfo-v3g0ext      SRNC-RelocationInfo-v3g0ext-IES,
                                        v4b0NonCriticalExtensions       SEQUENCE {
                                            SRNC-RelocationInfo-v4b0ext      SRNC-RelocationInfo-v4b0ext-IES,
                                            v590NonCriticalExtensions       SEQUENCE {
                                                SRNC-RelocationInfo-v590ext      SRNC-RelocationInfo-v590ext-IES,
                                                v5a0NonCriticalExtensions       SEQUENCE {
                                                    SRNC-RelocationInfo-v5a0ext      SRNC-RelocationInfo-v5a0ext-IES,
                                                    v5b0NonCriticalExtensions       SEQUENCE {
                                                        SRNC-RelocationInfo-v5b0ext      SRNC-RelocationInfo-v5b0ext-IES,
                                                        v6xyNonCriticalExtensions       SEQUENCE {
                                                            SRNC-RelocationInfo-v6xyext      SRNC-RelocationInfo-v6xyext-IES,
                                                            -- Reserved for future non critical extension
                                                            nonCriticalExtensions         SEQUENCE {} OPTIONAL
                                                        } OPTIONAL
                                                    } OPTIONAL
                                                } OPTIONAL
                                            } OPTIONAL
                                        } OPTIONAL
                                    } OPTIONAL
                                } OPTIONAL
                            } OPTIONAL
                        } OPTIONAL
                    } OPTIONAL
                } OPTIONAL
            } OPTIONAL
        } OPTIONAL
    } OPTIONAL
}

```

```

later-than-r3
r4           CHOICE {
    SEQUENCE {
        SRNC-RelocationInfo-r4           SRNC-RelocationInfo-r4-IEs,
        v4d0NonCriticalExtensions       SEQUENCE {
            sRNC-RelocationInfo-v4d0ext   SRNC-RelocationInfo-v4d0ext-IEs,
            -- Container for adding non critical extensions after freezing REL-5
            sRNC-RelocationInfo-r4-add-ext BIT STRING      OPTIONAL,
            v590NonCriticalExtensions     SEQUENCE {
                sRNC-RelocationInfo-v590ext   SRNC-RelocationInfo-v590ext-IEs,
                v5a0NonCriticalExtensions   SEQUENCE {
                    sRNC-RelocationInfo-v5a0ext   SRNC-RelocationInfo-v5a0ext-IEs,
                    v5b0NonCriticalExtensions   SEQUENCE {
                        sRNC-RelocationInfo-v5b0ext   SRNC-RelocationInfo-v5b0ext-IEs,
                        v6xyNonCriticalExtensions   SEQUENCE {
                            sRNC-RelocationInfo-v6xyext   SRNC-RelocationInfo-v6xyext-IEs,
                            nonCriticalExtensions     SEQUENCE {} OPTIONAL
                        } OPTIONAL
                    } OPTIONAL
                } OPTIONAL
            } OPTIONAL
        } OPTIONAL
    },
    criticalExtensions           CHOICE {
        r5           SEQUENCE {
            SRNC-RelocationInfo-r5           SRNC-RelocationInfo-r5-IEs,
            sRNC-RelocationInfo-r5-add-ext BIT STRING      OPTIONAL,
            v5a0NonCriticalExtensions     SEQUENCE {
                sRNC-RelocationInfo-v5a0ext   SRNC-RelocationInfo-v5a0ext-IEs,
                v5b0NonCriticalExtensions   SEQUENCE {
                    sRNC-RelocationInfo-v5b0ext   SRNC-RelocationInfo-v5b0ext-IEs,
                    v6xyNonCriticalExtensions   SEQUENCE {
                        sRNC-RelocationInfo-v6xyext   SRNC-RelocationInfo-v6xyext-IEs,
                        nonCriticalExtensions     SEQUENCE {} OPTIONAL
                    } OPTIONAL
                } OPTIONAL
            } OPTIONAL
        } OPTIONAL
    },
    criticalExtensions           CHOICE {
        r6           SEQUENCE {
            SRNC-RelocationInfo-r6           SRNC-RelocationInfo-r6-IEs,
            sRNC-RelocationInfo-r6-add-ext BIT STRING      OPTIONAL,
            nonCriticalExtensions         SEQUENCE {} OPTIONAL
        },
        criticalExtensions             SEQUENCE {}
    }
}

SRNC-RelocationInfo-r3-IEs ::=      SEQUENCE {
    -- Non-RRC IEs
    stateOfRRC                  StateOfRRC,
    stateOfRRC-Procedure         StateOfRRC-Procedure,
    -- Ciphering related information IEs
    -- If the extension v380 is included use the extension for the ciphering status per CN domain
    cipheringStatus               CipheringStatus,
    calculationTimeForCiphering   CalculationTimeForCiphering      OPTIONAL,
    -- The order of occurrence in the IE cipheringInfoPerRB-List is the
    -- same as the RBs in SRB-InformationSetupList in RAB-InformationSetupList.
    -- The signalling RBs are supposed to be listed
    -- first. Only UM and AM RBs that are ciphered are listed here
    cipheringInfoPerRB-List       CipheringInfoPerRB-List      OPTIONAL,
    count-C-List                 COUNT-C-List                OPTIONAL,
    integrityProtectionStatus     IntegrityProtectionStatus,
    -- In the IE srb-SpecificIntegrityProtInfo, the first information listed corresponds to
    -- signalling radio bearer RB0 and after the order of occurrence is the same as the SRBs in
    -- SRB-InformationSetupList
    -- The target RNC may ignore the IE srb-SpecificIntegrityProtInfo if the
    -- IE integrityProtectionStatus has the value "not started".
    srb-SpecificIntegrityProtInfo SRB-SpecificIntegrityProtInfoList,
    implementationSpecificParams ImplementationSpecificParams      OPTIONAL,
    -- User equipment IEs
    u-RNTI                      U-RNTI,
    c-RNTI                      C-RNTI                  OPTIONAL,
    ue-RadioAccessCapability     UE-RadioAccessCapability,
    ue-Positioning-LastKnownPos  UE-Positioning-LastKnownPos    OPTIONAL,
    -- Other IEs
    ue-RATSpecificCapability    InterRAT-UE-RadioAccessCapabilityList    OPTIONAL,
}

```

```

-- UTRAN mobility IEs
ura-Identity URA-Identity OPTIONAL,
-- Core network IEs
cn-CommonGSM-MAP-NAS-SysInfo NAS-SystemInformationGSM-MAP,
cn-DomainInformationList CN-DomainInformationList OPTIONAL,
-- Measurement IEs
ongoingMeasRepList OngoingMeasRepList OPTIONAL,
-- Radio bearer IEs
predefinedConfigStatusList PredefinedConfigStatusList,
srb-InformationList SRB-InformationSetupList,
rab-InformationList RAB-InformationSetupList OPTIONAL,
-- Transport channel IEs
ul-CommonTransChInfo UL-CommonTransChInfo OPTIONAL,
ul-TransChInfoList UL-AddReconfTransChInfoList OPTIONAL,
modeSpecificInfo CHOICE {
    fdd SEQUENCE {
        cpch-SetID CPCH-SetID OPTIONAL,
        transChDRAC-Info DRAC-StaticInformationList OPTIONAL
    },
    tdd NULL
},
dl-CommonTransChInfo DL-CommonTransChInfo OPTIONAL,
dl-TransChInfoList DL-AddReconfTransChInfoList OPTIONAL,
-- Measurement report
measurementReport MeasurementReport OPTIONAL
}

SRNC-RelocationInfo-v380ext-IEs ::= SEQUENCE {
    -- Ciphering related information IEs
    cn-DomainIdentity CN-DomainIdentity,
    cipheringStatusList CipheringStatusList
}

SRNC-RelocationInfo-v390ext-IEs ::= SEQUENCE {
    cn-DomainInformationList-v390ext CN-DomainInformationList-v390ext OPTIONAL,
    ue-RadioAccessCapability-v370ext UE-RadioAccessCapability-v370ext OPTIONAL,
    ue-RadioAccessCapability-v380ext UE-RadioAccessCapability-v380ext OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext DL-PhysChCapabilityFDD-v380ext,
    failureCauseWithProtErr FailureCauseWithProtErr OPTIONAL
}

SRNC-RelocationInfo-v3a0ext-IEs ::= SEQUENCE {
    cipheringInfoForSRB1-v3a0ext CipheringInfoPerRB-List-v3a0ext,
    ue-RadioAccessCapability-v3a0ext UE-RadioAccessCapability-v3a0ext OPTIONAL,
    -- cn-domain identity for IE startValueForCiphering-v3a0ext is specified
    -- in subsequent extension (SRNC-RelocationInfo-v3b0ext-IEs)
    startValueForCiphering-v3a0ext START-Value
}

SRNC-RelocationInfo-v3b0ext-IEs ::= SEQUENCE {
    -- cn-domain identity for IE startValueForCiphering-v3a0ext included in previous extension
    cn-DomainIdentity CN-DomainIdentity,
    -- the IE startValueForCiphering-v3b0ext contains the start values for each CN Domain. The
    -- value of start indicated by the IE startValueForCiphering-v3a0ext should be set to the
    -- same value as the start-Value for the corresponding cn-DomainIdentity in the IE
    -- startValueForCiphering-v3b0ext
    startValueForCiphering-v3b0ext STARTList2 OPTIONAL
}

SRNC-RelocationInfo-v3c0ext-IEs ::= SEQUENCE {
    -- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
    -- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
    -- Only included if type is "UE involved"
    rb-IdentityForHOMessage RB-Identity OPTIONAL
}

SRNC-RelocationInfo-v3d0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    uESpecificBehaviourInformation1idle UESpecificBehaviourInformation1idle OPTIONAL,
    uESpecificBehaviourInformation1interRAT UESpecificBehaviourInformation1interRAT OPTIONAL
}

SRNC-RelocationInfo-v3g0ext-IEs ::= SEQUENCE {
    ue-RadioAccessCapability-v3g0ext UE-RadioAccessCapability-v3g0ext OPTIONAL
}

SRNC-RelocationInfo-v3h0ext-IEs ::= SEQUENCE {
}

```

```

tpc-CombinationInfoList      TPC-CombinationInfoList      OPTIONAL,
nonCriticalExtension        SEQUENCE {}                  OPTIONAL
}

SRNC-RelocationInfo-v4d0ext-IEs ::= SEQUENCE {
    tpc-CombinationInfoList      TPC-CombinationInfoList      OPTIONAL
}

TPC-CombinationInfoList ::= SEQUENCE (SIZE (1..maxRL)) OF
    TPC-Combination-Info

STARTList2 ::= SEQUENCE (SIZE (2..maxCNdomains)) OF
    STARTSingle

SRNC-RelocationInfo-v4b0ext-IEs ::= SEQUENCE {
    ue-RadioAccessCapability-v4b0ext     UE-RadioAccessCapability-v4b0ext      OPTIONAL
}
}

SRNC-RelocationInfo-v590ext-IEs ::= SEQUENCE {
    ue-RadioAccessCapability-v590ext     UE-RadioAccessCapability-v590ext      OPTIONAL,
    ue-RATSpecificCapability-v590ext    InterRAT-UE-RadioAccessCapability-v590ext  OPTIONAL
}
}

SRNC-RelocationInfo-v5a0ext-IEs ::= SEQUENCE {
    storedCompressedModeInfo       StoredCompressedModeInfo      OPTIONAL
}
}

SRNC-RelocationInfo-v5b0ext-IEs ::= SEQUENCE {
    interRATCellInfoIndicator     InterRATCellInfoIndicator      OPTIONAL
}
}

CipheringInfoPerRB-List-v3a0ext ::= SEQUENCE {
    dl-UM-SN                      BIT STRING (SIZE (7))
}
}

CipheringStatusList ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
    CipheringStatusCNdomain

CipheringStatusCNdomain ::= SEQUENCE {
    cn-DomainIdentity            CN-DomainIdentity,
    cipheringStatus              CipheringStatus
}
}

CodeChangeStatusList ::= SEQUENCE (SIZE (1..maxRL)) OF
    CodeChangeStatus

CodeChangeStatus ::= SEQUENCE {
    primaryCPICH-Info           PrimaryCPICH-Info,
    scramblingCodeChange         ScramblingCodeChange
}
}

StoredCompressedModeInfo ::= SEQUENCE {
    storedTGP-SequenceList       StoredTGP-SequenceList,
    codeChangeStatusList         CodeChangeStatusList      OPTIONAL
}
}

| StoredTGP-SequenceList ::= SEQUENCE (SIZE (1..maxTGPS)) OF
|     StoredTGP-Sequence
|
| | StoredTGP-Sequence ::= SEQUENCE {
| |     tgpsi,
| |     current-tgps-Status
| |     active
| |     tgcfn
| |     },
| |     inactive
| |     NULL
| | },
| |     tgps-ConfigurationParams   TGPS-ConfigurationParams      OPTIONAL
|
| }

SRNC-RelocationInfo-r4-IEs ::= SEQUENCE {
    -- Non-RRM IE
    -- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
    -- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
    -- Only included if type is "UE involved"
    rb-IdentityForHOMessage      RB-Identity      OPTIONAL,
    stateOfRRM                   StateOfRRM,
    stateOfRRM-Procedure          StateOfRRM-Procedure,
}

```

```

-- Ciphering related information IEs
cipheringStatusList          CipheringStatusList-r4,
latestConfiguredCN-Domain    CN-DomainIdentity,
calculationTimeForCiphering CalculationTimeForCiphering      OPTIONAL,
count-C-List                 COUNT-C-List                OPTIONAL,
cipheringInfoPerRB-List     CipheringInfoPerRB-List-r4      OPTIONAL,
-- Integrity protection related information IEs
integrityProtectionStatus    IntegrityProtectionStatus,
-- The target RNC may ignore the IE srb-SpecificIntegrityProtInfo if the
-- IE integrityProtectionStatus has the value "not started".
srb-SpecificIntegrityProtInfo SRB-SpecificIntegrityProtInfoList,
implementationSpecificParams ImplementationSpecificParams      OPTIONAL,
-- User equipment IEs
u-RNTI                      U-RNTI,
c-RNTI                      C-RNTI                OPTIONAL,
ue-RadioAccessCapability     UE-RadioAccessCapability-r4,
ue-RadioAccessCapability-ext UE-RadioAccessCapabBandFDDList      OPTIONAL,
ue-Positioning-LastKnownPos  UE-Positioning-LastKnownPos      OPTIONAL,
uESpecificBehaviourInformationlidle UESpecificBehaviourInformationlidle      OPTIONAL,
uESpecificBehaviourInformationlinterRAT UESpecificBehaviourInformationlinterRAT
OPTIONAL,
-- Other IEs
ue-RATSpecificCapability    InterRAT-UE-RadioAccessCapabilityList      OPTIONAL,
-- UTRAN mobility IEs
ura-Identity                 URA-Identity      OPTIONAL,
-- Core network IEs
cn-CommonGSM-MAP-NAS-SysInfo NAS-SystemInformationGSM-MAP,
cn-DomainInformationList     CN-DomainInformationListFull      OPTIONAL,
-- Measurement IEs
ongoingMeasRepList          OngoingMeasRepList-r4      OPTIONAL,
-- Radio bearer IEs
predefinedConfigStatusList   PredefinedConfigStatusList,
srb-InformationList          SRB-InformationSetupList,
rab-InformationList          RAB-InformationSetupList-r4      OPTIONAL,
-- Transport channel IEs
ul-CommonTransChInfo         UL-CommonTransChInfo-r4      OPTIONAL,
ul-TransChInfoList           UL-AddReconfTransChInfoList      OPTIONAL,
modeSpecificInfo
  fdd                         CHOICE {
    cpch-SetID                 SEQUENCE {
      CPCH-SetID               OPTIONAL,
      transChDRAC-Info         DRAC-StaticInformationList      OPTIONAL
    },
    tdd                         NULL
  }
  dl-CommonTransChInfo        DL-CommonTransChInfo-r4      OPTIONAL,
  dl-TransChInfoList          DL-AddReconfTransChInfoList-r4      OPTIONAL,
-- Measurement report
measurementReport            MeasurementReport      OPTIONAL,
failureCause                 FailureCauseWithProtErr      OPTIONAL
}

SRNC-RelocationInfo-r5-IEs ::= SEQUENCE {
-- Non-RRC IEs
-- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
-- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
-- Only included if type is "UE involved"
rb-IdentityForHOMessage      RB-Identity      OPTIONAL,
stateOfRRRC                  StateOfRRRC,
stateOfRRRC-Procedure        StateOfRRC-Procedure,
-- Ciphering related information IEs
cipheringStatusList          CipheringStatusList-r4,
latestConfiguredCN-Domain    CN-DomainIdentity,
calculationTimeForCiphering CalculationTimeForCiphering      OPTIONAL,
count-C-List                 COUNT-C-List                OPTIONAL,
cipheringInfoPerRB-List     CipheringInfoPerRB-List-r4      OPTIONAL,
-- Integrity protection related information IEs
integrityProtectionStatus    IntegrityProtectionStatus,
srb-SpecificIntegrityProtInfo SRB-SpecificIntegrityProtInfoList      OPTIONAL,
implementationSpecificParams ImplementationSpecificParams      OPTIONAL,
-- User equipment IEs
u-RNTI                      U-RNTI,
c-RNTI                      C-RNTI                OPTIONAL,
ue-RadioAccessCapability     UE-RadioAccessCapability-r5,
ue-RadioAccessCapability-ext UE-RadioAccessCapabBandFDDList      OPTIONAL,
ue-Positioning-LastKnownPos  UE-Positioning-LastKnownPos      OPTIONAL,
uESpecificBehaviourInformationlidle UESpecificBehaviourInformationlidle      OPTIONAL,

```

```

    uESpecificBehaviourInformationlinterRAT
    UESpecificBehaviourInformationlinterRAT      OPTIONAL,
-- Other IEs
    ue-RATSpecificCapability
    InterRAT-UE-RadioAccessCapabilityList-r5      OPTIONAL,
-- UTRAN mobility IEs
    ura-Identity
    URA-Identity      OPTIONAL,
-- Core network IEs
    cn-CommonGSM-MAP-NAS-SysInfo
    NAS-SystemInformationGSM-MAP,
    cn-DomainInformationList
    CN-DomainInformationListFull      OPTIONAL,
-- Measurement IEs
    ongoingMeasRepList
    OngoingMeasRepList-r5      OPTIONAL,
-- Radio bearer IEs
    predefinedConfigStatusList
    PredefinedConfigStatusList,
    srb-InformationList
    SRB-InformationSetupList-r5,
    rab-InformationList
    RAB-InformationSetupList-r5      OPTIONAL,
-- Transport channel IEs
    ul-CommonTransChInfo
    UL-CommonTransChInfo-r4      OPTIONAL,
    ul-TransChInfoList
    UL-AddReconfTransChInfoList      OPTIONAL,
    modeSpecificInfo
    CHOICE {
        fdd
        CPCH-SetID
        transChDRAC-Info
        DRAC-StaticInformationList
        OPTIONAL,
        },
        tdd
        NULL
        OPTIONAL,
    }
    dl-CommonTransChInfo
    DL-CommonTransChInfo-r4      OPTIONAL,
    dl-TransChInfoList
    DL-AddReconfTransChInfoList-r5      OPTIONAL,
-- PhyCH IEs
    tpc-CombinationInfoList
    TPC-CombinationInfoList      OPTIONAL,
-- Measurement report
    measurementReport
    MeasurementReport      OPTIONAL,
-- Other IEs
    failureCause
    FailureCauseWithProtErr      OPTIONAL
}

SRNC-RelocationInfo-v6xyext-IEs ::= SEQUENCE {
    -- Radio bearer IEs
    rab-InformationSetupList
    RAB-InformationSetupList-r6-ext      OPTIONAL,
    -- MBMS IEs
    mbms-JoinedInformation
    MBMS-JoinedInformation-r6      OPTIONAL
}

SRNC-RelocationInfo-r6-IEs ::= SEQUENCE {
    -- Non-RRC IEs
    -- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
    -- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
    -- Only included if type is "UE involved"
    rb-IdentityForHOMessage
    RB-Identity      OPTIONAL,
    stateOfRRC
    StateOfRRC,
    stateOfRRC-Procedure
    StateOfRRC-Procedure,
    -- Ciphering related information IEs
    cipheringStatusList
    CipheringStatusList-r4,
    latestConfiguredCN-Domain
    CN-DomainIdentity,
    calculationTimeForCiphering
    CalculationTimeForCiphering      OPTIONAL,
    count-C-List
    COUNT-C-List      OPTIONAL,
    cipheringInfoPerRB-List
    CipheringInfoPerRB-List-r4      OPTIONAL,
    -- Integrity protection related information IEs
    integrityProtectionStatus
    IntegrityProtectionStatus,
    srb-SpecificIntegrityProtInfo
    SRB-SpecificIntegrityProtInfoList      OPTIONAL,
    implementationSpecificParams
    ImplementationSpecificParams      OPTIONAL,
    -- User equipment IEs
    u-RNTI
    U-RNTI,
    c-RNTI
    C-RNTI      OPTIONAL,
    ue-RadioAccessCapability
    UE-RadioAccessCapability-r5,
    ue-RadioAccessCapability-ext
    UE-RadioAccessCapabBandFDDList      OPTIONAL,
    ue-Positioning-LastKnownPos
    UE-Positioning-LastKnownPos      OPTIONAL,
    ueSpecificBehaviourInformationlidle
    UESpecificBehaviourInformationlidle      OPTIONAL,
    ueSpecificBehaviourInformationlinterRAT
    UESpecificBehaviourInformationlinterRAT      OPTIONAL,
    -- Other IEs
    ue-RATSpecificCapability
    InterRAT-UE-RadioAccessCapabilityList-r5      OPTIONAL,
    -- UTRAN mobility IEs
    ura-Identity
    URA-Identity      OPTIONAL,
    -- Core network IEs
    cn-CommonGSM-MAP-NAS-SysInfo
    NAS-SystemInformationGSM-MAP,
    cn-DomainInformationList
    CN-DomainInformationListFull      OPTIONAL,
    -- Measurement IEs

```

```

ongoingMeasRepList          OngoingMeasRepList-r5           OPTIONAL,
interRATCellInfoIndicator   InterRATCellInfoIndicator      OPTIONAL,
-- Radio bearer IEs
predefinedConfigStatusList PredefinedConfigStatusList,
srb-InformationList        SRB-InformationSetupList-r6,
rab-InformationList        RAB-InformationSetupList-r6   OPTIONAL,
-- Transport channel IEs
ul-CommonTransChInfo       UL-CommonTransChInfo-r4        OPTIONAL,
ul-TransChInfoList         UL-AddReconfTransChInfoList-r6  OPTIONAL,
modeSpecificInfo           CHOICE {
    fdd                  SEQUENCE {
        cpch-SetID        CPCH-SetID                OPTIONAL,
        transChDRAC-Info  DRAC-StaticInformationList OPTIONAL
    },
    tdd                  NULL                      OPTIONAL,
}
dl-CommonTransChInfo       DL-CommonTransChInfo-r4        OPTIONAL,
dl-TransChInfoList         DL-AddReconfTransChInfoList-r5  OPTIONAL,
-- PhyCH IEs
tpc-CombinationInfoList  TPC-CombinationInfoList      OPTIONAL,
storedCompressedModeInfo StoredCompressedModeInfo      OPTIONAL,
-- Measurement report
measurementReport          MeasurementReport            OPTIONAL,
-- Other IEs
failureCause               FailureCauseWithProtErr      OPTIONAL,
-- MBMS IEs
mbms-JoinedInformation   MBMS-JoinedInformation-r6     OPTIONAL
}

-- IE definitions

CalculationTimeForCiphering ::= SEQUENCE {
    cell-Id                 CellIdentity,
    sfn                     INTEGER (0..4095)
}

CipheringInfoPerRB ::= SEQUENCE {
    dl-HFN                  BIT STRING (SIZE (20..25)),
    ul-HFN                  BIT STRING (SIZE (20..25))
}

CipheringInfoPerRB-r4 ::= SEQUENCE {
    rb-Identity              RB-Identity,
    dl-HFN                  BIT STRING (SIZE (20..25)),
    dl-UM-SN                 BIT STRING (SIZE (7))           OPTIONAL,
    ul-HFN                  BIT STRING (SIZE (20..25))
}

-- TABULAR: CipheringInfoPerRB-List, multiplicity value numberOfRadioBearers
-- has been replaced with maxRB.
CipheringInfoPerRB-List ::= SEQUENCE (SIZE (1..maxRB)) OF
                                CipheringInfoPerRB

CipheringInfoPerRB-List-r4 ::= SEQUENCE (SIZE (1..maxRB)) OF
                                CipheringInfoPerRB-r4

CipheringStatus ::= ENUMERATED {
    started, notStarted }

CipheringStatusList-r4 ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
                                CipheringStatusCNdomain-r4

CipheringStatusCNdomain-r4 ::= SEQUENCE {
    cn-DomainIdentity        CN-DomainIdentity,
    cipheringStatus           CipheringStatus,
    start-Value                START-Value
}

CN-DomainInformation-v390ext ::= SEQUENCE {
    cn-DRX-CycleLengthCoeff CN-DRX-CycleLengthCoefficient
}

CN-DomainInformationList-v390ext ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
                                CN-DomainInformation-v390ext

CompressedModeMeasCapability-r4 ::= SEQUENCE {
    fdd-Measurements          BOOLEAN,

```

```

-- TABULAR: The IEs tdd-Measurements, gsm-Measurements and multiCarrierMeasurements
-- are made optional since they are conditional based on another information element.
-- Their absence corresponds to the case where the condition is not true.
tdd384-Measurements          BOOLEAN                      OPTIONAL,
tdd128-Measurements          BOOLEAN                      OPTIONAL,
gsm-Measurements             GSM-Measurements           OPTIONAL,
multiCarrierMeasurements     BOOLEAN                      OPTIONAL
}

COUNT-C-List ::=          SEQUENCE (SIZE (1..maxCNdomains)) OF
                           COUNT-CSingle

COUNT-CSingle ::=          SEQUENCE {
                           cn-DomainIdentity,
                           count-C
                           }

DL-PhysChCapabilityFDD-r4 ::= SEQUENCE {
                           maxNoDPCH-PDSCH-Codes      INTEGER (1..8),
                           maxNoPhysChBitsReceived    MaxNoPhysChBitsReceived,
                           supportForSF-512            BOOLEAN,
                           supportOfPDSCH              BOOLEAN,
                           simultaneousSCCPCH-DPCH-Reception SimultaneousSCCPCH-DPCH-Reception,
                           supportOfDedicatedPilotsForChEstimation SupportOfDedicatedPilotsForChEstimation   OPTIONAL
                           }

DL-PhysChCapabilityFDD-r5 ::= SEQUENCE {
                           maxNoDPCH-PDSCH-Codes      INTEGER (1..8),
                           maxNoPhysChBitsReceived    MaxNoPhysChBitsReceived,
                           supportForSF-512            BOOLEAN,
                           supportOfPDSCH              BOOLEAN,
                           simultaneousSCCPCH-DPCH-Reception SimultaneousSCCPCH-DPCH-Reception,
                           supportOfDedicatedPilotsForChEstimation SupportOfDedicatedPilotsForChEstimation   OPTIONAL,
                           fdd-hspdsch                 CHOICE {
                           supported                  SEQUENCE {
                           hdsch-physical-layer-category HSDSCH-physical-layer-category,
                           supportOfDedicatedPilotsForChannelEstimationOfHSDSCH BOOLEAN,
                           -- simultaneousSCCPCH-DPCH-HSDSCH-Reception shall be true only if the
                           -- IE SimultaneousSCCPCH-DPCH-Reception indicates support of simultaneous
                           -- reception of S-CCPCH and DPCH
                           simultaneousSCCPCH-DPCH-HSDSCH-Reception BOOLEAN
                           },
                           unsupported                NULL
                           }
                           }

DL-PhysChCapabilityTDD-r5 ::= SEQUENCE {
                           maxTS-PerFrame            MaxTS-PerFrame,
                           maxPhysChPerFrame          MaxPhysChPerFrame,
                           minimumSF                  MinimumSF-DL,
                           supportOfPDSCH             BOOLEAN,
                           maxPhysChPerTS              MaxPhysChPerTS,
                           tdd384-hspdsch              CHOICE {
                           supported                  HSDSCH-physical-layer-category,
                           unsupported                NULL
                           }
                           }

DL-PhysChCapabilityTDD-LCR-r5 ::= SEQUENCE {
                           maxTS-PerSubFrame          MaxTS-PerSubFrame-r4,
                           maxPhysChPerFrame          MaxPhysChPerSubFrame-r4,
                           minimumSF                  MinimumSF-DL,
                           supportOfPDSCH             BOOLEAN,
                           maxPhysChPerTS              MaxPhysChPerTS,
                           supportOf8PSK               BOOLEAN,
                           tdd128-hspdsch              CHOICE {
                           supported                  HSDSCH-physical-layer-category,
                           unsupported                NULL
                           }
                           }

DL-RFC3095-Context ::=      SEQUENCE {
                           rfc3095-Context-Identity  INTEGER (0..16383),
                           dl-mode                   ENUMERATED {u, o, r},
                           dl-ref-ir                 OCTET STRING ( SIZE (1..3000)),
                           dl-ref-time                INTEGER (0..4294967295)   OPTIONAL,
                           dl-curr-time               INTEGER (0..4294967295)   OPTIONAL,
                           dl-syn-offset-id           INTEGER (0..65535)        OPTIONAL,
                           }

```

```

dl-syn-slope-ts           INTEGER (0..4294967295)      OPTIONAL,
dl-dyn-changed           BOOLEAN

}

ImplementationSpecificParams ::=     BIT STRING (SIZE (1..512))

IntegrityProtectionStatus ::=      ENUMERATED {
                                    started, notStarted }

InterRAT-UE-RadioAccessCapabilityList-r5 ::=   SEQUENCE {
    interRAT-UE-RadioAccessCapability   InterRAT-UE-RadioAccessCapabilityList,
    geranIu-RadioAccessCapability       GERANIu-RadioAccessCapability           OPTIONAL
}

-- dummy is not used in this version of the specification, it should
-- not be sent and if received it should be ignored.
MaxHcContextSpace-r5 ::=          ENUMERATED {
                                    dummy, by1024, by2048, by4096, by8192,
                                    by16384, by32768, by65536, by131072 }

MeasurementCapability-r4 ::=      SEQUENCE {
    downlinkCompressedMode           CompressedModeMeasCapability-r4,
    uplinkCompressedMode            CompressedModeMeasCapability-r4
}

MeasurementCommandWithType ::=    CHOICE {
    setup                           MeasurementType,
    modify                          NULL,
    release                         NULL
}

MeasurementCommandWithType-r4 ::=  CHOICE {
    setup                           MeasurementType-r4,
    modify                          NULL,
    release                         NULL
}

OngoingMeasRep ::=              SEQUENCE {
    measurementIdentity             MeasurementIdentity,
    -- TABULAR: The CHOICE Measurement in the tabular description is included
    -- in MeasurementCommandWithType
    measurementCommandWithType      MeasurementCommandWithType,
    measurementReportingMode        MeasurementReportingMode           OPTIONAL,
    additionalMeasurementID-List   AdditionalMeasurementID-List      OPTIONAL
}

OngoingMeasRep-r4 ::=           SEQUENCE {
    measurementIdentity             MeasurementIdentity,
    -- TABULAR: The CHOICE Measurement in the tabular description is included
    -- in MeasurementCommandWithType-r4.
    measurementCommandWithType      MeasurementCommandWithType-r4,
    measurementReportingMode        MeasurementReportingMode           OPTIONAL,
    additionalMeasurementID-List   AdditionalMeasurementID-List      OPTIONAL
}

OngoingMeasRep-r5 ::=           SEQUENCE {
    measurementIdentity             MeasurementIdentity,
    -- TABULAR: The CHOICE Measurement in the tabular description is included
    -- in MeasurementCommandWithType-r4.
    measurementCommandWithType      MeasurementCommandWithType-r4,
    measurementReportingMode        MeasurementReportingMode           OPTIONAL,
    additionalMeasurementID-List   AdditionalMeasurementID-List      OPTIONAL,
    measurementCommand-v590ext      CHOICE {
        -- the choice "intra-frequency" shall be used for the case of intra-frequency measurement,
        -- as well as when intra-frequency events are configured for inter-frequency measurement
        intra-frequency                Intra-FreqEventCriteriaList-v590ext,
        inter-frequency                Inter-FreqEventCriteriaList-v590ext
    }                                OPTIONAL,
    intraFreqReportingCriteria-1b-r5 IntraFreqReportingCriteria-1b-r5      OPTIONAL,
    intraFreqEvent-1d-r5            IntraFreqEvent-1d-r5                  OPTIONAL
}

OngoingMeasRepList ::=          SEQUENCE (SIZE (1..maxNoOfMeas)) OF
                                OngoingMeasRep

OngoingMeasRepList-r4 ::=        SEQUENCE (SIZE (1..maxNoOfMeas)) OF
                                OngoingMeasRep-r4

```

```

OngoingMeasRepList-r5 ::=          SEQUENCE (SIZE (1..maxNoOfMeas)) OF
                                     OngoingMeasRep-r5

PDCP-Capability-r4 ::=           SEQUENCE {
  losslessSRNS-RelocationSupport   BOOLEAN,
  supportForRfc2507                CHOICE {
    notSupported                  NULL,
    supported                      MaxHcContextSpace
  },
  supportForRfc3095                CHOICE {
    notSupported                  NULL,
    supported                      SEQUENCE {
      maxROHC-ContextSessions     MaxROHC-ContextSessions-r4 DEFAULT s16,
      reverseCompressionDepth     INTEGER (0..65535)      DEFAULT 0
    }
  }
}

PDCP-Capability-r5 ::=           SEQUENCE {
  losslessSRNS-RelocationSupport   BOOLEAN,
  supportForRfc2507                CHOICE {
    notSupported                  NULL,
    supported                      MaxHcContextSpace-r5
  },
  supportForRfc3095                CHOICE {
    notSupported                  NULL,
    supported                      SEQUENCE {
      maxROHC-ContextSessions     MaxROHC-ContextSessions-r4 DEFAULT s16,
      reverseCompressionDepth     INTEGER (0..65535)      DEFAULT 0,
      supportForRfc3095ContextRelocation BOOLEAN
    }
  }
}

PhysicalChannelCapability-r4 ::=    SEQUENCE {
  fddPhysChCapability             SEQUENCE {
    downlinkPhysChCapability     DL-PhysChCapabilityFDD-r4,
    uplinkPhysChCapability       UL-PhysChCapabilityFDD
  OPTIONAL,
  tdd384-PhysChCapability        SEQUENCE {
    downlinkPhysChCapability     DL-PhysChCapabilityTDD,
    uplinkPhysChCapability       UL-PhysChCapabilityTDD
  OPTIONAL,
  tdd128-PhysChCapability        SEQUENCE {
    downlinkPhysChCapability     DL-PhysChCapabilityTDD-LCR-r4,
    uplinkPhysChCapability       UL-PhysChCapabilityTDD-LCR-r4
  OPTIONAL
}
}

PhysicalChannelCapability-r5 ::=    SEQUENCE {
  fddPhysChCapability             SEQUENCE {
    downlinkPhysChCapability     DL-PhysChCapabilityFDD-r5,
    uplinkPhysChCapability       UL-PhysChCapabilityFDD
  OPTIONAL,
  tdd384-PhysChCapability        SEQUENCE {
    downlinkPhysChCapability     DL-PhysChCapabilityTDD-r5,
    uplinkPhysChCapability       UL-PhysChCapabilityTDD
  OPTIONAL,
  tdd128-PhysChCapability        SEQUENCE {
    downlinkPhysChCapability     DL-PhysChCapabilityTDD-LCR-r5,
    uplinkPhysChCapability       UL-PhysChCapabilityTDD-LCR-r4
  OPTIONAL
}
}

RF-Capability-r4 ::=              SEQUENCE {
  fddRF-Capability               SEQUENCE {
    ue-PowerClass                 UE-PowerClassExt,
    txRxFrequencySeparation      TxRxFrequencySeparation
  OPTIONAL,
  tdd384-RF-Capability           SEQUENCE {
    ue-PowerClass                 UE-PowerClassExt,
    radioFrequencyBandTDDList     RadioFrequencyBandTDDList,
    chipRateCapability            ChipRateCapability
  OPTIONAL,
  tdd128-RF-Capability           SEQUENCE {
    ue-PowerClass                 UE-PowerClassExt,
    radioFrequencyBandTDDList     RadioFrequencyBandTDDList,
  }
}

```

```

        chipRateCapability           ChipRateCapability
    }
}

RFC3095-ContextInfo ::=          SEQUENCE {
    rb-Identity                  RB-Identity,
    rfc3095-Context-List         RFC3095-Context-List
}

RFC3095-Context-List ::=          SEQUENCE (SIZE (1..maxRFC3095-CID)) OF SEQUENCE {
    dl-RFC3095-Context          DL-RFC3095-Context      OPTIONAL,
    ul-RFC3095-Context          UL-RFC3095-Context      OPTIONAL
}

RLC-Capability-r5 ::=          SEQUENCE {
    totalRLC-AM-BufferSize       TotalRLC-AM-BufferSize-r5,
    maximumRLC-WindowSize        MaximumRLC-WindowSize,
    maximumAM-EntityNumber       MaximumAM-EntityNumberRLC-Cap
}

SRB-SpecificIntegrityProtInfo ::= SEQUENCE {
    ul-RRC-HFN                  BIT STRING (SIZE (28)),
    dl-RRC-HFN                  BIT STRING (SIZE (28)),
    ul-RRC-SequenceNumber        RRC-MessageSequenceNumber,
    dl-RRC-SequenceNumber        RRC-MessageSequenceNumber
}

SRB-SpecificIntegrityProtInfoList ::= SEQUENCE (SIZE (4..maxSRBsetup)) OF
                                         SRB-SpecificIntegrityProtInfo

StateOfRRC ::=                   ENUMERATED {
    cell-DCH, cell-FACH,
    cell-PCH, ura-PCH }

StateOfRRC-Procedure ::=          ENUMERATED {
    awaitNoRRC-Message,
    awaitRB-ReleaseComplete,
    awaitRB-SetupComplete,
    awaitRB-ReconfigurationComplete,
    awaitTransportCH-ReconfigurationComplete,
    awaitPhysicalCH-ReconfigurationComplete,
    awaitActiveSetUpdateComplete,
    awaitHandoverComplete,
    sendCellUpdateConfirm,
    sendUraUpdateConfirm,
    -- dummy is not used in this version of specification
    -- It should not be sent
    dummy,
    otherStates
}

TotalRLC-AM-BufferSize-r5 ::=     ENUMERATED {
    kb10, kb50, kb100, kb150, kb200,
    kb300, kb400, kb500, kb750, kb1000 }

TPC-Combination-Info ::= SEQUENCE {
    primaryCPICH-Info           PrimaryCPICH-Info,
    tpc-CombinationIndex         TPC-CombinationIndex
}

UE-MultiModeRAT-Capability-r5 ::= SEQUENCE {
    multiRAT-CapabilityList      MultiRAT-Capability,
    multiModeCapability          MultiModeCapability,
    supportOfUTRAN-ToGERAN-NACC  BOOLEAN
}

UE-Positioning-Capability-r4 ::=   SEQUENCE {
    standaloneLocMethodsSupported BOOLEAN,
    ue-BasedOTDOA-Supported       BOOLEAN,
    networkAssistedGPS-Supported  NetworkAssistedGPS-Supported,
    supportForUE-GPS-TimingOfCellFrames BOOLEAN,
    supportForIPDL                BOOLEAN,
    rx-tx-TimeDifferenceType2Capable BOOLEAN,
    validity-CellPCH-UraPCH       ENUMERATED { true }      OPTIONAL,
    sfm-sfnType2Capability        ENUMERATED { true }      OPTIONAL
}

UE-Positioning-LastKnownPos ::=    SEQUENCE {

```

```

    sfn                                INTEGER (0..4095),
    cell-id                           CellIdentity,
    positionEstimate                  PositionEstimate
}

UE-RadioAccessCapability-r4 ::=      SEQUENCE {
    accessStratumReleaseIndicator   AccessStratumReleaseIndicator,
    pdcp-Capability                PDCP-Capability-r4,
    rlc-Capability                 RLC-Capability,
    transportChannelCapability     TransportChannelCapability,
    rf-Capability                  RF-Capability-r4,
    physicalChannelCapability      PhysicalChannelCapability-r4,
    ue-MultiModeRAT-Capability    UE-MultiModeRAT-Capability,
    securityCapability              SecurityCapability,
    ue-positioning-Capability     UE-Positioning-Capability-r4,
    measurementCapability          MeasurementCapability-r4      OPTIONAL
}

UE-RadioAccessCapability-r5 ::=      SEQUENCE {
    accessStratumReleaseIndicator   AccessStratumReleaseIndicator,
    dl-CapabilityWithSimultaneousHS-DSCHConfig
        DL-CapabilityWithSimultaneousHS-DSCHConfig OPTIONAL,
    pdcp-Capability                PDCP-Capability-r5,
    rlc-Capability                 RLC-Capability-r5,
    transportChannelCapability     TransportChannelCapability,
    rf-Capability                  RF-Capability-r4,
    physicalChannelCapability      PhysicalChannelCapability-r5,
    ue-MultiModeRAT-Capability    UE-MultiModeRAT-Capability-r5,
    securityCapability              SecurityCapability,
    ue-positioning-Capability     UE-Positioning-Capability-r4,
    measurementCapability          MeasurementCapability-r4      OPTIONAL
}

UL-RFC3095-Context ::=             SEQUENCE {
    rfc3095-Context-Identity      INTEGER (0..16383),
    ul-mode                         ENUMERATED {u, o, r},
    ul-ref-ir                       OCTET STRING (SIZE (1..3000)),
    ul-ref-time                     INTEGER (0..4294967295)      OPTIONAL,
    ul-curr-time                    INTEGER (0..4294967295)      OPTIONAL,
    ul-syn-offset-id                INTEGER (0..65535)           OPTIONAL,
    ul-syn-slope-ts                 INTEGER (0..4294967295)      OPTIONAL,
    ul-ref-sn-1                     INTEGER (0..65535)           OPTIONAL
}

}

```

END

14.12.4 RRC messages exchanged between network nodes

14.12.4.2 SRNS RELOCATION INFO

This RRC message is sent between network nodes when preparing for an SRNS relocation or a handover/cell reselection from GERAN *Iu mode*.

With the presence or absence of the IE "RB identity for Hard Handover message" the source RNC indicates to the target SRNC whether the source RNC expects to receive the choice "DL DCCH message" in the IE "RRC information, target RNC to source RNC" in case the SRNS relocation is of type "UE involved". Furthermore the target RNC uses this information for the calculation of the MAC-I.

Direction: source RNC/RAT→target RNC

Information Element/Group Name	Need	Multi	Type and reference	Semantics description	Version
Non RRC IEs					
>RB identity for Handover message	OP		RB identity 10.3.4.16	Gives the id of the radio bearer on which the source RNC will transmit the RRC message in the case the relocation is of type "UE involved". In handover from GERAN <i>Iu mode</i> this IE is always set to 2.	
>State of RRC	MP		RRC state indicator, 10.3.3.35a		
>State of RRC procedure	MP		Enumerated (await no RRC message, await RB Release Complete, await RB Setup Complete, await RB Reconfiguration Complete, await Transport CH Reconfiguration Complete, await Physical CH Reconfiguration Complete, await Active Set Update Complete, await Handover Complete, send Cell Update Confirm, send URA Update Confirm,		

Information Element/Group Name	Need	Multi	Type and reference	Semantics description	Version
			, others)		
Ciphering related information					
>Ciphering status for each CN domain	MP	<1 to maxCNDo mains>			
>>CN domain identity	MP		CN domain identity 10.3.1.1		
>>Ciphering status	MP		Enumerated(Not started, Started)		
>>START	MP		START 10.3.3.38	START value to be used in this CN domain.	
>Latest configured CN domain	MP		CN domain identity 10.3.1.1	Value contained in the variable of the same name. In case this variable is empty, the source RNC can set any CN domain identity. In that case, the Ciphering status and the Integrity protection status should be Not started and the target RNC should not initialise the variable Latest configured CN domain.	
>Calculation time for ciphering related information	CV-Ciphering			Time when the ciphering information of the message were calculated, relative to a cell of the target RNC. In handover and cell reselection from GERAN <i>Iu mode</i> this field is not present.	
>>Cell Identity	MP		Cell Identity 10.3.2.2	Identity of one of the cells under the target RNC and included in the active set of the current call	
>>SFN	MP		Integer(0..4095)		
>COUNT-C list	OP	1 to <maxCNDo mains>		COUNT-C values for radio bearers using transparent mode RLC	
>>CN domain identity	MP		CN domain identity 10.3.1.1		
>>COUNT-C	MP		Bit string(32)		
>Ciphering info per radio bearer	OP	1 to <maxRB>		For signalling radio bearers this IE is mandatory.	
>>RB identity	MP		RB identity 10.3.4.16		
>>Downlink HFN	MP		Bit string(20..25)	This IE is either RLC AM HFN (20 bits) or RLC UM HFN (25 bits)	
>>Downlink SN	CV-SRB1		Bit String(7)	VT(US) of RLC UM	
>>Uplink HFN	MP		Bit string(20..25)	This IE is either RLC AM HFN (20 bits) or RLC UM HFN (25 bits)	
Integrity protection related information					
>Integrity protection status	MP		Enumerated(Not started, Started)		
>Signalling radio bearer specific integrity protection information	CV-IP	4 to <maxSRBs etup>			
>>Uplink RRC HFN	MP		Bit string (28)	For each SRB, in the case activation times for the next IP	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description	Version
				configuration to be applied on this SRB have already been reached this IE corresponds to the last value used. Else this value corresponds to the value the source would have initialized the HFN to at the activation time. Increment of HFN due to RRC SN roll over is taken care of by target based on value sent by the source.	
>>Downlink RRC HFN	MP		Bit string (28)	For each SRB, in the case activation times for the next IP configuration to be applied on this SRB have already been reached this IE corresponds to the last value used. Else this value corresponds to the value the source would have initialized the HFN to at the activation time. Increment of HFN due to RRC SN roll over is taken care of by target based on value sent by the source. In particular, for SRB2, this IE should not take into account the RRC message that will trigger the relocation.	
>>Uplink RRC Message sequence number	MP		Integer (0..15)	For each SRB, this IE corresponds to the last value received or in the case activation time was not reached for a configuration the value equals (activation time - 1).	
>>Downlink RRC Message sequence number	MP		Integer (0..15)	For each SRB, this IE corresponds to the last value used or in the case activation time was not reached for a configuration the value equals (activation time -1). In particular, for SRB2, this IE should not take into account the RRC message that will trigger the relocation.	
>Implementation specific parameters	OP		Bit string (1..512)		
RRC IEs					
UE Information elements					
>U-RNTI	MP		U-RNTI 10.3.3.47	G-RNTI is placed in this field when performing handover or cell reselection from GERAN <i>lu mode</i> .	
>C-RNTI	OP		C-RNTI 10.3.3.8		
>UE radio access Capability	MP		UE radio access capability 10.3.3.42		
>UE radio access capability extension	OP		UE radio access capability extension 10.3.3.42a		
>Last known UE position	OP				

Information Element/Group Name	Need	Multi	Type and reference	Semantics description	Version
>>SFN	MP		Integer (0..4095)	Time when position was estimated	
>>Cell ID	MP		Cell identity; 10.3.2.2	Indicates the cell, the SFN is valid for.	
>>CHOICE Position estimate	MP				
>>>Ellipsoid Point			Ellipsoid Point; 10.3.8.4a		
>>>Ellipsoid point with uncertainty circle			Ellipsoid point with uncertainty circle 10.3.8.4d		
>>>Ellipsoid point with uncertainty ellipse			Ellipsoid point with uncertainty ellipse 10.3.8.4e		
>>>Ellipsoid point with altitude			Ellipsoid point with altitude 10.3.8.4b		
>>>Ellipsoid point with altitude and uncertainty ellipsoid			Ellipsoid point with altitude and uncertainty ellipsoid 10.3.8.4c		
>UE Specific Behaviour Information 1 idle	OP		UE Specific Behaviour Information idle 1 10.3.3.51	This IE should be included if received via the "INTER RAT HANDOVER INFO", the "RRC CONNECTION REQUEST", the IE "SRNS RELOCATION INFO" or the "Inter RAT Handover Info with Inter RAT Capabilities"	
>UE Specific Behaviour Information 1 interRAT	OP		UE Specific Behaviour Information 1 interRAT 10.3.3.52	This IE should be included if received via the "INTER RAT HANDOVER INFO", the "RRC CONNECTION REQUEST", the IE "SRNS RELOCATION INFO" or the "Inter RAT Handover Info with Inter RAT Capabilities"	
Other Information elements					
>UE system specific capability	OP	1 to <maxSystemCapability>			
>>Inter-RAT UE radio access capability	MP		Inter-RAT UE radio access capability 10.3.8.7		
UTRAN Mobility Information elements					
>URA Identifier	OP		URA identity 10.3.2.6		
CN Information Elements					
>CN common GSM-MAP NAS system information	MP		NAS system information (GSM-MAP) 10.3.1.9		
>CN domain related information	OP	1 to <MaxCnDomains>		CN related information to be provided for each CN domain	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description	Version
>>CN domain identity	MP				
>>CN domain specific GSM-MAP NAS system info	MP		NAS system information (GSM-MAP) 10.3.1.9		
>>CN domain specific DRX cycle length coefficient	MP		CN domain specific DRX cycle length coefficient, 10.3.3.6		
Measurement Related Information elements					
>For each ongoing measurement reporting	OP	1 to <MaxNoOf Meas>			
>>Measurement Identity	MP		Measuremen t identity 10.3.7.48		
>>Measurement Command	MP		Measuremen t command 10.3.7.46		
>>Measurement Type	CV-Setup		Measuremen t type 10.3.7.50		
>>Measurement Reporting Mode	OP		Measuremen t reporting mode 10.3.7.49		
>>Additional Measurements list	OP		Additional measuremen ts list 10.3.7.1		
>>CHOICE Measurement	OP				
>>>Intra-frequency					
>>>>Intra-frequency cell info	OP		Intra-frequency cell info list 10.3.7.33		
>>>>Intra-frequency measurement quantity	OP		Intra-frequency measurement quantity 10.3.7.38		
>>>>Intra-frequency reporting quantity	OP		Intra-frequency reporting quantity 10.3.7.41		
>>>>Reporting cell status	OP		Reporting cell status 10.3.7.61		
>>>>Measurement validity	OP		Measuremen t validity 10.3.7.51		
>>>>CHOICE report criteria	OP				
>>>>>Intra-frequency measurement reporting criteria			Intra-frequency measurement reporting criteria 10.3.7.39		
>>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53		

Information Element/Group Name	Need	Multi	Type and reference	Semantics description	Version
>>>>No reporting			NULL		
>>>Inter-frequency					
>>>Inter-frequency cell info	OP		Inter-frequency cell info list 10.3.7.13		
>>>Inter-frequency measurement quantity	OP		Inter-frequency measurement quantity 10.3.7.18		
>>>Inter-frequency reporting quantity	OP		Inter-frequency reporting quantity 10.3.7.21		
>>>Reporting cell status	OP		Reporting cell status 10.3.7.61		
>>>Measurement validity	OP		Measurement validity 10.3.7.51		
>>>Inter-frequency set update	OP		Inter-frequency set update 10.3.7.22		
>>>CHOICE report criteria	OP				
>>>>Intra-frequency measurement reporting criteria			Intra-frequency measurement reporting criteria 10.3.7.39		
>>>>Inter-frequency measurement reporting criteria			Inter-frequency measurement reporting criteria 10.3.7.19		
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53		
>>>>No reporting			NULL		
>>>Inter-RAT					
>>>Inter-RAT cell info	OP		Inter-RAT cell info list 10.3.7.23		
>>>Inter-RAT measurement quantity	OP		Inter-RAT measurement quantity 10.3.7.29		
>>>Inter-RAT reporting quantity	OP		Inter-RAT reporting quantity 10.3.7.32		
>>>Reporting cell status	OP		Reporting cell status 10.3.7.61		
>>>Measurement validity	OP		Measurement validity 10.3.7.51		
>>>CHOICE report criteria	OP				
>>>>Inter-RAT measurement reporting criteria			Inter-RAT measurement		

Information Element/Group Name	Need	Multi	Type and reference	Semantics description	Version
			t reporting criteria 10.3.7.30		
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53		
>>>>No reporting			NULL		
>>>Traffic Volume					
>>>Traffic volume measurement Object	OP		Traffic volume measurement object 10.3.7.70		
>>>Traffic volume measurement quantity	OP		Traffic volume measurement quantity 10.3.7.71		
>>>Traffic volume reporting quantity	OP		Traffic volume reporting quantity 10.3.7.74		
>>>Measurement validity	OP		Measurement validity 10.3.7.51		
>>>CHOICE report criteria	OP				
>>>>Traffic volume measurement reporting criteria			Traffic volume measurement reporting criteria 10.3.7.72		
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53		
>>>>No reporting			NULL		
>>>Quality					
>>>Quality measurement quantity	OP		Quality measurement quantity 10.3.7.59		
>>>CHOICE report criteria	OP				
>>>>Quality measurement reporting criteria			Quality measurement reporting criteria 10.3.7.58		
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53		
>>>>No reporting			NULL		
>>>UE internal					
>>>UE internal measurement quantity	OP		UE internal measurement quantity 10.3.7.79		
>>>UE internal reporting quantity	OP		UE internal reporting quantity 10.3.7.82		
>>>CHOICE report criteria	OP				

Information Element/Group Name	Need	Multi	Type and reference	Semantics description	Version
>>>>UE internal measurement reporting criteria			UE internal measurement reporting criteria 10.3.7.80		
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53		
>>>>No reporting			NULL		
>>>UE positioning					
>>>LCS reporting quantity	OP		LCS reporting quantity 10.3.7.111		
>>>CHOICE report criteria	OP				
>>>>LCS reporting criteria			LCS reporting criteria 10.3.7.110		
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53		
>>>>No reporting					
Radio Bearer Information Elements					
>Predefined configuration status information	OP		Predefined configuration status information 10.3.4.5a		
>Signalling RB information list	MP	1 to <maxSRBs etup>		For each signalling radio bearer	
>>Signalling RB information	MP		Signalling RB information to setup 10.3.4.24		
>RAB information list	OP	1 to <maxRABs etup>		Information for each RAB	
>>RAB information	MP		RAB information to setup 10.3.4.10		
Transport Channel Information Elements					
Uplink transport channels					
>UL Transport channel information common for all transport channels	OP		UL Transport channel information common for all transport channels 10.3.5.24		
>UL transport channel information list	OP	1 to <MaxTrCH>			
>>UL transport channel information	MP		Added or reconfigured UL TrCH information 10.3.5.2		

Information Element/Group Name	Need	Multi	Type and reference	Semantics description	Version
>CHOICE mode	OP				
>>FDD					
>>>CPCH set ID	OP		CPCH set ID 10.3.5. 35		
>>>Transport channel information for DRAC list	OP	1 to <MaxTrCH >			
>>>>DRAC static information	MP		DRAC static information 10.3.5.7		
>>TDD				(no data)	
Downlink transport channels					
>DL Transport channel information common for all transport channels	OP		DL Transport channel information common for all transport channels 10.3.5.6		
>DL transport channel information list	OP	1 to <MaxTrCH >			
>>DL transport channel information	MP		Added or reconfigured DL TrCH information 10.3.5.1		

Information Element/Group Name	Need	Multi	Type and reference	Semantics description	Version
PhyCH information elements					
>TPC Combination Info list	OP	1 to <maxRL>			
>>Primary CPICH info	MP		Primary CPICH info 10.3.6.60		
>>TPC combination index	MP		TPC combination index 10.3.6.85		
>Transmission gap pattern sequence	OP	1 to <maxTGP S>			REL-5
>>TGPSI	MP		TGPSI 10.3.6.82		REL-5
>> Current TGPS Status Flag	MP		Enumerated(active, inactive)	This flag indicates the current status of the Transmission Gap Pattern Sequence, whether it is active or inactive	REL-5
>>TGCFN	CV-Active		Integer (0..255)	Connection Frame Number of the latest past frame of the first pattern within the Transmission Gap Pattern Sequence.	REL-5
>>Transmission gap pattern sequence configuration parameters	OP				REL-5
>>>TGMP	MP		Enumerated(TDD measurement, FDD measurement, GSM carrier RSSI measurement, GSM Initial BSIC identification, GSM BSIC re-confirmation, Multi-carrier measurement)	Transmission Gap pattern sequence Measurement Purpose.	REL-5
>>>TGPRC	MP		Integer (1..511, Infinity)	The number of remaining transmission gap patterns within the Transmission Gap Pattern Sequence.	REL-5
>>>TGSN	MP		Integer (0..14)	Transmission Gap Starting Slot Number The slot number of the first transmission gap slot within the TGCFN.	REL-5
>>>TGL1	MP		Integer(1..14)	The length of the first Transmission Gap within the transmission gap pattern expressed in number of slots	REL-5
>>>TGL2	MD		Integer (1..14)	The length of the second Transmission Gap within the transmission gap pattern. If omitted, then TGL2=TGL1. The value of TGL2 shall be ignored if TGD is set to "undefined"	REL-5
>>>TGD	MP		Integer(15..269,	Transmission gap distance indicates the number of slots	REL-5

Information Element/Group Name	Need	Multi	Type and reference	Semantics description	Version
			undefined)	between starting slots of two consecutive transmission gaps within a transmission gap pattern. If there is only one transmission gap in the transmission gap pattern, this parameter shall be set to undefined.	
>>>TGPL1	MP		Integer (1..144)	The duration of transmission gap pattern 1.	REL-5
>>>TGPL2	MD		Integer (1..144)	The duration of transmission gap pattern 2. If omitted, then TGPL2=TGPL1.	REL-5
>>>RPP	MP		Enumerated (mode 0, mode 1).	Recovery Period Power control mode during the frame after the transmission gap within the compressed frame. Indicates whether normal PC mode or compressed PC mode is applied	REL-5
>>>ITP	MP		Enumerated (mode 0, mode 1).	Initial Transmit Power is the uplink power control method to be used to compute the initial transmit power after the compressed mode gap.	REL-5
>>>CHOICE UL/DL mode	MP				REL-5
>>>>DL only				Compressed mode used in DL only	REL-5
>>>>Downlink compressed mode method	MP		Enumerated (puncturing, SF/2, higher layer scheduling)	Method for generating downlink compressed mode gap	REL-5
>>>>UL only				Compressed mode used in UL only	REL-5
>>>>Uplink compressed mode method	MP		Enumerated (SF/2, higher layer scheduling)	Method for generating uplink compressed mode gap	REL-5
>>>>UL and DL				Compressed mode used in UL and DL	REL-5
>>>>Downlink compressed mode method	MP		Enumerated (puncturing, SF/2, higher layer scheduling)	Method for generating downlink compressed mode gap	REL-5
>>>>Uplink compressed mode method	MP		Enumerated (SF/2, higher layer scheduling)	Method for generating uplink compressed mode gap	REL-5
>>>Downlink frame type	MP		Enumerated (A, B)		REL-5
>>>DeltaSIR1	MP		Real(0..3 by step of 0.1)	Delta in DL SIR target value to be set in the UE during the frame containing the start of the first transmission gap in the transmission gap pattern (without including the effect of the bit-rate increase)	REL-5
>>>DeltaSIRafter1	MP		Real(0..3 by step of 0.1)	Delta in DL SIR target value to be set in the UE one frame after the frame containing the start of the first transmission gap in the transmission gap pattern.	REL-5

Information Element/Group Name	Need	Multi	Type and reference	Semantics description	Version
>>>DeltaSIR2	OP		Real(0..3 by step of 0.1)	Delta in DL SIR target value to be set in the UE during the frame containing the start of the second transmission gap in the transmission gap pattern (without including the effect of the bit-rate increase) When omitted, DeltaSIR2 = DeltaSIR1.	REL-5
>>>DeltaSIRafter2	OP		Real(0..3 by step of 0.1)	Delta in DL SIR target value to be set in the UE one frame after the frame containing the start of the second transmission gap in the transmission gap pattern. When omitted, DeltaSIRafter2 = DeltaSIRafter1.	REL-5
>>>N Identify abort	CV-Initial BSIC		Integer(1..128)	Indicates the maximum number of repeats of patterns that the UE shall use to attempt to decode the unknown BSIC of the GSM cell in the initial BSIC identification procedure	REL-5
>>>T Reconfirm abort	CV-Re- confirm BSIC		Real(0.5..10.0 by step of 0.5)	Indicates the maximum time allowed for the re-confirmation of the BSIC of one GSM cell in the BSIC re-confirmation procedure. The time is given in steps of 0.5 seconds.	REL-5
>Scrambling Code Change List	CH-SF/2	1 to <maxRL>			REL-5
>>Primary CPICH info	MP		Primary CPICH info 10.3.6.60		REL-5
>>Scrambling code change	MP		Enumerated (code change, no code change)	Indicates whether the alternative scrambling code is used for compressed mode method 'SF/2'.	REL-5
Other Information elements					
>Measurement report	OP		MEASUREMENT REPORT 10.2.1.9		
>Failure cause	OP		Failure cause 10.3.3.13	Diagnostics information related to an earlier SRNC Relocation request (see NOTE 2 in 14.12.0a)	
>Protocol error information	CV-ProtErr		Protocol error information 10.3.8.12		
MBMS joined information	OP			Included if the UE has joined one or more MBMS services	REL-6
>P-TMSI	OP		P-TMSI (GSM-MAP) 10.3.1.13	In case the UE is in PMM-Idle	REL-6

Multi Bound	Explanation
MaxNoOfMeas	Maximum number of active measurements, upper limit 16

Condition	Explanation
<i>Setup</i>	The IE is mandatory present when the IE Measurement command has the value "Setup", otherwise the IE is not needed.
<i>Ciphering</i>	The IE is mandatory present when the IE Ciphering Status has the value "started" and the ciphering counters need not be reinitialised, otherwise the IE is not needed.
<i>IP</i>	The IE is mandatory present when the IE Integrity protection status has the value "started" and the integrity protection counters need not be reinitialised, otherwise the IE is not needed.
<i>ProtErr</i>	This IE is mandatory present if the IE "Protocol error indicator" is included and has the value "TRUE". Otherwise it is not needed.
<i>SRB1</i>	The IE is mandatory present for RB1. Otherwise it is not needed.
<i>Active</i>	This IE is mandatory present when the value of the IE "Current TGPS Status Flag" is "Active" and not needed otherwise.
<i>Initial BSIC</i>	This IE is mandatory present when the value of the IE "TGMP" is set to "GSM Initial BSIC identification" and not needed otherwise.
<i>Re-confirm BSIC</i>	This IE is mandatory present when the value of the IE "TGMP" is set to "GSM BSIC re-confirmation" and not needed otherwise.
<i>SF/2</i>	The IE is mandatory present if the IE "Transmission Gap Pattern Sequence" is included and has the value "SF/2" as the compressed mode method, and already sent the UE the IE "Scrambling Code Change" for each RL in the active set. Otherwise the IE is not needed.