

CHANGE REQUEST

⌘ **22.011 CR ??** ⌘ rev **-** ⌘ Current version: **3.3.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

Proposed change affects: ⌘ (U)SIM ME/UE Radio Access Network Core Network

Title:	⌘ Equivalent handling of PLMNs with different PLMN codes		
Source:	⌘ Motorola, Telia		
Work item code:	⌘ GSM-UMTS INTERWORKING	Date:	⌘ 5 March 2001
Category:	⌘ F	Release:	⌘ R99
	<p>Use <u>one</u> of the following categories:</p> <p>F (essential correction) A (corresponds to a correction in an earlier release) B (Addition of feature), C (Functional modification of feature) D (Editorial modification)</p> <p>Detailed explanations of the above categories can be found in 3GPP TR 21.900.</p>		<p>Use <u>one</u> of the following releases:</p> <p>2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) REL-4 (Release 4) REL-5 (Release 5)</p>

Reason for change:	⌘ In the new regulatory and commercial situation with both GSM and UMTS networks, it will be necessary for a mobile station to treat selected PLMNs with different PLMN codes as equivalent to each other at PLMN selection, handover, cell re-selection, etc. This was discussed at the SA adhoc meeting on UE in idle mode in Helsinki February 7-8, 2001. The solution proposed here was agreed in principle together with a mechanism for background scan for preferred PLMNs.
Summary of change:	⌘ Together with the existing requirement of multiple network IDs for access networks, a requirement is added that it shall be possible to indicate to the UE that a group of PLMNs are equivalent for PLMN selection, cell re-selection and handover.
Consequences if not approved:	⌘ The new regulatory and commercial situation for UMTS will not be supported.

Clauses affected:	⌘ 3.2.2.1, 3.2.2.2												
Other specs affected:	<table style="border: none;"> <tr> <td style="width: 15px;"><input checked="" type="checkbox"/></td> <td style="width: 350px;">Other core specifications</td> <td style="width: 15px;">⌘</td> <td style="width: 150px;">23.122, 24.008</td> </tr> <tr> <td><input type="checkbox"/></td> <td>Test specifications</td> <td></td> <td></td> </tr> <tr> <td><input type="checkbox"/></td> <td>O&M Specifications</td> <td></td> <td></td> </tr> </table>	<input checked="" type="checkbox"/>	Other core specifications	⌘	23.122, 24.008	<input type="checkbox"/>	Test specifications			<input type="checkbox"/>	O&M Specifications		
<input checked="" type="checkbox"/>	Other core specifications	⌘	23.122, 24.008										
<input type="checkbox"/>	Test specifications												
<input type="checkbox"/>	O&M Specifications												
Other comments:	⌘ Mirror CR is required for REL-4.												

How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at: http://www.3gpp.org/3G_Specs/CRs.htm. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be

downloaded from the 3GPP server under <ftp://www.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2000-09 contains the specifications resulting from the September 2000 TSG meetings.

- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

3.2 Network selection

3.2.1 General

The UE shall support both manual and automatic network selection mechanisms (modes). The UE shall select the last mode used, as the default mode, at every switch-on.

NOTE: By defaulting to the last mode used, e.g. manual network selection, the undesired automatic selection of an adjacent PLMN instead of the desired HPLMN in border areas, can be avoided at switch-on.

The user shall be given the opportunity to change mode at any time.

Except as defined below, the MMI shall be at the discretion of the UE manufacturer.

The UE shall contain display functions by which Available PLMNs and the Selected PLMN can be indicated.

3.2.2 Procedures

3.2.2.1 General

In the following procedures the UE selects and attempts registration on PLMNs.

In this ETS, the term "PLMN Selection" defines an UE based procedure, whereby candidate PLMNs are chosen, one at a time, for attempted registration.

A User Controlled PLMN Selector data field exists on the USIM to allow the user to indicate a preference for network selection. It shall be possible for the user to update the User Controlled PLMN Selector data field, but it shall not be possible to update this data field over the radio interface, e.g. using SIM Application Toolkit.

It shall be possible to have an Operator Controlled PLMN Selector list and a User Controlled PLMN Selector list stored on the SIM/USIM card. Both PLMN Selector lists may contain a list of preferred PLMNs in priority order. It shall be possible to have an associated Access Technology identifier e.g., UTRA, or GSM associated with each entry in the PLMN Selector lists.

NOTE 1: A PLMN in a Selector list, including HPLMN, may have multiple occurrences, with different access technology identifiers.

It shall be possible to handle cases where one network operator accepts access from access networks with different network IDs. It shall also be possible to indicate to the UE that a group of PLMNs are equivalent regarding PLMN selection, cell re-selection and handover.

If registration on a PLMN is successful, the UE shall indicate this PLMN (the "registered PLMN") and be capable of making and receiving calls on it. The identity of the registered PLMN shall be stored on the SIM/USIM. However, if registration is unsuccessful, the UE shall ensure that there is no registered PLMN stored in the SIM/USIM.

If a registration is unsuccessful because the IMSI is unknown in the home network, or the UE is illegal, then the UE shall not allow any further registration attempts on any network, until the UE is next powered-up or a SIM/USIM is inserted.

If the registration is unsuccessful due to the lack to service entitlement, specific behaviour by the UE may be required, see subclause 3.2.2.4.

To avoid unnecessary registration attempts, lists of forbidden PLMNs and LAs are maintained in the UE, see subclause 3.2.2.4 and TS 23.122 [3].

Registration attempts shall not be made by UEs without a SIM/USIM inserted.

An UE/ME which has not successfully registered shall nevertheless be able to make emergency call attempts on an available PLMN(which supports the emergency call teleservice), without the need for the user to select a PLMN. An available PLMN is determined by radio characteristics (TS 23.122 [3]).

3.2.2.2 At switch-on or recovery from lack of coverage

If the UE is within coverage (at switch-on) or returns to coverage of the PLMN on which it is already registered (as indicated by the registered PLMN stored in the SIM/USIM), the UE shall perform a location update to a new location area if necessary.

If there is no registered PLMN stored in the SIM/USIM, or if this PLMN is unavailable, or the attempted registration fails, the UE shall follow one of the following procedures for network selection:

A) Automatic network selection mode

The UE shall select and attempt registration on other PLMNs, if available and allowable and the location area is not in the list of "forbidden LSs for roaming" (see TS 23.122 [3]), in the following order:

- i) HPLMN for preferred access technologies in the order specified. ~~(Note: Allowance shall be made for cases where the HPLMN uses different network IDs for different access networks).~~ It shall be possible to configure a voice capable UE so that it shall not attempt registration on a PLMN if all cells identified as belonging to the PLMN do not support the corresponding voice service;
- ii) each PLMN in the "User Controlled PLMN Selector" data field in the USIM (in priority order) . It shall be possible to configure a voice capable UE so that it shall not attempt registration on a PLMN if all cells identified as belonging to the PLMN do not support the corresponding voice service;
- iii) each PLMN in the "Operator Controlled PLMN Selector" data field in the SIM/USIM (in priority order). It shall be possible to configure a voice capable UE so that it shall not attempt registration on a PLMN if all cells identified as belonging to the PLMN do not support the corresponding voice service;
- iv) other PLMN/access technology combinations with sufficient received signal level (see TS 23.122 [3]) in random order;
- v) other PLMN/access technology combinations with sufficient received signal quality (see TS 23.122 [3]) in random order. It shall be possible to configure a voice capable UE so that it shall not attempt registration on a PLMN if all cells identified as belonging to the PLMN do not support the corresponding voice service;
- vi) all other PLMN/access technology combinations in order of decreasing signal quality. It shall be possible to configure a voice capable UE so that it shall not attempt registration on a PLMN if all cells identified as belonging to the PLMN do not support the corresponding voice service.

An allowable PLMN is one which is not in the "Forbidden PLMN" data field in the SIM/USIM . This data field may be extended in the ME memory.(see subclause 3.2.2.4).

If successful registration is achieved, the UE shall indicate the selected PLMN.

If registration cannot be achieved on any PLMN, the UE shall indicate "no service" to the user, wait until a new PLMN is detected, or new location areas of an allowed PLMN are found which are not in the forbidden LA list(s), and then repeat the procedure. When registration cannot be achieved, different (discontinuous) PLMN search schemes may be used in order to minimize the access time while maintaining battery life, e.g. by prioritizing the search in favour of BCCH carriers which have a high probability of belonging to an available and allowable PLMN.

B) Manual network selection mode

The UE shall indicate PLMNs, including "Forbidden PLMNs", which are available. If there are none, this shall also be indicated.

Any available PLMN's shall be presented in the following order:

- i) HPLMN;
- ii) PLMNs contained in the "User Controlled PLMN Selector" data field in the SIM/USIM (in priority order);
- iii) PLMNs contained in the "Operator Controlled PLMN Selector" data field in the SIM/USIM (in priority order);
- iv) other PLMN/access technology combinations with sufficient received signal level (see TS 23.122 [3]) in random order;

- v) all other PLMN/access technology combinations in order of decreasing signal strength.

If a PLMN does not support voice services then this shall be indicated to the user.

The user may select his desired PLMN and the UE shall attempt registration on this PLMN. (This may take place at any time during the presentation of PLMNs.)

If the registration cannot be achieved on the selected PLMN, the UE shall indicate "No Service". The user may then select and attempt to register on another or the same PLMN following the above procedure. The UE shall not attempt to register on a PLMN which has not been selected by the user.

If a PLMN is selected but the UE cannot register on it because registration is rejected with the cause "PLMN not allowed", the UE shall not re-attempt to register on that network unless the same PLMN is selected again by the user.

If a PLMN is selected but the UE cannot register on it for other reasons, the UE shall, upon detection of a new LA (not in a forbidden LA list) of the selected PLMN, attempt to register on the PLMN.

If the UE is registered on a PLMN but loses coverage, different (discontinuous) carrier search schemes may be used to minimize the time to find a new valid BCCH carrier and maintain battery life, e.g. by prioritizing the search in favour of BCCH carriers of the registered PLMN.