

**Source:** TSG CN WG 1  
**Title:** CR to Rel-6 on Work Item T-GSM towards 24.008  
**Agenda item:** 9.11  
**Document for:** APPROVAL

---

**Introduction:**

This document contains 1 CR, **Rel-5 to Work Item "T-GSM"**, that have been agreed by **TSG CN WG1**, and are forwarded to TSG CN Plenary meeting #19 for approval.

| Spec   | CR  | Rev | Cat | Phase | Subject  | Version-Current | Version-New | Meeting-2nd-Level | Doc-2nd-Level |
|--------|-----|-----|-----|-------|--|-----------------|-------------|-------------------|---------------|
| 24.008 | 739 | 2   | B   | Rel-6 | Implementation of new frequency ranges into 24.008 | 5.6.0           | 6.0.0       | N1-28             | N1-030270     |

Dublin, Ireland, 10 – 14 February 2003

|                       |               |                  |                |
|-----------------------|---------------|------------------|----------------|
| CR-Form-v7            |               |                  |                |
| <b>CHANGE REQUEST</b> |               |                  |                |
| ⌘                     | <b>24.008</b> | <b>CR</b>        | <b>739</b>     |
| ⌘                     | rev           | <b>2</b>         | ⌘              |
|                       |               | Current version: | <b>5.6.0</b> ⌘ |

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

**Proposed change affects:** UICC apps  ME  Radio Access Network  Core Network

|                        |   |   |   |
|------------------------|---|---|---|
| <b>Title:</b>          | ⌘ | Implementation of new frequency ranges into 24.008                            |   |
| <b>Source:</b>         | ⌘ | Nokia   |   |
| <b>Work item code:</b> | ⌘ | T-GSM   | <b>Date:</b> ⌘ 13/02/2003                 |
| <b>Category:</b>       | ⌘ | <b>B</b>  | <b>Release:</b> ⌘ Rel-6                   |
|                        |   | Use <u>one</u> of the following categories:                                   | Use <u>one</u> of the following releases: |
|                        |   | <b>F</b> (correction)   | 2 (GSM Phase 2)                           |
|                        |   | <b>A</b> (corresponds to a correction in an earlier release)                  | R96 (Release 1996)                        |
|                        |   | <b>B</b> (addition of feature),   | R97 (Release 1997)                        |
|                        |   | <b>C</b> (functional modification of feature)                                 | R98 (Release 1998)                        |
|                        |   | <b>D</b> (editorial modification)   | R99 (Release 1999)                        |
|                        |   | Detailed explanations of the above categories can be found in 3GPP TR 21.900. | Rel-4 (Release 4)                         |
|                        |   |   | Rel-5 (Release 5)                         |
|                        |   |   | Rel-6 (Release 6)                         |

|                                      |   |  |
|--------------------------------------|---|--|
| <b>Reason for change:</b>            | ⌘ | TSG GERAN agreed the addition of T-GSM frequency bands for Rel-6. Incoming LS to CN1#28 in Tdoc GP-023372, includes a CR for CN1 approval.   |
| <b>Summary of change:</b>            | ⌘ | Addition of frequency ranges, necessary adjustment of parameters close to transition bands, alignment of parameters in the 380 and 410 MHz. In addition to that there was a mistake in table 10.5.6.a, RF Power Capability (Octet 3). For the UMTS case, the T-GSM bands were not mentioned; this is the only difference from the original CR sent by GERAN. |
| <b>Consequences if not approved:</b> | ⌘ | T-GSM bands will not be covered.   |

|                              |   |                                   |   |   |  |   |  |  |   |                           |   |
|------------------------------|---|-----------------------------------|---|---|--|---|--|--|---|---------------------------|---|
| <b>Clauses affected:</b>     | ⌘   | 10.5.1.6, 10.5.1.7 and 10.5.5.12a |   |   |  |   |  |  |   |                           |   |
| <b>Other specs affected:</b> | <table border="1" style="font-size: x-small;"> <tr> <td style="width: 20px;">Y</td> <td style="width: 20px;">N</td> </tr> <tr> <td style="text-align: center;">X</td> <td style="text-align: center;"> </td> </tr> <tr> <td style="text-align: center;">X</td> <td style="text-align: center;"> </td> </tr> <tr> <td style="text-align: center;"> </td> <td style="text-align: center;">X</td> </tr> </table> | Y                                 | N | X |  | X |  |  | X | Other core specifications | ⌘ 43.022, 45.001, 45.005, 45.050<br>51010-1 |
|                              | Y   | N                                 |   |   |  |   |  |  |   |                           |   |
|                              | X   |                                   |   |   |  |   |  |  |   |                           |   |
| X                            |   |                                   |   |   |  |   |  |  |   |                           |   |
|                              | X   |                                   |   |   |  |   |  |  |   |                           |   |
|                              | Test specifications   |                                   |   |   |  |   |  |  |   |                           |   |
|                              | O&M Specifications  |                                   |   |   |  |   |  |  |   |                           |   |
| <b>Other comments:</b>       | ⌘   |                                   |   |   |  |   |  |  |   |                           |   |

**How to create CRs using this form:**

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.

- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

### 10.5.1.6 Mobile Station Classmark 2

The purpose of the *Mobile Station Classmark 2* information element is to provide the network with information concerning aspects of both high and low priority of the mobile station equipment. This affects the manner in which the network handles the operation of the mobile station. The Mobile Station Classmark information indicates general mobile station characteristics and it shall therefore, except for fields explicitly indicated, be independent of the frequency band of the channel it is sent on.

The *Mobile Station Classmark 2* information element is coded as shown in figure 10.5.6/3GPP TS 24.008, table 10.5.6a/3GPP TS 24.008 and table 10.5.6b/3GPP TS 24.008.

The *Mobile Station Classmark 2* is a type 4 information element with 5 octets length.

|   |                   |                         |           |                |                        |      |      |         |
|---|-------------------|-------------------------|-----------|----------------|------------------------|------|------|---------|
| 8   | 7                 | 6                       | 5         | 4              | 3                      | 2    | 1    |         |
| Mobile station classmark 2 IEI                |                   |                         |           |                |                        |      |      | octet 1 |
| Length of mobile station classmark 2 contents |                   |                         |           |                |                        |      |      | octet 2 |
| 0<br>spare                                    | Revision<br>level |                         | ES<br>IND | A5/1           | RF power<br>capability |      |      | octet 3 |
| 0<br>spare                                    | PS<br>capa.       | SS Screen.<br>Indicator |           | SM ca<br>pabi. | VBS                    | VGCS | FC   | octet 4 |
| CM3   | 0<br>spare        | LCSVA<br>CAP            | UCS2      | SoLSA          | CMSP                   | A5/3 | A5/2 | octet 5 |

NOTE: Owing to backward compatibility problems, bit 8 of octet 4 should not be used unless it is also checked that the bits 8, 7 and 6 of octet 3 are not "0 0 0".

**Figure 10.5.6/3GPP TS 24.008 Mobile Station Classmark 2 information element**

**Table 10.5.6a/3GPP TS 24.008: Mobile Station Classmark 2 information element**

|  |   |
|--|---|
| Revision level (octet 3)   |   |
| Bits   |   |
| <b>7</b>   | <b>6</b>  |
| 0  | 0   |
| Reserved for GSM phase 1   |   |
| 0  | 1   |
| Used by GSM phase 2 mobile stations  |   |
| 1  | 0   |
| Used by mobile stations supporting R99 or later versions of the protocol   |   |
| 1  | 1   |
| Reserved for future use. If the network receives a revision level specified as 'reserved for future use', then it shall use the highest revision level supported by the network. |   |
| ES IND (octet 3, bit 5) "Controlled Early Classmark Sending" option implementation   |   |
| AN MS not supporting GSM shall set this bit to '0'.  |   |
| An MS supporting GSM shall indicate the associated GSM capability (see table):   |   |
| 0  | "Controlled Early Classmark Sending" option is not implemented in the MS  |
| 1  | "Controlled Early Classmark Sending" option is implemented in the MS  |
| NOTE:  | The value of the ES IND gives the implementation in the MS. It's value is <b>not</b> dependent on the broadcast SI 3 Rest Octet <Early Classmark Sending Control> value |

**Table 10.5.6a/3GPP TS 24.008: Mobile Station Classmark 2 information element**

|   |  |
|---|--|
| A5/1 algorithm supported (octet 3, bit 4)   |  |
| An MS not supporting GSM shall set this bit to '1'.   |  |
| An MS supporting GSM shall indicate the associated GSM capability (see table)   |  |
| 0   | encryption algorithm A5/1 available                                  |
| 1   | encryption algorithm A5/1 not available                              |
| RF Power Capability (Octet 3)   |  |
| When T-GSM 380, T-GSM 410, GSM 450, GSM 480, GSM 700, GSM 850, GSM 900 P, E, T [or R] band is used (for exceptions see 3GPP TS 44.018), the MS shall indicate the RF power capability of the band used (see table).   |  |
| When UMTS is used, a single band T-GSM 380, T-GSM 410, GSM 450, GSM 480, GSM 700, GSM 850, GSM 900 P, E, T [or R] MS shall indicate the RF power capability corresponding to the (GSM) band it supports (see table). In this case, information on which single band is supported is found in classmark 3. |  |
| Bits  |  |
| <b>3 2 1</b>  |  |
| 0 0 0   | class 1  |
| 0 0 1   | class 2  |
| 0 1 0   | class 3  |
| 0 1 1   | class 4  |
| 1 0 0   | class 5  |
| All other values are reserved.  |  |
| When the DCS 1800 or PCS 1900 band is used (for exceptions see 3GPP TS 44.018) The MS shall indicate the RF power capability of the band used (see table).  |  |
| When UMTS is used, a single band DCS 1800 or PCS 1900 MS shall indicate the RF power capability corresponding to the (GSM) band it supports (see table). In this case, information on which single band is supported is found in classmark 3  |  |
| Bits  |  |
| <b>3 2 1</b>  |  |
| 0 0 0   | class 1  |
| 0 0 1   | class 2  |
| 0 1 0   | class 3  |
| All other values are reserved.  |  |
| When UMTS is used, an MS not supporting any GSM band or a multiband GSM MS shall code this field as follows (see table):  |  |
| Bits  |  |
| <b>3 2 1</b>  |  |
| 1 1 1   | RF Power capability is irrelevant in this information element        |
| All other values are reserved.  |  |
| PS capability (pseudo-synchronization capability) (octet 4)   |  |
| An MS not supporting GSM shall set this bit to '0'.   |  |
| An MS supporting GSM shall indicate the associated GSM capability (see table):  |  |
| Bit 7   |  |
| 0   | PS capability not present  |
| 1   | PS capability present  |
| SS Screening Indicator (octet 4)  |  |
| Bits  |  |
| <b>6 5</b>  |  |
| 0 0   | defined in 3GPP TS 24.080  |
| 0 1   | defined in 3GPP TS 24.080  |
| 1 0   | defined in 3GPP TS 24.080  |
| 1 1   | defined in 3GPP TS 24.080  |
| SM capability (MT SMS pt to pt capability) (octet 4)  |  |
| Bit 4   |  |
| 0   | Mobile station does not support mobile terminated point to point SMS |
| 1   | Mobile station supports mobile terminated point to point SMS         |

**Table 10.5.6a/3GPP TS 24.008: Mobile Station Classmark 2 information element**

|   |   |
|---|---|
| VBS notification reception (octet 4)  |   |
| An MS not supporting GSM shall set this bit to '0'.   |   |
| An MS supporting GSM shall indicate the associated GSM capability (see table):  |   |
| <b>Bit 3</b>  |   |
| 0   | no VBS capability or no notifications wanted  |
| 1   | VBS capability and notifications wanted   |
| VGCS notification reception (octet 4)   |   |
| An MS not supporting GSM shall set this bit to '0'.   |   |
| An MS supporting GSM shall indicate the associated GSM capability (see table):  |   |
| <b>Bit 2</b>  |   |
| 0   | no VGCS capability or no notifications wanted   |
| 1   | VGCS capability and notifications wanted  |
| FC Frequency Capability (octet 4)   |   |
| When the <u>T-GSM 400</u> , GSM 400, or GSM 700, or GSM 850, or DCS 1800, <u>T-GSM 900</u> , or PCS 1900 band or UMTS is used (for exceptions see 3GPP TS 44.018), for definitions of frequency band see 3GPP TS 45.005, this bit shall be sent with the value '0'. |   |
| Note: This bit conveys no information about support or non support of the E-GSM or R-GSM bands when <u>T-GSM 400</u> , GSM 400, GSM 700, GSM 850, <u>T-GSM 900</u> , DCS 1800, PCS 1900 band or UMTS is used.   |   |
| When a GSM 900 band is used (for exceptions see 3GPP TS 44.018):  |   |
| <b>Bit 1</b>  |   |
| 0   | The MS does not support the E-GSM or R-GSM band (For definition of frequency bands see 3GPP TS 45.005 [33]) |
| 1   | The MS does support the E-GSM or R-GSM (For definition of frequency bands see 3GPP TS 45.005 [33])          |
| NOTE: For mobile station supporting the R-GSM band further information can be found in MS Classmark 3.  |   |
| CM3 (octet 5, bit 8)  |   |
| 0   | The MS does not support any options that are indicated in CM3   |
| 1   | The MS supports options that are indicated in classmark 3 IE  |
| LCS VA capability (LCS value added location request notification capability) (octet 5, bit 6)   |   |
| 0   | LCS value added location request notification capability not supported                                      |
| 1   | LCS value added location request notification capability supported  |
| UCS2 treatment (octet 5, bit 5)   |   |
| This information field indicates the likely treatment by the mobile station of UCS2 encoded character strings. For backward compatibility reasons, if this field is not included, the value 0 shall be assumed by the receiver.                                     |   |
| 0   | the ME has a preference for the default alphabet (defined in 3GPP TS 23.038 [8b]) over UCS2.                |
| 1   | the ME has no preference between the use of the default alphabet and the use of UCS2.                       |

**Table 10.5.6a/3GPP TS 24.008: Mobile Station Classmark 2 information element**

|  |  |
|--|--|
| SoLSA (octet 5, bit 4)   |  |
| An MS not supporting GSM shall set this bit to '0'.                            |  |
| An MS supporting GSM shall indicate the associated GSM capability (see table): |  |
| 0  | The ME does not support SoLSA.   |
| 1  | The ME supports SoLSA.   |
| CMSP: CM Service Prompt (octet 5, bit 3) \$(CCBS)\$                            |  |
| 0  | "Network initiated MO CM connection request" not supported.                          |
| 1  | "Network initiated MO CM connection request" supported for at least one CM protocol. |
| A5/3 algorithm supported (octet 5, bit 2)                                      |  |
| An MS not supporting GSM shall set this bit to '0'.                            |  |
| An MS supporting GSM shall indicate the associated GSM capability (see table): |  |
| 0  | encryption algorithm A5/3 not available  |
| 1  | encryption algorithm A5/3 available  |
| A5/2 algorithm supported (octet 5, bit 1)                                      |  |
| An MS not supporting GSM shall set this bit to '0'.                            |  |
| An MS supporting GSM shall indicate the associated GSM capability (see table): |  |
| 0  | encryption algorithm A5/2 not available  |
| 1  | encryption algorithm A5/2 available  |

NOTE: Additional mobile station capability information might be obtained by invoking the classmark interrogation procedure when GSM is used.

## NEXT CHANGE

### 10.5.1.7 Mobile Station Classmark 3

The purpose of the *Mobile Station Classmark 3* information element is to provide the network with information concerning aspects of the mobile station. The contents might affect the manner in which the network handles the operation of the mobile station. The Mobile Station Classmark information indicates general mobile station characteristics and it shall therefore, except for fields explicitly indicated, be independent of the frequency band of the channel it is sent on.

The *MS Classmark 3* is a type 4 information element with a maximum of 14 octets length.

The value part of a *MS Classmark 3* information element is coded as shown in figure 10.5.7/3GPP TS 24.008 and table 10.5.7/3GPP TS 24.008.

NOTE: The 14 octet limit is so that the CLASSMARK CHANGE message will fit in one layer 2 frame.

SEMANTIC RULE: a multiband mobile station shall provide information about all frequency bands it can support. A single band mobile station shall not indicate the band it supports in the *Multiband Supported*, *GSM 400 Bands Supported*, *GSM 700 Associated Radio Capability*, *GSM 850 Associated Radio Capability* or *PCS 1900 Associated Radio Capability* fields in the MS Classmark 3. Due to shared radio frequency channel numbers between DCS 1800 and PCS 1900, the mobile should indicate support for either DCS 1800 band OR PCS 1900 band.

SEMANTIC RULE: a mobile station shall include the MS Measurement Capability field if the *Multi Slot Class* field contains a value of 19 or greater (see 3GPP TS 45.002 [32]).

Typically, the number of spare bits at the end is the minimum to reach an octet boundary. The receiver may add any number of bits set to "0" at the end of the received string if needed for correct decoding.

```

<Classmark 3 Value part> ::=
  < spare bit >
  { < Multiband supported : { 000 } >
    < A5 bits >
  | < Multiband supported : { 101 | 110 } >
    < A5 bits >
    < Associated Radio Capability 2 : bit(4) >
    < Associated Radio Capability 1 : bit(4) >
  | < Multiband supported : { 001 | 010 | 100 } >
    < A5 bits >
    < spare bit >(4)
    < Associated Radio Capability 1 : bit(4) > }
  { 0 | 1 < R Support > }
  { 0 | 1 < HSCSD Multi Slot Capability > }
  < UCS2 treatment: bit >
  < Extended Measurement Capability : bit >
  { 0 | 1 < MS measurement capability > }
  { 0 | 1 < MS Positioning Method Capability > }
  { 0 | 1 < ECSD Multi Slot Capability > }
  { 0 | 1 < ECSD Struct > }
  { 0 | 1 < GSM 400 Bands Supported : { 01 | 10 | 11 } >
    < GSM 400 Associated Radio Capability: bit(4) > }

  { 0 | 1 <GSM 850 Associated Radio Capability : bit(4) > }
  { 0 | 1 <PCS 1900 Associated Radio Capability : bit(4) > }
  < UMTS FDD Radio Access Technology Capability : bit >
  < UMTS 3.84 Mcps TDD Radio Access Technology Capability : bit >
  < CDMA 2000 Radio Access Technology Capability : bit >

  { 0 | 1 < DTM GPRS Multi Slot Class : bit(2) >
    < MAC Mode Support : bit >
    { 0 | 1 < DTM EGPRS Multi Slot Class : bit(2) > } }
  { 0 | 1 < Single Band Support > } -- Release 4 starts here:
  { 0 | 1 <GSM 700 Associated Radio Capability : bit(4)>}

  < UMTS 1.28 Mcps TDD Radio Access Technology Capability : bit >
  < GERAN Feature Package 1 : bit >

  { 0 | 1 < Extended DTM GPRS Multi Slot Class : bit(2) >
    < Extended DTM EGPRS Multi Slot Class : bit(2) > }

  < GERAN Iu Mode Capability : bit >

  { 0 | 1 < T-GSM 400 Bands Supported : { 01 | 10 | 11 } >
    < T-GSM 400 Associated Radio Capability: bit(4) > }

  { 0 | 1 < T-GSM 900 Associated Radio Capability: bit(4) > }

  < spare bit > ;

< A5 bits > ::=
  < A5/7 : bit > < A5/6 : bit > < A5/5 : bit > < A5/4 : bit > ;

<R Support>::=
  < R-GSM band Associated Radio Capability : bit(3) > ;

< HSCSD Multi Slot Capability > ::=
  < HSCSD Multi Slot Class : bit(5) > ;

< MS Measurement capability > ::=
  < SMS_VALUE : bit (4) >
  < SM_VALUE : bit (4) > ;

< MS Positioning Method Capability > ::=
  < MS Positioning Method : bit(5) > ;

```



```
< ECSD Multi Slot Capability > ::=
  < ECSD Multi Slot Class : bit(5) > ;

< ECSD Struct > ::=
  < Modulation Capability : bit >
  { 0 | 1 < EDGE RF Power Capability 1: bit(2) > }
  { 0 | 1 < EDGE RF Power Capability 2: bit(2) > }

< Single Band Support > ::=
  < GSM Band : bit (4) > ;
```

**Figure 10.5.7/3GPP TS 24.008 *Mobile Station Classmark 3* information element**

**Table 10.5.7/3GPP TS 24.008: Mobile Station Classmark 3 information element**

|   |   |
|---|---|
| Multiband Supported (3 bit field)   |   |
| Band 1 supported  |   |
| Bit 1   |   |
| 0   | P-GSM not supported                     |
| 1   | P-GSM supported                         |
| Band 2 supported  |   |
| Bit 2   |   |
| 0   | E-GSM or R-GSM not supported            |
| 1   | E-GSM or R-GSM supported                |
| Band 3 supported  |   |
| Bit 3   |   |
| 0   | DCS 1800 not supported                  |
| 1   | DCS 1800 supported                      |
| The indication of support of P-GSM band or E-GSM or R-GSM band is mutually exclusive.   |   |
| When the 'Band 2 supported' bit indicates support of E-GSM or R-GSM, the presence of the <R Support> field, see below, indicates if the E-GSM or R-GSM band is supported.   |   |
| In this version of the protocol, the sender indicates in this field either none, one or two of these 3 bands supported.   |   |
| For single band mobile station or a mobile station supporting none of the GSM 900 bands(P-GSM, E-GSM and R-GSM) and DCS 1800 bands, all bits are set to 0.  |   |
| A5/4  |   |
| 0   | Encryption algorithm A5/4 not available |
| 1   | Encryption algorithm A5/4 available     |
| A5/5  |   |
| 0   | Encryption algorithm A5/5 not available |
| 1   | Encryption algorithm A5/5 available     |
| A5/6  |   |
| 0   | Encryption algorithm A5/6 not available |
| 1   | Encryption algorithm A5/6 available     |
| A5/7  |   |
| 0   | Encryption algorithm A5/7 not available |
| 1   | Encryption algorithm A5/7 available     |
| Associated Radio capability 1 and 2 (4 bit fields)  |   |
| If either of P-GSM or E-GSM or R-GSM is supported, the radio capability 1 field indicates the radio capability for P-GSM, E-GSM or R-GSM, and the radio capability 2 field indicates the radio capability for DCS1800 if supported, and is spare otherwise. |   |
| If none of P-GSM or E-GSM or R-GSM are supported, the radio capability 1 field indicates the radio capability for DCS1800, and the radio capability 2 field is spare.   |   |
| The radio capability contains the binary coding of the power class associated with the band indicated in multiband support bits (see 3GPP TS 45.005 [33]).  |   |

(continued...)

**Table 10.5.1.7/3GPP TS 24.008 (continued): MS Classmark 3 information element**

|  |   |   |   |                                    |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |   |   |   |   |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |
|--|---|---|---|------------------------------------|--|---|---|---|---|----------------------------------|---|---|---|---|----------------------------------|---|---|---|---|----------------------------------|-----|--|--|--|--|---|---|---|---|------------------------------------|---|---|---|---|--|---|---|---|---|----------------------------------|---|---|---|---|----------------------------------|---|---|---|---|----------------------------------|-----|--|--|--|--|---|---|---|---|------------------------------------|
| <p><b>R-GSM band Associated Radio Capability (3 bit field)</b></p> <p>In case where the R-GSM band is supported the R-GSM band associated radio capability field contains the binary coding of the power class associated (see GSM 45.005) (regardless of the number of GSM bands supported). A mobile station supporting the R-GSM band shall also when appropriate, (see 10.5.1.6) indicate its support in the 'FC' bit in the Mobile Station Classmark 2 information element.</p> <p>NOTE: The coding of the power class for P-GSM, E-GSM, R-GSM and DCS 1800 in radio capability 1 and/or 2 is different to that used in the Mobile Station Classmark 1 and Mobile Station Classmark 2 information elements.</p> <p><b>HSCSD Multi Slot Class (5 bit field)</b></p> <p>In case the MS supports the use of multiple timeslots for HSCSD then the HSCSD Multi Slot Class field is coded as the binary representation of the multislot class defined in 3GPP TS 45.002 [32].</p> <p><b>UCS2 treatment (1 bit field)</b></p> <p>This information field indicates the likely treatment by the mobile station of UCS2 encoded character strings. If not included, the value 0 shall be assumed by the receiver.</p> <ul style="list-style-type: none"> <li>0 the ME has a preference for the default alphabet (defined in 3GPP TS 23.038 [8b]) over UCS2.</li> <li>1 the ME has no preference between the use of the default alphabet and the use of UCS2.</li> </ul> <p><b>Extended Measurement Capability (1 bit field)</b></p> <p>This bit indicates whether the mobile station supports 'Extended Measurements' or not</p> <ul style="list-style-type: none"> <li>0 the MS does not support Extended Measurements</li> <li>1 the MS supports Extended Measurements</li> </ul> <p><b>SMS_VALUE (Switch-Measure-Switch) (4 bit field)</b></p> <p>The SMS field indicates the time needed for the mobile station to switch from one radio channel to another, perform a neighbour cell power measurement, and the switch from that radio channel to another radio channel.</p> <p>Bits</p> <table style="border: none;"> <tr><td>4</td><td>3</td><td>2</td><td>1</td><td></td></tr> <tr><td>0</td><td>0</td><td>0</td><td>0</td><td>1/4 timeslot (~144 microseconds)</td></tr> <tr><td>0</td><td>0</td><td>0</td><td>1</td><td>2/4 timeslot (~288 microseconds)</td></tr> <tr><td>0</td><td>0</td><td>1</td><td>0</td><td>3/4 timeslot (~433 microseconds)</td></tr> <tr><td>...</td><td></td><td></td><td></td><td></td></tr> <tr><td>1</td><td>1</td><td>1</td><td>1</td><td>16/4 timeslot (~2307 microseconds)</td></tr> </table> <p><b>SM_VALUE (Switch-Measure) (4 bit field)</b></p> <p>The SM field indicates the time needed for the mobile station to switch from one radio channel to another and perform a neighbour cell power measurement.</p> <p>Bits</p> <table style="border: none;"> <tr><td>4</td><td>3</td><td>2</td><td>1</td><td></td></tr> <tr><td>0</td><td>0</td><td>0</td><td>0</td><td>1/4 timeslot (~144 microseconds)</td></tr> <tr><td>0</td><td>0</td><td>0</td><td>1</td><td>2/4 timeslot (~288 microseconds)</td></tr> <tr><td>0</td><td>0</td><td>1</td><td>0</td><td>3/4 timeslot (~433 microseconds)</td></tr> <tr><td>...</td><td></td><td></td><td></td><td></td></tr> <tr><td>1</td><td>1</td><td>1</td><td>1</td><td>16/4 timeslot (~2307 microseconds)</td></tr> </table> <p><b>MS Positioning Method (5 bit field)</b></p> <p>This field indicates the Positioning Method(s) supported by the mobile station for the provision of location services (LCS) via the CS domain in A-mode.</p> <p><u>MS assisted E-OTD</u></p> <p>Bit 5</p> <ul style="list-style-type: none"> <li>0 MS assisted E-OTD not supported</li> <li>1 MS assisted E-OTD supported</li> </ul> | 4 | 3 | 2 | 1                                  |  | 0 | 0 | 0 | 0 | 1/4 timeslot (~144 microseconds) | 0 | 0 | 0 | 1 | 2/4 timeslot (~288 microseconds) | 0 | 0 | 1 | 0 | 3/4 timeslot (~433 microseconds) | ... |  |  |  |  | 1 | 1 | 1 | 1 | 16/4 timeslot (~2307 microseconds) | 4 | 3 | 2 | 1 |  | 0 | 0 | 0 | 0 | 1/4 timeslot (~144 microseconds) | 0 | 0 | 0 | 1 | 2/4 timeslot (~288 microseconds) | 0 | 0 | 1 | 0 | 3/4 timeslot (~433 microseconds) | ... |  |  |  |  | 1 | 1 | 1 | 1 | 16/4 timeslot (~2307 microseconds) |
| 4  | 3 | 2 | 1 |                                    |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |   |   |   |   |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |
| 0  | 0 | 0 | 0 | 1/4 timeslot (~144 microseconds)   |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |   |   |   |   |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |
| 0  | 0 | 0 | 1 | 2/4 timeslot (~288 microseconds)   |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |   |   |   |   |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |
| 0  | 0 | 1 | 0 | 3/4 timeslot (~433 microseconds)   |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |   |   |   |   |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |
| ...  |   |   |   |                                    |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |   |   |   |   |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |
| 1  | 1 | 1 | 1 | 16/4 timeslot (~2307 microseconds) |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |   |   |   |   |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |
| 4  | 3 | 2 | 1 |                                    |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |   |   |   |   |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |
| 0  | 0 | 0 | 0 | 1/4 timeslot (~144 microseconds)   |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |   |   |   |   |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |
| 0  | 0 | 0 | 1 | 2/4 timeslot (~288 microseconds)   |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |   |   |   |   |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |
| 0  | 0 | 1 | 0 | 3/4 timeslot (~433 microseconds)   |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |   |   |   |   |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |
| ...  |   |   |   |                                    |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |   |   |   |   |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |
| 1  | 1 | 1 | 1 | 16/4 timeslot (~2307 microseconds) |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |   |   |   |   |  |   |   |   |   |                                  |   |   |   |   |                                  |   |   |   |   |                                  |     |  |  |  |  |   |   |   |   |                                    |

Table 10.5.1.7/3GPP TS 24.008 (continued): *MS Classmark 3* information elementMS based E-OTDBit 4

- 0 MS based E-OTD not supported
- 1 MS based E-OTD supported

MS assisted GPSBit 3

- 0 MS assisted GPS not supported
- 1 MS assisted GPS supported

MS based GPSBit 2

- 0 MS based GPS not supported
- 1 MS based GPS supported

MS Conventional GPSBit 1

- 0 conventional GPS not supported
- 1 conventional GPS supported

**ECSD Multi Slot class** (5 bit field)

In case the **ECSD** MS supports the use of multiple timeslots and the number of supported time slots is different from number of time slots supported for GMSK then the **ECSD Multi Slot class** field is included and is coded as the binary representation of the multislot class defined in 3GPP TS 45.002 [32].

**Modulation Capability**

The Modulation Capability field indicates the modulation scheme the MS supports in addition to GMSK.

- 0 8-PSK supported for downlink reception only
- 1 8-PSK supported for uplink transmission and downlink reception

**EDGE RF Power Capability 1 (2 bit field)**

If 8-PSK modulation is supported for both uplink and downlink, the **EDGE RF Power Capability 1** field indicates the radio capability for 8-PSK modulation in GSM 400, GSM700, GSM850 or GSM900.

**EDGE RF Power Capability 2 (2 bit field)**

If 8-PSK modulation is supported for both uplink and downlink, the **EDGE RF Power Capability 2** field indicates the radio capability for 8-PSK modulation in DCS1800 or PCS1900 if supported, and is not included otherwise.

The respective **EDGE RF Power Capability 1** and **EDGE RF Power Capability 2** fields contain the following coding of the 8-PSK modulation power class (see 3GPP TS 45.005 [33]):

|      |   |   |                |
|------|---|---|----------------|
| Bits | 2 | 1 |                |
|      | 0 | 0 | Reserved       |
|      | 0 | 1 | Power class E1 |
|      | 1 | 0 | Power class E2 |
|      | 1 | 1 | Power class E3 |

Table 10.5.1.7/3GPP TS 24.008 (continued): *MS Classmark 3* information element**GSM 400 Bands Supported (2 bit field)**

See the semantic rule for the sending of this field.

Bits

|     |  |
|-----|--|
| 2 1 |  |
| 0 1 | GSM 480 supported, GSM 450 not supported |
| 1 0 | GSM 450 supported, GSM 480 not supported |
| 1 1 | GSM 450 supported, GSM 480 supported     |

**GSM 400 Associated Radio Capability (4 bit field)**

If either GSM 450 or GSM 480 or both is supported, the GSM 400 Associated Radio Capability field indicates the radio capability for GSM 450 and/or GSM 480.

The radio capability contains the binary coding of the power class associated with the band indicated in GSM 400 Bands Supported bits (see 3GPP TS 45.005 [33]).

NOTE: The coding of the power class for GSM 450 and GSM 480 in GSM 400 Associated Radio Capability is different to that used in the Mobile Station Classmark 1 and Mobile Station Classmark 2 information elements.

**GSM 850 Associated Radio Capability (4 bit field)**

See the semantic rule for the sending of this field.

This field indicates whether GSM 850 band is supported and its associated radio capability.

The radio capability contains the binary coding of the power class associated with the GSM 850 band (see 3GPP TS 45.005 [33]).

Note: the coding of the power class for GSM 850 in GSM 850 Associated Radio Capability is different to that used in the Mobile Station Classmark 1 and Mobile Station Classmark 2 information elements.

**PCS 1900 Associated Radio Capability (4 bit field)**

See the semantic rule for the sending of this field.

This field indicates whether PCS 1900 band is supported and its associated radio capability.

The radio capability contains the binary coding of the power class associated with the PCS 1900 band (see 3GPP TS 45.005 [33]).

Note: the coding of the power class for PCS 1900 in PCS 1900 Associated Radio Capability is different to that used in the Mobile Station Classmark 1 and Mobile Station Classmark 2 information elements.

Table 10.5.1.7/3GPP TS 24.008 (continued): MS Classmark 3 information element

|   |
|---|
| <p><b>UMTS FDD Radio Access Technology Capability (1 bit field)</b></p> <p>0 UMTS FDD not supported<br/>1 UMTS FDD supported</p> <p><b>UMTS 3.84 Mcps TDD Radio Access Technology Capability (1 bit field)</b></p> <p>0 UMTS 3.84 Mcps TDD not supported<br/>1 UMTS 3.84 Mcps TDD supported</p> <p><b>CDMA 2000 Radio Access Technology Capability (1 bit field)</b></p> <p>0 CDMA2000 not supported<br/>1 CDMA2000 supported</p> <p><b>DTM GPRS Multi Slot Class (2 bit field)</b><br/>This field indicates the GPRS DTM multislot capabilities of the MS. It is coded as follows:</p> <p>Bit</p> <p>2 1</p> <p>0 0 Multislot class 1 supported<br/>0 1 Multislot class 5 supported<br/>1 0 Multislot class 9 supported<br/>1 1 Reserved for future extension. If received, the network shall interpret this as '00'</p> <p><b>MAC Mode Support (1 bit field)</b><br/>This field indicates whether the MS supports Dynamic and Fixed Allocation or only supports Exclusive Allocation. It is coded as follows:</p> <p>0 Dynamic and Fixed Allocation not supported<br/>1 Dynamic and Fixed allocation supported</p> <p><b>EGPRS DTM Multi Slot Class (2 bit field)</b><br/>This field indicates the EGPRS DTM multislot capabilities of the MS. This field shall be included only if the mobile station supports EGPRS DTM. This field is coded as the DTM GPRS Multi Slot Class field.</p> <p><b>Single Band Support</b><br/>This field shall be sent if the mobile station supports UMTS and one and only one GSM band with the exception of R-GSM; this field shall not be sent otherwise</p> <p><b>GSM Band (4 bit field)</b></p> <p>Bits</p> <p>4 3 2 1</p> <p>0 0 0 0 E-GSM is supported<br/>0 0 0 1 P-GSM is supported<br/>0 0 1 0 DCS 1800 is supported<br/>0 0 1 1 GSM 450 is supported<br/>0 1 0 0 GSM 480 is supported<br/>0 1 0 1 GSM 850 is supported<br/>0 1 1 0 PCS 1900 is supported<br/>0 1 1 1 GSM 700 is supported</p> <p>All other values are reserved for future use.</p> <p>NOTE: When this field is received, the associated RF power capability is found in Classmark 1 or 2.</p> <p><b>GSM 700 Associated Radio Capability (4 bit field)</b></p> <p>See the semantic rule for the sending of this field.<br/>This field indicates whether GSM 700 band is supported and its associated radio capability.</p> <p>The radio capability contains the binary coding of the power class associated with the GSM 700 band (see 3GPP TS 45.005 [33]).</p> <p>NOTE: The coding of the power class for GSM 700 in GSM 700 Associated Radio Capability is different to that used in the Mobile Station Classmark 1 and Mobile Station Classmark 2 information elements.</p> <p><b>UMTS 1.28 Mcps TDD Radio Access Technology Capability (1 bit field)</b></p> <p>0 UMTS 1.28 Mcps TDD not supported</p> |
|---|

1 UMTS 1.28 Mcps TDD supported

**GERAN Feature Package 1** (1 bit field)

This field indicates whether the MS supports the GERAN Feature Package 1 (see 3GPP TS 44.060). It is coded as follows:

- 0 GERAN feature package 1 not supported.
- 1 GERAN feature package 1 supported.

**Extended GPRS DTM Multi Slot Class** (2 bit field)

This field indicates the extended GPRS DTM multislot capabilities of the MS and shall be interpreted in conjunction with the GPRS DTM Multi Slot Class field. It is coded as follows, where 'DGMSC' denotes the DTM GPRS Multi Slot Class field:

| DGMSC Bit | 2 | 1 | Bit 2 1   |  |
|-----------|---|---|-----------|--|
|           | 0 | 0 | <b>00</b> | Multislot class 2 supported                                      |
|           | 0 | 0 | <b>01</b> | Multislot class 3 supported                                      |
|           | 0 | 0 | <b>10</b> | Multislot class 4 supported                                      |
|           | 0 | 0 | <b>11</b> | Multislot class 8 supported                                      |
|           | 0 | 1 | <b>00</b> | Multislot class 5 supported                                      |
|           | 0 | 1 | <b>01</b> | Multislot class 6 supported                                      |
|           | 0 | 1 | <b>10</b> | Multislot class 7 supported                                      |
|           | 0 | 1 | <b>11</b> | Spare. If received, the network shall interpret it as '(01) 00'. |
|           | 1 | 0 | <b>00</b> | Multislot class 9 supported                                      |
|           | 1 | 0 | <b>01</b> | Multislot class 10 supported                                     |
|           | 1 | 0 | <b>10</b> | Multislot class 11 supported                                     |
|           | 1 | 0 | <b>11</b> | Multislot class 12 supported                                     |

The presence of this field indicates that the MS supports combined fullrate and halfrate GPRS channels in the downlink. When this field is not present, the MS supports the multislot class indicated by the *DTM GPRS Multi Slot Class* field.

**Extended DTM EGPRS Multi Slot Class** (2 bit field)

This field is not considered when the EGPRS DTM Multi Slot Class field is not included. This field indicates the extended EGPRS DTM multislot capabilities of the MS and shall be interpreted in conjunction with the EGPRS DTM Multi Slot Class field. This field is coded as the Extended DTM GPRS Multi Slot Class field. The presence of this field indicates that the MS supports combined fullrate and halfrate GPRS channels in the downlink.

When this field is not present, the MS supports the multislot class indicated by the *DTM GPRS Multi Slot Class* field.

**GERAN Iu Mode Capability** (1 bit field)

Bit

- 0 GERAN Iu mode not supported
- 1 GERAN Iu mode supported

**T-GSM 400 Bands Supported** (2 bit field)

See the semantic rule for the sending of this field.

Bits

|  | 2 | 1 |  |
|--|---|---|--|
|  | 0 | 1 | T-GSM 380 supported, T-GSM 410 not supported |
|  | 1 | 0 | T-GSM 410 supported, T-GSM 380 not supported |
|  | 1 | 1 | T-GSM 410 supported, T-GSM 380 supported     |

**T-GSM 400 Associated Radio Capability** (4 bit field)

If either T-GSM 410 or T-GSM 380 or both is supported, the T-GSM 400 Associated Radio Capability field indicates the radio capability for T-GSM 410 and/or T-GSM 380.

The radio capability contains the binary coding of the power class associated with the band indicated in T-GSM 400 Bands Supported bits (see 3GPP TS 45.005 [33]).

NOTE: The coding of the power class for T-GSM 410 and T-GSM 380 in T-GSM 400 Associated Radio Capability is different to that used in the Mobile Station Classmark 1 and Mobile Station Classmark 2 information elements.

**T-GSM 900 Associated Radio Capability** (4 bit field)

See the semantic rule for the sending of this field.

This field indicates whether T-GSM 900 band is supported and its associated radio capability.

The radio capability contains the binary coding of the power class associated with the T-GSM 900 band (see

3GPP TS 45.005 [33]).

Note: the coding of the power class for T-GSM 900 in T-GSM 900 Associated Radio Capability is different to that used in the Mobile Station Classmark 1 and Mobile Station Classmark 2 information elements.

## NEXT CHANGE

### 10.5.5.12a MS Radio Access capability

The purpose of the *MS RA capability* information element is to provide the radio part of the network with information concerning radio aspects of the mobile station. The contents might affect the manner in which the network handles the operation of the mobile station.

The *MS RA capability* is a type 4 information element, with a maximum length of 52 octets.

The value part of a *MS RA capability* information element is coded as shown in table 10.5.146/3GPP TS 24.008.

For the indication of the Access Technology Types the following conditions shall apply:

- Among the three Access Type Technologies GSM 900-P, GSM 900-E and GSM 900-R only one shall be present.
- Due to shared radio frequency channel numbers between GSM 1800 and GSM 1900, the mobile station should provide the relevant radio access capability for either GSM 1800 band OR GSM 1900 band, not both.
- The MS shall indicate its supported Access Technology Types during a single MM procedure.
- If the alternative coding by using the Additional access technologies struct is chosen by the mobile station, the mobile station shall indicate its radio access capability for the serving BCCH frequency band in the first included Access capabilities struct.
- The first Access Technology Type shall not be set to "1111".

For error handling the following shall apply:

- If a received Access Technology Type is unknown to the receiver, it shall ignore all the corresponding fields.
- If within a known Access Technology Type a receiver recognizes an unknown field it shall ignore it.
- For more details about error handling of MS radio access capability see 3GPP TS 48.018 [86].



Table 10.5.146/3GPP TS 24.008: *Mobile Station Radio Access Capability Information Element*

```

<MS Radio Access capability IE > ::=
<MS Radio Access capability IEI : 00100100 >
<Length of MS RA capability: <octet>> -- length in octets of MS RA capability value part and spare bits
<MS RA capability value part : <MS RA capability value part struct >>
<spare bits>**; -- may be used for future enhancements

<MS RA capability value part struct > ::= --recursive structure allows any number of Access technologies
{ { < Access Technology Type: bit (4) > exclude 1111
  < Access capabilities : <Access capabilities struct > > }

  | { < Access Technology Type: bit (4) == 1111 > -- structure adding Access technologies with same
capabilities
  < Length : bit (7) > -- length in bits of list of Additional access technologies and spare bits
  { 1 < Additional access technologies: < Additional access technologies struct > > } ** 0
  <spare bits>** } }

{ 0 | 1 <MS RA capability value part struct > } ;

< Additional access technologies struct > ::=
  < Access Technology Type : bit (4) >
  < GMSK Power Class : bit (3) >
  < 8PSK Power Class : bit (2) > ;

< Access capabilities struct > ::=
  < Length : bit (7) > -- length in bits of Content and spare bits
  <Access capabilities : <Content>>
  <spare bits>** ; -- expands to the indicated length
  -- may be used for future enhancements

< Content > ::=
  < RF Power Capability : bit (3) >
  { 0 | 1 <A5 bits : <A5 bits> > } -- zero means that the same values apply for parameters as in the immediately
preceding Access capabilities field within this IE
  < ES IND : bit >
  < PS : bit >
  < VGCS : bit >
  < VBS : bit >
  { 0 | 1 < Multislot capability : Multislot capability struct > } -- zero means that the same values for multislot
parameters as given in an earlier Access capabilities field within this IE apply also here
-- Additions in release 99
  { 0 | 1 < 8PSK Power Capability : bit(2)> } -- '1' also means 8PSK modulation capability in uplink.
  < COMPACT Interference Measurement Capability : bit >
  < Revision Level Indicator : bit >
  < UMTS FDD Radio Access Technology Capability : bit > -- 3G RAT
  < UMTS 3.84 Mcps TDD Radio Access Technology Capability : bit > -- 3G RAT
  < CDMA 2000 Radio Access Technology Capability : bit > -- 3G RAT
-- Additions in release 4
  < UMTS 1.28 Mcps TDD Radio Access Technology Capability: bit > -- 3G RAT
  < GERAN Feature Package 1 : bit >
  { 0 | 1 < Extended DTM GPRS Multi Slot Class : bit(2) >
  < Extended DTM EGPRS Multi Slot Class : bit(2) > }
-- Additions in release 5
  < GERAN Iu Mode Capability : bit >;
  -- error: struct too short, assume features do not exist
  -- error: struct too long, ignore data and jump to next Access technology

```

Table 10.5.146/3GPP TS 24.008 (continued): *Mobile Station Radio Access Capability IE*

```

< Multislot capability struct > ::=
  { 0 | 1 < HSCSD multislot class : bit (5) > }
  { 0 | 1 < GPRS multislot class : bit (5) > < GPRS Extended Dynamic Allocation Capability : bit > }
  { 0 | 1 < SMS_VALUE : bit (4) > < SM_VALUE : bit (4) > }
-- Additions in release 99
  { 0 | 1 < ECSD multislot class : bit (5) > }
  { 0 | 1 < EGPRS multislot class : bit (5) > < EGPRS Extended Dynamic Allocation Capability : bit > }
  { 0 | 1 < DTM GPRS Multi Slot Class: bit(2)>
    <MAC Mode Support : bit>
    { 0 | 1 <EGPRS DTM Multi Slot Class : bit(2)> } } ;
-- error: struct too short, assume features do not exist

<A5 bits> ::= < A5/1 : bit> <A5/2 : bit> <A5/3 : bit> <A5/4 : bit> <A5/5 : bit> <A5/6 : bit> <A5/7 : bit>; -- bits for circuit
mode ciphering algorithms. These fields are not used by the network and may be excluded by the MS.

Access Technology Type
This field indicates the access technology type to be associated with the following access capabilities.

Bits
4 3 2 1
0 0 0 0 GSM P
0 0 0 1 GSM E --note that GSM E covers GSM P
0 0 1 0 GSM R --note that GSM R covers GSM E and GSM P
0 0 1 1 GSM 1800
0 1 0 0 GSM 1900
0 1 0 1 GSM 450
0 1 1 0 GSM 480
0 1 1 1 GSM 850
1 0 0 0 GSM 700
1 0 0 1 GSM T 380
1 0 1 0 GSM T 410
1 0 1 1 GSM T 900
1 1 1 1 Indicates the presence of a list of Additional access technologies
All other values are treated as unknown by the receiver.

RF Power Capability, GMSK Power Class (3 bit field)
This field contains the binary coding of the power class used for GMSK associated with the indicated Access
Technology Type (see 3GPP TS 45.005).

8PSK Power Capability (2 bit field)
If 8-PSK modulation is supported for uplink, this field indicates the radio capability for 8-PSK modulation. The
following coding is used (see 3GPP TS 45.005 [33]):
Bits 2 1
0 0 Reserved
0 1 Power class E1
1 0 Power class E2
1 1 Power class E3

8PSK Power Class (2 bit field)
This field indicates the radio capability for 8-PSK modulation. The following coding is used (see 3GPP TS 45.005):
Bits 2 1
0 0 8PSK modulation not supported for uplink
0 1 Power class E1
1 0 Power class E2
1 1 Power class E3

Additional access technologies struct
This structure contains the GMSK Power Class and 8PSK Power Class for an additional Access Technology. All
other capabilities for this indicated Access Technology are the same as the capabilities indicated by the preceding
Access capabilities struct.

A5/1
0 encryption algorithm A5/1 not available
1 encryption algorithm A5/1 available

A5/2

```

0 encryption algorithm A5/2 not available  
1 encryption algorithm A5/2 available  
**A5/3**  
0 encryption algorithm A5/3 not available  
1 encryption algorithm A5/3 available  
**A5/4**  
0 encryption algorithm A5/4 not available  
1 encryption algorithm A5/4 available  
**A5/5**  
0 encryption algorithm A5/5 not available  
1 encryption algorithm A5/5 available  
**A5/6**  
0 encryption algorithm A5/6 not available  
1 encryption algorithm A5/6 available  
**A5/7**  
0 encryption algorithm A5/7 not available  
1 encryption algorithm A5/7 available  
  
**ES IND** – (Controlled early Classmark Sending)  
0 "controlled early Classmark Sending" option is not implemented  
1 "controlled early Classmark Sending" option is implemented

**Table 10.5.146/3GPP TS 24.008 (concluded): Mobile Station Radio Access Capability Information Element**

|   |
|---|
| <p><b>PS</b> – (Pseudo Synchronisation)<br/>                 0 PS capability not present<br/>                 1 PS capability present</p> <p><b>VGCS</b> – (Voice Group Call Service)<br/>                 0 no VGCS capability or no notifications wanted<br/>                 1 VGCS capability and notifications wanted.</p> <p><b>VBS</b> – (Voice Broadcast Service)<br/>                 0 no VBS capability or no notifications wanted<br/>                 1 VBS capability and notifications wanted</p> <p><b>HSCSD Multi Slot Class</b><br/>                 The Multi Slot Class field is coded as the binary representation of the multislot class defined in 3GPP TS 45.002 [32]. This field is not used by the network and may be excluded by the MS.<br/>                 Range 1 to 18, all other values are reserved.</p> <p><b>GPRS Multi Slot Class</b><br/>                 The GPRS Multi Slot Class field is coded as the binary representation of the multislot class defined in 3GPP TS 45.002 [32].</p> <p>-- Additions in release 99</p> <p><b>ECSD Multi Slot Class</b><br/>                 The presence of this field indicates ECSD capability. Whether the MS is capable of 8-PSK modulation in uplink is indicated by the presence of 8-PSK Power Capability field. The Multi Slot Class field is coded as the binary representation of the multislot class defined in 3GPP TS 45.002 [32]. This field is not used by the network and may be excluded by the MS.<br/>                 Range 1 to 18, all other values are reserved.</p> <p><b>EGPRS Multi Slot Class</b><br/>                 The presence of this field indicates EGPRS capability. Whether the MS is capable of 8-PSK modulation in uplink is indicated by the presence of 8-PSK Power Capability field. The EGPRS Multi Slot Class field is coded as the binary representation of the multislot class defined in 3GPP TS 45.002 [32].</p> <p><b>GPRS Extended Dynamic Allocation Capability</b><br/>                 0 Extended Dynamic Allocation Capability for GPRS is not implemented<br/>                 1 Extended Dynamic Allocation Capability for GPRS is implemented</p> <p><b>EGPRS Extended Dynamic Allocation Capability</b><br/>                 0 Extended Dynamic Allocation Capability for EGPRS is not implemented<br/>                 1 Extended Dynamic Allocation Capability for EGPRS is implemented</p> <p><b>SMS_VALUE (Switch-Measure-Switch) (4 bit field)</b><br/>                 The SMS field indicates the time needed for the mobile station to switch from one radio channel to another, perform a neighbor cell power measurement, and the switch from that radio channel to another radio channel. This field is not used by the network and may be excluded by the MS.<br/>                 Bits<br/>                 4 3 2 1<br/>                 0 0 0 0 1/4 timeslot (~144 microseconds)<br/>                 0 0 0 1 2/4 timeslot (~288 microseconds)<br/>                 0 0 1 0 3/4 timeslot (~433 microseconds)<br/>                 . . .<br/>                 1 1 1 1 16/4 timeslot (~2307 microseconds)</p> <p><b>(SM_VALUE) Switch-Measure (4 bit field)</b><br/>                 The SM field indicates the time needed for the mobile station to switch from one radio channel to another and perform a neighbour cell power measurement. This field is not used by the network and may be excluded by the MS.<br/>                 Bits<br/>                 4 3 2 1<br/>                 0 0 0 0 1/4 timeslot (~144 microseconds)<br/>                 0 0 0 1 2/4 timeslot (~288 microseconds)<br/>                 0 0 1 0 3/4 timeslot (~433 microseconds)<br/>                 . . .<br/>                 1 1 1 1 16/4 timeslot (~2307 microseconds)</p> |
|---|

**DTM GPRS Multi Slot Class** (2 bit field)

This field indicates the GPRS DTM multislot capabilities of the MS. It is coded as follows:

Bits

2 1

0 0 Multislot class 1 supported

0 1 Multislot class 5 supported

1 0 Multislot class 9 supported

1 1 Reserved for future extension. If received, the network shall interpret this as '00'

**MAC Mode Support** (1 bit field)

This field indicates whether the MS supports Dynamic and Fixed Allocation or only supports Exclusive Allocation

Bit

0 Dynamic and Fixed Allocation not supported

1 Dynamic and Fixed allocation supported

**EGPRS DTM Multi Slot Class** (2 bit field)

This field indicates the EGPRS DTM multislot capabilities of the MS. This field shall be included only if the mobile station supports EGPRS DTM. This field is coded as the DTM GPRS multislot Class field.

**COMPACT Interference Measurement Capability** (1 bit field)

0 COMPACT Interference Measurement Capability is not implemented

1 COMPACT Interference Measurement Capability is implemented

**Revision Level Indicator** (1 bit field)

Bit

0 The ME is Release '98 or older

1 The ME is Release '99 onwards

**UMTS FDD Radio Access Technology Capability** (1 bit field)

Bit

0 UMTS FDD not supported

1 UMTS FDD supported

**UMTS 3.84 Mcps TDD Radio Access Technology Capability** (1 bit field)

Bit

0 UMTS 3.84 Mcps TDD not supported

1 UMTS 3.84 Mcps TDD supported

**CDMA 2000 Radio Access Technology Capability** (1 bit field)

Bit

0 CDMA 2000 not supported

1 CDMA 2000 supported

**UMTS 1.28 Mcps TDD Radio Access Technology Capability** (1 bit field)

Bit

0 UMTS 1.28 Mcps TDD not supported

1 UMTS 1.28 Mcps TDD supported

**GERAN Feature Package 1** (1 bit field)

This field indicates whether the MS supports the GERAN Feature Package 1 (see 3GPP TS 44.060). It is coded as follows:

0 GERAN feature package 1 not supported.

1 GERAN feature package 1 supported.

**Extended GPRS DTM Multi Slot Class** (2 bit field)

This field indicates the extended GPRS DTM capabilities of the MS and shall be interpreted in conjunction with the GPRS DTM Multi Slot Class field. It is coded as follows, where 'DGMSC' denotes the DTM GPRS multislot class field:

| DGMSC Bit | 2 1 | Bit 2 1 |                             |
|-----------|-----|---------|-----------------------------|
|           | 0 0 | 0 0     | Multislot class 2 supported |
|           | 0 0 | 0 1     | Multislot class 3 supported |
|           | 0 0 | 1 0     | Multislot class 4 supported |
|           | 0 0 | 1 1     | Multislot class 8 supported |
|           | 0 1 | 0 0     | Multislot class 5 supported |

|     |            |  |
|-----|------------|--|
| 0 1 | <b>0 1</b> | Multislot class 6 supported  |
| 0 1 | <b>1 0</b> | Multislot class 7 supported  |
| 0 1 | <b>1 1</b> | Spare. If received, the network shall interpret it as '01 <b>00</b> '. |
| 1 0 | <b>0 0</b> | Multislot class 9 supported  |
| 1 0 | <b>0 1</b> | Multislot class 10 supported   |
| 1 0 | <b>1 0</b> | Multislot class 11 supported   |
| 1 0 | <b>1 1</b> | Multislot class 12 supported   |

The presence of this field indicates that the MS supports combined fullrate and halfrate GPRS channels in the downlink. When this field is not present, the MS supports the multislot class indicated by the *DTM GPRS Multi Slot Class* field.

**Extended EGPRS DTM Multislot Class** (2 bit field)

This field is not considered when the EGPRS DTM Multislot Class field is not included. This field indicates the extended EGPRS DTM multislot capabilities of the MS and shall be interpreted in conjunction with the EGPRS DTM Multislot Class field. This field is coded as the Extended DTM GPRS Multislot Class field. The presence of this field indicates that the MS supports combined fullrate and halfrate GPRS channels in the downlink. When this field is not present, the MS supports the multislot class indicated by the *DTM GPRS Multi Slot Class* field.

**GERAN Iu Mode Capability** (1 bit field)

Bit

|   |                             |
|---|-----------------------------|
| 0 | GERAN Iu mode not supported |
| 1 | GERAN Iu mode supported     |